



Cisco Nexus 5600 Series NX-OS System Management Command Reference

First Published: 2016-05-19

Last Modified: 2022-02-18

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883



CONTENTS

CHAPTER 1

Preface 1

Preface 2

Audience 2

Document Conventions 2

Related Documentation 3

Documentation Feedback 4

Communications, Services, and Additional Information 4

CHAPTER 2

A Commands 5

abort (Call Home) 6

abort (Call Home) 7

abort (session) 8

aclog match-log-level 9

alert-group (Call Home) 10

CHAPTER 3

C Commands 13

callhome 14

callhome send diagnostic 15

callhome test 16

clear flow exporter 17

clear logging logfile 18

clear logging nvram 19

clear logging onboard 20

clear logging session 21

clear ntp session 22

clear ntp statistics 23

- collect flow 24
- commit (Call Home) 26
- commit (session) 27
- configure maintenance profile 28
- contract-id (Call Home) 30
- customer-id (Call Home) 31

CHAPTER 4

D Commands 33

- description (NetFlow exporter) 34
- description (NetFlow monitor) 35
- description (NetFlow record) 36
- description (NetFlow sampler) 37
- description (SPAN, ERSPAN) 38
- destination 40
- destination (ERSPAN session) 41
- destination (SPAN session) 43
- destination-profile (Call Home) 46
- diagnostic bootup level 49
- dscp 50

CHAPTER 5

E Commands 51

- email-contact (Call Home) 52
- enable (Call Home) 53
- erspan-id 54
- exporter 56

CHAPTER 6

F Commands 57

- factory reset 58
- feature netflow 60
- feature ptp 61
- fex-group 62
- filter access-group 63
- flow monitor 64
- flow monitor (interface) 66

flow record 68
flow timeout 70

CHAPTER 7**H Commands 71**

hardware pq-drain 72
hardware random-detect 73

CHAPTER 8**I Commands 75**

ip access-list (session) 76
ip dns source-interface 77
ip domain-list 78
ip domain-lookup 80
ip domain-name 81
ip dscp (ERSPAN) 83
ip host 85
ip name-server 86
ip port access-group (session) 88
ip ttl (ERSPAN) 89

CHAPTER 9**L Commands 91**

layer2-switched flow monitor 92
logging abort 93
logging commit 94
logging console 95
logging distribute 96
logging event 97
logging event port 98
logging ip access-list cache 99
logging level 101
logging logfile 102
logging module 103
logging monitor 104
logging server 105
logging timestamp 107

CHAPTER 10	M Commands	109
	match datalink	110
	match ip	111
	match ipv4	112
	match transport	113
	mode	114
	monitor erspan origin ip-address	115
	monitor session	116
	mtu	120

CHAPTER 11	N Commands	123
	ntp	124
	ntp abort	125
	ntp authenticate	126
	ntp commit	127
	ntp distribute	128
	ntp sync-retry	129

CHAPTER 12	O Commands	131
	option exporter-stats timeout	132
	option interface-table timeout	133
	option sampler-table timeout	134

CHAPTER 13	P Commands	135
	packet latency threshold	136
	periodic-inventory (Call Home)	137
	phone-contact (Call Home)	138
	poweroff module	139
	ptp announce	140
	ptp delay request minimum interval	141
	ptp domain	142
	ptp priority1	143
	ptp priority2	144

ptp source 145
 ptp sync interval 146
 ptp vlan 147

CHAPTER 14
R Commands 149

rmon alarm 150
 rmon event 152
 rmon hcalarm 153

CHAPTER 15
S Commands 155

sampler 157
 snapshot create 159
 snapshot delete 160
 snapshot section 161
 snmp trap link-status 163
 snmp-server community 165
 snmp-server aaa-user cache-timeout 166
 snmp-server contact 167
 snmp-server context 168
 snmp-server enable traps 169
 snmp-server enable traps link 172
 snmp-server globalEnforcePriv 174
 snmp-server host 175
 snmp-server location 177
 snmp-server mib community-map 178
 snmp-server tcp-session 179
 snmp-server user 180
 source 182
 source interface (SPAN, ERSPAN) 183
 source ip 186
 switchport monitor rate-limit 187
 switch-profile 188
 system fex-group shutdown 191
 system mode maintenance 192

system mode maintenance always-use-custom-profile	194
system mode maintenance dont-generate-profile	195
system mode maintenance on-reload reset-reason	197
system mode maintenance shutdown	199
system mode maintenance timeout	201
system soft-reload enable	202
shut (SPAN, ERSPAN)	204
site-id (Call Home)	206
sleep instance	207
soft-reload	209

CHAPTER 16

Show Commands	211
show snmp host	213
show snmp sessions	214
show snmp trap	215
show snmp user	217
show system mode	218
show tech-support mmode	220
show diagnostic bootup level	222
show diagnostic result	223
show flow exporter	225
show flow interface	227
show flow record	229
show flow timeout	231
show hosts	232
show ip dns source-interface	233
show logging console	234
show logging info	235
show logging last	236
show logging level	237
show logging logfile	239
show logging module	240
show logging monitor	241
show logging nvram	242

show logging onboard	243
show logging pending	248
show logging pending-diff	249
show logging server	250
show logging session status	251
show logging status	252
show logging timestamp	253
show monitor session	254
show ntp authentication-status	256
show ntp peers	257
show ntp peer-status	258
show ntp statistics	259
show ntp timestamp-status	260
show ptp brief	261
show ptp clock	262
show ptp clocks foreign-masters-record	263
show ptp corrections	264
show ptp parent	265
show ptp port interface	266
show ptp time-property	267
show rmon	268
show run mmode	270
show running-config callhome	272
show running-config interface vethernet	274
show running-config monitor	275
show running-config poe	276
show running-config port-security	277
show sampler	278
show snapshots	279
show snapshots compare	280
show snapshots dump	282
show snapshots sections	284
show snmp community	285
show snmp context	286

show snmp engineID 287
 show snmp group 288
 show system soft-reload status 290

CHAPTER 17

T Commands 291
 template data timeout 292

CHAPTER 18

V Commands 293
 verify (session) 294
 version 5 295
 version 9 296
 vrf (ERSPAN) 298



Preface

- [Preface, on page 2](#)

Preface

This preface describes the audience, organization, and conventions of the Book Title. It also provides information on how to obtain related documentation.

This chapter includes the following topics:

Audience

This publication is for experienced network administrators who configure and maintain Cisco NX-OS on Cisco Nexus 5000 Series Platform switches.

Document Conventions



Note

- As part of our constant endeavor to remodel our documents to meet our customers' requirements, we have modified the manner in which we document configuration tasks. As a result of this, you may find a deviation in the style used to describe these tasks, with the newly included sections of the document following the new format.
- The Guidelines and Limitations section contains general guidelines and limitations that are applicable to all the features, and the feature-specific guidelines and limitations that are applicable only to the corresponding feature.

Command descriptions use the following conventions:

Convention	Description
bold	Bold text indicates the commands and keywords that you enter literally as shown.
<i>Italic</i>	Italic text indicates arguments for which the user supplies the values.
[x]	Square brackets enclose an optional element (keyword or argument).
[x y]	Square brackets enclosing keywords or arguments separated by a vertical bar indicate an optional choice.
{x y}	Braces enclosing keywords or arguments separated by a vertical bar indicate a required choice.
[x {y z}]	Nested set of square brackets or braces indicate optional or required choices within optional or required elements. Braces and a vertical bar within square brackets indicate a required choice within an optional element.
<i>variable</i>	Indicates a variable for which you supply values, in context where italics cannot be used.

Convention	Description
string	A nonquoted set of characters. Do not use quotation marks around the string or the string will include the quotation marks.

Examples use the following conventions:

Convention	Description
screen font	Terminal sessions and information the switch displays are in screen font.
boldface screen font	Information you must enter is in boldface screen font.
<i>italic screen font</i>	Arguments for which you supply values are in italic screen font.
< >	Nonprinting characters, such as passwords, are in angle brackets.
[]	Default responses to system prompts are in square brackets.
!, #	An exclamation point (!) or a pound sign (#) at the beginning of a line of code indicates a comment line.

This document uses the following conventions:



Note Means reader take note. Notes contain helpful suggestions or references to material not covered in the manual.



Caution Means reader be careful. In this situation, you might do something that could result in equipment damage or loss of data.

Related Documentation

Documentation for Cisco Nexus 5000 Series Switches is available at:

- Configuration Guides

<http://www.cisco.com/c/en/us/support/switches/nexus-5000-series-switches/products-installation-and-configuration-guides-list.html>

- Command Reference Guides

<http://www.cisco.com/c/en/us/support/switches/nexus-5000-series-switches/products-command-reference-list.html>

- Release Notes

<http://www.cisco.com/c/en/us/support/switches/nexus-5000-series-switches/products-release-notes-list.html>

- Install and Upgrade Guides

<http://www.cisco.com/c/en/us/support/switches/nexus-5000-series-switches/products-installation-guides-list.html>

- Licensing Guide

<http://www.cisco.com/c/en/us/support/switches/nexus-5000-series-switches/products-licensing-information-listing.html>

Documentation for Cisco Nexus 5000 Series Switches and Cisco Nexus 2000 Series Fabric Extenders is available at:

<http://www.cisco.com/c/en/us/support/switches/nexus-2000-series-fabric-extenders/products-installation-and-configuration-guides-list.html>

Documentation Feedback

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions and services, visit [Cisco Marketplace](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.



A Commands

- [abort \(Call Home\)](#), on page 6
- [abort \(Call Home\)](#), on page 7
- [abort \(session\)](#), on page 8
- [acllog match-log-level](#), on page 9
- [alert-group \(Call Home\)](#), on page 10

abort (Call Home)

To discard Call Home configuration changes and release the Cisco Fabric Services (CFS) lock, use the abort command.

```
abort
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines Use this command if you are the CFS lock owner or if you are logged into the device that holds the CFS lock.

Examples

This example shows how to discard Call Home configuration changes:

```
switch(config-callhome)# abort
switch(config-callhome)#
```

Related Commands

Command	Description
show callhome	Displays Call Home configuration information.
show running-config callhome	Displays the running configuration information for Call Home.

abort (Call Home)

To discard Call Home configuration changes and release the Cisco Fabric Services (CFS) lock, use the abort command.

```
abort
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Callhome configuration mode

Command History	Release	Modification
		This command was introduced.

Usage Guidelines Use this command if you are the CFS lock owner or if you are logged into the device that holds the CFS lock.

Examples This example shows how to discard Call Home configuration changes:

```
switch(config-callhome)# abort
switch(config-callhome)#
```

Related Commands	Command	Description
	show callhome	Displays Call Home configuration information.
	show running-config callhome	Displays the running configuration information for Call Home.

abort (session)

To discard the current configuration session, use the abort command.

abort

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Session configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to abort the current configuration session:

```
switch# configure session MySession1
switch(config-s)# abort
switch#
```

Related Commands

Command	Description
commit	Commits a session.
configure session	Creates a configuration session.
show configuration session	Displays the contents of the session.
verify	Verifies a session.

aclog match-log-level

To specify the minimum severity level to log ACL matches, use the `aclog match-log-level` command. To remove the `aclog match-log-level`, use the `no` form of this command.

```
aclog match-log-level severity-level
no aclog match-log-level severity-level
```

Syntax Description

severity-level	<p>Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows:</p> <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition—default level • 6—informational: Informational message only (default) • 7—debugging: Appears during debugging only
----------------	---

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set the `aclog match-log-level` to 6, informational:

```
switch(config)# aclog match-log-level 6
switch(config)#
```

Related Commands

Command	Description
logging level	Enables logging messages from a specified facility and configures the logging severity level.
logging logfile	Configures the name of the log file used to store system messages and sets the minimum severity level to log.

alert-group (Call Home)

To configure a CLI show command for an alert group, use the alert-group command. To remove a CLI command from an alert group, use the no form of this command.

```
alert-group alert user-def-cmd CLI-command
no alert-group alert user-def-cmd CLI-command
```

Syntax Description

alert	Alert group. The alert group can be one of the following: <ul style="list-style-type: none"> • All—All alert groups • Cisco-TAC—Cisco TAC events • Configuration—Configuration events • Diagnostic—Diagnostic events • EEM—EEM events • Environmental—Power, fan, temperature-related events • Inventory—Inventory status events • License—Licensing events • Linecard-Hardware—Linecard-related events • Supervisor-Hardware—Supervisor-related events • Syslog-group-port—Syslog message events filed by port manager • System—Software-related events • Test—User-generated test events
user-def-cmd	Specifies a CLI command for an alert group.
CLI-command	CLI show command. The command can be a maximum of 512 characters.

Command Default

None

Command Modes

Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

You can customize predefined alert groups to execute additional CLI show commands when specific events occur and send that show output with the Call Home message. You can assign a maximum of five user-defined CLI show commands to an alert group.

You must enclose the show command in double quotes. Only valid show commands are accepted.



Note

You cannot add user-defined CLI show commands to the CiscoTAC-1 destination profile.

You can add show commands only to full text and XML destination profiles. Short text destination profiles do not support additional show commands because they only allow 128 bytes of text.

Examples

This example shows how to add a show command output to a Call Home message sent for an alert group:

```
switch(config-callhome)# alert-group configuration user-def-cmd "show running-config"
switch(config-callhome)#
```

Related Commands

Command	Description
copy running-config startup-config	Saves this configuration change.
show callhome user-def-cmd	Displays information about all user-defined show commands added to alert groups.



C Commands

- [callhome](#), on page 14
- [callhome send diagnostic](#), on page 15
- [callhome test](#), on page 16
- [clear flow exporter](#), on page 17
- [clear logging logfile](#), on page 18
- [clear logging nvram](#), on page 19
- [clear logging onboard](#), on page 20
- [clear logging session](#), on page 21
- [clear ntp session](#), on page 22
- [clear ntp statistics](#), on page 23
- [collect flow](#), on page 24
- [commit \(Call Home\)](#), on page 26
- [commit \(session\)](#), on page 27
- [configure maintenance profile](#), on page 28
- [contract-id \(Call Home\)](#), on page 30
- [customer-id \(Call Home\)](#), on page 31

callhome

To configure the Cisco Smart Call Home service and enter the callhome configuration mode, use the callhome command.

```
callhome
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines You must configure the e-mail, phone, and street address information for Call Home. You can optionally configure the contract ID, customer ID, site ID, and switch priority information.

Examples

This example shows how to enter callhome configuration mode:

```
switch(config)# callhome
switch(config-callhome)#
```

Related Commands

Command	Description
email-contact	Configures the e-mail address.
show callhome	Displays a summary of the Call Home configuration.
snmp-server contact	Configures the SNMP contact (sysContact).

callhome send diagnostic

To send a specified Call Home test message to all configured destinations, use the `callhome send diagnostic` command.

```
callhome send diagnostic
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Callhome configuration mode

Command History	Release	Modification
		This command was introduced.

Usage Guidelines You can generate a test message to test your Call Home communications using the `callhome send diagnostic` command.

Examples

This example shows how to configure Call Home to send test messages to all configured destinations:

```
switch(config-callhome) # callhome send diagnostic

switch(config-callhome) #
```

Related Commands	Command	Description
	show callhome	Displays Call Home configuration information.
	show running-config callhome	Displays the running configuration information for Call Home.

callhome test

To send a Call Home test message to all configured destinations, use the callhome test command.

```
callhome test [inventory]
```

Syntax Description

inventory	(Optional) Specifies that a Call Home inventory message be sent for testing the Call Home configuration.
-----------	--

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
	This command was introduced.

Examples

This example shows how to send a Call Home test message to all configured destinations:

```
switch# callhome test
trying to send test callhome message
successfully sent test callhome message
switch#
```

This example shows how to send a Call Home inventory message to all configured destinations:

```
switch# callhome test inventory
trying to send test callhome inventory message
successfully sent test callhome inventory message
switch#
```

Related Commands

Command	Description
show callhome	Displays Call Home configuration information.
show running-config callhome	Displays the running configuration information for Call Home.

clear flow exporter

To clear the statistics for a Flexible NetFlow flow exporter, use the clear flow exporter command.

```
clear flow exporter name exporter-nameexporter-name
```

Syntax Description

name	Specifies the name of a flow exporter.
exporter-name	Name of an existing flow exporter.

Command Default

None

Command Modes

Any command mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

You must have already enabled traffic monitoring with Flexible NetFlow using an exporter before you can use the clear flow exporter command.

This command does not require a license.

Examples

This example clears the statistics for the flow exporter named NFC-DC-PHOENIX:

```
switch# clear flow exporter name
NFC-DC-PHOENIX
switch#
```

Related Commands

Command	Description
clear flow exporter	Clears the statistics for exporters.
flow exporter	Creates a flow exporter.
show flow exporter	Displays flow exporter status and statistics.

clear logging logfile

To clear the contents of the log file, use the clear logging logfile command.

```
clear logging logfile
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to clear the logging logfile:

```
switch# clear logging logfile
switch#
```

Related Commands

Command	Description
show logging logfile	Displays the messages in the log file.

clear logging nvram

To clear the NVRAM logs, use the clear logging nvram command.

```
clear logging nvram
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples This example shows how to clear the NVRAM logs:

```
switch# clear logging nvram
```

Command	Description
show logging nvram	Displays the NVRAM logs.

clear logging onboard

To clear the onboard failure logging (OBFL) entries in the persistent log, use the clear logging onboard command.

```
clear logging onboard [environmental-history] [exception-log] [obfl-log] [stack-trace]
```

Syntax Description

environmental-history	(Optional) Clears the OBFL environmental history.
exception-log	(Optional) Clears the OBFL exception log entries.
obfl-log	(Optional) Clears the OBFL (boot-uptime/device-version/obfl-history).
stack-trace	(Optional) Clears the OBFL stack trace entries.

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to clear the OBFL environmental history entries:

```
switch# clear logging onboard environmental-history
```

This example shows how to clear the OBFL exception-log entries:

```
switch# clear logging onboard exception-log
```

This example shows how to clear the OBFL (boot-uptime/device-version/obfl-history) entries:

```
switch# clear logging onboard obfl-log
```

This example shows how to clear the OBFL stack trace entries:

```
switch# clear logging onboard stack-trace
```

Related Commands

Command	Description
show logging onboard	Displays onboard failure logs.

clear logging session

To clear the current logging session, use the clear logging session command.

```
clear logging session
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to clear the current logging session:

```
switch# clear logging session
```

Command	Description
show logging session	Displays the logging session status.

clear ntp session

To clear the Network Time Protocol (NTP) session, use the clear ntp session command.

```
clear ntp session
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to discard the NTP Cisco Fabric Services (CFS) distribution session in progress:

```
switch# clear ntp session
```

Related Commands	Command	Description
	show ntp	Displays NTP information.

clear ntp statistics

To clear the Network Time Protocol (NTP) session, use the clear ntp statistics command.

```
clear ntp statistics all-peers | io | local | memory
```

Syntax Description		
	all-peers	Clears all peer transaction statistics.
	io	Clears I/O statistics.
	local	Clears local statistics.
	memory	Clears memory statistics.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to discard the NTP I/O statistics:

```
switch# clear ntp statistics io
```

Related Commands	Command	Description
	show ntp	Displays NTP information.

collect flow

To configure the flow sampler ID number as a nonkey field and collect their values for a Flexible NetFlow flow record, use the collect flow command. To disable the use of the flow direction or the flow sampler ID number as a nonkey field for a Flexible NetFlow flow record, use the no form of this command.

```
collect flow sampler id
no collect flow sampler id
```

Syntax Description

sampler id	Configures the flow sampler ID as a nonkey field and collects the ID of the sampler that is assigned to the flow monitor.
------------	---

Command Default

This command is not enabled by default.

Command Modes

Flow record configuration

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

The Flexible NetFlow commands that start with collect are used to configure nonkey fields for the flow monitor record and to enable capturing the values in the fields for the flow created with the record. The values in nonkey fields are added to flows to provide additional information about the traffic in the flows. A change in the value of a nonkey field does not create a new flow. In most cases, the values for nonkey fields are taken from only the first packet in the flow.

Use the collect flow sampler id command to collect the ID of the flow sampler that is used to monitor the flow. Use this command when more than one flow sampler is being used with different sampling rates. The option sampler-table command exports option records with mappings of the flow sampler ID to the sampling rate so that the collector can calculate the scaled counters for each flow.

This command does not require a license.

Examples

This example shows how to configure an ID of the flow sampler that is assigned to the flow as a nonkey field and collects the ID of the flow sampler:

```
switch(config)# flow record FLOW-RECORD-1
switch(config-flow-record)# collect flow sampler id
```

Related Commands

Command	Description
collect counter	Configures the counters as a nonkey field and collects the counter values.
collect flow	Configures flow identifying fields as nonkey fields and collects their values.
collect ip	Configures an IPv4 field as a nonkey field and collects the value in it.
collect routing	Configures a routing attribute as a nonkey field and collects the value of the field.

Command	Description
collect timestamp	Configures the times tamp fields as nonkey fields and collects the values.
collect transport	Configures a transport layer field as a nonkey field and collects the values.
flow record	Creates a flow record.
match ip	Configures one or more of the IP fields as a key field.
match ipv4	Configures one or more of the IPv4 fields as a key field.
match ipv6	Configures one or more of the IPv6 fields as a key field.
match transport	Configures one or more of the transport fields as key fields.
show flow record	Displays the flow record status and statistics.

commit (Call Home)

To commit Call Home configuration changes and distribute the changes to call Cisco Fabric Services (CFS)-enabled devices, use the commit command.

```
commit
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Call home configuration mode

Command History

Release	Modification
	This command was introduced.

Examples

This example shows how to commit CFS Call Home configuration changes:

```
switch(config-callhome)# commit
switch(config-callhome)#
```

Related Commands

Command	Description
show callhome	Displays Call Home configuration information.
show running-config callhome	Displays the running configuration information for Call Home.

commit (session)

To commit the current configuration session, use the commit command.

```
commit
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Session configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to commit the current session:

```
switch(config-s)# commit
```

```
switch(config-s)#
```

Related Commands	Command	Description
	configure session	Creates a configuration session.
	show configuration session	Displays the contents of the session.
	verify	Verifies a session.

configure maintenance profile

To enter a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile, use the `configure maintenance profile` command. To delete the existing maintenance mode profile or normal mode profile, use the `no` form of this command. Starting with Cisco NX-OS Release 7.3(0)N1(1), we recommend not using the `configure profile [maintenance-mode | normal-mode] type admin` command and we strongly recommend using the `configure maintenance profile [maintenance-mode | normal-mode]` command.

```
configure maintenance profile [maintenance-mode | normal-mode]
no configure maintenance profile [maintenance-mode | normal-mode]
```

Syntax Description

<code>maintenance-mode</code>	Enters the maintenance profile configuration session for a maintenance mode profile.
<code>normal-mode</code>	Enters the maintenance profile configuration session for a normal mode profile.

Command Default

None

Command Modes

Privileged EXEC (#)

Global configuration mode (config)

Command History

Release	Modification
7.3(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to enter a maintenance profile configuration session for a maintenance mode profile:

```
switch# configure maintenance profile maintenance-mode
Please configure 'system mode maintenance always-use-custom-profile' if you want to use
custom profile always for maintenance mode.
Enter configuration commands, one per line. End with CNTL/Z.
switch(config-mm-profile)#
```

This example shows how to enter a maintenance profile configuration session for a normal mode profile:

```
switch# configure maintenance profile normal-mode
Please configure 'system mode maintenance always-use-custom-profile' if you want to use
custom profile always for maintenance mode.
Enter configuration commands, one per line. End with CNTL/Z.
switch(config-mm-profile)#
```

This example shows how to delete a maintenance profile:

```
switch# no configure maintenance profile maintenance-mode
Maintenance mode profile maintenance-mode successfully deleted
```

Enter configuration commands, one per line. End with CNTL/Z.
Exit maintenance profile mode.

Related Commands

Command	Description
show run mmode	Displays the currently running maintenance profile configuration on a switch.
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance always-use-custom-profile	Applies the existing custom maintenance-mode profile and prevents creation of auto-generated maintenance-mode profile.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance-mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

contract-id (Call Home)

To configure the optional contract number for the customer, use the `contract-id` command. To remove a contract number, use the `no` form of this command.

```
contract-id contract-number
no contract-id
```

Syntax Description

<code>contract-number</code>	Contract number. The contract number can be up to 255 alphanumeric characters in free format.
------------------------------	---

Command Default

None

Command Modes

Call home configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

You can configure the customer identification information that Cisco Smart Call Home should use. The service agreement includes the customer identification information, such as the customer ID, contract ID, and site ID.

Examples

This example shows how to configure the contract number for the customer:

```
switch(config-callhome) # contract-id 12095134-1706
switch(config-callhome) #
```

Related Commands

Command	Description
<code>customer-id</code>	Configures the customer number for the switch.
<code>show callhome</code>	Displays a summary of the Call Home configuration.

customer-id (Call Home)

To configure the optional unique identification number for the customer, use the customer-id command. To remove a customer number, use the no form of this command.

```
customer-id customer-no
no customer-id
```

Syntax Description

customer-no	Customer number, as specified in the service agreement. The customer number can be up to 255 alphanumeric characters in free format.
-------------	--

Command Default

None

Command Modes

Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

You can configure the customer identification information that Cisco Smart Call Home should use. The service agreement includes the customer identification information, such as the customer ID, contract ID, and site ID.

Examples

This example shows how to configure a customer number:

```
switch(config-callhome)# customer-id AXC-1203
switch(config-callhome)#
```

Related Commands

Command	Description
site-id	Configures the site number for the switch.
show callhome	Displays a summary of the Call Home configuration.



D Commands

- [description \(NetFlow exporter\)](#), on page 34
- [description \(NetFlow monitor\)](#), on page 35
- [description \(NetFlow record\)](#), on page 36
- [description \(NetFlow sampler\)](#), on page 37
- [description \(SPAN, ERSPAN\)](#), on page 38
- [destination](#), on page 40
- [destination \(ERSPAN session\)](#), on page 41
- [destination \(SPAN session\)](#), on page 43
- [destination-profile \(Call Home\)](#), on page 46
- [diagnostic bootup level](#), on page 49
- [dscp](#), on page 50

description (NetFlow exporter)

To add a description to a NetFlow exporter, use the description command. To remove the description, use the no form of this command.

```
description line
no description [line]
```

Syntax Description

line	Description string. The string can have a maximum of 63 alphanumeric characters.
------	--

Command Default

None

Command Modes

NetFlow exporter configuration (config-flow-exporter)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to add a description to a NetFlow exporter:

```
switch(config)#flow export Netflow-Exporter-1
switch(config-flow-exporter)# description Custom-Exporter-1
switch(config-flow-exporter)
```

This example shows how to remove the description:

```
switch(config-flow-exporter)#no description
switch(config-flow-exporter)
```

Related Commands

Command	Description
show flow exporter	Displays information about NetFlow exporters.

description (NetFlow monitor)

To add a description to a NetFlow monitor, use the description command. To remove the description, use the no form of this command.

```
description line
no description [line]
```

Syntax Description

line	Description string. The string can have a maximum of 63 alphanumeric characters.
------	--

Command Default

None

Command Modes

NetFlow monitor configuration (config-flow-monitor)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to add a description to a NetFlow monitor:

```
switch(config)#flow monitor NetFlow-Monitor-1
switch(config-flow-monitor)#description Custom-Monitor-1
switch(config-flow-monitor)#
```

This example shows how to remove the description:

```
switch(config-flow-monitor)#no description
```

Related Commands

Command	Description
show flow record	Displays information about NetFlow records.

description (NetFlow record)

To add a description to a NetFlow record, use the description command. To remove the description, use the no form of this command.

```
description line
no description [line]
```

Syntax Description

line	Description string. The string can have a maximum of 63 alphanumeric characters.
------	--

Command Default

None

Command Modes

NetFlow record configuration (config-flow-record)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to add a description to a NetFlow record:

```
switch(config)#flow record NetFlow-Record-1
switch(config-flow-record)#description Custom-Flow-Record-1
switch(config-flow-record)#
```

This example shows how to remove the description:

```
switch(config-flow-record)#no description
```

Related Commands

Command	Description
show flow record	Displays information about NetFlow records.

description (NetFlow sampler)

To add a description to a NetFlow sampler, use the description command. To remove the description, use the no form of this command.

```
description line
no description [line]
```

Syntax Description

line	Description string. The string can have a maximum of 63 alphanumeric characters.
------	--

Command Default

None

Command Modes

NetFlow sampler configuration (config-flow-sampler)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to add a description to a NetFlow sampler:

```
switch(config)# sampler Netflow-Sampler-1
switch(config-flow-sampler)#description Custom-Sampler-1
switch(config-flow-sampler)#
```

This example shows how to remove the description:

```
switch(config-flow-sampler)#no description
```

Related Commands

Command	Description
show sampler	Displays information about NetFlow samplers.

description (SPAN, ERSPAN)

To add a description to an Ethernet Switched Port Analyzer (SPAN) or an Encapsulated Remote Switched Port Analyzer (ERSPAN) session configuration, use the description command. To remove the description, use the no form of this command.

```
description description
no description
```

Syntax Description

description	String description of the SPAN session configuration. This string is limited to 32 characters.
-------------	--

Command Default

No description is added.

Command Modes

SPAN session configuration mode (config-monitor)
 ERSPAN source session configuration mode (config-erspan-src)
 ERSPAN destination session configuration mode (config-erspan-dst)
 SPAN-on-Drop session configuration mode (config-span-on-drop)
 SPAN-on-Drop ERSPAN session configuration mode (config-span-on-drop-erspan)
 SPAN-on-Latency session configuration mode (config-span-on-latency)
 SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: ERSPAN destination session configuration mode, SPAN-on-Drop session configuration mode, SPAN-on-Drop ERSPAN session configuration mode, SPAN-on-Latency session configuration mode, and SPAN-on-Latency ERSPAN session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Use the description command to provide a reminder in the configuration to describe what certain SPAN and ERSPAN sessions are used for. The description appears in the output of the following commands such as show monitor session and show running-config monitor.

Examples

This example shows how to add a description for a SPAN session:

```
switch# configure terminal
switch(config)# monitor session 9 type local
switch(config-monitor)# description A Local SPAN session
switch(config-monitor)#
```

This example shows how to add a description for an ERSPAN source session:

```
switch# configure terminal
switch(config)# monitor session 9 type erspan-source
```



```
switch(config-erspan-src) # description ERSPAN-source-session
switch(config-erspan-src) #
```

This example shows how to add a description for an ERSPAN destination session:

```
switch# configure terminal
switch(config) # monitor session 9 type erspan-destination
switch(config-erspan-dst) # description ERSPAN-destination-session
switch(config-erspan-dst) #
```

This example shows how to add a description for an SPAN-on-Drop session:

```
switch# configure terminal
switch(config) # monitor session 9 type span-on-drop
switch(config-span-on-drop) # description span-on-drop-session
switch(config-span-on-drop) #
```

This example shows how to add a description for an ERSPAN SPAN-on-Drop session:

```
switch# configure terminal
switch(config) # monitor session 9 type span-on-drop-erspan
switch(config-span-on-drop-erspan) # description span-on-drop-erspan-session
switch(config-span-on-drop-erspan) #
```

This example shows how to add a description for an SPAN-on-Latency session:

```
switch# configure terminal
switch(config) # monitor session 9 type span-on-latency
switch(config-span-on-latency) # description span-on-latency-session
switch(config-span-on-latency) #
```

This example shows how to add a description for an ERSPAN SPAN-on-Latency session:

```
switch# configure terminal
switch(config) # monitor session 9 type span-on-latency-erspan
switch(config-span-on-latency-erspan) # description span-on-latency-erspan-session
switch(config-span-on-latency-erspan) #
```

Related Commands

Command	Description
destination (SPAN session)	Configures a destination SPAN port.
monitor session	Creates a new SPAN session configuration.
show monitor session	Displays SPAN session configuration information.
show running-config monitor	Displays the running configuration information of a SPAN session.
source (SPAN session)	Configures a source SPAN port.

destination

To specify the destination for a NetFlow exporter, use the destination command. To remove a destination, use the no form of this command.

```
destination ipaddripv6addr [use-vrf vrf_name]
no destination ipaddripv6addr [use-vrf vrf_name]
```

Syntax Description

ipaddr	Destination IP address for a collector.
ipv6addr	Destination IPv6 address for a collector.
use-vrf vrf_name	(Optional) Specifies the Virtual Routing and Forwarding (VRF) label.

Command Default

None

Command Modes

NetFlow exporter configuration (config-flow-exporter)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to specify the destination for a NetFlow exporter:

```
switch(config)# Flow exporter NetFlow-Exporter-1
switch(config-flow-exporter)# destination 192.168.11.2
switch(config-flow-exporter)#
```

This example shows how to remove the destination:

```
switch(config-flow-exporter)#no destination
```

Related Commands

Command	Description
show flow exporter	Displays information about NetFlow exporters.

destination (ERSPAN session)

To configure an Encapsulated Remote Switched Port Analyzer (ERSPAN) session destination IP address, use the destination command. To remove the destination ERSPAN IP address, use the no form of this command.

```
destination ip ip_address
no destination ip ip_address
```

Syntax Description	ip	Configures the remote IP address.
	ip_address	IPv4 address in the format A .B .C .D .

Command Default None

Command Modes ERSPAN source session configuration mode (config-erspan-src)
 SPAN-on-Drop ERSPAN session configuration mode (config-span-on-drop-erspan)
 SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Command History	Release	Modification
	7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: SPAN-on-Drop ERSPAN session configuration mode and SPAN-on-Latency ERSPAN session configuration mode.
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines You can configure only one destination IP address for an ERSPAN.
 This command does not require a license.

Examples

This example shows how to configure an ERSPAN source session destination IP address:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# destination ip 192.0.3.1
switch(config-erspan-src)#
```

This example shows how to configure an ERSPAN SPAN-on-Drop session destination IP address:

```
switch# configure terminal
switch(config)# monitor session 9 type span-on-drop-erspan
switch(config-span-on-drop-erspan)# destination ip 192.0.3.1
switch(config-span-on-drop-erspan)#
```

This example shows how to configure an ERSPAN SPAN-on-Latency session destination IP address:

```
switch# configure terminal
switch(config)# monitor session 9 type span-on-latency-erspan
```

```
switch(config-span-on-latency-erspan)# destination ip 192.0.3.1
switch(config-span-on-latency-erspan)#
```

Related Commands

Command	Description
monitor session	Creates a new SPAN session configuration.
show monitor session	Displays SPAN session configuration information.
show running-config monitor	Displays the running configuration information of a SPAN session.
source (ERSPAN session)	Configures a source SPAN port.
source (SPAN session)	Configures a source SPAN port.

destination (SPAN session)

To configure a Switched Port Analyzer (SPAN) destination port, use the destination command. To remove the destination SPAN port, use the no form of this command.

```
destination interface ethernet slot /[QSF-module/] port | port-channel channel-num | vlan vlan-num
| vsan vsan-num
no destination interface ethernet slot /[QSF-module/] port | port-channel channel-num | vlan vlan-num
| vsan vsan-num
```

Syntax Description

interface	Specifies the interface type to use as the destination SPAN port.
ethernet slot/[QSF-module/]port	Specifies the Ethernet interface to use as the destination SPAN port. The slot number is from 1 to 255. The QSFP-module number is from 1 to 199. The port number is from 1 to 128.
port-channel channel-num	Specifies the EtherChannel interface to use as the destination SPAN port. The EtherChannel number is from 1 to 4096.
vlan vlan-num	Specifies the VLAN interface to use as the destination SPAN port. The range is from 1 to 3967 and 4048 to 4093.
vsan vsan-num	Specifies the virtual storage area network (VSAN) to use as the destination SPAN port. The range is from 1 to 4093.

Command Default

None

Command Modes

SPAN session configuration mode (config-monitor)
 SPAN-on-Drop session configuration mode (config-span-on-drop)
 SPAN-on-Latency session configuration mode (config-span-on-latency)
 ERSPAN destination session configuration mode (config-erspan-dst)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: ERSPAN destination session configuration mode, SPAN-on-Drop session configuration mode, SPAN-on-Latency session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Each local SPAN, SPAN-on-Drop, and ERSPAN destination session must have a destination port (also called a monitoring port) that receives a copy of traffic from the source port.

The destination port can be any Ethernet physical port and must reside on the same switch as the source port (for a local SPAN session). The destination port cannot be a source port, a port channel, a VLAN, Host Interface (HIF), or a SAN port channel group.

A destination port receives copies of sent and received traffic for all monitored source ports. If a destination port is oversubscribed, it can become congested. This congestion can affect traffic forwarding on one or more of the source ports.

Examples

This example shows how to configure an Ethernet interface SPAN destination port and activate the SPAN session:

```
switch# configure terminal
switch(config)# interface ethernet 1/5
switch(config-if)# switchport monitor
switch(config-if)# exit

switch(config)# monitor session 9 type local
switch(config-monitor)# description A Local SPAN session
switch(config-monitor)# source interface ethernet 1/1
switch(config-monitor)# destination interface ethernet 1/5
switch(config-monitor)# no shutdown
switch(config-monitor)#
```

This example shows how to configure an Ethernet interface SPAN destination port and activate the SPAN-on-Drop session :

```
switch# configure terminal
switch(config)# interface ethernet 3/5
switch(config-if)# switchport monitor
switch(config-if)# exit

switch(config)# monitor session 11 type span-on-drop
switch(config-span-on-drop)# source interface ethernet 3/1
switch(config-span-on-drop)# destination interface ethernet 3/5
switch(config-span-on-drop)#
```

This example shows how to configure an Ethernet interface SPAN destination port and activate the SPAN-on-Latency session:

```
switch# configure terminal
switch(config)# interface ethernet 4/5
switch(config-if)# switchport monitor
switch(config-if)# exit

switch(config)# monitor session 12 type span-on-latency
switch(config-span-on-latency)# source interface ethernet 4/1
switch(config-span-on-latency)# destination interface ethernet 4/5
switch(config-span-on-latency)#
```

This example shows how to configure an Ethernet interface SPAN destination port and activate the ERSPAN destination session:

```
switch# configure terminal
switch(config)# interface ethernet 2/5
switch(config-if)# switchport monitor
switch(config-if)# exit

switch(config)# monitor session 10 type erspan-destination
switch(config-erspan-dst)# source ip 10.1.1.1
switch(config-erspan-dst)# destination interface ethernet 2/5
switch(config-erspan-dst)#
```

Related Commands

Command	Description
source (SPAN session)	Configures a source SPAN port.
monitor session	Creates a new SPAN session configuration.
show monitor session	Displays SPAN session configuration information.
show running-config monitor	Displays the running configuration information of a SPAN session.

destination-profile (Call Home)

To create a user-defined destination profile, or modify a predefined or user-defined destination profile, and configure the message format for that new destination profile, use the destination-profile command. To remove the destination profile, use the no form of this command.

```
destination-profile CiscoTAC-1 | full-txt-destination | short-txt-destination message-level level | message-size
size alert-group alert | email-addr email-address | http url | transport-method email | http
destination-profile profile-name [alert-group alert | email-addr email-address | format XML | full-txt |
short-txt | http url | message-level level | message-size size | transport-method email | http]
no destination-profile
```

Syntax Description

CiscoTAC-1	Configures a destination profile for Extensible Markup Language (XML) messages.
full-txt-destination	Configures a destination profile for plain text messages.
short-txt-destination	Configures a destination profile for short text message.
message-level level	Specifies the Call Home message severity level. The range is from 0 to 9, with 0 being the lowest urgency, and 9 the highest urgency.
message-size size	Specifies the maximum message size. The range is as follows: <ul style="list-style-type: none"> • full-txt-destination—From 0 to 5000000, and the default is 2500000. • short-txt-destination—From 0 to 100000, and the default is 4000. • CiscoTAC-1—5000000, which is not changeable.
alert-group alert	Associates one or more alert groups with a destination profile. The alert group can be one of the following: <ul style="list-style-type: none"> • All—All alert groups • Cisco-TAC—Cisco TAC events • Configuration—Configuration events • Diagnostic—Diagnostic events • EEM—EEM events • Environmental—Power, fan, and temperature-related events • Inventory —Inventory status events • License—Licensing events • Linecard-Hardware—Linecard-related events • Supervisor-Hardware—Supervisor-related events • Syslog-group-port—Syslog message events filed by the port manager • System—Software-related events • Test—User-generated test events
email-addr	Specifies the e-mail address to which the alert should be sent.
email-address	E-mail address in email address format. The address can be a maximum of 255 alphanumeric characters and cannot contain white spaces; for example, personname@companyname.com.

http url	Specifies the HTTP or HTTPS URL. The url can be a maximum of 255 alphanumeric characters and cannot contain white spaces; for example, http://site.com/services/callserv https://site2.com/serv/CALL
transport-method	Specifies the transport method for sending Call Home messages.
email	Specifies that Call Home messages be sent through e-mail.
http	Specifies that Call Home messages be sent using HTTP.
profile-name	User-defined profile name. The profile name can be a maximum of 31 alphanumeric characters.
format	(Optional) Specifies the Call Home message format. The default is XML.
XML	Specifies that the Call Home message format is XML.
full-txt	Specifies that the Call Home message format is plain text.
short-txt	Specifies that the Call Home message format is a short text message.

Command Default

Message format: XML.

Message size: 2500000 for full-txt-destination, 4000 for short-txt-destination, and 4000000 for XML format.

Message level: 0

Alert group: All for full-text-destination and short-text-destination profiles. The cisco-tac alert group for the CiscoTAC-1 destination profile.

Command Modes

Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

You can modify the following attributes for a predefined or user-defined destination profile:

- Destination e-mail address—The e-mail address to which the alert should be sent.
- Message formatting—The message format used for sending the alert (full text, short text, or XML).
- Message level—The Call Home message severity level for this destination profile.
- Message size—The allowed length of a Call Home message sent to the e-mail addresses in this destination profile.



Note You cannot modify or delete the CiscoTAC-1 destination profile.

The Cisco Nexus 5000 Series switch does not generate an alert if the Call Home severity level of the alert is lower than the message severity level set for the destination profile.

Table 1 lists each Call Home message level keyword.

Table 1: Call Home Message Severity Level

Call Home Level	Keyword	Description
9	Catastrophic	Network-wide catastrophic failure.
8	Disaster	Significant network impact.
7	Fatal	System is unusable.
6	Critical	Critical conditions that indicate that immediate attention is needed.
5	Major	Major conditions.
4	Minor	Minor conditions.
3	Warning	Warning conditions.
2	Notification	Basic notification and informational messages.
1	Normal	Normal event signifying return to normal state.
0	Debugging	Debugging messages.

Examples

This example shows how to create a user-defined Call Home destination profile to send Call Home messages through e-mail:

```
switch(config-callhome) # destination-profile myProfile alert-group Configuration email-addr
myname@somecompany.com message-level 3 transport-method email
```

```
switch(config-callhome) #
```

Related Commands

Command	Description
callhome	Configures a Call Home service.
copy running-config startup-config	Saves this configuration change.
show callhome	Displays Call Home configuration information.
show callhome destination-profile	Displays Call Home information for a destination profile.

diagnostic bootup level

To configure the bootup diagnostic level to trigger diagnostics when the device boots, use the diagnostic bootup level command. To remove bootup diagnostic level configuration, use the no form of this command.

```
diagnostic bootup level bypass | complete
no diagnostic bootup level bypass | complete
```

Syntax Description	
bypass	Specifies that all bootup tests are skipped.
complete	Specifies that all bootup diagnostics are performed. This is the default value.

Command Default Complete

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure the bootup diagnostics level to trigger the complete diagnostics:

```
switch(config)# diagnostic bootup level complete
switch(config)#
```

This example shows how to remove the bootup diagnostics level configuration:

```
switch(config)# no diagnostic bootup level complete
switch(config)#
```

Related Commands	Command	Description
	show diagnostic bootup level	Displays the bootup diagnostics level.
	show diagnostic bootup result	Displays the results of the diagnostics tests.

dscp

To specify the differentiated services code point (DSCP) for a NetFlow exporter, use the `dscp` command. To remove the DSCP parameter, use the `no` form of this command.

```
dscp dscp
no dscp [dscp]
```

Syntax Description

dscp	Differentiated services code point value. The range is from 0 to 63.
------	--

Command Default

None

Command Modes

NetFlow exporter configuration (config-flow-exporter)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the DSCP parameter:

```
switch(config)# Flow exporter Custom-NetFlow-Exporter-1
switch(config-flow-exporter)# dscp 32
switch(config-flow-exporter)#
```

This example shows how to remove the DSCP parameter:

```
switch(config-flow-exporter)#
no dscp
switch(config-flow-exporter)
```

Related Commands

Command	Description
show flow exporter	Displays information about NetFlow exporters.



E Commands

- [email-contact \(Call Home\)](#), on page 52
- [enable \(Call Home\)](#), on page 53
- [erspan-id](#), on page 54
- [exporter](#), on page 56

email-contact (Call Home)

To configure the e-mail address for the primary person responsible for the switch, use the `email-contact` command. To remove an email contact, use the `no` form of this command.

```
email-contact email-address
no email-contact
```

Syntax Description

email-address	E-mail address. The address can be a maximum of 255 alphanumeric characters in e-mail address format and cannot contain spaces.
---------------	---

Command Default

None

Command Modes

Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Examples

This example shows how to configure an e-mail address:

```
switch(config-callhome) # email-contact abc@xyz.com
switch(config-callhome) #
```

Related Commands

Command	Description
<code>copy running-config startup-config</code>	Saves this configuration change.
<code>phone-contact</code>	Configures the phone number for the primary person responsible for the switch.
<code>show callhome</code>	Displays a summary of the Call Home configuration.

enable (Call Home)

To enable the Cisco Smart Call Home service after you have configured the contact information, use the enable command. To disable the Smart Call Home service, use the no form of this command.

```
enable
no enable
```

Syntax Description This command has no arguments or keywords.

Command Default Disabled

Command Modes Callhome configuration mode

Command History	Release	Modification
		This command was introduced.

Usage Guidelines You must configure an e-mail server. Your switch must have IP connectivity to an e-mail server. You must configure the contact name (SNMP server contact), phone, and street address information before you enable Call Home.

Examples

This example shows how to enable the Cisco Smart Call Home service:

```
switch(config-callhome)# enable

contact email address is not configured
callhome can not be enabled on the switch, because necessary configuration has not been
done
Please check if all of following configuration is done
contact person name(sysContact)
contact person's email
contact person's phone number
street addr
To configure sysContact, please use snmp-server command
switch(config-callhome)#
```

This example shows how to disable the Cisco Smart Call Home service:

```
switch(config-callhome)# no enable

switch(config-callhome)#
```

Related Commands	Command	Description
	copy running-config startup-config	Saves this configuration change.
	email-contact	Configures the e-mail address.
	show callhome	Displays a summary of the Call Home configuration.

erspan-id

To configure the flow ID for an Encapsulated Remote Switched Port Analyzer (ERSPAN) session, use the `erspan-id` command. To remove the flow ID, use the `no` form of this command.

```
erspan-id flow_id
```

Syntax Description

flow_id	ERSPAN flow ID. The range is from 1 to 1023.
---------	--

Command Default

None

Command Modes

ERSPAN source session configuration mode (`config-erspan-src`)

ERSPAN destination session configuration mode (`config-erspan-dst`)

SPAN-on-Drop ERSPAN session configuration mode (`config-span-on-drop-erspan`)

SPAN-on-Latency ERSPAN session configuration mode (`config-span-on-latency-erspan`)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: ERSPAN destination session configuration mode, SPAN-on-Drop ERSPAN session configuration mode, and SPAN-on-Drop ERSPAN session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the flow ID for an ERSPAN source session:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# erspan-id 100
switch(config-erspan-src)#
```

This example shows how to configure the flow ID for an ERSPAN destination session:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-destination
switch(config-erspan-dst)# erspan-id 100
switch(config-erspan-dst)#
```

This example shows how to configure the flow ID for a SPAN-on-Drop ERSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-drop-erspan
switch(config-span-on-drop-erspan)# erspan-id 100
switch(config-span-on-drop-erspan)#
```

This example shows how to configure the flow ID for a SPAN-on-Latency ERSPAN session:


```
switch# configure terminal
switch(config)# monitor session 1 type span-on-latency-erspan
switch(config-span-on-latency-erspan)# erspan-id 100
switch(config-span-on-latency-erspan)#
```

Related Commands

Command	Description
ip dscp	Configures the DSCP value of the packets in the ERSPAN traffic.
ip ttl	Configures the IP time-to-live (TTL) value of the ERSPAN traffic.
vrf	Configures the VRF for ERSPAN traffic forwarding.
monitor-session	Enters the monitor configuration mode for configuring an ERSPAN or SPAN session for analyzing traffic between ports.

exporter

To specify a NetFlow exporter to use for a NetFlow monitor, use the `exporter` command. To remove a NetFlow exporter, use the `no` form of this command.

```
exporter name
no exporter name
```

Syntax Description

name	Name of the exporter.
------	-----------------------

Command Default

None

Command Modes

NetFlow monitor configuration (config-flow-monitor)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure a NetFlow exporter for a NetFlow monitor:

```
switch(config)# flow monitor Custom-Flow-Monitor-1
switch(config-flow-monitor)# exporter Custom-Flow-Exporter-1
switch(config-flow-monitor)#
```

This example shows how to remove a NetFlow exporter:

```
switch(config-flow-monitor)# no exporter
```

Related Commands

Command	Description
show flow record	Displays information about NetFlow records.



F Commands

- [factory reset](#), on page 58
- [feature netflow](#), on page 60
- [feature ptp](#), on page 61
- [fex-group](#), on page 62
- [filter access-group](#), on page 63
- [flow monitor](#), on page 64
- [flow monitor \(interface\)](#), on page 66
- [flow record](#), on page 68
- [flow timeout](#), on page 70

factory reset

To remove all the identifiable customer information on Cisco NX-OS devices in conditions of product removal due to Return Merchandise Authorization (RMA), or upgrade or replacement, or system end-of-life you can use the factory-reset command to securely erase all information.



Note There is no form of this command, once deleted you cannot regain the deleted information.

```
factory-reset fex-id | <all>
```

Command History

fex id	Securely erase fex as per identifier number. The range is 100-199.
all	Securely erase all the fex.
factory-reset	Securely erase data on the switch.

Command History

Release	Modification
7.3(11)N1(1)	This command was introduced.

Usage Guidelines

You use this command to erase customer information.
This command does not require a license.



Note If fex is attached to the switch, to erase the customer data on the connected fex perform below operation before performing a factory reset on the switch:

- To erase customer data on a single fex - factory reset fex <fex-id>
- To erase customer data on all fex - factory reset all

Examples

This example shows the factory-reset of a switch:

```
switch(config)# factory-reset
!!!! WARNING !!!!
```

The factory reset operation will erase ALL persistent storage on the specified module. This includes configuration, all log data, and the full contents of flash and SSDs. Special steps are taken in an effort to render data non-recoverable. Please, proceed with caution and understanding that this operation cannot be undone and will leave the system in a fresh-from-factory state.

```
!!!! WARNING !!!!
Continue? (y/n) [n] y
```

```
A device reload is required for the reset operation to proceed.  
Please, wait...  
WARNING: This command will reboot the system  
2006 Apr 24 06:23:17 switch %$ VDC-1 %$ %PFMA-2-PFM_SYSTEM_RESET: Manual system restart  
from Command Line Interface  
[ 972.939186] Shutdown Ports..  
[ 972.947864] writing reset reason 9,  
Secure erase requested! Please, do not power off module!
```

feature netflow

To globally enable the NetFlow feature, use the feature netflow command. To disable NetFlow, use the no form of this command.

```
feature netflow
no feature netflow
```

Syntax Description This command does not have any arguments or keywords.

Command Default Disabled

Command Modes Global configuration mode

Command History	Release	Modification
	7.0(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to enable NetFlow on a Cisco NX-OS device:

```
switch(config)# configure terminal
switch(config)# feature netflow
switch(config)#
```

This example shows how to disable NetFlow on a Cisco NX-OS device:

```
switch(config)# no feature netflow
switch(config)#
```

Related Commands	Command	Description
	flow record	Creates a flow record and enters flow record configuration mode.
	show flow record	Displays information about NetFlow flow records.

feature ptp

To enable the PTP feature, use the `feature ptp` command. To unconfigure the PTP feature, use the `no` form of this command.

```
feature ptp
no feature ptp
```

Syntax Description There are no arguments or keywords for this command.

Command Default None

Command Modes Global configuration mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to enable PTP on the device:

```
switch# configure terminal
switch(config)# feature ptp
```

Related Commands	Command	Description
	<code>feature ptp</code>	Enables or disables PTP on the device.
	<code>ptp source</code>	Configures the source IP address for all PTP packets.
	<code>ptp domain</code>	Configures the domain number to use for this clock.
	<code>ptp priority1</code>	Configures the priority 1 value to use when advertising this clock.
	<code>ptp priority2</code>	Configures the priority 1 value to use when advertising this clock.
	<code>show ptp brief</code>	Displays the PTP status.
	<code>show ptp clock</code>	Displays the properties of the local clock.

fex-group

To create a Fabric Extender (FEX) group, use the `fex-group` command. To delete a FEX group., use the `no` form of this command.

```
fex-group name
no fex-group name
```

Syntax Description

name	Specifies the name of the FEX group.
------	--------------------------------------

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
7.3(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to create a FEX group “fg1”:

```
switch# fex-group fg1
```

This example shows how to delete a FEX group “fg1”:

```
switch# no fex-group fg1
```

Related Commands

Command	Description
configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
show run mmode	Displays the currently running maintenance profile configuration on a switch.
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

filter access-group

To apply an access group to an Encapsulated Remote Switched Port Analyzer (ERSPAN) or Switched Port Analyzer (SPAN) source session, use the filter access-group command. To remove an access group, use the no form of this command.

```
filter access-group acl-filter
no filter access-group acl-filter
```

Syntax Description	acl-filter	Access control list (ACL) name. An ACL associates the access list with the SPAN session.
---------------------------	------------	--

Command Default	None
------------------------	------

Command Modes	SPAN session configuration mode (config-monitor) ERSPAN source session configuration mode (config-erspan-src)
----------------------	--

Command History	Release	Modification
	7.0(0)N1(1)	This command was introduced.

Usage Guidelines	ACL filtering allows you to filter SPAN and ERSPAN traffic so that you can reduce bandwidth congestion. An ACL is a list of permissions associated to any entity in the system; in the context of a monitoring session, an ACL is a list of rules which results in the spanning of traffic that matches the ACL criteria, saving bandwidth for more meaningful data. The filter applies to all sources in the session.
-------------------------	--



Note	If the ACL has rules with a log option configured, the log option is ignored but the rule is implemented.
-------------	---

Examples

This example shows how to enable an ACL filter for a SPAN session:

```
switch# configure terminal
switch(config)# monitor session 3
switch(config-monitor)# filter access-group acl_span_ses_3
```

This example shows how to enable an ACL filter for a ERSPAN session:

```
switch# configure terminal
switch(config)# monitor session 4 type erspan-source
switch(config-erspan-src)# filter access-group acl_erspan_ses_3
```

Related Commands	Command	Description
	monitor session	Creates a new SPAN or ERSPAN session.

flow monitor

To create a Flexible NetFlow flow monitor or to modify an existing Flexible NetFlow flow monitor and enter flow monitor configuration mode, use the flow monitor command. To remove a Flexible NetFlow flow monitor, use the no form of this command.

```
flow monitor monitor-name
no flow monitor monitor-name
```

Syntax Description

monitor-name	Name of the flow monitor that is created or modified.
--------------	---

Command Default

Flow monitors are not present in the configuration until you create them.

Command Modes

Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

Flow monitors are the Flexible NetFlow component that is applied to interfaces to perform network traffic monitoring. Flow monitors consist of a record that you add to the flow monitor after you create the flow monitor and a cache that is automatically created at the time that the flow monitor is applied to the first interface. Flow data is collected from the network traffic during the monitoring process based on the key and nonkey fields in record that is configured for the flow monitor and stored in the flow monitor cache.

Once you enter the flow monitor configuration mode, the prompt changes to the following:

```
switch(config-flow-monitor)#
```

Within the flow monitor configuration mode, the following keywords and arguments are available to configure the flow monitor:

- `description description`—Provides a description for this flow monitor; you use a maximum of 63 characters.
- `exit`—Exits from the current configuration mode.
- `exporter name`—Specifies the name of an exporter to export records.
- `no`—Negates a command or sets its defaults.
- `record {record-name | netflow ipv4collection-type | netflow-original}`—Specifies a flow record to use as follows:
 - `record-name`—Name of a record.
 - `netflow ipv4collection-type`—Specifies the traditional IPv4 NetFlow collection schemes as follows:

`original-input`—Specifies the traditional IPv4 input NetFlow.

`original-output`—Specifies the traditional IPv4 output NetFlow.

`protocol-port`—Specifies the protocol and ports aggregation scheme.

- `netflow-original`—Specifies the traditional IPv4 input NetFlow with origin autonomous systems.

The `netflow-original` and `original-input` keywords are the same and are equivalent to the following commands:

- match ipv4 source address
- match ipv4 destination address
- match ip tos
- match ip protocol
- match transport source-port
- match transport destination-port
- match interface input
- collect counter bytes
- collect counter packet
- collect timestamp sys-uptime first
- collect timestamp sys-uptime last
- collect interface output
- collect transport tcp flags
- collect routing next-hop address ipv4
- collect routing source as
- collect routing destination as

The original-output keywords are the same as the original-input keywords except for the following:

- match interface output (instead of match interface input)
- collect interface input (instead of collect interface output)

This command does not require a license.

Examples

This example shows how to create and configure a flow monitor named FLOW-MONITOR-1:

```
switch(config)# flow monitor FLOW-MONITOR-1
switch(config-flow-monitor)# description monitor location las vegas, NV
switch(config-flow-monitor)# exporter exporter-name1
switch(config-flow-monitor)# record test-record
switch(config-flow-monitor)# netflow ipv4
original-input
```

Related Commands

Command	Description
feature netflow	Enables the NetFlow feature.

flow monitor (interface)

To enable a Flexible NetFlow flow monitor for traffic that the router is receiving or forwarding, use the `flow monitor (interface)` command. To disable a Flexible NetFlow flow monitor, use the `no` form of this command.

```
ip | ipv6 flow monitor monitor-name input sampler sampler-name
no ip | ipv6 flow monitor monitor-name input sampler sampler-name
```

Syntax Description

<code>ip</code>	Configures IP Flexible NetFlow flow monitoring.
<code>ipv6</code>	Configures IPv6 Flexible NetFlow flow monitoring.
<code>monitor-name</code>	Name of a flow monitor that you previously configured.
<code>input</code>	Monitors traffic that the routers are receiving on the interface.
<code>sampler</code>	Specifies the name of a flow sampler for the flow monitor.
<code>sampler-name</code>	Flow sampler for this flow monitor using the name of a sampler that you previously configured.

Command Default

Disabled

Command Modes

Interface configuration (`config-if`)
 VLAN feature configuration (`config-vlan-config`)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

You must have already created a flow monitor by using the `flow monitor` command before you can apply the flow monitor to an interface with the `ip flow monitor` or `ipv6 flow monitor` command to enable traffic monitoring with Flexible NetFlow.

You must have already created a sampler by using the `sampler` command before you can enable a flow sampler for this flow monitor with the `ip flow monitor` or `ipv6 flow monitor` command.

When adding a sampler to a flow monitor, only packets that are selected by the named sampler are entered into the cache to form flows. Each use of a sampler results in separate statistics being stored for that usage.

You cannot add a sampler to a flow monitor after the flow monitor has been enabled on an interface. You must remove the flow monitor from the interface before you enable the same flow monitor with a sampler. See the “Examples” section for more information.



Note

The statistics for each flow needs to be scaled to give the expected true usage. For example, if you are using a 1 in 16 sampler, you must multiply the packet and byte counters by 16.

This command does not require a license.

Examples

This example shows how to enable an IPv6 flow monitor for monitoring input traffic on a VLAN:

```
switch(config)# vlan configuration 2
switch(config-vlan-config)# ip flow monitor FLOW-MONITOR-1 input sampler vlan-sampler
```



Note VLAN configuration mode enables you to configure VLANs independently of their creation, which is required for VTP client support.

- Egress NetFlow on VLAN is not supported

This example shows how to enable a flow monitor for monitoring input traffic:

```
switch(config)# interface ethernet1/1
switch(config-if)# ip flow monitor FLOW-MONITOR-1 input sampler sampler-1
```

This example shows how to enable two different flow monitors on two different interfaces for monitoring input traffic:

```
switch(config)# interface ethernet1/1
switch(config-if)# ip flow monitor FLOW-MONITOR-1 input sampler sampler-2
switch(config)# interface ethernet1/2
switch(config-if)# ip flow monitor FLOW-MONITOR-2 input sampler sampler-3
```

This example shows how to enable a flow monitor for monitoring input traffic with a sampler to limit the input packets that are sampled:

```
switch(config)# interface ethernet1/1
switch(config-if)# ip flow monitor FLOW-MONITOR-1 input sampler SAMPLER-1
```

This example shows how to remove the flow monitor and sampler from an IPv6 interface:

```
switch(config)# interface Ethernet
1/1
switch(config-if)# no ipv6 flow monitor FLOW-MONITOR-1 input sampler SAMPLER-1
```

Related Commands

Command	Description
flow exporter	Creates a flow exporter.
flow monitor	Creates a flow monitor.
flow record	Creates a flow record.
sampler	Creates a flow sampler.

flow record

To create a Flexible NetFlow flow record or to modify an existing Flexible NetFlow flow record and enter flow record configuration mode, use the flow record command. To remove a Flexible NetFlow flow record, use the no form of this command.

```
flow record record-name
no flow record record-name
```

Syntax Description

record-name	Name of the flow record that is created or modified.
-------------	--

Command Default

Flow records are not present in the configuration until you create them.

Command Modes

Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

Flexible NetFlow uses key and nonkey fields just as original NetFlow does to create and populate flows in a cache. In Flexible NetFlow, a combination of key and nonkey fields is called a record. Original NetFlow and Flexible NetFlow both use the values in key fields in IP datagrams, such as the IP source or destination address and the source or destination transport protocol port, as the criteria for determining when a new flow must be created in the cache while network traffic is being monitored. A flow is defined as a stream of packets between a given source and a given destination. New flows are created whenever NetFlow analyzes a packet that has a unique value in one of the key fields.

Once you enter the flow record configuration mode, the prompt changes to the following:

```
switch(config-flow-record) #
```

Within the flow record configuration mode, the following keywords and arguments are available to configure the flow record:

- collect—Specifies a nonkey field. See the collect command for additional information.
- description description—Provides a description for this flow record; you use a maximum of 63 characters.
- exit—Exits from the current configuration mode.
- match— Specifies a key field. See the match command for additional information.
- no—Negates a command or sets its defaults.

Cisco NX-OS enables the following match fields by default when you create a flow record:

- match interface input
- match interface output
- match flow direction

This command does not require a license.

Examples

This example shows how to create a flow record and enter flow record configuration mode:

```
switch(config)# flow record FLOW-RECORD-1  
switch(config-flow-record)#
```

Related Commands

Command	Description
flow monitor	Creates a flow monitor.

flow timeout

To create a Flexible NetFlow flow timeout or to modify an existing Flexible NetFlow flow timeout, use the flow timeout command. To remove a Flexible NetFlow flow timeout, use the no form of this command.

```
flow timeout [seconds]
no flow timeout [seconds]
```

Syntax Description

seconds	Flow timeout value in seconds. The range is from 5 to 60 seconds.
---------	---

Command Default

The default settings is 15 seconds.

Command Modes

Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

Cisco NX-OS exports data to the remote collector, using UDP frames, whenever a timeout occurs. By default, the flow timeout value is set to 15 seconds.

This command does not require a license.

Examples

This example shows how to specify the flow timeout in seconds:

```
switch(config)# flow timeout 45
switch(config)#
```

Related Commands

Command	Description
flow record	Creates a flow exporter.
flow monitor	Creates a flow monitor.



H Commands

- [hardware pq-drain](#), on page 72
- [hardware random-detect](#), on page 73

hardware pq-drain

To configure the proxy-queue drain rate settings, use the `hardware pq-drain` command in global configuration mode. To disable proxy-queue drain settings, use the `no` form of this command.

```
hardware pq-drain 10g 10g-drain-rate 40g 40g-drain-rate
no hardware pq-drain
```

Syntax Description

10g 10g-drain-rate	Proxy Queue drain rate for the 10 G interface. The range is from 1 Mbps to 20000 Mbps.
40g 40g-drain-rate	Proxy Queue drain rate for the 10 G interface. The range is from 1 Mbps to 80000 Mbps.

Command Default

Disabled

Command Modes

Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines



Note This command is applicable to only Cisco Nexus 6000 switches.

When the proxy queue reaches a threshold that indicates congestion, Explicit Congestion Notification (ECN) marking is performed so that the receiver of the packet echoes the congestion indication to the sender. The proxy-queue drain rate is configured to ensure that during congestion at egress ports only a certain amount of packets are drained.

Examples

This example shows how to configure proxy-queue settings to drain 9900 Mbps of traffic from 10 Gigabit interfaces and 39900 Mbps of traffic from 40 Gigabit interfaces:

```
switch(config)# hardware pq-drain 10g 9900 40g 39900
```

Related Commands

Command	Description
<code>hardware random-detect</code>	Configures ECN for a QoS group.

hardware random-detect

To configure Explicit Congestion Notification (ECN) for a Quality of Service (QoS) group, use the hardware random-detect command in global configuration mode. To disable ECN, use the no form of this command.

```
hardware random-detect min-thresh 10g 10g-min-threshold 40g 40g-min-threshold max-thresh 10g
10g-max-threshold 40g 40g-max-threshold ecn qos-group group-number
no hardware random-detect
```

Syntax Description

min-thresh	Minimum threshold.
10g 10g-min-threshold	Minimum threshold for 10 Gigabit interfaces. The range is from 1 to 67108863 bytes.
40g 40g-min-threshold	Minimum threshold for 40 Gigabit interfaces. The range is from 1 to 67108863 bytes.
max-thresh	Maximum threshold.
10g 10g-max-threshold	Maximum threshold for 10 Gigabit interfaces. The range is from 1 to 67108863 bytes.
40g 40g-max-threshold	Maximum threshold for 40 Gigabit interfaces. The range is from 1 to 67108863 bytes.
ecn	Enables ECN for the specified QoS group.
qos-group group-number	Specifies the QoS group that is being configured.

Command Default

Disabled

Command Modes

Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines



Note This command is applicable to only Cisco Nexus 6000 switches.

To implement Weighted Random Early Detection (WRED) Explicit Congestion Notification (ECN) on proxy queues you use the hardware random-detect command to configure minimum and maximum threshold values per QoS group. Then you use the hardware pq-drain command to configure the proxy-queue drain rate.

Examples

This example shows how to enable ECN threshold values for the class-default QoS group:

```
switch(config)# hardware random-detect min-thresh 10g 64000 40g 4000 max-thresh 10g 128000  
40g 246000 ecn qos-group 0
```

Related Commands

Command	Description
hardware pq-drain	Configures proxy queue drain rate.



I Commands

- [ip access-list \(session\)](#), on page 76
- [ip dns source-interface](#), on page 77
- [ip domain-list](#), on page 78
- [ip domain-lookup](#), on page 80
- [ip domain-name](#), on page 81
- [ip dscp \(ERSPAN\)](#), on page 83
- [ip host](#), on page 85
- [ip name-server](#), on page 86
- [ip port access-group \(session\)](#), on page 88
- [ip ttl \(ERSPAN\)](#), on page 89

ip access-list (session)

To create an IPv4 access control list (ACL) within a configuration session, use the ip access-list command. To remove an ACL from a configuration session, use the no form of this command.

```
ip access-list ACL-name
no ip access-list ACL-name
```

Syntax Description

ACL-name	Name of the IPv4 ACL. The name can be up to 64 alphanumeric characters and cannot contain a space or quotation mark.
----------	--

Command Default

No IPv4 ACLs are defined by default.

Command Modes

Global session configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to create an IPv4 ACL for a configuration session:

```
switch# configure session MySession1
switch(config-s)# ip access-list myACL
switch(config-s-acl)#
```

Related Commands

Command	Description
configure session	Creates a configuration session.
deny	Configures a deny rule in an IPv4 ACL.
permit	Configures a permit rule in an IPv4 ACL.
show configuration session	Displays the contents of the session.

ip dns source-interface

To configure the source interface for the Domain Name Server (DNS) domain lookup, use the ip dns source-interface command. To revert to the default settings, use the no form of this command.

```
ip dns source-interface ethernet slot /[QSFP-module/] port | loopback intf-num [vrf vrf-name | default | management]
no ip dns source-interface ethernet slot /[QSFP-module/] port | loopback intf-num [vrf vrf-name | default | management]
```

Syntax Description		
ethernet slot/[QSFP-module/]port		Specifies the Ethernet interface to use as the destination SPAN port. The slot number is from 1 to 255. The QSFP-module number is from 1 to 199. The port number is from 1 to 128.
loopback intf-num		Specifies the loopback interface to use as the source interface. The range of values is from 0 to 1023.
vrf		(Optional) Specifies the virtual routing and forwarding (VRF) instance.
vrf-name		(Optional) VRF name. The name is case sensitive and can be a maximum of 32 characters.
default		(Optional) Specifies the default VRF.
management		(Optional) Specifies the management VRF.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to configure an Ethernet interface as the source interface for a DNS lookup:

```
switch# configure terminal
switch(config)# ip dns source-interface ethernet 1/5
switch(config)#
```

Related Commands	Command	Description
	ip domain-lookup	Enables the DNS lookup feature.
	show ip dns source-interface	Displays information about the DNS source interfaces.

ip domain-list

To configure the IP domain list, use the ip domain-list command. To disable the IP domain list, use the no form of the command.

```
ip domain-list domain-name [use-vrf name]
no ip domain-list domain-name [use-vrf name]
```

Syntax Description

domain-list	Specifies the domain name for the IP domain list. The name can be any case-sensitive, alphanumeric string up to 63 characters.
use-vrf name	(Optional) Specifies the virtual routing and forwarding (VRF) to use to resolve the domain name for the IP domain list. The name can be any case-sensitive, alphanumeric string up to 32 characters.

Command Default

None

Command Modes

Global configuration mode
 VRF context configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Use the ip domain-list command to configure additional domain names for the device. Use the vrf context command to enter the VRF context mode to configure additional domain names for a particular VRF.

Examples

This example shows how to configure the IP domain list for the default VRF:

```
switch# config terminal
switch(config)# ip domain-list Mysite.com
```

This example shows how to configure the IP domain list for the management VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# ip domain-list Mysite.com
```

This example shows how to configure the IP domain list for the default VRF to use the management VRF as a backup if the domain name cannot be resolved through the default VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# exit
switch(config)# ip domain-name Mysite.com use-vrf management
switch(config)# ip name-server 192.0.2.1
switch(config)# ip domain-list Mysite2.com
```


Related Commands

Command	Description
show hosts	Displays information about the IP domain name configuration.

ip domain-lookup

To enable the Domain Name Server (DNS) lookup feature, use the ip domain-lookup command. Use the no form of this command to disable this feature.

```
ip domain-lookup
no ip domain-lookup
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines Use the ip domain-lookup command to enable DNS.

Examples This example shows how to configure the DNS server lookup feature:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# exit
switch(config)# ip domain-name Mysite.com use-vrf management
switch(config)# ip name-server 192.0.2.1
switch(config)# ip domain-lookup
switch(config)#
```

Related Commands	Command	Description
	show hosts	Displays information about the DNS.

ip domain-name

To configure a domain name, use the ip domain-name command. To delete a domain name, use the no form of the command.

```
ip domain-name domain-name [use-vrf name]
no ip domain-name domain-name [use-vrf name]
```

Syntax Description	domain-name	Domain name. The name can be any case-sensitive, alphanumeric string up to 63 characters.
	use-vrf name	(Optional) Specifies the virtual routing and forwarding (VRF) to use to resolve the domain name. The name can be any case-sensitive, alphanumeric string up to 32 characters.

Command Default None

Command Modes Global configuration mode
VRF context configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines Use the ip domain-name command to configure the domain name for the device. Use the vrf context command to enter the VRF context mode to configure the domain monastery for a particular VRF.

Examples This example shows how to configure the IP domain name for the default VRF:

```
switch# config terminal
switch(config)# ip domain-name Mysite.com
switch(config)#
```

This example shows how to configure the IP domain name for the management VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# ip domain-name Mysite.com
switch(config-vrf)#
```

This example shows how to configure the IP domain name for the default VRF to use the management VRF as a backup if the domain name cannot be resolved through the default VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# exit
switch(config)# ip domain-name Mysite.com use-vrf management
```

Related Commands	Command	Description
	ip domain-list	Configures the IP domain list.

Command	Description
ip domain-lookup	Enables the Domain Name Server (DNS) lookup feature.
show hosts	Displays information about the IP domain name configuration.

ip dscp (ERSPAN)

To configure the differentiated services code point (DSCP) value of the packets in the Encapsulated Remote Switched Port Analyzer (ERSPAN) traffic, use the ip dscp command. To revert to the default value, use the no form of this command.

```
ip dscp dscp_value
no ip dscp dscp_value
```

Syntax Description	dscp_value	DSCP value of the packets in the ERSPAN traffic. The range is from 0 to 63.
---------------------------	------------	---

Command Default None

Command Modes ERSPAN source session configuration mode (config-erspan-src)
 SPAN-on-Drop ERSPAN session configuration mode (config-span-on-drop-erspan)
 SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Command History	Release	Modification
	7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: SPAN-on-Drop ERSPAN session configuration mode, and SPAN-on-Latency ERSPAN session configuration mode.
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to configure the DSCP value of the packets in the ESRSPAN traffic for an ERSPAN source session:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# ip dscp 10
switch(config-erspan-src)#
```

This example shows how to configure the DSCP value of the packets in the ESRSPAN traffic for a SPAN-on-Drop ERSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-drop-erspan
switch(config-span-on-drop-erspan)# ip dscp 20
switch(config-span-on-drop-erspan)#
```

This example shows how to configure the DSCP value of the packets in the ESRSPAN traffic for a SPAN-on-Latency ERSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-latency-erspan
```

```
switch(config-span-on-latency-erspan)# ip dscp 30
switch(config-span-on-latency-erspan)#
```

Related Commands

Command	Description
ip prec	Configures the IP precedence value of the ERSPAN traffic.
ip ttl	Configures the IP time-to-live (TTL) value of the ERSPAN traffic.
monitor-session	Enters the monitor configuration mode for configuring an ERSPAN or SPAN session for analyzing traffic between ports.

ip host

To define static hostname-to-address mappings in the Domain Name System (DNS) hostname cache, use the ip host command. To remove a hostname-to-address mapping, use the no form of this command.

```
ip host name address1 [address2 ... address6]
no ip host name address1 [address2 ... address6]
```

Syntax Description

name	Hostname. The name can be any case-sensitive, alphanumeric string up to 80 characters.
address1	IPv4 address in the x.x.x.x format.
address2 ...address6	(Optional) Up to five additional IPv4 addresses in the x.x.x.x format.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Use the ip host command to add a static hostname to DNS.

Examples

This example shows how to configure a static hostname:

```
switch(config)# ip host mycompany.com 192.0.2.1
```

Related Commands

Command	Description
ipv6 host	Configures a static host name in the DNS database.
show hosts	Displays information about the IP domain name configuration.

ip name-server

To configure a name server, use the ip name-server command. To disable this feature, use the no form of the command.

```
ip name-server ip-address [use-vrf name]
no ip name-server ip-address [use-vrf name]
```

Syntax Description

ip-address	IP address for the name server.
use-vrf name	(Optional) Specifies the virtual routing and forwarding (VRF) to use to reach the name-server. The name can be any case-sensitive, alphanumeric string up to 32 characters.

Command Default

None

Command Modes

VRF context configuration mode
Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Use the ip name-server command to configure the name server for the device. Use the vrf context command to enter the VRF context mode to configure the domain names for a particular VRF.

Examples

This example shows how to configure the IP name server for the default VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# exit
switch(config)# ip domain-name Mysite.com use-vrf management
switch(config)# ip name-server 192.0.2.1
```

This example shows how to configure the IP name server for the management VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# ip name-server 192.0.2.1
```

This example shows how to configure the IP name server for the default VRF to use the management VRF as a backup if the IP name server cannot be reached through the default VRF:

```
switch# config terminal
switch(config)# vrf context management
switch(config-vrf)# exit
switch(config)# ip domain-name Mysite.com use-vrf management
switch(config)# ip name-server 192.0.2.1 use-vrf management
```


Related Commands

Command	Description
ip domain-list	Defines a list of domains.
ip domain lookup	Enables DNS-based host name-to-address translation.
show hosts	Displays information about the IP domain name configuration.
vrf context	Creates a virtual routing and forwarding (VRF) instance.

ip port access-group (session)

To apply an IPv4 access control list (ACL) to an interface as a port ACL, use the ip port access-group command. To remove an IPv4 ACL from an interface, use the no form of this command.

```
ip port access-group access-list-name in | out
no ip port access-group access-list-name in | out
```

Syntax Description

access-list-name	Name of the IPv4 ACL. The name can be up to 64 alphanumeric, case-sensitive characters long.
in	Specifies that the ACL applies to inbound traffic.
out	Specifies that the ACL applies to outbound traffic.

Command Default

None

Command Modes

Session interface configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to apply an IPv4 ACL named ip-acl-01 to the Ethernet interface 1/2 as a port ACL:

```
switch# configure session MySession1
switch(config-s)# interface ethernet 1/2
switch(config-s-if)# ip port access-group ip-acl-01 in
switch(config-s-if)#
```

This example shows how to remove an IPv4 ACL named ip-acl-01 from Ethernet interface 1/2:

```
switch(config-s)# interface ethernet 1/2
switch(config-s-if)# no ip port access-group ip-acl-01 in
switch(config-s-if)#
```

Related Commands

Command	Description
show access-lists	Displays all ACLs.
show configuration session	Displays the contents of the session.

ip ttl (ERSPAN)

To configure the IP time-to-live (TTL) value of the Encapsulated Remote Switched Port Analyzer (ERSPAN) traffic, use the ip ttl command. To revert to the default configuration, use the no form of this command.

```
ip ttl ttl_value
no ip ttl ttl_value
```

Syntax Description	ttl_value IP TTL value of the ERSPAN traffic. The range is from 1 to 255.
---------------------------	---

Command Default 255

Command Modes ERSPAN source session configuration mode (config-erspan-src)
 SPAN-on-Drop ERSPAN session configuration mode (config-span-on-drop-erspan)
 SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: SPAN-on-Drop ERSPAN session configuration mode, and SPAN-on-Latency ERSPAN session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to configure the IP TTL value of the ESRSPAN source:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# ip ttl 30
switch(config-erspan-src)#
This example shows how to remove the IP TTL value from the ESRSPAN source:
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# no ip ttl 30
switch(config-erspan-src)#
```

This example shows how to configure the IP TTL value in a SPAN-on-Drop ESRSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-drop-erspan
switch(config-span-on-drop-erspan)# ip ttl 30
switch(config-span-on-drop-erspan)#
```

This example shows how to remove the IP TTL value in a SPAN-on-Latency ESRSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-latency-erspan
```

```
switch(config-span-on-drop-latency)# no ip ttl 30
switch(config-span-on-drop-latency)#
```

Related Commands

Command	Description
ip dscp	Configures the DSCP value of the packets in the ERSPAN traffic.
monitor-session	Enters the monitor configuration mode for configuring an ERSPAN or SPAN session for analyzing traffic between ports.



L Commands

- [layer2-switched flow monitor](#), on page 92
- [logging abort](#), on page 93
- [logging commit](#), on page 94
- [logging console](#), on page 95
- [logging distribute](#), on page 96
- [logging event](#), on page 97
- [logging event port](#), on page 98
- [logging ip access-list cache](#), on page 99
- [logging level](#), on page 101
- [logging logfile](#), on page 102
- [logging module](#), on page 103
- [logging monitor](#), on page 104
- [logging server](#), on page 105
- [logging timestamp](#), on page 107

layer2-switched flow monitor

To associate a flow monitor and a sampler to the switch port input packets, use the later2-switched flow monitor command. To remove the association, use the no form of this command.

```
layer2-switched flow monitor flow-name input sampler sampler-name
no layer2-switched flow monitor flow-name input sampler sampler-name
```

Syntax Description

flow-name	Name of the flow monitor to associate with the input packets.
input	Specifies that this association applies to input packets only.
sampler sampler-name	The sampler to associate with the input packets.

Command Default

none.

Command Modes

Interface configuration mode (config-if)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

You must have already created a flow monitor by using the flow monitor command before you can associate a flow monitor to the switch port input packets.

You must have already created a sampler by using the sampler command before you can associate a sampler to the switch port input packets

Examples

This example shows how to associate a flow monitor and a sampler to the switch port input packets:

```
switch(config)# interface ethernet 1/3
switch(config-if)# layer2-switched flow monitor test-flow-monitor input sampler test-sampler
```

Related Commands

Command	Description
flow monitor	Create a Flexible NetFlow flow monitor.
sampler	Defines a sampler and enters the sampler configuration mode.

logging abort

To discard the pending changes to the syslog server configuration, use the logging abort command.

```
logging abort
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to discard the changes made to the syslog server configuration:

```
switch(config)# logging distribute

switch(config)# logging abort
switch(config)#
```

Command	Description
logging distribute	Enables the distribution of the syslog server configuration to network switches using the CFS infrastructure.
show logging pending	Displays the pending changes to the syslog server configuration.
show logging status	Displays the logging status.

logging commit

To commit the pending changes to the syslog server configuration for distribution to the switches in the fabric, use the logging commit command.

```
logging commit
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to commit the distribution of the syslog server configuration:

```
switch(config)# logging distribute
```

```
switch(config)# commit
```

```
switch(config)#
```

Related Commands	Command	Description
	logging distribute	Enables the distribution of the syslog server configuration to network switches using the CFS infrastructure.
	show logging status	Displays the logging status.

logging console

To enable logging messages to the console session, use the logging console command. To disable logging messages to the console session, use the no form of this command.

```
logging console [severity-level]
no logging console
```

Syntax Description

severity-level	<p>(Optional) Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows:</p> <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition—default level • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition • 6—informational: Informational message only • 7—debugging: Appears during debugging only
----------------	--

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to enable logging messages with a severity level of 4 (warning) or higher to the console session:

```
switch# configure terminal
switch(config)# logging console 4
```

Related Commands

Command	Description
show logging console	Displays the console logging configuration.

logging distribute

To enable the distribution of the syslog server configuration to network switches using the Cisco Fabric Services (CFS) infrastructure, use the logging distribute command. To disable the distribution, use the no form of this command.

```
logging distribute
no logging distribute
```

Syntax Description This command has no arguments or keywords.

Command Default Distribution is disabled.

Command Modes Global configuration mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to enable the distribution of the syslog server configuration:

```
switch(config)# logging distribute
```

```
switch(config)#
```

This example shows how to disable the distribution of the syslog server configuration:

```
switch(config)# no logging distribute
```

```
switch(config)#
```

Related Commands

Command	Description
logging abort	Cancels the pending changes to the syslog server configuration.
logging commit	Commits the changes to the syslog server configuration for distribution to the switches in the fabric.
show logging status	Displays the logging status.

logging event

To log interface events, use the logging event command. To disable logging of interface events, use the no form of this command.

```
logging event port link-status | trunk-status default | enable
no logging event port link-status | trunk-status default | enable
```

Syntax Description	
link-status	Specifies to log all UP/DOWN and CHANGE messages.
trunk-status	Specifies to log all TRUNK status messages.
default	Specifies to the default logging configuration is used by interfaces not explicitly configured.
enable	Enables the logging to override the port level configuration.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to log interface events:

```
switch# configure terminal
switch(config)# logging event link-status default
```

Related Commands	Command	Description
	show logging	Displays the logging status.

logging event port

To log events on an interface, use the logging event port command. To disable logging of interface events, use the no form of this command.

```
logging event port link-status | trunk-status [default]
no logging event port link-status | trunk-status
```

Syntax Description

link-status	Specifies to log all UP/DOWN and CHANGE messages.
trunk-status	Specifies to log all TRUNK status messages.
default	(Optional) Specifies the default logging configuration that is used by interfaces not explicitly configured.

Command Default

None

Command Modes

Interface configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to log interface events:

```
switch# configure terminal

switch(config)# interface ethernet 1/1
switch(config-if)# logging event port link-status default
```

Related Commands

Command	Description
show interface	Displays the interface configuration information.
show logging	Displays the logging status.

logging ip access-list cache

To configure the Optimized ACL Logging (OAL) parameters, use the logging ip access-list cache command. To reset to the default settings, use the no form of this command.

```
logging ip access-list cache entries num_entries | interval seconds | threshold num_packets
no logging ip access-list cache entries num_entries | interval seconds | threshold num_packets
```

Syntax Description		
entries num_entries	Specifies the maximum number of log entries that are cached in the software. The range is from 0 to 1048576. The default value is 8000 entries.	
interval seconds	Specifies the maximum time interval before an entry is sent to a syslog. The range is from 5 to 86400. The default value is 300 seconds.	
threshold num_packets	Specifies the number of packet matches (hits) before an entry is sent to a syslog. The range is from 0 to 1000000. The default value is 0 packets—rate limiting is off; the system log is not triggered by the number of packet matches.	

Command Default None

Command Modes Global configuration
network-admin

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples

This example shows how to specify the maximum number of log entries that are cached in the software:

```
switch# configure terminal
switch(config)# logging ip access-list cache entries 200
switch(config)#
```

This example shows how to specify the maximum time interval before an entry is sent to the system log:

```
switch# configure terminal
switch(config)# logging ip access-list cache interval 350
switch(config)#
```

This example shows how to specify the number of packet matches before an entry is sent to the system log:

```
switch# configure terminal
switch(config)# logging ip access-list cache threshold 125
switch(config)#
```

Related Commands

Command	Description
show logging ip access-list	Displays the status of IP access list logging.

logging level

To enable logging messages from a defined facility that have the specified severity level or higher, use the logging level command. To disable logging messages from a defined facility, use the no form of this command.

```
logging level facility severity-level
no logging level facility severity-level
```

Syntax Description	facility	severity-level
	Facility. The facilities are listed in Table 1-1 of Appendix 1 , “System Message Logging Facilities.” To apply the same severity level to all facilities, use the all facility.	Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows: <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition—default level • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition • 6—informational: Informational message only • 7—debugging: Appears during debugging only

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to enable logging messages from the AAA facility that have a severity level of 2 or higher:

```
switch(config)# logging level aaa 2
```

Related Commands	Command	Description
	show logging level	Displays the facility logging level configuration.

logging logfile

To configure the name of the log file used to store system messages and the minimum severity level to log, use the logging logfile command. To disable logging to the log file, use the no form of this command.

```
logging logfile logfile-name severity-level [size bytes]
no logging logfile logfile-name severity-level [size bytes]
```

Syntax Description	
logfile-name	Name of the log file to be used to store system messages.
severity-level	Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows: <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition—default level • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition • 6—informational: Informational message only • 7—debugging: Appears during debugging only
size bytes	(Optional) Specifies a maximum file size. The default file size is 4194304 bytes and can be configured from 4096 to 4194304 bytes.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure a log file called logfile to store system messages and set its severity level to 4:

```
switch(config)# logging logfile logfile 4
```

Related Commands	Command	Description
	show logging logfile	Displays the log file.

logging module

To enable module log messages, use the logging module command. To disable module log messages, use the no form of this command.

```
logging module [severity-level]
no logging module
```

Syntax Description

severity-level	<p>(Optional) Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows:</p> <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition—default level • 6—informational: Informational message only • 7—debugging: Appears during debugging only
----------------	--

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Set a specified severity level or use the default.

Examples

This example shows how to enable module log messages:

```
switch(config)# logging module
```

Related Commands

Command	Description
show logging module	Displays the module logging status.

logging monitor

To enable the device to log messages to the monitor (terminal line), use the logging monitor command. To disable monitor log messages, use the no form of this command.

```
logging monitor [severity-level]
no logging monitor
```

Syntax Description

severity-level	<p>(Optional) Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows:</p> <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition—default level • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition • 6—informational: Informational message only • 7—debugging: Appears during debugging only
----------------	--

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This configuration applies to Telnet and Secure Shell (SSH) sessions.

Examples

This example shows how to enable monitor log messages:

```
switch(config)# logging monitor
```

Related Commands

Command	Description
show logging monitor	Displays the status of monitor logging.

logging server

To configure a remote syslog server at the specified hostname or IPv4/IPv6 address, use the logging server command. To disable the remote syslog server, use the no form of this command.

```
logging server host [severity-level] [facility auth | authpriv | cron | daemon | ftp | kernel | local0 | local1 |
local2 | local3 | local4 | local5 | local6 | local7 | lpr | mail | news | syslog | user | uucp | use-vrf vrf_name |
management]
```

```
no logging server host [severity-level] [facility auth | authpriv | cron | daemon | ftp | kernel | local0 | local1 |
local2 | local3 | local4 | local5 | local6 | local7 | lpr | mail | news | syslog | user | uucp | use-vrf vrf_name |
management]
```

Syntax Description

host	Hostname or IPv4/IPv6 address of the remote syslog server.
severity-level	(Optional) Number of the desired severity level at which messages should be logged. Messages at or numerically lower than the specified level are logged. Severity levels are as follows: <ul style="list-style-type: none"> • 0—emergency: System unusable • 1—alert: Immediate action needed • 2—critical: Critical condition—default level • 3—error: Error condition • 4—warning: Warning condition • 5—notification: Normal but significant condition • 6—informational: Informational message only • 7—debugging: Appears during debugging only
facility facility	(Optional) Specifies the outgoing facility . The facilities are listed in Table 1-1 of Appendix 1, “System Message Logging Facilities.” The default outgoing facility is local7.
vrf vrf_name	(Optional) Specifies the virtual routing and forwarding (VRF) to be used in the remote server. The name can be a maximum of 32 alphanumeric characters.
management	Specifies the management VRF. This is the default VRF.

Command Default

The default outgoing facility is local7. The default VRF is management.

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure a remote syslog server at a specified IPv4 address, using the default outgoing facility:

```
switch(config)# logging server 192.168.2.253
```

This example shows how to configure a remote syslog server at a specified hostname with severity level 5 or higher:

```
switch(config)# logging server syslogA 5
```

Related Commands

Command	Description
show logging server	Displays the configured syslog servers.

logging timestamp

To set the logging time-stamp units, use the logging timestamp command. To reset the logging time-stamp units to the default, use the no form of this command.

```
logging timestamp microseconds | milliseconds | seconds
no logging timestamp microseconds | milliseconds | seconds
```

Syntax Description	
microseconds	Specifies the units to use for logging timestamps in microseconds. The default units are seconds.
milliseconds	Specifies the units to use for logging timestamps in milliseconds.
seconds	Specifies the units to use for logging timestamps in seconds. The default units are seconds.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines By default, the units are seconds.

Examples This example shows how to set the logging time-stamp units to microseconds:

```
switch(config)# logging timestamp microseconds
```

Related Commands	Command	Description
	show logging timestamp	Displays the logging time-stamp configuration.

logging timestamp



M Commands

- [match datalink](#), on page 110
- [match ip](#), on page 111
- [match ipv4](#), on page 112
- [match transport](#), on page 113
- [mode](#), on page 114
- [monitor erspan origin ip-address](#), on page 115
- [monitor session](#), on page 116
- [mtu](#), on page 120

match datalink

To configure the match data link (or Layer 2) attributes option in a flow record, use the match datalink command. To remove the data link configuration, use the no form of this command.

```
match datalink mac source-address | mac destination-address | ethertype | vlan
no match datalink mac source-address | mac destination-address | ethertype | vlan
```

Syntax Description

mac	Specifies the MAC address.
source-address	Specifies the source MAC address.
destination-address	Specifies the destination MAC address.
ethertype	Specifies the EtherType.
vlan	Specifies the VLAN ID.

Command Default

None

Command Modes

NetFlow record configuration (config-flow-record)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the match data link attributes option in a flow record:

```
switch(config)# flow record NetFlow1
switch(config-flow-record)# match datalink mac source-address
switch(config-flow-record)#
```

This example shows how to remove the data link match option from a flow record:

```
switch(config-flow-record)# no
match datalink mac source-address
switch(config-flow-record)#
```

Related Commands

Command	Description
match ip	Configures the match IP option for defining a NetFlow record map.
match ipv4	Configures the match IPv4 option for defining a NetFlow record map.

match ip

To configure the match IP option for defining a NetFlow record map, use the match ip command. To remove this option, use the no form of this command.

```
match ip protocol | tos
no match ip protocol | tos
```

Syntax Description

protocol	Specifies the protocol.
tos	Specifies the type of service (ToS).

Command Default

None

Command Modes

NetFlow record configuration (config-flow-record)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the match IP option for defining a NetFlow record map:

```
switch(config)# flow record Custom-NetFlow-Record-1
switch(config-flow-record)# match ip protocol
switch(config-flow-record)# match ip tos
switch(config-flow-record)#
```

This example shows how to remove the match option:

```
switch(config-flow-record)# no match ip protocol
switch(config-flow-record)# no match ip tos
switch(config-flow-record)#
```

Related Commands

Command	Description
show flow record	Displays information about NetFlow records.

match ipv4

To configure the match IPv4 option for defining a NetFlow record map, use the match ipv4 command. To remove this option, use the no form of this command.

```
match ipv4 source | destination address
no match ipv4 source | destination address
```

Syntax Description

source	Specifies the source address.
destination	Specifies the destination address.
address	Specifies the address.

Command Default

None

Command Modes

NetFlow record configuration (config-flow-record)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the match IPv4 option for defining a NetFlow record map:

```
switch(config)# flow record Custom-NetFlow-Record-1
switch(config-flow-record)# match ipv4 source address
switch(config-flow-record)# match ipv4 destination address
switch(config-flow-record)#
```

This example shows how to remove the match IPv4 configuration:

```
switch(config-flow-record)# no
match ipv4 source address
switch(config-flow-record)# no
match ipv4 destination address
switch(config-flow-record)#
```

Related Commands

Command	Description
show flow record	Displays information about NetFlow records.

match transport

To configure the match transport option for defining a NetFlow record map, use the match transport command. To remove the match transport option, use the no form of this command.

```
match transport destination-port | source-port
no match transport destination-port | source-port
```

Syntax Description

destination-port	Specifies the transport destination port.
source-port	Specifies the transport source port.

Command Default

None

Command Modes

NetFlow record configuration (config-flow-record)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the match transport option for defining a NetFlow record map:

```
switch(config)# flow record Custom-NetFlow-Record-1
switch(config-flow-record)#
match transport source-port
```

This example shows how to remove the configuration:

```
switch(config-flow-record)# no
match transport source-port
switch(config-flow-record)
```

Related Commands

Command	Description
show flow record	Displays information about NetFlow records.

mode

To specify the mode in a NetFlow sampler, use the mode command. To remove the mode, use the no form of this command.

```
mode samples out-of packets
no mode [samples out-of packets]
```

Syntax Description

samples	Number of samples per sampling. The range is from 1 to 64.
out-of	M out of N packets.
packets	Number of packets in each sampling. The range is from 1 to 65536, and must be a power of 2.

Command Default

None

Command Modes

NetFlow sampler configuration (config-flow-sampler)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to specify the mode in a NetFlow sampler:

```
switch(config)#
sampler Custom-NetFlow-Sampler-1
switch(config-flow-sampler)# mode 1 out-of 1024
switch(config-flow-sampler)#
```

This example shows how to remove the mode configuration:

```
switch(config-flow-sampler)# no mode
```

Related Commands

Command	Description
show sampler	Displays information about NetFlow samplers.

monitor erspan origin ip-address

To configure the Encapsulated Remote Switched Port Analyzer (ERSPAN) origin IP address, use the `monitor erspan origin ip-address` command. To remove the ERSPAN origin IP address configuration, use the `no` form of this command.

```
monitor erspan origin ip-address ip-address [global]
no monitor erspan origin ip-address ip-address [global]
```

Syntax Description	ip-address	IP address.
	global	(Optional) Specifies the default virtual device context (VDC) configuration across all VDCs.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines When you change the origin IP address in the default VDC, it impacts all the sessions. This command does not require a license.

Examples

This example shows how to configure the ERSPAN origin IP address:

```
switch# configure terminal
switch(config)# monitor erspan origin ip-address 10.1.1.1 global
switch(config)#
```

This example shows how to remove the ERSPAN IP address:

```
switch# configure terminal
switch(config)# no monitor erspan origin ip-address 10.1.1.1 global
switch(config)#
```

Related Commands	Command	Description
	monitor session	Configures a SPAN or an ERSPAN session.

monitor session

To create a new Ethernet Switched Port Analyzer (SPAN) or an Encapsulated Remote Switched Port Analyzer (ERSPAN) session configuration for analyzing traffic between ports or add to an existing session configuration, use the `monitor session` command. To clear SPAN or ERSPAN sessions, use the `no` form of this command.

```
monitor session session-number [shut | type local | erspan-destination | erspan-source | span-on-drop |
span-on-drop-erspan | span-on-latency | span-on-latency-erspan | all shut]
no monitor session session-number | all [shut]
```

Syntax Description

session-number	SPAN session to create or configure. The range is from 1 to 48.
all	Specifies to apply configuration information to all SPAN sessions.
shut	(Optional) Specifies that the selected session will be shut down for monitoring.
type	(Optional) Specifies the type of session to configure.
local	Specifies the session type to be local.
erspan-destination	Creates an ERSPAN destination session.
erspan-source	Creates an ERSPAN source session.
span-on-drop	Creates a SPAN on drop session.
span-on-drop-erspan	Creates a SPAN on drop ERSPAN session.
span-on-latency	Creates a SPAN on latency session
span-on-latency-erspan	Creates a SPAN on latency ERSPAN session
suspend	(Optional) Specifies to suspend the referenced SPAN session.

Command Default None

Command Modes Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. Support was added for the <code>erspan-destination</code> , <code>span-on-drop</code> , <code>span-on-drop-erspan</code> , <code>span-on-latency</code> , <code>span-on-latency-erspan</code> keywords, and the <code>session-number</code> range was increased from 18 to 48.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

To ensure that you are working with a completely new session, you can clear the desired session number or all SPAN sessions.



Note The limit on the number of egress (TX) sources in a monitor session has been lifted. Port-channel interfaces can be configured as egress sources.

After you create an ERSPAN session, you can describe the session and add interfaces and VLANs as sources and destinations.

Examples

This example shows how to create a SPAN session:

```
switch# configure terminal
switch(config)# monitor session 2
switch(config)#
```

This example shows how to enter the monitor configuration mode for configuring SPAN session number 9 for analyzing traffic between ports:

```
switch(config)# monitor session 9 type local
switch(config-monitor)# description A Local SPAN session
switch(config-monitor)# source interface ethernet 1/1
switch(config-monitor)# destination interface ethernet 1/2
switch(config-monitor)# no shutdown
```

This example shows how to configure any SPAN destination interfaces as Layer 2 SPAN monitor ports before activating the SPAN session:

```
switch(config)# interface ethernet 1/2
switch(config-if)# switchport
switch(config-if)# switchport monitor
switch(config-if)# no shutdown
```

This example shows how to configure a typical SPAN destination trunk interface:

```
switch(config)# interface Ethernet1/2
switch(config-if)# switchport
switch(config-if)# switchport mode trunk
switch(config-if)# switchport monitor
switch(config-if)# switchport trunk allowed vlan 10-12
switch(config-if)# no shutdown
```

This example shows how to create an ERSPAN source session:

```
switch# configure terminal
```

```
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# description ERSPAN-source-session
switch(config-erspan-src)# source interface ethernet 1/5 rx
switch(config-erspan-src)# destination ip 192.0.3.1
switch(config-erspan-src)# erspan-id 100
switch(config-erspan-src)# filter access-group acl_erspan_ses_3
switch(config-erspan-src)# ip dscp 10
switch(config-erspan-src)#
```

This example shows how to create an ERSPAN destination session:

```
switch(config)# interface ethernet 2/5
switch(config-if)# switchport monitor
switch(config-if)# no monitor session 3
switch(config-if)# monitor session 3 type erspan-destination
switch(config-erspan-dst)# description erspan_dst_session_3
switch(config-erspan-dst)# source ip 10.1.1.1
switch(config-erspan-dst)# destination interface ethernet 2/5
switch(config-erspan-dst)# erspan-id 5
switch(config)# no shut
```

This example shows how to create a SPAN-on-Latency session:

```
switch(config)# interface Ethernet 1/2

switch(config-if)# switchport monitor
switch(config-if)# packet latency threshold 530000000
switch(config)# monitor session 9 type span-on-latency
switch(config-span-on-latency)# description span-on-latency-session
switch(config-span-on-latency)# source interface ethernet 4/1
switch(config-span-on-latency)# destination interface ethernet 4/5
```

This example shows how to create an ERSPAN SPAN-on-Latency session:

```
switch(config)# interface Ethernet 1/1

switch(config-if)# switchport monitor
switch(config-if)# packet latency threshold 530000000
switch(config)# monitor session 10 type span-on-drop-latency-erspan
switch(config-span-on-latency-erspan)# description span-on-latency-erspan-session
switch(config-span-on-latency-erspan)# destination ip 192.0.3.1
switch(config-span-on-latency-erspan)#
```

Related Commands

Command	Description
description (SPAN, ERSPAN)	Adds a description to identify the SPAN session.
destination (ERSPAN)	Configures the destination IP port for an ERSPAN packet.
erspan-id (ERSPAN)	Sets the flow ID for an ERSPAN session.
ip dscp (ERSPAN)	Sets the DSCP value for an ERSPAN packet.
ip prec (ERSPAN)	Sets the IP precedence value for an ERSPAN packet.
ip ttl (ERSPAN)	Sets the time-to-live (TTL) value for an ERSPAN packet.

Command	Description
mtu (ERSPAN)	Sets the maximum transmission value (MTU) for ERSPAN packets.
packet latency threshold	Configures the latency threshold value on an interface.
show monitor session	Displays SPAN session configuration information.
source (SPAN, ERSPAN)	Adds a SPAN source port.

mtu

To configure the maximum transmission unit (MTU) truncation size for packets in the specified Ethernet Switched Port Analyzer (SPAN) session, use the `mtu` command. To remove the MTU truncation size configuration, use the `no` form of this command.

```
mtu mtu-size
no mtu
```

Syntax Description

mtu-size	MTU truncation size. The range is from 64 to 1518.
----------	--

Command Default

Disabled

Command Modes

SPAN session configuration mode (config-monitor)
 ERSPAN source session configuration mode (config-erspan-src)
 SPAN-on-Latency session configuration mode (config-span-on-latency)
 SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: ERSPAN source session configuration mode, SPAN-on-Latency session configuration mode, and SPAN-on-Latency ERSPAN session configuration mode. The upper limit of the range was changed from 1500 to 1518.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the MTU truncation size for packets in the specified SPAN session:

```
switch# configure terminal
switch(config)# monitor session 5
switch(config-monitor)# mtu 128
switch(config-monitor)#
```

This example shows how to remove the MTU truncation size configuration for packets in the specified SPAN session:

```
switch# configure terminal
switch(config)# monitor session 5
switch(config-monitor)# no mtu
```

Related Commands

Command	Description
monitor session	Places you in the monitor configuration mode for configuring a SPAN session.
show monitor session	Displays the status of the SPAN session.



N Commands

- [ntp](#), on page 124
- [ntp abort](#), on page 125
- [ntp authenticate](#), on page 126
- [ntp commit](#), on page 127
- [ntp distribute](#), on page 128
- [ntp sync-retry](#), on page 129

ntp

To configure the Network Time Protocol (NTP) peers and servers for the switch, use the `ntp` command. To remove configured peers and servers, use the `no` form of this command.

```
ntp peer hostname | server hostname [prefer] [ use-vrf vrf-name ]
no ntp peer hostname | server hostname
```

Syntax Description

<code>peer hostname</code>	Specifies the hostname or IP address of an NTP peer.
<code>server hostname</code>	Specifies the hostname or IP address of the NTP server.
<code>prefer</code>	(Optional) Specifies this peer/server as the preferred peer/server.
<code>use-vrf vrf-name</code>	(Optional) Specifies the virtual routing and forwarding (VRF) used to reach this peer/server.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

You can specify multiple peer associations.

Examples

This example shows how to form a server association with a server:

```
switch(config)# ntp server ntp.cisco.com
```

This example shows how to form a peer association with a peer:

```
switch(config)# ntp peer 192.168.10.0
```

This example shows how to delete an association with a peer:

```
switch(config)# no ntp peer 192.168.10.0
```

Related Commands

Command	Description
<code>ntp distribute</code>	Enables CFS distribution for NTP.
<code>show ntp</code>	Displays NTP information.

ntp abort

To discard the Network Time Protocol (NTP) Cisco Fabric Services (CFS) distribution session in progress, use the `ntp abort` command.

```
ntp abort
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to discard the NTP CFS distribution session in progress:

```
switch(config)# ntp abort
```

Related Commands	Command	Description
	<code>ntp distribute</code>	Enables CFS distribution for NTP.
	<code>show ntp</code>	Displays NTP information.

ntp authenticate

To enable Network Time Protocol (NTP) authentication, use the `ntp authenticate` command. To disable NTP authentication, use the `no` form of this command.

```
ntp authenticate
no ntp authenticate
```

Syntax Description This command has no arguments or keywords.

Command Default Disabled

Command Modes Global configuration (config)

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to enable NTP authentication:

```
switch(config)# ntp authenticate
```

This example shows how to disable NTP authentication:

```
switch(config)# no ntp authenticate
switch(config)#
```

Related Commands	Command	Description
	<code>show ntp authentication-status</code>	Displays the status of NTP authentication.

ntp commit

To apply the pending configuration pertaining to the Network Time Protocol (NTP) Cisco Fabric Services (CFS) distribution session in progress in the fabric, use the `ntp commit` command.

```
ntp commit
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to commit changes to the active NTP configuration:

```
switch(config)# ntp commit
```

Related Commands	Command	Description
	ntp distribute	Enables CFS distribution for NTP.
	show ntp	Displays NTP information.

ntp distribute

To enable Cisco Fabric Services (CFS) distribution for Network Time Protocol (NTP), use the `ntp distribute` command. To disable this feature, use the `no` form of this command.

```
ntp distribute
no ntp distribute
```

Syntax Description This command has no arguments or keywords.

Command Default Disabled

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines Before distributing the Fibre Channel timer changes to the fabric, the temporary changes to the configuration must be committed to the active configuration using the `ntp commit` command.

Examples This example shows how to distribute the active NTP configuration to the fabric:

```
switch(config)# ntp distribute
```

Related Commands	Command	Description
	<code>ntp commit</code>	Commits the NTP configuration changes to the active configuration.
	<code>show ntp</code>	Displays NTP information.

ntp sync-retry

To retry synchronization with the configured Network Time Protocol (NTP) servers, use the `ntp sync-retry` command.

```
ntp sync-retry
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to retry synchronization with the configured NTP servers:

```
switch# ntp sync-retry
```

Related Commands	Command	Description
	ntp distribute	Enables CFS distribution for NTP.
	show ntp	Displays NTP information.



0 Commands

- [option exporter-stats timeout, on page 132](#)
- [option interface-table timeout, on page 133](#)
- [option sampler-table timeout, on page 134](#)

option exporter-stats timeout

To configure the NetFlow exporter resend timer, use the `option exporter-stats timeout` command. To remove the NetFlow exporter resend timer, use the `no` form of this command.

```
option exporter-stats timeout time
no option exporter-stats timeout
```

Syntax Description

<code>time</code>	Time in seconds. The range is from 1 to 86400.
-------------------	--

Command Default

None

Command Modes

NetFlow exporter version 9 configuration (`config-flow-exporter-version-9`)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the NetFlow exporter resend timer:

```
switch(config)# flow exporter Custom-Flow-Exporter-1
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# option exporter-stats timeout 1200
switch(config-flow-exporter-version-9)#
```

This example shows how to remove the NetFlow exporter resend timer configuration:

```
switch(config-flow-exporter-version-9)# no option exporter-stats timeout
switch(config-flow-exporter-version-9)#
```

Related Commands

Command	Description
<code>show flow exporter</code>	Displays information about NetFlow exporters.

option interface-table timeout

To configure the NetFlow exporter interface-table timer, use the option interface-table timeout command. To remove the interface-table timer, use the no form of this command.

```
option interface-table timeout time
no option interface-table timeout [time]
```

Syntax Description

time	Time in seconds. The range is from 1 to 86400.
------	--

Command Default

None

Command Modes

NetFlow exporter version 9 configuration (config-flow-exporter-version-9)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the NetFlow exporter interface-table timer:

```
switch(config)# flow exporter Custom-Flow-Exporter-1
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# option interface-table timeout 1200
switch(config-flow-exporter-version-9)#
```

This example shows how to remove the NetFlow exporter interface-table timer configuration:

```
switch(config-flow-exporter-version-9)# no
option interface-table timeout
```

Related Commands

Command	Description
show flow exporter	Displays information about the NetFlow exporters.

option sampler-table timeout

To configure the NetFlow exporter sampler-table timer, use the option sampler-table timeout command. To remove the sampler-table timer, use the no form of this command.

```
option sampler-table timeout time
no option sampler-table timeout [time]
```

Syntax Description

time	Time in seconds. The range is from 1 to 86400.
------	--

Command Default

None

Command Modes

NetFlow exporter version 9 configuration (config-flow-exporter-version-9)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the NetFlow exporter sampler-table timer:

```
switch(config)# flow exporter Custom-Flow-Exporter-1
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# option sampler-table timeout 1200
switch(config-flow-exporter-version-9)#
```

This example shows how to remove the sampler-table timer configuration:

```
switch(config)#nooption sampler-table timeout
switch(config)#
```

Related Commands

Command	Description
show flow exporter	Displays information about NetFlow exporters.



P Commands

- [packet latency threshold](#), on page 136
- [periodic-inventory \(Call Home\)](#), on page 137
- [phone-contact \(Call Home\)](#), on page 138
- [poweroff module](#), on page 139
- [ptp announce](#), on page 140
- [ptp delay request minimum interval](#), on page 141
- [ptp domain](#), on page 142
- [ptp priority1](#), on page 143
- [ptp priority2](#), on page 144
- [ptp source](#), on page 145
- [ptp sync interval](#), on page 146
- [ptp vlan](#), on page 147

packet latency threshold

To configure the latency threshold value on an interface, use the packet latency threshold command. To remove the threshold value, use the no form of this command.

```
packet latency threshold threshold-value
no packet latency threshold
```

Syntax Description

threshold-value	Module number. The range is from 8 to 536870904 nano seconds.
-----------------	---

Command Default

None

Command Default

Interface configuration (config-if)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

You apply this command to egress interfaces where SPAN-on-Latency functionality is needed. When latency on the egress interface exceeds the configured threshold, packets are spanned on the interface configured as the destination port for the SPAN-on-Latency session. Only one SPAN-on-Latency session is supported at a time.

Examples

This example shows how to set the latency threshold value to 530000000 nano seconds:

```
switch(config)# interface ethernet 1/1
switch(config-if)# packet latency threshold 530000000
```

Related Commands

Command	Description
monitor session	Creates a SPAN or an ERSPAN session.

periodic-inventory (Call Home)

To configure the switch to periodically send a message with an inventory of all software services currently enabled and running on the device with hardware inventory information, use the `periodic-inventory` command. To disable the periodic messages, use the `no` form of this command.

```
periodic-inventory notification [interval time-period | timeofday time-of-day]
no periodic-inventory notification [interval time-period | timeofday time-of-day]
```

Syntax Description	notification	Enables sending periodic software inventory messages.
	interval time-period	(Optional) Specifies the time period for periodic inventory notification. The time period range is from 1 to 30 days, and the default is 7 days.
	timeofday time-of-day	(Optional) Specifies the time of day for periodic inventory notification. The time of day is in HH:MM format.

Command Default Interval: 7 days

Command Modes Callhome configuration mode

Command History	Release	Modification
		This command was introduced.

Usage Guidelines The switch generates two Call Home notifications: periodic configuration messages and periodic inventory messages.

Examples This example shows how to configure a periodic inventory notification to generate every 5 days:

```
switch(config-callhome)# periodic-inventory notification interval 5
switch(config-callhome)#
```

This example shows how to disable a periodic inventory notification for Call Home:

```
switch(config-callhome)# no periodic-inventory notification interval 5
switch(config-callhome)#
```

Related Commands	Command	Description
	copy running-config startup-config	Saves this configuration change.
	show callhome	Displays Call Home configuration information.
	show running-config callhome	Displays the running configuration information for Call Home.

phone-contact (Call Home)

To configure the phone number for the primary person responsible for the device, use the phone-contact command. To remove a phone contact, use the no form of this command.

```
phone-contact phone-no
no phone-contact
```

Syntax Description

phone-no	Phone number in international phone number format, such as +1-800-123-4567. The phone number can be a maximum of 17 alphanumeric characters and cannot contain spaces. Note You must use the + prefix before the number.
----------	--

Command Default

None

Command Modes

Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Examples

This example shows how to configure a phone number for the primary person responsible for the device:

```
switch(config-callhome) # phone-contact +1-800-123-4567
switch(config-callhome) #
```

Related Commands

Command	Description
copy running-config startup-config	Saves this configuration change.
show callhome	Displays a summary of the Call Home configuration.
streetaddress	Configures the street address for the primary person responsible for the switch.

poweroff module

To power off a module, use the poweroff module command. To return power to the module, use the no form of this command.

```
poweroff module module
no poweroff module module
```

Syntax Description	module	Module number. The range is from 1 to 18.
---------------------------	--------	---

Command Default	None
------------------------	------

Command Default	Global configuration (config)
------------------------	-------------------------------

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines	This command does not require a license.
-------------------------	--

Examples	This example shows how to power off module 2:
-----------------	---

```
switch# poweroff module 2
```

Related Commands	Command	Description
	show module	Displays information about modules.

ptp announce

To configure the interval between PTP announcement messages on an interface or the number of PTP intervals before a timeout occurs on an interface, use the `ptp announce` command. To disable this feature, use the `no` form of this command.

```
ptp announce interval log-seconds | timeout count
no ptp announce
```

Syntax Description

interval log-seconds	The number of log seconds between PTP announcement messages. The range is from 0 to 4 seconds.
timeout count	The number of PTP intervals before a timeout occurs on the interface. The range is from 2 to 10.

Command Default

The default interval is 1 log second.

The default timeout is 3 announce intervals.

Command Modes

Interfaces configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set the announcement interval on interface 5/1 to 1:

```
switch# configure terminal
switch(config) # interface ethernet
5/1
switch(config-if)# ptp announce interval 1
switch(config-if)
```

Related Commands

Command	Description
<code>feature ptp</code>	Enables or disables PTP on the device.
<code>ptp delay request minimum interval</code>	Configures the minimum interval allowed between PTP delay-request messages when the port is in the master state.
<code>ptp sync interval</code>	Configures the interval between PTP synchronization messages on an interface.
<code>ptp vlan</code>	Configures the VLAN for the interface where PTP is being enabled.
<code>show ptp brief</code>	Displays the PTP status.
<code>show ptp port interface ethernet</code>	Displays the status of the PTP port on the switch.

ptp delay request minimum interval

To configure the minimum interval allowed between PTP delay request messages when the port is in the master state, use the `ptp delay request minimum interval` command. To disable this feature, use the `no` form of this command.

```
ptp delay request minimum interval log-seconds
no ptp delay request minimum interval
```

Syntax Description	log-seconds	The number of log seconds between PTP delay request messages. The range is from -1 to 6 seconds.
---------------------------	-------------	--

Command Default 0 log seconds

Command Modes Interface configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set the minimum delay request interval to 3:

```
switch# configure terminal
switch(config) # interface ethernet 5/1
switch(config-if) # ptp delay request minimum interval 3
```

Related Commands	Command	Description
	feature ptp	Enables or disables PTP on the device.
	ptp announce	Configures the interval between PTP announce messages on an interface or the number of PTP intervals before a timeout occurs on an interface.
	ptp sync interval	Configures the interval between PTP synchronization messages on an interface.
	ptp vlan	Configures the VLAN for the interface where PTP is being enabled.
	show ptp brief	Displays the PTP status.
	show ptp port interface ethernet	Displays the status of the PTP port on the switch.

ptp domain

To configure the domain number to use for this clock, use the `ptp domain` command. PTP domains allow you choose multiple independent PTP clocking subdomains on a single network.

```
ptp domain number
no ptp domain number
```

Syntax Description

number	Configures the domain number to use for this clock. The range is from 0 to 128.
--------	---

Command Default

0

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure the domain number for use with a clock:

```
switch(config)# ptp domain 1
```

Related Commands

Command	Description
<code>feature ptp</code>	Enables or disables PTP on the device.
<code>ptp source</code>	Configures the source IP address for all PTP packets.
<code>ptp priority1</code>	Configures the priority 1 value to use when advertising this clock.
<code>ptp priority2</code>	Configures the priority 1 value to use when advertising this clock.
<code>show ptp brief</code>	Displays the PTP status.
<code>show ptp clock</code>	Displays the properties of the local clock.

ptp priority1

To configure the priority1 value to use when advertising this clock, use the ptp priority1 command.

```
ptp priority1 value
no ptp priority1 value
```

Syntax Description

value	The configured value overrides the default criteria (clock quality, clock class, etc.) for best master clock selection. Lower values take precedence. The range is from 0 to 255.
-------	---

Command Default

255 when advertising the clock

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set the priority1 value used to advertise this clock:

```
switch(config)# ptp priority1 10
```

Related Commands

Command	Description
feature ptp	Enables or disables PTP on the device.
ptp source	Configures the source IP address for all PTP packets.
ptp domain	Configures the domain number to use for this clock.
ptp priority2	Configures the priority2 value to use when advertising this clock.
show ptp brief	Displays the PTP status.
show ptp clock	Displays the properties of the local clock.

ptp priority2

To configure the priority2 value to use when advertising this clock, use the ptp priority2 command.

```
ptp priority2 value
no ptp priority2 value
```

Syntax Description

value	The configured value is used to decide between two devices that are otherwise equally matched in the default criteria. For example, you can use the priority2 value to give a specific switch priority over other identical switches. The range is from 0 to 255.
-------	---

Command Default

255 when advertising the clock

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set the priority2 value used to advertise this clock:

```
switch(config)# ptp priority2 20
```

Related Commands

Command	Description
feature ptp	Enables or disables PTP on the device.
ptp source	Configures the source IP address for all PTP packets.
ptp domain	Configures the domain number to use for this clock.
ptp priority1	Configures the priority1 value to use when advertising this clock.
show ptp brief	Displays the PTP status.
show ptp clock	Displays the properties of the local clock.

ptp source

To configure the source IP address for all PTP packets, use the `ptp source` command. To unconfigure the source IP address for all PTP packets, use the `no` form of this command.

```
ptp source ip-address [vrf vrf]
no ptp source ip-address [vrf vrf]
```

Syntax Description		
	ip-address	Specifies the source IP address for all PTP packets. The IP address can be in IPv4 or IPv6 format.
	vrf vrf	Specifies the VRF.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure the source IP address for all PTP packets:

```
switch(config)# ptp source 192.0.2.1
```

Related Commands	Command	Description
	feature ptp	Enables or disables PTP on the device.
	ptp domain	Configures the domain number to use for this clock.
	ptp priority1	Configures the priority 1 value to use when advertising this clock.
	ptp priority2	Configures the priority 1 value to use when advertising this clock.
	show ptp brief	Displays the PTP status.
	show ptp clock	Displays the properties of the local clock.

ptp sync interval

To configure the interval between PTP synchronization messages, use the `ptp sync interval` command. To disable this feature, use the `no` form of this command.

```
ptp sync interval log-seconds
no ptp sync interval
```

Syntax Description

log-seconds	The number of log seconds between PTP synchronization messages on an interface. The range is from -3 seconds to 1 second.
-------------	---

Command Default

None

Command Modes

Interface configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set the PTP synchronization interval to -3:

```
switch# configure terminal
switch(config) # interface ethernet
5/1
switch(config-if) # ptp sync interval -3
```

Related Commands

Command	Description
<code>feature ptp</code>	Enables or disables PTP on the device.
<code>ptp announce</code>	Configures the interval between PTP announce messages on an interface or the number of PTP intervals before a timeout occurs on an interface.
<code>ptp delay request minimum interval</code>	Configures the minimum interval allowed between PTP delay-request messages when the port is in the master state.
<code>ptp vlan</code>	Configures the VLAN for the interface where PTP is being enabled.
<code>show ptp brief</code>	Displays the PTP status.
<code>show ptp port interface ethernet</code>	Displays the status of the PTP port on the switch.

ptp vlan

To specify the VLAN for the interface where PTP is being enabled, use the `ptp vlan` command. To disable this feature, use the `no` form of this command.

```
ptp vlan vlan-id
no ptp vlan
```

Syntax Description

vlan-id	The VLAN ID for the interface where PTP is being enabled. The range is from 1 to 4094.
---------	--

Command Default

1

Command Modes

Interface configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

PTP can only be enabled on one VLAN on an interface.

Examples

This example shows how to specify VLAN 10 as the interface where PTP is being enabled:

```
switch# configure terminal
switch(config) # interface ethernet 5/1
switch(config-if) # ptp vlan 10
```

Related Commands

Command	Description
<code>feature ptp</code>	Enables or disables PTP on the device.
<code>ptp announce</code>	Configures the interval between PTP announce messages on an interface or the number of PTP intervals before a timeout occurs on an interface.
<code>ptp delay request minimum interval</code>	Configures the minimum interval allowed between PTP delay-request messages when the port is in the master state.
<code>ptp sync interval</code>	Configures the interval between PTP synchronization messages on an interface.
<code>show ptp brief</code>	Displays the PTP status.
<code>show ptp port interface ethernet</code>	Displays the status of the PTP port on the switch.



R Commands

- [rmon alarm](#), on page 150
- [rmon event](#), on page 152
- [rmon hcalarm](#), on page 153

rmon alarm

To configure Remote Monitoring (RMON) alarms on any integer-based Simple Network Management Protocol (SNMP) management information base (MIB) object, use the `rmon alarm` command. To remove an RMON alarm, use the `no` form of this command.

```
rmon alarm alarm-no MIB-obj sample-interval absolute|delta rising-threshold rising-threshold-value
event-index falling-threshold fall-threshold-value [event-index] [owner name] | falling-threshold
fall-threshold-value [event-index] [owner name]
no rmon alarm alarm-no MIB-obj sample-interval absolute|delta rising-threshold rising-threshold-value
event-index falling-threshold fall-threshold-value [event-index] [owner name] | falling-threshold
fall-threshold-value [event-index] [owner name]
```

Syntax Description

alarm-no	Alarm number. The range is from 1 to 65535.
MIB-obj	MIB object to monitor. The MIB object must be an existing SNMP MIB object in standard dot notation; for example, 1.3.6.1.2.1.2.2.1.17.83886080.
sample-interval	Sample interval at which the switch collects a sample value of the MIB object. The range is from 1 to 700000 seconds.
absolute	Specifies the sample type as absolute.
delta	Specifies the sample type as delta.
rising-threshold	Configures the rising threshold value at which the switch triggers a rising alarm or resets a falling alarm.
rising-threshold-value	Rising threshold value. The range is from -2147483648 to 2147483647.
event-index	Event or action that the switch takes when an alarm, rising or falling, triggers. The event index range is from 0 to 65535.
falling-threshold	Configures the falling threshold value at which the switch triggers a falling alarm or resets a rising alarm.
fall-threshold-value	Falling threshold value. The range is from -2147483648 to 2147483647. Note The falling threshold value must be less than the rising threshold.
owner name	(Optional) Specifies an owner for the alarm. The name can be any alphanumeric string.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

Before you use this command, you must have configured an SNMP user and enabled SNMP notifications using the `snmp-server user` and `snmp-server enable traps` command, respectively.

You can only configure an RMON alarm on an integer-based SNMP MIB object. The MIB object must be in standard dot notation. For example, 1.3.6.1.2.1.2.2.1.17 represents `ifOutOctets.17`.

Absolute samples take the current snapshot of the MIB object value. Delta samples take two consecutive samples and calculate the difference between them. For example, you can set a delta type rising alarm on an error counter MIB object. If the error counter delta exceeds this value, you can trigger an event that sends an SNMP notification and logs the rising alarm event. This rising alarm will not occur again until the delta sample for the error counter drops below the falling threshold.

You can associate a particular event to each RMON alarm. RMON supports the following event types:

- **SNMP notification**—Sends an SNMP `risingAlarm` or `fallingAlarm` notification when the associated alarm triggers.
- **Log**—Adds an entry in the RMON log table when the associated alarm triggers.
- **Both**—Sends an SNMP notification and adds an entry in the RMON log table when the associated alarm triggers.

You can specify a different event for a falling alarm and a rising alarm.

Examples

This example shows how to configure an RMON alarm:

```
switch(config)# rmon alarm 1 1.3.6.1.2.1.2.2.1.17.83886080 5 delta rising-threshold 5 1
falling-threshold 0 owner test

switch(config)#
```

Related Commands

Command	Description
<code>copy running-config startup-config</code>	Saves the running configuration to the startup configuration file.
<code>snmp-server enable traps</code>	Enables SNMP notifications on the switch.
<code>snmp-server user</code>	Configures an SNMP user.
<code>show rmon</code>	Displays information about RMON alarms and events.

rmon event

To configure Remote Monitoring (RMON) events to associate with RMON alarms, use the `rmon event` command. To remove an RMON event, use the `no` form of this command.

```
rmon event event-index [description string] [log] [trap] [owner name]
no rmon event event-index [description string] [log] [trap] [owner name]
```

Syntax Description

event-index	Event or action that the switch takes when an alarm, rising or falling, triggers. The event index range is from 0 to 65535.
description string	(Optional) Specifies a description for the event. The description can be any alphanumeric string.
log	(Optional) Specifies that an RMON log be generated when the event occurs.
trap	(Optional) Specifies that an SNMP trap be generated when the event occurs.
owner name	(Optional) Specifies an owner for the alarm. The name can be any alphanumeric string.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

Before you use this command, you must have configured an SNMP user and enabled SNMP notifications using the `snmp-server user` and `snmp-server enable traps` command, respectively.

You can reuse the same event with multiple RMON alarms.

Examples

This example shows how to configure an RMON event:

```
switch(config)# rmon event 1 owner test
switch(config)#
```

Related Commands

Command	Description
<code>copy running-config startup-config</code>	Saves the running configuration to the startup configuration file.
<code>snmp-server enable traps</code>	Enables SNMP notifications on the switch.
<code>snmp-server user</code>	Configures an SNMP user.
<code>show rmon</code>	Displays information about RMON alarms and events.

rmon hcalarm

To configure a high-capacity Remote Monitoring (RMON) alarm, use the `rmon hcalarm` command. To remove a high-capacity RMON alarm, use the `no` form of this command.

```
rmon hcalarm alarm-no MIB-obj sample-interval absolute|delta startupalarm startup-alarm-type
rising-threshold rising-threshold-value event-index falling-threshold fall-threshold-value [event-index]
[owner name]
```

```
no rmon hcalarm alarm-no MIB-obj sample-interval absolute|delta startupalarm startup-alarm-type
rising-threshold rising-threshold-value event-index falling-threshold fall-threshold-value [event-index]
[owner name]
```

Syntax Description

alarm-no	Alarm number. The range is from 1 to 65535.
MIB-obj	MIB object to monitor. The MIB object must be an existing SNMP MIB object in standard dot notation; for example, 1.3.6.1.2.1.2.2.1.17.83886080.
sample-interval	Sample interval at which the switch collects a sample value of the MIB object. The range is from 1 to 700000 seconds.
absolute	Specifies the sample type as absolute.
delta	Specifies the sample type as delta.
startupalarm	Configures the startup alarm type.
startup-alarm-type	Startup alarm type. The range is from 1 to 3, where 1 is rising, 2 is falling, and 3 is rising or falling.
rising-threshold	Configures the rising threshold value at which the switch triggers a rising alarm or resets a falling alarm.
rising-threshold-value	Rising threshold value. The range is from 0 to 18446744073709551615.
event-index	Event or action that the switch takes when an alarm, rising or falling, triggers. The event index range is from 0 to 65535.
falling-threshold	Configures the falling threshold value at which the switch triggers a falling alarm or resets a rising alarm.
fall-threshold-value	Falling threshold value. The range is from 0 to 18446744073709551615. Note The falling threshold value must be less than the rising threshold.
owner name	(Optional) Specifies an owner for the alarm. The name can be any alphanumeric string.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

Before you use this command, you must have configured an SNMP user and enabled SNMP notifications using the `snmp-server user` and `snmp-server enable traps` command, respectively.

You can configure a high-capacity RMON alarm on any integer-based SNMP MIB object. The MIB object must be in standard dot notation. For example, 1.3.6.1.2.1.2.2.1.17 represents `ifOutOctets.17`.

Absolute samples take the current snapshot of the MIB object value. Delta samples take two consecutive samples and calculate the difference between them. For example, you can set a delta type rising alarm on an error counter MIB object. If the error counter delta exceeds this value, you can trigger an event that sends an SNMP notification and logs the rising alarm event. This rising alarm will not occur again until the delta sample for the error counter drops below the falling threshold.

You can associate a particular event to each high-capacity RMON alarm. RMON supports the following event types:

- **SNMP notification**—Sends an SNMP `risingAlarm` or `fallingAlarm` notification when the associated high-capacity alarm triggers.
- **Log**—Adds an entry in the RMON log table when the associated high-capacity alarm triggers.
- **Both**—Sends an SNMP notification and adds an entry in the RMON log table when the associated high-capacity alarm triggers.

You can specify a different event for a falling high-capacity alarm and a rising high-capacity alarm.

Examples

This example shows how to configure an RMON high-capacity alarm:

```
switch(config)# rmon hcalarm 3 1.3.6.1.2.1.2.2.1.17.83886080 5 delta startupalarm 3
rising-threshold 5 1 falling-threshold 3 3 owner test

switch(config)#
```

Related Commands

Command	Description
<code>copy running-config startup-config</code>	Saves the running configuration to the startup configuration file.
<code>snmp-server enable traps</code>	Enables SNMP notifications on the switch.
<code>snmp-server user</code>	Configures an SNMP user.
<code>show rmon</code>	Displays information about RMON alarms and events.



S Commands

- [sampler](#), on page 157
- [snapshot create](#), on page 159
- [snapshot delete](#), on page 160
- [snapshot section](#), on page 161
- [snmp trap link-status](#), on page 163
- [snmp-server community](#), on page 165
- [snmp-server aaa-user cache-timeout](#), on page 166
- [snmp-server contact](#), on page 167
- [snmp-server context](#), on page 168
- [snmp-server enable traps](#), on page 169
- [snmp-server enable traps link](#), on page 172
- [snmp-server globalEnforcePriv](#), on page 174
- [snmp-server host](#), on page 175
- [snmp-server location](#), on page 177
- [snmp-server mib community-map](#), on page 178
- [snmp-server tcp-session](#), on page 179
- [snmp-server user](#), on page 180
- [source](#), on page 182
- [source interface \(SPAN, ERSPAN\)](#), on page 183
- [source ip](#), on page 186
- [switchport monitor rate-limit](#), on page 187
- [switch-profile](#), on page 188
- [system fex-group shutdown](#), on page 191
- [system mode maintenance](#), on page 192
- [system mode maintenance always-use-custom-profile](#), on page 194
- [system mode maintenance dont-generate-profile](#), on page 195
- [system mode maintenance on-reload reset-reason](#), on page 197
- [system mode maintenance shutdown](#), on page 199
- [system mode maintenance timeout](#), on page 201
- [system soft-reload enable](#), on page 202
- [shut \(SPAN, ERSPAN\)](#), on page 204
- [site-id \(Call Home\)](#), on page 206
- [sleep instance](#), on page 207

- [soft-reload](#), on page 209

sampler

To define a sampler and enter the sampler configuration mode, use the `sampler` command. To remove the sampler definition, use the `no` form of this command.

```
sampler name
no sampler name
```

Syntax Description

name	Name of the sampler. The name can have a maximum of 63 alphanumeric characters.
-------------	---

Command Default

No samplers are defined.

Command Modes

Global configuration mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

NetFlow sampling means that M out of N packets are sampled. When a packet is sampled and there is a NetFlow cache miss, a NetFlow cache entry is created for this flow. The first packet timestamp is updated and the statistics for the first packet are initialized (for example, the bytes are set to the number of bytes in the packet and the packet count is set to one). If there is a NetFlow cache hit when the packet is sampled, the cache for this flow is updated, which includes adding the number of bytes in the packet to the byte counter and incrementing the packet count by one.

Once you enter the `sampler name` command, you enter the sampler configuration mode, and the prompt changes to the following:

```
switch(config-flow-sampler)#
```

Within the sampler configuration mode, the following keywords and arguments are available to configure the flow monitor:

- `description description`—Provides a description for this sampler; you can add a maximum of 63 characters.
- `exit`—Exits from the current configuration mode.
- `mode sample-num out-of packets`—Configures the sampler mode. The valid values are as follows:
 - `sample-num`—Number of samples per sampling. The range is from 1 to 64.
 - `out-of`—Specifies the samples per packet ratio.
 - `packets`—Number of packets in each sampling. The range is from 1 to 65536, and must be a power of 2.
- `no`—Negates a command or sets its defaults.

This command does not require a license.

Examples

This example shows how to define a sampler and enter the sampler configuration mode:

```
switch(config)# sampler testsampler
switch(config-flow-sampler)#
```

This example shows how to configure the sampler mode:

```
switch(config)# sampler testsampler  
switch(config-flow-sampler)# mode 24 out-of 1024
```

This example shows how to remove a sampler definition:

```
switch(config)# no sampler testsampler  
switch(config-flow)#
```

Related Commands

Command	Description
flow exporter	Creates a flow exporter.
flow monitor	Creates a flow monitor.
flow record	Creates a flow record.

snapshot create

To create a snapshot, use the snapshot create command.

```
snapshot create name description
```

Syntax Description

name	The name variable can be 64 characters in length.
description	The description variable can be 256 characters in length.

Command Default

None.

Command History

Release	Modification
7.1.0	This command was introduced.

Examples

This example shows how to create a snapshot:

```
switch# snapshot create snap1 For documentation purposes.
Executing show interface... Done
Executing show bgp sessions vrf all... Done
Executing show ip eigrp topology summary... Done
Executing show ipv6 eigrp topology summary... Done
Executing show vpc... Done
Executing show ip ospf vrf all... Done
Feature 'ospfv3' not enabled, skipping...
Executing show isis vrf all... Done
Snapshot 'snap1' created
switch#
```

Related Commands

Command	Description
show snapshots before-maintenance-mode description	Displays snapshots present on the switch.
snapshot delete	Deletes the snapshot.
show snapshot compare	Compares snapshots and showing the summary and details of each feature.

snapshot delete

To delete a single snapshot or to delete all the snapshots in a system, use the snapshot delete command.

```
snapshot delete allsnapshot-name
```

Syntax Description

all	Deletes all the snapshots in the system.
snapshot-name	Deletes the specified snapshot.

Command Default

None

Command History

Release	Modification
7.3(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to delete all the snapshots in a system:

```
switch# snapshot delete all
```

This example shows how to delete a specific snapshot:

```
switch # snapshot delete snapshot1
```

Related Commands

Command	Description
show snapshots	Displays snapshots present on the switch.
snapshot create	Generates a snapshot.
snapshot section	Adds or deletes a snapshot section.

snapshot section

To add or delete a snapshot section, use the snapshot section command.

```
snapshot section add section "show-command" row-id element-key1 [element-key2] | delete section
```

Syntax	Description
add	Adds the specified snapshot section to the snapshot.
section	Names the snapshot section that is added to the snapshot to display the show command output.
"show command"	Specifies the show command. The output of this show command is displayed in the new snapshot section created. This show command has to be specified within quotation marks ("show").
row-id	The row-id argument specifies the tag of each row entry of the show command's XML output.
element-key1	Specifies the tag used to distinguish among row entries in the show command snapshot section output.
element-key2	(Optional) Specifies another tag used to distinguish among row entries in the show command snapshot section output.
delete	Deletes the specified snapshot section from the snapshot.

Command Default None.

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to add a snapshot section that displays the output of the show ip route detail vrf all command to the snapshot:

```
switch# snapshot section add v4route show "show ip route detail vrf all" ROW_prefix ipprefix
```

This example shows how to delete a snapshot section from the snapshot:

```
switch# snapshot section delete v4route
```

Related Commands	Command	Description
	show snapshots	Displays snapshots present on the switch.

Command	Description
snapshot create	Generates a snapshot.
snapshot delete	Deletes snapshots.

snmp trap link-status

To enable Simple Network Management Protocol (SNMP) link trap generation on an interface, use the `snmp trap link-status` command. To disable SNMP link traps, use the `no` form of this command.

```
snmp trap link-status
no snmp trap link-status
```

Syntax Description This command has no arguments or keywords.

Command Default Enabled

Command Modes Interface configuration mode
Virtual Ethernet interface configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines By default, SNMP link traps are sent when a Layer 2 interface goes up or down. You can disable SNMP link trap notifications on an individual interface. You can use these limit notifications on a flapping interface (an interface that transitions between up and down repeatedly).

You can use this command on the following interfaces:

- Layer 2 interface
- Layer 3 interface



Note Use the `no switchport` command to configure an interface as a Layer 3 interface.

- Virtual Ethernet interface

Examples

This example shows how to disable SNMP link-state traps for a specific Layer 2 interface:

```
switch(config)# interface ethernet 1/1
switch(config-if)# no snmp trap link-status
switch(config-if)#
```

This example shows how to enable SNMP link-state traps for a specific Layer 3 interface:

```
switch(config)# interface ethernet 1/5
switch(config-if)# no switchport
switch(config-if)# snmp trap link-status
switch(config-if)#
```

This example shows how to enable SNMP link-state traps for a specific Layer 2 interface:

```
switch(config)# interface ethernet 1/1
switch(config-if)# snmp trap link-status
switch(config-if)#
```

This example shows how to enable SNMP link-state traps for a specific virtual Ethernet interface:

```
switch(config)# interface vethernet 1
switch(config-if)# snmp trap link-status
switch(config-if)#
```

Related Commands

Command	Description
interface vethernet	Configures a virtual Ethernet interface.
no switchport	Configures an interface as a Layer 3 routed interface.
show snmp trap	Displays the SNMP notifications, enabled or disabled.

snmp-server community

To create Simple Network Management Protocol (SNMP) communities for SNMPv1 or SNMPv2c, use the `snmp-server community` command. To revert to the defaults, use the `no` form of this command.

```
snmp-server community com-name [group grp-name | ro | rw | use-acl acl-name]
no snmp-server community com-name [group grp-name | ro | rw | use-acl acl-name]
```

Syntax Description	com-name	SNMP community string. The name can be any alphanumeric string up to 32 characters.
	group grp-name	(Optional) Specifies the group to which the community belongs. The name can be a maximum of 32 characters.
	ro	(Optional) Specifies read-only access with this community string.
	rw	(Optional) Specifies read-write access with this community string.
	use-acl acl-name	(Optional) Specifies the access control list (ACL) to filter SNMP requests. The name can be a maximum of 32 characters.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines You can assign an access list (ACL) to a community to filter incoming SNMP requests. If the assigned ACL allows the incoming request packet, SNMP processes the request. If the ACL denies the request, SNMP drops the request and sends a system message.

See the Security Configuration Guide for your platform for more information on creating ACLs. The ACL applies to both IPv4 and IPv6 over UDP and TCP. After creating the ACL, assign the ACL to the SNMP community.

Examples

This example shows how to create an SNMP community string and assign an ACL to the community to filter SNMP requests:

```
switch(config)# snmp-server community public use-acl my_acl_for_public
switch(config)#
```

Related Commands	Command	Description
	show snmp community	Displays the SNMP community strings.

snmp-server aaa-user cache-timeout

To configure the Simple Network Management Protocol (SNMP) time-out value for synchronized AAA users, use the `snmp-server aaa-user cache-timeout` command. To revert to the default settings, use the `no` form of this command.

```
snmp-server aaa-user cache-timeout seconds
no snmp-server aaa-user cache-timeout seconds
```

Syntax Description

seconds	Timeout value, in seconds. The range is from 1 to 86400. The default value is 3600 seconds.
---------	---

Command Default

3600 seconds.

Command Modes

Global configuration mode

Command History

Release	Modification
7.3(2)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the AAA user synchronization timeout value:

```
switch(config)# snmp-server aaa-user cache-timeout 6000
```

Related Commands

Command	Description
show snmp	Displays information about SNMP.

snmp-server contact

To configure the Simple Network Management Protocol (SNMP) contact (sysContact) information, use the snmp-server contact command. To remove the contact information, use the no form of this command.

```
snmp-server contact [text]
no snmp-server contact [text]
```

Syntax Description

text	(Optional) String that describes the system contact information. The text can be any alphanumeric string up to 32 characters and cannot contain spaces.
------	---

Command Default

No system contact (sysContact) string is set.

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set an SNMP contact:

```
switch(config)# snmp-server contact DialSystemOperatorAtBeeper#1235
switch(config)#
```

This example shows how to remove an SNMP contact:

```
switch(config)# no snmp-server contact DialSystemOperatorAtBeeper#1235
switch(config)#
```

Related Commands

Command	Description
show snmp	Displays information about SNMP.
snmp-server location	Sets the system location string.

snmp-server context

To configure the Simple Network Management Protocol (SNMP) context to logical network entity mapping, use the `snmp-server context` command. To remove the context, use the `no` form of this command.

```
snmp-server context context-name [instance instance-name] [vrf vrf-name | default | management]
[topology topology-name]
no snmp-server context context-name [instance instance-name] [vrf vrf-name | default | management]
[topology topology-name]
```

Syntax Description

context-name	SNMP context. The name can be any alphanumeric string up to 32 characters.
instance instance-name	(Optional) Specifies a protocol instance. The name can be any alphanumeric string up to 32 characters.
vrf vrf-name	(Optional) Specifies the virtual routing and forwarding (VRF) instance. The name is case sensitive, and can be a maximum of 32 alphanumeric characters.
default	Specifies the default VRF.
management	Specifies the management VRF.
topology topology-name	(Optional) Specifies the topology. The name can be any alphanumeric string up to 32 characters.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Use the `snmp-server context` command to map between SNMP contexts and logical network entities, such as protocol instances or VRFs.

Examples

This example shows how to map the `public1` context to the default VRF:

```
switch(config)# snmp-server context public1 vrf default
switch(config)#
```

Related Commands

Command	Description
<code>show snmp</code>	Displays the SNMP status.
<code>show snmp context</code>	Displays information about SNMP contexts.

snmp-server enable traps

To enable the Simple Network Management Protocol (SNMP) notifications, use the `snmp-server enable traps` command. To disable SNMP notifications, use the `no` form of this command.

```
snmp-server enable traps [aaa [server-state-change] | callhome [event-notify | smtp-send-fail] | entity
entity_fan_status_change | entity_mib_change | entity_module_inserted | entity_module_removed |
entity_module_status_change | entity_power_out_change | entity_power_status_change |
entity_unrecognised_module | fcdomain | fcns | fcs | fctrace | fspf | license [notify-license-expiry |
notify-license-expiry-warning | notify-licensefile-missing | notify-no-license-for-feature] | link | rf
[redundancy_framework] | rmon [fallingAlarm | hcFallingAlarm | hcRisingAlarm | risingAlarm] | rscn | snmp
[authentication] | vsan | vtp | zone [default-zone-behavior-change | merge-failure | merge-success |
request-reject1 | unsupp-mem]]
no snmp-server enable traps [aaa [server-state-change] | callhome [event-notify | smtp-send-fail] | entity
entity_fan_status_change | entity_mib_change | entity_module_inserted | entity_module_removed |
entity_module_status_change | entity_power_out_change | entity_power_status_change |
entity_unrecognised_module | fcdomain | fcns | fcs | fctrace | fspf | license [notify-license-expiry |
notify-license-expiry-warning | notify-licensefile-missing | notify-no-license-for-feature] | link | rf
[redundancy_framework] | rmon [fallingAlarm | hcFallingAlarm | hcRisingAlarm | risingAlarm] | rscn | snmp
[authentication] | vsan | vtp | zone [default-zone-behavior-change | merge-failure | merge-success |
request-reject1 | unsupp-mem]]
```

Syntax Description

aaa	(Optional) Enables notifications for a AAA server state change.
server-state-change	(Optional) Specifies the AAA server state change.
callhome	(Optional) Enables Cisco Call Home notifications.
event-notify	(Optional) Specifies the Cisco Call Home external event notification.
smtp-send-fail	(Optional) Specifies the SMTP message send fail notification.
entity	(Optional) Enables notifications for a change in the module status, fan status, or power status.
entity_fan_status_change	(Optional) Specifies the entity fan status change.
entity_mib_change	(Optional) Specifies the entity MIB change.
entity_module_inserted	(Optional) Specifies the entity module inserted.
entity_module_removed	(Optional) Specifies the entity module removed.
entity_module_status_change	(Optional) Specifies the entity module status change.
entity_power_out_change	(Optional) Specifies the entity power out change.
entity_power_status_change	(Optional) Specifies the entity power status change.
entity_unrecognised_module	(Optional) Specifies the entity unrecognized module.
fcdomain	(Optional) Enables notifications for the Fibre Channel domain.

fens	(Optional) Enables notifications for the name server.
fcs	(Optional) Enables notifications for the fabric configuration server.
fctrace	(Optional) Enables notifications for the route to an N port.
fspf	(Optional) Enables notifications for the Fabric Shortest Path First (FSPF).
license	(Optional) Enables notifications for the license manager.
notify-license-expiry	(Optional) Specifies the license expiry notification.
notify-license-expiry-warning	(Optional) Specifies the license expiry warning notification.
notify-licensefile-missing	(Optional) Specifies the license file missing notification.
notify-no-license-for-feature	(Optional) Specifies that a notification is sent when no license needs to be installed for the feature.
link	(Optional) Enables notifications for uplink and downlink interfaces.
rf	(Optional) Enables notifications for the redundancy framework.
redundancy_framework	(Optional) Specifies the Redundancy_Framework (RF) supervisor switchover MIB.
rmon	(Optional) Enables notifications for rising, falling, and high-capacity alarms.
fallingAlarm	(Optional) Specifies the RMON falling alarm.
hcFallingAlarm	(Optional) Specifies the high-capacity RMON falling alarm.
hcRisingAlarm	(Optional) Specifies the high-capacity RMON rising alarm.
risingAlarm	(Optional) Specifies the RMON rising alarm.
rscn	(Optional) Enables RSCN notifications.
snmp	(Optional) Enables SNMP authentication notifications.
authentication	(Optional) Specifies the SNMP authentication trap.
vsan	(Optional) Enables notifications for VSANs.
vtp	(Optional) Enables notifications for a VLAN Trunking Protocol (VTP) domain.
zone	(Optional) Enables zone notifications.
default-zone-behavior-change	(Optional) Specifies the default zone behavior change notification.
merge-failure	(Optional) Specifies the merge failure notification.
merge-success	(Optional) Specifies the merge success notification.
request-reject1	(Optional) Specifies the request reject notification.

unsupp-mem	(Optional) Specifies the unsupported member notification.
------------	---

Command Default All notifications

Command Modes Global configuration mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines The snmp-server enable traps command enables both traps and informs, depending on the configured notification host receivers.

Examples

This example shows how to enable SNMP notifications for the server state change:

```
switch(config)# snmp-server enable traps aaa
switch(config)#
```

This example shows how to disable all SNMP notifications:

```
switch(config)# no snmp-server enable traps
switch(config)#
```

Related Commands	Command	Description
	snmp-server enable traps link	Enables the Simple Network Management Protocol (SNMP) notifications on link traps.
	show snmp trap	Displays the SNMP notifications enabled or disabled.

snmp-server enable traps link

To enable the Simple Network Management Protocol (SNMP) notifications on link traps, use the `snmp-server enable traps link` command. To disable SNMP notifications on link traps, use the `no` form of this command.

```
snmp-server enable traps link [notification-type]
no snmp-server enable traps link [notification-type]
```

Syntax Description

notification-type	<p>(Optional) Type of notification to enable. If no type is specified, all notifications available on your device are sent. The notification type can be one of the following keywords:</p> <ul style="list-style-type: none"> • <code>IETF-extended-linkDown</code>—Enables the Internet Engineering Task Force (IETF) extended link state down notification. • <code>IETF-extended-linkUp</code>—Enables the IETF extended link state up notification. • <code>cisco-extended-linkDown</code>—Enables the Cisco extended link state down notification. • <code>cisco-extended-linkUp</code>—Enables the Cisco extended link state up notification. • <code>connUnitPortStatusChange</code>—Enables the overall status of the connectivity unit Notification. • <code>delayed-link-state-change</code>—Enables the delayed link state change. • <code>fcTrunkIfDownNotify</code>—Enables the Fibre Channel Fabric Element (FCFE) link state down notification. • <code>fcTrunkIfUpNotify</code>—Enables the FCFE link state up notification. • <code>fcot-inserted</code>—Specifies that the Fibre Channel optical transmitter (FCOT) hardware has been inserted. • <code>fcot-removed</code>—Specifies that the FCOT has been removed. • <code>linkDown</code>—Enables the IETF Link state down notification. • <code>linkUp</code>—Enables the IETF Link state up notification.
-------------------	--

Command Default

Disabled

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This command is disabled by default. Most notification types are disabled.

If you enter this command with no notification-type arguments, the default is to enable all notification types controlled by this command

Examples

This example shows how to enable the SNMP link trap notification on the switch:

```
switch(config)# snmp-server enable tra
ps link
switch(config)#
```

This example shows how to disable the SNMP link trap notification on the switch:

```
switch(config)# no snmp-server enable tra  
ps link  
switch(config)#
```

Related Commands

Command	Description
show snmp trap	Displays the SNMP notifications enabled or disabled.

snmp-server globalEnforcePriv

To configure Simple Network Management Protocol (SNMP) message encryption for all users, use the `snmp-server globalEnforcePriv` command. To remove the encryption, use the no form of this command.

```
snmp-server globalEnforcePriv
no snmp-server globalEnforcePriv
```

Syntax Description This command has no arguments or keywords.

Command Default The SNMP agent accepts SNMPv3 messages without authentication and encryption.

Command Modes Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure SNMP message encryption for all users:

```
switch(config)# snmp-server globalEnforcePriv
switch(config)#
```

This example shows how to remove SNMP message encryption for all users:

```
switch(config)# no snmp-server globalEnforcePriv
switch(config)#
```

Related Commands

Command	Description
<code>snmp-server user</code>	Configures a new user to an SNMP group.
<code>show snmp sessions</code>	Displays the current SNMP sessions.

snmp-server host

To specify the recipient of a Simple Network Management Protocol (SNMP) notification operation, use the `snmp-server host` command. To remove the specified host, use the `no` form of this command.

```
snmp-server host host-address community-string | filter-vrf vrf-name | default | management | informs |
traps community-string | version 1 | 2c | 3 auth | noauth | priv community-string [udp-port port] | version
1 | 2c | 3 auth | noauth | priv community-string [udp-port port]
```

```
no snmp-server host host-address community-string | filter-vrf vrf-name | default | management | informs
| traps community-string | version 1 | 2c | 3 auth | noauth | priv community-string [udp-port port] | version
1 | 2c | 3 auth | noauth | priv community-string [udp-port port]
```

Syntax Description

host-address	IPv4 or IPv6 address or DNS name of the SNMP notification host.
community-string	String sent with the notification operation. The string can be a maximum of 32 alphanumeric characters. We recommend that you define this string using the <code>snmp-server community</code> command prior to using the <code>snmp-server host</code> command.
filter-vrf vrf-name	Specifies the virtual routing and forwarding (VRF) instance. The name is case sensitive and can be a maximum of 32 alphanumeric characters.
default	Specifies the default VRF.
management	Specifies the management VRF.
informs	Sends SNMP informs to this host.
traps	Sends SNMP traps to this host.
version	Specifies the version of the SNMP used to send the traps. Version 3 is the most secure model, because it allows packet encryption with the <code>priv</code> keyword. If you use the <code>version</code> keyword, one of the following must be specified: <ul style="list-style-type: none"> • 1—SNMPv1. • 2c—SNMPv2C. • 3—SNMPv3. The following three optional keywords can follow the <code>version 3</code> keyword: <ul style="list-style-type: none"> • <code>auth</code>—Enables Message Digest 5 (MD5) and Secure Hash Algorithm (SHA) packet authentication • <code>noauth</code> (Default)—The <code>noAuthNoPriv</code> security level. This is the default if the <code>auth</code>, <code>noauth</code>, or <code>priv</code> keyword is not specified. • <code>priv</code>—Enables Data Encryption Standard (DES) packet encryption (also called “privacy”)
udp-port port	(Optional) Specifies the UDP port of the host to use. The port range is from 0 to 65535.

Command Default

Disabled

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines SNMP notifications can be sent as traps or inform requests. Traps are unreliable because the receiver does not send acknowledgments when it receives traps. The sender cannot determine if the traps were received. However, an SNMP entity that receives an inform request acknowledges the message with an SNMP response PDU. If the sender never receives the response, the inform request can be sent again. Therefore, informs are more likely to reach their intended destination.

Examples This example shows how to send the SNMP traps to the host specified by the IPv4 address 192.168.0.10. The community string is defined as my_acl_for_public.:

```
switch(config)# snmp-server community public use-acl my_acl_for_public

switch(config)# snmp-server host 192.168.0.10
my_acl_for_public

switch(config)#
```

This example shows how to send all inform requests to the host myhost.cisco.com using the community string my_acl_for_public:

```
switch(config)# snmp-server enable traps

switch(config)# snmp-server host myhost.cisco.com informs version 2c my_acl_for_public

switch(config)#
```

Related Commands	Command	Description
	show snmp host	Displays information about the SNMP host.

snmp-server location

To set the Simple Network Management Protocol (SNMP) system location string, use the `snmp-server location` command. To remove the location string, use the `no` form of this command.

```
snmp-server location [text]
no snmp-server location [text]
```

Syntax Description

text	(Optional) String that describes the system location information.
------	---

Command Default

No system location string is set.

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to set a system location string:

```
switch(config)# snmp-server location Building 3/Room 21
switch(config)#
```

This example shows how to remove the system location string:

```
switch(config)# no snmp-server location Building 3/Room 21
switch(config)#
```

Related Commands

Command	Description
snmp-server contact	Sets the SNMP system contact (sysContact) string.

snmp-server mib community-map

To configure a Simple Network Management Protocol (SNMP) context to map to a logical network entity, such as a protocol instance or VRF, use the `snmp-server mib community-map` command. To remove the mapping, use the `no` form of this command.

```
snmp-server mib community-map community-string context context-name
no snmp-server mib community-map community-string context context-name
```

Syntax Description

community-string	String sent with the notification operation. The string can be a maximum of 32 alphanumeric characters. We recommend that you define this string using the <code>snmp-server community</code> command prior to using the <code>snmp-server mib community-map</code> command.
context	Specifies the SNMP context to be mapped to the logical network entity.
context-name	SNMP context. The name can be any alphanumeric string up to 32 characters.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to map an SNMPv2c community named `my_acl_for_public` to an SNMP context `public1`:

```
switch(config)# snmp-server mib community-map my_acl_for_public context public1
switch(config)#
```

This example shows how to remove the mapping of an SNMPv2c community to an SNMP context:

```
switch(config)# no snmp-server mib community-map my_acl_for_public context public1
switch(config)#
```

Related Commands

Command	Description
<code>snmp-server community</code>	Configures an SNMP community.
<code>snmp-server context</code>	Configures an SNMP context.
<code>show snmp</code>	Displays the SNMP status.

snmp-server tcp-session

To enable a one-time authentication for Simple Network Management Protocol (SNMP) over a TCP session, use the `snmp-server tcp-session` command. To disable the one-time authentication, use the `no` form of this command.

```
snmp-server tcp-session [auth]
no snmp-server tcp-session [auth]
```

Syntax Description

<code>auth</code>	(Optional) Specifies that one-time authentication for SNMP be enabled over the TCP session.
-------------------	---

Command Default

Disabled

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to enable one-time authentication for SNMP over a TCP session:

```
switch(config)# snmp-server tcp-session auth
switch(config)#
```

This example shows how to disable one-time authentication for SNMP over a TCP session:

```
switch(config)# no snmp-server tcp-session auth
switch(config)#
```

Related Commands

Command	Description
<code>show snmp</code>	Displays the SNMP status.

snmp-server user

To configure a new user to a Simple Network Management Protocol (SNMP) group, use the `snmp-server user` command. To remove a user from an SNMP group, use the `no` form of this command.

```
snmp-server user username [groupname] [auth md5 | sha auth-password [engineID engine-ID |
localizedkey | priv priv-password | aes-128]]
no snmp-server user
```

Syntax Description

username	Name of the user on the host that connects to the agent. The name can be a maximum of 32 alphanumeric characters.
groupname	(Optional) Name of the group to which the user is associated. The name can be a maximum of 32 alphanumeric characters.
auth	(Optional) Specifies that an authentication level setting will be initiated for the session.
md5	(Optional) Specifies that the HMAC-MD5-96 authentication level be used for the session.
sha	(Optional) Specifies that the HMAC-SHA-96 authentication level be used for the session.
auth-password	(Optional) Authentication password for the user that enables the agent to receive packets from the host. The password can be a maximum of 130 characters.
engineID engine-ID	(Optional) Specifies the SNMP engine ID.
localizedkey	(Optional) Specifies whether the passwords are in localized key format.
priv	(Optional) The option that initiates a privacy authentication level setting session.
priv-password	(Optional) Privacy password for the user that enables the host to encrypt the content of the message that it sends to the agent. The password can be a maximum of 130 characters.
aes-128	(Optional) Specifies that a 128-bit AES algorithm for privacy be used for the session.

Command Default

None

Command Modes

Global configuration mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to configure an SNMP user named `authuser` with authentication and privacy parameters:

```
switch(config)# snmp-server user authuser publicsecurity auth sha shapwd priv aes-128
```

```
switch(config)#
```

This example shows how to delete an SNMP user:

```
switch(config)# no snmp-server user authuser  
switch(config)#
```

Related Commands

Command	Description
show snmp user	Displays information about one or more SNMP users.

source

To configure the NetFlow exporter interface to use to reach the NetFlow collector for the configured destination, use the source command. To remove the source, use the no form of this command.

```
source if-type if-number
no source [if-type if-number]
```

Syntax Description

if-type	Interface type. For more information, use the question mark (?) online help function.
if-number	Interface or subinterface number. For more information about the numbering syntax for your networking device, use the question mark (?) online help function.

Command Default

None

Command Modes

NetFlow exporter configuration (config-flow-exporter)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the NetFlow exporter source interface:

```
switch(config)#
flow exporter Netflow-Exporter-1
switch(config-flow-exporter)# source Ethernet3/11
switch(config-flow-exporter)#
```

This example shows how to remove the NetFlow exporter source interface configuration:

```
switch(config-flow-exporter)# no
source Ethernet3/11
switch(config-flow-exporter)#
```

Related Commands

Command	Description
show flow exporter	Displays information about NetFlow exporters.

source interface (SPAN, ERSPAN)

To add an Ethernet Switched Port Analyzer (SPAN) or an Encapsulated Remote Switched Port Analyzer (ERSPAN) source port, use the source command. To remove the source SPAN or ERSPAN port, use the no form of this command.

```
source interface ethernet slot \ [QSFP-module/ port / port | port-channel channel-num | vethernet
veth-num [both | rx | tx] | vlan vlan-num | vsan vsan-num
no source interface ethernet slot \ [QSFP-module/ port / port | port-channel channel-num | vethernet
veth-num | vlan vlan-num | vsan vsan-num
```

Syntax Description

interface	Specifies the interface type to use as the source SPAN port.
ethernet slot/[QSFP-module/]port	Specifies the Ethernet interface to use as the source SPAN port. The slot number is from 1 to 255. The QSFP-module number is from 1 to 199. The port number is from 1 to 128.
port-channel channel-num	Specifies the EtherChannel interface to use as the source SPAN port. The EtherChannel number is from 1 to 4096.
vethernet veth-num	Specifies the virtual Ethernet interface to use as the source SPAN or ERSPAN port. The virtual Ethernet interface number is from 1 to 1048575.
both	(Optional) Specifies both ingress and egress traffic on the source port.
rx	(Optional) Specifies only ingress traffic on the source port.
tx	(Optional) Specifies only egress traffic on the source port.
vlan vlan-num	Specifies the VLAN interface to use as the source SPAN port. Valid values are from 1 to 3967 and 4048 to 4093. For VLAN span sources only ingress traffic is spanned.
vsan vsan-num	Specifies the virtual storage area network (VSAN) to use as the source SPAN port. The range is from 1 to 4093. For VSAN span sources only ingress traffic is spanned.

Command Default

None

Command Modes

SPAN session configuration mode (config-monitor)
 ERSPAN source session configuration mode (config-erspan-src)
 SPAN-on-Drop session configuration mode (config-span-on-drop)
 SPAN-on-Drop ERSPAN session configuration mode (config-span-on-drop-erspan)
 SPAN-on-Latency session configuration mode (config-span-on-latency)
 SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: SPAN session configuration mode, ERSPAN destination session configuration mode, SPAN-on-Drop session configuration mode, SPAN-on-Drop ERSPAN session configuration mode, SPAN-on-Latency session configuration mode, and SPAN-on-Latency ERSPAN session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

A source port (also called a monitored port) is a switched port that you monitor for network traffic analysis. In a single local SPAN session, you can monitor source port traffic such as received (Rx), transmitted (Tx), or bidirectional (both).

A source port can be an Ethernet port, port channel, SAN port channel, VLAN, or a VSAN port. It cannot be a destination port.

**Note**

For VLAN and VSAN span sources only ingress traffic is spanned.

There is no limit to the number of egress SPAN source ports.

SAN Port Channel interfaces can be configured as ingress or egress source ports.

The limit on the number of egress (TX) sources in a monitor session has been lifted.

Port-channel interfaces can be configured as both ingress and egress sources.

For local SPAN and ERSPAN, if you do not specify both, rx, or tx, the source traffic is analyzed for both directions.

SPAN on Latency sessions analyze source traffic on TX only, and SPAN on Drop sessions analyze source traffic on RX only.

Examples

This example shows how to configure an Ethernet SPAN source port:

```
switch# configure terminal
switch(config)# monitor session 9 type local
switch(config-monitor)# description A Local SPAN session
switch(config-monitor)# source interface ethernet 1/1
switch(config-monitor)#
```

This example shows how to configure a port channel SPAN source:

```
switch# configure terminal
switch(config)# monitor session 2
switch(config-monitor)# source interface port-channel 5

switch(config-monitor)#
```

This example shows how to configure an ERSPAN source port:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
```

```
switch(config-erspan-src)# source interface ethernet 1/5 rx
switch(config-erspan-src)#
```

Related Commands

Command	Description
destination (SPAN, ERSPAN)	Configures a destination SPAN port.
monitor session	Creates a new SPAN session configuration.
show monitor session	Displays SPAN session configuration information.
show running-config monitor	Displays the running configuration information of a SPAN session.

source ip

To add a source port to an Encapsulated Remote Switched Port Analyzer (ERSPAN) destination session use the `source ip` command, in ERSPAN destination session configuration mode. To remove the source port, use the `no` form of this command.

```
source ip ip-address
no source ip-address
```

Syntax Description	ip-address	Specifies the IP address of the source port.
---------------------------	------------	--

Command Default None

Command Modes ERSPAN destination session configuration mode (config-erspan-dst)

Command History	Release	Modification
	7.0(0)N1(1)	This command was introduced..

Usage Guidelines A source port (also called a monitored port) is a switched port that you monitor for network traffic analysis.

Examples This example shows how to configure an ERSPAN destination session source port:

```
switch# configure terminal
switch(config)# monitor session 11 type erspan-destination
switch(config-erspan-dst)# source ip 10.1.1.1
switch(config-erspan-dst)#
```

Related Commands	Command	Description
	destination (SPAN, ERSPAN)	Configures a destination SPAN port.
	monitor session	Creates a new SPAN session configuration.
	show monitor session	Displays SPAN session configuration information.
	show running-config monitor	Displays the running configuration information of a SPAN session.

switchport monitor rate-limit

To configure a rate limit to monitor traffic on an interface, use the `switchport monitor rate-limit` command. To remove a rate limit, use the `no` form of this command.

```
switchport monitor rate-limit 1G
no switchport monitor rate-limit [1G]
```

Syntax Description	1G (Optional) Specifies that the rate limit is 1 GB.
---------------------------	--

Command Default	None
------------------------	------

Command Modes	Interface configuration mode
----------------------	------------------------------

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command is applicable to the following Cisco Nexus 5000 Series switches:

- Cisco Nexus 5010 Series
- Cisco Nexus 5020 Series

This command does not require a license.

Examples

This example shows how to limit the bandwidth on Ethernet interface 1/2 to 1 GB:

```
switch(config)# interface ethernet 1/2
switch(config-if)# switchport monitor rate-limit 1G
switch(config-if)#
```

Related Commands	Command	Description
	show interface switchport	Displays information on all interfaces configured as switch ports.
	switchport private-vlan association trunk	Associates the isolated trunk port with the primary and secondary VLANs of a private VLAN.

switch-profile

To create or configure a switch profile, use the switch-profile command. To delete a switch profile, use the no form of this command.

```
switch-profile sw-profile-name
no switch-profile sw-profile-name all-config | local-config | profile-only
```

Syntax Description

sw-profile-name	Name of the switch profile. The name is case sensitive, can be a maximum of 64 alphanumeric characters and can include an underscore and hyphen. The name cannot contain spaces or special characters.
all-config	Specifies that the switch profile be deleted with all local and peer configurations.
local-config	Specifies that the switch profile and all local configurations be deleted.
profile-only	Specifies that the switch profile only is to be deleted and no other configurations.

Command Default

None

Command Modes

Configuration synchronization mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

Use this command to create a switch profile on each of the peer switches. You must use the same profile name on both the switches in the Cisco Fabric Services (CFS) peer configuration.



Note

In this release of Cisco NX-OS, only a pair of switches can be configured as a peer.

You can configure only one active switch profile on each peer switch. If you create or configure a second switch profile, you see the following error message:

```
Error: Another switch profile already exists. Cannot configure more than one switch-profile.
```

The configuration that is made locally on the switch is synchronized and made available on the peer switch only after the connectivity is established between the peer switches and the configuration is verified and committed on the local switch.

You can configure a switch profile to include the interface configuration, quality of service (QoS), and virtual port channel (vPC) commands. FCoE commands are not supported on a switch profile.

When you delete a switch profile, you can choose to delete the local switch profile with the local configurations on the switch, delete the switch profile with the local configurations and configuration information in the peer, or delete the switch profile only while saving all other configuration information. The peer becomes unreachable.

Examples

This example shows how to create a switch profile named s6000a on switch 1 of the peer:

Peer A

```
switch# configure terminal
switch(config)# cfs ipv4 distribute
switch(config)# exit
switch# config sync
Enter configuration commands, one per line. End with CNTL/Z.
switch(config-sync)# switch-profile s6000a
Switch-Profile started, Profile ID is 1
switch(config-sync-sp)#
```

This example shows how to create a switch profile named s6000a on switch 2 of the peer:

Peer B

```
switch# configure terminal
switch(config)# cfs ipv4 distribute
switch(config)# exit
switch# config sync
Enter configuration commands, one per line. End with CNTL/Z.
switch(config-sync)# switch-profile s6000a
Switch-Profile started, Profile ID is 1
switch(config-sync-sp)#
```

This example shows how to delete a switch profile named s6000a and its local configuration on switch 1 of the peer:

Peer A

```
switch# config sync
Enter configuration commands, one per line. End with CNTL/Z.
switch(config-sync)# no switch-profile s6000a local-config
switch(config-sync)#
```

Related Commands

Command	Description
config sync	Enters configuration synchronization mode.
show switch-profile	Displays the switch profile created on the switch and its configuration revision.

Command	Description
sync-peers destination	Configures the peer switch for configuration synchronization.

system fex-group shutdown

To shutdown a Fabric Extender (FEX) group, use the system fex-group shutdown command. To bring up a FEX group, use the no form of this command.

```
system fex-group name shutdown
no system fex-group name shutdown
```

Syntax Description	name Specifies the name of the FEX group.
---------------------------	---

Command Default	None
------------------------	------

Command Modes	Maintenance profile configuration (config-mm-mode)
----------------------	--

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines	This command does not require a license.
-------------------------	--

Examples	This example shows how to shutdown a FEX group:
-----------------	---

```
switch# configure terminal
switch(config)# configure maintenance profile maintenance-mode
switch(config-mm-profile)# system fex-group fg1 shutdown
```

This example shows how to bring up a FEX group:

```
switch# configure terminal
switch(config)# configure maintenance profile maintenance-mode
switch(config-mm-profile)# no system fex-group fg1 shutdown
```

Related Commands	Command	Description
	configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
	show run mmode	Displays the currently running maintenance profile configuration on a switch.
	show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.

system mode maintenance

To put the switch in maintenance mode, use the system mode maintenance command. To exit the maintenance mode and return to normal mode, use the no form of the command.

```
system mode maintenance
no system mode maintenance
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration (config)

Release	Modification
7.3(0)N1(1)	This command was modified. The default mode for Graceful Insertion and Removal (GIR) is "isolate".
7.1(0)N1(1)	This command was introduced. The default mode for GIR is "shutdown".

Usage Guidelines In Cisco NX-OS Release 7.1(0)N1(1), the default mode for Graceful Insertion and Removal (GIR) is "shutdown". The switch will use the shutdown command to bring down the protocols and shut down the physical ports.

Beginning from Cisco NX-OS Release 7.3(0)N1(1), the default mode for GIR is "isolate". The switch will use the isolate command to isolate the protocols from the network. The switch will then be isolated from the network but is not shut down.

This command does not require a license.

Examples

This example shows how to put the switch in maintenance mode:

```
switch# configure terminal
switch(config)# system mode maintenance
Following configuration will be applied:
router bgp 100
  isolate
router ospf 100
  isolate
router isis 100
  isolate
Do you want to continue (y/n)? [no] y
Generating a snapshot before going into maintenance mode
Starting to apply commands...
Applying : router bgp 100
Applying : isolate
Applying : router ospf 100
Applying : isolate
Applying : router isis 100
Applying : isolate
Maintenance mode operation successful.
```

This example shows how to exit the maintenance mode and return to normal mode:

```

switch# configure terminal
switch(config)# no system mode maintenance
Following configuration will be applied:
router isis 100
  no isolate
router ospf 100
  no isolate
router bgp 100
  no isolate
Do you want to continue (y/n)? [no] y
Starting to apply commands...
Applying : router isis 100
Applying : no isolate
Applying : router ospf 100
Applying : no isolate
Applying : router bgp 100
Applying : no isolate
Maintenance mode operation successful.
Generating Current Snapshot
Please use 'show snapshots compare before_maintenance after_maintenance' to check the health
of the system

```

Related Commands

Command	Description
configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance always-use-custom-profile	Applies the existing custom maintenance mode profile and prevents creation of auto-generated maintenance mode profile.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

system mode maintenance always-use-custom-profile

To apply the existing custom maintenance-mode profile and prevent creation of auto-generated maintenance-mode profile, use the system mode maintenance always-use-custom-profile command.

```
system mode maintenance always-use-custom-profile
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode (config)

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines The always-use-custom-profile option forces the dont-generate-profile option to be used even if it has not been specified using the system mode maintenance command. You cannot use the "shutdown" option when the always-use-custom-profile option is being used.

This command does not require a license.

Examples

This example shows how to always apply the existing custom maintenance mode profile and prevent creation of auto-generated maintenance mode profile:

```
switch(config)# system mode maintenance always-use-custom-profile
```

Related Commands

Command	Description
configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
show run mmode	Displays the currently running maintenance profile configuration on a switch.
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

system mode maintenance dont-generate-profile

To prevent the dynamic searching of enabled protocols and put the switch in maintenance mode by executing commands configured in a custom maintenance mode profile, use the system mode maintenance dont-generate-profile command. To exit maintenance mode and return to normal mode, use the no form of this command.

```
system mode maintenance dont-generate-profile
no system mode maintenance dont-generate-profile
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration (config)

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples

This example shows how to prevent the dynamic searching of enabled protocols and put the switch in maintenance mode by executing commands configured in a custom maintenance mode profile:

```
switch(config)# system mode maintenance dont-generate-profile
Following configuration will be applied:
router bgp 100
  isolate
sleep instance 1 10
interface Ethernet1/1
  shutdown
Do you want to continue (y/n)? [no] y
Generating a snapshot before going into maintenance mode
Starting to apply commands...
Applying : router bgp 100
Applying :   isolate
Applying : sleep instance 1 10
Applying : interface Ethernet1/1
Applying :   shutdown
Maintenance mode operation successful.
```

Related Commands	Command	Description
	configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
	show run mmode	Displays the currently running maintenance profile configuration on a switch.

Command	Description
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

system mode maintenance on-reload reset-reason

To boot the switch into maintenance-mode automatically in the event of a specified system crash, use the system mode maintenance on-reload reset-reason command. To prevent the switch from being brought up in maintenance mode in the event of a system crash, use the no form of this command.

```
system mode maintenance on-reload reset-reason reason
no system mode maintenance on-reload reset-reason reason
```

Syntax Description	<table border="1"> <tr> <td style="vertical-align: top;">reason</td> <td> <p>Specifies the reset reason. The reset reasons are as follows:</p> <ul style="list-style-type: none"> • HW_ERROR—Hardware error • SVC_FAILURE—Critical service failure • KERN_FAILURE—Kernel panic • WDOG_TIMEOUT—Watchdog timeout • FATAL_ERROR—Fatal error • MANUAL_RELOAD---Manual reload • MAINTENANCE—Reloads the switch in maintenance mode if the switch was already in maintenance mode before reload. • MATCH_ANY—Any of the above reasons • ANY_OTHER—Any reload reason not specified above </td> </tr> </table>	reason	<p>Specifies the reset reason. The reset reasons are as follows:</p> <ul style="list-style-type: none"> • HW_ERROR—Hardware error • SVC_FAILURE—Critical service failure • KERN_FAILURE—Kernel panic • WDOG_TIMEOUT—Watchdog timeout • FATAL_ERROR—Fatal error • MANUAL_RELOAD---Manual reload • MAINTENANCE—Reloads the switch in maintenance mode if the switch was already in maintenance mode before reload. • MATCH_ANY—Any of the above reasons • ANY_OTHER—Any reload reason not specified above
reason	<p>Specifies the reset reason. The reset reasons are as follows:</p> <ul style="list-style-type: none"> • HW_ERROR—Hardware error • SVC_FAILURE—Critical service failure • KERN_FAILURE—Kernel panic • WDOG_TIMEOUT—Watchdog timeout • FATAL_ERROR—Fatal error • MANUAL_RELOAD---Manual reload • MAINTENANCE—Reloads the switch in maintenance mode if the switch was already in maintenance mode before reload. • MATCH_ANY—Any of the above reasons • ANY_OTHER—Any reload reason not specified above 		

Command Default None

Command Modes Global configuration (config)

Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>7.3(0)N1(1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	7.3(0)N1(1)	This command was introduced.
Release	Modification				
7.3(0)N1(1)	This command was introduced.				

Usage Guidelines We recommend configuring the reset reason and saving it to the startup configuration. This enables the switch to go into the maintenance mode after a switch reloads due to any reason.

This command does not require a license.

Examples

This example shows how to automatically boot the switch into maintenance mode if a fatal error or a hardware error occurs

```
switch(config)# system mode maintenance on-reload reset-reason fatal_error
switch(config)# system mode maintenance on-reload reset-reason hw_error
```

Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>configure maintenance profile</td> <td>Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.</td> </tr> </tbody> </table>	Command	Description	configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
Command	Description				
configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.				

Command	Description
show run mmode	Displays the currently running maintenance profile configuration on a switch.
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

system mode maintenance shutdown

To shut down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command), use the system mode maintenance shutdown command.

```
system mode maintenance shutdown
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration (config)

Release	Modification
7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples

This example shows how to shut down all protocol and interfaces on the switch except the management interface:

```
switch# configure terminal
switch(config)# system mode maintenance shutdown
Following configuration will be applied:
router bgp 100
  shutdown
router ospf 100
  shutdown
router isis 100
  shutdown
system interface shutdown
Do you want to continue (y/n)? [no] y
Generating a snapshot before going into maintenance mode
Starting to apply commands...
Applying : router bgp 100
Applying :  shutdown
Applying : router ospf 100
Applying :  shutdown
Applying : router isis 100
Applying :  shutdown
Applying : system interface shutdown
Maintenance mode operation successful.
```

Related Commands	Command	Description
	configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
	show run mmode	Displays the currently running maintenance profile configuration on a switch.

Command	Description
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

system mode maintenance timeout

To configure the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes, use the system mode maintenance timeout command. To remove the configured timer, use the no form of this command.

```
system mode maintenance timeout value
no system mode maintenance timeout value
```

Syntax Description	value Specifies the number of minutes for which the switch will be in maintenance mode. Range is from 5 to 65535 minutes.
---------------------------	---

Command Default None

Command Modes Global configuration (config)

Command History	<table border="1"> <thead> <tr> <th>Release</th> <th>Modification</th> </tr> </thead> <tbody> <tr> <td>7.3(0)N1(1)</td> <td>This command was introduced.</td> </tr> </tbody> </table>	Release	Modification	7.3(0)N1(1)	This command was introduced.
Release	Modification				
7.3(0)N1(1)	This command was introduced.				

Usage Guidelines We recommend setting the timeout value to at least 30 minutes. Once the configured time elapses, the switch returns to normal mode automatically.

This command does not require a license.

Examples

This example shows how to keep the switch in maintenance mode for a specific number of minutes:

```
switch# configure terminal
switch(config)# system mode maintenance timeout 30
```

Related Commands	<table border="1"> <thead> <tr> <th>Command</th> <th>Description</th> </tr> </thead> <tbody> <tr> <td>configure maintenance profile</td> <td>Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.</td> </tr> <tr> <td>show run mmode</td> <td>Displays the currently running maintenance profile configuration on a switch.</td> </tr> <tr> <td>show system mode</td> <td>Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.</td> </tr> <tr> <td>system mode maintenance on-reload reset-reason</td> <td>Boots the switch into maintenance mode automatically in the event of a specified system crash.</td> </tr> </tbody> </table>	Command	Description	configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.	show run mmode	Displays the currently running maintenance profile configuration on a switch.	show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.	system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
Command	Description										
configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.										
show run mmode	Displays the currently running maintenance profile configuration on a switch.										
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.										
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.										

system soft-reload enable

To enable the switch to perform a soft reload after a process crash, use the `system soft-reload enable` command. To disable soft reload, use the `no` form of this command.

```
system soft-reload enable
no system soft-reload enable
```

Syntax Description This command has no arguments or keywords.

Command Default Soft reload is disabled.

Command Modes Global configuration mode (`config`)

Release	Modification
7.3(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license. A normal switch reload is attempted if a soft reload due to a process crash fails. A soft reload is not triggered when the following scenarios occur:

- If Layer 3 licenses (`LAN_BASE_SERVICES_PKG` and `LAN_ENTERPRISE_SERVICES_PKG`) are installed.
- Kernel panic/crash
- Sysmgr crash
- Crashing of the following processes: `mmode`, `provision`, `xmlma`, `res`, `evms`, `evmc`, `securityd`, `aaa`, `snmpd`, `callhome`, `cts`, `m2rib`, `stp`, `ntp`, `ntpd`, `bigsurusd`, `carmelusd`, `pfma`, `sensor`, `pacifica`, `bootvar`, `ipqosmgr`, `vms`, `sh`, `libvirtd`, `init`, `sysmgr`, `pfma`, `vshd`, `licmgr` and `sysinfo`.

Examples This example shows how to perform a soft reload after a process crash:

```
switch# configure terminal
switch(config)# system soft-reload enable
```

This example shows how to disable soft reload:

```
switch# configure terminal
switch(config)# no system soft-reload enable
```

Command	Description
<code>show system soft-reload status</code>	Displays the status of the soft reload.

Command	Description
soft-reload	Performs a manual soft reload of the switch.

shut (SPAN, ERSPAN)

To shut down an Ethernet Switched Port Analyzer (SPAN) or an Encapsulated Remote Switched Port Analyzer (ERSPAN) or an Ethernet Switched Port Analyzer (SPAN) session, use the shut command. To enable a SPAN or an ERSPAN or SPAN session, use the no form of this command.

```
shut
no shut
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes

- SPAN session configuration mode (config-monitor)
- ERSPAN source session configuration mode (config-erspan-src)
- ERSPAN destination session configuration mode (config-erspan-dst)
- SPAN-on-Drop session configuration mode (config-span-on-drop)
- SPAN-on-Drop ERSPAN session configuration mode (config-span-on-drop-erspan)
- SPAN-on-Latency session configuration mode (config-span-on-latency)
- SPAN-on-Latency ERSPAN session configuration mode (config-span-on-latency-erspan)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: SPAN session configuration mode, ERSPAN destination session configuration mode, SPAN-on-Drop session configuration mode, SPAN-on-Drop ERSPAN session configuration mode, SPAN-on-Latency session configuration mode, and SPAN-on-Latency ERSPAN session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to shut down an ERSPAN source session:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# shut
switch(config-erspan-src)#
```

This example shows how to enable an ERSPAN destination session:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-destination
switch(config-erspan-dst)# no shut
switch(config-erspan-dst)#
```

This example shows how to shut down a SPAN-on-Drop ERSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-drop-erspan
switch(config-span-on-drop-erspan)# shut
switch(config-span-on-drop-erspan)#
```

This example shows how to enable a SPAN-on-Latency ERSPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-latency-erspan
switch(config-span-on-latency-erspan)# no shut
switch(config-span-on-latency-erspan)#
```

This example shows how to shut down a SPAN session:

```
switch# configure terminal
switch(config)# monitor session 1 type local
switch(config-monitor)# shut
switch(config-monitor)#
```

This example shows how to shut down a SPAN-on-Drop session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-drop
switch(config-span-on-drop)# shut
switch(config-span-on-drop)#
```

This example shows how to enable a SPAN-on-Latency session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-latency
switch(config-span-on-latency)# no shut
switch(config-span-on-latency)#
```

Related Commands

Command	Description
monitor session	Enters the monitor configuration mode.
show monitor session	Displays the virtual SPAN or ERSPAN configuration.

site-id (Call Home)

To configure the optional site number for the customer, use the `site-id` command. To remove a site number, use the `no` form of this command.

```
site-id site-number
no site-id
```

Syntax Description

site-number	Site number. The site number can be up to 255 alphanumeric characters in free format.
-------------	---

Command Default

None

Command Modes

Callhome configuration mode

Command History

Release	Modification
	This command was introduced.

Usage Guidelines

You can configure the customer identification information that Cisco Smart Call Home should use. The service agreement includes the customer identification information, such as the customer ID, contract ID, and site ID.

Examples

This example shows how to configure a site number:

```
switch(config-callhome)# site-id 10020-1203
switch(config-callhome)#
```

Related Commands

Command	Description
switch-priority	Configures the switch priority for the switch.
show callhome	Displays a summary of the Call Home configuration.

sleep instance

To delay the execution of a command by a specified number of seconds in the maintenance profile, use the `sleep instance` command. You can delay multiple instances of a command. To remove the delay, use the `no` form of this command.

```
sleep instance instance-number seconds
no sleep instance instance-number seconds
```

Syntax Description	instance-number	seconds
	Provides a label for the configuration by specifying a particular instance number. The range is from 0 to 2177483647.	
		Specifies the number of seconds by which the execution of the command has to be delayed. The range is from 0 to 2177483647.

Command Default None

Command Modes maintenance profile configuration (config-mm-profile)

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Examples

This example shows how to delay the execution of one command by 20 seconds and another command by 10 seconds:

```
switch#
configure maintenance profile normal-mode
Please configure 'system mode maintenance always-use-custom-profile' if you want to use
custom profile always for maintenance mode.
Enter configuration commands, one per line. End with CNTL/Z.
switch(config-mm-profile)#
interface ethernet 1/1
switch(config-mm-profile-if-verify)#
no shutdown

switch(config-mm-profile-if-verify)#
exit
switch(config-mm-profile)#
sleep instance 1 20
switch(config-mm-profile)#
router bgp 200
switch(config-mm-profile-router)#
address-family ipv4 unicast
switch(config-mm-profile-router-af)#
redistribute direct route-map my-rmap-deny
switch(config-mm-profile-router-af)#
exit

switch(config-mm-profile-router)#
exit
```

```
switch(config-mm-profile)#  
sleep instance 1 10
```

Related Commands

Command	Description
configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
show run mmode	Displays the currently running maintenance profile configuration on a switch.
show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.

soft-reload

To perform a manual soft reload of the switch, use the soft-reload command.

```
soft-reload
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Privileged EXEC mode

Command History	Release	Modification
	7.3(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

If a soft reload that has been triggered by using the soft-reload command fails, the switch will not be reloaded. Soft reload can then be attempted again by using the soft-reload command after the failures shown have been corrected.

Examples This example shows how to perform a manual soft reload of the switch:

```
switch# soft-reload
```

Related Commands	Command	Description
	show system soft-reload status	Displays the status of the soft reload.
	system soft-reload enable	Enables the switch to perform a soft reload after a process crash.



Show Commands

- [show snmp host, on page 213](#)
- [show snmp sessions, on page 214](#)
- [show snmp trap, on page 215](#)
- [show snmp user, on page 217](#)
- [show system mode, on page 218](#)
- [show tech-support mmode, on page 220](#)
- [show diagnostic bootup level, on page 222](#)
- [show diagnostic result, on page 223](#)
- [show flow exporter, on page 225](#)
- [show flow interface, on page 227](#)
- [show flow record, on page 229](#)
- [show flow timeout, on page 231](#)
- [show hosts, on page 232](#)
- [show ip dns source-interface, on page 233](#)
- [show logging console, on page 234](#)
- [show logging info, on page 235](#)
- [show logging last, on page 236](#)
- [show logging level, on page 237](#)
- [show logging logfile, on page 239](#)
- [show logging module, on page 240](#)
- [show logging monitor, on page 241](#)
- [show logging nvram, on page 242](#)
- [show logging onboard, on page 243](#)
- [show logging pending, on page 248](#)
- [show logging pending-diff, on page 249](#)
- [show logging server, on page 250](#)
- [show logging session status, on page 251](#)
- [show logging status, on page 252](#)
- [show logging timestamp, on page 253](#)
- [show monitor session, on page 254](#)
- [show ntp authentication-status, on page 256](#)
- [show ntp peers, on page 257](#)
- [show ntp peer-status, on page 258](#)

- [show ntp statistics](#), on page 259
- [show ntp timestamp-status](#), on page 260
- [show ptp brief](#), on page 261
- [show ptp clock](#), on page 262
- [show ptp clocks foreign-masters-record](#), on page 263
- [show ptp corrections](#), on page 264
- [show ptp parent](#), on page 265
- [show ptp port interface](#), on page 266
- [show ptp time-property](#), on page 267
- [show rmon](#), on page 268
- [show run mmode](#), on page 270
- [show running-config callhome](#), on page 272
- [show running-config interface vethernet](#), on page 274
- [show running-config monitor](#), on page 275
- [show running-config poe](#), on page 276
- [show running-config port-security](#), on page 277
- [show sampler](#), on page 278
- [show snapshots](#), on page 279
- [show snapshots compare](#), on page 280
- [show snapshots dump](#), on page 282
- [show snapshots sections](#), on page 284
- [show snmp community](#), on page 285
- [show snmp context](#), on page 286
- [show snmp engineID](#), on page 287
- [show snmp group](#), on page 288
- [show system soft-reload status](#), on page 290

show snmp host

To display the Simple Network Management Protocol (SNMP) host information, use the `show snmp host` command.

```
show snmp host
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples This example shows how to display the SNMP host:

```
switch# show snmp host
```

Command	Description
snmp-server host	Configures an SNMP host.

show snmp sessions

To display the current Simple Network Management Protocol (SNMP) sessions, use the `show snmp sessions` command.

```
show snmp sessions
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the SNMP sessions:

```
switch# show snmp sessions
```

Related Commands	Command	Description
	show running-config snmp	Displays the running configuration information about SNMP.

show snmp trap

To display the Simple Network Management Protocol (SNMP) link trap generation information, use the show snmp trap command.

```
show snmp trap
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the SNMP traps:

```
switch# show snmp trap
```

```
-----
Trap type           Description                                     Enabled
-----
entity              : entity_mib_change                             Yes
entity              : entity_module_status_change                   Yes
entity              : entity_power_status_change                   Yes
entity              : entity_module_inserted                       Yes
entity              : entity_module_removed                         Yes
entity              : entity_unrecognised_module                   Yes
entity              : entity_fan_status_change                     Yes
link                 : linkDown                                     Yes
link                 : linkUp                                       Yes
link                 : IETF-extended-linkDown                       Yes
link                 : IETF-extended-linkUp                         Yes
link                 : cisco-extended-linkDown                     Yes
link                 : cisco-extended-linkUp                       Yes
callhome             : event-notify                                 No
callhome             : smtp-send-fail                               No
cfs                  : state-change-notif                          No
cfs                  : merge-failure                               No
rf                   : redundancy_framework                         Yes
aaa                  : server-state-change                          No
license              : notify-license-expiry                        Yes
license              : notify-no-license-for-feature                Yes
license              : notify-licensefile-missing                   Yes
license              : notify-license-expiry-warning                Yes
zone                 : unsupp-mem                                   No
upgrade              : UpgradeOpNotifyOnCompletion                  Yes
upgrade              : UpgradeJobStatusNotify                       Yes
feature-control      : FeatureOpStatusChange                        No
sysmgr               : cseFailSwCoreNotifyExtended                 No
rmon                  : risingAlarm                                  No
rmon                  : fallingAlarm                                  No
rmon                  : hcRisingAlarm                                No
rmon                  : hcFallingAlarm                               No
-----
```

show snmp trap

```

config          : ccmCLIRunningConfigChanged      No
snmp            : authentication                  No
bridge         : topologychange                   No
bridge         : newroot                          No
stp            : inconsistency                     No
stp            : loop-inconsistency               No
stp            : root-inconsistency               No
switch#

```

Related Commands

Command	Description
snmp trap link-status	Enables SNMP link trap generation.

show snmp user

To display information on each Simple Network Management Protocol (SNMP) user, use the show snmp user command.

```
show snmp user
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the SNMP users configured on the switch:

```
switch# show snmp user

SNMP USERS

User                               Auth  Priv(enforce)  Groups
-----
admin                               md5    des(no)         network-admin

NOTIFICATION TARGET USERS (configured for sending V3 Inform)

User                               Auth  Priv
-----
switch#
```

This example shows how to display information about a specific SNMP user:

```
switch# show snmp user admin

switch#
```

Related Commands	Command	Description
	snmp-server user	Configures a new user to an SNMP group.

show system mode

To display the current system mode, use the show system mode command. Starting with Cisco NX-OS Release 7.3(0)N1(1), you can use the show system mode command to also display the current state of the maintenance mode timer when the switch is in maintenance mode

```
show system mode
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Any command mode

Release	Modification
7.3(0)N1(1)	Supports display of current state of the maintenance mode timer when the switch is in maintenance mode.
7.1.0	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to display the current system mode:

```
switch# show system mode
```

```
System Mode : Normal
```

This example shows how to display the current system mode and the state of the maintenance mode timer when the switch is in maintenance mode:

```
switch# show system mode
```

```
System Mode: Maintenance
Maintenance Mode Timer: 24 minutes 55 seconds remaining
```

This example shows that the switch is in maintenance mode and that the maintenance mode timer is not running:

```
switch# show system mode
```

```
System Mode: Maintenance
Maintenance Mode Timer: not running
```

Command	Description
show run mmode	Displays the currently running maintenance profile configuration on a switch.

Command	Description
system mode maintenance always-use-custom-profile	Applies the existing custom maintenance-mode profile and prevents creation of auto-generated maintenance-mode profile.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance-mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

show tech-support mmode

To display information for maintenance profile troubleshooting, use the show tech-support mmode command.

```
show tech-support mmode
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Privileged EXEC

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to display information for maintenance profile troubleshooting:

```
switch# show tech-support mmode
`show system mode`
System Mode: Normal
`show maintenance profile`
[Normal Mode]
router bgp 100
  no isolate
[Maintenance Mode]
router bgp 100
  isolate
`show maintenance on-reload reset-reasons`
Reset reasons for on-reload maintenance mode:
-----
(not configured)
bitmap = 0x0
`show maintenance timeout`
Maintenance mode timeout value: 0 minutes
`show system internal mmode mem-stats`
Num blocks      User size      Total size      Library
-----
      16           560           800      mmode
     265          51818          55824      ld-2.8.so
       1            20            32      libdl-2.8.so
       1            38            56      libpthread-2.8.so
      12           2860           3056      libsviifdb.so.0.0.0
```

Related Commands

Command	Description
system mode maintenance always-use-custom-profile	Applies the existing custom maintenance-mode profile and prevents creation of auto-generated maintenance-mode profile.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance-mode automatically in the event of a specified system crash.

Command	Description
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

show diagnostic bootup level

To display the current bootup diagnostic level on the switch, use the show diagnostic bootup level command.

```
show diagnostic bootup level
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the current bootup diagnostic level:

```
switch# show diagnostic bootup level

Current bootup diagnostic level: complete
switch#
```

Related Commands	Command	Description
	diagnostic bootup level	Configures the bootup diagnostic level for a faster module bootup time.
	show diagnostic result	Displays the results of the diagnostics tests.

show diagnostic result

To display the results of the diagnostic tests, use the show diagnostic result command.

```
show diagnostic result module module-no | all
```

Syntax Description	
module	Specifies the module for which diagnostic results are displayed.
module-no	Module number. Valid values are 1 to 3.
all	Displays the diagnostic results for all modules.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the diagnostic results for a specific module:

```
switch# show diagnostic result module 1

Current bootup diagnostic level: complete
Module 1: 48X10GE/Supervisor SerialNo : JAF1339ANGH
Overall Diagnostic Result for Module 1 : PASS
Diagnostic level at card bootup: complete
Test results: (. = Pass, F = Fail, I = Incomplete,
              U = Untested, A = Abort)
  1) TestUSBFlash -----> .
  2) TestSPROM -----> .
  3) TestPCIE -----> .
  4) TestLED -----> .
  5) TestOBFL -----> .
  6) TestNVRAM -----> .
  7) TestPowerSupply -----> F
  8) TestTemperatureSensor -----> .
  9) TestFan -----> .
 10) TestVoltage -----> .
 11) TestGPIO -----> .
 12) TestInbandPort -----> .
 13) TestManagementPort -----> .
 14) TestMemory -----> .
 15) TestFabricEngine :
Eth   1  2  3  4  5  6  7  8  9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Port -----
      .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .
Eth  25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48
Port -----
      .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .  .
 16) TestFabricPort :
Eth   1  2  3  4  5  6  7  8  9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Port -----
```

show diagnostic result

```

Eth  25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48
Port -----
. . . . .
17) TestForwardingEngine :
Eth  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Port -----
. . . . .
Eth  25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48
Port -----
. . . . .
18) TestForwardingEnginePort :
Eth  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Port -----
. . . . .
Eth  25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48
Port -----
. . . . .
19) TestFrontPort :
Eth  1  2  3  4  5  6  7  8  9 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Port -----
. . . . .
Eth  25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48
Port -----
. . . . .
switch#

```

Related Commands

Command	Description
diagnostic bootup level	Configures the bootup diagnostic level for a faster module bootup time.
show diagnostic bootup level	Displays the bootup diagnostics level.

show flow exporter

To display the Flexible NetFlow flow exporter status and statistics, use the show flow exporter command.

```
show flow exporter [name exporter-name]
```

Syntax Description

name exporter-name	(Optional) Specifies the name of a flow exporter. The name can be any case-sensitive, alphanumeric string up to 64 characters.
--------------------	--

Command Default

Information for all flow exporters configured on the router is displayed.

Command Modes

Any command mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

You must have already enabled traffic monitoring with Flexible NetFlow using an exporter before you can use the show flow exporter command.

This command does not require a license.

Examples

This example shows how to display the status and statistics for all of the flow exporters configured on the router:

```
switch# show flow exporter
Flow Exporter NFC-DC-PHOENIX:
Export Version 5
Exporter Statistics
  Number of Flow Records Exported 0
  Number of Export Packets Sent 0
  Number of Export Bytes Sent 0
  Number of Destination Unreachable Events 0
  Number of No Buffer Events 0
  Number of Packets Dropped (No Route to Host) 0
  Number of Packets Dropped (other) 0
  Number of Packets Dropped (LC to RP Error) 0
  Number of Packets Dropped (Output Drops) 0
  Time statistics were last cleared: Never
Flow exporter timeout:
Export Version 5
Exporter Statistics
  Number of Flow Records Exported 0
  Number of Export Packets Sent 0
  Number of Export Bytes Sent 0
  Number of Destination Unreachable Events 0
  Number of No Buffer Events 0
  Number of Packets Dropped (No Route to Host) 0
  Number of Packets Dropped (other) 0
  Number of Packets Dropped (LC to RP Error) 0
  Number of Packets Dropped (Output Drops) 0
  Time statistics were last cleared: Never
Flow exporter test-exporter:
  Description: test server in San Jose CA
```

```

Export Version 5
Exporter Statistics
  Number of Flow Records Exported 0
  Number of Export Packets Sent 0
  Number of Export Bytes Sent 0
  Number of Destination Unreachable Events 0
  Number of No Buffer Events 0
  Number of Packets Dropped (No Route to Host) 0
  Number of Packets Dropped (other) 0
  Number of Packets Dropped (LC to RP Error) 0
  Number of Packets Dropped (Output Drops) 0
  Time statistics were last cleared: Never

```

Related Commands

Command	Description
clear flow exporter	Clears the statistics for exporters.
destination	Configures an export destination for flow exporters.
dscp	Configures optional differentiated services code point (DSCP) parameters for flow exporters.
flow exporter	Creates a flow exporter.
option	Configure options for flow exporters.
show flow exporter	Displays flow exporter status and statistics.
source	Configures the source IP address interface for flow exporters.
template	Configures the template resend timeout for flow exporters.
transport	Configures the transport protocol for flow exporters.

show flow interface

To display the Flexible NetFlow configuration and status for an interface, use the show flow interface command.

```
show flow interface [interface-type number]
```

Syntax Description

interface-type number	(Optional) Type of interface that you want to view Flexible NetFlow accounting configuration information on.
-----------------------	--

Command Default

Information for the Flexible NetFlow accounting configuration on the interface is displayed.

Command Modes

Any command mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

You must have already enabled traffic monitoring with Flexible NetFlow before you can use the show flow interface command.

This command does not require a license.

Examples

This example shows how to display the Flexible NetFlow accounting configuration on interface Ethernet 1/30:

```
switch# show flow interface ethernet 1/30

Interface Ethernet1/30
  Monitor:          m1
  Direction: Input
  Traffic(IPv4): sampler SAMPLER-2#
```

Table 1 describes the significant fields shown in the display.

Table 2: show flow interface Field Descriptions

Field	Description
Interface	The interface that information is applicable to.
monitor	The name of the flow monitor that is configured on the interface.
direction:	The direction of traffic the flow monitor is monitoring.
traffic (ip)	Indicates if the flow monitor is in normal mode or sampler mode. The possible values are as follows: <ul style="list-style-type: none"> • On—The flow monitor is in normal mode. • Sampler— The flow monitor is in sampler mode (the name of the sampler is included in the display).

Related Commands

Command	Description
show flow sampler	Displays flow sampler status and statistics.

show flow record

To display the status and statistics of a Flexible NetFlow flow record, use the show flow record command.

```
show flow record [[name record-name] [netflow ipv4 | ipv6 record | layer2-switched input | protocol-port]
| netflow-original]
```

Syntax Description	
name record-name	(Optional) Specifies the name of a flow record that you previously configured.
netflow record	(Optional) Configures the flow monitor to use one of the predefined records. See Table 3: Keywords and Descriptions for the record Argument, on page 229 for a listing of the available records and their definitions.
layer2-switched input	(Optional) Configures the flow monitor to use the Layer 2 switched collection scheme records.
protocol-port	(Optional) Configures the flow monitor to use protocol and ports aggregation records.
netflow-original	(Optional) Specifies the Flexible NetFlow implementation of original NetFlow with origin autonomous systems.

Command Default Information for all flow exporters configured on the router is displayed.

Command Modes Any command mode

Command History	Release	Modification
	7.0(0)N1(1)	This command was introduced.

Usage Guidelines You must have already enabled traffic monitoring with Flexible NetFlow using an exporter before you can use the show flow exporter command.

Table 2 describes the keywords and descriptions for the record argument.

Table 3: Keywords and Descriptions for the record Argument

original-input	Traditional IPv4 input NetFlow.
original-output	Traditional IPv4 output NetFlow.

This command does not require a license.

Examples

This example shows how to display the status and statistics of the original input NetFlow record:

```
switch# show flow record netflow ipv4 original-input
```

```
Flow record ipv4 original-input:
  Description: Traditional IPv4 input NetFlow
  No. of users: 0
  Template ID: 0
  Fields:
```

```

match ipv4 source address
match ipv4 destination address
match ip protocol
match ip tos
match transport source-port
match transport destination-port
match interface input
collect routing source as
collect routing destination as
collect routing next-hop address ipv4
collect transport tcp flags
collect counter bytes
collect counter packets
collect timestamp sys-uptime first
collect timestamp sys-uptime last
collect interface output
switch#

```

Table 3 describes the significant fields shown in the display.

Table 4: show flow record netflow-original Field Descriptions

Field	Description
Description	The description that you configured for the record or the default description—User defined.
No. of users	The number of references to this record in the configuration.
Fields	The fields that are included in this record. For more information on the fields, refer to the match and collect commands.

Related Commands

Command	Description
exporter	Specifies a flow exporter for flow monitors.
flow monitor	Creates a flow monitor.
record	Configures a flow record for the flow monitor.
record	Configures a flow record a for flow monitor.

show flow timeout

To display the Flexible NetFlow flow cache timeout values, use the show flow timeout command.

```
show flow timeout
```

Syntax Description

This command has no arguments or keywords.

Command Default

Information for the Flexible NetFlow accounting configuration on the interface is displayed.

Command Modes

Any command mode

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

You must have already enabled traffic monitoring with Flexible NetFlow before you can use the show flow timeout command.

This command does not require a license.

Examples

This example shows how to display the Flexible NetFlow flow cache timeout values:

```
switch# show flow timeout
Flow timeout values
  Active timeout:           1800 seconds
  Inactive timeout:        15 seconds
  Flush Cache timeout      15 seconds
  Fast timeout:            Disabled
  Session aging timeout:   Disabled
  Aggressive aging timeout: Disabled
switch#
```

Related Commands

Command	Description
flow timeout	Creates a flow timeout.

show hosts

To display the Domain Name Server (DNS) name servers and domain names, use the show hosts command.

```
show hosts
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the IP addresses of the DNS servers that are used to resolve host names:

```
switch# show hosts
DNS lookup enabled
Default domain for vrf:default is mysite.com
Name/address lookup uses domain service
Name servers are 255.255.255.255
Vrf                Use-vrf           Token             Config
default            management        domain            mysite.com
default            management        add. domain(s)   mysite2.com
Host                Address
```

Related Commands

Command	Description
ip domain-list	Defines a list of domains.
ip domain lookup	Enables DNS-based host name-to-address translation.
ip domain-name	Configures a name server.

show ip dns source-interface

To display the source interfaces configured for Domain Name Server (DNS) domain lookup, use the `show ip dns source-interface` command.

```
show ip dns source-interface [vrf vrf-name | all | default | management]
```

Syntax Description		
vrf	(Optional) Displays information about the virtual routing and forwarding (VRF) instance.	
vrf-name	(Optional) VRF name. The name is case sensitive and can be a maximum of 32 characters.	
all	(Optional) Displays all VRF instances.	
default	(Optional) Displays the default VRF information.	
management	(Optional) Displays the management VRF information.	

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to display the source interfaces configured for DNS domain lookup:

```
switch# show ip dns source-interface
VRF Name          Interface
default           Ethernet1/5
switch#
```

Related Commands	Command	Description
	ip domain-lookup	Enables the DNS lookup feature.
	ip dns source-interface	Configures interfaces for DNS domain lookup.

show logging console

To display the console logging configuration, use the show logging console command.

```
show logging console
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the console logging configuration:

```
switch# show logging console
```

Related Commands	Command	Description
	logging console	Configures logging to the console.

show logging info

To display the logging configuration, use the show logging info command.

```
show logging info
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the logging configuration:

```
switch# show logging info
```

Related Commands	Command	Description
	logging level	Enables logging messages from a defined facility.

show logging last

To display the last number of lines of the logfile, use the show logging last command.

```
show logging last number
```

Syntax Description

number	Enters the number of lines to display from 1 to 9999.
--------	---

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the last 42 lines of the log file:

```
switch# show logging last 42
```

Related Commands

Command	Description
logging level	Enables logging messages from a defined facility.

show logging level

To display the facility logging severity level configuration, use the show logging level command.

```
show logging level [facility]
```

Syntax Description	facility (Optional) Logging facility. The facilities are listed in Table 1-1 of show logging level
---------------------------	--

Command Default	None
------------------------	------

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the EtherChannel logging severity level configuration:

```
switch# show logging level port-channel
```

This example shows how to display the Flex Links logging severity level configuration:

```
switch# show logging level flexlink
```

```
Facility           Default Severity      Current Session Severity
-----
Flexlink           2                      5
0(emergencies)    1(alerts)             2(critical)
3(errors)         4(warnings)           5(notifications)
6(information)    7(debugging)
switch#
```

This example shows how to display the FCoE NPV logging severity level configuration:

```
switch# show logging level fcoe_mgr
```

```
Facility           Default Severity      Current Session Severity
-----
fcoe_mgr          2                      3
0(emergencies)    1(alerts)             2(critical)
3(errors)         4(warnings)           5(notifications)
6(information)    7(debugging)
switch#
```

This example shows how to display the Power over Ethernet (PoE) logging severity level configuration:

```
switch# show logging level poed
Facility           Default Severity      Current Session Severity
-----
poe               5                      5
0(emergencies)    1(alerts)             2(critical)
3(errors)         4(warnings)           5(notifications)
```

show logging level

```
6 (information)          7 (debugging)
switch#
```

Related Commands

Command	Description
logging level	Configures the facility logging level.

show logging logfile

To display the messages in the log file that were timestamped within the span entered, use the show logging logfile command.

```
show logging logfile [start-time yyyy mmm dd hh : mm : ss] [end-time yyyy mmm dd hh : mm : ss]
```

Syntax Description	
start-time yyyy mmm dd hh:mm:ss	(Optional) Specifies a start time in the format yyyy mmm dd hh:mm:ss . Use three characters for the month (mmm) field, digits for the year (yyyy) and day (dd) fields, and digits separated by colons for the time (hh:mm:ss) field.
end-time yyyy mmm dd hh:mm:ss	(Optional) Specifies an end time in the format yyyy mmm dd hh:mm:ss . Use three characters for the month (mmm) field, digits for the year (yyyy) and day (dd) fields, and digits separated by colons for the time (hh:mm:ss) field.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines If you do not enter an end time, the current time is used.

Examples This example shows how to display the messages in the log file that were timestamped within the span shown:

```
switch# show logging logfile start-time 2008 mar 11 12:10:00
```

Related Commands	Command	Description
	logging logfile	Configures logging to a log file.

show logging module

To display the module logging configuration, use the show logging module command.

```
show logging module
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the module logging configuration:

```
switch# show logging module
```

Related Commands	Command	Description
	logging module	Configures module logging.

show logging monitor

To display the monitor logging configuration, use the show logging monitor command.

```
show logging monitor
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the monitor logging configuration:

```
switch# show logging monitor
```

Related Commands	Command	Description
	logging monitor	Configures logging on the monitor.

show logging nvram

To display the messages in the nonvolatile random access memory (NVRAM) log, use the show logging nvram command.

```
show logging nvram [last number-lines]
```

Syntax Description

last number-lines	(Optional) Specifies the number of lines to display. The number of lines is from 1 to 100.
----------------------	--

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the last 20 messages in the NVRAM log:

```
switch# show logging nvram last 20
```

Related Commands

Command	Description
logging level	Enables logging messages from a defined facility.

show logging onboard

To display the onboard logging information based on the error type, use the show logging onboard command.

```
show logging onboard boot-uptime | device-version | endtime | environmental-history | exception-log |
kernel-trace | obfl-history | obfl-logs | stack-trace | starttime | status [> file | type]
```

Syntax	Description
boot-uptime	Displays the onboard failure logging (OBFL) boot and uptime information.
device-version	Displays the OBFL device version information.
endtime	Displays the OBFL logs until the specified end time in the following format: mm/dd/yy-HH:MM:SS
environmental-history	Displays the OBFL environmental history.
exception-log	Displays the OBFL exception log.
kernel-trace	Displays the OBFL kernel trace information.
obfl-history	Displays the OBFL history information.
obfl-logs	Displays the OBFL technical support log information.
stack-trace	Displays the OBFL kernel stack trace information.
starttime	Displays the OBFL logs from the specified start time in the following format: mm/dd/yy-HH:MM:SS
status	Displays the OBFL status enable or disable.
> file	(Optional) Redirects the output to a file. See the “Usage Guidelines” section for additional information.
type	(Optional) Filters the output. See the “Usage Guidelines” section for additional information.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines The date and time arguments for the starttime and endtime keywords are entered as the date month/day/year (mm/dd/yy), followed by a hyphen, and the time in 24-hour format in hours:minutes:seconds (HH:MM:SS). For example:

- starttime 01/30/13-15:01:57
- endtime 01/30/13-15:04:57

The valid values for file are as follows:

- bootflash:
- ftp:
- scp:
- sftp:
- tftp:
- volatile:

The valid values for type are as follows:

- begin [-i] [-x] [word] —Begin with the line that matches the text.
 - -i—Ignores the case difference when comparing the strings.
 - -x—Prints only the lines where the match is a whole line.
 - word—Specifies for the expression.
- count [> file | | type] —Counts number of lines.
- egrep | grep print-match—Egrep or Grep. Egrep searches for lines of text that match more sophisticated regular expression syntax than grep. Grep searches for lines of text that match one or many regular expressions, and outputs only the matching lines.
 - -A num—Prints the specifies number of lines of context after every matching line. Range: 1 to 999.
 - -B num—Prints the specifies number of lines of context before every matching line. Range: 1 to 999.
 - -c—Prints a total count of matching lines only.
 - -i—Ignores the case difference when comparing the strings.
 - -n—Prints each match preceded by its line number.
 - -v—Prints only the lines that contain no matches for the word argument.
 - -w—Prints only lines where the match is a complete word.
 - -x—Prints only the lines where the match is a whole line.
 - word—Specifies for the expression.
- exclude [-i] [-x] [word] —Excludes the lines that match.
 - -i—Ignores the case difference when comparing the strings.
 - -x—Prints only the lines where the match is a whole line.
 - word—Specifies for the expression.
- head [-n num] —Stream Editor. The optional -n num keyword and argument allow you to specify the number of lines to print. Range: 0 to 2147483647.
- include [-i] [-x] [word] —Include the lines that match.
 - -i—Ignores the case difference when comparing the strings.
 - -x—Prints only the lines where the match is a whole line.
 - word—Specifies for the expression.
- last num] —Displays the last lines to print. The optional num specifies the number of lines to print. Range: 0 to 9999.
- less [-E | -d]—Quits at the end of the file.
 - -E—(Optional) Quits at the end of the file.
 - -d—(Optional) Specifies a dumb terminal.

- no-more—Turns-off pagination for command output.
- sed command—Stream Editor
- wc—Counts words, lines, and characters.
 - -c—(Optional) Specifies the output character count.
 - -l—(Optional) Specifies the output line count.
 - -w—(Optional) Specifies the output word count.
 - >—Redirects it to a file.
 - |—Pipes command output to filter.

Use this command to view OBFL data from the system hardware. The OBFL feature is enabled by default and records operating temperatures, hardware uptime, interrupts, and other important events and messages that can assist with diagnosing problems with hardware cards or modules installed in a Cisco router or switch. Data is logged to files stored in nonvolatile memory. When the onboard hardware is started up, a first record is made for each area monitored and becomes a base value for subsequent records.

The OBFL feature provides a circular updating scheme for collecting continuous records and archiving older (historical) records, ensuring accurate data about the system. Data is recorded in one of two formats: continuous information that displays a snapshot of measurements and samples in a continuous file, and summary information that provides details about the data being collected. The message “No historical data to display” is seen when historical data is not available.

Examples

This example shows how to display the OBFL boot and uptime information:

```
switch# show logging onboard boot-uptime

Wed Jan 30 06:11:59 2013:  Boot Record
-----
Boot Time.....: Wed Jan 30 06:11:59 2013
Slot Number.....: 1
Serial Number.....: FLC12345678
Bios Version.....: v1.2.0(06/19/08)
Firmware Version...: 6.0(2)N1(1) [build 6.0(2)N1(1)]
```

Table 4 describes the significant fields shown in the display.

Table 5: show logging onboard boot-uptime Command Output

Field	Description
Boot Time	Time boot occurred.
Slot Number	Slot number.
Serial Number	Serial number of the module.
Bios Version	Primary binary input and output system (BIOS) version.
Firmware Version	Firmware version.

This example shows how to display the OBFL logging device information:

```
switch# show logging onboard device-version
```

```

OBFL Data for
  Module: 1
-----
Device Version Record
-----
Timestamp                Device Name          Instance Hardware Software
                        Num   Version   Version
-----
Wed Jan 30 07:07:00 2013  GATOS                2         2         0
Wed Jan 30 07:07:00 2013  GATOS                3         2         0
Wed Jan 30 07:07:00 2013  GATOS                4         2         0
Wed Jan 30 07:07:00 2013  GATOS                5         2         0
Wed Jan 30 07:07:00 2013  GATOS                6         2         0
Wed Jan 30 07:07:00 2013  GATOS                7         2         0
Wed Jan 30 07:07:00 2013  GATOS                8         2         0
Wed Jan 30 07:07:00 2013  GATOS                9         2         0
Wed Jan 30 07:07:00 2013  GATOS               10         2         0
Wed Jan 30 07:07:00 2013  GATOS               11         2         0
Wed Jan 30 07:07:00 2013  GATOS               12         2         0
Wed Jan 30 07:07:00 2013  GATOS               13         2         0
Wed Jan 30 07:07:00 2013  ALTOS                 0         2         0
Wed Jan 30 07:07:00 2013  GATOS                 0         2         0
Wed Jan 30 07:07:00 2013  GATOS                 1         2         0
Wed Jan 30 07:07:00 2013  GATOS                 2         2         0

```

Table 5 describes the significant fields shown in the display.

Table 6: show logging onboard device-version Command Output

Field	Description
Timestamp	Day, date, and time.
Device Name	Device name.
Instance Num	Number of instances.
Hardware Version	Hardware device version.
Software Version	Software device version.

This example shows how to display the OBFL history information:

```
switch# show logging onboard obfl-history
```

The show logging onboard obfl-history command displays the following information:

- Timestamp when OBFL is manually disabled.
- Timestamp when OBFL is manually enabled.
- Timestamp when OBFL data is manually cleared.

This example shows how to display the OBFL kernel stack trace information:

```
switch# show logging onboard stack-trace
```

The show logging onboard stack-trace command displays the following information:

- Time in seconds
- Time in microseconds
- Error description string

- Current process name and identification
- Kernel jiffies
- Stack trace

Related Commands

Command	Description
clear logging onboard	Clears the OBFL entries in the persistent log.
hw-module logging onboard	Enables or disabled OBFL entries based on the error type.

show logging pending

To display the pending changes to the syslog server configuration, use the show logging pending command.

```
show logging pending
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the pending changes to the syslog server configuration:

```
switch# show logging pending
switch#
```

Related Commands

Command	Description
logging abort	Cancels the pending changes to the syslog server configuration.

show logging pending-diff

To display the differences from the current syslog server configuration to the pending changes of the syslog server configuration, use the show logging pending-diff command.

```
show logging pending-diff
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the pending differences of the syslog server configuration:

```
switch# show logging pending-diff
switch#
```

Command	Description
logging abort	Cancels the pending changes to the syslog server configuration.

show logging server

To display the syslog server configuration, use the show logging server command.

```
show logging server
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the syslog server configuration:

```
switch# show logging server
```

Related Commands	Command	Description
	logging server	Configures a remote syslog server.

show logging session status

To display the logging session status, use the show logging session status command.

```
show logging session status
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the logging session status:

```
switch# show logging session status
```

Related Commands	Command	Description
	logging level	Enables logging messages from a defined facility.

show logging status

To display the logging status, use the show logging status command.

```
show logging status
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the logging status:

```
switch# show logging status

Fabric Distribute      : Enabled
Session State         : IDLE
switch#
```

Related Commands	Command	Description
	logging distribute	Enables the distribution of the syslog server configuration to network switches using the Cisco Fabric Services (CFS) infrastructure.

show logging timestamp

To display the logging time-stamp configuration, use the show logging timestamp command.

```
show logging timestamp
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the logging time-stamp configuration:

```
switch# show logging timestamp
```

Related Commands	Command	Description
	logging timestamp	Configures the logging time stamp granularity.

show monitor session

To display information about the Switched Port Analyzer (SPAN) or Encapsulated Remote Switched Port Analyzer (ERSPAN) sessions, use the show monitor session command.

```
show monitor session [session | all [brief] | range range [brief] | status]
```

Syntax Description

session	(Optional) Number of the session. The range is from 1 to 18.
all	(Optional) Displays all sessions.
brief	(Optional) Displays a brief summary of the information.
range range	(Optional) Displays a range of sessions. The range is from 1 to 18.
status	(Optional) Displays the operational state of all sessions. Note This keyword applies only to SPAN sessions.

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display information about SPAN session 1:

```
switch# show monitor session 1
session 1
-----
description      : A Local SPAN session
type             : local
state            : down (No operational src/dst)
source intf      :
  rx              : Eth1/5
  tx              : Eth1/5
  both           : Eth1/5
source VLANs     :
  rx              :
source VSANs     :
  rx              :
destination ports : Eth1/21
Legend: f = forwarding enabled, l = learning enabled
switch#
```

This example shows how to display a brief information about a SPAN session:

```
switch# show monitor session range 1 brief
session 1
-----
```



```

description      : A Local SPAN session
type             : local
state            : down (No operational src/dst)
source intf     :
  rx              : Eth1/5
  tx              : Eth1/5
  both           : Eth1/5
source VSANs    :
destination ports : Eth1/21
Legend: f = forwarding enabled, l = learning enabled
switch#

```

This example shows how to display the information about an ERSPAN session on a switch:

```

switch# show monitor session 1
session 1
-----
description      : ERSPAN Source configuration
type             : erspan-source
state            : down (No valid global IP Address)
flow-id          : 1
vrf-name         : default
destination-ip   : 192.0.2.1
ip-ttl           : 255
ip-dscp          : 0
origin-ip        : origin-ip not specified
source intf     :
  rx              : Eth1/5
  tx              : Eth1/5
  both           : Eth1/5
source VLANs    :
  rx              : 5
switch#

```

Related Commands

Command	Description
monitor session	Creates a new Switched Port Analyzer (SPAN) session configuration.
show running-config monitor	Displays the running configuration information about SPAN sessions.

show ntp authentication-status

To display the status of the Network Time Protocol (NTP) authentication, use the `show ntp authentication-status` command.

```
show ntp authentication-status
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Any command mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the authentication status for NTP:

```
switch(config)#show ntp authentication-status
```

Related Commands	Command	Description
	[no] ntp authenticate	Displays information about NTP peers.

show ntp peers

To display information about Network Time Protocol (NTP) peers, use the show ntp peers command.

```
show ntp peers
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display information about NTP peers:

```
switch(config)#show ntp peers
```

Command	Description
show ntp peer-status	Displays status information about NTP peers.

show ntp peer-status

To display the status of the Network Time Protocol (NTP) peers, use the show ntp peer-status command.

```
show ntp peer-status
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the peer status for NTP:

```
switch(config)# show ntp peer-status
```

Related Commands	Command	Description
	show ntp peers	Displays information about NTP peers.

show ntp statistics

To display Network Time Protocol (NTP) statistics, use the show ntp statistics command.

```
show ntp statistics io | local | memory | peer ipaddr address | name name1 [ . . nameN]
```

Syntax Description

io	Displays the input-output statistics.
local	Displays the counters maintained by the local NTP.
memory	Displays the statistics counters related to the memory code.
peer	Displays the per-peer statistics counter of a peer.
ipaddr address	Displays statistics for the peer with the configured IPv4 or IPv6 address. The IPv4 address format is dotted decimal, x.x.x.x. The IPv6 address format is hexadecimal A:B::C:D.
name name1	Displays statistics for a named peer.
..nameN	(Optional) Displays statistics for one or more named peers.

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the statistics for NTP:

```
switch(config)#show ntp statistics local
```

Related Commands

Command	Description
clear ntp statistics	Clears NTP statistics

show ntp timestamp-status

To display the Network Time Protocol (NTP) time-stamp information, use the show ntp timestamp-status command.

```
show ntp timestamp-status
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the NTP time-stamp status:

```
switch(config)#show ntp timestamp-status
```

Related Commands	Command	Description
	clear ntp statistics	Clears NTP statistics
	ntp	Configures NTP peers and servers on the switch.

show ptp brief

To display the PTP information, use the show ptp brief command.

```
show ptp brief
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples This example shows how to display the PTP status:

```
switch(config)#show ptp brief
```

Related Commands	Command	Description
	show ptp clock	Displays the properties of the local clock.
	show ptp clocks foreign-masters-record	Displays the state of foreign masters known to the PTP process.
	show ptp corrections	Displays the last few PTP corrections.
	show ptp parent	Displays the properties of the PTP parent and grandmaster clock.
	show ptp port interface	Displays the status of the PTP port.
	show ptp time-property	Displays the PTP clock time properties.

show ptp clock

To display the properties of the local PTP clock including clock identity, use the show ptp clock command.

```
show ptp clock
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples This example shows how to display the properties of the local clock:

```
switch(config)#show ptp clock
```

Related Commands	Command	Description
	show ptp brief	Displays the PTP status.
	show ptp clocks foreign-masters-record	Displays the state of foreign masters known to the PTP process.
	show ptp corrections	Displays the last few PTP corrections.
	show ptp parent	Displays the properties of the PTP parent and grandmaster clock.
	show ptp port interface	Displays the status of the PTP port.
	show ptp time-property	Displays the PTP clock time properties.

show ptp clocks foreign-masters-record

To display the state of the foreign masters known to the PTP process, use the show ptp clocks foreign-masters-record command.

```
show ptp clocks foreign-masters-record [ethernet slot /[QSFP-module/] port]
```

Syntax Description	Parameter	Description
	ethernet	Specifies an Ethernet interface.
	slot/[QSFP-module/]port	The slot number is from 1 to 255. The QSFP-module number is from 1 to 199. The port number is from 1 to 128.

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines For each foreign master, the output displays the clock identity, basic clock properties, and whether the clock is being used as a grandmaster.

Examples This example shows how to display the foreign masters known to the PTP process:

```
switch(config)#show ptp foreign-masters-record
```

Related Commands	Command	Description
	show ptp brief	Displays the PTP status.
	show ptp clock	Displays the properties of the local clock.
	show ptp corrections	Displays the last few PTP corrections.
	show ptp port interface	Displays the status of the PTP port.
	show ptp parent	Displays the properties of the PTP parent and grandmaster clock.
	show ptp time-property	Displays the PTP clock time properties.

show ptp corrections

To display the last few PTP corrections, use the show ptp corrections command.

```
show ptp corrections
```

Syntax Description There are no arguments or keywords for this command.

Command Default None

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the most recent PTP corrections on the switch:

```
switch(config)#show ptp corrections
```

Related Commands

Command	Description
show ptp brief	Displays the PTP status.
show ptp clock	Displays the properties of the local clock.
show ptp clocks foreign-masters-record	Displays the state of foreign masters known to the PTP process.
show ptp port interface	Displays the status of the PTP port.
show ptp parent	Displays the properties of the PTP parent and grandmaster clock.
show ptp time-property	Displays the PTP clock time properties.

show ptp parent

To display the properties of the PTP parent and grandmaster clock, use the show ptp parent command.

```
show ptp parent
```

Syntax Description

There are no arguments or keywords for this command.

Command Default

None

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the properties of the PTP parent and grandmaster clock:

```
switch(config)#show ptp parent
```

Related Commands

Command	Description
show ptp brief	Displays the PTP status.
show ptp clock	Displays the properties of the local clock.
show ptp clocks foreign-masters-record	Displays the state of foreign masters known to the PTP process.
show ptp corrections	Displays the last few PTP corrections.
show ptp port interface	Displays the status of the PTP port.
show ptp time-property	Displays the PTP clock time properties.

show ptp port interface

To display the status of the PTP port, use the `show ptp port interface ethernet` command.

```
show ptp port interface [ethernet slot /[QSFP-module/] port]
```

Syntax Description		
	ethernet	Specifies an Ethernet interface.
	slot/[QSFP-module/]port	The slot number is from 1 to 255. The QSFP-module number is from 1 to 199. The port number is from 1 to 128.

Command Default None

Command Modes Global configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the status of the PTP port on the switch:

```
switch(config)#show ptp port interface ethernet 5/1
```

Related Commands	Command	Description
	show ptp brief	Displays the PTP status.
	show ptp clock	Displays the properties of the local clock.
	show ptp clocks foreign-masters-record	Displays the state of foreign masters known to the PTP process.
	show ptp corrections	Displays the last few PTP corrections.
	show ptp port interface	Displays the status of the PTP port.
	show ptp parent	Displays the properties of the PTP parent and grandmaster clock.
	show ptp time-property	Displays the PTP clock time properties.

show ptp time-property

To display the PTP clock time properties, use the show ptp time-property command.

```
show ptp time-property
```

Syntax Description

There are no arguments or keywords for this command.

Command Default

None

Command History

Release	Modification
6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the PTP clock time properties:

```
switch(config)#show ptp time-property
```

Related Commands

Command	Description
show ptp brief	Displays the PTP status.
show ptp clock	Displays the properties of the local clock.
show ptp clocks foreign-masters-record	Displays the state of foreign masters known to the PTP process.
show ptp corrections	Displays the last few PTP corrections.
show ptp parent	Displays the properties of the PTP parent and grandmaster clock.
show ptp port interface	Displays the status of the PTP port.

show rmon

To display information about Remote Monitoring (RMON) alarms or high-capacity alarms or events, use the show rmon command.

show rmon alarms | events | hcalarms | info | logs

Syntax Description

alarms	Displays the RMON alarms.
events	Displays the RMON events.
hcalarms	Displays the RMON high-capacity alarms.
info	Displays the RMON configuration information.
logs	Displays information about the RMON event logs.

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
	This command was introduced.

Examples

This example shows how to display the RMON high-capacity alarms configured on the switch:

```
switch# show rmon hcalarms

High Capacity Alarm 3 is active, owned by admin
Monitors 1.3.6.1.2.1.2.2.1.17.83886080 every 5 second(s)
Taking delta samples, last value was 216340
Rising threshold is 0, assigned to event 3
Falling threshold is 0, assigned to event 0
On startup enable rising alarm
Number of Failed Attempts is 0
switch#
```

This example shows how to display the RMON events configured on the switch:

```
switch# show rmon events

Event 5 is active, owned by admin
Description is myRMONEvent
Event firing causes nothing, last fired never
switch#
```

This example shows how to display the RMON configuration information:

```
switch# show rmon info

Maximum allowed 32 bit or 64 bit alarms : 512
Number of 32 bit alarms configured : 0
```

```
Number of 64 bit hcalarms configured : 1  
switch#
```

Related Commands

Command	Description
rmon alarm	Creates RMON alarms.
rmon event	Creates RMON events.
rmon hcalarm	Creates RMON high-capacity alarms.
show running-config	Displays the running configuration.

show run mmode

To display the currently running maintenance profile configuration on a switch, use the show run mmode command.

```
show run mmode [all]
```

Syntax Description	all Displays the currently running maintenance profile configuration along with the defaults.
---------------------------	---

Command Default None

Command Modes Privileged EXEC

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples

This example shows how to display the currently running maintenance profile configuration on a switch:

```
switch(config)# show run mmode
!Command: show running-config mmode
!Time: Wed May 13 22:37:02 1970
version 7.3(0)N1(1)
configure maintenance profile normal-mode
  router isis 100
    no isolate
  router ospf 100
    no isolate
  router bgp 100
    no isolate
configure maintenance profile maintenance-mode
  router bgp 100
    isolate
  router ospf 100
    isolate
  router isis 100
    isolate
configure terminal
```

Related Commands	Command	Description
	configure maintenance profile	Enters a maintenance profile configuration session to create a custom maintenance mode profile or a custom normal mode profile.
	show system mode	Displays the current system mode and the current state of the maintenance mode timer when the switch is in maintenance mode.

Command	Description
system mode maintenance always-use-custom-profile	Applies the existing custom maintenance mode profile and prevents creation of auto-generated maintenance mode profile.
system mode maintenance on-reload reset-reason	Boots the switch into maintenance mode automatically in the event of a specified system crash.
system mode maintenance shutdown	Shuts down all protocols and interfaces except the management interface (by using the shutdown command and not the default isolate command).
system mode maintenance timeout	Configures the maintenance window timer to keep the switch in maintenance mode for a specified number of minutes.

show running-config callhome

To display the Call Home running configuration, use the show running-config callhome command.

```
show running-config callhome [all]
```

Syntax Description

all	(Optional) Displays all the default and configured information.
-----	---

Command Default

Displays only the configured information.

Command Modes

EXEC mode

Command History

Release	Modification
	This command was introduced.

Examples

This example shows how to display the Call Home running configuration:

```
switch# show running-config callhome
!Command: show running-config callhome
!Time: Fri Jun 18 09:37:56 2010
version 5.0(2)N1(1)
callhome
  alert-group configuration user-def-cmd show ip routing
switch#
```

This example shows how to display the entire Call Home running configuration, including the default values:

```
switch# show running-config callhome all
!Command: show running-config callhome all
!Time: Fri Jun 18 09:38:03 2010
version 5.0(2)N1(1)
callhome
  switch-priority 7
  destination-profile CiscoTAC-1 transport-method email
  no destination-profile CiscoTAC-1 transport-method http
  destination-profile CiscoTAC-1 message-size 5000000
  destination-profile CiscoTAC-1 message-level 0
  destination-profile full_txt transport-method email
  no destination-profile full_txt transport-method http
  destination-profile full_txt message-size 2500000
  destination-profile full_txt message-level 0
  destination-profile short_txt transport-method email
  no destination-profile short_txt transport-method http
  destination-profile short_txt message-size 4000
  destination-profile short_txt message-level 0
  destination-profile CiscoTAC-1 alert-group cisco-tac
  destination-profile full_txt alert-group all
  destination-profile short_txt alert-group all
  alert-group configuration user-def-cmd show ip routing
  no enable
  duplicate-message throttle
  periodic-inventory notification
```

```
periodic-inventory notification interval 7
periodic-inventory notification timeofday 08:00
switch#
```

Related Commands

Command	Description
show callhome	Displays Call Home configuration information.

show running-config interface vethernet

To display the the currently running configuration for a virtual Ethernet interface, use the show running-config interface vethernet command.

```
show running-config interface vethernet veth-id [all | expand-port-profile]
```

Syntax Description		
	veth-id	Virtual Ethernet interface number. The range is from 1 to 1,048,575.
	all	(Optional) Displays the full operating information including default settings.
	expand-port-profile	(Optional) Displays the configuration information of port profiles.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	5.1(3)N1(1)	This command was introduced.

Examples

This example shows how to display the running configuration for a virtual Ethernet interface :

```
switch# show running-config interface vethernet 10
!Command: show running-config interface Vethernet10
!Time: Fri Jan  2 01:40:37 2009
version 5.1(3)N1(1)
interface Vethernet10
  inherit port-profile ppVEth
  untagged cos 3
  switchport access vlan 101
  bind interface Ethernet1/5 channel 10
switch#
```

This example shows how to display detailed information on the running configuration for a specified virtual Ethernet interface:

```
switch# show running-config interface vethernet 10 all
```

Related Commands	Command	Description
	interface vethernet	Configures a virtual Ethernet interface.

show running-config monitor

To display the running configuration for the Switched Port Analyzer (SPAN) or Encapsulated Remote Switched Port Analyzer (ERSPAN) session, use the show running-config monitor command.

```
show running-config monitor [all]
```

Syntax Description	all (Optional) Displays current SPAN configuration information including default settings.
---------------------------	--

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display information on the running SPAN configuration:

```
switch# show running-config monitor

!Command: show running-config monitor
!Time: Wed Jan 30 07:07:00 2013
version 6.0(2)N1(1)
monitor session 1
  description A Local SPAN session
  source interface Ethernet1/5 both
  destination interface Ethernet1/21
  no shut
switch#
```

This example shows how to display detailed information on the running SPAN configuration:

```
switch# show running-config monitor all

!Command: show running-config monitor all
!Time: Wed Jan 30 07:07:00 2013
version 6.0(2)N1(1)
monitor session 1 type local
  description A Local SPAN session
  source interface Ethernet1/5 both
  destination interface Ethernet1/21
  no shut
switch#
```

Related Commands	Command	Description
	monitor session	Configures SPAN or ERSPAN sessions.
	show monitor session	Displays information about SPAN or ERSPAN sessions.

show running-config poe

[NOTE: per Christine, “the commands exist in the software but I was told they will remain in the code but we shouldn't show them in the docs until the rubicon fex goes out”]

To display the running configuration for Power over Ethernet (PoE) ports, use the show running-config poe command.

```
show running-config poe [all]
```

Syntax Description

all	(Optional) Displays detailed information about PoE ports, including default settings.
-----	---

Command Default

None

Command Modes

EXEC mode

Command History

Release	Modification
5.0(3)N2(1)	This command was introduced.

Examples

This example shows how to display the running configuration for PoE ports:

```
switch# show running-config poe
```

Related Commands

Command	Description
show startup-config poe	Displays the startup configuration information about PoE ports.
show tech-support poe	Displays troubleshooting information about PoE ports.

show running-config port-security

To display the running system configuration information about secure ports, use the show running-config port-security command.

```
show running-config port-security [all]
```

Syntax Description	all (Optional) Displays detailed information about secure ports, including default settings.
---------------------------	--

Command Default	None
------------------------	------

Command Modes	EXEC mode
----------------------	-----------

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines	This command does not require a license.
-------------------------	--

Examples This example shows how to display the running system configuration of all secure ports on an interface:

```
switch# show running-config port-security
!Command: show running-config port-security
!Time: Wed Jan 30 07:07:00 2013
version 5.1(3)N1(1)
feature port-security
interface Ethernet1/5
  switchport port-security
  switchport port-security aging time 3
  switchport port-security maximum 10
  switchport port-security mac-address sticky
switch#
```

Related Commands	Command	Description
	clear port-security dynamic	Clears the dynamically secured addresses on a port.
	show startup-config port-security	Displays the configuration information in the startup file.

show sampler

To display a NetFlow sampler, use the show sampler command.

```
show sampler [name] [sampler-name]
```

Syntax Description	name	(Optional) Specifies a sampler.
	sampler-name	(Optional) Sampler name. The maximum number of characters is 63.

Command Default None

Command Modes Any command mode

Command History	Release	Modification
	7.0(0)N1(1)	This command was introduced.

Usage Guidelines You can create a sampler to define the NetFlow sampling rate for a flow. This command does not require a license.

Examples This example shows how to display a NetFlow sampler:

```
switch(config)#
show sampler
Sampler Netflow-Sampler-1:
 mode 1 out-of 1024
switch(config)#
```

Related Commands	Command	Description
	sampler	Configures a sampler to collect data for a user selected packet ratio to preserve hardware resources.

show snapshots

To display the snapshots present on the switch, use the show snapshots command.

```
show snapshots
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Privileged EXEC

Release	Modification
7.1.0	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to display the snapshots present on the switch:

```
switch# show snapshots
Snapshot Name      Time                Description
-----
before_maintenance  Wed May 13 13:21:16 1970  system-internal-snapshot
new                 Mon May 11 15:51:27 1970  after if down
```



Note In the above output example, “before_Maintenance” is the system-generated snapshot and “new” is the user-generated snapshot.

Command	Description
snapshot create name description	Creates a snapshot. The name variable can be 64 characters in length. The description variable can be 256 characters in length.
snapshot delete	Deletes a snapshot.
show snapshots compare	Displays the comparison between two snapshots.
show snapshots dump	Displays content of the various sections in a generated snapshot.
snapshot section	Adds or deletes a snapshot section.

show snapshots compare

To display the comparison between the two snapshots on a switch, use the show snapshots compare command.

```
show snapshots snapshot-1 snapshot-2 [ipv4routes | ipv6routes | summary]
```

Syntax Description

snapshot-1 snapshot-2	Displays the comparison between the two snapshots.
ipv4routes	Displays a comparison of the IPv4 routes between the two snapshots.
ipv6routes	Displays a comparison of the IPv6 routes between the two snapshots.
summary	Displays a summary of the comparison between the two snapshots.

Command Default

None

Command Modes

Privileged EXEC

Command History

Release	Modification
7.1.0	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to display a comparison between two snapshots:

```
switch# show snapshots compare before_maint during_maint
```

```
=====
Feature                Tag                before_maint      during_maint
=====
[bgp]
-----
[eigrp]
-----
[eigrpv6]
-----
[interface]
-----
... <snip> ...
[v4route]
-----

[ipprefix:0.0.0.0/32]
uptime                PT24M32S          **PT58M37S**
```

```
[ipprefix:127.0.0.0/8]
uptime                PT24M32S          **PT58M37S**
```

This example shows how to display a summary of the comparison between two snapshots:

```
switch# show snapshots compare before_maintenance after_maintenance summary

=====
Feature                                before_maintenance after_maintenance
changed
=====
basic summary
# of interfaces                        50                50
# of vlans                             0                 0
# of ipv4 routes vrf default           13                13
# of ipv4 paths vrf default            13                13
# of ipv4 routes vrf management        14                14
# of ipv4 paths vrf management         14                14
# of ipv6 routes vrf default           3                 3
# of ipv6 paths vrf default            3                 3
interfaces
# of eth interfaces                    48                48
# of eth interfaces up                  1                 1
# of eth interfaces down                47                47
# of eth interfaces other               0                 0
# of vlan interfaces                   0                 0
# of vlan interfaces up                 0                 0
# of vlan interfaces down               0                 0
# of vlan interfaces other              0                 0
```

This example shows how to display a comparison of the IPv4 routes between the two snapshots:

```
switch# show snapshots compare snapshot1 snapshot2 ipv4routes
```

Related Commands

Command	Description
show snapshots	Displays snapshots on a switch.
show snapshots dump	Display content of the various sections in a generated snapshot.
show snapshots sections	Displays content of the various sections in a generated snapshot.
snapshot create name description	Creates a snapshot. The name variable can be 64 characters in length. The description variable can be 256 characters in length.
snapshot delete	Deletes a snapshot.
show snapshots dump	Displays content of the various sections in a generated snapshot.
snapshot section	Adds or deletes a snapshot section.

show snapshots dump

To display content of the various sections in a generated snapshot, use the show snapshots dump command.

```
show snapshots dump snapshot-name
```

Syntax Description	snapshot-name	Name of the snapshot.

Command Default None

Command Modes Privileged EXEC

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples

The following example shows how to display content of the various sections in a generated snapshot:

```
switch# show snapshots dump new
```

```
File: interface.xml      Snapshot: new
=====
<?xml version="1.0" encoding="ISO-8859-1"?>
<nf:rpc-reply xmlns:nf="urn:ietf:params:xml:ns:netconf:base:1.0" xmlns="http://www.cisco.com/nxos:7.3.0.N1.1.1:if_manager">
  <nf:data>
    <show>
      <interface>
        <_readonly_>
          <TABLE_interface>
            <ROW_interface>
              <interface>mgmt0</interface>
              <state>up</state>
              <admin_state>up</admin_state>
              <eth_hw_desc>GigabitEthernet</eth_hw_desc>
              <eth_hw_addr>5cfc.666d.3b34</eth_hw_addr>
              <eth_bia_addr>5cfc.666d.3b34</eth_bia_addr>
              <eth_ip_addr>5.24.100.101</eth_ip_addr>
              <eth_ip_mask>16</eth_ip_mask>
              <eth_ip_prefix>5.24.0.0</eth_ip_prefix>
              <eth_mtu>1500</eth_mtu>
            </ROW_interface>
          </TABLE_interface>
        </_readonly_>
      </interface>
    </show>
  </nf:data>
</nf:rpc-reply>
```

Related Commands

Command	Description
show snapshots	Displays snapshots on a switch.
show snapshots sections	Displays content of the various sections in a generated snapshot.
snapshot create name description	Creates a snapshot. The name variable can be 64 characters in length. The description variable can be 256 characters in length.

Command	Description
snapshot delete	Deletes a snapshot.
show snapshots dump	Displays content of the various sections in a generated snapshot.
snapshot section	Adds or deletes a snapshot section.

show snapshots sections

To display the user-specified sections in a snapshot, use the show snapshots sections command.

```
show snapshots sections
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Privileged EXEC

Command History	Release	Modification
	7.3(0)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to display the user-specified sections in a snapshot:

```
switch# show snapshots sections
user-specified snapshot sections
-----
[v4route]
show command: show ip route detail vrf all
row id: ROW_prefix
key1: ipprefix
key2: -
```

Related Commands	Command	Description
	show snapshots compare	Displays the comparison between two snapshots.
	show snapshots dump	Displays content of the various sections in a generated snapshot.
	snapshot create name description	Creates a snapshot. The name variable can be 64 characters in length. The description variable can be 256 characters in length.
	snapshot delete	Deletes a snapshot.
	snapshot section	Adds or deletes a snapshot section.

show snmp community

To display the Simple Network Management Protocol (SNMP) community strings configured on the switch, use the `show snmp community` command.

```
show snmp community
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the SNMP community strings:

```
switch# show snmp community

Community          Group / Access      context  acl_filter
-----          -
public            network-admin
switch#
```

Related Commands	Command	Description
	snmp-server community	Configures the community access string to permit access to the SNMP protocol.

show snmp context

To display the Simple Network Management Protocol (SNMP) contexts configured on the switch, use the `show snmp context` command.

```
show snmp context
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the SNMP contexts:

```
switch# show snmp context
```

Related Commands	Command	Description
	snmp-server context	Configures an SNMP context.

show snmp engineID

To display the identification of the local Simple Network Management Protocol (SNMP) engine, use the show snmp engineID command.

```
show snmp engineID
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Usage Guidelines An SNMP engine is a copy of SNMP that can reside on a local or remote device. SNMP passwords are localized using the SNMP engine ID of the authoritative SNMP engine.

Examples

This example shows how to display the SNMP engine ID:

```
switch# show snmp engineID

Local SNMP engineID: [Hex] 8000000903000DECB230C0
                    [Dec] 128:000:000:009:003:000:013:236:178:048:192
switch#
```

Related Commands	Command	Description
	show running-config snmp	Displays the running configuration information about SNMP.

show snmp group

To display the names of the Simple Network Management Protocol (SNMP) groups configured on the switch, use the show snmp group command.

```
show snmp group
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes EXEC mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to display the SNMP groups:

```
switch# show snmp group

Role: network-admin
  Description: Predefined network admin role has access to all commands
                on the switch
-----
Rule    Perm    Type      Scope      Entity
-----
1       permit  read-write
Role: network-operator
  Description: Predefined network operator role has access to all read
                commands on the switch
-----
Rule    Perm    Type      Scope      Entity
-----
1       permit  read
Role: vdc-admin
  Description: Predefined vdc admin role has access to all commands within
                a VDC instance
-----
Rule    Perm    Type      Scope      Entity
-----
1       permit  read-write
Role: vdc-operator
  Description: Predefined vdc operator role has access to all read commands
                within a VDC instance
-----
Rule    Perm    Type      Scope      Entity
-----
1       permit  read
Role: priv-3
  Description: This is a system defined privilege role.
  vsan policy: permit (default)
  Vlan policy: permit (default)
  Interface policy: permit (default)
  Vrf policy: permit (default)
Role: priv-2
```

```

Description: This is a system defined privilege role.
vsan policy: permit (default)
Vlan policy: permit (default)
Interface policy: permit (default)
Vrf policy: permit (default)
Role: priv-1
Description: This is a system defined privilege role.
vsan policy: permit (default)
Vlan policy: permit (default)
Interface policy: permit (default)
Vrf policy: permit (default)
Role: priv-0
Description: This is a system defined privilege role.
vsan policy: permit (default)
Vlan policy: permit (default)
Interface policy: permit (default)
Vrf policy: permit (default)
-----
Rule      Perm    Type      Scope      Entity
-----
10       permit  command               traceroute6 *
9        permit  command               traceroute *
8        permit  command               telnet6 *
7        permit  command               telnet *
6        permit  command               ping6 *
5        permit  command               ping *
4        permit  command               ssh6 *
3        permit  command               ssh *
2        permit  command               enable *
1        permit  read
Role: priv-15
Description: This is a system defined privilege role.
vsan policy: permit (default)
Vlan policy: permit (default)
Interface policy: permit (default)
Vrf policy: permit (default)
-----
Rule      Perm    Type      Scope      Entity
-----
1        permit  read-write
switch#
    
```

Related Commands

Command	Description
show running-config snmp	Displays the running configuration information about SNMP.

show system soft-reload status

To display the status of the soft reload, use the show system soft-reload status command.

```
show system soft-reload status
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Privileged EXEC mode

Command History	Release	Modification
	7.3(2)N1(1)	This command was introduced.

Usage Guidelines This command does not require a license.

Examples This example shows how to display the status of the soft reload:

```
switch# show system soft-reload status
Soft-reload is disabled
```

Related Commands	Command	Description
	soft-reload	Performs a manual soft reload of the switch.
	system soft-reload enable	Enables the switch to perform a soft reload after a process crash.



T Commands

- [template data timeout, on page 292](#)

template data timeout

To configure the template data timeout parameter for the NetFlow exporter, use the `template data timeout` command. To remove the template data timeout parameter, use the `no` form of this command.

```
template data timeout time
no template data timeout [time]
```

Syntax Description

time	(Optional) Time in seconds. The range is from 1 to 86400.
------	---

Command Default

None

Command Modes

NetFlow exporter version 9 configuration (`config-flow-exporter-version-9`)

Command History

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure the template data timeout parameter:

```
switch(config)#
flow exporter Netflow-Exporter-1
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# template data timeout 120
```

This example shows how to remove the template data timeout parameter configuration:

```
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# no template data timeout 120
```

Related Commands

Command	Description
<code>show flow exporter</code>	Displays information about NetFlow exporters.



V Commands

- [verify \(session\)](#), on page 294
- [version 5](#), on page 295
- [version 9](#), on page 296
- [vrf \(ERSPAN\)](#), on page 298

verify (session)

To verify the current configuration session, use the verify command.

```
verify
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes Session configuration mode

Command History	Release	Modification
	6.0(2)N1(1)	This command was introduced.

Examples

This example shows how to verify a session:

```
switch(config-s)# verify
```

```
Failed to start Verification: Session Database already locked, Verify/Commit in Progress.
switch(config-s)#
```

Related Commands

Command	Description
commit	Commits a session.
configure session	Creates a configuration session.
show configuration session	Displays the contents of the session.

version 5

To configure version 5 for the NetFlow exporter, use the version 5 command. To remove the version 5 configuration, use the no form of this command

```
version 5
no version 5
```

Syntax Description This command has no arguments or keywords.

Command Default None

Command Modes NetFlow exporter configuration (config-flow-exporter)

Release	Modification
7.0(0)N1(1)	This command was introduced.

Usage Guidelines The default NetFlow exporter version is 5.
If you remove the version 5 configuration, the NetFlow exporter defaults to version 9.
This command does not require a license.

Examples This example shows how to configure the NetFlow exporter version to version 5:

```
switch(config)#
flow exporter Netflow-Exporter-1
switch(config-flow-exporter)#
version 5
switch(config-flow-exporter-version-5)#
```

This example shows how to remove the version 5 configuration, which causes the NetFlow exporter to default to version 9:

```
switch(config-flow-exporter-version-5)#
no version 5
switch(config-flow-exporter)#
```

Command	Description
show flow exporter	Displays information about NetFlow exporters.
version 9	Configures the NetFlow exporter to version 9.

version 9

To specify the export version 9 and enter the export version configuration mode, use the version 9 command.

```
version 9
no version 9
```

Syntax Description This command has no arguments or keywords.

Command Default Flow exporters are not present in the configuration until you create them.

Command Modes Flow export configuration

Command History	Release	Modification
	7.0(0)N1(1)	This command was introduced.

Usage Guidelines Flow exporters export the data in the flow monitor cache to a remote system, such as a server running NetFlow collector, for analysis and storage. Flow exporters are created as separate entities in the configuration. Flow exporters are assigned to flow monitors to provide data export capability for the flow monitors. You can create several flow exporters and assign them to one or more flow monitors to provide several export destinations. You can create one flow exporter and apply it to several flow monitors.

Once you enter the flow exporter configuration mode, the prompt changes to the following:

```
switch(config-flow-exporter)#
```

Within the flow exporter configuration mode, you can enter the version 9 keywords. Once you enter the version 9 keywords, the prompt changes to the following:

```
switch(config-flow-exporter-version-9)#
```

When entering the no form of this command, the seconds argument is optional.

This command does not require a license.

Examples

This example shows how to specify the name of the flow exporter that is created or modified.

```
switch(config)# flow exporter flow-export-test
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)#
```

This example shows how to specify the version 9 exporter statistics option templates and data:

```
switch(config)# flow exporter flow-export-test
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# exporter-stats
```

This example shows how to specify the version 9 interface table option templates and data:

```
switch(config)# flow exporter flow-export-test
```

```
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# interface-table
```

This example shows how to specify the version 9 interface table option templates and data:

```
switch(config)# flow exporter flow-export-test
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# sampler-table
```

This example shows how to specify the option resend time in seconds:

```
switch(config)# flow exporter flow-export-test
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# timeout 32
```

This example shows how to specify the data template:

```
switch(config)# flow exporter flow-export-test
switch(config-flow-exporter)# version 9
switch(config-flow-exporter-version-9)# template data
```

Related Commands

Command	Description
flow exporter	Creates a flow exporter.
flow monitor	Creates a flow monitor.
flow record	Creates a flow record.
sampler	Creates a flow sampler.

vrf (ERSPAN)

To configure a virtual routing and forwarding (VRF) instance for Encapsulated Remote Switched Port Analyzer (ERSPAN) traffic forwarding in both the source and destination, use the `vrf` command. To revert to the defaults, use the `no` form of this command.

```
vrf vrf_name | default | management
no vrf vrf_name | default | management
```

Syntax Description

<code>vrf_name</code>	Name of the VRF. The VRF name can be any case-sensitive, alphanumeric string up to 32 characters.
<code>default</code>	Specifies the default VRF instance.
<code>management</code>	Specifies the management VRF instance.

Command Default

None

Command Modes

ERSPAN source session configuration mode (`config-erspan-src`)

SPAN-on-Drop ERSPAN session configuration mode (`config-span-on-drop-erspan`)

SPAN-on-Latency ERSPAN session configuration mode (`config-span-on-latency-erspan`)

Command History

Release	Modification
7.0(0)N1(1)	This command was modified. This command was implemented in the following modes: SPAN-on-Drop ERSPAN session configuration mode and SPAN-on-Latency ERSPAN session configuration mode.
6.0(2)N1(1)	This command was introduced.

Usage Guidelines

This command does not require a license.

Examples

This example shows how to configure a VRF instance for the ESRSPAN source session:

```
switch# configure terminal
switch(config)# monitor session 1 type erspan-source
switch(config-erspan-src)# vrf default
switch(config-erspan-src)#
```

This example shows how to configure a VRF instance for the SPAN-on-Drop ESRSPAN source session:

```
switch# configure terminal
switch(config)# monitor session 1 type span-on-drop-erspan
switch(config-span-on-drop-erspan)# vrf default
switch(config-span-on-drop-erspan)#
```

This example shows how to configure a VRF instance for the SPAN-on-Latency ESRSPAN source session:

```
switch# configure terminal  
switch(config)# monitor session 1 type span-on-latency-erspan  
switch(config-span-on-latency-erspan)# vrf default  
switch(config-span-on-latency-erspan)#
```

Related Commands

Command	Description
monitor-session	Enters the monitor configuration mode for configuring an ERSPAN or SPAN session for analyzing traffic between ports.
show monitor session	Displays information about the Ethernet switched port analyzer (SPAN) or ERSPAN monitor session.

