



Cisco Nexus 3000 Series NX-OS Release Notes, Release 6.0(2)U3(8)

First Published: April 17, 2015

Last Updated: April 17, 2015

This document describes the features, bugs, and limitations for Cisco Nexus 3000 Series and Cisco Nexus 3100 Series switches. Use this document in combination with documents listed in the “Obtaining Documentation and Submitting a Service Request” section.

Note: Release notes are sometimes updated with new information about restrictions and bugs. See the following website for the most recent version of the Cisco Nexus 3000 Series release notes:

<http://www.cisco.com/c/en/us/support/switches/nexus-3000-series-switches/products-release-notes-list.html>.

Table 1 shows the online change history for this document.

Table 1. Online History Change

| Date | Description |
|------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| April 17, 2015 | Created NX-OS Release 6.0(2)U3(8) release notes |
| May 11, 2015 | Created Known Behaviors section |
| July 15, 2015 | Removed CSCun87600 |
| November 2, 2015 | Added the following note: GLC-SX-MMD is supported on all Cisco Nexus 3000 Series Switches except for the Cisco Nexus 3064-T. Please refer to the comparability matrix for all the supported platforms. |
| December 4, 2015 | |

Contents

| | |
|-----------------------------------------------------------------------|-----------|
| Introduction | 2 |
| System Requirements | 3 |
| New and Changed Information | 30 |
| Upgrade and Downgrade Guidelines | 31 |
| Limitations | 31 |
| Caveats | 33 |
| MIB Support | 34 |
| Related Documentation | 34 |
| Documentation Feedback | 35 |
| Obtaining Documentation and Submitting a Service Request | 35 |

Introduction

Several new hardware and software features are introduced for the Cisco Nexus 3000 Series and Cisco Nexus 3100 Series devices to improve the performance, scalability, and management of the product line. Cisco NX-OS Release 6.x also supports all hardware and software supported in Cisco NX-OS Release 5.1 and Cisco NX-OS Release 5.0.

Cisco NX-OS offers the following benefits:

- Cisco NX-OS runs on all Cisco data center switch platforms: Cisco Nexus 7000, Nexus 5000, Nexus 4000, Nexus 3000, Nexus 2000, and Nexus 1000V Series switches.
- Cisco NX-OS software interoperates with Cisco products that run any variant of Cisco IOS software and also with any networking operating system that conforms to common networking standards.
- Cisco NX-OS modular processes are triggered on demand, each in a separate protected memory space. Processes are started and system resources are allocated only when a feature is enabled. The modular processes are governed by a real-time preemptive scheduler that helps ensure timely processing of critical functions.
- Cisco NX-OS provides a programmatic XML interface that is based on the NETCONF industry standard. The Cisco NX-OS XML interface provides a consistent API for devices. Cisco NX-OS also provides support for Simple Network Management Protocol (SNMP) Versions 1, 2, and 3 MIBs.
- Cisco NX-OS enables administrators to limit access to switch operations by assigning roles to users. Administrators can customize access and restrict it to the users who require it.

Also see the following:

- [Cisco Nexus 3000 Series Switches](#)
- [Cisco Nexus 3100 Series Switches](#)

Cisco Nexus 3000 Series Switches

The Cisco Nexus 3000 Series switches are high-performance, high-density, ultra-low-latency Ethernet switches that provide line-rate Layer 2 and Layer 3 switching. The Cisco Nexus 3000 Series includes the following switches:

System Requirements

- The Cisco Nexus 3064 switch is a 1 RU switch that supports 48 1- or 10-Gigabit downlink ports, four Quad Small Form-Factor Pluggable (QSFP+) ports that can be used as a 40 Gigabit Ethernet port or 4 x10-Gigabit Ethernet ports, one 10/100/1000 management port, and one console port.
- The Cisco Nexus 3048 switch is a 1 rack unit (RU) switch that supports 48 10/100/1000 Ethernet server-facing (downlink) ports, four 10-Gigabit network-facing (uplink) ports, one 100/1000 management port, and one console port.
- The Cisco Nexus 3016 is a 1 RU, 16-port QSFP+ switch. Each QSFP+ port can be used as a 40-Gigabit Ethernet port or 4 x10-Gigabit Ethernet ports.

Each switch includes one or two power supply units and one fan tray module, and each switch can be ordered with either forward (port-side exhaust) airflow or reverse (port-side intake) airflow for cooling. All platforms support both AC and DC power supplies. All combinations of power (AC/DC) and airflow (forward/reverse) are available. The Cisco Nexus 3000 Series switches run the Cisco NX-OS software.

For information about the Cisco Nexus 3000 Series, see the [Cisco Nexus 3000 Series Hardware Installation Guide](#).

Cisco Nexus 3100 Series Switches

The Cisco Nexus 3100 Series switches are high-performance, high-density, ultra-low-latency Ethernet switches that provide line-rate Layer 2 and Layer 3 switching. In Cisco NX-OS Release 6.0(2)U2(2), the Cisco Nexus 3100 Series includes the Cisco Nexus 3132 and Nexus 3172 switches.

The Cisco Nexus 3172PQ switch is a 10-Gbps Enhanced Small Form-Factor Pluggable (SFP+)-based ToR switch with 48 SFP+ ports and 6 Enhanced Quad SFP+ (QSFP+) ports.

The Cisco Nexus 3172TQ switch is a 10GBASE-T switch with 48 10GBASE-T ports and 6 Quad SFP+ (QSFP+) ports.

Each SFP+ port can operate in 100-Mbps, 1-Gbps, or 10-Gbps mode, and each QSFP+ port can operate in native 40-Gbps or 4 x 10-Gbps mode. This switch is a true physical-layer-free (phy-less) switch that is optimized for low latency and low power consumption.

The Cisco Nexus 3132Q switch is a 1RU, 40-Gbps QSFP-based switch that supports 32 fixed 40-Gbps QSFP+ ports. It also has 4 SFP+ ports that can be internally multiplexed with the first QSFP port. Each QSFP+ port can operate in the default 40-Gbps mode or 4 x 10-Gbps mode, up to a maximum of 104 10-Gbps ports.

Each switch includes dual redundant power supply units, four redundant fans, one 10/100/1000 management port, and one console port. Each switch can be ordered with either forward (port-side exhaust) airflow or reverse (port-side intake) airflow for cooling. It supports both AC and DC power supplies. All combinations of power (AC/DC) and airflow (forward/reverse) are available. The Cisco Nexus 3100 Series switches run the Cisco NX-OS software.

For information about the Cisco Nexus 3100 Series, see the [Cisco Nexus 3000 Series Hardware Installation Guide](#).

System Requirements

This section includes the following topics:

- [Memory Requirements](#)
- [Hardware Supported](#)
- [Twinax Cable Support on Cisco Nexus 3000 Switches](#)
- [Cisco QSFP 40-Gbps Bidirectional Short-Reach Transceiver](#)

Memory Requirements

The Cisco NX-OS Release 6.0(2)U3(8) software requires 135 MB of flash memory.

Hardware Supported

Cisco NX-OS Release 6.0(2)U3(8) supports the Cisco Nexus 3000 Series switches. You can find detailed information about supported hardware in the Cisco Nexus 3000 Series Hardware Installation Guide.

[Table 2](#) shows the hardware supported by the Cisco NX-OS Release 6.x software. [Table 3](#) shows the hardware supported by the Cisco NX-OS 5.x releases.

[Table 4](#) shows the transceivers supported by the Cisco NX-OS Release 6.x software. [Table 5](#) shows transceivers supported by the Cisco NX-OS 5.x releases.

Table 2. Hardware Supported by Cisco NX-OS Related 6.x Software.

| Hardware | Part Number | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8) 6.0(2)U3(7) 6.0(2)U3(6) 6.0(2)U3(5) 6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1) |
|----------------------------------------------------------------------|------------------|-----------------------------------------------------------|-------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------|
| Cisco Nexus 3172TQ switch | N3K-C3172TQ-10GT | | | X |
| Cisco Nexus 3172PQ switch | N3K-C3172PQ-10GE | | X | X |
| Cisco Nexus 3132Q switch | N3K-C3132Q-40GE | | X | X |
| Cisco Nexus 3016 switch | N3K-C3016Q-40GE | X | X | X |
| Cisco Nexus 3048 switch | N3K-C3048TP-1GE | X | X | X |
| Cisco Nexus 3064-TQ switch | N3K-C3064TQ-10GT | X | X | X |
| Cisco Nexus 3064-X switch | N3K-C3064PQ-10GX | X | X | X |
| Cisco Nexus 3064-E switch | N3K-C3064PQ-10GE | X | X | X |
| Cisco Nexus 3064 switch | N3K-C3064PQ | X | X | X |
| Cisco Nexus 3048 fan module with forward airflow (port-side exhaust) | N3K-C3048-FAN | X | X | X |

System Requirements

| Hardware | Part Number | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8) 6.0(2)U3(7) 6.0(2)U3(6) 6.0(2)U3(5) 6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1) |
|---------------------------------------------------------------------------------------------------------|-------------------|-----------------------------------------------------------|-------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------|
| Cisco Nexus 3048 fan module with reverse airflow (port-side intake) | N3K-C3048-FAN-B | X | X | X |
| Cisco Nexus 3064-T 500W forward airflow (port-side exhaust) AC power supply | NXA-PAC-500W | X | X | X |
| Cisco Nexus 3064-T 500W reverse airflow (port-side intake) AC power supply | NXA-PAC-500W-B | X | X | X |
| Cisco Nexus 3064-X forward airflow (port-side exhaust) AC power supply | N3K-C3064-X-FA-L3 | X | X | X |
| Cisco Nexus 3064-X reversed airflow (port-side intake) AC power supply | N3K-C3064-X-BA-L3 | X | X | X |
| Cisco Nexus 3064-X forward airflow (port-side exhaust) DC power supply | N3K-C3064-X-FD-L3 | X | X | X |
| Cisco Nexus 3064-X forward airflow (port-side intake) DC power supply | N3K-C3064-X-BD-L3 | X | X | X |
| Cisco Nexus 3064 fan module with forward airflow (port-side exhaust); also used in the Cisco Nexus 3016 | N3K-C3064-FAN | X | X | X |
| Cisco Nexus 3064 fan module with reverse airflow (port-side intake); also used in the Cisco Nexus 3016 | N3K-C3064-FAN-B | X | X | X |
| Cisco Nexus 3000 power supply with forward airflow (port-side exhaust) | N2200-PAC-400W | X | X | X |

System Requirements

| Hardware | Part Number | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8) 6.0(2)U3(7) 6.0(2)U3(6) 6.0(2)U3(5) 6.0(2)U3(4) 6.0(2)U3(3) 6.0(2)U3(2) 6.0(2)U3(1) |
|--------------------------------------------------------------------------|------------------|-----------------------------------------------------------|-------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------|
| Cisco Nexus 3000 power supply with reverse airflow (port-side intake) | N2200-PAC-400W-B | X | X | X |
| Cisco Nexus 2000 power supply with forward airflow (port-side exhaust) | N2200-PDC-400W | X | X | X |
| Cisco Nexus 2000 DC power supply with reverse airflow (port-side intake) | N3K-PDC-350W-B | X | X | X |

Table 3. Hardware Supported by Cisco NX-OS Release 5.x Software

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|-------------------------|-----------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3016 switch | N3K-C3016Q-40GE | X | X | X | X | X | - | - |
| Cisco Nexus 3048 switch | N3K-C3048TP-1GE | X | X | X | X | - | - | - |

System Requirements

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|----------------------------------------------------------------------|------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3064-TQ switch | N3K-C3064TQ-10GT | X ¹ | - | - | - | - | - | - |
| Cisco Nexus 3064-X switch | N3K-C3064P10GX | X | X | X | - | - | - | - |
| Cisco Nexus 3064-E switch | N3K-C3064PQ-10GE | X | X | X | X | X | X | - |
| Cisco Nexus 3064 switch | N3K-C3064PQ | X | X | X | X | X | X | X |
| Cisco Nexus 3048 fan module with forward airflow (port-side exhaust) | N3K-C3048-FAN | X | X | X | X | - | - | - |

¹ Recommended release for Cisco Nexus 3064-TQ switch is Cisco NX-OS Release 5.0(3)U5(1c) or later releases.

System Requirements

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|-----------------------------------------------------------------------|-----------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3048 fan module with reverse airflow (port-side intake) | N3K-C3048-FAN-B | X | X | X | X | - | - | - |
| Nexus 3064-T 500W forward airflow (port side exhaust) AC power supply | NXA-PAC-500W | X | X | - | - | - | - | - |
| Nexus 3064-T 500 W reverse airflow (port side intake) AC power supply | NXA-PAC-500W-B | X | X | - | - | - | - | - |

System Requirements

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|------------------------------------------------------------------------|-------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3064-X forward airflow (port-side exhaust) AC power supply | N3K-C3064-X-FA-L3 | X | X | X | - | - | - | - |
| Cisco Nexus 3064-X reversed airflow (port-side intake) AC power supply | N3K-C3064-X-BA-L3 | X | X | X | - | - | - | - |
| Cisco Nexus 3064-X forward airflow (port-side exhaust) DC power supply | N3K-C3064-X-FD-L3 | X | X | X | - | - | - | - |

System Requirements

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|---------------------------------------------------------------------------------------------------------|-------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3064-X forward airflow (port-side intake) DC power supply | N3K-C3064-X-BD-L3 | X | X | X | - | - | - | - |
| Cisco Nexus 3064 fan module with forward airflow (port-side exhaust); also used in the Cisco Nexus 3016 | N3K-C3064-FAN | X | X | X | X | X | X | X |

System Requirements

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|--------------------------------------------------------------------------------------------------------|-----------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3064 fan module with reverse airflow (port-side intake); also used in the Cisco Nexus 3016 | N3K-C3064-FAN-B | X | X | X | X | X | X | X |
| Cisco Nexus 3000 power supply with forward airflow (port-side exhaust) | N2200-PAC-400W | X | X | X | X | X | X | X |

System Requirements

| Hardware | Part Number | Supported Cisco NX-OS Release | | | | | | |
|--------------------------------------------------------------------------|------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|----------------------------------------------|--------------|-----------------------------------------------------------|--------------|
| | | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2d) 5.0(3)U2(2c) 5.0(3)U2(2b) | 5.0(3)U2(2a) | 5.0(3)U2(2) 5.0(3)U2(1) 5.0(3)U1(2a) 5.0(3)U1(2) | 5.0(3)U1(1d) |
| Cisco Nexus 3000 power supply with reverse airflow (port-side intake) | N2200-PAC-400W-B | X | X | X | X | X | X | X |
| Cisco Nexus 2000 power supply with forward airflow (port-side exhaust) | N2200-PDC-400W | X | X | X | X | X | X | X |
| Cisco Nexus 2000 DC power supply with reverse airflow (port-side intake) | N3K-PDC-350W-B | X | X | X | X | X | X | X |

Table 4. Transceivers Supported by Cisco NX-OS Release 6.x Software.

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|---------------------------------------------------------------|-------------------|----------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a)) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| QSFP | | | | |
| 40GBASE-LR4 QSFP40G transceiver module (SMF) | QSFP-40G-LR4 | | | X |
| 40GBASE-CR4 QSFP+ direct-attach copper cable, 7 meters active | QSFP-H40G-ACU7M | | | X |
| 40GBASE-CR4 QSFP+ direct-attach copper cable, 8 meters active | QSFP-H40G-ACU8M | | | X |
| 40GBASE-CR4 QSFP+ direct-attach copper cable, 9 meters active | QSFP-H40G-ACU9M | | | X |
| 40GBASE-CR4 QSFP+ direct-attach copper cable, 10 m active | QSFP-H40G-ACU10M | | | X |
| 40G QSFP direct-attach active optical cable, 15 m | QSFP-H40G-AOC15M | | | X |
| QSFP to 4 x SFP 10Gbps active optical cable 15 m | QSFP-4X10G-AOC15M | | | X |
| QSFP 40G Bidirectional short-reach transceiver | QSFP-40G-SR-BD | X | X | X |
| QSFP 40G active optical cable 1 m | QSFP-H40G-AOC1M | X | X | X |
| QSFP 40G active optical cable 2 m | QSFP-H40G-AOC2M | X | X | X |
| QSFP 40G active optical cable 3 m | QSFP-H40G-AOC3M | X | X | X |
| QSFP 40G active optical cable 5 m | QSFP-H40G-AOC5M | X | X | X |
| QSFP 40G active optical cable 7 m | QSFP-H40G-AOC7M | X | X | X |
| QSFP 40G active optical cable 10 m | QSFP-H40G-AOC10M | X | X | X |

² OIR is supported for all optical modules and transceivers in Cisco NX-OS Release 6.02 and later releases.

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|---------------------------------------------------------------------------------------------|-------------------------------|----------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a)) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| QSFP to 4 x SFP 10Gbps active optical cable 1 m | QSFP-4X10G-AOC1M | X | X | X |
| QSFP to 4 x SFP 10Gbps active optical cable 2 m | QSFP-4X10G-AOC2M | X | X | X |
| QSFP to 4 x SFP 10Gbps active optical cable 3 m | QSFP-4X10G-AOC3M | X | X | X |
| QSFP to 4 x SFP 10Gbps active optical cable 5 m | QSFP-4X10G-AOC5M | X | X | X |
| QSFP to 4 x SFP 10Gbps active optical cable 7 m | QSFP-4X10G-AOC7M | X | X | X |
| QSFP to 4 x SFP 10Gbps active optical cable 10 m | QSFP-4X10G-AOC10M | X | X | X |
| Active copper splitter cable 7 m | QSFP-4x10G-AC7M ³ | X | X | X |
| Active copper splitter cable 10 m | QSFP-4x10G-AC10M ² | X | X | X |
| Active copper QSFP transceiver module 7 m | QSFP-H40G-ACU7M ² | X | X | X |
| Active copper QSFP transceiver module 10 m | QSFP-H40G-ACU10M ² | X | X | X |
| 40GBASE-CSR4 QSFP transceiver module with multifiber push-on (MPO) connector 300 m | QSFP-40G-CSR4 ² | X | X | X |
| 40GBASE-CSR4 QSFP transceiver module with MPO connector 300 m (using fiber splitter cables) | QSFP-40G-CSR4 ² | X | X | X |
| 40GBASE-SR4 QSFP transceiver module with MPO connector 100 m | QSFP-40G-SR4 ² | X | X | X |
| 40GBASE-SR4 QSFP transceiver module with MPO connector 100 m (using fiber splitter cables) | QSFP-40G-SR4 ² | X | X | X |
| 40GBASE-LR4 QSFP transceiver module with LC connector 10 km (using single mode fiber) | QSFP-40GE-LR4 | X | X | X |

³ Supported on the Cisco Nexus 3016, Cisco Nexus 3064-X, Cisco Nexus 3064-TQ, Cisco Nexus 3064, Cisco Nexus 3064-E, and all Cisco Nexus 3100 Series switches.

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|---------------------------------------------------------------|------------------------------|-----------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| QSFP to SFP/SFP+ adapter | CVR-QSFP-SFP10G | X | X | X |
| 40GBASE-CR4 passive copper cable, 1 m | QSFP-H40G-CU1M | X | X | X |
| 40GBASE-CR4 passive copper cable, 3 m | QSFP-H40G-CU3M | X | X | X |
| 40GBASE-CR4 passive copper cable, 5 m | QSFP-H40G-CU5M | X | X | X |
| QSFP to 4xSFP10G passive copper splitter cable, 1 m | QSFP-4SFP10G-CU1M | X | X | X |
| QSFP to 4xSFP10G passive copper splitter cable, 3 m | QSFP-4SFP10G-CU3M | X | X | X |
| QSFP to 4xSFP10G passive copper splitter cable, 5 m | QSFP-4SFP10G-CU5M | X | X | X |
| Revision 2 copper splitter cables 3 m | QSFP-4SFP10G-CU3 (Rev. 2) | X | X | X |
| Revision 2 copper splitter cables 5 m | QSFP-4SFP10G-CU5 (Rev. 2) | X | X | X |
| 10-Gigabit | | | | |
| 10 db attenuator | FA-920-073-12310 | | | X |
| 10GBASE-ZR SFP+ module (single-mode fiber [SMF]) ⁴ | SFP-10G-ZR ³ | | | X |
| Cisco QSFP to SFP/SFP+ Adapter (QSA) module | CVR-QSFP-SFP10G | | | X |
| Cisco QSFP to SFP/SFP+ Adapter (QSA) module with 10GBASE-DWDM | QSA w/ DWDM | | | X |

⁴ Supported on the Cisco Nexus 3064-E and Cisco Nexus 3064-X switches.

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|--------------------------------------------------------------------------------|-------------------|----------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a)) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| 10GBASE-DWDM 1558.98 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-58.98 | | | X |
| 10GBASE-DWDM 1539.77 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-39.77 | | | X |
| 10GBASE-DWDM 1561.41 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-61.41 | | | X |
| 10GBASE-DWDM 1542.94 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-42.94 | | | X |
| 10GBASE-DWDM 1553.33 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-53.33 | | | X |
| 10GBASE-DWDM 1537.40 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-37.40 | | | X |
| 10GBASE-DWDM 1542.14 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-42.14 | | | X |
| 10GBASE-DWDM 1556.55 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-56.55 | | | X |
| 10GBASE-DWDM 1550.92 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-50.92 | | | X |
| 10GBASE-DWDM 1531.12 nm SFP+ (100-GHz ITU grid) | DWDM-SFP10G-31.12 | | | X |
| 10GBASE-DWDM long-range transceiver module 80 km with single mode duplex fiber | DWDM-SFP10G-C | | | X |
| 10GBASE-DWDM long-range transceiver module 80 km with single mode duplex fiber | DWDM-SFP10G | X | X | X |
| 10GBASE-SR SFP+ module (multimode fiber [MMF]) | SFP-10G-SR | X | X | X |

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|-----------------------------------------------------------------|-------------------------------|-----------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| 10GBASE-LR SFP+ module (single-mode fiber [SMF]) | SFP-10G-LR | X | X | X |
| 10GBASE-ER SFP+ module (single-mode fiber [SMF]) | SFP-10G-ER | X | X | X |
| 10GBASE-ZR SFP+ module (single-mode fiber [SMF]) | SFP-10G-ZR ² | X | X | X |
| 10GBASE-DWDM SFP+ module (single-mode fiber [SMF]) ³ | 10-2767-01 ³ | X | X | X |
| Active Twinax cable assembly, 7 m | SFP-H10GB-ACU7M | X | X | X |
| Active Twinax cable assembly, 10 m | SFP-H10GB-ACU10M | X | X | X |
| 10GBASE-CU SFP+ cable 1 m (Twinax cable) | SFP-H10GB-CU1M | X | X | X |
| 10GBASE-CU SFP+ cable 1.5 m (Twinax cable) | SFP-H10GB-CU1-5M | X | X | X |
| 10GBASE-CU SFP+ cable 2 m (Twinax cable) ⁴ | SFP-H10GB-CU2M ⁵ | X | X | X |
| 10GBASE-CU SFP+ cable 3 m (Twinax cable) | SFP-H10GB-CU3M | X | X | X |
| 10GBASE-CU SFP+ cable 5 m (Twinax cable) | SFP-H10GB-CU5M | X | X | X |
| 10GBASE-CU SFP+ cable 2.5 m (Twinax cable) ⁴ | SFP-H10GB-CU2-5M ⁴ | X | X | X |
| Active optical cable 1 m | SFP-10G-AOC1M ⁵ | X | X | X |
| Active optical cable 2 m | SFP-10G-AOC2M | X | X | X |
| Active optical cable 3 m | SFP-10G-AOC3M ⁵ | X | X | X |
| Active optical cable 5 m | SFP-10G-AOC5M ⁵ | X | X | X |

⁵ Supported on the Cisco Nexus 3048, Cisco Nexus 3064-X, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a)) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| Active optical cable 7 m | SFP-10G-AOC7M ⁵ | X | X | X |
| Active optical cable 10 m | SFP-10G-AOC10M | X | X | X |
| 1-Gigabit Ethernet | | | | |
| Gigabit Ethernet SFP, LC connector SX transceiver (MMF) | GLC-SX-MMD Note: GLC-SX-MMD is supported on all Cisco Nexus 3000 Series Switches except for the Cisco Nexus 3064-T. Please refer to the comparability matrix for all the supported platforms. | | | X |
| Gigabit Ethernet SFP, LC connector LX/LH transceiver (SMF) | GLC-LH-SMD | | | X |
| Cisco QSFP to SFP/SFP+ Adapter (QSA) module with GLC-T | QSA w/ GLC-T | | | X |
| 1000BASE-T SFP | GLC-TE | | | X |
| Cisco QSFP to SFP/SFP+ Adapter (QSA) module with GLC-TE | QSA w/ GLC-TE | | | X |
| Cisco QSFP to SFP/SFP+ Adapter (QSA) module with SFP-GE-T | QSA w/SFP-GE-T | | | X |
| 1000Base-BX fiber transceiver | GLC-BX-D ⁵ | X | X | X |
| 1000Base-BX fiber transceiver | GLC-BX-U ⁵ | X | X | X |
| 1000BASE-EX fiber transceiver module, SMF | GLC-EX-SMD | X | X | X |

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|-----------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a)) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| Gigabit Ethernet SFP, LC connector LX/LH transceiver (SMF) | GLC-LH-SM ⁵ | X | X | X |
| 1000BASE-LX/LH SFP transceiver module for MMF and SMF | GLC-LH-SMD ⁵ | X | X | X |
| Gigabit Ethernet SFP, LC connector SX transceiver (MMF) | GLC-SX-MM ⁴ | X | X | X |
| Gigabit Ethernet SFP, LC connector SX transceiver (MMF) | GLC-SX-MMD Note: GLC-SX-MMD is supported on all Cisco Nexus 3000 Series Switches except for the Cisco Nexus 3064-T. Please refer to the comparability matrix for all the supported platforms. | X | X | X |
| 1000BASE-T SFP ⁶ | GLC-T ⁵ | X | X | X |
| 1000BASE-ZX fiber transceiver module, SMF, 1550 nm | GLC-ZX-SMD | X | X | X |
| 1000BASE-T SFP transceiver module with extended operating temperature range | SFP-GE-T ⁵ | X | X | X |
| 100-Mbps Ethernet | | | | |

System Requirements

| Transceivers ² | Part Number | Supported Cisco NX-OS Release | | |
|-------------------------------------------------------------------------------|-------------------------|----------------------------------------------------------------|-------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------|
| | | 6.0(2)U1(3) 6.0(2)U1(2) 6.0(2)U1(1a)) 6.0(2)U1(1) | 6.0(2)U2(5) 6.0(2)U2(4) 6.0(2)U2(3) 6.0(2)U2(2) 6.0(2)U2(1) | 6.0(2)U3(8)) 6.0(2)U3(7)) 6.0(2)U3(6)) 6.0(2)U3(5)) 6.0(2)U3(4)) 6.0(2)U3(3)) 6.0(2)U3(2)) 6.0(2)U3(1)) |
| 100BASE-FX SFP module for Gigabit Ethernet ports GLC-GE-100FX ⁶ | 10-2019-02 ⁷ | | | 100BASE-FX SFP module for Gigabit Ethernet ports GLC-GE-100FX |

Note: The Cisco Nexus 3000 supports 1,000 and 10,000 speeds while using SFP+ with Cisco QSA [CVR-QSFP-SFP10G] (and a maximum of 6 QSAs). The 100 speed is not supported on the SFP+ along with QSA, but using any speed 100 is supported on the SFP+.

Table 5. Transceivers Supported by Cisco NX-OS Release 5.x Software.

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1)) | 5.0(3)U3(2b)) 5.0(3)U3(2a)) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c)) 5.0(3)U2(2b)) 5.0(3)U2(2a)) 5.0(3)U2(2) | 5.0(3)U2(1)) | 5.0(3)U1(2) 5.0(3)U1(2a)) | 5.0(3)U1(1a)) 5.0(3)U1(1b)) 5.0(3)U1(1d)) |
|--------------|-------------|-------------------------------------------------------------------------------------------------------------|------------------|----------------------------------------------------------------------|----------------------------------------------------------------------------|------------------|----------------------------------|-------------------------------------------------------------|
| QSFP | | | | | | | | |

⁶ Supported on the Cisco Nexus 3064, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches. For the GLC-GE-100FX, only part number 10-2019-02 is supported.

⁷ Supported on the Cisco Nexus 3048, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches. Not supported on Cisco Nexus 3132Q-X.

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|---------------------------------------------------------------|-------------------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| Active copper splitter cable 7 m | QSFP-4x10G-AC7M ⁸ | X | – | – | – | – | – | – |
| Active copper splitter cable 10 m | QSFP-4x10G-AC10M ⁸ | X | – | – | – | – | – | – |
| Active copper QSFP transceiver module 7 m | QSFP-H40G-ACU7M ⁸ | X | – | – | – | – | – | – |
| Active copper QSFP transceiver module 10 m | QSFP-H40G-ACU10M ⁸ | X | – | – | – | – | – | – |
| 40GBASE-CSR4 QSFP transceiver module with MPO connector 300 m | QSFP-40G-CSR4 ⁸ | X | X | – | – | – | – | – |

⁸ Supported on the Cisco Nexus 3016, Cisco Nexus 3064-X, Cisco Nexus 3064-TQ, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|---------------------------------------------------------------------------------------------|----------------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| 40GBASE-CSR4 QSFP transceiver module with MPO connector 300 m (using fiber splitter cables) | QSFP-40G-CSR4 ⁸ | X | X | - | - | - | - | - |
| 40GBASE-SR4 QSFP transceiver module with MPO connector 100 m | QSFP-40G-SR4 ⁸ | X | X | X | X | X | X | X |
| 40GBASE-SR4 QSFP transceiver module with MPO connector 100 m (using fiber splitter cables) | QSFP-40G-SR4 ⁸ | X | X | X | X | X | X | X |
| 40GBASE-CR4 passive copper cable, 1 m | QSFP-H40G-CU1M | X | X | X | X | X | X | X |

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|-----------------------------------------------------|-------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| 40GBASE-CR4 passive copper cable, 3 m | QSFP-H40G-CU3M | X | X | X | X | X | X | X |
| 40GBASE-CR4 passive copper cable, 3 m | QSFP-H40G-CU3M | X | X | X | X | X | X | X |
| 40GBASE-CR4 passive copper cable, 5 m | QSFP-H40G-CU5M | X | X | X | X | X | X | X |
| QSFP to 4xSFP10G passive copper splitter cable, 1 m | CU5M CU1M | X | X | X | X | X | X | X |
| QSFP to 4xSFP10G passive copper splitter cable, 3 m | QSFP-4SFP10G-CU3M | X | X | X | X | X | X | X |
| QSFP to 4xSFP10G passive copper splitter cable, 5 m | QSFP-4SFP10G-CU5M | X | X | X | X | X | X | X |

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|--------------------------------------------------|---------------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| Revision 2 copper splitter cables 3 m | QSFP-4SFP10G-CU3 (Rev. 2) | X | - | - | - | - | - | - |
| Revision 2 copper splitter cables 5 m | QSFP-4SFP10G-CU5 (Rev. 2) | X | - | - | - | - | - | - |
| 10-Gigabit | | | | | | | | |
| 10GBASE-SR SFP+ module (multimode fiber [MMF]) | SFP-10G-SR | X | X | X | X | X | X | X |
| 10GBASE-LR SFP+ module (single-mode fiber [SMF]) | SFP-10G-LR | X | X | X | X | X | X | X |
| 10GBASE-ER SFP+ module (single-mode fiber [SMF]) | SFP-10G-ER | X | X | X | X | X | X | X |

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|-----------------------------------------------------------------|-------------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| 10GBASE-ZR SFP+ module (single-mode fiber [SMF]) ⁹ | SFP-10G-ZR ⁹ | X | X | X | – | – | – | – |
| 10GBASE-DWDM SFP+ module (single-mode fiber [SMF]) ⁹ | 10-2767-01 ⁹ | X | X | X | – | – | – | – |
| 10GBASE-CU SFP+ cable 1 m (Twinax cable) | SFP-H10GB-CU1M | X | X | X | X | X | X | X |
| 10GBASE-CU SFP+ cable 3 m (Twinax cable) | SFP-H10GB-CU3M | X | X | X | X | X | X | X |
| 10GBASE-CU SFP+ cable 5 m (Twinax cable) | SFP-H10GB-CU5M | X | X | X | X | X | X | X |

⁹ Supported on the Cisco Nexus 3064-E and Cisco Nexus 3064-X switches.

System Requirements

| Transceiver s | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|----------------------------------------------------------------------------------|-----------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|-----------------|--------------------------------------------------------------------|-------------------------------------------------------------------------|-----------------|---------------------------------|----------------------------------------------------------|
| 10GBASE- CU SFP+ cable 2 m (Twinax cable) ³ ¹⁰ | SFP- H10GB- CU2M ¹⁰ | X | X | - | - | - | - | - |
| 10GBASE- CU SFP+ cable 2.5 m (Twinax cable) ¹⁰ | SFP- H10GB- CU2-5M ³ ¹⁰ | X | X | - | - | - | - | - |
| Active optical cable 1 m | SFP-10G- AOC1M ¹¹ | X | - | - | - | - | - | - |
| Active optical cable 3 m | SFP-10G- AOC3M ¹¹ | X | - | - | - | - | - | - |
| Active optical cable 5 m | SFP-10G- AOC5M ¹¹ | X | - | - | - | - | - | - |
| Active optical cable 7 m | SFP-10G- AOC7M ¹¹ | X | - | - | - | - | - | - |
| 1-Gigabit Ethernet | | | | | | | | |
| 1000BASE- T SFP ¹¹ | GLC-T ¹¹ | X | X | X | X | X | X | X |

¹⁰ Supported on the Cisco Nexus 3048, Cisco Nexus 3064-X, Cisco Nexus 3064, and Cisco Nexus 3064-E switches.¹¹ Supported on the Cisco Nexus 3048, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches.

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| Gigabit Ethernet SFP, LC connector SX transceiver (MMF) | GLC-SX-MM ¹⁰ | X | X | X | X | X | X | X |
| Gigabit Ethernet SFP, LC connector SX transceiver (MMF) | GLC-SX-MMD Note: GLC-SX-MMD is supported on all Cisco Nexus 3000 Series Switches except for the Cisco Nexus 3064-T. Please refer to the comparability matrix for all the supported platforms. | X | X | – | – | – | – | – |
| Gigabit Ethernet SFP, LC connector LX/LH transceiver (SMF) | GLC-LH-SM ¹¹ | X | X | X | X | X | X | X |

System Requirements

| Transceivers | Part Number | 5.0(3)U5(1f) 5.0(3)U5(1e) 5.0(3)U5(1d) 5.0(3)U5(1c) 5.0(3)U5(1b) 5.0(3)U5(1a) 5.0(3)U5(1) | 5.0(3)U4(1) | 5.0(3)U3(2b) 5.0(3)U3(2a) 5.0(3)U3(2) 5.0(3)U3(1) | 5.0(3)U2(2c) 5.0(3)U2(2b) 5.0(3)U2(2a) 5.0(3)U2(2) | 5.0(3)U2(1) | 5.0(3)U1(2) 5.0(3)U1(2a) | 5.0(3)U1(1a) 5.0(3)U1(1b) 5.0(3)U1(1d) |
|-----------------------------------------------------------------------------|------------------------------------------|-------------------------------------------------------------------------------------------------------------|-------------|------------------------------------------------------------|-------------------------------------------------------------|-------------|-----------------------------|----------------------------------------------|
| 1000BASE-LX/LH SFP transceiver module for MMF and SMF | GLC-LH-SMD ¹¹ | X | – | – | – | – | – | – |
| 1000Base-BX fiber transceiver | GLC-BX-U ¹¹ | X | – | – | – | – | – | – |
| 1000Base-BX fiber transceiver | GLC-BX-D ¹¹ | X | – | – | – | – | – | – |
| 1000BASE-T SFP transceiver module with extended operating temperature range | SFP-GE-T ¹¹ | X | – | – | – | – | – | – |
| 100-Mbps Ethernet | | | | | | | | |
| 100BASE-FX SFP module for Gigabit Ethernet ports GLC-GE-100FX ¹² | 10-2019-02 ¹² GLC-GE-100FX | X | X | X | X | X | X | X |

¹² Supported on the Cisco Nexus 3064, Cisco Nexus 3064-E, and Cisco Nexus 3064-X switches. For the GLC-GE-100FX, only part number 10-2019-02 is supported.

Twinax Cable Support on Cisco Nexus 3000 Switches

Starting with Cisco Release NX-OS 5.0(3)U1(1), the following algorithm is used to detect copper SFP+ twinax, QSFP+ twinax, and QSFP+ splitter cables on Cisco Nexus 3000 Series switches.

If the attached interconnect (transceiver) is a copper SFP+ twinax or QSFP+ twinax cable:

- Verify the transceiver SPROM to match the Cisco magic code.
- If the check succeeds, bring up the interface. Otherwise, print the following warning message appears stating that a non-Cisco transceiver is attached and that you should try to bring up the port.

```
2009 Oct 9 01:46:42 switch %ETHPORT-3-IF_NON-CISCO_TRANSCEIVER: Non-Cisco transceiver on interface Ethernet1/18 is detected.
```

If the attached transceiver is a QSFP+ splitter cable, then no special check is performed. The Cisco NX-OS software tries to bring up the port.

The following disclaimer applies to non-Cisco manufactured and non-Cisco certified QSFP copper splitter cables:

If a customer has a valid support contract for Cisco Nexus switches, Cisco TAC will support twinax cables that are a part of the compatibility matrix for the respective switches. However, if the twinax cables are not purchased through Cisco, a customer cannot return these cables through an RMA to Cisco for replacement.

If a twinax cable that is not part of the compatibility matrix is connected into a system, Cisco TAC will still debug the problem, provided the customer has a valid support contract on the switches. However TAC may ask the customer to replace the cables with Cisco qualified cables if there is a situation that points to the cables possibly being faulty or direct the customer to the cable provider for support. Cisco TAC cannot issue an RMA against uncertified cables for replacement.

Cisco QSFP 40-Gbps Bidirectional Short-Reach Transceiver

The Cisco QSFP 40-Gbps Bidirectional (BiDi) transceiver is a short-reach pluggable optical transceiver with a duplex LC connector for 40-GbE short-reach data communications and interconnect applications by using multimode fiber (MMF). The Cisco QSFP 40-Gbps BiDi transceiver offers a solution that uses existing duplex MMF infrastructure for 40-GbE connectivity. With the Cisco QSFP 40-Gbps BiDi transceiver, customers can upgrade their network from 10-GbE to 40-GbE without incurring any fiber infrastructure upgrade cost. The Cisco QSFP 40-Gbps BiDi transceiver can enable 40-GbE connectivity in a range of up to 100 meters over OM3 fiber, which meets most data center reach requirements. It complies with the Multiple Source Agreement (MSA) QSFP specification and enables customers to use it on all Cisco QSFP 40-Gbps platforms and achieve high density in a 40-GbE network. It can be used in data centers, high-performance computing (HPC) networks, enterprise and distribution layers, and service provider transport applications.

New and Changed Information

This section lists the new and changed features and includes the following topics:

- [New Supported Hardware](#)
- [New Software Features](#)

New Supported Hardware

Cisco NX-OS Release 6.0(2)U3(8) does not include new hardware.

New Software Features

All Cisco Nexus 3000 Series switches are supported by Cisco NX-OS Release 6.0(2)U3(8). Cisco NX-OS interoperates with any networking operating system, including Cisco IOS software, that conforms to the networking standards listed in the product data sheet. This release does not include any new software features.

Upgrade and Downgrade Guidelines

- Ensure that you use the install all command to upgrade the switch software from one Cisco NX-OS release to another.
- Cisco Nexus 3000 Series switches that use software versions older than Cisco NX-OS Release 5.0(3)U5(1) need to be updated to Cisco NX-OS Release 5.0(3)U5(1) before they are upgraded to Cisco NX-OS Release 6.0(2).
- Cisco NX-OS Release 5.0(3)U3(1) does not support a software upgrade from Cisco NX-OS Release 5.0(3)U2(2c). If you want to upgrade through this path, see [CSCty75328](#) for details about how to work around this issue.

Note: It is recommended that you upgrade to Cisco NX-OS Release 6.0(2)U3(8) by using Cisco NX-OS install procedures.

- In Cisco NX-OS Release 5.0(3)U3(1), support for IPv6 has been added in Control Plane Policing (CoPP). To enable redirection of IPv6 control packets to the CPU, you must configure IPv6 CoPP on the system. Entering the write erase command on a device that runs Release 5.0(3)U3(1) automatically applies CoPP on the device and ensures that all IPv4 and IPv6-related CoPP configuration is set up correctly.
- If you upgrade from a Cisco NX-OS release that does not support the CoPP feature to a release that does support the CoPP feature, you must run the setup utility after the upgrade to enable CoPP on the device.
- If you upgrade from Cisco NX-OS Release 5.0(3)U2(2), which supports the CoPP feature, to Cisco NX-OS Release 5.0(3)U3(1), which adds CoPP classes for IPv6 support, you must run the setup script to enable the IPv6 CoPP feature on the device.
- In Cisco NX-OS Release 6.0(2)U2(2), the default interface name in LLDP MIB is in short form. To make it long form, you must set lldp portid-subtype to 1. In Cisco NX-OS Release 6.0(2)U2(3), this behavior was reversed. The default interface name in LLDP MIB is now in long form. To make it short form, you must set lldp portid-subtype to 0.
- If you have set lldp port-subtype to 1 and you are upgrading to Cisco NX-OS Release 6.0(2)U2(4), ensure that you set lldp port-subtype to 0.

Limitations

The following are the known limitations for Cisco NX-OS Release 6.0(2)U3(8):

- The lldp tlv-set vlan command must be run on Layer 2 ports only. If you run this command on Layer 3 ports, this configuration will be ignored while determining the mgmt IP address for LLDP mgmt TLV. However, the

Limitations

configuration will not be removed. When the port layer mode is changed to Layer 2 again, this configuration will be considered again (See [CSCuo03279](#)).

- During congestion, when traffic for priority levels 1 and 2 takes up all the available port bandwidth, all priority level 3 traffic is dropped even though the priority level 3 queue is configured with a shaper that has minimum guarantee.

To provide the priority level 3 queue with some bandwidth, apply max shaper values, which are less than the total port bandwidth on priority level 1 and priority level 2 queues. (See [CSCum99198](#)).

- When configuring breakout or breakin on a range of ports, the following behavior is always observed (See [CSCun44231](#)):
 - Breakout or breakin takes 2-3 minutes if it is done on all QSFP ports simultaneously using the interface range command.
This does not have a workaround.
 - Running the speed 40000 command on an interface range of ports to breakin to 40G mode displays an error message:

```
switch(config)# interface Ethernet 1/49-54
```

```
switch(config-if-range)# speed 40000
```

```
ERROR: Ethernet1/49-13, Ethernet1/50-14, Ethernet1/51-15, Ethernet1/52-16, Ethernet1/53-17,
Ethernet1/54-18: Configuration does not match the port capability
```

Interface ranges such as interface ethernet1/49-54 are not supported on QSFP ports with breakout mode. It will behave inconsistently if used. This is applicable for Cisco Nexus 3132, 3172PQ and 3172TQ switches.

However, interface range can be used as follows:

When in 40G mode,

```
switch(config)# int e1/49,e1/50,e1/51,e1/52,e1/53,e1/54
```

```
switch(config-if-range)
```

When in 10G mode,

```
switch(config)#
```

```
switch(config)# int eth1/49/1-4,eth1/50/1-4
```

- On Nexus 3172, whenever you change the portmode from 72x10G to 48x10G+breakout6x40G mode, all QSFP ports get converted to 4x10G breakout mode automatically (See [CSCun46788](#)).

To get back to the 40G breakin mode, run the speed 40000 command on the QSFP ports.

- Flows are created for VLANs that do not exist on the OVA via the controller. The OVA accepts these flows instead of rejecting them (See [CSCul69881](#)).

Caveats

- OSPF over vPC and BFD with OSPF are supported on Cisco Nexus 3000 and 3100 Series switches. However, BFD with OSPF over vPC peer links is not currently supported (See [CSCtu87075](#)).
- MPLS stripping is not supported on Cisco NX-OS Release 6.0(2)U3(8).
- In Cisco NX-OS Release 6.0(2)U3(8), Cisco Nexus 3100 Series switches do not support PTP.
- Link Level Flow Control (LLFC) is not supported on Cisco Nexus 3000 series and Cisco Nexus 3100 series switches.

Caveats

The open and resolved bugs for this release are accessible through the Cisco Bug Search Tool. This web-based tool provides you with access to the Cisco bug tracking system, which maintains information about bugs and vulnerabilities in this product and other Cisco hardware and software products.

Note: You must have a Cisco.com account to log in and access the [Cisco Bug Search Tool](#). If you do not have one, you can [register for an account](#).

For more information about the Cisco Bug Search Tool, see the Bug Search Tool Help & FAQ.

- [Resolved Bugs in this Release](#)
- [Open Bugs for this Release](#)
- [Known Behaviors for this Release](#)

Resolved Bugs in this Release

[Table 6](#) lists descriptions of resolved bugs in Cisco NX-OS Release 6.0(2)U3(8). You can use the record ID to search [Cisco Bug Search Tool](#) for details about the bug.

Table 6 Cisco NX-OS Release 6.0(2)U3(8) – Resolved Bugs

| Record Number | Resolved Bug Headline |
|----------------------------|-----------------------------------------------------------------|
| CSCut42930 | The neutron_usd process crashes after upgrading to 6.0(2)U3(7). |
| CSCut42940 | No is core found after neutron_usd crashes. |
| CSCut70482 | bcm_usd may crash on fast-reload and abort upgrade. |

Open Bugs for this Release

[Table 7](#) lists descriptions of open bugs in Cisco NX-OS Release 6.0(2)U3(8). You can use the record ID to search the [Cisco Bug Search Tool](#) for details about the bug.

Table 7 Cisco NX-OS Release 6.0(2)U3(8) –Open Bugs

| Record Number | Resolved Bug Headline |
|----------------------------|--------------------------------------------------------------------------------------------------------------------------|
| CSCuj10855 | show tunnel int # is not showing in/out tunnel traffic statistics. |
| CSCun19114 | Port channel members flapping on peer reload in VPC on Cisco Nexus 3000 Series switches. |
| CSCun74653 | RIP neighbor is coming up even after shut on RIP process after system reboot. |
| CSCun98182 | Overwrite should not happen when mode OpenFlow or tap is given to interface. |
| CSCuo64647 | Input type queuing policy errors out on configuration replay from file. |
| CSCuo98834 | VTY ACLs are not shown in startup after upgrade from Cisco NX-OS Release 6.0(2)U1(x) to Cisco NX-OS Release 6.0(2)U3(1). |

Known Behaviors for this Release

Large core files are split into 3 or more files. For example:

- 1405964207_0x101_fwm_log.3679.tar.gzaa
- 1405964207_0x101_fwm_log.3679.tar.gzab
- 1405964207_0x101_fwm_log.3679.tar.gzac

To decode the multiple core files, first club the files to a single file:

```
$ cat 1405964207_0x101_fwm_log.3679.tar.gz* > 1405964207_0x101_fwm_log.3679.tar.gz
```

MIB Support

The Cisco Management Information Base (MIB) list includes Cisco proprietary MIBs and many other Internet Engineering Task Force (IETF) standard MIBs. These standard MIBs are defined in Requests for Comments (RFCs). To find specific MIB information, you must examine the Cisco proprietary MIB structure and related IETF-standard MIBs supported by the Cisco Nexus 3000 Series switch. The MIB Support List is available at the following FTP sites:

<ftp://ftp.cisco.com/pub/mibs/supportlists/nexus3000/Nexus3000MIBSupportList.html>

Related Documentation

Documentation for the Cisco Nexus 3000 Series Switch is available at the following URL:

http://www.cisco.com/en/US/products/ps11541/tsd_products_support_series_home.html

The documentation set is divided into the following categories:

Release Notes

Documentation Feedback

The release notes are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_release_notes_list.html

Installation and Upgrade Guides

The installation and upgrade guides are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_installation_guides_list.html

Command References

The command references are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_command_reference_list.html

Technical References

The technical references are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/prod_technical_reference_list.html

Configuration Guides

The configuration guides are available at the following URL:

http://www.cisco.com/en/US/products/ps11541/products_installation_and_configuration_guides_list.html

Error and System Messages

The system message reference guide is available at the following URL:

http://www.cisco.com/en/US/products/ps11541/products_system_message_guides_list.html

Documentation Feedback

To provide technical feedback on this document, or to report an error or omission, please send your comments to nexus3k-docfeedback@cisco.com. We appreciate your feedback.

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the **monthly What's New in Cisco Product Documentation, which also lists all new and revised Cisco technical documentation**, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

© 2015 Cisco Systems, Inc. All rights reserved.