

اھھالص او لوصولا ۃطقن عاطخاً فاشکتسا مکحت ۃدھویلإ مضنت ال يتلا

تايي وتحمل

[قىمدقمل](#)

[قىس اس ألا تابل طتم](#)

[تابل طتم](#)

[قىمدختس مل اتانوكم](#)

[تاجال طص ال](#)

[قىس اس أ تامولع](#)

[اھھالص او عاطخاً فاشكتسا ۃيمىزراوچ](#)

[قلص تاذ تامولع](#)

ۃمدقمل

حضويو show ap join stats Cisco Wireless AireOS مکحتلا ۃدھویف رماو دنتسمل اذه فصي لاعف لكشب اهم ادختسا ۃيفيك.

ۃيىس اس ألا تابل طتم

تابل طتم

دنتسمل اذهل ۃصالخ تابل طتم دجوت ال.

ۃمدختس مل اتانوكم

رمايىب يف ۃدوچوملا ۃزهجألا نم دنتسمل اذه يف ۃدراؤلا تامولع ملعاشنا مرتناك اذا .(يىضارتغا) حوسمم نىوكتب دنتسمل اذه يف ۃمدختس مل ۃزهجألا عيمج تأدبا رمايىل لمتحمل ريا ثأتلل كمهف نم دكأتف ،ليغشتلا ديق كتكبش.

تاجال طص ال

تاجال طصا لوح تامولع مل ا نم ديزم ىلع لوصح للل ۃينقتلا Cisco تاجيىملت تاجال طصا عجار تادنتسمل ا.

ۃيىس اس أ تامولع

ۃدھویف show ap ۃدي دجل ا لوصولا ۃطقن مامضنا رماو لوح تامولع دنتسمل اذه مدقى عجا ،تامولع مل ا نم ديزمل .لاعف لكشب اهم ادختسا ۃيفيك حضويو 4.2.61.0 رادص إلا مکحتلا

فڪبش مڪحت ڏڌو ۾ لامضنٽ ال Lightweight عضولائي فلوض و ظقون ئاطخاً فاشڪتساً ۾ لامدعا ببس ب لاعف لڪشب اهحالص او (AP) لوضولما ظقون ئاطخاً فاشڪتساً ال ڦيڪلس ال ڦيلجم جاتحت تنا، مڪحت زاهجلا ۾ طبر ap لامسري ال نا. مڪحت ڏڌو ۾ ap لامضنما لامضنما ap لاميف ىرحتي نا.

نم ڏڌاً رادص ال 4.2.61 نم (WLC) مڪحتلا ڏڌو تارادصا عيمج ىلع دنتسملا اذه قبطنی 7.2.103.

تامولعم ماسقاً دع ب مڪحتلا ڏڌو ٺڌت يتلما ڦفلتخملما ئاطخاً تاجرم نم ديدعلما ڏڌوت اهحالص او ڦيمزراوخلا ئاطخاً فاشڪتساً او ڦيفلخلا.


يتلما لوضولما طاقن عيمج بقعيتب نآلا مڪحتلا ڏڌو موقيت، 4.2.61.0، رادص ال مڪحتلا ڏڌو ڦيف بقعيتي امك. فاشڪتساً ادر اهيلا لسرت يتلما لوضولما طاقن فاشڪتساً بـCLI لسرت رم 2 کانه. ال ما ڦهجان تناك اذا ام و مڪحتلا ڏڌو ۾ مامضنالا لواحت يتلما (AP) لوضولما طاقن ڦطقن ئاطخاً فاشڪتساً ڦيف ڦدعاسمـلـلـ مـڪـحـتـلـاـ ڏـڌـوـ ڦـڍـوـ ڦـڍـوـ ڦـڍـوـ (SSH) وأ مڪحت ڏڌو: مڪحتلا ڏڌو ۾ مامضنالا ڦيف لوضولما ڦطقن لشفت نا نكمي اذامل اهحالص او لوضولما

<#root>

```
show ap join stats summary [all | AP_Mac_Address]
show ap join stats detail <AP_Mac_Address>
```

اهحالص او ئاطخاً فاشڪتساً ڦيمزراوخ

ڏڌو ۾ ماضنٽ ال يتلما لوضولما طاقن ڦفرعمل all show ap join stats summary رم ال مدخـتـسـاـ ضـرعـلـاـ ڦـلـاـ لـوضـولـاـ ڦـطـقـنـ مـامـضـنـاـ تـالـاـحـ ڦـمـئـاـقـ ڦـيـفـ لـوضـولـاـ ڦـطـقـنـ جـارـدـاـ مـتـيـ. مـڪـحـتـلـاـ فـاشـڪـتـسـاـ بـCLIـ لـزـاهـجـ مـلـتـسـيـ نـأـ درـجـمـبـ.



طبر تالاح ۆمئاقد نم لوصولـا ۆطقـن ۆلـا زـاـب اـدـبـا مـكـحـتـلـا ۆـدـحـوـ مـوقـتـ الـ: ۆـظـحـاـلـمـ
ۆـلـشـافـلـا لـوـصـوـلـا طـاـقـنـ تـلـواـجـ ، تـالـاـحـلـا ضـعـبـ يـفـ . مـكـحـتـلـا ۆـدـحـوـ دـيـهـمـتـ ۆـدـاعـ! مـتـيـ ىـتـحـ
رـمـأـلـا مـدـخـتـسـأـ . اـمـامـتـ ۆـلـصـتـمـ رـيـغـ اـهـنـأـ وـأـ مـوـيـ نـمـ رـثـكـأـلـ مـاـمـضـنـالـاـ
نـمـ رـيـخـأـلـا مـاـمـضـنـالـاـ بـلـطـوـ رـيـخـأـلـاـ فـاـشـتـكـالـاـ بـلـطـ لـاسـرـاـ مـتـ ىـتـمـ ۆـفـرـعـمـلـ ۆـطـقـنـ
مـكـحـتـلـا ۆـدـحـوـبـ لـاـصـتـالـاـ تـدـقـفـ دـقـ لـوـصـوـلـاـ ۆـطـقـنـ تـنـاـكـ اـذـاـمـ دـيـدـحـتـلـ لـوـصـوـلـاـ ۆـطـقـنـ
ىـرـخـأـ مـكـحـتـ ۆـدـحـوـىـلـاـ اـهـلـقـنـ مـتـ اـمـبـرـ وـأـ.

تابـلـطـ مـكـحـتـلـاـ زـاـجـ اـهـنـمـ مـلـتـسـاـ يـتـلـاـ لـوـصـوـلـاـ طـاـقـنـلـ يـلـامـجـاـلـاـ دـدـعـلـاـ جـاتـنـإـلـاـ يـطـعـيـ
الـ: مـأـ مـكـحـتـلـاـ ۆـدـحـوـبـ اـيـلـاحـ ۆـلـصـتـمـ هـذـهـ لـوـصـوـلـاـ طـاـقـنـ تـنـاـكـ اـذـاـمـ درـسـيـ مـثـ ، فـاـشـتـكـاـ

<#root>

(Cisco Controller) >

```
show ap join stats summary all

Number of APs..... 3
00:0b:85:1b:7c:b0..... Joined
00:12:44:bb:25:d0..... Joined
```

```
00:13:19:31:9c:e0..... Not joined
```

طبر ap ضرعلا تلمعتسا ،يقالتي مل نوكـي نـا ap لـا نـم نـاونـع MAC لـا تـنـأـيـقـلـتـيـنـاـمـلـشـفـلـلـبـبـسـوـطـبـرـرـخـآـفـشـتـكـيـنـأـ**ـةـصـالـخـ**.

```
<#root>
```

```
(Cisco Controller) >
```

```
show ap join stats summary 00:14:f2:63:12:50

Is the AP currently connected to controller..... Yes
Time at which the AP joined this controller last time...
Jan 24 12:21:32.414
Type of error that occurred last.....
AP got or has been disconnected
Reason for error that occurred last.....
Timed out while waiting for ECHO response from the AP
Time at which the last join error occurred.....
Jan 24 12:21:14.751
```

تابـلـطـوـمـامـضـنـاـلـاـتـابـلـطـوـفـاشـتـكـاـلـاـتـابـلـطـلـوـحـةـيـلـيـصـفـتـتـاـمـوـلـعـمـدـيـرـتـتـنـكـاـذـاـمـىـلـاـاضـيـأـرـمـأـلـاـاـذـهـرـيـشـيـ.ـشـوـاـپـجـسـتـاـلـاـمـدـخـتـسـأـ،ـنـيـوـكـتـلـاـبـلـطـىـرـتـاـلـاـهـنـكـلـوـاـلـاـمـأـطـقـفـلـوـصـوـلـاـةـطـقـنـنـمـفـاشـتـكـاـبـلـطـىـرـتـمـكـحـتـلـاـةـدـحـوـتـنـاـكـاـذـاـمـامـضـنـاـ.

```
<#root>
```

```
(Cisco Controller) >
```

```
show ap join stats detail 00:14:f2:63:12:50

Discovery phase statistics
- Discovery requests received..... 2
- Successful discovery responses sent..... 2
- Unsuccessful discovery request processing..... 0
- Reason for last unsuccessful discovery attempt.....
  Not applicable
- Time at last successful discovery attempt.....
  Jan 24 12:21:20.547
- Time at last unsuccessful discovery attempt.....
  Not applicable

Join phase statistics
- Join requests received..... 2
- Successful join responses sent..... 2
- Unsuccessful join request processing..... 0
- Reason for last unsuccessful join attempt.....
  Not applicable
- Time at last successful join attempt.....
  Jan 24 12:21:30.669
- Time at last unsuccessful join attempt.....
  Not applicable
```

Configuration phase statistics

- Configuration requests received..... 2
- Successful configuration responses sent..... 2
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt....
 - Not applicable
- Successful configuration attempt.....
 - Jan 24 12:21:32.414
- Time at last unsuccessful configuration attempt.....
 - Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure.....
 - Not applicable

Last AP disconnect details

- Reason for last AP connection failure.....
 - Timed out while waiting for ECHO response from the AP

Last join error summary

- Type of error that occurred last.....
 - AP got or has been disconnected
- Reason for error that occurred last.....
 - Timed out while waiting for ECHO response from the AP
- Time at which the last join error occurred.....
 - Jan 24 12:21:14.751

لاثم 1

ةلومح نأ ىلا أطخلا ريشي .حيحصل ريغ مكحتلا ٽدحو ىلع دوجوملا تقولا نوكى ،ةلاحلا هذه يف ٽرتفل جراخ ناك مكحتلا ٽدحو ىلع دوجوملا تقولا نأ أطخلا اذه ٽدح .ةحيحص ريغ APs ٽداهش حيحصللا تقولا ىلا ريشي show time رمألا نأ نم دكأت .تاداهشلا ٽيحالصل ٽينمزلا .



ةدحول ةعاسلا أدب تثيح انه .هاندأ جتانلا يف 1993 سرام/راذاً 6 تقو ميق: ةظحالم نيوكت نودب مكحتلا NTP.

تقولا ماتخأب ريرقتلا تايئاصحإ لوصولا ةطقنل ثالثلالا لحارملالا لثمتت ببس ةفرعمل "ريخالا أطخلا صخلم" نم ققحت .نيوكتلاو مامضنالا او فاشتكالا ةلحرم يف لاصتالا عطق وأ لاصتالا مدع ببس إلإ مامضنالا يف لوصولا ةطقن لشف.

<#root>

```
(Cisco Controller) >  
show ap join stats detailed 00:14:1b:5a:40:10
```

Discovery phase statistics

- Discovery requests received..... 2
- Successful discovery responses sent..... 1
- Unsuccessful discovery request processing..... 2113123
- Reason for last unsuccessful discovery attempt.....
Discovery request received on unsupported VLAN

- Time at last successful discovery attempt.....
Mar 06 19:03:50.779
- Time at last unsuccessful discovery attempt.....
Mar 06 19:03:50.782

Join phase statistics

- Join requests received..... 1
- Successful join responses sent..... 0
- Unsuccessful join request processing..... 1
- Reason for last unsuccessful join attempt.....
Certificate payload in join request contains
invalid certificate
- Time at last successful join attempt.....
Not applicable
- Time at last unsuccessful join attempt.....
Mar 06 19:04:00.810

Configuration phase statistics

- Configuration requests received..... 0
- Successful configuration responses sent..... 0
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt....
Not applicable
- Time at last successful configuration attempt.....
Not applicable
- Time at last unsuccessful configuration attempt.....
Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure.....
Not applicable

Last AP disconnect details

- Reason for last AP connection failure.....
Not applicable

Last join error summary

- Type of error that occurred last.....
Lwapp join request rejected
- Reason for error that occurred last.....

Certificate payload in join request contains invalid
certificate

- Time at which the last join error occurred.....
Mar 06 19:04:00.810

لاثم 2

ةكبش فالخ ب VLAN ةكبش ىلع فاشتكالا بـ لـ طـ لـ وصـ ولـ اـ ظـ قـ نـ لـ سـ رـ ، ةـ اـ حـ لـ اـ هـ ذـ يـ فـ مـ تـ يـ مـ لـ يـ تـ لـ اـ فـ اـ شـ تـ كـ الـ اـ تـ اـ بـ لـ طـ عـ يـ مـ جـ مـ كـ حـ تـ لـ اـ ةـ دـ حـ وـ ضـ فـ رـ . ةـ رـ اـ دـ إـ لـ اـ نـ اـ وـ نـ عـ بـ ةـ صـ اـ خـ لـ اـ ةـ رـ اـ دـ إـ لـ اـ ةـ هـ جـ اـ وـ لـ اـ ةـ يـ عـ رـ فـ لـ اـ ةـ كـ بـ شـ لـ اـ ىـ لـ عـ اـ هـ لـ اـ بـ قـ تـ سـ اـ .

<#root>

(Cisco Controller) >

```
show ap join stats detailed 00:14:1b:5a:40:10
```

Discovery phase statistics

- Discovery requests received..... 10
- Successful discovery responses sent..... 5
- Unsuccessful discovery request processing..... 2113123
- Reason for last unsuccessful discovery attempt.....
 - Discovery request received on unsupported VLAN
- Time at last successful discovery attempt.....
 - Jan 30 14:30:12.284
- Time at last unsuccessful discovery attempt.....
 - Jan 30 14:30:12.288

Join phase statistics

- Join requests received..... 4
- Successful join responses sent..... 0
- Unsuccessful join request processing..... 4
- Reason for last unsuccessful join attempt.....
 - Certificate payload in join request contains invalid certificate
- Time at last successful join attempt.....
 - Not applicable
- Time at last unsuccessful join attempt.....
 - Mar 06 19:19:03.345

Configuration phase statistics

- Configuration requests received..... 0
- Successful configuration responses sent..... 0
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt....
 - Not applicable
- Time at last successful configuration attempt.....
 - Not applicable
- Time at last unsuccessful configuration attempt.....
 - Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure.....
 - Not applicable

Last AP disconnect details

- Reason for last AP connection failure.....
 - Not applicable

Last join error summary

- Type of error that occurred last.....
 - Failed to send Lwapp discovery response
- Reason for error that occurred last.....

Discovery request received on unsupported VLAN

- Time at which the last join error occurred.....
 - Jan 30 14:30:12.288

(Cisco Controller) >

Join phase statistics

- Join requests received..... 21
- Successful join responses sent..... 21
- Unsuccessful join request processing..... 0
- Reason for last unsuccessful join attempt.....
 - Not applicable
- Time at last successful join attempt.....
 - Jan 30 14:39:07.085
- Time at last unsuccessful join attempt.....
 - Not applicable

Configuration phase statistics

- Configuration requests received..... 21
- Successful configuration responses sent..... 21
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt....
 - Not applicable
- Time at last successful configuration attempt.....
 - Jan 30 14:39:09.481
- Time at last unsuccessful configuration attempt.....
 - Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure.....
 - Not applicable

Last AP disconnect details

- Reason for last AP connection failure.....
 - Timed out while waiting for ECHO response from the AP

Last join error summary

- Type of error that occurred last.....
 - AP got or has been disconnected
- Reason for error that occurred last.....

Timed out while waiting for ECHO response from the AP

- Time at which the last join error occurred.....
 - Jan 30 14:40:15.451

لاثم 4

ةدحوىل عةحىحص لوصولا ةطقنل (SSC) ايتاذ ةعقوملا ةداهشلا نكت مل ،ةلاحلا هذه يف
ىلإ بطللا هيجوت ةداعإ لباق ئيلحملان ايـب ةدعـاق نـم اـمـئـاد مـكـحـتـلـا زـاهـج قـقـحـتـي .مـكـحـتـلـا
ةـطـقـنـلـ رـادـيـعـ دـامـتـعـا دـامـتـعـا تـاوـدـأـأـطـخـلـا ئـلـاسـرـ رـهـظـتـ ،ـكـلـذـلـ ظـجـيـتـنـوـ .ـفـرـعـمـ رـادـعـ
ايـلـحـمـ SSC مـكـحـتـلـا ةـدـحـوـ دـجـتـ الـ اـمـدـنـعـ "ـلـوـصـوـلـاـ".

<#root>

(Cisco Controller) >

```
show ap join stats detailed 00:13:5f:fa:88:50
```

Discovery phase statistics

- Discovery requests received..... 2

- Successful discovery responses sent..... 1
- Unsuccessful discovery request processing..... 2113123
- Reason for last unsuccessful discovery attempt.....
 - Discovery request received on unsupported VLAN
- Time at last successful discovery attempt.....
 - Jan 30 14:58:58.070
- Time at last unsuccessful discovery attempt.....
 - Jan 30 14:58:58.071

Join phase statistics

- Join requests received..... 1
- Successful join responses sent..... 0
- Unsuccessful join request processing..... 1
- Reason for last unsuccessful join attempt.....

RADIUS authorization is pending for the AP

- Time at last successful join attempt.....
 - Not applicable
- Time at last unsuccessful join attempt.....
 - Jan 30 14:59:13.111

Configuration phase statistics

- Configuration requests received..... 0
- Successful configuration responses sent..... 0
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt....
 - Not applicable
- Time at last successful configuration attempt.....
 - Not applicable
- Time at last unsuccessful configuration attempt.....
 - Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure.....
 - Not applicable

Last AP disconnect details

- Reason for last AP connection failure.....
 - Radius authorization of the AP has failed

Last join error summary

- Type of error that occurred last.....
 - AP got or has been disconnected
- Reason for error that occurred last.....

Radius authorization of the AP has failed

- Time at which the last join error occurred.....
 - Jan 30 14:59:13.117

(Cisco Controller) >

پاچ 5

<#root>

(Cisco Controller) >

```
show ap join stats detailed 0026cb8168c0
```

Discovery phase statistics

- Discovery requests received..... 202
- Successful discovery responses sent..... 0
- Unsuccessful discovery request processing..... 0
- Reason for last unsuccessful discovery attempt..... Not applicable
- Time at last successful discovery attempt..... Not applicable
- Time at last unsuccessful discovery attempt..... Not applicable

Join phase statistics

- Join requests received..... 122
- Successful join responses sent..... 0
- Unsuccessful join request processing..... 0
- Reason for last unsuccessful join attempt..... Not applicable
- Time at last successful join attempt..... Not applicable
- Time at last unsuccessful join attempt..... Not applicable

Configuration phase statistics

- Configuration requests received..... 115
- Successful configuration responses sent..... 0
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt..... Not applicable
- More-- or (q)uit
- Time at last successful configuration attempt..... Not applicable
- Time at last unsuccessful configuration attempt..... Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure..... Not applicable

Last AP disconnect details

- Reason for last AP connection failure..... Image data request received from an unsupported AP

Last join error summary

- Type of error that occurred last..... AP got or has been disconnected
- Reason for error that occurred last.....

Image data

request received from an unsupported AP

- Time at which the last join error occurred..... Feb 16 00:50:16.841

<#root>

Discovery phase statistics

- Discovery requests received..... 44
- Successful discovery responses sent..... 44
- Unsuccessful discovery request processing..... 0
- Reason for last unsuccessful discovery attempt..... Not applicable
- Time at last successful discovery attempt..... Feb 26 18:36:24.098
- Time at last unsuccessful discovery attempt..... Not applicable

Join phase statistics

- Join requests received..... 44
- Successful join responses sent..... 0
- Unsuccessful join request processing..... 44
- Reason for last unsuccessful join attempt..... Join request received from an unsupported AP

- Time at last successful join attempt..... Not applicable
- Time at last unsuccessful join attempt..... Feb 26 18:36:39.497

Configuration phase statistics

- Configuration requests received..... 0
- Successful configuration responses sent..... 0
- Unsuccessful configuration request processing..... 0
- Reason for last unsuccessful configuration attempt..... Not applicable
- Time at last successful configuration attempt--More-- or (q)uit
t..... Not applicable
- Time at last unsuccessful configuration attempt..... Not applicable

Last AP message decryption failure details

- Reason for last message decryption failure..... Not applicable

Last AP disconnect details

- Reason for last AP connection failure..... Not applicable

Last join error summary

- Type of error that occurred last..... Lwapp join request rejected
- Reason for error that occurred last.....

Join request receive

d from an unsupported AP

- Time at which the last join error occurred..... Feb 26 18:36:39.497

ةلص تاذ تامولعم

- مكحـت ةـدـحـوـىـلـاـ مـضـنـتـ الـ يـتـلـاـ عـضـولـاـ يـفـ لـوـصـولـاـ ةـطـقـنـ عـاطـخـأـ فـاشـكـتـسـأـ اـهـحـالـصـ اوـ ئـيـكـلـسـ الـلـاـ (ـLـA~Nـ)ـ ئـيـلـحـمـلـاـ ئـكـبـشـلـاـ يـفـ نـمـ تـالـيـزـنـتـلـاـ اوـ يـنـفـلـاـ معـدـلـاـ Cisco

هـ لـ وـ لـ جـ رـ تـ لـ اـ هـ ذـ هـ

ةـ يـ لـ آـ لـ اـ تـ اـ يـ نـ قـ تـ لـ اـ نـ مـ مـ جـ مـ وـ عـ مـ اـ دـ خـ تـ سـ اـ بـ دـ نـ تـ سـ مـ لـ اـ اـ ذـ هـ تـ مـ جـ رـ تـ
لـ اـ عـ لـ اـ ءـ اـ حـ نـ اـ عـ يـ مـ جـ يـ فـ نـ يـ مـ دـ خـ تـ سـ مـ لـ لـ مـ عـ دـ ئـ وـ تـ حـ مـ يـ دـ قـ تـ لـ ةـ يـ رـ شـ بـ لـ اـ وـ
اـ مـ كـ ةـ قـ يـ قـ دـ نـ وـ كـ تـ نـ لـ ةـ يـ لـ آـ ةـ مـ جـ رـ تـ لـ ضـ فـ اـ نـ اـ ةـ ظـ حـ اـ لـ مـ ئـ جـ رـ يـ .ـ صـ اـ خـ لـ اـ مـ هـ تـ غـ لـ بـ
يـ لـ خـ تـ .ـ فـ رـ تـ حـ مـ مـ جـ رـ تـ مـ اـ هـ دـ قـ يـ يـ تـ لـ اـ ةـ يـ فـ اـ رـ تـ حـ اـ لـ اـ ةـ مـ جـ رـ تـ لـ اـ عـ مـ لـ اـ حـ لـ اـ وـ
ىـ لـ إـ أـ مـ ئـ اـ دـ عـ وـ جـ رـ لـ اـ بـ يـ صـ وـ تـ وـ تـ اـ مـ جـ رـ تـ لـ اـ هـ ذـ هـ ةـ قـ دـ نـ عـ اـ هـ تـ يـ لـ وـ ئـ سـ مـ
(رـ فـ وـ تـ مـ طـ بـ اـ رـ لـ اـ)ـ يـ لـ صـ أـ لـ اـ يـ زـ يـ لـ جـ نـ إـ لـ اـ دـ نـ تـ سـ مـ لـ اـ).