



Connect to the Center

You can connect to the Center:

- Using the [Using the GUI](#).
- Using the [Using the console](#).
- [Using the GUI, on page 1](#)
- [Using the console, on page 2](#)

Using the GUI

The Public IP address and FQDN of your instance will be available on the Instance summary page:

Instance ID	Public IPv4 address	Private IPv4 addresses
i-0b19cd5b75ee7cffa	54.195.222.37 open address	172.31.7.229
Instance state	Public IPv4 DNS	Private IPv4 DNS
Running	ec2-54-195-222-37.eu-west-1.compute.amazonaws.com open address	ip-172-31-7-229.eu-west-1.compute.internal
Instance type	Elastic IP addresses	VPC ID
c5a.large	54.195.222.37 [Public IP]	vpc-77b96d0e
AWS Compute Optimizer finding	IAM Role	Subnet ID
Opt-in to AWS Compute Optimizer for recommendations. Learn more	-	subnet-919a9cf7

1. In your browser, use the public IP address or the FQDN to download and save the certificate:
 - `https://<Public IPV4 address>/ca/crt`
 - `https://<Public IPV4 DNS>/ca/crt`
2. In your browser, use the following address to access Cisco Cyber Vision:
`https://<CENTERNAME>/`

You can proceed with [Cisco Cyber Vision installation](#).

Using the console

You can connect to the Center using the AWS serial console.



Note Serial Console is only supported in the following AWS Regions: US East (N. Virginia), US East (Ohio), US West (Oregon), Europe (Ireland), Europe (Frankfurt), Asia Pacific (Sydney), Asia Pacific (Tokyo), Asia Pacific (Singapore).

To use the serial console, click Actions > Monitor and troubleshoot > EC2 Serial Console.

The screenshot shows the AWS Management Console interface. On the left is a navigation sidebar with options like 'EC2 Dashboard', 'Events', 'Tags', 'Limits', and 'Instances'. The main area displays a list of EC2 instances. One instance is selected, and a context menu is open over it. The menu includes options like 'Launch instances', 'Connect', 'Stop instance', 'Start instance', 'Reboot instance', 'Hibernate instance', 'Terminate instance', 'Instance settings', 'Networking', 'Security', 'Image and templates', and 'Monitor and troubleshoot'. The 'Monitor and troubleshoot' option is expanded, showing a sub-menu with 'EC2 Serial Console' highlighted.

The root password by default will be the instance ID of the Center you created.

Supported instance families:

- A1
- C5, C5a, C5ad, C5d, C5n, C6g, C6gd
- M5, M5a, M5ad, M5d, M5dn, M5n, M5zn, M6g, M6gd
- R5, R5a, R5ad, R5d, R5dn, R5n, R6, R6gd
- T3, T3a, T4g
- Z1d