

清除已删除的映像警报

目录

[简介](#)

[要求](#)

[使用的组件](#)

[背景信息](#)

[故障排除方法](#)

[重新安装-安装软件包捆绑包](#)

[删除策略](#)

[修改包版本](#)

[相关信息](#)

简介

本文档介绍清除Unified Computing System Manager域上已删除映像的警报的三种方法。

要求

Cisco 建议您了解以下主题：

- [统一计算系统管理器域\(UCSM\)](#)。

使用的组件

- [UCS管理器](#)。
- [在UCSM中管理策略](#)。

本文档中的信息都是基于特定实验室环境中的设备编写的。本文档中使用的所有设备最初均采用原始（默认）配置。如果您的网络处于活动状态，请确保您了解所有命令的潜在影响。

背景信息

删除仍在主机固件包中引用的固件捆绑包会导致出现已删除映像的错误消息。

Severity	Code	ID	Affected object	Cause	Last Transition	Description
Major	F0436	66868901	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
Major	F0436	66868899	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
Major	F0436	66868897	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
Major	F0436	66868895	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
Major	F0436	66868903	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	host_controller_ims...

Total: 104 Selected: 1

Details

Summary	Properties
Severity : Major/None	Affected object : org-root/fw-host-pack-test_HFE/pack-image-Cisco Systems Inc UCSB-VIC-M84-4P adaptor
Last Transition : 2023-11-16T16:09:20Z	Description : adaptor image with vendor Cisco Systems Inc, model UCSB-VIC-M84-4P and version 5.2(3e) is deleted
Actions	ID : 66868901 Type : management
Acknowledge Fault	

故障排除方法

重新安装-安装软件包捆绑包

步骤1:从software.cisco.com下载软件捆绑包。

第二步：要查看已删除图像的故障，请导航到Equipment选项卡> Faults并选择警报。

Filters	Severity	Code	ID	Affected object	Cause	Last Transition	Description
Severity: <input type="checkbox"/> Show All, <input type="checkbox"/> Critical, <input checked="" type="checkbox"/> Major, <input type="checkbox"/> Minor, <input type="checkbox"/> Warning, <input type="checkbox"/> Info, <input type="checkbox"/> Condition, <input type="checkbox"/> Cleared, <input type="checkbox"/> Soaking, <input type="checkbox"/> Suppressed	Major	F0436	66868901	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
Category: <input checked="" type="checkbox"/> All, <input checked="" type="checkbox"/> Generic, <input checked="" type="checkbox"/> Server	Major	F0436	66868899	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
	Major	F0436	66868897	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
	Major	F0436	66868895	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	adaptor image with v...
	Major	F0436	66868903	org-root/fw-host-pa...	image-deleted	2023-11-16T16:09:20Z	host_controller_ims...


Total: 104 Selected: 1

Details

Summary	Properties
Severity : Major/None	Affected object : org-root/ fw-host-pack-test_HFE /pack-image-Cisco Systems Inc UCSB-VIC-M84-4P adaptor
Last Transition : 2023-11-16T16:09:20Z	Description : adaptor image with vendor Cisco Systems Inc, model UCSB-VIC-M84-4P and version 5.2(3e) is deleted
Actions	ID : 66868901 Type : management
Acknowledge Fault	


The name of host firmware policy referencing deleted image

第三步：浏览Equipment选项卡>固件管理>下载任务，然后点击屏幕底部附近的Add下载捆绑包。



删除策略


步骤1: 导航到受影响对象引用的特定策略。



第二步：浏览“Servers”选项卡>“Policies”>“Host Firmware Packages”并选择受影响的策略。

第三步：在之前选定的受影响策略下，点击“Show policy Usage”以确认当前服务配置文件或模板未

使用此策略。



Service Profiles/Templates Including 4.11c

Service Profiles/Templates


The policy 4.11c is included in the service profiles/templates listed in the table below.


Advanced Filter Export Print

Name	Assoc State	Overall Status	Server
No data available			

Ensure that this policy is not being used

第四步：选择delete。








注意：作为一种最佳实践，通过选择show policy usage确保程序包版本当前未在任何服务配置文件模板中使用。如果未使用，请继续删除策略，方法是右键单击该策略并选择delete。

修改包版本

步骤1:导航到Servers tab > Policies > Host Firmware Packages > 在右窗格上，选择受影响的策略，然后单击Info。



第2步：在之前选择的受影响策略下，点击“Show policy Usage”以确认当前未使用任何服务配置文件或OMPH。



第三步：选择“修改软件包版本”，然后删除或替换它所引用的刀片或机架软件包捆绑包，然后选择

“应用”以保存更改。

Properties for: 4.110 Modify Package Versions

Blade Package :

Rack Package :

Service Pack : 4.1(3b)B

The images from Service Pack will take precedence over the images from Blade or Rack Package

Excluded Components:

- Adapter
- BIOS
- Board Controller
- CIMC
- FC Adapters
- Flex Flash Controller
- GPUs
- HBA Option ROM
- Host NIC
- Host NIC Option ROM
- Local Disk
- NVME Mswitch Firmware
- PSU

Set it to <not set> or to the correct version that exist

OK Apply Cancel Help



注意：前面提到的故障排除步骤不会造成中断。

相关信息

[清除“已删除图像”警报视频](#)

[管理主机固件包](#)

software.cisco.com

关于此翻译

思科采用人工翻译与机器翻译相结合的方式将此文档翻译成不同语言，希望全球的用户都能通过各自的语言得到支持性的内容。

请注意：即使是最好的机器翻译，其准确度也不及专业翻译人员的水平。

Cisco Systems, Inc. 对于翻译的准确性不承担任何责任，并建议您总是参考英文原始文档（已提供链接）。