



## **Command Line Interface Reference, Modes R - Z, StarOS Release 21.16**

**First Published:** 2019-10-24

### **Americas Headquarters**

Cisco Systems, Inc.  
170 West Tasman Drive  
San Jose, CA 95134-1706  
USA  
<http://www.cisco.com>  
Tel: 408 526-4000  
800 553-NETS (6387)  
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com go trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2019 Cisco Systems, Inc. All rights reserved.



## CONTENTS

---

<b>CHAPTER 1</b>	<b>Command Line Interface Reference, Modes R - Z, StarOS Release 21.16</b>	<b>1</b>
	Note	2

---

<b>CHAPTER 2</b>	<b>Radio Congestion Policy Configuration Mode Commands</b>	<b>3</b>
	congestion-level	4
	correlation-method	6
	data-loss threshold	7
	do show	9
	end	10
	exit	11
	reporting-interval	12
	rtt-samples	13
	rtt-variance	14
	sampling-interval	15

---

<b>CHAPTER 3</b>	<b>RANAP Cause Code Group Configuration Mode</b>	<b>17</b>
	cause	18
	do show	19
	end	20
	exit	21

---

<b>CHAPTER 4</b>	<b>Remote Address List Configuration Mode Commands</b>	<b>23</b>
	address	24
	do show	25
	end	26
	exit	27

---

<b>CHAPTER 5</b>	<b>Remote Server List Configuration Mode Commands</b>	<b>29</b>
	address	30
	do show	31
	end	32
	exit	33

---

<b>CHAPTER 6</b>	<b>Remote Secret List Configuration Mode Commands</b>	<b>35</b>
	do show	36
	end	37
	exit	38
	remote-id	39

---

<b>CHAPTER 7</b>	<b>RLF Template Configuration Mode Commands</b>	<b>41</b>
	delay-tolerance	42
	do show	43
	end	44
	exit	45
	msg-rate	46
	threshold	48

---

<b>CHAPTER 8</b>	<b>RNC Configuration Mode Commands</b>	<b>49</b>
	associate-gtpu-bind-address	51
	description	52
	direct-tunnel	53
	do show	54
	dual-address-pdp	55
	enb-data-forward	57
	enb-direct-data-forward	58
	end	59
	exit	60
	lac	61
	mbms	62
	overload-action disable	63

paging-non-searching-indication	66
pointcode	67
pooled	68
rab-asymmetry-indicator	69
rab-modify-procedure	71
ranap arp-ie	73
ranap bidirectional-always	74
ranap eutran-service-handover-ie	75
ranap global-cn-id	77
ranap paging-area-id	79
ranap paging-cause-ie	80
ranap rab-arsp-ue-radio-lost	83
ranap rab-release-with-radiolost	84
ranap rfsp-id-ie	85
ranap signalling-indication-ie	86
ranap ue-ambr-ie	87
ran-information-management	88
release-compliance	89
reset-resource	91

---

**CHAPTER 9****RoHC Profile Common Options Configuration Mode Commands 93**

delay-release-hc-context-timer	94
do show	95
end	96
exit	97
inactive-traffic-release-hc-context-timer	98

---

**CHAPTER 10****RoHC Profile Compression Configuration Mode Commands 99**

context-timeout	101
do show	102
end	103
exit	104
ipid-history-size	105
max-jitter-cd	106

max-sliding-window	107
multiple-ts-stride	108
new-context-blocking-time	109
num-pkts-ts	110
num-pkts-u-mode	111
num-updates-ir	112
optimistic-repeats	113
rtp-sn-p	114
rtp-sn-p-override	115
rtp-time-stride	116
rtp-ts-deviation	117
rtp-ts-stride	118
sliding-window-ts	119
total-jitter-ipv4	120
total-jitter-ipv6	121
unimode-timeout-to-fo-state	122
unimode-timeout-to-ir-state	123
use-calculated-rtp-time-stride	124
use-calculated-rtp-ts-stride	125
use-ipid-override	126
use-optimized-talkspurt	127
use-optimized-transience	128
use-timer-based-compression	129
use-uncomp-profile	130

---

**CHAPTER 11**      **RoHC Profile Configuration Mode Commands**    131

common-options	132
compression-options	133
decompression-options	134
do show	135
end	136
exit	137

---

**CHAPTER 12**      **RoHC Profile Decompression Configuration Mode Commands**    139

accept-delayed-pkts	141
context-timeout	142
crc-errors-fo	143
crc-errors-so	144
do show	145
end	146
exit	147
nack-limit	148
optimistic-mode-ack	149
optimistic-mode-ack-limit	150
piggyback-wait-time	151
preferred-feedback-mode	152
rtp-sn-p	154
rtp-sn-p-override	155
sliding-window-ts	156
use-clock-option	157
use-crc-option	158
use-feedback	159
use-jitter-option	160
use-reject-option	161
use-sn-not-valid-option	162
use-sn-option	163

---

**CHAPTER 13****Route-map Configuration Mode Commands 165**

do show	167
end	168
exit	169
match as-path	170
match community	171
match extcommunity	172
match interface	173
match ip address	174
match ip next-hop	175
match ipv6 address	176

match ipv6 next-hop	177
match metric	178
match origin	179
match route-type external	180
match tag	181
set as-path	182
set community	183
set extcommunity rt	185
set ip next-hop	186
set ipv6 next-hop	187
set local-preference	188
set metric	189
set metric-type	190
set origin	191
set tag	192
set weight	193

---

**CHAPTER 14**      **RS-232 Port Configuration Mode Commands**    195

do show	196
end	197
exit	198
preferred slot	199
snmp trap link-status	201
terminal	202

---

**CHAPTER 15**      **S102 Pool Area Configuration Mode Commands**    205

cell-id	206
do show	207
end	208
exit	209
hash-value	210
msc-id	212
plmnid	213



---

<b>CHAPTER 16</b>	<b>S102 Service Configuration Mode Commands</b>	<b>215</b>
	lxtt	216
	bind	217
	do show	218
	end	219
	exit	220
	ip	221
	msc	222
	non-pool-area	223
	pool-area	225

---

<b>CHAPTER 17</b>	<b>S102 MSC Configuration Mode Commands</b>	<b>227</b>
	do show	228
	end	229
	exit	230
	ipv4-address	231

---

<b>CHAPTER 18</b>	<b>S1AP Cause Code Configuration Mode Commands</b>	<b>233</b>
	class	234
	do show	236
	end	237
	exit	238

---

<b>CHAPTER 19</b>	<b>S1-U Relay Configuration Mode Commands</b>	<b>239</b>
	associate	240
	do show	241
	end	242
	exit	243
	ip	244

---

<b>CHAPTER 20</b>	<b>SAEGW Service Configuration Mode Commands</b>	<b>247</b>
	associate	248
	do show	250

gtpc handle-collision upc nrupc 251  
 end 252  
 exit 253

---

**CHAPTER 21 SaMOG Service Configuration Mode Commands 255**

associate 256  
 do show 258  
 end 259  
 exit 260  
 max-sessions 261  
 timeout 262

---

**CHAPTER 22 SBc Service Configuration Mode Commands 265**

associate 266  
 bind 267  
 cbc-associations 268  
 do show 269  
 end 270  
 exit 271  
 ip 272  
 sbc-mme 273  
 send 274

---

**CHAPTER 23 SCCP Network Configuration Mode Commands 275**

associate 276  
 description 277  
 destination 278  
 do show 280  
 end 281  
 exit 282  
 global-title-translation 283  
 hop-count 284  
 self-point-code 285

timeout 287

---

**CHAPTER 24****SCTP Parameter Template Configuration Mode Commands 291**

do show 293  
end 294  
exit 295  
sctp-alpha 296  
sctp-alt-accept-flag 297  
sctp-beta 298  
sctp-checksum-type 299  
sctp-cookie-life 300  
sctp-max-assoc-retx 301  
sctp-max-in-strms 302  
sctp-max-init-retx 303  
sctp-max-mtu-size 304  
sctp-max-out-strms 305  
sctp-max-path-retx 306  
sctp-min-mtu-size 307  
sctp-rto-initial 308  
sctp-rto-max 309  
sctp-rto-min 310  
sctp-sack-frequency 311  
sctp-sack-period 312  
sctp-start-mtu-size 313  
timeout 314

---

**CHAPTER 25****Security Configuration Mode Commands 317**

category 318  
end 319  
exit 320  
server 321

---

**CHAPTER 26****Service Chain Configuration Mode Commands 323**

end 324

exit 325  
nsh-format 326

---

**CHAPTER 27****Service Redundancy Protocol Configuration Mode Commands 327**

advertise-routes-in-standby-state 329  
audit 331  
bfd-mon-ignore-dead-interval 333  
bind 334  
chassis-mode 335  
checkpoint session 336  
configuration-interval 338  
dead-interval 339  
delay-interval 340  
delta-route-modifier 341  
do show 342  
dscp-marking 343  
end 345  
exit 346  
guard-timer 347  
handle-interim-resource-msg 349  
hello-interval 350  
internal-switchover-retry-interval 351  
monitor authentication-probe 352  
monitor bfd 354  
monitor bgp 356  
monitor diameter 358  
monitor hsrp 360  
num-internal-switchover-retry 362  
peer-ip-address 363  
priority 364  
retain-complete-sess-info 365  
route-modifier 366  
standby database-recovery 367  
switchover allow-all-data-traffic 368

switchover allow-early-active-transition 369  
switchover allow-volte-data-traffic 370  
switchover control-outage-optimization 371

---

**CHAPTER 28**      **Session Event Module Configuration Mode Commands 373**

do show 374  
end 375  
event 376  
exit 379  
file 380

---

**CHAPTER 29**      **Session Trace Template Configuration Mode Commands 385**

archive 386  
disk-limit 387  
do show 388  
end 389  
exit 390  
interface 391  
target-interface 395  
target-ne 397  
trace-extension 399

---

**CHAPTER 30**      **SGSN ASP Configuration Mode Commands 401**

do show 402  
end 403  
end-point 404  
exit 406

---

**CHAPTER 31**      **SGSN Congestion Action Profile Configuration Mode 407**

active-call-policy 408  
do show 410  
end 411  
exit 412  
new-call-policy 413

sm-messages 415

---

**CHAPTER 32**      **SGSN Congestion Control Configuration Mode 417**

congestion-action-profile 418

do show 419

end 420

exit 421

---

**CHAPTER 33**      **SGSN Global Configuration Mode Commands 423**

aggregate-ipc-msg 425

apn-resolve-dns-query snaptr 427

bssgp-message dl-unitdata 428

bssgp-message ms-flow-control-from-unknown-ms 429

bssgp-message ptp-bvc-reset 431

bssgp-timer 432

bvc-unblock 433

canonical-node-name 435

common-ra-paging 436

congestion-control 437

do show 438

dscp-template 439

dual-address-pdp 441

ec-gsm 443

eir-profile 444

end 445

exit 446

gmm-message 447

gmm-sm-statistics 448

gprs-mocn 449

interface-management 450

ipms-suppress 451

imsi-range 452

location-services 455

map-message 456

max-pending-attaches	457
msisdn-group	458
msisdn-range	459
old-tlli invalidate tlli	460
old-tlli hold-time	461
pdp-deactivation-rate	462
qos-arp-rp-map-profile	464
ranap excess-len ignore	465
ran-information-management	466
target-offloading	467
tlli-cb-audit	468
umts-aka-r99	469

---

**CHAPTER 34**      **SGSN Interface Management Configuration Mode**    471

do show	472
end	473
exit	474
interface	475
lock-interface	477
paging-rlf-template	478

---

**CHAPTER 35**      **SGSN Pool Area Configuration Mode Commands**    481

do show	482
end	483
exit	484
hash-value	485
lac	487

---

**CHAPTER 36**      **SGSN PSP Configuration Mode Commands**    489

associate	491
do show	493
end	494
end-point	495
exchange-mode	497

exit	498
psp-mode	499
routing-context	500
sctp-alpha	502
sctp-beta	503
sctp-checksum-type	504
sctp-cookie-life	505
sctp-init-rwnd	506
sctp-max-assoc-retx	507
sctp-max-data-chunks	508
sctp-max-in-strms	509
sctp-max-init-retx	510
sctp-max-mtu size	511
sctp-max-out-strms	512
sctp-max-path-retx	514
sctp-parameter	515
sctp-rto-initial	516
sctp-rto-max	517
sctp-rto-min	518
sctp-sack-frequency	520
sctp-sack-period	521
sctp-suppress-alarm	522
shutdown	524
timeout	525

---

**CHAPTER 37**      **SGSN Service Configuration Mode Commands**    **527**

accounting	529
admin-disconnect-behavior	531
associate	533
cc profile	537
check-imei	539
check-imei-timeout-action	541
core-network	542
disable/enable super-charger	543



[dns israu-mcc-mnc-encoding](#) 544  
[dns mcc-mnc-encoding](#) 545  
[do show](#) 547  
[end](#) 548  
[exit](#) 549  
[gmm](#) 550  
[gs-service](#) 556  
[lac](#) 558  
[max-pdp-contexts](#) 559  
[mobile-application-part](#) 560  
[network-sharing cs-ps-coordination](#) 562  
[nri length](#) 563  
[override-lac-li](#) 566  
[override-rac-li](#) 567  
[qos-modification](#) 568  
[rac](#) 570  
[ran-protocol](#) 571  
[reporting-action event-record](#) 572  
[s4-overcharge-protection](#) 573  
[sgsn-number](#) 575  
[sgtp-service](#) 576  
[sm](#) 577

---

**CHAPTER 38**
**SGTP Service Configuration Mode Commands** 581

[direct-tunnel-disabled-ggsn](#) 582  
[disable-remote-restart-counter-verification](#) 584  
[do show](#) 586  
[end](#) 587  
[exit](#) 588  
[ggsn-fail-retry-timer](#) 589  
[gn-delay-monitoring](#) 590  
[gtpc](#) 592  
[gtpu](#) 597  
[ignore-remote-restart-counter-change](#) 600

max-remote-restart-counter-change 601  
 mbms 603  
 path-failure 604  
 pool 605

---

**CHAPTER 39 S-GW Access Peer Profile Configuration Mode Commands 607**

description 608  
 do show 609  
 end 610  
 exit 611  
 ntsr 612

---

**CHAPTER 40 S-GW Paging Profile Configuration Mode Commands 613**

do show 614  
 end 615  
 exit 616  
 ipv4 | ipv6 617

---

**CHAPTER 41 S-GW Service Configuration Mode Commands 619**

accounting context 621  
 accounting mode 622  
 accounting stop-trigger 623  
 associate 624  
 ddn failure-action 627  
 ddn isr-sequential-paging 628  
 ddn success-action no-user-connect ddn-retry-timer 629  
 ddn temp-ho-rejection mbr-guard-timer 630  
 ddn throttle 632  
 do show 635  
 egtp-service 636  
 end 637  
 exit 638  
 gtpc handle-collision upc nrupc 639  
 gtpu-error-ind 640

mag-service 642  
 ntsr session-hold timeout 643  
 page-ue 644  
 paging-policy-differentiation 645  
 path-failure 647  
 pgw-fteid-in-relocation-cs-rsp 649  
 plmn 650  
 reporting-action 651  
 timeout idle 652

---

**CHAPTER 42**      **SLs Service Configuration Mode Commands 655**

bind 656  
 do show 658  
 end 659  
 esmlc 660  
 exit 662  
 ip 663  
 max-retransmissions 664  
 t-3x01 665  
 t-3x02 666

---

**CHAPTER 43**      **SMS Service Configuration Mode Commands 667**

cp-data 668  
 do show 669  
 end 670  
 exit 671  
 mo-message-forwarding-destination 672  
 smsc-address-restriction-list 673  
 smsc-address-restriction-type 674  
 smsc-address-selection-prioritization 675  
 smsc-routing 677  
 timeout 679

---

**CHAPTER 44**      **SS7 Routing Domain Configuration Mode Commands 681**

asp 682  
description 683  
do show 684  
end 685  
exit 686  
inbound-asp-identifier validate 687  
linkset 688  
MTU-size 689  
peer-server 690  
route 691  
routing-context 693  
ssf 694

---

**CHAPTER 45**      **SSH Configuration Mode Commands 697**

allowusers add 698  
authorized-key 700  
ciphers 701  
client-alive-countmax 703  
client-alive-interval 705  
do show 706  
end 707  
exit 708  
listen 709  
macs 710  
max servers 712  
subsystem 713

---

**CHAPTER 46**      **Stats Profile Configuration Mode Commands 715**

do show 716  
end 717  
exit 718  
packet-drop 719  
qci 720  
rat-type 722

---

**CHAPTER 47****Subscriber Configuration Mode Commands 723**

- aaa 727
- access-link ip-fragmentation 729
- accounting-mode 730
- active-charging bandwidth-policy 732
- active-charging link-monitor tcp 733
- active-charging radio-congestion 735
- active-charging rulebase 736
- always-on 737
- asn-header-compression-rohc 738
- asn nspid 739
- asn-pdfid 740
- asn-policy 741
- associate accounting-policy 744
- authorized-flow-profile-id 745
- content-filtering category 746
- credit-control-client 748
- credit-control-group 750
- credit-control-service 751
- data-tunneling ignore df-bit 752
- dcca peer-select 753
- default 754
- description 757
- dhcp dhcpv6 758
- dhcp options 759
- dhcp parameter-request-list-option 760
- dhcp service 761
- dns 762
- do show 763
- eap 764
- encrypted password 765
- end 766
- exit 767

external-inline-server	768
firewall policy	769
gtp	771
idle-timeout-activity	772
ikev2 tsr	773
ims application-manager	774
ims-auth-service	775
inter-pdsn-handoff	776
ip access-group	777
ip address	778
ip address pool	779
ip address secondary-pool	781
ip allowed-dscp	782
ip context-name	785
ip header-compression	786
ip hide-service-address	789
ip local-address	790
ip multicast discard	791
ip qos-dscp	792
ip route	794
ip source-validation	796
ip user-datagram-tos copy	797
ip vlan	799
ipv6 access-group	800
ipv6 address	801
ipv6 dns	802
ipv6 dns-proxy	803
ipv6 egress-address-filtering	804
ipv6 initial-router-advt	805
ipv6 interface-id	807
ipv6 minimum-link-mtu	808
ipv6 secondary-address	809
l2tp send accounting-correlation-info	810
l3-to-l2-tunnel address-policy	811

loadbalance-tunnel-peers 813  
long-duration-action 814  
max-pdn-connections 816  
mediation-device 817  
mobile-ip 819  
mobile-ip ha 823  
mobile-ip reg-lifetime-override 824  
mobile-ip send access-technology 825  
mobile-ip send accounting-correlation-info 826  
mobile-ip send bsid 827  
mobile-ip send pcf-address 828  
mobile-ip send service-option 829  
mobile-ip send subnet-id 830  
mobile-ipv6 831  
nai-construction-domain 833  
nbns 834  
nexthop-forwarding-address 835  
npu qos 836  
nw-reachability-server 838  
outbound 840  
overload-disconnect 841  
password 843  
pdif mobile-ip 845  
permission 846  
policy ipv6 tunnel 847  
policy-group 848  
ppp 849  
prepaid 3gpp2 853  
prepaid custom 855  
prepaid unclassify 857  
prepaid voice-push 858  
prepaid wimax 859  
proxy-dns intercept list-name 860  
proxy-mip 861

qos apn-ambr	862
qos rate-limit	864
qos traffic-police	869
qos traffic-shape	872
radius accounting	875
radius group	878
radius returned-framed-ip-address	879
radius rulebase-format	880
rohc-profile-name	882
secondary ip pool	883
send-destination-pgw	884
simultaneous	885
timeout absolute	886
timeout idle	887
timeout long-duration	889
tpo policy	890
tunnel address-policy	891
tunnel ipip	893
tunnel ipsec	894
tunnel l2tp	895
w-apn	897

**CHAPTER 48****TACACS+ Configuration Mode Commands 899**

accounting	900
authorization	901
do show	902
end	903
exit	904
idle-session threshold	905
max-sessions	906
on-authen-fail	907
on-network-error	908
on-unknown-user	909
priv-lvl	911



rem\_addr client-ip 913  
server 914  
user-id 917

---

**CHAPTER 49**      **Telnet Configuration Mode Commands**    919

do show 920  
end 921  
exit 922  
max servers 923

---

**CHAPTER 50**      **TFTP Configuration Mode Commands**    925

do show 926  
end 927  
exit 928  
max servers 929

---

**CHAPTER 51**      **Throttling Override Policy Configuration Mode Commands**    931

do show 932  
egress bypass-rlf 933  
end 936  
exit 937

---

**CHAPTER 52**      **Traffic Optimization Policy Configuration**    939

bandwidth-mgmt 940  
curbing-control 942  
do show 944  
end 945  
exit 946  
heavy-session 947  
link-profile 948  
session-params 949

---

**CHAPTER 53**      **Traffic Optimization Profile Configuration Mode Commands**    951

data-record 952

efd-flow-cleanup-interval 953  
end 954  
exit 955  
heavy-session detection-threshold 956  
mode 957  
stats-interval 958  
stats-options 959

---

**CHAPTER 54****Traffic Policy-Map Configuration Mode Commands 961**

3gpp2 data-over-signaling 962  
access-control 963  
accounting suppress 964  
accounting trigger 965  
class-map 967  
description 968  
do show 969  
end 970  
exit 971  
flow-tp-trigger 972  
ip header-compression 973  
qos encaps-header 974  
qos traffic-police 976  
qos user-datagram dscp-marking 978  
sess-tp-trigger 979  
type 980

---

**CHAPTER 55****Traffic Policy Group Configuration Mode Commands 983**

3gpp2 data-over-signaling 984  
access-control 985  
accounting suppress 986  
accounting trigger 987  
class-map 989  
description 990

do show 991  
 end 992  
 exit 993  
 flow-tp-trigger 994  
 ip header-compression 995  
 qos encaps-header 996  
 qos traffic-police 998  
 qos user-datagram dscp-marking 1000  
 sess-tp-trigger 1001  
 type 1002

---

**CHAPTER 56**      **Traffic Steering Configuration Mode Commands 1005**

appliance-group 1006  
 do show 1007  
 end 1008  
 exit 1009  
 service-chain 1010

---

**CHAPTER 57**      **Traffic Steering Appliance Group Configuration Mode Commands 1011**

do show 1012  
 end 1013  
 exit 1014  
 ip 1015  
 nsh-format 1016

---

**CHAPTER 58**      **Traffic Steering Service Chain Configuration Mode Commands 1017**

do show 1018  
 end 1019  
 exit 1020  
 load-balancing 1021  
 sfp 1022

---

**CHAPTER 59**      **TSI Server Configuration Mode Commands 1023**

do show 1024

end 1025  
 exit 1026  
 ip 1027  
 logging 1028  
 sftp 1029  
 update-time 1030

---

**CHAPTER 60**      **Tunnel Interface Configuration Mode Commands 1031**

description 1032  
 end 1033  
 exit 1034  
 ip address 1035  
 ip ospf authentication-key 1036  
 ip ospf authentication-type 1037  
 ip ospf bfd 1038  
 ip ospf cost 1039  
 ip ospf dead-interval 1040  
 ip ospf hello-interval 1041  
 ip ospf message-digest-key 1042  
 ip ospf network 1043  
 ip ospf priority 1044  
 ip ospf retransmit-interval 1045  
 ip ospf transmit-delay 1046  
 ip vrf 1047  
 ipv6 address 1048  
 tunnel-mode 1049

---

**CHAPTER 61**      **TWAN Profile Configuration Mode Commands 1051**

access-type 1052  
 dictionary 1054  
 do show 1055  
 end 1056  
 exit 1057  
 radius 1058

session-trigger 1060

ue-address 1062

---

**CHAPTER 62**      **UDR Format Configuration Mode Commands**    1063

attribute 1064

do show 1070

end 1071

event-label 1072

exit 1073

rule-variable 1074

---

**CHAPTER 63**      **UDR Module Configuration Mode Commands**    1077

cdr 1078

do show 1083

end 1084

exit 1085

file 1086

---

**CHAPTER 64**      **UIDH Server Configuration Mode Commands**    1093

end 1094

exit 1095

refresh-interval 1096

remote-address 1098

response-timeout 1099

---

**CHAPTER 65**      **Unnumbered Interface Configuration Mode Commands**    1101

description 1102

end 1103

exit 1104

---

**CHAPTER 66**      **Video Group Configuration Mode**    1105

do show 1106

end 1107

exit 1108

keepalive-server 1109  
local-address 1111  
server 1112

---

**CHAPTER 67**    **VLAN Configuration Mode Commands 1113**

bind interface 1114  
do show 1115  
end 1116  
exit 1117  
ingress-mode 1118  
priority 1119  
shutdown 1120  
vlan-map 1121

---

**CHAPTER 68**    **WSG Lookup Priority List Configuration Mode Commands 1123**

do show 1124  
end 1125  
exit 1126  
priority 1127

---

**CHAPTER 69**    **WSG Service Configuration Mode Commands 1129**

associate subscriber-map 1130  
bind address 1131  
deployment-mode 1132  
dhcp 1133  
dns-server 1134  
do show 1135  
duplicate-session-detection 1136  
end 1137  
exit 1138  
initiator-mode-duration 1139  
ip 1140  
ipv6 1142

peer-list 1144  
pre\_fragment mtu 1145  
responder-mode-duration 1146  
Server dhcp 1147

---

**CHAPTER 70****X2-GW Service Configuration Mode Commands 1149**

bind 1150  
do show 1151  
end 1152  
exit 1153  
x2-c 1154







# Command Line Interface Reference, Modes R - Z, StarOS Release 21.16

---

- [Note, on page 2](#)

# Note



---

**Important**

The ASR 5000 hardware platform has reached end of life and is not supported in this release. Any references to the ASR 5000 (specific or implied) or its components in this document are coincidental. Full details on the ASR 5000 hardware platform end of life are available at:  
<https://www.cisco.com/c/en/us/products/collateral/wireless/asr-5000-series/eos-eol-notice-c51-735573.html>

---



# Radio Congestion Policy Configuration Mode Commands

The Radio Congestion Policy Configuration Mode provides the commands to configure the parameters to interpret the congestion indications per TCP flow, the congestion sampling time and reporting frequency.



## Important

In release 20.0, MVG is not supported. Commands in this configuration mode must not be used in release 20.0. For more information, contact your Cisco account representative.

## Command Modes

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy) #
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [congestion-level](#), on page 4
- [correlation-method](#), on page 6
- [data-loss threshold](#), on page 7
- [do show](#), on page 9
- [end](#), on page 10
- [exit](#), on page 11
- [reporting-interval](#), on page 12
- [rtt-samples](#), on page 13
- [rtt-variance](#), on page 14
- [sampling-interval](#), on page 15

# congestion-level

Configures the congestion values for each congestion level — None, Low, Medium, High, and Extreme.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator, Operator, Inspector

---

**Command Modes**

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

**Syntax Description**

**congestion-level low** *low\_value* **medium** *medium\_value* **high** *high\_value* **extreme** *extreme\_value*

**default congestion-level**

**default**

Configures this command with its default setting.

**low** *low\_value*

Specifies the congestion range for low congestion.

*low\_value* must be a number from 1 to 100.

Default: 20

**medium** *medium\_value*

Specifies the congestion range for medium congestion.

*medium\_value* must be a number from 1 to 100.

Default: 40

**high** *high\_value*

Specifies the congestion range for high congestion.

*high\_value* must be a number from 1 to 100.

Default: 60

**extreme** *extreme\_value*

Specifies the congestion range for extreme congestion.

*extreme\_value* must be a number from 1 to 100.

Default: 80

---

**Usage Guidelines**

Use this command to configure the congestion values for each congestion level — None, Low, Medium, High, and Extreme. The congestion level values will be reported to the CAE in order to select a video optimization mechanism suitable for subscriber-side network congestion condition. The congestion level range for NO congestion must be less than 10.

**Example**

The following command configures the values — *10*, *20*, *30* and *40* for Low, Medium, High and Extreme congestion respectively:

```
congestion-level low 10 medium 20 high 30 extreme 40
```

# correlation-method

Configures the correlation method used to correlate multiple flows of a subscriber to calculate the congestion level of a subscriber.

---

**Product** All

---

**Privilege** Security Administrator, Administrator, Operator, Inspector

---

**Command Modes** Exec > ACS Configuration > Radio Congestion Policy Configuration  
**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

**Syntax Description** **correlation-method { mean | optimistic | pessimistic }**  
**default correlation-method**

## default

Configures this command with its default setting.

Default: **mean**

## mean

Configures the mean correlation method. The congestion level is the average across all concurrent TCP flows.

## optimistic

Configures the optimistic correlation method. The congestion level is the lowest value indicated across all the concurrent flows.

## pessimistic

Configures the pessimistic correlation method. The congestion level is the highest value indicated across all concurrent flows.

---

**Usage Guidelines** Use this command to configure the method used to correlate multiple flows of a subscriber to calculate the congestion level of a subscriber. Each flow will have a congestion level and at the end of each reporting interval, the correlation method will be used to correlate all these flows to arrive at a congestion level for the subscriber.

## Example

The following command configures the **optimistic** correlation method:

```
correlation-method optimistic
```

# data-loss threshold

Configures the acceptable data loss percentage in the network.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator, Operator, Inspector

---

**Command Modes**

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

**Syntax Description**

**data-loss threshold** *threshold\_value* **weightage** *weightage\_value*  
**default data-loss**

**default**

Configures this command with its default setting.

**threshold** *threshold\_value*

Configures the percentage of packet loss considered as acceptable in the network. This is used to determine the congestion level to be reported.

*threshold\_value* must be a number from 1 to 99.

Default: 1%

**weightage** *weightage\_value*

Configures the data loss weightage to be given to packet loss while calculating the congestion level for a subscriber.

*weightage\_value* must be a number from 0 to 100.

Default: 50

---

**Usage Guidelines**

Use this command to configure the acceptable percentage of packet-loss in the network, and the data loss weightage to be given to packet loss while calculating the congestion level for a subscriber. Currently, the minimum value allowed to be configured is 1%. This is required to offset the effects of parameters other than the airlink congestion. The congestion primarily occurs at the airlink, but it is also possible at other places in the flow path. The link monitor cannot distinguish between airlink and congestion at any other point. For example, if 1% packet loss is considered normal in some network and if some flow of a subscriber experiences a packet loss of 2%, then it will be considered as a sign of congestion. If some flow of a subscriber has a packet loss of 1% or less, then it is not considered as congestion, as it is in the normal range for that network.

**Example**

The following command sets the packet loss percentage to 1 and the data loss weightage to 50:

```
data-loss threshold 1 weightage 50
```



# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# reporting-interval

Configures the reporting interval in terms of the number of sampling intervals.

---

## Product

All

---

## Privilege

Security Administrator, Administrator, Operator, Inspector

---

## Command Modes

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

## Syntax Description

**reporting-interval** *interval\_value* **min-samples-required** *num\_samples*  
**default reporting-interval**

### default

Configures this command with its default setting.

### reporting-interval *interval\_value*

Specifies the reporting interval in seconds.

*interval\_value* must be a number from 1 to 60.

Default: 5 seconds

### min-samples-required *num\_samples*

Specifies the minimum number of samples required for reporting.

*num\_samples* must be a number from 1 to 60.

Default: 5

---

## Usage Guidelines

Use this command to configure the reporting interval in terms of the number of sampling intervals. This indicates after how many sampling intervals, the report must be generated and reported to external entities like PCRF if required.

### Example

The following command configures the reporting interval as 10 seconds and 5 samples for a subscriber:

```
reporting-interval 10 min-samples-required 5
```

# rft-samples

Configures RTT (Round Trip Time) samples for base RTT.

---

## Product

All

---

## Privilege

Security Administrator, Administrator, Operator, Inspector

---

## Command Modes

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

## Syntax Description

**rft-samples** *min\_samples*  
**default rft-samples**

### default

Configures this command with its default setting.

Default:

### *min\_samples*

Specifies the minimum number of RTT samples for base RTT.

*min\_samples* must be a number from 1 to 20.

---

## Usage Guidelines

Use this command to configure the minimum number of RTT samples for base RTT.

### Example

The following command configures 10 RTT samples:

```
rft-samples 10
```

# rtt-variance

Configures the RTT (Round Trip Time) variance.

---

## Product

MVG

---

## Privilege

Security Administrator, Administrator, Operator, Inspector

---

## Command Modes

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

## Syntax Description

**rtt-variance threshold** *variance\_percent* **weightage** *rtt\_weightage*  
**default** **rtt-variance**

### default

Configures this command with its default setting.

### **rtt-variance threshold** *variance\_percent*

Specifies the RTT acceptable variance percentage.

*variance\_percent* must be a number from 50 to 500.

Default: 100

### **weightage** *rtt\_weightage*

Specifies the weightage to be given to RTT variance while calculating the congestion level of a subscriber.

*rtt\_weightage* must be a number from 0 to 100.

Default: 50

---

## Usage Guidelines

Use this command to configure the RTT variance.

### Example

The following command sets the RTT variance threshold to 60% and weightage to 80:

```
rtt-variance threshold 60 weightage 80
```

# sampling-interval

Configures the sampling interval.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator, Operator, Inspector

---

**Command Modes**

Exec > ACS Configuration > Radio Congestion Policy Configuration

**active-charging service** *service\_name* > **radio-congestion policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-radio-congestion-policy)#
```

---

**Syntax Description**

**sampling-interval** *sampling\_interval*  
**default sampling-interval**

**default**

Configures this command with its default setting.

Default: 5 seconds

**sampling\_interval**

Specifies the sampling interval, in seconds.

*sampling\_interval* must be a number from 2 to 60.

---

**Usage Guidelines**

Use this command to configure the sampling interval. This indicates the interval in seconds at which various TCP parameters are captured to determine the congestion level.

**Example**

The following command specifies a sampling interval of 20 seconds:

```
sampling-interval 20
```

■ sampling-interval





## RANAP Cause Code Group Configuration Mode

Commands in this mode enable the operator to define multiple cause codes for the 3G service.

### Command Modes

Exec > Global Configuration > LTE Policy Configuration > RANAP Cause Code Configuration

**configure > lte-policy > cause-code-group** *group\_name* **protocol ranap**

Entering the above command sequence results in the following prompt:

```
[local] host_name(ranap-cause-code)
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [cause](#), on page 18
- [do show](#), on page 19
- [end](#), on page 20
- [exit](#), on page 21

# cause

Enables the operator to specify one or more cause codes for the 3G service.

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > LTE Policy Configuration > RANAP Cause Code Configuration

**configure > lte-policy > cause-code-group** *group\_name* **protocol ranap**

Entering the above command sequence results in the following prompt:

```
[local] host_name(ranap-cause-code)
```

---

## Syntax Description

**cause** *cause\_code*

**no cause** *cause\_code*

### no

When included with the command, the specified cause code is deleted from the group. If all cause codes are deleted from the group then the group is automatically deleted.

### *cause\_code*

Enter an integer from 1 to 512 to identify a cause code. Valid options are listed in 3GPP TS 25.413 v11.5.0 (or later version), subsection on *Cause* in section for *Radio Network Layer Related IEs*.

---

## Usage Guidelines

A maximum of 16 RANAP protocol cause codes can be defined per group. Note that under each cause code group the maximum number of cause codes (ranap+bssgp+slap) that can be supported is 16.

Benefit of using the cause code group for 3G service is

- *if* the RANAP cause code configured by the operator matches with the cause received in the Iu-Release Request message, and
- *if* the Subscriber Overcharging Protection feature is enabled for 3G service in the SGSN-Service configuration,
- *then* the S4-SGSN includes ARRL (i.e., Abnormal Release of Radio Link) bit in Release Access Bearer Request message initiated on Iu-Release.

## Example

Repeat the command to define multiple cause codes for the group.

```
cause 27
cause 121
cause 200
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

■ exit



## Remote Address List Configuration Mode Commands

---

The Remote Address List Configuration Mode is used to configure address lists for the Remote Address-based Accounting feature on a per-context basis.

### Command Modes

Exec > Global Configuration > Context Configuration > Remote Address List Configuration  
**configure** > **context** *context\_name* > **radius accounting ip remote-address list** *list\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-remaddr-list) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [address, on page 24](#)
- [do show, on page 25](#)
- [end, on page 26](#)
- [exit, on page 27](#)

# address

Configures addresses within a Remote Address List.

---

## Product

PDSN

HA

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Remote Address List Configuration

**configure** > **context** *context\_name* > **radius accounting ip remote-address list** *list\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-remaddr-list)#
```

---

## Syntax Description

[ **no** ] **address** *ip\_address* **netmask** *subnet*

### **no**

Removes a previously configured address.

### ***ip\_address***

Specifies the IP address of the remote device.

*ip\_address* is entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

### **netmask** *subnet*

Specifies the subnet mask of the remote device.

*subnet* is the netmask expressed in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

---

## Usage Guidelines

Use this command to configure remote address lists for use with the Remote Address-based accounting feature. A maximum of 10 address can be configured per list.

### **Example**

The following command adds an IP address of *192.168.100.1* with a subnet mask of *255.255.255.0* to the list:

```
address 192.168.100.1 netmask 255.255.255.0
```



# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

■ exit



# Remote Server List Configuration Mode Commands

---

## Command Modes

The Remote Server List Configuration Mode manages the list of server addresses to which a context has access.

Exec > Global Configuration > Remote Server List Configuration

**configure** > **context** *context\_name* > **remote-server-list** **name** *list\_name*

[*context\_name*] *host\_name* (config-remote-server-list) #



## Important

Available commands or keywords/variables vary based on platform type, product version, and installed license(s).

- [address](#), on page 30
- [do show](#), on page 31
- [end](#), on page 32
- [exit](#), on page 33

# address

Configures or removes an IP address to a remote server.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Remote Server List Configuration

**configure** > **context** *context\_name* > **remote-server-list name** *list\_name*

[*context\_name*] *host\_name* (config-remote-server-list) #

---

## Syntax Description

**address** *remote-ip-address* **netmask** *ip\_netmask*

**no address** *remote-ip-address* **netmask** *ip\_netmask*

### no

Removes the specified IP address from the Remote Server List.

### **remote-ip-address netmask ip\_netmask**

Specifies the IP address and netmask of the remote server in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

---

## Usage Guidelines

Use this command to create and maintain a list of remote servers accessible by this context.

### Example

```
address 193.154.78.9 netmask 255.255.255.0
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

■ exit



# Remote Secret List Configuration Mode Commands

---

## Command Modes

The Remote Secret List Configuration Mode manages the list of for storing remote secrets based on ID type.

Exec > Global Configuration > Remote Secret List Configuration

> **crypto remote-secret-list** *listname*

[*local\_context*] *host\_name*(config-remote-server-list) #

- [do show, on page 36](#)
- [end, on page 37](#)
- [exit, on page 38](#)
- [remote-id, on page 39](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# remote-id

Configures the remote pre-shared key based on the ID type.

---

**Product**

WSG

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Remote Secret List Configuration

> **crypto remote-secret-list** *listname*

*[local\_context]host\_name(config-remote-server-list)#*

---

**Syntax Description**

```
remote-id id-type { der-asn1-dn | fqdn | ip-addr | key-id | rfc822-addr
} id id_value secret [ encrypted ] key key_value
no remote-id id-type { der-asn1-dn | fqdn | ip-addr | key-id | rfc822-addr
} id id_value
```

---

**no**

Removes the specified ID from the remote secret list.

---

**id-type { der-asn1-dn | fqdn | ip-addr | key-id | rfc822-addr }**

Configures the NAI IDr type parameter. If no id-type is specified, then **rfc822-addr** is assumed.

- **der-asn1-dn**: configures NAI Type DER\_ASN1\_DN (Distinguished Encoding Rules, ASN.1 encoding, Distinguished Name)
- **fqdn**: configures NAI Type ID\_FQDN (Internet Fully Qualified Domain Name).
- **ip-addr**: configures NAI Type ID\_IP\_ADDR (IP Address).
- **key-id**: configures NAI Type ID\_KEY\_ID (opaque octet string).
- **rfc822-addr**: configures NAI Type ID\_RFC822\_ADDR (RFC 822 email address).

---

**secret [ encrypted ] key key\_value**

Specifies the use of an encrypted or plain text secret key. *key\_value* is an alphanumeric string of 1 through 255 bytes or a hexadecimal string of 16 to 444 bytes.

---

**Usage Guidelines**

Use this command to enter up to 1000 entries in the remote secret list. Each entry is designated by ID type and ID value. Repeat the command sequence to add entries to the list.

---

**Example**

The following command enters an ip address in the remote secret list:

```
remote-id id-type ip-addr id 10.1.1.1
```







## RLF Template Configuration Mode Commands

Rate Limiting Function (RLF) Template Configuration Mode is accessed from the Global Configuration Mode. This mode allows an operator to configure the RLF template that can be associated with Diameter and other applications for throttling and rate controlling of messages sent to external network interfaces.



---

**Important**

Rate Limiting Function (RLF) is a license-controlled feature. A valid feature license must be installed prior to configuring this feature. Contact your Cisco account representative for more information.

---

---

**Command Modes**

Exec > Global Configuration > RLF Template Configuration

**configure** > **rlf-template** *rlf\_template\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(cfg-rlf-template)#
```



---

**Important**

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [delay-tolerance](#), on page 42
- [do show](#), on page 43
- [end](#), on page 44
- [exit](#), on page 45
- [msg-rate](#), on page 46
- [threshold](#), on page 48

# delay-tolerance

Defines the maximum number of seconds a control plane signaling message can be queued before being processed. After exceeding this delay, the message is dropped.

---

## Product

GGSN  
P-GW  
SaMOG

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > RLF Template Configuration

**configure** > **rlf-template** *rlf\_template\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(cfg-rlf-template)#
```

---

## Syntax Description

**delay-tolerance** *tolerance\_value* [ **-noconfirm** ]  
**default delay-tolerance**

### default

Removes the configuration associated with the RLF template. Default value is 2.

### *tolerance\_value*

Specifies the maximum number of seconds a message can be queued in the RLF module. The message must be sent after expiry of "delay-tolerance" seconds.

*tolerance\_value* must be an integer from 0 through 10. Default value is 2.

### [ **-noconfirm** ]

Specifies that the command must execute without any prompts and confirmation from the user.

---

## Usage Guidelines

Use this command to define the maximum number of seconds a message can be queued in the RLF module before being processed. After exceeding this delay, the message is dropped.

### Example

The following command sets the value of delay tolerance to 4 seconds:

```
delay-tolerance 4
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# msg-rate

Sets the maximum number of messages that can be processed per second.

---

## Product

GGSN  
P-GW  
SaMOG

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > RLF Template Configuration

**configure** > **rlf-template** *rlf\_template\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(cfg-rlf-template) #
```

---

## Syntax Description

**msg-rate** *tps\_value* **burst-size** *size* [ **-noconfirm** ]

### *tps\_value*

Specifies the number of messages that can be processed per second. This is the maximum number of allowed transactions per second (TPS) for an external interface.




---

### Important

The TPS value (configured per external interface) is at a chassis-level and is distributed appropriately to all session managers, AAA manager, Diamproxy, or any other applications that use RLF. RLF employs the Token Bucket Algorithm to achieve the rate limiting.

*tps\_value* must be an integer from 1 through 100000.

### **burst\_size size**

Defines the maximum number of messages (burst) that can be sent out together at any instant of time. If this setting is not configured, the default value is the current message rate.

Burst size is used to derive the shaping interval in such a way that it splits the 1000 ms in N slots, where N can be 1, 2, 4, 5, 10, 20, 50, and 100.

*size* must be an integer from 1 through 100000.

### [ **-noconfirm** ]

Specifies that the command must execute without any prompts and confirmation from the user.

---

## Usage Guidelines

Use this command to define the number of messages that can be processed per second. This is the maximum number of allowed transactions per second (TPS) for an external interface. The RLF ensures that the maximum configured TPS rate is not exceeded on the interface.

If burst-size is not configured, the messages are sent without delay when they arrive in RLF. For example, if the CLI command **msg-rate 1000 burst-size 100** is configured, then all 1,000 messages are sent to an external

interface in bursts of 100 messages (burst-size). If the burst size is not configured, then all 1,000 messages are sent as they arrive in RLF (regardless of TPS).

**Example**

The following command sets the value of message rate to 20:

```
msg-rate 20
```

# threshold

Configures the threshold for rate-limiting the outgoing messages.

---

## Product

GGSN  
P-GW  
SaMOG

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > RLF Template Configuration

**configure** > **rlf-template** *rlf\_template\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(cfg-rlf-template)#
```

---

## Syntax Description

```
threshold { lower lowerThreshold_value | upper upperThreshold_value } [ -noconfirm ]  
default threshold
```

### default

Returns the command to its default settings.

### lower *lowerThreshold\_value*

This threshold indicates that the application has message-rate control enabled.

Default is 30%. If the number of outstanding messages in the RLF queue drops below 30% of msg-rate, RLF will transition to READY state.

### upper *upperThreshold\_value*

This threshold indicates that action will be taken when the message-rate reaches the maximum limit.

Default is 80%. If the number of outstanding messages in the RLF queue exceeds 80% of msg-rate, RLF will transition to OVER\_THRESHOLD state.

---

## Usage Guidelines

Use this command to configure the desired threshold value for rate limiting the outgoing messages.

The configurable threshold value of TPS for an interface is used to notify applications of corrective actions when the threshold criteria is met.

### Example

The following command configures the upper threshold to 80 and the lower threshold to 60 for throttling and rate control:

```
threshold upper 80 lower 60
```





## RNC Configuration Mode Commands

### Command Modes

The RNC (radio network controller) configuration mode defines the parameters related to the SGSN connection with an RNC.

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



### Note

From R15.0 onwards, License Control is implemented on all Network Sharing related commands.

- [associate-gtpu-bind-address](#), on page 51
- [description](#), on page 52
- [direct-tunnel](#), on page 53
- [do show](#), on page 54
- [dual-address-pdp](#), on page 55
- [enb-data-forward](#), on page 57
- [enb-direct-data-forward](#), on page 58
- [end](#), on page 59
- [exit](#), on page 60
- [lac](#), on page 61
- [mbms](#), on page 62
- [overload-action disable](#), on page 63
- [paging-non-searching-indication](#), on page 66
- [pointcode](#), on page 67
- [pooled](#), on page 68
- [rab-asymmetry-indicator](#), on page 69
- [rab-modify-procedure](#), on page 71

- [ranap arp-ie](#), on page 73
- [ranap bidirectional-always](#), on page 74
- [ranap eutran-service-handover-ie](#), on page 75
- [ranap global-cn-id](#), on page 77
- [ranap paging-area-id](#), on page 79
- [ranap paging-cause-ie](#), on page 80
- [ranap rab-arsp-ue-radio-lost](#), on page 83
- [ranap rab-release-with-radiolost](#), on page 84
- [ranap rfsp-id-ie](#), on page 85
- [ranap signalling-indication-ie](#), on page 86
- [ranap ue-ambr-ie](#), on page 87
- [ran-information-management](#), on page 88
- [release-compliance](#), on page 89
- [reset-resource](#), on page 91

# associate-gtpu-bind-address

This command defines the GTP-U loopback address and associates (binds) this address with a particular interface (non-loopback) address.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration  
**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

**Syntax Description** [ **no** ] **associate-gtpu-bind-address** *ip\_address* **to-interface-address** *ip\_address*

**no**

Removes the loopback address definition and interface association from the current RNC configuration.

***ip\_address***

*ip\_address*: Must be specified using the standard IPv4 dotted decimal notation.

**Usage Guidelines** Use this command to setup associations between loopback GTP-U addresses and a non-loopback addresses.

## Example

Bind the GTP-U loopback address of *123.1.1.1* to interface address *222.1.1.1*:

```
associate-gtpu-bind-address 123.1.1.1 to-interface-address 222.1.1.1
```

## description

This command defines an alphanumeric string that is intended to provide descriptive information about the radio network controller (RNC). This is used for operator reference only.

---

### Product

SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

### Syntax Description

**description** *string*  
**no description**

#### **no**

Removes the description string from the current RNC configuration.

#### **string**

Specifies the alphanumeric string that is stored. must be from 1 through 255 alphanumeric characters. Strings with spaces must be enclosed in double-quotes. See the example below.

---

### Usage Guidelines

Use this command to set a description for reference by operators.

### Example

The following command sets the description to identify a particular RNC and carrier in Uganda "RNC1 Carrier2 Uganda":

```
description "RNC1 Carrier2 Uganda"
```

# direct-tunnel

This command enables/disables the direct tunnel feature through the interface to the radio network controller (RNC).

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description** **direct-tunnel not-permitted-by-rnc**  
**default direct-tunnel**

## default

Sets the direct tunnel support on RNC to default mode; i.e. enabling direct tunnel.

## not-permitted-by-rnc

Default: enabled

Disables the direct-tunnel support on radio network controller (RNC).

---

**Usage Guidelines** Use this command to disable/enable the direct-tunnel function through the interface to the RNC.

## Example

Following command disables the direct tunnel support to the RNC:

```
direct-tunnel not-permitted-by-rnc
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# dual-address-pdp

This command enables the SGSN to work with an RNC with functioning dual address (IPv4v6) bearer support capability. By default, it is assumed that the RNC does not support dual PDP-type addressing.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context *context\_name* > iups-service *service\_name* > rnc id *rnc\_id***

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

**Syntax Description** **dual-address-pdp { not-supported | supported }**  
**default dual-address-pdp**

## default

Resets the SGSN to function with an RNC that is not supporting dual PDP addressing.

## not-supported

Default

Enables the SGSN to work with an RNC that does not support dual PDP-type addressing. It allows a single address bearer PDP-type to be activated with a configured PDP-type.

## supported

Enables the SGSN to work with an RNC that does support dual PDP-type addressing.

## Usage Guidelines

This command enables the SGSN to support dual PDP-type addressing (IPv4v6) per RNC.

For a dual PDP context to be activated, the RNC should support the PDP-type IPv4v6 in the RAB assignment request. For an RNC that does support the dual PDP-type addressing, use this command to change the default configuration and to configure the SGSN to work with the RNC's dual address bearer support capability.

If the RNC does not support this functionality, then the **default** form of this command should be configured to enable the SGSN to activate a single-address bearer PDP context even if (1) the UE requests PDP type IPv4v6 and if (2) the subscription allows this PDP type. The single address bearer PDP type will be activated with a configured PDP type.

When a UE moves from an RNC that supports dual PDP-type addressing to another RNC that does not support dual PDP-type addressing, then the SGSN will deactivate the PDP context. This is done because, even if we preserve the PDP contexts, the UE would be unaware of the preserved PDP context. This would lead to non-synchronized behavior in the network. So the SGSN deactivates the PDP context with cause code "reactivation-required" to ensure the UE, RNC, SGSN, and GGSN are in synch. As well, this gives the UE the opportunity to activate a PDP context again without dual bearers.

The **sgsn-rnc-no-dual-pdp-init-pdp-deact** disconnect reason is used to indicate that a PDP context has been deactivated because of roaming into an RNC that does not support this feature.

**Important**

For this configuration to function, support for dual PDP-type addressing must be enabled at the global level (the default). To confirm the functionality is enabled, issue the **show sgsn-mode** command from the Exec mode. If the PDP-type addressing is not enabled, then refer to the instructions for the **dual-address-pdp** command in the *SGSN Global Configuration Mode Commands* section.

**Example**

Use the following command to enable dual PDP-type addressing with a supporting RNC:

```
dual-address-pdp supported
```



# enb-data-forward

Use this command to enable forwarding of data from this RNC to eNodeB.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc) #
```

---

**Syntax Description**

[no] **enb-data-forward**

[ no ]

Disables the forwarding of data from this RNC to eNodeB.

**enb-data-forward**

Enables the forwarding of data from this RNC to eNodeB.

---

**Usage Guidelines**

Use this command to configure forwarding of data from the RNC to eNodeB

**Example**

Use the following command to enable forwarding of data from this RNC to eNodeB.

**enb-data-forward**

## enb-direct-data-forward

Selects the setup of indirect data forwarding tunnels (IDFT) between the eNodeB and the RNC via the SGW during SRNS relocation, or, selects the use of direct data forwarding.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

**Syntax Description** [no] **enb-direct-data-forward**

[ no ]

Disables direct data forwarding and enables the setup of indirect data forwarding tunnels between the eNodeB and the RNC via the SGW during SRNS relocation. This allows the S4-SGSN to support connected mode handovers between the UTRAN and E-UTRAN networks across the S3 interface. This is the default setting.

### enb-direct-data-forward

Enables the use of direct data forwarding between the eNodeB and the RNC via the SGW. If this setting is configured and the SGSN receives a Relocation Required message from this RNC for a subscriber with target node as an eNodeB, then the SGSN will set the indication->DFI (direct forwarding indicator) flag in the Forward Relocation Request message sent across the S3 interface. Use of this command disables the setup of indirect data forwarding tunnels.

### Usage Guidelines

Use this command to enable the setup of direct data forwarding tunnels between the eNodeB and the RNC during inter RAT connected mode handover. Enabling direct data forwarding tunnels allows the S4-SGSN to support connected mode handovers between the UTRAN and E-UTRAN networks across the S3 interface without the use of indirect data forwarding tunnels through SGW. Once direct data forwarding is enabled, indirect data forwarding is automatically disabled.

### Example

Enable the setup of indirect data forwarding tunnels between the eNodeB and RNC via the SGW during SRNS relocation. This command also disables direct data forwarding.

```
no enb-direct-data-forward
```

# end

Exits the configuration mode and returns to the Exec mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Change the mode to the Exec mode.

# exit

Exits the current configuration mode and returns to the IuPS Service configuration mode.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Return to the previous configuration mode.

# lac

This command identifies a Local Area Concentrator (LAC) and a Remote Area Concentrator (RAC) and associates them with this RNC definition.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration  
**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description** [ **no** ] **lac** *lac\_id* **rac** *rac\_id*

**no**

Deletes the LAC and RAC information from the system configuration.

***lac\_id***

A unique numeric identifier for the LAC associated with the RNC.

*lac\_id* must be an integer between 1 and 65535.

***rac\_id***

A unique numeric identifier for the RLAC associated with the RNC.

*rac\_id* must be an integer between 1 and 255.

---

**Usage Guidelines** Creates an association with a specific LAC and RAC.

**Example**

Associate LAC *545* and RAC *23* with this RNC:

```
lac 545 rac 23
```

# mbms

Configures RNC options for multimedia broadcast multicast service.



---

**Important**

This feature and command are currently under development and are not supported.

---

---

**Product**

SGSN

# overload-action disable

This command maps an action to be taken if traffic reaches or exceeds defined levels.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration <b>configure &gt; context</b> <i>context_name</i> > <b>iups-service</b> <i>service_name</i> > <b>rnc id</b> <i>rnc_id</i> Entering the above command sequence results in the following prompt: <pre>[<i>context_name</i>]<i>host_name</i>(config-ctx-iups-service-rnc)#</pre>
<b>Syntax Description</b>	<pre><b>overload-action disable</b> { <b>activate</b>   <b>attach</b>   <b>auth-challenge</b>   <b>modify-request</b>   <b>paging-downlink-data</b>   <b>ptmsi-reallocation</b>   <b>service-request-data</b>   <b>sms</b>   <b>srns</b> } <b>traffic-level</b> <i>traffic-level</i> [ <b>no</b>   <b>default</b> ] <b>overload-action disable</b> { <b>activate</b>   <b>attach</b>   <b>auth-challenge</b>   <b>modify-request</b>   <b>paging-downlink-data</b>   <b>ptmsi-reallocation</b>   <b>service-request-data</b>   <b>sms</b>   <b>srns</b> }</pre> <p><b>no</b></p> <p>Removes the defined overload action from configuration.</p> <p><b>default</b></p> <p>Resets the traffic level to the default level for the associated overload action.</p> <p><b>activate traffic-level <i>traffic-level</i></b></p> <p>The system rejects new requests to activate PDP contexts if the defined traffic-level is exceeded.  <i>traffic-level</i>: An integer 1 to 15.          Default: 14</p> <p><b>attach traffic-level <i>traffic-level</i></b></p> <p>The system rejects new requests for GPRS attach if the defined traffic-level is exceeded.  <i>traffic-level</i>: An integer 1 to 15.          Default: 15</p> <p><b>auth-challenge traffic-level <i>traffic-level</i></b></p> <p>The system skips performing authentication challenges if the defined traffic-level is exceeded.  <i>traffic-level</i>: An integer 1 to 15.          Default: 4</p>

**modify-request traffic-level**

The system rejects requests to modify a PDP context if the defined traffic-level is exceeded.

*traffic-level*: An integer 1 to 15.

Default: 12

**paging-downlink-data traffic-level traffic-level**

If the defined traffic-level is exceeded, then paging is not performed for data during downlinks if RABs are not available.

*traffic-level*: An integer 1 to 15.

Default: 11

**ptmsi-reallocation traffic-level traffic-level**

The system skips performing ptmsi-reallocation if the defined traffic-level is reached or exceeded.

*traffic-level*: An integer from 1 to 15.

Default: 4

**service-request-data traffic-level traffic-level**

The system rejects service requests to accept data and establish new RABs if the defined traffic-level is reached or exceeded.

*traffic-level*: An integer from 1 to 15.

Default: 10

**sms traffic-level traffic-level**

The system rejects SMS signaling if the defined traffic-level is reached or exceeded.

*traffic-level*: An integer 1 to 15.

Default: 8

**srns traffic-level traffic-level**

The SGSN rejects/disables SRNS if the target RNC is in overload at the specified traffic level. This keyword setting is effective for both Inter-SGSN SRNS and Intra-SGSN SRNS.

*traffic-level*: An integer 1 to 15.

Default: 15

**Usage Guidelines**

This command defines traffic levels and the actions to take if traffic exceeds the defined levels. The command can be re-entered multiple times to create individual definitions for each type of traffic level and action.

**Example**

Use the following to instruct the system to reject service requests to establish new RABs if the traffic level reaches 3:



```
overload-action disable service-request-data traffic-level 3
```

# paging-non-searching-indication

This command instructs the SGSN to include the non-searching indicator flag in the page-request message.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

```
paging-non-searching-indication { non-searching | searching }  
[ no | default ] paging-non-searching-indication
```

**no | default**

This is the default. Entering no or default with this command disables the inclusion of the flag.

**non-searching**

Set the non-searching-indication to non-searching in the page-request message.

**searching**

Set the non-searching-indication to searching in the page-request message.

---

**Usage Guidelines**

Use this command to determine which type of search indicator flag will be included in the page-request message.

**Example**

Use this command to include the non-searching flag in page-request messages:

```
paging-non-searching-indication non-searching
```

# pointcode

Configures the point code of the RNC.

The access protocol that is part of the IuPS Service configuration mode must be configured prior to defining the RNC's point code.

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > IuPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc) #
```

---

## Syntax Description

**pointcode** *pt\_code*  
**no pointcode**

**no**

Deletes the RNC's point code information from the system configuration.

***pt\_code***

Point code in dotted-decimal format :

- ITU Range 0.0.1 to 7.255.7
- ANSI Range 0.0.1 to 255.255.255
- TTC Range 0.0.1 to 15.31.255
- string of 1 to 11 characters

---

## Usage Guidelines

Use this command to identify the point code of the associated RNC.

### Example

Identify the pointcode for this RNC as *1.234.2*:

```
pointcode 1.234.2
```

# pooled

Configure an RNC as either 'pooled' or 'non-pooled'.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

**pooled**  
 [ **default** | **no** ] **pooled**

**default** | **no**

Entering either **default** or **no** returns the RNC configuration to the default 'non-pooled' state.

---

**Usage Guidelines**

Each RNC, one-at-a-time, can be identified as 'pooled' -- as participating within an SGSN pool -- or 'non-pooled'. Pooled RNCs can co-exist with non-pooled RNCs.

**Example**

Identify this RNC as being part of an SGSN pool:

```
pooled
```

# rab-asymmetry-indicator

Configures the SGSN to force "Asymmetric-Bidirectional" as the RAB Asymmetry Indicator when uplink/downlink bitrates are equal.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

## Syntax Description

```
rab-asymmetry-indicator symmetric-bidirectional  
force-asymmetric-bidirectional  
no rab-asymmetry-indicator symmetric-bidirectional  
force-asymmetric-bidirectional  
default rab-asymmetry-indicator
```

### default | no

Disables the override and sets the indicator based on the symmetry of the bitrates as described for the Default Functionality below.

## Usage Guidelines

This command defines an override that uses "Asymmetric-Bidirectional" as the RAB Asymmetry Indicator when uplink/downlink bitrates are equal (default functionality item #1). This overrides the default functionality (see below) for the RAB indicator in the RAB Assignment Request.

As a result of using this override command, two sets of bitrates, one for downlink and one for uplink, will be included in RAB Assignment Requests for establish or modify per 3GPP TS 25.413.

**Default Functionality:** The SGSN sets the value of the RAB Asymmetry Indicator based on symmetry of negotiated maximum bitrates in the following manner:

- If the uplink and downlink bitrates are equal, then it is set to "Symmetric-Bidirectional".
- If uplink bitrate is set to 0 kbps, then it is set to "Asymmetric-Unidirectional-Downlink".
- If downlink bitrate is set to 0 kbps, then it is set to "Asymmetric-Unidirectional-Uplink".
- If the uplink and downlink bitrates are non-zero and different, then it is set to "Asymmetric-Bidirectional".

## Example

Override the use of the "Symmetric-Bidirectional" RAB Asymmetry Indicator for equal up/downlink bitrates with the following command:

```
rab-asymmetry-indicator symmetric-bidirectional  
force-asymmetric-bidirectional
```

Disable the override with the following command:

```
no rab-asymmetry-indicator symmetric-bidirectional  
force-asymmetric-bidirectional
```

# rab-modify-procedure

This command configures how the RAB (radio access bearer) assignment procedure will be modified.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

```
rab-modify-procedure { normal-modify [ data-vol-report-ind-ie | pdp-type-info-ie ] | release-and-establish }
default rab-modify-procedure
no rab-modify-procedure normal-modify [ data-vol-report-ind-ie | pdp-type-info-ie ]
```

**default**

Resets the configuration to use 'release-and-establish', the SGSN's default RAB Assignment modification procedure.

**normal-modify**

Selects the normal modification procedure for RAB assignment. Either one of two IE options can be included:

- **data-vol-report-ind-ie** sends the "Data Volume Reporting Indication IE" as part of the modification request of the RAB Assignment Request procedure.
- **pdp-type-info-ie** sends the "PDP Type Information IE" as part of the modification request of the RAB Assignment Request procedure.

**release-and-establish**

Instructs the system to release and establish the RAB procedure.

In the case of S4-SGSN, SGSN does not send the Release Access Bearer Request to the S-GW as the RAB is immediately re-established after the release of RAB in direct tunnel.

---

**Usage Guidelines**

Set the type of modification procedure to be used to establish the radio access bearer (RAB) assignment.

The command can be issued multiple times to configure either or both IEs for 'normal-modify' procedure.

The effect of adding the **no** prefix to the command depends on the keyword options included with the command:

- **no rab-modify-procedure normal-modify** disables a previously configured normal modify procedure and sets the configuration to use the default RAB Assignment modification procedure (**release-and-establish**).

- **no rab-modify-procedure normal-modify data-vol-report-ind-ie** changes the configuration to disable sending "Data Volume Reporting Indication IE" in the RAB Assignment request for modification. NOTE: This command does not change the use of the normal RAB modification procedure (**normal-modify**).
- **no rab-modify-procedure normal-modify pdp-type-info-ie** changes the configuration to disable sending "PDP Type Information IE" in the RAB Assignment request for modification. NOTE: This command does not change the use of the normal RAB modification procedure (**normal-modify**).

Use either of the following commands to verify the current configuration for type of RAB Assignment modification procedure, and if optional IEs are to be used:

- **show configuration verbose**
- **show iups-service**

### Example

Use the following command to enable 'normal-modify' as the modification procedure to be used for RAB Assignment:

```
rab-modify-procedure normal-modify
```

Use the following command to configure 'release-establish' as the modification procedure to be used by the SGSN for RAB Assignments:

```
default rab-modify-procedure
```

Use the following command to enable the "Data Volume Reporting Indication IE" as part of the normal modification request of the RAB Assignment Request procedure.

```
rab-modify-procedure normal-modify data-vol-report-ind-ie
```



# ranap arp-ie

This command enables or disables the inclusion of ARP-IE in RAB assignment / Relocation request RANAP messages per RNC.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc) #
```

---

**Syntax Description** **ranap arp-ie**  
[ **default** | **no** ] **ranap arp-ie**

## **default**

Returns the configuration to the default setting, the inclusion of ARP-IE in RAB assignment / Relocation request RANAP messages is disabled.

## **no**

Disables the inclusion of ARP-IE in RAB assignment / Relocation request RANAP messages per RNC.

## ranap bidirectional-always

Enables or disables sending of extended bitrates bi-directionally. When this command is enabled, the specified extended bitrates (MBR or GBR) are included bi-directionally (uplink and downlink directions) in the RAB Assignment Request even if the negotiated bitrate indicates that extended bitrates should be included in one direction.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; luPS Service Configuration &gt; RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

**ranap bidirectional-always ext-mbr-ie [ext-gbr-ie]**  
**no ranap bidirectional-always**

**no**

Disables sending of both extended MBR and GBR bi-directionally.

**ranap bidirectional-always ext-mbr-ie**

When this command is configured, if the maximum bitrate for either uplink or downlink directions indicates that extended bitrates should be included (that is, the maximum bitrate negotiated value exceeds "16" Mbps in either uplink or downlink direction), then the maximum bitrate extended IE is included in both uplink and downlink directions. If in one direction (uplink or downlink) the negotiated value does not exceed "16" Mbps then extended maximum bitrate is sent as "16000001".

**ext-gbr-ie**

Enables sending of Extended Guaranteed Bitrates IE.

---

**Usage Guidelines**

Configure this command to include the extended bitrates in both directions when it is present in one direction.

**Example**

Use the following command to include extended MBR bitrates bi-directionally in the RAB Assignment Request:

```
ranap bidirectional-always ext-mbr-ie
```

# ranap eutran-service-handover-ie

Enables/disables the inclusion of the E-UTRAN Service Handover Information Element in RAB Assignment Request messages (during the PDP activation phase) and Relocation Request RANAP messages (during the SRNS relocation phase). This ensures that an SRNS relocation handover to E-UTRAN is not allowed for E-UTRAN capable UEs that have only a UTRAN/GERAN roaming agreement in place.

---

**Product**

SGSN

---

**Privilege**

Administrator, Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration  
**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

**ranap eutran-service-handover-ie**  
**[ default | no ] ranap eutran-service-handover-ie**

**ranap eutran-service-handover-ie**

Enables the inclusion of the E-UTRAN Service Handover Information Element in RAB Assignment Request (during the PDP activation phase) and Relocation Request RANAP messages (during the SRNS relocation phase). The IE in the RAB Assignment Request during the PDP activation phase informs the RNC not to handover the subscriber to E-UTRAN. The IE in Relocation Request is sent when there is an intra- SGSN SRNS or inter-SGSN SRNS relocation within the UTRAN itself so that the target RNC knows that it shall not handover the subscriber to E-UTRAN.

**no ranap eutran-service-handover-ie**

Specifies that the SGSN will not include the E-UTRAN Service Handover IE in RAB Assignment Request and Relocation Request RANAP messages.

**default**

Returns the configuration to the default setting. The inclusion of the E-UTRAN Service Handover Information Element in RAB Assignment Request and Relocation Request RANAP messages is disabled.

**no**

Disables the inclusion of the E-UTRAN Service Handover Information Element in RAB Assignment Request and Relocation Request RANAP messages is disabled.

---

**Usage Guidelines**

Use this feature to prevent handovers to E-UTRAN in the following scenarios:

1. A UE is E-UTRAN capable, the PLMN is E-UTRAN capable, but the UE has not subscribed to EPS services (no 4G subscription available).
2. The VPLMN is E-UTRAN-capable, and the UE of an inbound roamer is E-UTRAN capable, but the UE has only a UTRAN/GERAN roaming agreement in place.

Enabling this parameter helps ensure that an SRNS relocation handover to E-UTRAN is not allowed for E-UTRAN capable UEs that have only a UTRAN/GERAN roaming agreement. This results in an elimination of potential service denial or disruption issues, and unnecessary signaling.

The following commands and features must be executed before enabling the **ranap eutran-service-handover-ie** setting:

- The SRNS relocation feature must be configured in *Call Control Profile Configuration Mode* via the **srns-inter** and/or **srns-intra** commands.
- The **eutran-not-allowed** flag must be enabled in the access-restriction-data command in *Call Control Profile Configuration Mode*.
- The call-control-profile must then be associated with an operator policy via the **associate** command in *Operator Policy Configuration Mode*.

### Example

This example enables the inclusion of the E-UTRAN Service Handover IE in RAB Assignment Request and Relocation Request RANAP messages.

```
ranap eutran-service-handover-ie
```

# ranap global-cn-id

This command configures the SGSN to use include the Global Core Network ID IE in the various messages.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

```
ranap global-cn-id { paging-request | relocation-request | reset-procedure
| reset-resource-procedure } [ network-sharing selected-plmn ]
[ default | no ] ranap global-cn-id { paging-request | relocation-request
}
```

**default**

Returns the configuration to the default setting and sends the common-plmn in the Global CN ID IE.

**no**

Disables sending the Global CN ID IE.

**paging-request**

Instructs the SGSN to send the Global CN ID IE in the Paging Request message.

**relocation-request**

Instructs the SGSN to send the Global CN ID IE in the Relocation Request message.

**reset-procedure**

Instructs the SGSN to send the Global CN ID IE in the Reset/Ack message.

**reset-resource-procedure**

Instructs the SGSN to send the Global CN ID IE in the Reset-Resource/Ack message.

**network-sharing selected-plmn**

Instructs the SGSN to send the selected-plmn in the Global CN ID IE *if* network sharing has been enabled.

---

**Usage Guidelines**

Use this command to configure the SGSN to use 'selected-plmn' in the Global Core Network ID IE in various messages when network sharing is enabled.

**Example**

Use the following command to include the global-cn-id IE in a Paging Request with the common PLMN when network sharing is enabled :

```
default ranap global-cn-id paging-request
```

Use the following command to include global-cn-id IE in Relocation Request with the selected-plmn (assumes network sharing has been enabled):

```
ranap global-cn-id relocation-request network-sharing selected-plmn
```

# ranap paging-area-id

This command configures the SGSN to use include the Paging Area ID IE in the Paging Request message.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

```
ranap paging-area-id paging-request [ network-sharing selected-plmn ]
[ default | no ] ranap paging-area-id paging-request [ network-sharing
selected-plmn ]
```

**default**

Returns the configuration to the default setting and sends the common-plmn in the Paging Area ID IE.

**no**

Disables sending the Paging Area ID IE.

**paging-request**

Instructs the SGSN to send the Paging Area ID IE in the Paging Request message.

**network-sharing selected-plmn**

Instructs the SGSN to send the selected-plmn in the Paging Area ID IE *if* network sharing has been enabled.

---

**Usage Guidelines**

Use this command to configure the SGSN to use 'selected-plmn' in the Paging Area ID IE in the Paging Request message when network sharing is enabled.

**Example**

Use the following command to include the paging-area-id IE in a Paging Request with the common PLMN when network sharing is enabled :

```
default ranap paging-area-id paging-request
```

Use the following command to include global-cn-id IE in Paging Request with the selected-plmn (assumes network sharing has been enabled):

```
ranap global-cn-id paging-request network-sharing selected-plmn
```

## ranap paging-cause-ie

This command sets the paging cause value and either includes or suppresses the Paging Cause IE in responses to Paging Requests due to various sources. This command is available in releases 8.1 and higher.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

### Syntax Description

```
ranap { paging-cause-ie { all | background-data [ value ] |
conversational-data [ value ] | gmm-signalling [ value ] | gs-signalling [
value ] | interactive-data [ value ] | mme-signalling [ value ] |
sm-signalling [ value ] | sms-signalling [ value ] | streaming-data [ value
] }
[ default | no ] ranap { paging-cause-ie { all | background-data |
conversational-data | gmm-signalling | gs-signalling | interactive-data
| mme-signalling | sm-signalling | sms-signalling | streaming-data }
```

#### default

Resets the specific parameters value to default.

#### no

Suppresses the Paging Cause IE so that it is not included in responses to Paging Requests from respective sources.

#### all

Using **all** sets the action for the Paging Cause IE value for all paging due to all sources.

#### background-data [ value ]

Default: 3 (terminating background call)

Set the Paging Cause IE value for paging due to background data.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

#### conversational-data [ value ]

Default: 5 (terminating high priority signaling)

Set the Paging Cause IE value for paging due to conversational data.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.



**gmm-signalling [ value ]**

Default: 5 (terminating high priority signaling)

Set the Paging Cause IE value for paging due to gmm-signaling.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**gs-signalling [ value ]**

Default: 5 (terminating high priority signaling)

Set the Paging Cause IE value for paging due to VLR Paging Request.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**interactive-data [ value ]**

Default: 2 (terminating interactive call)

Set the Paging Cause IE value for paging due to interactive data.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**mme-signalling [ value ]**

Default: 5 (terminating high priority signaling)

Sets the Paging Cause IE value for paging from MME due to Circuit Switch Fallback (CSFB).

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**sm-signalling [ value ]**

Default: 5 (terminating high priority signaling)

Set the Paging Cause IE value for paging due to SM signaling.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**sms-signalling [ value ]**

Default: 4 (terminating low priority signaling)

Set the Paging Cause IE value for paging due to SMS signaling.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**streaming-data [ value ]**

Default: 5 (terminating high priority signaling)

Set the Paging Cause IE value for paging due to streaming data.

*value* : Must be an integer from 0 to 5. See Paging Cause value mapping in Usage section.

**Usage Guidelines**

This command can be used to set the value (meaning) of the Paging Cause IE included in responses to Paging Requests or it can be used to suppress the inclusion of the Paging Cause IE in the responses. These actions can be configured for paging for all sources or for a specified source.

The following values are applicable to all Paging Cause IEs:

- 0 - Terminating conversational call
- 1 - Terminating streaming call
- 2 - Terminating interactive call
- 3 - Terminating background call
- 4 - Terminating low priority signaling
- 5 - Terminating high priority signaling

### Example

Use the following command to set Paging Cause value to 3 for paging due to GMM signaling without affecting cause values for other sources:

```
ranap paging-cause-ie gmm-signalling 3
```

Use the following command to suppress the Paging Cause IE from all Paging Requests to the RNC:

```
no ranap paging-cause-ie all
```

Either of the following commands will cause the Paging Cause IE to be included in Paging Requests with the default value for SM signaling without affecting the cause for other sources:

```
ranap paging-cause-ie sm-signalling  
default ranap paging-cause-ie sm-signalling
```

# ranap rab-arsp-ue-radio-lost

This command configures the Iu Release Command when SGSN receives the RAB Assignment Response with cause 46 "Radio Connection with UE Lost".

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > IuPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc) #
```

**Syntax Description** [ **no** ] **ranap rab-arsp-ue-radio-lost**

**no**

When **no ranap rab-arsp-ue-radio-lost** is configured, SGSN will send the RAB Assignment Request with cause RAB Release to RNC.

**Usage Guidelines**

Use this command to enable or disable handling of the RAB Assignment Response with cause 46 "Radio Connection With UE Lost". SGSN sends the Iu Release Command with normal cause to RNC when it receives the RAB Assignment Response with cause 46.


This command is disabled by default.



**Note** This command applies to Gn-SGSN only.

## ranap rab-release-with-radiolost

This command configures the Iu Release Command when SGSN receives the RAB Release Request with cause 46 "Radio Connection with UE Lost".

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > Context Configuration > IuPS Service Configuration > RNC Configuration <b>configure</b> > <b>context</b> <i>context_name</i> > <b>iups-service</b> <i>service_name</i> > <b>rnc id</b> <i>rnc_id</i> Entering the above command sequence results in the following prompt: <pre>[context_name]host_name(config-ctx-iups-service-rnc)#</pre>
<b>Syntax Description</b>	[ no ] <b>ranap rab-release-with-radiolost</b>  <b>no</b> When <b>no ranap rab-release-with-radiolost</b> is configured, SGSN will send the RAB Assignment Request with cause RAB Release to RNC.
<b>Usage Guidelines</b>	Use this command to enable or disable handling of the RAB Release Request with cause 46 "Radio Connection With UE Lost". SGSN sends the Iu Release Command to RNC when it receives the RAB Release Request with cause 46.  This command is disabled by default.
 <b>Note</b>	This command applies to Gn-SGSN only.

# ranap rfsp-id-ie

Configure this command to enable or disable the inclusion of the Subscriber Profile ID for RAT/Frequency priority IE in RANAP Direct transfer Extension and Common Id. Extension messages.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure** > **context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

**Syntax Description** **ranap rfsp-id-ie**  
**no ranap rfsp-id-ie**

**no**

Instructs the SGSN to exclude the Subscriber Profile ID for RAT/Frequency priority IE in RANAP Direct transfer Extension and Common Id Extension messages.

**rfsp-id-ie**

This keyword enables the Subscriber Profile ID for RAT/Frequency priority IE to be inserted in outbound RANAP Direct transfer Extension and Common Id Extension messages.

**Usage Guidelines**

Inclusion of RFSP ID IE is disabled by default in RANAP Direct transfer extension and Common ID Extension. Configure the keyword **rfsp-id-ie** to include Subscriber Profile ID for RAT/Frequency priority IE in RANAP Direct transfer Extension and Common Id Extension messages.

**Example**

Use the following command to include Subscriber Profile ID for RAT/Frequency priority IE in outbound RANAP Direct transfer Extension and Common Id Extension messages.

```
ranap rfsp-id-ie
```

# ranap signalling-indication-ie

This command enables/disables the inclusion of the Signaling Indication IE in either or both the RAB Assignment Request and/or the Relocation Request RANAP messages.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration <b>configure &gt; context</b> <i>context_name</i> > <b>iups-service</b> <i>service_name</i> > <b>rnc id</b> <i>rnc_id</i>

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

<b>Syntax Description</b>	<b>ranap signalling-indication-ie</b> { <b>rab-assignment-request</b> [ <b>relocation-request</b> ]   <b>relocation-request</b> [ <b>rab-assignment-request</b> ] } <b>no ranap signalling-indication-ie</b> <b>default ranap signalling-indication-ie</b>
---------------------------	--

## no

Sets the configuration so that the SGSN never includes the IE.

## default

Resets the configuration to the default - the SGSN includes the IE in the messages if preconditions are met (see Usage section).

## rab-assignment-request | relocation-request

Including one or both of these keywords configures what type of RANAP message will include the IE.

<b>Usage Guidelines</b>	The command enables the operator to determine whether the signalling indication information element is included in either or both the RAB Assignment Request and Relocation Request messages during the PDP context setup procedure.
-------------------------	--

For this command configuration to work so that the IE is included, two preconditions must be met:

- Received QoS traffic class for the context must be interactive
- Received QoS has a signalling indication value as optimized

When an RNC receives this IE, the RNC assumes that the customer is using IMS signaling and allocates massive amounts of bandwidth, potentially causing cell congestion. This command enables the operator to determine the usage of this IE which provides the operator with additional session management control.

## Example

Use the following command to include the signalling indication IE in the RAB Assignment Request:

```
ranap signalling-indication-ie rab-assignment-request
```

# ranap ue-ambr-ie

Enables the SGSN to include UE AMBR IE when sending RANAP messages.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

---

**Syntax Description**

[ no ] **ranap ue-ambr-ie**

**no**

Returns to the default functionality by disabling the sending of the UE AMBR IE.

---

**Usage Guidelines**

This command allows the operator to determine if the UE AMBR IE is to be included when the SGSN sends RANAP messages of the type RAB Assignment Request and Relocation Request. This functionality can be enabled per RNC basis.

**Example**

If configuration for this functionality has been enabled, using the following command disables the sending of UE AMBR IE in RANAP messages.

```
no ranap ue-ambr-ie
```

# ran-information-management

Use this command to inform the SGSN which RNC are capable of handling RAN information management (RIM) messages.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context *context\_name* > iups-service *service\_name* > rnc id *rnc\_id***

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

**Syntax Description** [ **default** | **no** ] **ran-information-management**

## default

Resets the default so RIM is disabled.

## no

Disables the RIM support in the configuration file.

## Usage Guidelines

By default, handling of RAN information management (RIM) messages is disabled. This command informs the SGSN which RNC are capable of handling RIM messages. This configuration only becomes 'operational' if the **ran-information-management** command is enabled in the SGSN global configuration mode.

When RIM support is enabled on both the SGSN and the destination node, then all RIM PDUs are forwarded to the BSC/RNC. If RIM message handling is not enabled on both nodes, then the RIM PDUs are dropped silently.

## Example

Use the following command to enable RIM support:

```
ran-information-management
```

Use the following command to disable RIM support that has been added to the configuration:

```
no ran-information-management
```



# release-compliance

This command allows the SGSN to set support based on the RNC's 3GPP release compliance and to define per RNC QoS overrides.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > luPS Service Configuration > RNC Configuration

**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc)#
```

## Syntax Description

```
release-compliance { pre-release-7 | release-7 } [ gbr-down gbr_dn_val | gbr-up gbr_up_val | mbr-down mbr_dn_val | mbr-up mbr_up_val ] + default release-compliance
```

### default

Returns the configuration to the default value, **release-7**.

### pre-release-7

Enables support for an RNC with capabilities compliant with releases prior to Release 7, such as HSPA in R6.

### release-7

Enables support for RNC with capabilities compliant with 3GPP Release 7 or later, such as HSPA+ available in R7.

### **gbr-down** *gbr\_dn\_val*

Defines a guaranteed kbps bit rate for downlink direction,

- options for **pre-release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000. Default cap is 16000.
- options for **release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000, 21000, 28000, 42000. See default cap information below.

### **gbr-up** *gbr\_up\_val*

Defines a guaranteed kbps bit rate for uplink direction,

- options for **pre-release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000. Default cap is 16000.
- options for **release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000, 21000, 28000, 42000. See default cap information below.

**mbr-down *mbr\_dn\_val***

Defines a maximum kbps bit rate for downlink direction,

- options for **pre-release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000. Default cap is 16000.
- options for **release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000, 21000, 28000, 42000. See default cap information below.

**mbr-up *mbr\_up\_val***

Defines a maximum kbps bit rate for uplink direction,

- options for **pre-release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000. Default cap is 16000.
- options for **release-7** include: 16, 32, 64, 128, 256, 512, 1024, 2048, 4096, 8192, 11500, 16000, 21000, 28000, 42000. See default cap information below.

**Usage Guidelines**

Use this command to match the 3GPP release support by the RNC. As the 3GPP releases each support differing data rate options - R6 supports HSPA and R7 supports HSPA+ - then selecting the compliance is a method of performing data rate management on a per RNC basis.

Also use this command to set QoS capping overrides for each RNC separately. Default caps for Release 7 RNC will vary depending upon which overrides are set.

**Important**

Once caps are set for an RNC, if the RNC release level changes the capping remains the same until the QoS override values are changed for that RNC. Values do not automatically change to the default values appropriate for that release .

**Example**

Enable HSPA fallback to R6 compliance:

```
release-compliance pre-release-7
```

## reset-resource

This command enables the operator to control message length by configuring the number of IuConIDs sent in each RANAP Reset Resource messages.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > IuPS Service Configuration > RNC Configuration  
**configure > context** *context\_name* > **iups-service** *service\_name* > **rnc id** *rnc\_id*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-ctx-iups-service-rnc) #
```

---

**Syntax Description** **reset-resource max-iuconid-per-msg** *number*  
**default reset-resource max-iuconid-per-msg**

### default

Resets the number of Iu connection Ids included in the Reset Resource messages. Default is 250.

### max-iuconid-per-msg *number*

Sets the number of Iu connection Ids to be included in the Reset Resource messages.

*number*: Integer from 1 to 250.

Default: 250

---

### Usage Guidelines

Id numbers for each Iu connection are included in the RANAP Reset Resource messages. Including this potentially long stream of numbers can make the message very long. With this command, the operator can control the size of the messages by controlling the number of Id messages included in the messages.

### Example

Limit the number of Iu connection IDs to 30:

```
reset-resource max-iuconid-per-msg 30
```





# RoHC Profile Common Options Configuration Mode Commands

---

The RoHC Profile Common Options Configuration Mode is used to set timers that, upon expiration, release robust header compression contexts.

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Common Options Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-common) #
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [delay-release-hc-context-timer](#), on page 94
- [do show](#), on page 95
- [end](#), on page 96
- [exit](#), on page 97
- [inactive-traffic-release-hc-context-timer](#), on page 98

# delay-release-hc-context-timer

Sets a delay in releasing Robust Header Compression (RoHC) contexts allowing for context continuation during intra-gateway handoffs.

**Product** HSGW  
PDSN

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Common Options Configuration  
**configure > rohc-profile profile-name profile\_name > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-common)#
```

**Syntax Description** **delay-release-hc-context-timer** *seconds*  
**no delay-release-hc-context-timer**

**no**

Removes previously configured value for this command. No value disables the feature.

**seconds**

Specifies the number of seconds the system delays before releasing the header compression context as an integer from 0 to 65535.

**Usage Guidelines** Use this command to set a delay in releasing a header compression context. This command is necessary when employing RoHC and mobility. Typically, when an RP connection is released, the header compression context is also released immediately. However, in mobility situations, such as intra-PDSN handoffs, the header compression context should be preserved. Adding a delay to cover the handoff time allows the context to be maintained.

A header compression context contains the compression/decompression configuration and statistics for the session.

## Example

The following command sets the header compression release delay to 20 seconds:

```
delay-release-hc-context-timer 20
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# inactive-traffic-release-hc-context-timer

Sets an inactivity timer that is checked when inactivity is detected on an SO67 A10 bearer connection with negotiated RoHC parameters. When this timer expires, the header compression context is released.

<b>Product</b>	HSGW PDSN
<b>Privilege</b>	Administrator
<b>Command Modes</b>	Exec> Global Configuration > RoHC Profile Configuration > RoHC Profile Common Options Configuration <b>configure &gt; rohc-profile profile-name profile_name &gt; compression-options</b> Entering the above command sequence results in the following prompt: <code>[context_name]host_name(config-rohcprofile-profile_name-common)#</code>
<b>Syntax Description</b>	<b>inactive-traffic-release-hc-context-timer</b> <i>seconds</i> <b>no inactive-traffic-release-hc-context-timer</b>  <b>no</b> Removes previously configured value for this command. No value disables the feature.  <b>seconds</b> Specifies the time, in seconds, the system waits for activity on the bearer channel before releasing the header compression context as an integer from 1 through 65535.
<b>Usage Guidelines</b>	Use this command to set a timer that is started upon detecting inactivity on the bearer channel. Upon expiry, the header compression context is released. Enable this feature for more efficient memory utilization.
<b>Example</b>	The following command sets the bearer channel inactivity timer to 60 seconds: <b>inactive-traffic-release-hc-context-timer 60</b>



# RoHC Profile Compression Configuration Mode Commands

---

The RoHC Profile Compression Configuration Mode is used to configure RoHC (Robust Header Compression) Compressor parameters. RoHC is not supported on GGSN.

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```



## Important

The availability of commands, keywords and variables in this mode are dependent on platform type, product version, and installed license(s).

- [context-timeout](#), on page 101
- [do show](#), on page 102
- [end](#), on page 103
- [exit](#), on page 104
- [ipid-history-size](#), on page 105
- [max-jitter-cd](#), on page 106
- [max-sliding-window](#), on page 107
- [multiple-ts-stride](#), on page 108
- [new-context-blocking-time](#), on page 109
- [num-pkts-ts](#), on page 110
- [num-pkts-u-mode](#), on page 111
- [num-updates-ir](#), on page 112
- [optimistic-repeats](#), on page 113
- [rtp-sn-p](#), on page 114
- [rtp-sn-p-override](#), on page 115
- [rtp-time-stride](#), on page 116
- [rtp-ts-deviation](#), on page 117
- [rtp-ts-stride](#), on page 118
- [sliding-window-ts](#), on page 119

- [total-jitter-ipv4](#), on page 120
- [total-jitter-ipv6](#), on page 121
- [unimode-timeout-to-fo-state](#), on page 122
- [unimode-timeout-to-ir-state](#), on page 123
- [use-calculated-rtp-time-stride](#), on page 124
- [use-calculated-rtp-ts-stride](#), on page 125
- [use-ipid-override](#), on page 126
- [use-optimized-talkspurt](#), on page 127
- [use-optimized-transience](#), on page 128
- [use-timer-based-compression](#), on page 129
- [use-uncomp-profile](#), on page 130

# context-timeout

Context timeout in seconds.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp) #
```

---

**Syntax Description**

**context-timeout** *seconds*  
**default context-timeout**

**default**

Returns the command to its default value.

**seconds**

Specifies the context timeout value (in seconds) as an integer from 0 through 100.

Default: 20

---

**Usage Guidelines**

Use this command to set the context timeout.

**Example**

The following command sets the context timeout to 10 seconds:

```
context-timeout-period 10
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.



# ipid-history-size

Specifies the number of IP-IDs of previously sent packets to store. An IP ID is a 16-bit header field that stores IPv4 Identification information.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**ipid-history-size** *number*  
**default ipid-history-size**

**default**

Returns the command to its default value.

**number**

Specifies the number of IP IDs to store as an integer from 1 through 32.

Default: 8

---

**Usage Guidelines**

Use this command to set the number of IP IDs to store in the history.

**Example**

The following command sets the history size to 24 IP-IDs:

```
ipid-history-size 24
```

# max-jitter-cd

Specifies the upper boundary of jitter expected on the communication channel between the compressor and decompressor.

---

**Product** HSGW  
PDSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name profile\_name > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description** **max-jitter-cd** *num\_ms*  
**default max-jitter-cd**

## default

Returns the command to its default value.

## num\_ms

Specifies the number of milliseconds for the maximum jitter setting as an integer from 0 through 999999999.

Default: 150

---

**Usage Guidelines** Use this command to set the maximum amount of jitter allowed on the communication channel between compressor and decompressor.

## Example

The following command sets the jitter limit to 1000 ms (1 second):

```
max-jitter-cd 1000
```

# max-sliding-window

Specifies the width of the sliding window for W-LSB (Windows-based Least Significant Bits) encoded values.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**max-sliding-window** *size*  
**default max-sliding-window**

**default**

Returns the command to its default value.

**size**

Specifies the size of the sliding window as an integer from 1 through 1000.

Default: 6

---

**Usage Guidelines**

Use this command to set the size of the sliding window used to compute jitter for W-LSB encoded values.

**Example**

The following command sets the sliding window size to 500:

```
max-sliding-window 500
```

# multiple-ts-stride

Enables or disables the use of repeated transmission of RTS\_STRIDE for timer-based compression.

---

## Product

HSGW

PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

[ no ] **multiple-ts-stride**

**no**

Disables the use of repeated transmission of RTS\_STRIDE for time-based compression.

---

## Usage Guidelines

Use this command to enable or disable a gateway's ability to repeatedly transmit RTS\_STRIDE for timer-based compression.

# new-context-blocking-time

Specifies the time period in seconds for blocking the establishment of new contexts after the compressor has received a feedback reject.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**new-context-blocking-time** *seconds*  
**default context-timeout**

**default**

Returns the command to its default value.

**seconds**

Specifies the context blocking time (in seconds) as an integer from 0 through 100.

Default: 20

---

**Usage Guidelines**

Use this command to set the context blocking time after the compressor has received a feedback reject.

**Example**

The following command sets the context blocking time to 10 seconds:

```
new-context-blocking-time 10
```

# num-pkts-ts

Specifies the number packets per RTP timestamp (TS).

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**num-pkts-ts** *num\_pkts*  
**default num-pkts-ts**

### default

Returns the command to its default value.

### *num\_pkts*

Specifies the number of packets for the timestamp as an integer from 0 through 999.

Default: 6

---

## Usage Guidelines

Use this command to set the number of packets for each RTP timestamp (TS).

### Example

The following command sets the number of packets per timestamp to 50:

```
num-pkts-ts 50
```

# num-pkts-u-mode

Specifies the number of packets sent when operating in U-Mode (unidirectional mode).

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**num-pkts-u-mode** *num\_pkts*  
**default num-pkts-u-mode**

**default**

Returns the command to its default value.

***num\_pkts***

Specifies the number of packets sent in U-Mode as an integer from 0 through 999.

Default: 1

---

**Usage Guidelines**

Use this command to set the number of packets sent when in U-Mode.

**Example**

The following command sets the number of packets for U-Mode to 50:

```
num-pkts-u-mode 50
```

# num-updates-ir

Configures the number of IR (Initiation and Refresh state) updates.

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**num-updates-ir** *num\_pkts*  
**default num-updates-ir**

### default

Returns the command to its default value of 4.

### *num\_pkts*

Specifies the number of IR updates as an integer from 0 through 999.

Default: 4

---

## Usage Guidelines

Use this command to set the number of IR updates.

### Example

The following command sets the number of IR updates to 30:

```
num-updates-ir 30
```



# optimistic-repeats

Specifies the number of repeated packets to send to the decompressor. For transition from the FO (First Order) to the SO (Second Order) state, the compressor should be confident that the decompressor has all the parameters needed to decompress according to a fixed pattern. The compressor obtains its confidence about decompressor status by sending several packets with the same information according to the lower compression state. If the decompressor receives any of these packets, it is in sync with the compressor.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name profile\_name > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**optimistic-repeats** *num\_pkts*  
**default optimistic-repeats**

**default**

Returns the command to its default value.

**num\_pkts**

Specifies the number of packets to repeat with the same information to assure synchronization with the decompressor.

*num\_pkts* must be an integer from 0 through 10.

Default: 6

---

**Usage Guidelines**

Use this command to set the number of packets to repeat to the decompressor to assure synchronization before transition states.

**Example**

The following command sets the number of repeated packets to 5:

```
optimistic-repeats 5
```

## rtp-sn-p

Specifies the value of *p* in RTP SN (RTP Sequence Number) calculation. Least Significant Bits (LSB) encoding is used for header fields whose values are usually subject to small changes. With LSB encoding, the *k* least significant bits of the field value are transmitted instead of the original field value, where *k* is a positive integer. After receiving *k* bits, the decompressor derives the original value using a previously received value as reference (*v\_ref*). The scheme is guaranteed to be correct if the compressor and the decompressor each use interpretation intervals as follows:

- In which the original value resides
- And in which the original value is the only value that has the exact same *k* least significant bits as those transmitted.

The interpretation interval can be described as a function:

$$f(v\_ref, k). \text{ Let } f(v\_ref, k) = [v\_ref - p, v\_ref + (2^k - 1) - p]$$

Where *p* is an integer.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name profile\_name > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

### Syntax Description

**rtp-sn-p** *p\_value*  
**default rtp-sn-p**

#### **default**

Returns the command to its default value.

#### ***p\_value***

Specifies the value of *p* in the RTP SN calculation as an integer from 0 through 999.

Default: 6

---

### Usage Guidelines

Use this command to set the value for *p* when performing the RTP SN calculation.

#### **Example**

The following command sets the value of *p* to 100:

```
rtp-sn-p 100
```

# rtp-sn-p-override

Enables an override of p in the RTP SN calculation. This is disabled by default.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

[ **default** | **no** ] **rtp-sn-p-override**

**default**

Returns the command to its default value of disabled.

**no**

Disables overriding p in RTP SN calculation.

---

**Usage Guidelines**

Use this command to enable an override of p in RTP SN calculation.

**Example**

The following command enables the override of p in the RTP SN calculation:

```
rtp-sn-p-override
```

## rtp-time-stride

Sets the time interval used for one TS (RTP Time Stamp) stride. This interval is used when timer-based encoding is enabled.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

### Syntax Description

**rtp-time-stride** *num\_ms*  
**default rtp-time-stride**

#### default

Returns the command to its default value.

#### *num\_ms*

Specifies the number of milliseconds to use for TS\_STRIDE as an integer from 0 through 999999999.

Default: 20

---

### Usage Guidelines

Use this command to set the length of the TS\_STRIDE in milliseconds.

#### Example

The following command sets TS\_STRIDE to 100ms:

```
rtp-time-stride 100
```

# rtp-ts-deviation

Sets the maximum percentage of deviation allowed for input RTP packets for timer-based compression.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**rtp-ts-deviation** *percentage*

**default rtp-ts-deviation**

**default**

Returns the command to its default value of 25.

***percentage***

Specifies the maximum percentage of deviation allowed for input RTP packets for timer-based compression as an integer value from 0 through 100.

Default: 25

---

**Usage Guidelines**

Use this command to set the maximum percentage of deviation allowed for input RTP packets for timer-based compression.

**Example**

The following command sets the percentage to 30:

```
rtp-ts-deviation 30
```

# rtp-ts-stride

Specifies the amount by which TS (RTP time stamp) is incremented. This value is used for Scaled RTP TS encoding.

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**rtp-ts-stride** *num\_ms*  
**default** **rtp-ts-stride**

### default

Returns the command to its default value of 160.

### *num\_ms*

Specifies the number of milliseconds to use incrementing TS as an integer from 0 through 999999999.

Default: 160

---

## Usage Guidelines

Use this command to set the amount by which TS is incremented for Scaled RTP TS encoding.

### Example

The following command sets amount by which TS is incremented to 100ms:

```
rtp-ts-stride 100
```

# sliding-window-ts

Sets the sliding window used to compute jitter.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name profile\_name > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**sliding-window-ts** *size*  
**default sliding-window-ts**

**default**

Returns the window to its default value of 4.

**size**

Specifies the size of the sliding window as an integer from 1 through 1000.

Default: 4

---

**Usage Guidelines**

Use this command to set the size of the sliding window used to compute jitter for the current RoHC profile.

**Example**

The following command sets the sliding window size to 500:

```
sliding-window-ts 500
```

# total-jitter-ipv4

Specifies the total jitter allowed after compression for IPv4.

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**total-jitter-ipv4** *time*  
**default total-jitter-ipv4**

### default

Returns the command to its default value of 270.

### time

Specifies the time interval to use (in milliseconds) as an integer from 0 through 999999999.

Default: 270

---

## Usage Guidelines

Use this command to set the jitter limit after compression.

### Example

The following command sets the jitter after compression limit to 900 ms:

```
total-jitter-ipv4 900
```



# total-jitter-ipv6

Specifies the total jitter allowed after compression for IPv6.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

```
total-jitter-ipv6 time  
default total-jitter-ipv6
```

**default**

Returns the command to its default value 580.

**time**

Specifies the total jitter interval allowed (in milliseconds) as an integer from 0 through 999999999.

Default: 580

---

**Usage Guidelines**

Use this command to set the jitter limit after compression.

**Example**

The following command sets the jitter after compression limit to 900 ms:

```
total-jitter-ipv6 900
```

## unimode-timeout-to-fo-state

Specifies the time period in seconds before falling back to the FO (First Order) state.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

### Syntax Description

**unimode-timeout-to-fo-state** *num\_ms*  
**default unimode-timeout-to-fo-state**

#### default

Returns the command to its default value of 3.

#### *num\_ms*

Specifies the timeout period (in seconds) as an integer from 0 through 10.

Default: 3

---

### Usage Guidelines

Use this command to set the timeout before falling back to the FO state when in Unimode.

#### Example

The following command sets the fall back timeout to 2 seconds:

```
unimode-timeout-to-fo-state 2
```

# unimode-timeout-to-ir-state

Specifies the time period in seconds before falling back to the IR (Initiation and Refresh) state.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

**unimode-timeout-to-ir-state** *num\_ms*  
**default unimode-timeout-to-ir-state**

**default**

Returns the command to its default value of 5.

***num\_ms***

Specifies the timeout period in seconds as an integer from 0 through 20.

Default: 5

---

**Usage Guidelines**

Use this command to set the timeout before falling back to the IR state when in Unimode.

**Example**

The following command sets the fall back timeout to 3 seconds:

```
unimode-timeout-to-ir-state 3
```

# use-calculated-rtp-time-stride

Overrides the configured value of rtp-time-stride with a calculated value.

---

## Product

HSGW

PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**[ default | no ] use-calculated-rtp-time-stride**

### default

Returns the command to its default value of enabled.

### no

Disables the use of calculated RTP time stride override.

---

## Usage Guidelines

This command overrides the configured value of rtp-time-stride with a calculated value.

### Example

The following command overrides the configured value of rtp-time-stride.

```
use-calculated-rtp-time-stride
```

# use-calculated-rtp-ts-stride

Overrides the configured value of rtp-ts-stride with a calculated value.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

[ **default** | **no** ] **use-calculated-rtp-ts-stride**

**default**

Returns the command to its default value of enabled.

**no**

Disables the use of calculated RTP TS time stride override.

---

**Usage Guidelines**

This command overrides the configured value of rtp-ts-stride with a calculated value.

**Example**

The following command overrides the configured value of rtp-ts-stride.

```
use-calculated-rtp-ts-stride
```

# use-ipid-override

Enables or disables overriding the IP-ID (IPv4 Identification header field).

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**[ default | no ] use-ipid-override**

### default

Returns the command to its default value of disabled.

### no

Disables the IP-ID override.

---

## Usage Guidelines

Use this command to enable overriding of the IP-ID.

### Example

The following command enables the IP-ID override feature:

```
use-ipid-override
```

The following command disables the IP-ID override feature:

```
no use-ipid-override
```

The following command also disables the IP-ID override feature:

```
default use-ipid-override
```

# use-optimized-talkspurt

Enables or disables the use of optimized talkspurt.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

[ **default** | **no** ] **use-optimized-talkspurt**

**default**

Returns the command to its default value of enabled.

**no**

Disables the use of optimized talkspurt.

---

**Usage Guidelines**

Use this command to enable and disable the use of optimized talkspurt

**Example**

The following command enables the use of optimized talkspurt:

```
use-optimized-talkspurt
```

The following command disables the use of optimized talkspurt:

```
no use-optimized-talkspurt
```

# use-optimized-transience

Enables or disables the use of optimized transience.

---

## Product

HSGW

PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**[ default | no ] use-optimized-transience**

### default

Returns the command to its default value of enabled.

### no

Disables the use of optimized transience.

---

## Usage Guidelines

Use this command to enable or disable the use of optimized transience.

### Example

The following command enables the use of optimized transience.

```
use-optimized-transience
```

The following command disables the use of optimized transience.

```
no use-optimized-transience
```



# use-timer-based-compression

Enables or disables timer-based compression of the RTP time stamp (TS) at the compressor.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration

**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

**Syntax Description**

[ **default** | **no** ] **use-timer-based-compression**

**default**

Returns the command to its default value of enabled.

**no**

Disables the use of timer-based compression.

---

**Usage Guidelines**

Use this command to enable or disable the use of timer-based compression.

**Example**

The following command enables the use of timer-based compression.

```
use-timer-based-compression
```

The following command disables the use of timer-based compression.

```
no use-timer-based-compression
```

# use-uncomp-profile

Enables or disables the use of the Uncompressed Profile (0x0000) if required at the compressor.

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration > RoHC Profile Compression Configuration  
**configure > rohc-profile profile-name *profile\_name* > compression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-comp)#
```

---

## Syntax Description

**[default | no ] useS-uncomp-profile**

### default

Returns the command to its default value of disabled.

### no

Disables the use of the Uncompressed Profile.

---

## Usage Guidelines

Use this command to enable or disable the use of the Uncompressed Profile.

### Example

The following command enables the use of the Uncompressed Profile.

```
use-uncomp-profile
```

The following command disables the use of the Uncompressed Profile.

```
no use-uncomp-profile
```



## RoHC Profile Configuration Mode Commands

The RoHC Profile Configuration Mode is used to configure RoHC (Robust Header Compression) Compressor and Decompressor parameters. The profiles can then be assigned to specific subscriber sessions when RoHC header compression is configured. RoHC is not supported on GGSN.

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration

**configure** > **rohc-profile** **profile-name** *profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name) #
```



### Important

The availability of commands, keywords and variables in this mode is dependent on platform type, product version, and installed license(s).

- [common-options](#), on page 132
- [compression-options](#), on page 133
- [decompression-options](#), on page 134
- [do show](#), on page 135
- [end](#), on page 136
- [exit](#), on page 137

## common-options

Enters the RoHC Profile Common Options Configuration Mode where inactivity and delay timers are set to support dynamic header compression contexts and context preservation during handoffs.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration

**configure** > **rohc-profile profile-name** *profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name)#
```

---

### Syntax Description

[ **default** ] **common-options**

#### **default**

Reset all parameters in the RoHC Profile Common Options Configuration Mode to default values.

---

### Usage Guidelines

Use this command to enter the RoHC Profile Common Options Configuration Mode where parameters for maintaining header compression contexts and inactivity timers can be configured.

Entering this command results in the following prompt:

```
[context_name]host(config-rohcprofile-<profile_name>-common)#
```

RoHC Profile Common Options Configuration Mode commands are defined in the RoHC Profile Common Options Configuration Mode Commands chapter.

# compression-options

Enters the RoHC Profile Compression Options Configuration Mode allowing configuration of options applied during RoHC compression for the current RoHC profile.

**Product** HSGW  
PDSN

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration  
**configure** > **rohc-profile profile-name profile\_name**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name)#
```

**Syntax Description** [ **default** ] **compression-options**

## default

Reset all options in the RoHC Profile Compression Configuration Mode to their default values.

## Usage Guidelines

Use this command to enter RoHC Profile Compression Configuration Mode to set the compression options that are used for subscriber sessions using the current RoHC profile.

Entering this command results in the following prompt:

```
[context_name]host(config-rohcprofile-<profile_name>-comp)#
```

RoHC Profile Compression Options Configuration Mode commands are defined in the RoHC Profile Compression Configuration Mode Commands chapter.

## Example

The following command enters RoHC Profile Compression Options Configuration Mode:

```
compression-options
```

The following command sets all compression options to their default values:

```
default compression-options
```

# decompression-options

Enters the RoHC Profile Decompression Options Configuration Mode allowing configuration of options applied during RoHC decompression for the current RoHC profile.

**Product** HSGW  
PDSN

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration  
**configure > rohc-profile profile-name** *profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name)#
```

**Syntax Description** **[default ] decompression-options**

## default

Reset all options in the RoHC Profile Decompression Options Configuration Mode to their default values.

## Usage Guidelines

Use this command to enter RoHC Profile Decompression Options Configuration Mode to set the decompression options used for subscriber sessions using the current RoHC profile.

Entering this command results in the following prompt:

```
[context_name]host(config-rohcprofile-<profile_name>-decomp)#
```

RoHC Profile Decompression Options Configuration Mode commands are defined in the RoHC Profile Decompression Configuration Mode Commands chapter.

## Example

The following command enters RoHC Profile Decompression Options Configuration Mode:

```
decompression-options
```

The following command sets all decompression options to their default values:

```
default decompression-options
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

■ exit



# RoHC Profile Decompression Configuration Mode Commands

---

The RoHC Profile Decompression Configuration Mode is used to configure RoHC (Robust Header Compression) Decompressor parameters.

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp) #
```



## Important

The availability of commands, keywords and variables in this mode are dependent on platform type, product version, and installed license(s).

- [accept-delayed-pkts](#), on page 141
- [context-timeout](#), on page 142
- [crc-errors-fo](#), on page 143
- [crc-errors-so](#), on page 144
- [do show](#), on page 145
- [end](#), on page 146
- [exit](#), on page 147
- [nack-limit](#), on page 148
- [optimistic-mode-ack](#), on page 149
- [optimistic-mode-ack-limit](#), on page 150
- [piggyback-wait-time](#), on page 151
- [preferred-feedback-mode](#), on page 152
- [rtp-sn-p](#), on page 154
- [rtp-sn-p-override](#), on page 155
- [sliding-window-ts](#), on page 156
- [use-clock-option](#), on page 157
- [use-crc-option](#), on page 158
- [use-feedback](#), on page 159
- [use-jitter-option](#), on page 160

- [use-reject-option](#), on page 161
- [use-sn-not-valid-option](#), on page 162
- [use-sn-option](#), on page 163

# accept-delayed-pkts

Accepts delayed packets

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp) #
```

---

**Syntax Description**

[ **default** ] **accept-delayed-pkts**

**default**

Returns the command to its default value of disabled.

---

**Usage Guidelines**

This command helps reduce packet loss during context repair.

**Example**

Use the following command to enable the system to accept delayed packets:

**accept-delayed-pkts**

## context-timeout

Ensures that no expired contexts are used for data compression.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

### Syntax Description

**context-timeout** *seconds*  
**default context-timeout**

#### **default**

Returns the command to its default value.

#### **seconds**

Specifies the context timeout value (in seconds) as an integer from 0 through 100.

Default: 20

---

### Usage Guidelines

The RoHC stack should periodically clean up expired contexts and release memory in case there is no data activity for the call on this context. The context cleanup period is internally calculated to be set to half of the value of the context-timeout value. This will ensure that no expired contexts are used for data compression.

#### **Example**

The following command sets the context-timeout parameter to 30 seconds:

```
context-timeout 30
```

## crc-errors-fo

Sets the limits for when a NACK message is sent while in the FO (First Order) state. A NACK is sent whenever CRC errors are detected within a specified number of packets.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name profile\_name > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

### Syntax Description

**crc-errors-fo-k** *num\_errors*  
**crc-errors-fo-n** *num\_packets*  
**default** **crc-errors-fo-k**  
**default** **crc-errors-fo-n**

#### default

Returns the command to its default value.

#### crc-errors-fo-k *num\_errors*

Specifies the number of received packets that trigger the sending of a NACK as an integer from 1 through 10.

Default: 1




---

### Important

*num\_errors* must be less than or equal to the value specified with the **crc-errors-fo-n** command.

---

#### crc-errors-fo-n *num\_packets*

Specifies the number of packets to check for CRC errors as an integer from 1 through 10.

Default: 1

---

### Usage Guidelines

Use this command to set the parameters that trigger sending a NACK message when in the FO state.

#### Example

To configure a NACK to be sent when 4 out of the last 10 packets have CRC errors when in the FO state, use the following commands:

```
crc-errors-fo-k 4
crc-errors-fo-n 10
```

## crc-errors-so

Sets the limits for when a NACK message is sent while in the SO (Second Order) state. A NACK is sent whenever CRC errors are detected within a specified number of packets.

---

**Product** HSGW  
PDSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration >  
**configure > rohc-profile profile-name profile\_name > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

**Syntax Description**

**crc-errors-so-k** *num\_errors*  
**crc-errors-so-n** *num\_packets*  
**default** **crc-errors-so-k**  
**default** **crc-errors-so-n**

### default

Returns the command to its default value.

### crc-errors-so-k *num\_errors*

Specifies the number of received packets that trigger the sending of a NACK as an integer from 0 through 10.

Default: 1




---

**Important** *num\_errors* must be less than or equal to the value specified with the **crc-errors-so-n** command.

---

### crc-errors-so-n *num\_packets*

Specifies the number of packets to check for CRC errors as an integer from 1 through 10.

Default: 1

---

**Usage Guidelines** Use this command to set the parameters that trigger sending a NACK message when in the SO state.

### Example

To configure a NACK to be sent when 4 out of the last 10 packets have CRC errors when in the SO state, use the following commands:

```
crc-errors-so-k 4
crc-errors-so-n 10
```



# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# nack-limit

Sets the number of unsuccessful decompressions allowed before a NACK is sent.

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

## Syntax Description

**nack-limit** *limit*  
**default** **nack-limit**

### **default**

Returns the command to its default value.

### **limit**

Specifies the number of unsuccessful decompressions allowed as an integer from 0 through 20.

Default: 0

---

## Usage Guidelines

Use this command to set the maximum number of unsuccessful decompressions before a NACK message is sent.

### **Example**

The following command sets the number of unsuccessful decompressions allowed to 10:

```
nack-limit 10
```

# optimistic-mode-ack

When this command is enabled and a type 2 IR-DYN packet is successfully decompressed, an optional ACK is sent in U-mode.

---

**Product** HSGW  
PDSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration >  
**configure > rohc-profile profile-name profile\_name > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp) #
```

---

**Syntax Description** [ **default** | **no** ] **optimistic-mode-ack**

**default**

Returns the command to its default value of enabled.

**no**

Disables the sending of the optional ACK.

---

**Usage Guidelines** Use this command to enable and disable the sending of an optional ACK in U-mode when a type 2 IR-DYN packet is successfully decompressed.

**Example**

To enable the sending of the optional ACK, enter the following command:

```
optimistic-mode-ack
```

To disable the sending of the optional ACK, enter the following command:

```
no optimistic-mode-ack
```

# optimistic-mode-ack-limit

Sets the number of packets for which to send ACKs.

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

## Syntax Description

**optimistic-mode-ack-limit** *num\_pkts*  
**default optimistic-mode-ack-limit**

### default

Returns the command to its default value.

### *num\_pkts*

Specifies the number of packets for which to send ACKs as an integer from 0 through 20.

Default: 3

---

## Usage Guidelines

Use this command to set the number of packets to send the optional ACK for when a type 2 IR-DYN packet is successfully decompressed.

### Example

Enter the following command to set the number of packets to send and ACK for to 6:

```
optimistic-mode-ack-limit 6
```

Use the following command to set the number of packets to send an ACK for back to the default of 3:

```
default optimistic-mode-ack-limit
```

# piggyback-wait-time

Specifies the time in milliseconds to wait for a feedback packet to be picked up as piggybacked feedback by the associated compressor.

---

**Product** HSGW  
PDSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > RoHC Profile Configuration >  
**configure** > **rohc-profile profile-name profile\_name** > **decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp) #
```

---

**Syntax Description** **piggyback-wait-time** *m\_secs*  
**default piggyback-wait-time**

## default

Returns the command to its default value.

## *m\_secs*

Specifies the time (in milliseconds) to wait for a feedback packet to be picked up as an integer value from 0 through 1000.

Default: 80

---

**Usage Guidelines** Use this command to set the time in milliseconds to wait for a feedback packet to be picked up as piggybacked feedback by the associated compressor.

## Example

The following command sets the wait time to 120 ms:

```
piggyback-wait-time 120
```

# preferred-feedback-mode

Specifies the preferred feedback mode to use between the compressor and the decompressor

---

## Product

HSGW  
PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

## Syntax Description

```
preferred-feedback-mode { bidirectional-optimistic | bidirectional-reliable  
| unidirectional }  
default preferred-feedback-mode
```

### default

Returns the command to its default setting of bidirectional-optimistic.

### bidirectional-optimistic

This mode is similar to the Unidirectional mode, with the exception of a feedback channel used to send error recovery requests from the decompressor to compressor.

This is the default mode.

### bidirectional-reliable

Reliable mode makes extensive use of a feedback channel to avoid packet loss from context invalidation. A secure reference model is used instead of the optimistic approach used in the other modes. With the secure reference model, the confidence of the compressor depends on acknowledgements from the decompressor for every context updating packet.

Periodically the compressor sends context updating packets repeatedly until an acknowledgement is received from the decompressor.

### unidirectional

Packets are sent in only one direction, from the compressor to the decompressor.

---

## Usage Guidelines

Use this command to specify the preferred feedback method to use between the compressor and the decompressor for the current RoHC profile.

### Example

Use the following command to set the preferred feedback mode to bidirectional-reliable:



```
preferred-feedback-mode bidirectional-reliable
```

## rtp-sn-p

Specifies the value of p in RTP SN (RTP Sequence Number) calculation. Least Significant Bits (LSB) encoding is used for header fields whose values are usually subject to small changes. With LSB encoding, the k least significant bits of the field value are transmitted instead of the original field value, where k is a positive integer. After receiving k bits, the decompressor derives the original value using a previously received value as reference (v\_ref). The scheme is guaranteed to be correct if the compressor and the decompressor each use interpretation intervals as follows:

- In which the original value resides
- And in which the original value is the only value that has the exact same k least significant bits as those transmitted.

The interpretation interval can be described as a function:

$$f(v\_ref, k). \text{ Let } f(v\_ref, k) = [v\_ref - p, v\_ref + (2^k - 1) - p]$$

Where p is an integer.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name profile\_name > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

### Syntax Description

**rtp-sn-p** *value*  
**default** **rtp-sn-p**

#### **default**

Returns the command to its default value.

#### **value**

Specifies the number the value of p in the RTP SN calculation as an integer from 0 through 999.

---

### Usage Guidelines

Use this command to set the value to use for p when performing the RTP SN calculation.

#### **Example**

The following command sets the RTP Sequence Number integer "p" value to 100:

```
rtp-sn-p 100
```

# rtp-sn-p-override

Allows an override of p in RTP SN calculation. This is disabled by default.

---

**Product**

HSGW

PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

**Syntax Description**

[ **default** | **no** ] **rtp-sn-p-override**

**default**

Returns the command to its default value of disabled.

**no**

Disables overriding p in RTP SN calculation.

---

**Usage Guidelines**

Use this command to allow an override of p in RTP SN calculations.

**Example**

The following command enables the override of p in the RTP SN calculation:

```
rtp-sn-p-override
```

# sliding-window-ts

Computes jitter as described in RFC 3095,[4.5.4]

---

## Product

HSGW

PDSN

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

## Syntax Description

**sliding-window-ts** *size*  
**default sliding-window-ts**

### default

Returns the command to its default value of 4.

### size

Sets the size of the sliding window. *size* must be an integer from 1 through 1000.

Default: 4

---

## Usage Guidelines

Use this command to set the size of the sliding window used to compute jitter for the current RoHC profile.

### Example

The following command sets the sliding window size to 500:

```
sliding-window-ts 500
```

# use-clock-option

Controls usage of the RoHC clock option. The clock option informs the compressor of the clock resolution of the decompressor. This allows the compressor to estimate the jitter introduced by the clock of the decompressor when doing timer-based compression of the RTP timestamp.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

**Syntax Description**

[ **default** | **no** ] **use-clock-option**

**default**

Returns the command to its default value of enabled.

**no**

Disables use of the RoHC clock option.

---

**Usage Guidelines**

Use this command to enable and disable the use of the RoHC clock option.

**Example**

The following command enables RoHC clock option usage:

```
use-clock-option
```

The following command disables RoHC clock option usage:

```
no use-clock-option
```

## use-crc-option

Controls usage of the RoHC cyclic redundancy check (CRC) option. The CRC option contains an 8-bit CRC computed over the entire feedback payload, without the packet type and code octet, but including any CID fields,

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

### Syntax Description

[ **default** | **no** ] **use-crc-option**

#### **default**

Returns the command to its default value of enabled.

#### **no**

Disables use of the CRC option.

---

### Usage Guidelines

Use this command to enable and disable the use of the RoHC CRC option.

#### **Example**

The following command enables RoHC CRC option usage:

```
use-crc-option
```

The following command disables RoHC CRC option usage:

```
no use-crc-option
```

# use-feedback

Controls use of the feedback channel. A feedback channel sends error recovery requests and (optionally) acknowledgments of significant context updates from the decompressor to the compressor.

---

## Product

HSGW  
PDSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure** > **rohc-profile profile-name** *profile\_name* > **decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

## Syntax Description

[ **default** | **no** ] **use-feedback**

### default

Returns the command to its default value of disabled.

### no

Disables use of the feedback channel.

---

## Usage Guidelines

Use this command to enable and disable the use of the RoHC feedback channel.

### Example

The following command enables RoHC feedback channel usage:

```
use-feedback
```

The following command disables RoHC feedback channel usage:

```
no use-feedback
```

## use-jitter-option

Controls usage of RoHC jitter option. The jitter option allows the decompressor to report the maximum jitter it has observed

<b>Product</b>	HSGW PDSN
<b>Privilege</b>	Administrator
<b>Command Modes</b>	Exec > Global Configuration > RoHC Profile Configuration > <b>configure &gt; rohc-profile profile-name <i>profile_name</i> &gt; decompression-options</b> Entering the above command sequence results in the following prompt: <code>[context_name]host_name(config-rohcprofile-profile_name-decomp)#</code>
<b>Syntax Description</b>	<b>[ default   no ] use-jitter-option</b>  <b>default</b> Returns the command to its default value of enabled.  <b>no</b> Disables use of the jitter option.
<b>Usage Guidelines</b>	Use this command to enable and disable the use of the RoHC jitter option.

### Example

The following command enables RoHC jitter option usage:

```
use-jitter-option
```

The following command disables RoHC jitter option usage:

```
no use-jitter-option
```



## use-reject-option

Controls usage of RoHC reject option. The reject option informs the compressor that the decompressor does not have sufficient resources to handle the flow.

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

**Syntax Description**

[ **default** | **no** ] **use-reject-option**

**default**

Returns the command to its default value of disabled.

**no**

Disables use of the reject option.

---

**Usage Guidelines**

Use this command to enable and disable the use of the RoHC reject option.

**Example**

The following command enables RoHC reject option usage:

```
use-reject-option
```

The following command disables RoHC reject option usage:

```
no use-reject-option
```

## use-sn-not-valid-option

Controls usage of the RoHC SN not valid option. The sn-not-valid option indicates that the SN of the feedback is not valid. A compressor must not use the SN of the feedback to find the corresponding sent header when this option is present.

---

### Product

HSGW  
PDSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

### Syntax Description

[ **default** | **no** ] **use-sn-not-valid-option**

#### **default**

Returns the command to its default value of enabled.

#### **no**

Disables use of the sn-not-valid option.

---

### Usage Guidelines

Use this command to enable and disable the use of the RoHC sn not valid option.

#### **Example**

The following command enables RoHC sn not valid option usage:

```
use-sn-not-valid-option
```

The following command disables RoHC sn not valid option usage:

```
no use-sn-not-valid-option
```

## use-sn-option

Controls usage of RoHC sn option. The sn option provides eight additional bits of SN (Sequence Number, usually the RTP Sequence Number.)

---

**Product**

HSGW  
PDSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > RoHC Profile Configuration >

**configure > rohc-profile profile-name *profile\_name* > decompression-options**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-rohcprofile-profile_name-decomp)#
```

---

**Syntax Description**

[ **default** | **no** ] **use-sn-option**

**default**

Returns the command to its default value of enabled.

**no**

Disables use of the SN option.

---

**Usage Guidelines**

Use this command to enable and disable the use of the RoHC SN option.

**Example**

The following command enables RoHC SN option usage:

```
use-sn-option
```

The following command disables RoHC SN option usage:

```
no use-sn-option
```

■ use-sn-option



## Route-map Configuration Mode Commands

The Route-Map Configuration sub-mode is used for the OSPFv2 and BGP-4 routing protocols. This mode includes commands that configure matching rules and set actions to perform on matched routes.

### Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 167
- [end](#), on page 168
- [exit](#), on page 169
- [match as-path](#), on page 170
- [match community](#), on page 171
- [match extcommunity](#), on page 172
- [match interface](#), on page 173
- [match ip address](#), on page 174
- [match ip next-hop](#), on page 175
- [match ipv6 address](#), on page 176
- [match ipv6 next-hop](#), on page 177
- [match metric](#), on page 178
- [match origin](#), on page 179
- [match route-type external](#), on page 180
- [match tag](#), on page 181
- [set as-path](#), on page 182
- [set community](#), on page 183
- [set extcommunity rt](#), on page 185
- [set ip next-hop](#), on page 186
- [set ipv6 next-hop](#), on page 187
- [set local-preference](#), on page 188

- [set metric, on page 189](#)
- [set metric-type, on page 190](#)
- [set origin, on page 191](#)
- [set tag, on page 192](#)
- [set weight, on page 193](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# match as-path

Matches an Autonomous System (AS) path access list

---

## Product

HA

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

## Syntax Description

[ **no** ] **match as-path** *AS\_list*

### **no**

Disables matching the specified AS path access list.

### **AS\_list**

Specifies the name of an AS path access list for matching as an alphanumeric string of 1 through 79 characters.

---

## Usage Guidelines

This command is used for BGP-4 routing to specify an AS path access list to be matched. Refer to the **ip as-path access-list** command for more information.

### **Example**

To match entries in an AS path access list named *ASlist1*, enter the following command;

```
match as-path ASlist1
```

# match community

Configures filtering (permit or deny) via a BGP community-list in a route map.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

**Syntax Description**

```
[no] match community { named named_list | standard identifier }
```

**no**

Disables matching the specified community list.

**named** *named\_list*

Specifies the name of a community list as an alphanumeric string of 1 through 79 characters.

**standard** *identifier*

Specifies the name of a community list as an integer from 1 through 99.

---

**Usage Guidelines**

Configures filtering (permit or deny) via a BGP community-list in a route map.

The community list must have been previously configured via the Context Configuration mode **ip community-list** command.

**Example**

This command matches community-list number 2:

```
match community standard 2
```

# match extcommunity

Configures filtering (permit or deny) via a BGP external community-list in a route map. An external community-list is a Route Target.

**Product** HA

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

**Syntax Description** **[no] match extcommunity { named *named\_list* | standard *identifier* }**

**no**

Disables matching the specified external community list.

**named *named\_list***

Specifies the name of an external community list as an alphanumeric string of 1 through 79 characters.

**standard *identifier***

Specifies the name of an external community list as an integer from 1 through 99.

## Usage Guidelines

Configures filtering (permit or deny) via a BGP external community-list in a route map. An external community-list is a Route Target.

A BGP extended community defines a route target. MPLS VPNs use a 64-bit Extended Community attribute called a Route Target (RT). An RT enables distribution of reachability information to the correct information table.

The external community list must have been previously configured via the Context Configuration mode **ip extcommunity-list** command.

## Example

This command matches external community-list number 99:

```
match extcommunity standard 99
```

# match interface

Specifies the next-hop interface name of a route to be matched.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description**

```
[ no ] match interface interface_name
```

**no**

Disables matching the specified interface name.

***interface\_name***

Specifies the name of the virtual interface for matching as an alphanumeric string of 1 through 79 characters.

---

**Usage Guidelines**

Use this command to specify the next hop interface name for routes to be matched.

**Example**

To match routes that have the next hop interface specified as *Interface123*, enter the following command:

```
match interface Interface123
```

# match ip address

Matches IPv4 routes with entries in a route-access-list or prefix-list.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

## Syntax Description

[ **no** ] **match ip address** { **prefix-list** | **route-access-list** } *list\_name*

### **no**

Disables matching from the specified prefix list or route access list.

### **prefix-list**

Matches any routes with entries in a prefix-list.

### **route-access-list**

Matches any routes with entries in a route-access-list.

### **list\_name**

Specifies the name of the IPv4 prefix list or IPv4 route access-list as an alphanumeric string of 1 through 79 characters.

---

## Usage Guidelines

Use this command to match routes specified in an IPV4 route-access-list or prefix-list.

### **Example**

To match routes that are specified in an IPv4 prefix list named *Prefix100*, enter the following command:

```
match ip address prefix-list Prefix100
```

# match ip next-hop

Matches next-hop IPv4 addresses with entries in a specified prefix-list or route-access-list.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

**Syntax Description**

```
[ no ] match ip next-hop { prefix-list | route-access-list } list_name
```

**no**

Disables matching from the specified prefix list or route access list.

**prefix-list**

Matches any routes that have a next-hop router IPv4 address that has an entry in the specified prefix list.

**route-access-list**

Matches any routes that have a next-hop router IPv4 address that has an entry in the specified route-access-list.

**list\_name**

Specifies the name of the prefix-list or route-access-list as an alphanumeric string of 1 through 79 characters.

---

**Usage Guidelines**

Use this command to match next-hop IPv4 addresses that have entries in the specified prefix-list or route-access-list.

**Example**

To match next-hop IPv4 addresses with entries in a prefix-list named *Prefix100*, enter the following command:

```
match ip next-hop prefix-list Prefix100
```

# match ipv6 address

Matches IPv6 routes with entries in a specified route-access-list or prefix-list.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

## Syntax Description

[ **no** ] **match ipv6 address** { **prefix-list** | **route-access-list** } *list\_name*

### **no**

Disables matching from the specified prefix list or route access list.

### **prefix-list**

Matches any routes with entries in a prefix-list.

### **route-access-list**

Matches any routes with entries in a route-access-list.

### **list\_name**

Specifies the name of the IPv6 prefix list or IPv6 route access-list as an alphanumeric string of 1 through 79 characters.

---

## Usage Guidelines

Matches IPv6 routes with entries in a specified route-access-list or prefix-list.

### **Example**

To match routes that are specified in an IPv6 prefix list named *Prefix600*, enter the following command:

```
match ipv6 address prefix-list Prefix600
```



# match ipv6 next-hop

Matches next-hop IPv6 addresses with entries in specified standard prefix-list or route-access-list.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Route-map Configuration  
**configure > context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description** [ **no** ] **match ipv6 next-hop** { **prefix-list** | **route-access-list** } *list\_name*

**no**

Disables matching from the specified prefix list or route access list.

**prefix-list**

Matches any routes that have a next-hop router IPv6 address that has an entry in the specified prefix list.

**route-access-list**

Matches any routes that have a next-hop router IPv6 address that has an entry in the specified route-access-list.

**list\_name**

Specifies the name of the prefix-list or route-access-list as an alphanumeric string of 1 through 79 characters.

---

**Usage Guidelines** Use this command to match next-hop IPv6 addresses that have entries in the specified prefix-list or route-access-list.

**Example**

To match next-hop IPv6 addresses with entries in a prefix-list named *Prefix600*, enter the following command:

```
match ipv6 next-hop prefix-list Prefix600
```

# match metric

Matches routes that have the specified route metric.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

## Syntax Description

[ **no** ] **match metric** *metric\_value*

### **no**

Disables matching of the specified route metric.

### **metric\_value**

Specifies the route metric to match as an integer from 0 through 4294967295.

---

## Usage Guidelines

Use this command to match routes that have the specified route metric.

### **Example**

To match routes with the route metric of 1200, enter the following command:

```
match metric 1200
```

# match origin

Matches the origin code learned from BGP. This command is for route maps that are used with BGP routing only.

---

**Product** HA

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Route-map Configuration  
**configure > context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

**Syntax Description** [ **no** ] **match origin** { **egp** | **igp** | **incomplete** }

**no**

Disables matching of the origin code.

**egp**

Matches origins learned via the External Gateway Protocol (EGP)

**igp**

Match origins learned via the local Interior Glittery Protocol (IGP)

**incomplete**

Match origins with unknown heritage.

---

**Usage Guidelines** Use this command to match origin codes for BGP routing.

## Example

To match origin codes learned from EGP, enter the following command:

```
match origin egp
```

# match route-type external

Match external Open Shortest Path First (OSPF) routes of the specified type.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

## Syntax Description

[ **no** ] **match route-type external** { **type-1** | **type-2** }

### **no**

Disables matching with external OSPF routes of the specified type.

### **type-1**

Only matches type-1 external routes.

### **type-2**

Only matches type-2 external routes.

---

## Usage Guidelines

Use this command to match external routes of a specific type.

### **Example**

The following command matches all external routes that are type-2:

```
match route-type external type-2
```

# match tag

Matches routes with the specified route tag value.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

**Syntax Description**

[ **no** ] **match tag** *tag\_value*

**no**

Disables matching routes with the specified route tag value.

**tag\_value**

Specifies the route tag value to match as an integer from 0 through 4294967295.

---

**Usage Guidelines**

Use this command to match routes that have the specified route tag value.

**Example**

Use the following command match routes that have a route tag value of 1234:

```
match tag 1234
```

## set as-path

Modifies an Autonomous System (AS) path for a route by adding the specified AS numbers to the front of the path.

---

**Product** HA

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Route-map Configuration  
**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description** [ **no** ] **set as-path prepend** *asn+*

**no**

Disables prepending the AS path. Any previously set prepends are removed.

**prepend**

Prepends the AS path.

**asn**

AS number(s) to be prepended to the AS path. You can specify up to 16 different AS numbers to be prepended in the order specified. Each AS number must be separated by a space. *asn* must be an integer from 1 through 65535.

---

**Usage Guidelines** Use this command to add up to 16 specified AS numbers to the front of the AS path.

**Example**

The following command prepends the AS numbers 100, 200, and 1000 to matching AS paths:

```
set as-path prepend 100 200 1000
```

# set community

Sets the BGP community destination for the routes matching the route-map.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

**Syntax Description**

```
set community [additive] { internet | local-AS | no-advertise | no-export
| none | value AS-community_number AS-community_number AS-community_number+ }
{ internet | local-AS | no-advertise | no-export | none | value
AS-community_number AS-community_number AS-community_number ... }
{ internet | local-AS | no-advertise | no-export | none | value
AS-community_number AS-community_number AS-community_number ... }
no set community { internet | local-AS | no-advertise | no-export | value
AS-community_number }
```

**no**

Unsets the specified community destination.

**[additive]**

When enabled this option allows multiple BGP destinations and route targets to be included in the same community.

**{ internet | local-AS | no-advertise | no-export | value *AS-community\_number***

Specifies the destination for the community.

- **internet** – Advertise this route to the internet community, and any router that belongs to it.
- **local-AS** – Use in confederation scenarios to prevent sending packets outside the local autonomous system (AS).
- **no-advertise** – Do not advertise this route to any BGP peer, internal or external.
- **no-export** – Do not advertise to external BGP (eBGP) peers. Keep this route within an AS.
- **none** – No community attribute
- **value** *AS-community\_number* – Specifies a community string in AS:NN format, where AS = 2-byte AS-community hexadecimal number and NN = 2-byte hexadecimal number (1 to 11 characters).

You can enter multiple destinations and route targets separated by spaces.

---

**Usage Guidelines**

Sets the BGP community destinations for the routes matching the route-map.

The community list must have been previously configured via the Context Configuration mode **ip community-list** command.

**Example**

The following command sets the BGP community destination to AS 400:50:

```
set community value 400:50
```



## set extcommunity rt

Sets the BGP external community destination for the routes matching the route-map. The external community is the Route Target (RT).

**Product** All

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Route-map Configuration  
**configure > context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

**Syntax Description** **set extcommunity rt** *rt\_number* *rt\_number* *rt\_number*+  
**no set extcommunity rt***rt\_number* +

**no**

Unsets the specified BGP external community (Route Target).

***rt\_number***

Specifies a Route Target as a string in AS:NN format, where AS = 2-byte AS-community hexadecimal number and NN = 2-byte hexadecimal number (1 to 11 characters). You can enter multiple route targets separated by spaces.

**Usage Guidelines** Sets the BGP external community destinations (route targets) for the routes matching the route-map.

The external community list must have been previously configured via the Context Configuration mode **ip extcommunity-list** command.

### Example

The following command sets the BGP route target to AS 212:34:

```
set extcommunity rt 212:34
```

# set ip next-hop

Sets the IPv4 address that is applied as the next hop for routes.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description**

[ **no** ] **set ip next-hop** *ipv4\_address*

**no**

Disables the specified next hop IPv4 address.

***ipv4\_address***

Specifies the IPv4 address of the next hop to which packets are output, entered using IPv4 dotted-decimal notation.

---

**Usage Guidelines**

Use this command to set the IPv4 address that is used as the next hop for routes.

**Example**

To set the next hop for routes to the IPv4 address 192.168.2.100, use the following command:

```
set ip next-hop 192.168.2.100
```

# set ipv6 next-hop

Sets the IPv6 address that is applied as the next hop for routes.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Route-map Configuration  
**configure > context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description** [ **no** ] **set ipv6 next-hop** *ipv6\_address*

**no**

Disables the specified next hop address.

***ipv6\_address***

Specifies the IPv6 address of the next hop to which packets are output, entered using IPv6 colon-separated-hexadecimal notation.

---

**Usage Guidelines** Use this command to set the IPv6 address that is used as the next hop for routes.

## Example

To set the next hop for routes to the IPv6 address 2001:4A2B::1f3F, use the following command:

```
set ipv6 next-hop 2001:4A2B::1f3F
```

# set local-preference

Sets the BGP local preference attribute that is sent by the BGP speaker only to IBGP peers.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

## Syntax Description

[ **no** ] **set local-preference** *pref\_number*

### **no**

Disables the specified local preference.

### **pref\_number**

Specifies the BGP local preference number as an integer from 1 through 16777214.

---

## Usage Guidelines

Sets the BGP local preference attribute that is sent by the BGP speaker only to IBGP peers. This value can be used by peers to determine the exit point of the Autonomous System (AS).

There is no **match** clause corresponding to local preference in the route-map because local-preference is directly used in the route selection algorithm.

## Example

The following command sets the BGP local preference attribute to 33:

```
set local-preference 33
```

# set metric

Sets the route metric for matching routes to a specified value.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description**

```
[ no ] set metric metric_value
```

**no**

Disables the specified metric type.

***metric\_value***

Specifies the metric value that is set for routes as an integer from 1 through 16777214.

---

**Usage Guidelines**

Use this command to set the route metric for matched routes.

**Example**

To set the route metric to 12345, use the following command:

```
set metric 12345
```

## set metric-type

This command sets the route metric type to either Type-1 or Type-2 in the AS-external-LSA.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description**

```
[ no ] set metric-type { type-1 | type-2 }
```

**type-1**

Sets the route metric to external type-1.

**type-2**

Sets the route metric to external type-2

---

**Usage Guidelines**

Use this command to set the route metric to either external type-1 or external type-2.

**Example**

To set the route metric to type-1, enter the following command:

```
set metric-type type-1
```

# set origin

Sets the Border Gateway Protocol (BGP) origin code to a specified value. This command is for route maps that are used with BGP routing only.

---

**Product**

HA

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Route-map Configuration

**configure > context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map)#
```

---

**Syntax Description**

```
[ no ] set origin { egp | igp | incomplete }
```

**no**

Disables setting the origin code.

**egp**

Sets the origin code to specify that the path is from a remote External Gateway Protocol (EGP) system.

**igp**

Sets the origin code to specify that the path is from a local Interior Gateway Protocol (IGP) system.

**incomplete**

Sets the origin code to specify that the path is from an unknown system.

---

**Usage Guidelines**

Use this command to set a specified origin code for BGP.

**Example**

To set the origin code to be from an External Gateway Protocol (EGP) system, enter the following command:

```
set origin egp
```

# set tag

Sets the route tag value for matched routes.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description**

[ **no** ] **set tag** *tag\_value*

**no**

Disables setting the route tag to the specified value.

***tag\_value***

Specifies the route tag value as an integer from 0 through 4294967295.

---

**Usage Guidelines**

Use this command to set the route tag value that is applied to all matched routes.

**Example**

To set the route tag value to 12345, enter the following command:

```
set tag 12345
```



# set weight

Sets the weight in the routing table for matching routes to the specified value.

---

**Product**

PDSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Route-map Configuration

**configure** > **context** *context\_name* > **route-map** *map\_name* { **deny** | **permit** } *seq\_number*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-route-map) #
```

---

**Syntax Description**

[ **no** ] **set weight** *value*

**no**

Disables setting the routing weight value.

**value**

Specifies the weight in the routing table as an integer from 1 through 4294967295.

---

**Usage Guidelines**

Use this command to set the routing table weight on matched routes.

**Example**

The following command sets the routing table weight for matched routes to 1000:

```
set weight 1000
```

**set weight**



## RS-232 Port Configuration Mode Commands

The RS-232 Port Configuration Mode is used to manage the RS-232 ports on the SPIO cards.

### Command Modes

Exec > Global Configuration > RS-232 Port Configuration

**configure** > **port rs232** *slot\_number/port\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 196
- [end](#), on page 197
- [exit](#), on page 198
- [preferred slot](#), on page 199
- [snmp trap link-status](#), on page 201
- [terminal](#), on page 202

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.


**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# preferred slot

Assigns revertive or non-revertive control to port redundancy auto-recovery.

Default: non-revertive operation

---

## Product

PDSN  
FA  
HA  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > RS-232 Port Configuration

**configure** > **port rs232** *slot\_number/port\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number) #
```

---

## Syntax Description

[ **default** | **no** ] **preferred slot** *slot\_number*

### default

Sets the port for non-revertive operation for port redundancy auto-recovery; requiring an administrative user to manually issue a **port switch to** command to return service to the original port.

### no

Disables revertive, or auto-recovery, operation for selected port.

### *slot\_number*

Identifies the physical chassis slot where the SPIO card is installed.

---

## Usage Guidelines

This command enables or disables revertive port redundancy, wherein after a port failover, when the original port is restored to service (such as link up) the system will return service to that port automatically.

Disabled, which is the default setting, causes non-revertive operation; requiring an administrative user to manually issue a port switch to command to return service to the original port.

This command must be issued on a per port basis, allowing you to configure specific ports to be used on individual line cards or SPIO cards. For example, ports 1 through 4 could be configured as "preferred" on the line card in slot 17, while ports 5 through 8 are "preferred" on the line card in slot 33. In this scenario, both line cards would be in an Active operational state while still providing LC and port redundancy for the other.




---

## Important

This command is not supported on all platforms.

---

**Example**

The following command sets the preferred slot to 24:

```
preferred slot 24
```



# snmp trap link-status

Enables or disables the generation of an SNMP trap for link status changes.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > RS-232 Port Configuration

**configure** > **port rs232** *slot\_number/port\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number) #
```

---

**Syntax Description**

[ **no** ] **snmp trap link-status**

**no**

Disables the sending of traps for link status changes.

---

**Usage Guidelines**

Enable link status change traps when a monitoring facility can use the information or if there are trouble shooting activities in progress.

**Example**

The following command enables link status change traps:

```
snmp trap link-status
```

# terminal

Configures the console port on the SPIO.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > RS-232 Port Configuration

**configure** > **port rs232** *slot\_number/port\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number)#
```

---

## Syntax Description

```
terminal { carrierdetect { off | on } | databits { 7 | 8 } | flowcontrol
  { hardware | none } | parity { even | none | odd } | speed { 115200 |
19200 | 38400 | 57600 | 9600 } | stopbits { 1 | 2 } }
default terminal { all | databits | flowcontrol | parity | speed | stopbits
}
```

**carrierdetect** { **off** | **on** }

Specifies whether or not the console port is to use carrier detect when connecting to a terminal.

**databits** { **7** | **8** }

Specifies the number of data bits used to transmit and receive characters. Default: 8

**default terminal** **all**

Restores all settings to their default values.

**flowcontrol** { **hardware** | **none** }

Specifies how the flow of data is controlled between the SPIO and a terminal. Default: none

**parity** { **even** | **none** | **odd** }

Specifies the type of error checking used on the port.

**even**: Enables error checking by setting the parity bit to 1 (if needed) making the number of 1s in the data bits even.

**none**: Disables error checking. This is the default setting.

**odd**: Enables error checking by setting the parity bit to 1 (if needed) making the number of 1s in the data bits odd.

**speed** { **115200** | **19200** | **38400** | **57600** | **9600** }

Specifies the flow of data in bits per second between the console port and terminal. Default: 9600

**stopbits { 1 | 2 }**

Specifies the number of stop bits between each transmitted character. Default: 1

---

**Usage Guidelines**

Sets the SPIO console port parameters for communication with the terminal device.

**Example**

The following sequence of commands set the SPIO's console port to operate with specific values. The terminal must support these values.

```
terminal carrierdetect off
terminal databits 7
terminal flowcontrol hardware
terminal parity even
terminal speed 115200
terminal stopbits 1
```





## S102 Pool Area Configuration Mode Commands

---

### Command Modes

The commands in this configuration mode manage the configuration of the pool area characteristics.

Exec > Global Configuration > Context Configuration >

**configure** > **context** *context\_name* > **s102-service** *service\_name* **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-pool-area) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



---

### Important

The **plmnid** option that is visible in the code is not supported at this time. This option is for future development.

- [cell-id](#), on page 206
- [do show](#), on page 207
- [end](#), on page 208
- [exit](#), on page 209
- [hash-value](#), on page 210
- [msc-id](#), on page 212
- [plmnid](#), on page 213

# cell-id

Configure the sector cell ID to be used to locate the pool-area for the MSC selection process for CDMA2000 message handling in either a CSFB for 1xRTT or SRVCC for 1xRTT scenario.

**Product** MME

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > Context Configuration >  
**configure** > **context** *context\_name* > **s102-service** *service\_name* **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-pool-area) #
```

**Syntax Description** [ **no** ] **cell-id** *cell-id* +

**no**

Erases the specific cell ID information from the S102 pool-area configuration.

**cell-id**

Enter an integer from 1 through 65535 to identify a CDMA2000 sector cell ID that you are assigning to this S102 pool-area configuration.

+ Means you can enter up to 24 cell IDs, separated by a single blank space, in the same command.

**Usage Guidelines** Configure up to 24 cell IDs per S102 pool-area instance.

## Example

Use a command similar to the following to define the three cell ID(s) for this S102 pool-area configuration:

```
cell-id 6 8 11 17
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# hash-value

This command configures the hash-value(s) for the S102 pool-area. The hash-value is to be used by the MME for MSC selection for CDMA2000 message handling in either a CSFB for 1xRTT or SRVCC for 1xRTT scenario.



## Important

**Prerequisite:** Each of the MSCs to be included in the pool-area configuration must have been configured and associated with the S102 service before the MSC can be included in the pool-area configuration.

## Product

MME

## Privilege

Administrator

## Command Modes

Exec > Global Configuration > Context Configuration >

**configure** > **context** *context\_name* > **s102-service** *service\_name* **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-pool-area) #
```

## Syntax Description

```
[ no ] hash-value { hash_value | non-configured-values | range lower_hash_value
to higher_hash_value } { msc msc_name }
```

### **no**

Erases the configured hash-value information from the S102 pool-area configuration.

### **hash\_value**

Enter an integer from 0 through 999 to identify a specific MSC.

### **non-configured-values msc msc\_name**

Assigns all non-configured hash values to use the named MSC.

*msc\_name* Enter a string of 1 to 63 alphanumeric characters to identify one of the MSCs previously configured in the S102 service configuration.

### **range lower\_hash\_value to higher\_hash\_value msc msc\_name**

Specifies the range of hash values for an MSC:

- *lower\_hash\_value* Enter an integer from 0 through 999 to identify the start value for a range of hash. The *lower\_hash\_value* must be lower than the *end\_value*.
- *higher\_hash\_value* Enter an integer from 0 through 999 to identify the end value for a range of hash. The *higher\_hash\_value* must be higher than the *start\_value*.
- **msc msc\_name** Enter a string of 1 to 63 alphanumeric characters to identify one of the MSCs previously configured in the S102 service configuration.

**Usage Guidelines**

This command enables the operator to use hash as a filter in the MSC selection process. For more information about MSC selection and how it works, refer to either the *SRVCC for 1xRTT* feature chapter or the *CSFB for 1xRTT* feature chapter in the *MME Administration Guide*.

**Example**

Use a command similar to the following to setup a hash filter for MSC selection for a pool-area definition. The following command configures a hash value range filter of *24 to 43* for the selection of the MSC named *mscHouston* :

```
hash-value range 24 to 43 msc mscHouston
```

# msc-id

Configures the numeric ID for an MSC in the S102 pool-area configuration.



## Important

**Prerequisite:** Each of the MSCs to be included in the pool-area configuration must have been configured and associated with the S102 service before the MSC can be identified in the pool-area configuration.

## Product

MME

## Privilege

Administrator

## Command Modes

Exec > Global Configuration > Context Configuration >

**configure** > **context** *context\_name* > **s102-service** *service\_name* **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-pool-area)#
```

## Syntax Description

[ **no** ] **msc-id** *msc-id*

### **no**

Erases the MSC ID configuration from this S102 pool-area configuration.

### **msc-id**

Enter an integer from 1 through 16777215 to identify the unique numeric ID for the MSC.

## Usage Guidelines

Both the cell ID and the MSC ID must be configured in the S102 pool-area configuration for the MME to have sufficient information to perform MSC selection.

For information about the pool-area, refer to the **pool-area** command in the *S102 Service Configuration Mode Commands* chapter.

For more information about MSC selection and how it works, refer to either the *SRVCC for IxRTT* feature chapter or the *CSFB for IxRTT* feature chapter in the *MME Administration Guide*.

## Example

Identify the unique numeric ID, such as 2555, for the MSC that has been configured for the S102 pool-area:

```
msc-id 2555
```

# plmnid

---

**Product**

MME



---

**Important**

---

The **plmnid** option that is visible in the code is not supported at this time. This option is for future development.

---

plmnid



## S102 Service Configuration Mode Commands

The S102 Service configuration mode is used to create and manage the configuration instance for the S102 Service which controls the S102 interface. This service works in conjunction with the MME Service.

### Command Modes

Exec > Global Configuration > Context Configuration > S102 Service

**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



### Important

The **default** command prefix is visible in the S102 Service configuration mode. However, it is not supported at this time and has been included for the purpose of future development.

- [lxrtt](#), on page 216
- [bind](#), on page 217
- [do show](#), on page 218
- [end](#), on page 219
- [exit](#), on page 220
- [ip](#), on page 221
- [msc](#), on page 222
- [non-pool-area](#), on page 223
- [pool-area](#), on page 225

# 1xrtt

Identifies the type of CDMA2000 single-carrier radio transmission technology (1xRTT) functionality, CSFB or SRVCC, to be enabled for this S102 service.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; S102 Service

**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```

---

**Syntax Description**

```
[ no ] 1xrtt { csfb | srvcc }
```

**no**

Removes the 1xRTT identification from the S102 service/interface configuration.

**csfb**

Enables CSFB for 1xRTT for the S102 service/interface.

**srvcc**

Enables SRVCC for 1xRTT for the S102 service/interface.

---

**Usage Guidelines**

This command determines the type of signaling and functionality to be supported on the S102 interface, either circuit-switched fallback (CSFB) or single radio voice call continuity (SRVCC). The S102 interface provides the tunnel for the MME to pass CDMA2000 messages to/from the 1xCS IWS (interworking solution function)/MSC (mobile switching center).

For details of usage and configuration, refer to either the *CSFB for 1xRTT* feature chapter or the *SRVCC for 1xRTT* feature chapter in the *MME Administration Guide*.

**Example**

Use the following command to configure the S102 interface to support CSFB for 1xRTT:

```
1xrtt csfb
```

Use the following command to remove an S102 interface configuration for SRVCC for 1xRTT:

```
no 1xrtt srvcc
```



# bind

Bind and unbind a logical IP address and port to the S102 interface.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > S102 Service

**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```

---

**Syntax Description**

[ **no** ] **bind ipv4-address** *ipv4\_address* [ **port** *port\_number* ]

**no**

Removes the logical interface IPv4 address binding (unbinds) from the S102 service/interface.

**ipv4-address** *ipv4\_address*

Specifies the source IPv4 address of the S102 interface in IPv4 dotted-decimal notation.

**port** *port\_number*

Including this keyword is optional. If included, it configures the numeric identification of the port to be bound to the S102 interface.

*port\_number* Enter an integer from 1 through 65535.

---

**Usage Guidelines**

Bind the S102 service to a specific logical IP address. The logical IP address or interface takes on the characteristics of an S102 interface that provides the session connectivity for the MME to pass CDMA2000 messages to/from the 1xCS IWS (interworking solution function)/MSC (mobile switching center).




---

**Caution**

This is a critical configuration. Any change to this configuration will cause the S102 service to restart. Removing or disabling this configuration will stop the S102 service.

---

**Example**

The following command binds the logical IP interface with the IPv4 address of 192.68.10.22 to the S102 service.

```
bind ipv4-address 192.68.10.22
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ip

This command configures the IP parameters on the S102 interface.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > S102 Service

**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```

---

**Syntax Description**

[ **no** ] **ip qos-dscp** *dscp\_value*

**no**

Removes IP parameter configuration from the S102 service/interface.

**qos-dscp** *dscp\_value*

The **qos-dscp** keyword designates the Quality of Service - Differentiated Services Code Point value to the packet leaving through the S102 interface.

*dscp\_value* is a value assigned to the packet for DSCP marking. The value can be a pre-defined DSCP value or an arbitrary value ranging from 0x01 to 0x3F.

---

**Usage Guidelines**

S102 interface allows Differentiated Services Code Point (DSCP) marking functionality. DSCP marking helps in packet traffic management. DSCP marking can be performed only on IPv4 packets leaving the S102 interface.

Either the pre-defined DSCP values can be used for marking, or any arbitrary value ranging from 0x01 to 0x3F can be assigned. The default DSCP value is 0x00 or be (Best Effort). The default DSCP value is automatically set when the configuration is disabled.

**Example**

The following command shows the IP configuration for DSCP marking on the S102 service.

```
ip qos-dscp ef
```

## msc

Command creates a configuration instance for a single mobile switching center (1x RTT MSC) in the S102 service configuration. The MSCs are used by the SRVCC and CSFB functions when the MME handles CDMA2000 messages from/to UEs.

---

**Product** MME

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > S102 Service  
**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```

---

**Syntax Description** [ **no** ] **msc** *msc\_name*

**no**

Erases the MSC configuration from the S102 service configuration.

***msc\_name***

Identifies a specific MSC. The name must be a string of 1 through 63 alphanumeric characters. We recommend that each defined MSC name be unique on the system.

---

### Usage Guidelines

This command creates an instance of an MSC configuration for the S102 service configuration and it provides access to the S102 MSC configuration mode commands to configure parameters related to the MSC.

The MSC(s) configured with this command can be identified in the **pool-area** and **non-pool-area** configurations to setup MSC selection. For more details about MSC selection, refer to the *SRVCC for 1xRTT* or *CSFB for 1xRTT* feature chapters in the *MME Administration Guide*.

It is possible to associate up to 10 MSCs with the S102 interface/service configuration. Repeat the **msc**, **ipv4-address**, and **exit** commands sequence as often as needed to identify all MSCs.

### Example

Use a command similar to the following one to assign a unique name to identify an MSC in the S102 service configuration:

```
msc msc1
```

# non-pool-area

This command configures a non-pool-area instance to be used by the MME for MSC selection for CDMA2000 message handling in either a CSFB for 1xRTT or SRVCC for 1xRTT scenario.



## Important

**Prerequisite:** Each of the MSCs to be included in the non-pool-area configuration must have been configured and associated with the S102 service before the MSC can be identified in the non-pool-area configuration.

## Product

MME

## Privilege

Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > S102 Service

**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```

## Syntax Description



## Important

The **plmn** option that is visible in the code is not supported at this time and so it is not included in the following syntax description. This option is included in the code for future development.

```
non-pool-area non_pool_area_name msc msc_name msc-id msc_id cell-id cell_id +
no non-pool-area non_pool_area_name cell-id cell_id +
```

**no**

Erases the configured non-pool-area information.

### ***non\_pool\_area\_name***

Enter a string of 1 to 63 alphanumeric characters to uniquely identify this non-pool-area configuration to be used for MSC selection.

### ***msc msc\_name***

Identify a 1x RTT mobile switching center (MSC) that is associated with the S102 service/interface configuration.

*msc\_name* Enter a string of 1 to 63 alphanumeric characters to identify one of the MSCs previously configured in the S102 service configuration.

### ***msc-id msc\_id***

*msc\_id* Enter an integer from 1 through 16777215 to identify the unique numeric ID for the MSC.

**cell-id *cell\_id* +**

*cell\_id* Enter an integer from 1 through 65535 to identify a CDMA2000 sector cell ID that you are assigning to this non-pool area configuration.

+ Indicates that more than one cell ID can be included in the command. Enter up to 24 cell IDs, separated by a single blank space, in the same command.

**Usage Guidelines**

Up to 10 MSC pool or non-pool areas can be configured per S102 service in support of MSC selection for the MME handling either SRVCC or CSFB 1xRTT CDMA2000 messages from a UE. Both the MSC-Id and the Cell-Id are used to locate the pool or non-pool area for the MSC selection process.

For information about the pool-area, refer to the **pool-area** command sheet also in the S102 Service configuration mode.

For more information about MSC selection and how it works, refer to either the *SRVCC for 1xRTT* feature chapter or the *CSFB for 1xRTT* feature chapter in the *MME Administration Guide*.

**Example**

Use a command similar to the following to setup a non-pool-area definition. The following command configures a non-pool-area named *npoolLondon1* and includes an MSC named *mscLondon* that has a numeric ID of *2443* and includes cells *5, 6, 7, and 22*:

```
non-pool-area npoolLondon1 msc mscLondon msc-id 2443 cell-id 5 6 7 22
```



# pool-area

This command creates a pool-area instance to be used by the MME for MSC selection for CDMA2000 message handling in either a CSFB for 1xRTT or SRVCC for 1xRTT scenario.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; S102 Service

**configure** > **context** *context\_name* > **s102-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-service)#
```

---

**Syntax Description**

[ **no** ] **pool-area** *pool\_area\_name*

**no**

Erases the pool-area instance from the S102 service configuration.

***pool\_area\_name***

Enter a string of 1 to 63 alphanumeric characters to uniquely identify this pool-area configuration to be used for MSC selection.

---

**Usage Guidelines**

Up to 10 MSC pool and/or non-pool areas can be configured per S102 service in support of MSC selection for the MME handling either SRVCC or CSFB 1xRTT CDMA2000 messages from a UE. Both the MSC-Id and the Cell-Id are used to locate the pool or non-pool area for the MSC selection process.

Issuing this command also takes the MME into the S102 Pool Area configuration mode for the commands to configure the pool-area characteristics: Cell ID, hash-value, and MSC ID. Refer to the *S102 Pool Area Configuration Mode Commands* in this document.

For information about the non-pool-area, refer to the **non-pool-area** command section also in the *S102 Service Configuration Mode Commands* chapter.

For more information about MSC selection and how it works, refer to either the *SRVCC for 1xRTT* feature chapter or the *CSFB for 1xRTT* feature chapter in the *MME Administration Guide*.

**Example**

The following command creates the S102 pool-area instance named *s102pool-1*:

```
pool-area s102pool-1
```

pool-area



## S102 MSC Configuration Mode Commands

The commands of the S102 MSC configuration mode define the characteristics of the CDMA2000 1xRTT mobile switching center (MSC) associated with the S102 interface.

### Command Modes

Exec > Global Configuration > Context Configuration > S102 Service Configuration > S102 MSC Configuration

**configure** > **context** *context\_name* > **s102-service** *service\_name* **msc** *msc\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-msc) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 228
- [end](#), on page 229
- [exit](#), on page 230
- [ipv4-address](#), on page 231

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.


**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ipv4-address

Adds the IPv4 address of the interface associated with the MSC, and optionally the port ID, to the S102 service configuration.

---

**Product** MME

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > S102 Service Configuration > S102 MSC Configuration

**configure** > **context** *context\_name* > **s102-service** *service\_name* **msc** *msc\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-s102-msc)#
```

---

**Syntax Description** [ **no** ] **ipv4-address** *ipv4\_address* **port** *port\_number*

**no**

Erases the specific IPv4 address configuration for the MSC from the S102 service configuration.

***ipv4\_address***

Identifies IPv4 address of the interface to the MSC. The value for the IPv4 address must be entered in standard IPv4 dotted-decimal notation.

***port port\_number***

If this keyword option is included with the command, it configures an identifying port number for the MSC. The port number must be an integer from 1 through 65535.

---

**Usage Guidelines** It is possible to associate up to 10 IWS/MSCs with the S102 interface/service configuration. Repeat the **msc**, **ipv4-address**, and **exit** commands sequence as often as needed to identify all MSCs.

**Example**

Use a command similar to the following to define the target IPv4 address and port number for the MSC's interface:

```
msc 111.111.111.1 port 4334
```

**ipv4-address**





## S1AP Cause Code Configuration Mode Commands

The cause code group object allows an operator to group together a set of cause codes. This group can then be used as a named object in other commands.

### Command Modes

Exec > Global Configuration > LTE Policy Configuration > S1AP Cause Code Configuration

**configure** > **lte-policy** > **cause-code-group** *group\_name*

Entering the above command sequence results in the following prompt:

```
[local] host_name (slap-cause-code)
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [class](#), on page 234
- [do show](#), on page 236
- [end](#), on page 237
- [exit](#), on page 238

# class

Configures a set of cause codes within a cause code group.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > LTE Policy Configuration > S1AP Cause Code Configuration

**configure** > **lte-policy** > **cause-code-group** *group\_name*

Entering the above command sequence results in the following prompt:

```
[local] host_name (slap-cause-code)
```

---

**Syntax Description**

```
[no] class { miscellaneous | nas | protocol | radio | transport } cause
cause_no
```

**no**

Removes the specified cause code class.

**miscellaneous**

Specifies the class of miscellaneous cause codes.

**nas**

Specifies the class of NAS cause codes.

**protocol**

Specifies the class of protocol cause codes.

**radio**

Specifies the class of radio cause codes.

**transport**

Specifies the class of transport cause codes.

**cause cause\_no**

Specifies the cause codes to add to this class. Cause codes must be defined one at a time.

*cause\_no* is a numeric cause code value, as defined in 3GPP TS 36.413.

---

**Usage Guidelines**

Use this command to configure the specific cause codes within this S1AP Cause Code Group.

A maximum of 16 cause codes can be added to a cause-code-group entry.

Refer to the **policy service-request** command and **policy tau** command in the MME Service Configuration Commands Chapter to configure the behavior of the MME when the initial context setup fails during a service request procedure or while processing a TAU request.

The specific action taken by the MME can be mapped to the cause codes defined in this command.

### Example

The following commands add causes **failure-in-radio-interface-procedure** and **interaction-with-other-procedure** to the cause code group.

```
class radio cause 26
class radio cause 29
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.



## S1-U Relay Configuration Mode Commands



### Important

In Release 20, 21.0 and 21.1, HeNBGW is not supported. Commands in this configuration mode must not be used in these releases. For more information, contact your Cisco account representative.

The S1-U Relay configuration option enables the S1-U Relay service functionality to the HeNB-GW Access Service. . In this mode user can configure associations to the Access and Network GTP-U services for S1-U Relay

### Command Modes

Exec > Global Configuration > Context Configuration > HeNB-GW Access Service Configuration > S1-U Relay Configuration

**configure > context** *context\_name* > **henbgw-access-service** *access\_svc\_name* > **s1u-relay**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(s1u-relay)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [associate](#), on page 240
- [do show](#), on page 241
- [end](#), on page 242
- [exit](#), on page 243
- [ip](#), on page 244

# associate

Associates previously configured Access GTP-U service as well as the Network GTP-U service to this HeNB-GW Access Service for S1-U relay service functionality. The Access and Network GTP-U services must be configured in the Context Configuration mode before using this configuration.

---

**Product** HeNB-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > HeNB-GW Access Service Configuration > S1-U Relay Configuration

**configure > context *context\_name* > henbgw-access-service *access\_svc\_name* > s1u-relay**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(s1u-relay)#
```

---

**Syntax Description** **associate { access-gtpu-service *access\_gtpu\_svc* | network-gtpu-service *network\_gtpu\_svc* } [ context *ctxt\_name* ]**  
**no associate { access-gtpu-service | network-gtpu-service }**

**no**

Removes the associated Access or Network GTP-U service from this HeNB-GW Access service configuration.

***access\_gtpu\_svc***

Identifies the name of the pre-configured Access GTP-U service in Context Configuration Mode to associate with this HeNB-GW Access Service for S1-U relay.

*access\_gtpu\_svc* is an alphanumeric string of 1 through 63 characters.

***network\_gtpu\_svc***

Identifies the name of the pre-configured Network GTP-U service to associate with this HeNB-GW Access Service for S1-U relay.

*network\_gtpu\_svc* is an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines**

Use this command to bind/associate a pre-configured Access or Network GTP-U service to this HeNB-GW Access service. When S1-U Relay is enabled, the association to ingress and egress GTP-U services is considered as critical configuration for the HeNB-GW Access service. When S1-U relay is enabled, both access and network gtpu services needs to be in STARTED state for the HENBGW access service to be started.

**Example**

Following command associates a Network GTP-U service named *net\_gtpu* in egress context with a specific HeNB-GW Access service:

```
associate network-gtpu-service net_gtpu context egress
```



# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ip

Configures the Internet protocol (IP) parameters including downlink and uplink of data for specified HENBGW ACCESS service.

---

**Product** HeNB-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > HeNB-GW Access Service Configuration > S1-U Relay Configuration

**configure** > **context** *context\_name* > **henbgw-access-service** *access\_svc\_name* > **s1u-relay**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(s1u-relay)#
```

---

**Syntax Description** **Release 19.2 and later:**

```
ip { downlink | uplink } qci-dscp-mapping-table table_name
```

**Release 18 and earlier:**

```
ip { downlink | uplink } qos-dscp { af11 | af12 | af13 | af21 | af22 | af23 | af31 | af32 | af33 | af41 | af42 | af43 | be | ef }
```




---

**Important** The **qos-dscp** keyword is deprecated from 19.2 and later releases.

---

```
no ip { downlink | uplink } qci-dscp-mapping-table
```

**no**

Removes the IP parameters for downlink/uplink data from this HeNB-GW Access service configuration.

Removes the QCI-DSCP mapping table for downlink/uplink data from this HeNB-GW Access service configuration.

**downlink**

Direction (towards henb) in which DSCP marking shall be done.

**uplink**

Direction (towards sgw) in which DSCP marking shall be done.

**qci-dscp-mapping-table** *table\_name*

QCI-DSCP mapping table to refer for this HENBGW ACCESS service.

*table\_name* is the table name , which is a string of size 1 to 63.

**qos-dscp** { **af11** | **af12** | **af13** | **af21** | **af22** | **af23** | **af31** | **af32** | **af33** | **af41** | **af42** | **af43** | **be** | **ef** }

Default: **af11**

Specifies the DSCP for the specified QoS traffic pattern. **qos-dscp** can be configured to any one of the following:

**af11**: Assured Forwarding 11 per-hop-behavior (PHB)

**af12**: Assured Forwarding 12 PHB

**af13**: Assured Forwarding 13 PHB

**af21**: Assured Forwarding 21 PHB

**af22**: Assured Forwarding 22 PHB

**af23**: Assured Forwarding 23 PHB

**af31**: Assured Forwarding 31 PHB

**af32**: Assured Forwarding 32 PHB

**af33**: Assured Forwarding 33 PHB

**af41**: Assured Forwarding 41 PHB

**af42**: Assured Forwarding 42 PHB

**af43**: Assured Forwarding 43 PHB

**be**: Best effort forwarding PHB

**ef**: Expedited forwarding PHB

### Usage Guidelines

Use this command to configure the Internet protocol (IP) parameters including downlink and uplink of data for specified HENBGW ACCESS service.

### Example

Following command configures the DSCP-level for uplink data traffic through a specific HeNB-GW Access service to **af31**:

```
ip uplink qos-dscp af31
```

Following command configures the QCI-DSCP mapping table table1.

```
ip uplink qci-dscp-mapping-table table1
```

ip



# SAEGW Service Configuration Mode Commands

---

## Command Modes

The System Architecture Evolution Gateway (SAEGW) Service Configuration Mode is used to create and manage the relationship between specified services used for S-GW and P-GW network traffic.

Exec > Global Configuration > Context Configuration > SAEGW Service Configuration

**configure** > **context** *context\_name* > **saegw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-saegw-service)#
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [associate](#), on page 248
- [do show](#), on page 250
- [gtpc handle-collision upc nrupc](#), on page 251
- [end](#), on page 252
- [exit](#), on page 253

# associate

Associates the SAEGW service with specific pre-configured services configured in the same context.

---

**Product**

SAEGW

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SAEGW Service Configuration

**configure** > **context** *context\_name* > **saegw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-saegw-service)#
```

---

**Syntax Description**

```
[ no ] associate { pgw-service name | sgw-service name }
```

**no**

Removes the selected association from this service.

**pgw-service *name***

Specifies that the SAEGW service is to be associated with an existing P-GW service within this context.

*name* must be an alphanumeric string of 1 through 63 characters and be an existing P-GW service.

**sgw-service *name***

Specifies that the SAEGW service is to be associated with an existing S-GW service within this context.

*name* must be an alphanumeric string of 1 through 63 characters and be an existing S-GW service.




---

**Important**

S-GW egress eGTP service must be in the same context as this SAEGW service. In addition, PMIP is not supported for the S-GW service egress.

---



---

**Usage Guidelines**

Use this command to associate the SAEGW service with other pre-configured services configured in the same context.




---

**Important**

Each P-GW or S-GW service may only be associated with one SAEGW service; however, there may be multiple SAEGW services configured on a system in separate contexts.

---

**Example**

The following commands associate this SAEGW service with a P-GW service called *pgw1* and a S-GW service called *sgw2*:



```
associate pgw-service pgw1  
associate sgw-service sgw2
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# gtpc handle-collision upc nrupc

This command helps in enabling or disabling collision handling between SGSN initiated UPC and NRUPC request.

---

**Product** SAEGW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > SAEGW Service Configuration

**configure** > **context** *context\_name* > **saegw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-saegw-service)#
```

---

**Syntax Description** [ **no** | **default** ] **gtpc handle-collision upc nrupc**

## **no**

Disables collision handling between SGSN initiated UPC and NRUPC request.

## **default**

Sets default collision handling behavior between SGSN initiated UPC and NRUPC request. By default, collision handling is enabled.

## **handle-collision upc nrupc**

Enables/Disables collision handling between SGSN initiated UPC and network requested UPC. By default, collision handling is enabled.

---

## **Usage Guidelines**

This command is used to enable or disable collision handling between SGSN initiated UPC and NRUPC request.

## **Example**

The following example disables collision handling between SGSN initiated UPC and NRUPC request.

```
no gtpc handle-collision upc nrupc
```

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

■ exit



## SaMOG Service Configuration Mode Commands

---

### Command Modes

Creates SaMOG service and enters SaMOG service configuration mode.

Exec > Global Configuration > Context Configuration > SAMOG Service Configuration

**configure** > **context** *context\_name* > **samog-service** *samog\_service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-samog-service)#
```



---

### Important

Available commands or keywords/variables vary based on platform type, product version, and installed license(s).

- [associate](#), on page 256
- [do show](#), on page 258
- [end](#), on page 259
- [exit](#), on page 260
- [max-sessions](#), on page 261
- [timeout](#), on page 262

# associate

SaMOG associates another service to this SAMOG service.

---

## Product

SaMOG

---

## Command Modes

Exec > Global Configuration > Context Configuration > SAMOG Service Configuration

**configure** > **context** *context\_name* > **samog-service** *samog\_service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-samog-service)#
```

---

## Syntax Description

```
associate { cgw-service cgw_service_name | dhcp-service dhcp_service_name [ level
  { system | user } ] | dhcpv6-service dhcpv6_service_name | mrme-service
mrme_service_name | subscriber-map subscriber_map_name }
no associate { cgw-service | dhcp-service | dhcpv6-service | mrme-service
  | subscriber-map }
```

### no

Disables the association of the service with the SaMOG service.

The **no associate dhcp-service** command does not disassociate existing sessions, and only new sessions will not be established. Existing sessions continue to use the DHCPv4 service to which it was bound during session establishment.

The **no associate dhcpv6-service** command stops the SaMOG service from processing DHCPv6 packets.

### cgw-service *cgw\_service\_name*

The CGW service should be configured before associating the same with SaMOG service.

*cgw\_service\_name* must be an alphanumeric string between 1 and 63 characters.

### dhcp-service *dhcp\_service\_name* [ level { system | user } ]

Specifies the DHCPv4 service to associate with the SaMOG service. DHCPv4 is optional while starting an SaMOG service.

*dhcp\_service\_name* must be an alphanumeric string from 1 through 63.

While the association of the DHCPv4 service with the SaMOG service is optional, DHCPv4 service must be associated with the SaMOG service for the SaMOG Ethernet over GRE (EoGRE) feature to function. If no DHCPv4 service is configured and associated, and at least one EoGRE access type Radius client exist, the output of the **show configuration errors** command will display a warning under the **SaMOG service system errors** section.




---

## Important

The associated DHCPv4 service must not be used for any service other than SaMOG, as packets are always forwarded over the EoGRE tunnel only.

---



**level { system | user }**: Specifies the processing level of the DHCP server messages. **system** will enable DHCP server messages to be processed at the system and user-level. **user** will enable DHCP server messages to be processed at the user-level only. The default value for processing DHCP messages is user level.

**dhcpv6-service *dhcpv6\_service\_name***

Specifies the DHCPv6 service to associate with the SaMOG service, to process DHCPv6 packets. Configure the DHCPv6 server using the **bind address** command in the DHCPv6 Service Configuration Mode.

*dhcpv6\_service\_name* must be an alphanumeric string from 1 through 63 characters.

**mrme-service *mrme\_service\_name***

The MRME service should be configured before associating the same with SaMOG service.

*mrme\_service\_name* must be an alphanumeric string from 1 through 63 characters.

**subscriber-map *subscriber\_map\_name***

The subscriber map service should be configured before associating the same with SaMOG service.

*subscriber\_map\_name* must be an alphanumeric string from 1 through 63 characters.

---

**Usage Guidelines**

Use this command to associate the SaMOG service to CGW service, DHCPv4 service, MRME service, or Subscriber Mapping.

**Example**

The following command associates subscriber-map *smap* with SaMOG Service.

```
associate subscriber-map smap
```

The following command associates cgw-service *cgw* with SaMOG Service.

```
associate cgw-service cgw
```

The following command associates mrme-service *mrme* with SaMOG Service.

```
associate mrme-service mrme
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# max-sessions

Configures maximum number of subscribers SAMOG service can support, ranging from 0 to 4000000.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SAMOG Service Configuration

**configure** > **context** *context\_name* > **samog-service** *samog\_service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-samog-service)#
```

---

**Syntax Description**

**max-sessions** *max\_sessions*  
**default max-sessions**

**max-sessions** *max\_sessions*

Configures maximum number of subscribers SAMOG service can support.

*max\_sessions* is an integer value between 0 and 4000000.

**default**

Sets the default value, 4000000 for Max Sessions.

---

**Usage Guidelines**

Use this command to configure the maximum number of subscribers SAMOG service can support.

**Example**

Use the following command to configure the maximum number of subscribers SAMOG service can support:

```
max-sessions 500
```

# timeout

Configures the session's time-to-live (TTL) settings under SAMOG service.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SAMOG Service Configuration

**configure** > **context** *context\_name* > **samog-service** *samog\_service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-samog-service)#
```

---

**Syntax Description**

```
timeout { absolute absolute_value | idle idle_value | setup-timeout
setup_timeout_value }
```

```
default timeout [ absolute | idle | setup-timeout ]
```

```
no timeout [ absolute | idle ]
```

**default**

Sets/restores the default value assigned for timeout.

The default value of absolute and idle timeout is *0*, which indicates the function is disabled.

The default value of setup-timeout is *60*.

**no**

Enables / Disables the timeout option.

**absolute** *absolute\_value*

Specifies the maximum duration of the session, in seconds, before the system automatically terminates the session.

*absolute\_value* must be an integer between *0* and *2147483647*.

**idle** *idle\_value*

Specifies the maximum duration a session can remain idle, in seconds, before the system automatically terminates the session. Zero indicates that the timeout function is disabled. Default is *0*.

*idle\_value* must be an integer between *0* and *2147483647*.

**setup-timeout** *setup\_timeout\_value*

Specifies the maximum time allowed for session setup in seconds. Default is *60* seconds.

*setup\_timeout\_value* must be an integer between *0* and *1000000*.

---

**Usage Guidelines**

Use this command to configure the session's time-to-live (TTL) settings under SAMOG service.

**Example**

Use the following command to configure the setup-timeout to 500 seconds:

```
timeout setup-timeout 500
```

Use the following command to configure the absolute timeout to 120 seconds:

```
timeout absolute 120
```

**timeout**





## SBc Service Configuration Mode Commands

The SBc (SBc-AP) interface is used by the MME to communicate with Cell Broadcast Centers (CBC) and deliver Public Warning Messages to eNodeBs. The SBc Service provides support on the MME for the Commercial Mobile Alert System (CMAS).

### Command Modes

Exec > Global Configuration > Context Configuration > SBc Service Configuration

**configure** > **context** *context\_name* > **sbc-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sbc-service) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



### Important

Beginning with Release 18.4, a valid license key is required to access the commands in this configuration mode. For information about obtaining such a license, contact your Cisco Representative.

- [associate](#), on page 266
- [bind](#), on page 267
- [cbc-associations](#), on page 268
- [do show](#), on page 269
- [end](#), on page 270
- [exit](#), on page 271
- [ip](#), on page 272
- [sbc-mme](#), on page 273
- [send](#), on page 274

# associate

This new command specifies the SCTP parameter template to employ for this SBc-AP interface.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SBc Service Configuration

**configure** > **context** *context\_name* > **sbc-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sbc-service)#
```

---

**Syntax Description**

**associate sctp-param-template** *sctp\_param\_template\_name*  
**no associate sctp-param-template**

**no**

Disassociates the specified SCTP Parameter Template from this SBc service.

**sctp-param-template** *sctp\_param\_template\_name*

Associates the previously created SCTP Parameter Template with this SBc service.

*sctp\_param\_template\_name* must be an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines**

Associates a previously created SCTP Parameter Template with this SBc service.

Configuration of the SCTP Parameter template is a pre-requisite for this command.

Changes to the configuration will restart the SBc service.

Associating the SBc service to the SCTP parameter template is not required for the SBc service to be operational.

Refer to the **sctp-param-template** command in the *Global Configuration Mode Commands (L-S) chapter* for more information about configuring a SCTP Parameter Template.

# bind

Binds the SBc service to a local SCTP IP address. This interface is used by the SBc service to communicate with the Cell Broadcast Center (CBC).

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SBc Service Configuration

**configure** > **context** *context\_name* > **sbc-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sbc-service)#
```

---

**Syntax Description**

```
bind { ipv4-address ipv4_address_value1 [ ipv4-address ipv4_address_value2 ] |
ipv6-address ipv6_address_value1 [ ipv6-address ipv6_address_value2 ]
no bind
```

**no**

Removes the interface binding from this SBc service.

**ipv4-address** *ipv4\_address\_value1* [ **ipv4-address** *ipv4\_address\_value2* ]

Specifies the IPv4 address of an interface in the current context through which communication with the CBC occurs.

A second IPv4 address can be specified for multi-homing purposes with the optional **ipv4-address** keyword.

**ipv6-address** *ipv6\_address\_value1* [ **ipv6-address** *ipv6\_address\_value2* ]

Specifies the IPv6 address of an interface in the current context through which communication with the CBC occurs.

A second IPv6 address can be specified for multi-homing purposes with the optional **ipv6-address** keyword.

---

**Usage Guidelines**

Use this command to bind the SBc service to an IP address.

The command is service critical; removing the configuration will stop the SBc service.

Up to two IPv4 or two IPv6 addresses can be specified for multi-homing purposes.

Refer to the **sbc-mme** command in this chapter to specify the SCTP port number to be used.

**Example**

The following command configures 2 IPv4 addresses for the SCTP connection (for multi homing):

```
bind ipv4-address 10.1.1.100 ipv4-address 10.1.1.200
```

## cbc-associations

Configures the maximum number of Cell Broadcast Center (CBC) connections allowed for this SBC service.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SBC Service Configuration

**configure** > **context** *context\_name* > **sbc-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sbc-service)#
```

---

**Syntax Description**

```
{ default | no } cbc-associations maximum number
```

**default**

Returns the maximum number of CBC associations allowed to the default of 1.

**no**

Removes the configured maximum number of CBC associations allowed, and returns the setting to the default value of 1.

**maximum *number***

Configures the maximum number of CBC associations allowed for this SBC service.

*number* must be an integer from 1 to 2.

Default: 1.

---

**Usage Guidelines**

Use this command to configure the maximum number of CBC associations allowed for this SBC service.


**Caution**

Changes to this configuration will restart the SBC service.

---

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ip

This command configures the IP parameters on the SGs interface.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > MME SGs Service Configuration

**configure** > **context** *context\_name* > **sgs-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgs-service)#
```

---

**Syntax Description**

[ **no** ] **ip qos-dscp** *dscp\_value*

**no**

Removes IP parameter configuration from the SGs service/interface.

**qos-dscp** *dscp\_value*

The **qos-dscp** keyword designates the Quality of Service - Differentiated Services Code Point value to the packet leaving through the SGs interface.

*dscp\_value* is a value assigned to the packet for DSCP marking. The value can be a pre-defined DSCP value or an arbitrary value ranging from 0x01 to 0x3F.

---

**Usage Guidelines**

SGs interface allows Differentiated Services Code Point (DSCP) marking functionality. DSCP marking helps in packet traffic management. DSCP marking can be performed on both IPv4 and IPv6 packets leaving the SGs interface.

Either the pre-defined DSCP values can be used for marking, or any arbitrary value ranging from 0x01 to 0x3F can be assigned. The default DSCP value is 0x00 or be (Best Effort). The default DSCP value is automatically set when the configuration is disabled.

**Example**

The following command shows the IP configuration for DSCP marking on the SGs service.

```
ip qos-dscp ef
```



# sbc-mme

Configures the SCTP port to be used for the SBc interface.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SBc Service Configuration

**configure** > **context** *context\_name* > **sbc-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sbc-service)#
```

---

**Syntax Description**

```
sbc-mme sctp port port_num  
[ default | no ] sbc-mme sctp port
```

**default**

Returns the command to the default SCTP port of 29168.

**no**

Removes the configured SCTP port value, and returns the command to the default SCTP port of 29168.

**sctp port *port\_num***

Configures the SCTP port to be used for the SBc interface.

*port\_num* must be an integer from 1 through 65535.

Default: 29168.

---

**Usage Guidelines**

Use this command to configure the SCTP port number for this SBc service.

**Example**

The following command configures this SBc service to use SCTP port number 21112:

```
mme-sbc sctp-port 21112
```

# send

This command enables or disables the warning indication messages towards CBC from MME.

.

<b>Product</b>	MME
<b>Privilege</b>	Administrator
<b>Command Modes</b>	Exec > Global Configuration > Context Configuration > SBC Service Configuration <b>configure</b> > <b>context</b> <i>context_name</i> > <b>sbc-service</b> <i>service_name</i> Entering the above command sequence results in the following prompt: <code>[context_name]host_name(config-sbc-service)#</code>
<b>Syntax Description</b>	<b>[ no   default ] send { stop-warning-ind   write-replace-warning-ind }</b>  <b>no</b> Removes the configuration of sending the warning indication [ stop warning / write replace warning ] messages towards CBC from MME.  <b>default</b> Sets the default configuration of sending the warning indication [ stop warning / write replace warning ] messages towards CBC from MME. By default sending of warning indication messages are disabled.  <b>send stop-warning-ind</b> Enables the stop warning indication messages towards CBC from MME.  <b>send write-replace-warning-ind</b> Enables the write-replace-warning indication messages towards CBC from MME.
<b>Usage Guidelines</b>	Use this command to enables or disables the warning indication messages towards CBC from MME.

## Example

The following command to stop warning indication message towards CBC from MME:

```
send stop-warning-ind
```



# SCCP Network Configuration Mode Commands

Signaling Connection Control Part (SCCP) is a routing protocol in the SS7 protocol suite in layer 4, which provides end-to-end routing for TCAP messages to their proper database.

## Command Modes

The SCCP Network Configuration Mode is used to configure properties for Signaling Connection Control Part (SCCP) services for SS7.

Exec > Global Configuration > SCCP Network Configuration

**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [associate](#), on page 276
- [description](#), on page 277
- [destination](#), on page 278
- [do show](#), on page 280
- [end](#), on page 281
- [exit](#), on page 282
- [global-title-translation](#), on page 283
- [hop-count](#), on page 284
- [self-point-code](#), on page 285
- [timeout](#), on page 287

# associate

Associates an SS7 routing domain with the SCCP network.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SCCP Network Configuration  
**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

## Syntax Description

**associate** **ss7-routing-domain** *rd\_id*  
no associate

### no

Removes the association with the SS7 routing domain from the system configuration.

### *rd\_id*

This number identifies an already defined SS7 routing domain.

*rd\_id*: enter an integer from 1 through 12.

## Usage Guidelines

Use this command to associate SS7 routing domain configurations with SCCP network configurations.

## Example

The following command associates the SCCP network with SS7 routing domain 2:

```
associate ss7-routing-domain 2
```

## description

This command defines a string that describes the SCCP network. The description is used for operator reference.



### Important

In Release 20 and later, HNBNW is not supported. This command must not be used for HNBNW in Release 20 and later. For more information, contact your Cisco account representative.

### Product

SGSN  
HNB-GW

### Privilege

Security Administrator, Administrator

### Command Modes

Exec > Global Configuration > SCCP Network Configuration

**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

### Syntax Description

**description** *string*

**no description**

#### *string*

This is a string to describe the SCCP network.

*string* must be an alphanumeric string from 1 through 127 characters in length. If there are spaces in the string the string must be enclosed in double-quotes. For example; "This is a Description".

#### **no**

Removes the description from the system configuration.

### Usage Guidelines

Use this command to configure a description of this SCCP service for operator reference.

### Example

The following command sets the description to "This is the SCCP Service Number 1":

```
description "This is the SCCP Service Number 1."
```

# destination

This command configures the SCCP network destination information. Use this command multiple times to set all of the destination information required.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SCCP Network Configuration

**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

## Syntax Description

```
destination dpc pt_code { name route_name | next-hop pt_code [ priority priority ] | ssn subsys_num | version sccp_ver }  
no destination dpc p_code [ name route_name | ssn ssn_num | version sccp_ver ]
```

**no**

Deletes the specified destination information from the SCCP network configuration.

**dpc** *pt\_code*

Specifies the SCCP destination point code.

*pt\_code*: Must be in SS7 point code dotted-decimal ###.###.### format or decimal ##### format.

**name** *route\_name*

The name of the SCCP destination route.

*route\_name*: enter an alphanumeric string from 1 through 64 characters in length.

**next-hop** *pt\_code* [ **priority** *priority* ]

Associates the next destination defined in the SS7 routing domain and assigns the next-hop a priority for use.

*pt\_code*: Must be in SS7 point code dotted-decimal ###.###.### format or decimal ##### format.

*priority*: Must be an integer from 0 to 15, with 0 setting the highest priority.

**ssn *subsys\_num***

The destination subsystem number.

*subsys\_num*: enter an integer from 1 through 255.

**version *sccp\_ver***

*sccp\_ver*: enter one of the following to select the SCCP variant:

- ANSI88
- ANSI92
- ANSI96
- BELL05
- CHINA
- GSM0806
- ITU88
- ITU92
- ITU96

**Usage Guidelines**

Use this command to configure the destination information for the SCCP network.

**Example**

The following commands set the name of the destination route to `default_route`, the subsystem number to 1, and the variant version to ITU96, all with a destination point code of 1:

```
destination dpc 1 name default_route
destination dpc 1 ssn 1
destination dpc version ITU96
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---



# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

SGSN

HNB-GW

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Return to the Exec mode.

# exit

Exits the current configuration mode and returns to the global configuration mode.

---

**Product**

SGSN

HNB-GW

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description****exit**

---

**Usage Guidelines**

Return to the global configuration mode.

# global-title-translation

This command associates a GTT address-map with this SCCP network.



---

**Important**

In Release 20 and later, HNBN is not supported. This command must not be used for HNBN in Release 20 and later. For more information, contact your Cisco account representative.

---

---

**Product**

SGSN  
HNB-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SCCP Network Configuration

**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

---

**Syntax Description**

**global-title-translation address-map instance** *instance*  
**no global-title-translation address-map instance** *instance*

**no**

Deletes the GTT address-map instance associated with this SCCP network.

***instance***

This value uniquely identifies a specific previously defined instance of a GTT address-map.

*instance*: enter an integer from 1 to 4096.

---

**Usage Guidelines**

Use this command to link a GTT address-map, configured with the GTT Address Map configuration mode, to a specific SCCP network configuration.

---

**Example**

```
global-title-translation address-map instance gtt-map1
```

# hop-count

This command specifies the hop count for this SCCP network.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SCCP Network Configuration  
**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

## Syntax Description

**hop-count** *hop\_cnt*  
**default hop-count**

### default

Resets the hop-count value to the system default of 5.

### *hop\_cnt*

The hop count to assign to this SCCP network.

*hop\_cnt*: enter an integer from 1 to 15.

## Usage Guidelines

Use this command to define the hop count for this SCCP network.

## Example

The following command sets the hop count to 3:

```
hop-count 3
```

# self-point-code

This command specifies the SS7 point code for this SCCP service.



## Important

In Release 20 and later, HNBN is not supported. This command must not be used for HNBN in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SCCP Network Configuration

**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

## Syntax Description

**self-point-code** *point\_code*  
**no self-point-code**

**no**

Deletes the configured self point code.

### ***point\_code***

Defines the point code to assign to this SCCP network service.

*point\_code*: value entered must adhere to the point code variant selected when the SCCP network instance was defined:

- ITU Range 0.0.1 to 7.255.7
- ANSI Range 0.0.1 to 255.255.255
- TTC Range 0.0.1 to 15.31.255
- a string of 1 to 11 combined digits and period.

## Usage Guidelines

Use this command to assign the self point code to use for this SCCP service.

## Example

The following command sets an ITU-based point code for this SCCP service:

```
self-pointcode 4.121.5
```

The following command removes the configured self-point code:

```
no self-pointcode
```

# timeout

This command configures the timeout parameters for this SCCP network.



## Important

In Release 20 and later, HNGBW is not supported. This command must not be used for HNGBW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SCCP Network Configuration  
**configure** > **sccp-network** *id\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sccp-network-sccp_id)#
```

## Syntax Description

```
timeout { attack-timer | congestion-timer | conn-est-timer | crd-timer |
decay-timer | iar-timer | ias-timer | interval-timer | reassembly-timer
| release-timer | repeat-release-timer | reset-timer | sst-timer } +
default timeout
no timeout timer
```

### **attack-timer** *time*

Defines the time before the attack timer expires.

*time*: enter an integer between 1 and 10.

### **congestion-timer** *time*

Defines the time before the congestion timer expires.

*time*: enter an integer between 1 and 10.

### **conn-est-timer** *time*

Defines the time before the connection timer expires.

*time*: enter an integer between 6 and 12.

### **crd-timer** *time*

Defines the time before the coordinated-state-change timer expires.

*time*: enter an integer between 60 and 120.

**decay-timer *time***

Defines the time before the decay timer expires.

*time*: enter an integer between 1 and 10.

**iar-timer *time***

Defines the time before the inactivity-receive timer expires.

*time*: enter an integer between 60 and 120.

**ias-timer *time***

Defines the time before the inactivity-send timer expires.

*time*: enter an integer between 30 and 60.

**interval-timer *time***

Defines the time before the interval timer expires.

*time*: enter an integer between 6 and 12

**reassembly-timer *time***

Defines the time before the reassembly-timer expires.

*time*: enter an integer between 10 and 20.

**release-timer *time***

Defines the time before the release-assembly timer expires.

*time*: enter an integer between 1 and 2.

**repeat-release-timer *time***

Defines the time before repeat-release timer expires.

*time*: enter an integer between 1 and 2

**reset-timer *time***

Defines the amount of time before the reset timer expires.

*time*: enter an integer between 1 and 2

**sst-timer *time***

Defines the amount of time before the subsystem status test timer expires.

*time*: enter an integer between 5 and 1200.

**default**

Resets the timeout parameter to the system default.



**no**

Deletes the specified timer configuration.

---

**Usage Guidelines**

Use this command to assign timeout timers and timeout values for this SCCP service.

**Example**

```
timeout reset-timer 75
```

**timeout**



# SCTP Parameter Template Configuration Mode Commands

---

This chapter provides information about commands used to configure parameters for Stream Control Transmission Protocol (SCTP) associations. The commands become part of a template that can be associated with services running on the system.

---

## Command Modes

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local] host_name(sctp-param-template) #
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [do show](#), on page 293
- [end](#), on page 294
- [exit](#), on page 295
- [sctp-alpha](#), on page 296
- [sctp-alt-accept-flag](#), on page 297
- [sctp-beta](#), on page 298
- [sctp-checksum-type](#), on page 299
- [sctp-cookie-life](#), on page 300
- [sctp-max-assoc-retx](#), on page 301
- [sctp-max-in-strms](#), on page 302
- [sctp-max-init-retx](#), on page 303
- [sctp-max-mtu-size](#), on page 304
- [sctp-max-out-strms](#), on page 305
- [sctp-max-path-retx](#), on page 306
- [sctp-min-mtu-size](#), on page 307
- [sctp-rto-initial](#), on page 308
- [sctp-rto-max](#), on page 309
- [sctp-rto-min](#), on page 310

- [sctp-sack-frequency](#), on page 311
- [sctp-sack-period](#), on page 312
- [sctp-start-mtu-size](#), on page 313
- [timeout](#), on page 314

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# sctp-alpha

Configures the SCTP retransmission timeout (RTO) alpha value.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-alpha** *value*  
**default** **sctp-alpha**

**default**

Returns the command to its default setting of 5.

**value**

Default: 5

Specifies the SCTP retransmission timeout alpha value. *value* must be an integer from 0 through 65535.

---

**Usage Guidelines**

Use this command to configure the SCTP RTO alpha value. The RTO alpha value is used in calculating the smoothed round-trip time (SRTT) and the round-trip time variation (RTTVAR) for new round trip time (RTT) measurements.

**Example**

The following command sets the SCTP RTO alpha value to 10:

```
sctp-alpha 10
```



# sctp-alt-accept-flag

Configures the SCTP alternate accept flag for additional life time for the association.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

```
sctp-alt-accept-flag { disable | enable }  
default sctp-alt-accept-flag
```

**default**

Returns the command to its default setting of enable.

**disable | enable**

Specifies if the alternate accept flag is enabled or disabled.

---

**Usage Guidelines**

Use this command to configure the SCTP alternate accept flag for additional life time for the association.

**Example**

The following command disables the alternate accept flag for the SCTP association:

```
sctp-alt-accept-flag disable
```

# sctp-beta

Configures the SCTP retransmission timeout (RTO) beta value.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-beta** *value*  
**default** **sctp-beta**

**default**

Returns the command to its default setting of 10.

**value**

Specifies the SCTP retransmission timeout beta value as an integer from 0 through 65535. Default: 10

---

**Usage Guidelines**

Use this command to configure the SCTP RTO beta value. The RTO beta value is used in calculating the smoothed round-trip time (SRTT) and the round-trip time variation (RTTVAR) for new round trip time (RTT) measurements.

**Example**

The following command sets the SCTP RTO beta value to 20:

```
sctp-beta 20
```

# sctp-checksum-type

Configures the checksum type used to increase the integrity of the SCTP packets during transmission.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

```
sctp-checksum-type { adler32 | crc32 }  
default sctp-checksum-type
```

**default**

Returns the command to its default setting of CRC32.

**adler32 | crc32**

Specifies the type of checksum used to increase data integrity of SCTP packets.

**adler32**: Specifies that the Adler-32 checksum algorithm is used to increase data integrity for SCTP packets.

**crc32**: Specifies that a 32-bit cyclic redundancy check is used to increase data integrity of SCTP packets.

---

**Usage Guidelines**

Use this command to select the checksum for data integrity of SCTP packets.

**Example**

The following command enables the Adler-32 checksum algorithm used to increase data integrity of SCTP packets:

```
sctp-checksum-type adler32
```

# sctp-cookie-life

Configures the lifetime of the SCTP cookie.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-cookie-life** *value*  
**default sctp-cookie-life**

**default**

Returns the command to its default setting of 600 (60000 milliseconds).

**value**

Default: 600 (60000 milliseconds)

Specifies the lifetime of the SCTP cookie. *value* is an integer from 50 through 1200. The range translates to 5000 milliseconds to 120000 milliseconds, as the granularity is in 100-millisecond increments.

---

**Usage Guidelines**

Use this command to configure the lifetime of the SCTP cookie.

**Example**

The following command configures the lifetime of the SCTP cookie to 80000 milliseconds:

```
sctp-cookie-life 800
```

# sctp-max-assoc-retx

Configures the maximum number of retransmissions for SCTP associations.

---

**Product** MME

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description** **sctp-max-assoc-retx** *value*  
**default** **sctp-max-assoc-retx**

**default**

Returns the command to its default setting of 10.

**value**

Specifies the maximum number of retransmissions allowed by this template for SCTP associations as an integer from 0 through 255. Default: 10

---

**Usage Guidelines** Use this command to configure the maximum number of retransmissions allowed.

**Example**

The following command configures the maximum number of retransmissions to 7:

```
sctp-max-assoc-retx 7
```

## sctp-max-in-strms

Configures the maximum number of incoming SCTP streams.

---

### Product

MME  
SGSN

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

### Syntax Description

**sctp-max-in-strms** *value*  
**default sctp-max-in-strms**

#### default

Returns the command to its default setting of 16.

#### value

Specifies the maximum number of incoming SCTP streams as an integer from 1 through 16. Default: 16.

The MME restricts the allowable range as 2-16. If a value of 1 is entered, value 2 will be applied for any MME service associated with this SCTP parameter template.

---

### Usage Guidelines

Use this command to configure the maximum number of incoming SCTP streams.

#### Example

The following command configures the maximum number of incoming SCTP streams to 5:

```
sctp-max-in-strms 5
```

## sctp-max-init-retx

Configures the maximum number of retransmissions for SCTP initiations.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-max-init-retx** *value*  
**default sctp-max-init-retx**

**default**

Returns the command to its default setting of 5.

**value**

Specifies the maximum number of retransmissions for SCTP initiations as an integer from 0 through 255.  
Default: 5

---

**Usage Guidelines**

Use this command to configure the maximum number of retransmissions for SCTP initiations.

**Example**

The following command configures the maximum number of retransmissions for SCTP initiations to 10:

```
sctp-max-init-retx 10
```

## sctp-max-mtu-size

Configures the maximum transmission unit (MTU) size (in bytes) for SCTP streams.

---

### Product

MME

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

### Syntax Description

**sctp-max-mtu-size** *bytes*  
**default sctp-max-mtu-size**

#### **default**

Returns the command to its default setting of 1500 bytes.

#### **bytes**

Specifies the maximum MTU size (in bytes) for SCTP streams as an integer from 508 through 65535. Default: 1500

---

### Usage Guidelines

Use this command to configure the maximum MTU size, in bytes, for SCTP streams.

#### **Example**

The following command configures the maximum MTU size for SCTP streams to *3000*:

```
sctp-max-mtu-size 3000
```



# sctp-max-out-strms

Configures the maximum number of outgoing SCTP streams.

---

**Product**

MME

SGSN

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template) #
```

---

**Syntax Description**

**sctp-max-out-strms** *value*  
**default sctp-max-out-strms**

**default**

Returns the command to its default setting of 2.

**value**

Specifies the maximum number of outgoing SCTP streams as an integer from 1 through 16.

MME Default 16.

SGSN Default: 2.

---

**Usage Guidelines**

Use this command to configure the maximum number of outgoing SCTP streams.

The MME restricts the allowable range as 2-16. If a value of 1 is entered, value 2 will be applied for any MME service associated with this SCTP parameter template.

For the SGSN, if the user tries to configure the value of **sctpmax-out-strms** less than "2", a message is displayed and the default value is set.

**Example**

The following command configures the maximum number of outgoing SCTP streams to 5:

```
sctp-max-out-strms 5
```

# sctp-max-path-retx

Configures the maximum number of retransmissions of SCTP paths.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-max-path-retx** *value*  
**default sctp-max-path-retx**

**default**

Returns the command to its default setting of 5.

**value**

Specifies the maximum number of retransmissions of SCTP paths as an integer from 0 through 255. Default: 5

---

**Usage Guidelines**

Use this command to configure the maximum number of retransmissions of SCTP paths. An SCTP path is a connection between an endpoint address and a peer endpoint address.

**Example**

The following command configures the maximum number of retransmissions of SCTP paths to *10*:

```
sctp-max-path-retx 10
```

# sctp-min-mtu-size

Configures the minimum maximum transmission unit (MTU) size (in bytes) for SCTP streams.

---

**Product** MME

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template) #
```

---

**Syntax Description** **sctp-min-mtu-size** *bytes*  
**default sctp-min-mtu-size**

## **default**

Returns the command to its default setting of 508 bytes.

## **bytes**

Specifies the minimum MTU size (in bytes) for SCTP streams as an integer from 508 through 65535. Default: 508

---

**Usage Guidelines** Use this command to configure the minimum MTU size, in bytes, for SCTP streams.

## **Example**

The following command configures the minimum MTU size for SCTP streams to *1000*:

```
sctp-min-mtu-size 1000
```

# sctp-rto-initial

Configures the initial time for SCTP retransmission timeouts (RTOs).

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-rto-initial** *value*  
**default sctp-rto-initial**

**default**

Returns the command to its default setting of 30 (3000 milliseconds).

**value**

Specifies the initial time for SCTP RTO as an integer from 1 through 1200. The granularity is in 100ms increments (20 = 2000ms). Default: 30 (3000 milliseconds)

---

**Usage Guidelines**

Use this command to configure the initial time for SCTP RTOs.

**Example**

The following command configures the initial SCTP RTO to 6000ms:

```
sctp-rto-initial 60
```

## sctp-rto-max

Configures the maximum time for SCTP retransmission timeouts (RTOs).

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-rto-max** *value*  
**default sctp-rto-max**

**default**

Returns the command to its default setting of 600 (60000 milliseconds).

**value**

Specifies the maximum time for SCTP RTOs as an integer from 5 through 1200. The granularity is in 100ms increments (120 = 12000ms). Default: 600 (60000 milliseconds)

---

**Usage Guidelines**

Use this command to configure the maximum time for SCTP RTOs.

**Example**

The following command configures the maximum time for SCTP RTOs to 120000ms:

```
sctp-rto-max 120
```

## sctp-rto-min

Configures the minimum SCTP retransmission timeout (RTO).

---

### Product

MME

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

### Syntax Description

**sctp-rto-min** [ **units-10ms** ] *value*  
**default sctp-rto-min**

#### **default**

Returns the command to its default setting of 10 (1000 milliseconds).

#### **units-10ms**

Including this keyword specifies that the integer *value* is to be calculated using 10ms increments (instead of 100ms increments) to allow for finer granularity. *value* is an integer from 0 through 500.

#### **value**

Specifies the minimum time for SCTP RTOs as an integer from 1 through 50. The granularity is in 100ms increments (20 = 2000ms). Default: 10 (1000 milliseconds)

---

### Usage Guidelines

Use this command to configure the minimum time for SCTP RTOs.

#### **Example**

The following command configures the minimum time for SCTP RTOs to 2000ms:

```
sctp-rto-min 20
```

# sctp-sack-frequency

Configures the frequency of transmission of SCTP selective acknowledgements (SACK).

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template) #
```

---

**Syntax Description**

**sctp-sack-frequency** *value*  
**default** **sctp-sack-frequency**

**default**

Returns the command to its default setting of 2.

**value**

Specifies the frequency of SCTP selective acknowledgements as an integer from 1 through 20. Default: 2

---

**Usage Guidelines**

Use this command to configure the frequency of SCTP selective acknowledgements.

**Example**

The following command configures the frequency of SCTP selective acknowledgements to 10:

```
sctp-sack-frequency 10
```

# sctp-sack-period

Configures the delay before sending an SCTP selective acknowledgement (SACK).

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

**sctp-sack-period** [ **units-10ms** ] *value*  
**default sctp-sack-period**

**default**

Returns the command to its default setting of 2 (200 milliseconds).

**units-10ms**

Including this keyword specifies that the integer *value* is to be calculated using 10ms increments (instead of 100ms increments) to allow for finer granularity. *value* is an integer from 0 through 50.

**value**

Specifies the period for SCTP selective acknowledgements as an integer from 0 through 5. The granularity is in 100ms increments (3 = 300ms). Default: 2 (200 milliseconds).




---

**Important**

If this value is set to 0, the MME service will automatically configure a 10 ms sack period in order to allow proper initialization of the CCPU SCTP stack.

---



---

**Usage Guidelines**

Use this command to configure the period for SCTP selective acknowledgements.

**Example**

The following command configures the period for SCTP selective acknowledgements to 400ms (using the 10ms granularity):

```
sctp-sack-period units-10ms 40
```



## sctp-start-mtu-size

Configures the start maximum transmission unit (MTU) size (in bytes) for SCTP streams.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template) #
```

---

**Syntax Description**

**sctp-start-mtu-size** *bytes*  
**default sctp-start-mtu-size**

**default**

Returns the command to its default setting of 1500 bytes.

**bytes**

Specifies the start MTU size (in bytes) for SCTP streams as an integer from 508 through 65535. Default: 1500

---

**Usage Guidelines**

Use this command to configure the start MTU size, in bytes, for SCTP streams.

**Example**

The following command configures the start MTU size for SCTP streams to *3000*:

```
sctp-start-mtu-size 3000
```

# timeout

Configures timeouts for SCTP data chunk bundle transmissions and/or SCTP heartbeat request responses.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; SCTP Parameter Template Configuration

**configure** > **sctp-param-template** *template\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(sctp-param-template)#
```

---

**Syntax Description**

```
timeout { sctp-bundle [ units-10ms ] timer | sctp-heart-beat value }
[ default | no ] timeout { sctp-bundle | sctp-heart-beat }
```

**default**

Returns the command to its default setting of disabled for **sctp-bundle** and 30 seconds for **sctp-heart-beat**.

**no**

Removes the selected configuration.

**sctp-bundle [ units-10ms ] timer**

Specifies that SCTP data chunks are to be queued until this timer expires at which time the data chunks are bundled and committed for transmission.

*timer* is an integer from 1 through 65535, in 100ms increments (10 = 1000ms or 1 second).

[ **units-10ms** ]: Including this optional keyword specifies that the integer *timer* is to be calculated using 10ms increments (instead of 100ms increments) to allow for finer granularity.

Default: Disabled.

**sctp-heart-beat value**

Default: 30 seconds

Specifies the SCTP heartbeat timeout (in seconds) as an integer from 1 through 300. An SCTP heartbeat is sent to a peer to determine reachability. If an acknowledgement is not received before this timer runs out, heartbeat requests are no longer sent and the peer is considered unreachable.

---

**Usage Guidelines**

Use this command to configure timeouts for SCTP data chunk bundle transmissions and/or SCTP heartbeat request responses.

**Example**

The following command enables the SCTP data chunk bundle timeout value and configures it to 2 seconds:

```
timeout sctp-bundle 20
```

**timeout**



## Security Configuration Mode Commands

---

The Security configuration mode is a sub-mode of the Global Configuration mode. This sub-mode enables you to define or modify the connection with the Talos Intelligence content-filtering server and configure URL categorization parameters.

---

### Command Modes

Exec > Global Configuration > Security Configuration

**configure > security**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-security) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [category](#), on page 318
- [end](#), on page 319
- [exit](#), on page 320
- [server](#), on page 321

# category

Adds or removes a URL categorization server.



## Important

This is a license-controlled feature. For more information, contact your Cisco account or support representative.

## Product

All

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Security Configuration

**configure > security**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-security)#
```

## Syntax Description

[ **no** ] **category server** *server\_name*

**no**

Removes the specified URL categorization server.

***server\_name***

Specifies the name of the URL categorization server. *server\_name* must be an alpha and/or numeric string from 1 through 31 characters that is case sensitive.

## Usage Guidelines

Use this command to create or remove a URL categorization server from the Security configuration mode.

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.



# server

This command creates or specifies a Talos Security Intelligence (TSI) server entry and enters the TSI Server Configuration mode.



## Important

This is a license-controlled feature. For more information, contact your Cisco account or support representative.

## Product

All

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Security Configuration

**configure > security**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-security)#
```

## Syntax Description

**[ no ] server talos-intelligence** *server\_name*

**no**

Removes the specified Talos Security Intelligence server.

***server\_name***

Specifies the name of the Talos Security Intelligence server to create, configure, or remove. *server\_name* must be an alpha and/or numeric string from 1 through 31 characters that is case sensitive.

## Usage Guidelines

Use this command to create, configure, or remove a Talos Security Intelligence server from the Security configuration mode.

Entering this command results in the following prompt:

```
[local]host_name(config-server-tsi)#
```

The various parameters available for configuration of a TSI server entry are defined in the *TSI Server Configuration Mode Commands* chapter.





## Service Chain Configuration Mode Commands

The Service Chain configuration mode is a sub-mode of the Global Configuration mode. This sub-mode associates nsh-format to service-chain.

---

### Command Modes

Exec > Global Configuration > Service Chain Configuration

**configure > service-chain**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [end, on page 324](#)
- [exit, on page 325](#)
- [nsh-format, on page 326](#)

**end**

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Return to the Exec mode.

# exit

Exits the current configuration mode and returns to the global configuration mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>exit</b>
<b>Usage Guidelines</b>	Returns to the global configuration mode.

# nsh-format

This command associates nsh format with service-chain.

---

## Product

P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Service Chain Configuration

**configure > service-chain**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain)#
```

---

## Syntax Description

[ **no** ] **nsh-format** <nsh\_format\_name>

**no**

Disassociates nsh format with the service-chain configuration.

**nsh-format**

Associates nsh format with service chain.

**nsh\_format\_name**

Specifies the name of nsh-format. This is entered as an alphanumeric string of 1 through 63 characters.

---

## Usage Guidelines

Use this command to associate nsh-format with service-chain.

### Example

The following commands associates a nsh-format to service-chain:

```
nsh-format ns1
```

The following commands disassociates the nsh-format with service-chain:

```
no nsh-format
```



# Service Redundancy Protocol Configuration Mode Commands

---

The Service Redundancy Protocol Mode is used to configure properties for Interchassis Session Recovery (ICSR) services.

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure** > **context** *context\_name* > **service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp) #
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---



---

## Important

SRP commands must be identically configured on both the active and standby ICSR chassis.

---

- [advertise-routes-in-standby-state](#), on page 329
- [audit](#), on page 331
- [bfd-mon-ignore-dead-interval](#), on page 333
- [bind](#), on page 334
- [chassis-mode](#), on page 335
- [checkpoint session](#), on page 336
- [configuration-interval](#), on page 338
- [dead-interval](#), on page 339
- [delay-interval](#), on page 340
- [delta-route-modifier](#), on page 341
- [do show](#), on page 342
- [dscp-marking](#), on page 343
- [end](#), on page 345
- [exit](#), on page 346
- [guard-timer](#), on page 347

- [handle-interim-resource-msg](#), on page 349
- [hello-interval](#), on page 350
- [internal-switchover-retry-interval](#), on page 351
- [monitor authentication-probe](#), on page 352
- [monitor bfd](#) , on page 354
- [monitor bgp](#), on page 356
- [monitor diameter](#), on page 358
- [monitor hsrp](#), on page 360
- [num-internal-switchover-retry](#), on page 362
- [peer-ip-address](#), on page 363
- [priority](#), on page 364
- [retain-complete-sess-info](#), on page 365
- [route-modifier](#), on page 366
- [standby database-recovery](#), on page 367
- [switchover allow-all-data-traffic](#), on page 368
- [switchover allow-early-active-transition](#), on page 369
- [switchover allow-volte-data-traffic](#), on page 370
- [switchover control-outage-optimization](#), on page 371



# advertise-routes-in-standby-state

Enables advertising BGP routes from an ICSR chassis in standby state.

---

**Product**

All products that support ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

```
advertise-routes-in-standby-state [ hold-off-time hold-off-time ] [ reset-bfd-nbrs bfd-down-time ]
default advertise-routes-in-standby-state [ hold-off-time] [reset-bfd-nbrs]
no advertise-routes-in-standby-state [ hold-off-time] [reset-bfd-nbrs]
```

**default**

Sets the specified route advertisement option to its default value—:

- **hold-off-time** – 30 seconds
- **reset-bfd-nbrs** – ??? milliseconds

**no**

Disables the specified type of route advertisement.

**[ hold-off-time *hold-off-time* ]**

This option delays advertising the BGP routes until the timer expires. Specify *hold-off-time* in seconds as an integer from 1 to 300.

**[ reset-bfd-nbrs *bfd-down-time* ]**

After resetting BFD, this option keeps the BFD sessions down for the configured number of milliseconds to improve network convergence. Specify *bfd-down-time* as an integer from 50 to 120000.

---

**Usage Guidelines**

Use this command and its keywords to take advantage of faster network convergence accrued from deploying BGP Prefix Independent Convergence (PIC) in the Optical Transport Network Generation Next (OTNGN).

BGP PIC is intended to improve network convergence which will safely allow for setting aggressive ICSR failure detection timers.

**Example**

The following command enables route advertisement from a standby ICSR chassis after a 40-second delay and will suppress BFD sessions for 50 milliseconds following a BFD reset.

**advertise-routes-in-standby-state**

```
advertise-routes-in-standby-state hold-off-time 40 reset-bfd-nbrs 50
```

# audit

Sets the start time and periodicity for ICSR Service Redundancy Protocol (SRP) audits. This command can also be used to enter a schedule for running the audit.

**Product** All products supporting ICSR

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

## Syntax Description

**[no] audit cron [ daily hour *hour\_number* minute *minute\_number* ] [ day-of-month *day\_number* ] [ month *month\_number* ] [ week-of-day *day\_name* ]**

**[no] audit daily-start-time *hour minute***

**[no] audit periodicity *minutes***

**default audit periodicity**

### default

Resets the specified parameter to its default setting of 60.

### no

Disables the specified function.

**audit cron [ daily hour *hour\_number* minute *minute\_number* ][ day-of-month *day\_number* ][ month *month\_number* ][ week-of-day *day\_name* ]**

Configures a cron job (time-based job scheduler) for running the audit. Supported scheduling variables include:

- **daily hour *hour\_number* minute *minute\_number*** – configures the hour and minute of the day when the job will run. Specify *hour\_number* as an integer from 0 to 23 and *minute\_number* as an integer from 0 to 59.
- **day-of-month *day\_number*** – configures the day of the month when the job will run. Specify *day\_number* as an integer from 1 to 31.
- **month *month\_number*** – configures the month of the year when the job will run. Specify *month\_number* as an integer from 1 to 12.
- **week-of-day *day\_name*** – configures the week day on which the job will run. Specify *day\_name* as one of the following names: friday, monday, saturday, sunday, thursday, tuesday, or wednesday.

### daily-start-time *hour minute*

Specifies the daily start time. *hour* is a two-digit integer from 00 through 23. *minute* is a two-digit interval from 00 through 59. For example, a start time of 06 00 indicates that the audit will begin at 6:00 AM.

**periodicity *minutes***

Specifies the interval in minutes for generating SRP audit statistics as an integer from 60 through 43200. For example, a periodicity of 90 indicates that SRP audit statistics will be generated every 90 minutes beginning at the specified start time. Default = 60.

**Usage Guidelines**

Use this command and its keywords to specify the start time and periodicity for generating ICSR SRP audit statistics.

You can also schedule audits to be run based on time-of-day, day-of-week, day-of-month and month-of-year.

This audit ensures that two ICSR peers are in synch and identifies any discrepancies prior to scheduled or unscheduled switchover events.

**Example**

The following command sequence specifies a start time of midnight and a periodicity of every two hours for generating SRP statistics:

```
audit daily-start-time 06 00
audit periodicity 90
```

The following command schedules the audit to run at midnight every Sunday.

```
cron daily hour 0 minute 0 week-of-day sunday
```

# bfd-mon-ignore-dead-interval

Causes the standby ICSR chassis to ignore the dead interval and remain in the standby state until all the BFD chassis-to-chassis monitors fail.

---

**Product** All products that support ICSR.

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description** **bfd-mon-ignore-dead-interval**  
**default bfd-mon-ignore-dead-interval**

## default

Disables this feature.

---

**Usage Guidelines** Enable this feature in association with BFD chassis-to-chassis monitoring to support more aggressive ICSR failure detection times.

For additional information, see the descriptions of the **dead-interval** and **monitor bfd** commands.

## Example

The following command enables this feature:

```
bfd-mon-ignore-dead-interval
```

# bind

Binds the service to the IP address of the local chassis.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

**bind address** { *ipv4\_address* | *ipv6\_address* }  
**no bind address**

**no**

Removes the IP bind address.

***ipv4\_address* | *ipv6\_address***

Specifies the system IP address using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.




---

## Important

Both peers must be using the same address family (IPv4 or IPv6) or the Service Redundancy Protocol (SRP) connection will not be established.

---



---

## Usage Guidelines

Defines the IP address of the local chassis defined as part of the ICSR configuration.

### Example

The following example binds the service to the IP address *10.1.1.1*:

```
bind address 10.1.1.1
```

# chassis-mode

Defines the chassis's operational mode - primary or backup - for ICSR.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

```
chassis-mode { backup | primary }  
default chassis-mode
```

**default**

Resets the chassis mode to the default setting of backup.

**backup**

(Default) Configures the system as the backup chassis operating in standby state.

**primary**

Configures the system as the primary chassis operating in active state.

---

**Usage Guidelines**

Sets the chassis mode (primary or backup) for the system within the framework of ICSR.

**Example**

The following example configures the system as the primary chassis operating in active state

```
chassis-mode primary
```

# checkpoint session

Configures checkpointing parameters between ICSR active and standby chassis.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

```
checkpoint session compression { lz4 | zlib }
checkpoint session duration { ims-session | non-ims-session } seconds
checkpoint session nack { macro | micro } [ max-response number ]
checkpoint session periodic-interval minutes
default checkpoint session { compression | duration { ims-session |
non-ims-session } | periodic-interval }
no checkpoint session { compression | duration { ims-session |
non-ims-session } | periodic-interval }
```

**default**

Resets the following checkpoint session parameters to their default values:

- compression = zlib
- duration = 60 seconds
- periodic-interval = 48 minutes

**no**

Disables **compression**, **duration**, **nack**, and **periodic-interval** features.

**compression { lz4 | zlib }**

Specifies whether the LZ4 or zlib compression algorithm will be used to compress SRP payload messages.

LZ4 compression is effective only if both chassis are configured with LZ4. If any one chassis has zlib (default) configured, the compression algorithm reverts to zlib. The algorithm is negotiated only during initial socket establishment. Once agreed no more negotiation takes place until the TCP socket connection is reset.




---

**Important**

A change in the configured compression algorithm resets the TCP Link.

---



**duration { ims-session | non-ims-session } seconds**

Specifies whether the checkpoint duration is being set for IMS (IP Multimedia Subsystem) or non-IMS sessions. The duration is the amount of time that a call must be active before it is check pointed, and is expressed as an integer from 0 through 65535 (Default = 60).

**nack { macro | micro } [ max-response number ]**

Enables a NACK feature for checkpoints. When this feature is enabled, the standby chassis sends a NACK in response to the receipt of a micro-checkpoint (MC) that fails to be successfully applied. The standby chassis will send more NACKs (configurable, default = 3) within a 10-minute window if an FC is not received. NACKs will continue to be sent within the 10-minute reset window until an FC is received and applied, or the configured number of maximum-responses is reached.

**max-response** is the total number NACKs that can be sent within the 10-minute window in response to a failed MC or FC expressed as an integer from 1 through 65535 (Default = 3).




---

**Note** The time interval window of 10 minutes is not configurable.

---

**periodic-interval minutes**

Configures the minimum periodic checkpoint duration in multiples of 12 minutes for sending macro-checkpoints (FCs) from the Active to the Standby chassis. The interval is specified as an integer divisible by 12 in the range from 24 through 1440 (Default = 48 minutes). The interval range for sending full checkpoints is 24 minutes to 24 hours (1140 minutes).

**Usage Guidelines**

Sets the type of compression algorithm to be used for SRP payload messages.

Sets the amount of time the chassis waits before check pointing an existing call session. Checkpoints can be separately set for IMS and/or non-IMS sessions.

Enable the NACK feature for handling checkpointing messaging on the Standby chassis.

Configures the interval between the sending of macro-checkpoints (full checkpoints) between the active and standby chassis.

**Important**


---

The **compression**, **nack** and **periodic-interval** keywords will only appear if a special ICSR optimization feature license has been purchased and installed. Contact your Cisco account representative for assistance.

---

For additional information on ICSR checkpointing, see the *System Administration Guide*.

**Example**

The following example configures sets the checkpoint session duration for an IMS session to 6500 seconds:

```
checkpoint session duration ims-session 6500
```

The following command resets the periodic interval for sending full checkpoints to 36 minutes:

```
checkpoint session periodic-interval 36
```

# configuration-interval

Defines the configuration validation interval.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

**configuration-interval *interval***  
**default configuration-interval**

### **default**

Resets the configuration interval to the default setting of 3600 seconds.

### ***interval***

Specifies the amount of time (number of seconds) between one configuration validation and the next configuration validation. *interval* must be an integer from 1 through 65535. Default = 3600.

---

## Usage Guidelines

This configures the interval between configuration validations of the primary and backup chassis.

### **Example**

The following example sets the configuration interval to 34 seconds:

```
configuration-interval 34
```

# dead-interval

Defines the timeout interval before a peer is determined to be down.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

**dead-interval *interval***  
**default dead-interval**

**default**

Resets the dead interval to the default setting of 30 seconds.

***interval***

Specifies the amount of time (in seconds) for the dead interval. *interval* must be an integer from 1 through 65535. Default = 30.

---

**Usage Guidelines**

This command specifies the amount of time that one chassis waits to receive a communication from a peer before the listening chassis determines that the peer chassis is down.

**Example**

The following example sets the dead interval to 65 seconds:

```
dead-interval 65
```

# delay-interval

Configures the delay time for starting the dead timer after configuration files are loaded.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp) #
```

---

**Syntax Description**

**delay-interval** *interval*  
**default delay-interval**

**default**

Sets or restores the default value assigned for the specified parameter.

**interval**

Specifies the amount of time (in seconds) for the delay interval. *interval* must be an integer from 1 through 65535.

---

**Usage Guidelines**

This configures interval for starting the dead timer after configuration files are loaded.

**Example**

The following example sets the delay interval to 65 seconds after the configuration files are loaded:

```
delay interval 65
```

# delta-route-modifier

Specifies the delta used to compute the route modifier difference between the active and standby chassis. This delta is applied only in the standby state. *For Release 15.0 or higher*, it is used in both states.

---

**Product** All products supporting ICSR

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description** **delta-route-modifier** *value*  
**default delta-route-modifier**

## **default**

Sets or restores the default value assigned for the specified parameter. Default = 1.

## **value**

Specifies the value to be used when computing the route-modifier. *value* must be an integer from 1 through 15 (for 21.7 and later releases), or 1 through 7 (for releases prior to 21.7). Default: 1.

---

**Usage Guidelines** The delta-route-modifier is used to compute the route modifier difference between active and standby chassis.

## **Example**

The following example sets the delta for the route modifier to 2:

```
delta-route-modifier 2
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# dscp-marking

Sets DSCP marking values for SRP control and checkpoint (session maintenance) messages.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

```
dscp-marking { control | session } dscp_value  
default dscp-marking { control | session }
```

**default**

Sets the DSCP value to its default: **be** (Best Effort Per-Hop-Behaviour).

**{ control | session }**

Specifies the SRP message type for which a DSCP value is being set.

- **control** – SRP control messages [originate from vpnmgr]
- **session** – checkpoint messages (session maintenance) [originate from sessmgr]

***dscp\_value***

Specifies the DSCP value to be used:

- **af11** – Assured Forwarding Class 1 low drop PHB (Per Hop Behavior)
- **af12** – Assured Forwarding Class 1 medium drop PHB
- **af13** – Assured Forwarding Class 1 high drop PHB
- **af21** – Assured Forwarding Class 2 low drop PHB
- **af22** – Assured Forwarding Class 2 medium drop PHB
- **af23** – Assured Forwarding Class 2 high drop PHB
- **af31** – Assured Forwarding Class 3 low drop PHB
- **af32** – Assured Forwarding Class 3 medium drop PHB
- **af33** – Assured Forwarding Class 3 high drop PHB
- **af41** – Assured Forwarding Class 4 low drop PHB
- **af42** – Assured Forwarding Class 4 medium drop PHB
- **af43** – Assured Forwarding Class 4 high drop PHB
- **be** – Best effort Per-Hop-Behaviour (default)
- **cs1** – Class selector 1 PHB
- **cs2** – Class selector 2 PHB
- **cs3** – Class selector 3 PHB
- **cs4** – Class selector 4 PHB

- **cs5** – Class selector 5 PHB
- **cs6** – Class selector 6 PHB
- **cs7** – Class selector 7 PHB
- **ef** – Expedited Forwarding PHB, for low latency traffic



---

**Important** If *dscp\_value* is set incorrectly, packet drops may occur in intermediate devices.

---

---

**Usage Guidelines** Use this command to enable DSCP marking of SRP and checkpoint messages in ICSR environments.

### Example

The following command sequence sets DSCP marking of control messages to Expedited Forwarding:

```
dscp-marking control ef
```



# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# guard-timer

Configures the redundancy-guard-period and monitor-damping-period for SRP service monitoring.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

```
guard-timer { aaa-switchover-timers { damping-period seconds | guard-period
seconds } | diameter-switchover-timers { damping-period seconds | guard-period
seconds } | srp-redundancy-timers { aaa { damping-period seconds |
guard-period seconds } | bgp { damping-period seconds | guard-period seconds }
| diam { damping-period seconds | guard-period seconds } }
default guard-timer aaa-switchover-timers { damping-period | guard-period
}
default guard-timer diameter-switchover-timers { damping-period |
guard-period }
default guard-timer srp-redundancy-timers { aaa { damping-period |
guard-period } | bgp { damping-period | guard-period } | diam {
damping-period | guard-period } }
```

**default**

Sets the specified guard timer to its default value:

- **damping-period** = 60 seconds
- **guard-period** = 60 seconds

**aaa-switchover-timers**

Sets timers that prevent back-to-back ICSR switchovers due to an AAA failure (post ICSR switchover) while the network is still converging.

**diameter-switchover-timers**

Sets timers that prevent a back-to-back ICSR switchover due to a Diameter failure (post ICSR switchover) while the network is still converging.

**srp-redundancy-timers**

Sets timers that prevent an ICSR switchover while the system is recovering from a local card-reboot/critical-task-restart failure.

**damping-period *seconds***

Configures a delay time to trigger an ICSR switchover due to a monitoring failure within the guard-period. Specify *seconds* as an integer from 0 to 300.

**guard-period *seconds***

Configures the local-failure-recovery network-convergence timer. Specify *seconds* as an integer from 0 to 300.

**{ *aaa* | *bgp* | *diam* }**

Specifies the type of SRP redundancy timer:

- **aaa** – local failure followed by AAA monitoring failure
- **bgp** – local failure followed by BGP monitoring failure
- **diam** – local failure followed by Diameter monitoring failure

**Usage Guidelines**

Use these guard timers to ensure that local failures, such as card reboots and task restarts, do not result in ICSR events which can be disruptive.

**Example**

The following command sets an SRP redundancy AAA guard period of 45 seconds:

```
guard-timer srp-redundancy-timers aaa guard-period 45
```

# handle-interim-resource-msg

Enables the proper handling of version 16.1 SRP Interim Resource messages during an ICSR upgrade from prior releases.

---

**Product** All products supporting ICSR

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description** **handle-interim-resource-msg version-16.1**  
**no handle-interim-resource-msg version-16.1**

**no**

Disables this feature after it has been enabled. By default this feature is disabled to preserve compatibility with release versions prior to 16.1.

---

**Usage Guidelines** Use this feature to properly handle Interim Resource messages when upgrading to StarOS 16.1. If you do not enable this feature, an ICSR configuration may experience PCRF binding problems (5002 error code message) when performing an ICSR upgrade from previous StarOS versions.

## Example

The following command enables this feature:

```
handle-interim-resource-msg version-16.1
```

# hello-interval

Defines the lapse time between sending the hello message.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

**hello-interval** *interval*  
**default hello-interval**

**default**

Resets the hello interval to the default setting of 10 seconds.

**interval**

Specifies the lapse time (in seconds) between sending the hello message. *interval* must be an integer from 1 through 65535. Default = 10.

---

**Usage Guidelines**

This command configures the hello interval - the amount of time that lapses between the sending of each hello message. Each chassis sends the other chassis a hello message at the expiration of every hello interval.

**Example**

The following example sets the hello interval to 35 seconds:

```
hello-interval 35
```

# internal-switchover-retry-interval

Defines the interval between internal switchover retries.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

**internal-switchover-retry-interval *interval***  
**default internal-switchover-retry-interval**

**default**

Resets the internal switchover retry interval to the default setting of 60 seconds.

***interval***

Specifies the amount of time (in seconds) between internal switchover retries. *interval* must be an integer from 10 through 120. Default = 60.

---

**Usage Guidelines**

This configures the interval between internal switchover retries. The system only initiates internal switchovers if Service Redundancy Protocol (SRP) monitoring is configured.



---

**Important**

See the **monitor authentication-probe**, **monitor bgp**, or **monitor diameter** commands for more information on associated SRP monitoring.

---

**Example**

The following example sets the internal switchover retry interval to 34 seconds:

```
internal-switchover-retry-interval 34
```

# monitor authentication-probe

Enables SRP monitoring of the connection between the specified AAA server and the primary chassis.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure** > **context** *context\_name* > **service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

```
[ no ] monitor authentication-probe context context_name { ipv4_address |
ipv6_address } [ group group_id ] [ port port_number ]
```

### **no**

Turns off the monitoring.

### **context context\_name**

Identifies the context being used.

*context\_name* must be an existing context expressed as an alphanumeric string of 1 through 79 characters.

### **ipv4\_address | ipv6\_address**

Defines the IP address of the AAA server to be monitored in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

### **group group\_id**

Defines a Service Redundancy Protocol (SRP) peer group as an integer from 0 through 9. Default = 0.

In an Interchassis Session Recovery (ICSR) configuration, failover would occur if all peers within a group fail.

### **port port\_number**

Identifies a specific AAA server port for the authentication probe. *port\_number* must be an integer from 1 through 65535.

---

## Usage Guidelines

This command initiates monitoring of the connection between the primary chassis and the specified AAA server through the use of authentication probe packets. If the connection drops, the standby chassis becomes active.



**Example**

The following example initiates the connection monitoring between the primary chassis and AAA server *10.2.3.4* at port *1025*:

```
monitor authentication-probe context test1 10.2.3.4 port 1025
```

# monitor bfd

Enables SRP monitoring of the connection between the specified Bidirectional Forwarding Detection (BFD) neighbor and the primary chassis.

**Product** All products supporting ICSR

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

**Syntax Description** [ **no** ] **monitor bfd context** *context\_name* { *ipv4\_address* | *ipv6\_address* } { **chassis-to-chassis** | **chassis-to-router** }

**no**

Disables monitoring.

**context *context\_name***

Identifies the context being used. *context\_name* must be an existing context expressed as an alphanumeric string of 1 through 79 characters.

***ipv4\_address* | *ipv6\_address***

Defines the IP address of the BFD neighbor to be monitored, entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

**chassis-to-chassis | chassis-to-router**

**chassis-to-chassis:** BFD runs between primary and backup chassis on non-SRP links.

**chassis-to-router:** BFD runs between chassis and router.

## Usage Guidelines

This command initiates monitoring of the connection between the primary chassis and the specified BFD neighbor in the specified context. If the connection drops, the standby chassis becomes active.



### Important

BFD monitoring must run between chassis-to-chassis or chassis-to-router.

For additional information, see the description of the **bfd-mon-ignore-dead-interval** command.

## Example

The following example initiates the chassis-to-chassis connection monitoring between the primary chassis and BFD neighbor *12.2.1.54*:

```
monitor bfd context test 12.2.1.54 chassis-to-chassis
```

# monitor bgp

Enables SRP monitoring of the connection between the specified Border Gateway Protocol (BGP) peer and the primary chassis.

**Product** All products supporting ICSR

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

**Syntax Description** [ **no** ] **monitor bgp context** *context\_name* { *ipv4\_address* | *ipv6\_address* } [ **group** *group\_id* [ **vrf** *vrf\_name* ]

**no**

Disables monitoring.

**context *context\_name***

Identifies the context being used. *context\_name* must be an existing context expressed as an alphanumeric string of 1 through 79 characters.

***ipv4\_address* | *ipv6\_address***

Specifies the IP address of the BGP peer to be monitored in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

**group *group\_id***

Defines a Service Redundancy Protocol (SRP) peer group as an integer from 0 through 9. Default = 0.

In an Interchassis Session Recovery (ICSR) configuration, failover would occur if all peers within a group fail (instead of all BGP peers in a context). This option is useful in deployments in which a combination of IPv4 and IPv6 peers are spread across multiple paired VLANs and IPv4 or IPv6 connectivity is lost by all members of a peer group.

**vrf *vrf\_name***

Defines the VPN Routing/Forwarding instance as an alphanumeric string of 1 through 63 characters.

**Usage Guidelines** This command initiates monitoring of the connection between the primary chassis and the specified BGP peer in the specified context. If the connection drops, the standby chassis becomes active.

**Example**

The following example initiates the connection monitoring between the primary chassis and BGP peer *125.2.1.56*:

```
monitor bgp context test 125.2.1.56
```

# monitor diameter

Enables SRP monitoring of the connection between the specified Diameter server and the primary chassis.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

```
[ no ] monitor diameter context context_name endpoint endpoint_name [ fqdn
fqdn | group group_id | peer { ipv4_address | ipv6_address } ] [ port port_number
]
```

### **no**

Turns off the monitoring.

### **context *context\_name***

Identifies the context being used. *context\_name* must be an existing context expressed as an alphanumeric string of 1 through 79 characters.

### **endpoint *endpoint\_name***

Identifies the endpoint being used. *endpoint\_name* must be for the Diameter server expressed as an alphanumeric string of 1 through 63 characters.

### **fqdn *fqdn***

Identifies a Fully Qualified Domain Name (FQDN). *fqdn* must be for the Diameter server expressed an alphanumeric string of 1 through 127 characters.

### **group *group\_id***

Defines a Service Redundancy Protocol (SRP) peer group as an integer from 0 through 9. Default = 0.

In an Interchassis Session Recovery (ICSR) configuration, failover would occur if all peers within the specified group fail.

### **peer { *ipv4\_address* | *ipv6\_address* }**

Defines the IP address of the Diameter server to be monitored, entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

**port *port\_number***

Identifies a specific port to monitor. *port\_number* must be the port for the Diameter server and an integer from 1 through 65535.

---

**Usage Guidelines**

This command initiates monitoring of the connection between the primary chassis and the specified Diameter server in the specified context. If the connection drops, the standby chassis becomes active.



---

**Important**

Endpoint name, FQDN, IP address, and port must all match the Diameter protocol configured values for the peer state to be updated.

---

**Example**

The following example initiates the connection monitoring between the primary chassis and the Diameter server on context *test1* and endpoint *end2*:

```
monitor diameter context test1 10.6.7.8 endpoint end2
```

# monitor hsrp

Enables monitoring of the Hot Standby Router Protocol (HSRP) connection between the ASR 9000 Route Switch Processor (RSP) and the StarOS Security Gateway (SecGW) running in a virtual machine on the Virtualized Services Module. HSRP is employed in high availability (HA) SecGW configurations. (ASR 9000 VSM only)

---

**Product**

SecGW

---

**Privilege**

System Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

**monitor hsrp interface *if\_name* afi-type *type* hsrp-group *hsrp\_group***  
**no monitor hsrp**

---

**no**

Turns off the monitoring.

---

**interface *if\_name***

Specifies the name of an existing RSP interface as an alphanumeric string of 1 through 63 characters.

---

**afi-type *type***

Specifies the RSP name of an existing Address Family Type (IPv4 or IPv6) as an alphanumeric string of 4 through 15 characters.

---

**hsrp-group *hsrp\_group***

Specifies the RSP name of an existing HSRP Group ID as an integer from 0 through 4095.

---

**Usage Guidelines**

Use this command to enable monitoring of the HSRP connection between the ASR 9000 RSP and the SecGW running in a virtual machine on the VSM.

This command must be associated with the Service Redundancy Protocol (SRP) context.

A maximum of one HSRP monitor is supported per VPC-VSM instance.




---

**Important**

The above parameters must match those of the HSRP configuration in the ASR 9000 RSP.

---



**Example**

The following command enables monitoring of Cisco HSRP on an ASR 9000 VSM running SecGW in a virtual machine:

```
monitor hsrp interface GigabitEthernet0/1/0/3 afi-type ipv4 hsrp-group 2
```

# num-internal-switchover-retry

Defines the number of times an internal switchover would be retried.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure** > **context** *context\_name* > **service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

**num-internal-switchover-retry** *retries*  
**default num-internal-switchover-retry**

### default

Resets the configuration interval to the default setting of 3 retries.

### retries

The number of times an internal switchover would be retried in case of standby chassis. *retries* must be an integer from 1 through 10.

Default: 3

---

## Usage Guidelines

This configures the number of times an internal switchover would be retried in case of standby chassis failure to respond or become active.

### Example

The following example sets the retry number to 5:

```
num-internal-switchover-retry 5
```

# peer-ip-address

Specifies the IP address for the peer chassis.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

**peer-ip-address { *ipv4\_address* | *ipv6\_address* }**  
**no peer-ip-address**

**no**

Removes the peer IP address of the backup chassis.

***ipv4\_address* | *ipv6\_address***

Specifies the IP address of the backup chassis, entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.




---

## Important

Both peers must be using the same address family (IPv4 or IPv6) or the Service Redundancy Protocol (SRP) connection will not be established.

---

## Usage Guidelines

This command is used to identify the peer chassis in the ICSR configuration. From the primary's perspective, the peer is the backup and from the backup's perspective, the peer is the primary.

## Example

The following example specifies *10.2.3.4* as a backup peer system to the primary system:

```
peer-ip-address 10.2.3.4
```

# priority

Sets the initial ICSR priority of each peer chassis.



## Important

**priority** takes affect only during simultaneous initializing of all chassis in an ICSR configuration, and only if a misconfiguration has both chassis in the same mode (both Primary or both Backup).

## Product

All products supporting ICSR

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure** > **context** *context\_name* > **service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

## Syntax Description

**priority** *priority\_value*  
**default** **priority**

### default

Resets the priority to the default setting of 125.

### *priority\_value*

Specifies the priority for the chassis. *priority\_value* must be an integer from 1 through 255, where 1 is the highest priority. Default = 125.

## Usage Guidelines

This command determines which chassis transitions to the Active state when all chassis have the same mode configuration. **priority** acts as a tie breaker for the state determination only when all chassis initialize simultaneously. The chassis with the higher priority (lower number) becomes Active, while the chassis with the lower priority (higher number) becomes Standby.

Once chassis become operational (after initialization), if there is an event requiring a chassis change of state, then each chassis returns to its previous state (Active or Standby) after both chassis recover.

## Example

The following example sets the priority value to 5:

```
priority 5
```

# retain-complete-sess-info

The new CLI command is added to retain complete session information locally when transitioning to the Standby state during a switchover.

---

**Product** P-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration  
**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description** **retain-complete-sess-info**  
**[no] retain-complete-sess-info**

**no**

Disables the command.

---

**Usage Guidelines** The new CLI command is added to retain complete session information locally when transitioning to the Standby state during a switchover.

## Example

The following command retains complete session information when transitioning from Active to Standby state during a switchover:

```
retain-complete-sess-info
```

# route-modifier

Sets the route modifier for the peer chassis.

---

## Product

All products supporting ICSR

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

## Syntax Description

**route-modifier threshold *threshold\_value***  
**default route-modifier**

### default

Resets the route modifier to the default setting of 16.

### *threshold\_value*

Specifies the value that causes the route-modifier counter to be reset to the initial value. *threshold\_value* must be an integer from 2 through 32. Default = 16.

---

## Usage Guidelines

This command is used to determine when the route modifier should be reset to its initial value to avoid rollover.

### Example

The following example sets the route modifier threshold to 10:

```
route-modifier threshold 10
```

# standby database-recovery

Configures the preferred method of SRP database synchronization on the Standby ICSR chassis.

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

```
standby database-recovery { aggressive | normal }  
default standby database-recovery
```

**default**

Restore SRP database recovery method to normal

**{ aggressive | normal }**

The **normal** (default) method for synchronizing the SRP database requires tens of seconds of delay whenever the TCP connection between the Active and Standby session managers is established. Once the TCP connection is established, heart beat messages are exchanged between both ICSR chassis every 3 seconds. The standby chassis waits for 7 heart beat messages from the active chassis before it is ready to accept data. This causes the significant delay in session manager database synchronization on the standby chassis.

The **aggressive** method for synchronizing the session manager database reduces recovery time in the following scenarios:

- Standby Session Manager crash
- Packet processing card crash on Standby chassis
- Standby chassis crash/reboot
- Temporary loss and recovery of SRP connection

The **aggressive** method reduces the number of heartbeat messages and amount of housekeeping information exchanged between ICSR chassis.

---

**Usage Guidelines**

Use this command to enable a more aggressive method for synchronizing the session manager database on a Standby ICSR chassis.

**Example**

The following command enables the aggressive method of session manager database recovery on a standby ICSR chassis:

```
standby database-recovery aggressive
```

# switchover allow-all-data-traffic

Allows all data traffic (VoLTE and non-VoLTE) during switchover transition. This command overwrites the **switchover allow-volte-data-traffic** command if enabled on a P-GW.



## Important

A special ICSR license is required to run this command. Contact your Cisco account representative for additional information.

## Product

P-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp) #
```

## Syntax Description

**switchover allow-all-data-traffic**  
**no switchover allow-all-data-traffic**

**no**

Disables this feature. The default behavior is to not allow data traffic during switchover.

## Usage Guidelines

Use this command to allow all data traffic (VoLTE and non-VoLTE) during an ICSR switchover. This feature reduces data traffic outage during the switchover.



## Important

This CLI command must be run on both the active and standby chassis to enable this feature.

All data traffic is allowed on the active chassis during flushing and internal auditing. The billing information is reconciled in the background once the flush is complete.

## Example

The following command enables this feature:

```
switchover allow-all-data-traffic
```



# switchover allow-early-active-transition

Enables or disables early transition to active state during an ICSR switchover. By default this feature is disabled.

**Important**

A special ICSR license is required to run this command. Contact your Cisco account representative for additional information.

**Important**

You must enable the **switchover allow-all-data-traffic** or **allow-volte-data-traffic** (without **maintain accounting**) command on both chassis prior to enabling this command.

**Product**

All products supporting ICSR

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

**Syntax Description**

**switchover allow-early-active-transition**  
**no switchover allow-early-active-transition**

**no**

Disables early transition following an ICSR switchover.

**Usage Guidelines**

Use this command in conjunction with the **switchover allow-all-data-traffic** or **allow-volte-data-traffic** (without **maintain accounting**) command to further reduce data outage during a planned switchover. The outage window is the amount time between initiating an ICSR switchover and when the newly active chassis starts processing data.

**Example**

The following command enables this feature:

```
switchover allow-early-active-transition
```

# switchover allow-volte-data-traffic

Allows VoLTE data traffic during ICSR switchover transition.



## Important

A special ICSR license is required to run this command. Contact your Cisco account representative for additional information.

## Product

P-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure** > **context** *context\_name* > **service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

## Syntax Description

**switchover allow-volte-data-traffic [ maintain-accounting ]**

### [ maintain-accounting ]

When enabled this option maintains accounting accuracy for VoLTE calls. VoLTE data is allowed on the active chassis after VoLTE accounting statistics are flushed.

## Usage Guidelines

Use this command to allow VoLTE data traffic during ICSR switchover transition. VoLTE data traffic is allowed on the active chassis during flushing and internal auditing. There may be some billing inaccuracy. Non-VoLTE data traffic is allowed after flushing and the internal audit are completed.

This feature is superseded when the **switchover allow-all-data-traffic** command is enabled.

## Example

The following command enables this feature:

```
switchover allow-volte-data-traffic maintain-accounting
```

# switchover control-outage-optimization

Optimizes restoration of control traffic (call-setup, modification, deletion) following an ICSR switchover.



---

**Important**

A special ICSR license is required to run this command. Contact your Cisco account representative for additional information.

---

---

**Product**

All products supporting ICSR

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Service Redundancy Protocol Configuration

**configure > context *context\_name* > service-redundancy-protocol**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-srp)#
```

---

**Syntax Description**

**switchover control-outage-optimization**  
**no switchover control-outage-optimization**

**no**

Disables optimization for restoring control traffic following an ICSR switchover.

---

**Usage Guidelines**

Use this command to optimize restoration of control traffic following an ICSR switchover.

**Example**

The following command enables this feature:

```
switchover control-outage-optimization
```

switchover control-outage-optimization



# Session Event Module Configuration Mode Commands

---

## Command Modes

The Session Event Module Configuration Mode is used to configure how subscriber-specific event data is handled on the S-GW. As users attach, detach, and move through the network, they trigger signaling events that need to be recorded. To provide a per-subscriber level of reporting, the S-GW sends a stream of user event data to an event reporting server over SFTP.

Exec > Global Configuration > Context Configuration > Session Event Module Configuration

**configure** > **context** *context\_name* > **session-event-module**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-event) #
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show, on page 374](#)
- [end, on page 375](#)
- [event, on page 376](#)
- [exit, on page 379](#)
- [file, on page 380](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# event

Sets the method and destination for transferring event files.

---

## Product

P-GW  
SAEGW  
S-GW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Session Event Module Configuration

**configure** > **context** *context\_name* > **session-event-module**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-event)#
```

---

## Syntax Description

```
event { purge { storage-limit bytes | time-limit seconds } | push-interval
value | push-trigger space-usage-percent trigger_percentage |
remove-file-after-transfer | transfer-mode { pull [ module-only ] | push
  primary { encrypted-url encrypted_url | url url } [ max-files files ] [
module-only ] [ secondary { encrypted-secondary-url url | secondary-url
url } ] [ via local-context ] } | use-harddisk }
default event [ purge | push-interval | push-trigger space-usage-percent
| remove-file-after-transfer | transfer-mode | use-harddisk ]
no event [ purge | remove-file-after-transfer | use-harddisk ]
```

### default

Configures the default setting for the specified keyword(s):

- **purge**: Not enabled.
- **push-interval**: 60 seconds
- **push-trigger**: 80 percent
- **remove-file-after-transfer**: Disabled
- **transfer mode**: Push
- **use-harddisk**: Disabled

### no

Disables the configured event file storage and processing in this mode:

- **purge**: Disables the deleting of record files on the hard disk based on a storage limit or a time limit.
- **remove-file-after-transfer**: Retains a copy of the file even after it has been pushed or pulled to another server.
- **use-harddisk**: Disables data storage on the system's hard disk.



**purge { storage-limit *bytes* | time-limit *seconds* }**

Configures parameters for deleting event records from the hard drive. This command is not enabled by default.

**storage-limit *bytes***: Specifies that event records are to be deleted from the hard drive upon reaching a storage limit defined in bytes.

*bytes* must be an integer value from 10485760 to 146800640.

**time-limit *seconds***: Specifies that event records are to be deleted from the hard drive upon reaching a time limit defined in seconds.

*seconds* must be an integer value from 600 to 2592000.

**push-interval *value***

Default: 60

Specifies the transfer interval (in seconds) when event files will be pushed to an external file server.

*value* must be an integer from 30 through 3600.

**push-trigger space-usage-percent *trigger\_percentage***

Default: 80

Specifies the disk space utilization percentage threshold at which an automatic push is triggered and files are transferred to the external server.

*trigger\_percentage* must be an integer from 10 through 80.

**remove-file-after-transfer**

Default: Disabled

Specifies that the system must delete event files after they have been transferred to the external file server.

**transfer-mode { pull [ module-only ] | push primary { encrypted-url *encrypted\_url* | url *url* } [ max-files *files* ] [ module-only ] [ secondary { encrypted-secondary-url *url* | secondary-url *url* } ] [ via local-context ] }**

Specifies the transfer mode to be used when transferring event files to an external file server.

- **pull**: Specifies that the destination server will pull the event files.
- **push**: Specifies that the system will push event files to the destination server. This is the default mode.
- **primary encrypted-url *encrypted\_url***: Specifies the primary URL location to which the system pushes the files in encrypted format.  
*encrypted\_url* must be an alphanumeric string of 1 through 8192 characters.
- **primary url *url***: Specifies the primary URL location to which the system pushes the event files. *url* must be an alphanumeric string of 1 through 1024 characters in the format: *//user:password@host:[port]/direct*.
- **max-files *number***: Specifies the maximum number of files that can be transferred per push.  
*number* must be an integer from 4 to 4000.
- **module-only**: Specifies that the transfer of event records is to be applied only to the module type for which the configuration was originally created. If this option is not enabled, the transfer will occur for all record types.

- **secondary encrypted-secondary-url *url***: Specifies the secondary URL location to which the system pushes the files in encrypted format.  
*url* must be an alphanumeric string of 1 through 8192 characters.
- **secondary-url *url***: Specifies the secondary URL location to which the system pushes the event files.  
*url* must be an alphanumeric string of 1 through 1024 characters in the format:  
*//user:password@host:[port]/direct*
- **via local-context**: Specifies that the local context, and, subsequently, the SPIO management ports, will be used to pull or push event files from/to the event server.

### use-harddisk

Default: Disabled

Specifies that the hard disk drive on the SMC is to be used to store P-GW or S-GW event records.

### Usage Guidelines

Use this command to configure how the P-GW or S-GW event records are moved and stored. By default, records are stored in the PSC RAM where the CDRMOD instance is running.

The **event use-harddisk** command can be run only in a context where CDRMOD is running. Configuring in any other context will result in failure with the message "Failure: Please Check if CDRMOD is running in this context or not."

If push transfer mode is configured, the server URL to which the event files will be transferred must be specified.

When changing the transfer-mode from pull to push, disable the pull setting before changing the transfer mode to push. The push to server URL must be accessible from the local context. Also, make sure that its base directory contains an **event** subdirectory.

After changing the transfer mode from push to pull, enable pull on the destination server. Any ongoing push activity will continue until all the file transfers are completed. If there is no ongoing push activity at the time of this configuration change, the push-related configuration is nullified immediately.

### Example

The following command sets the space usage trigger for pushing files to the event server to 60%:

```
event push-trigger space-usage-percent 60
```

The following command specifies that the event files are to be transferred to a server with the URL of `user:password@event-server.com`:

```
event transfer-mode push primary url //user:password@event-server.com
```

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# file

Sets the format and handling characteristics of event files.

---

## Product

P-GW  
SAEGW  
S-GW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Session Event Module Configuration

**configure** > **context** *context\_name* > **session-event-module**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-event)#
```

---

## Syntax Description

```
file [ compression { gzip | none } ] [ current-prefix string ] [
delete-timeout seconds ] [ directory directory_name ] [ exclude-checksum-record
] [ field-separator { hyphen | omit | underscore } ] [
file-sequence-number rulebase-seq-num ] [ headers ] [ name file_name ] [
reset-indicator ] [ rotation [ num-records number | time seconds | volume
bytes ] ] [ sequence-number { length length | omit | padded |
padded-six-length | unpadded } ] [ storage-limit limit ] [ time-stamp {
expanded-format | rotated-format | unix-format } ] [ trailing-text string
] [ trap-on-file-delete ] [ xor-final-record ] +
default file [ compression ] [ current-prefix ] [ delete-timeout ] [
directory ] [ field-separator ] [ file-sequence-number ] [ headers ] [
name ] [ reset-indicator ] [ rotation { num-records | time | volume } ]
[ sequence-number ] [ storage-limit ] [ time-stamp ] [ trailing-text ] +
```

### default

Configures the default setting for the specified keyword(s).

### compression { gzip | none }

Specifies compression of P-GW or S-GW event files.

- **gzip**: Enables GNU zip compression of the event file at approximately 10:1 ratio.
- **none**: Disables Gzip compression.

### current-prefix *string*

Specifies a string to add to the beginning of the event file that is currently being used to store records.

*string* must be an alphanumeric string of 1 through 31 characters. Default: **curr**

**delete-timeout *seconds***

Specifies a time period, in seconds, after which event files are deleted. By default, files are never deleted. *seconds* must be an integer from 3600 through 31536000. Default: Disabled

**directory *directory\_name***

Specifies a subdirectory in the default directory in which to store event files.

*directory\_name* must be an alphanumeric string of 1 through 191 characters. Default: **/records/event**

**exclude-checksum-record**

Excludes the final record containing #CHECKSUM followed by the 32-bit Cyclic Redundancy Check (CRC) of all preceding records from the event file.

Default: Disabled, a checksum record is included in the event file header.

**field-separator [ *hyphen* | *omit* | *underscore* ]**

Specifies the type of separators between two fields of an event file name:

- **hyphen**: Specifies the field separator as a "-" (hyphen) symbol between two fields.
- **omit**: Removes or omits the field separator between two fields.
- **underscore**: Specifies the field separator as an "\_" (underscore) symbol between two fields.

**file-sequence-number *rulebase-seq-num***

Specifies that the file name sequence numbers be unique per rulebase and event format name combination.

**headers**

Includes a file header summarizing the record layout.

**name *file\_name***

Specifies a string to be used as the base file name for event files.

*file\_name* must be an alphanumeric string of 1 through 31 characters. The file name format is as follows:

*base\_sequencenum\_timestamp* Default: **event**

- *base*: Specifies type of record in file or contains the operator-specified string. Default: **event**
- *sequencenum*: This is a 5-digit sequence number to detect the missing file sequence. It is unique among all event files on the system.
- *timestamp*: Adds a file creation timestamp (UTC time) in MMDDYYYYHHMMSS format.

**reset-indicator**

Specifies the inclusion of the reset indicator counter (value from 0 through 255) in the event file name. The counter is incremented whenever any of the following conditions occur:

- A peer chassis has taken over in compliance with Interchassis Session Recovery (ICSR).

- The sequence number (see **sequence-number** keyword) has rolled over to zero.

### **rotation { num-records *number* | time *seconds* | volume *bytes* }**

Specifies when to close an event file and create a new one.

- **num-records *number***: Specifies the maximum number of records that should be added to an event file. When the number of records in the file reaches this value, the file is complete.

*number* must be an integer 100 through 10240. Default: 1024

- **time *seconds***: Specifies the period of time to wait (in seconds) before closing the current event file and creating a new one.

*seconds* must be an integer from 30 through 86400. Default: 3600

- **volume *bytes***: Specifies the maximum size of the event file (in bytes) before closing it and creating a new one.

*bytes* must be an integer from 51200 through 62914560. Note that a higher setting may improve the compression ratio when the compression keyword is set to gzip. Default: 102400

### **sequence-number { length *length* | omit | padded | padded-six-length | unpadded }**

Includes with a specified format or excludes the sequence number in the file name.

- **length *length***: Includes the sequence number with the specified length.

*length* must be the file sequence number length with preceding zeroes in the file name, and must be an integer from 1 through 9.

- **omit**: Excludes the sequence number from the file name.

- **padded**: Includes the padded sequence number with preceding zeros in the file name. This is the default setting.

- **padded-six-length**: Includes the padded sequence number with six preceding zeros in the file name.

- **unpadded**: Includes the unpadded sequence number in the file name.

Default: **padded**

### **storage-limit *limit***

Files will be deleted when the specified amount of space (in bytes) is reached.

*limit* must be an integer from 10485760 through 536870912. Default: 33554432

### **time-stamp { expanded-format | rotated-format | unix-format }**

Specifies the format of the file creation timestamp to be included in the file name.

- **expanded-format**: Specifies the UTC (Universal Time Coordinated) MMDDYYYYHHMMSS format.

- **rotated-format**: Specifies the time stamp format to YYYYMMDDHHMMSS format.

- **unix-format**: Specifies the UNIX format of *x.y*, where *x* is the number of seconds since 1/1/1970 and *y* is the fractional portion of the current second that has elapsed.

**trailing-text string**

Specifies the inclusion of an arbitrary text string in the file name as an alphanumeric string of 1 through 30 characters.

**trap-on-file-delete**

Instructs the system to send an SNMP notification (trap) when an event file is deleted due to lack of space.

Default: Disabled

**xor-final-record**

Specifies inserting an exclusive OR (XOR) checksum (instead of a CRC checksum) into the event file header if the **exclude-checksum-record** is left at its default setting. Default: Disabled

+

More than one of the previous keywords can be entered within a single command.

---

**Usage Guidelines**

Use this command to configure event file characteristics.

**Example**

The following command sets the prefix of the current active event file to *Current*:

```
file current-prefix Current
```

The following command sets the base file name to *Eventfile*:

```
file name Eventfile
```

file





# Session Trace Template Configuration Mode Commands

---

The commands of the Session Trace Template configuration mode define the various template parameters needed to manage the trace functionality of the Session Trace and Cell Traffic Trace features. These functions are described in your product Administration Guide.

---

## Command Modes

Exec > Global Configuration > Session Trace Template Configuration

```
configure > template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw | mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-sesstrc-template) #
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [archive](#), on page 386
- [disk-limit](#), on page 387
- [do show](#), on page 388
- [end](#), on page 389
- [exit](#), on page 390
- [interface](#), on page 391
- [target-interface](#), on page 395
- [target-ne](#), on page 397
- [trace-extension](#), on page 399

# archive

This command defines the archive directory capacity and other related parameters.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Session Trace Template Configuration

```
configure > template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw | mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sesstrc-template)#
```

---

**Syntax Description**

```
[ no ] archive files number_of_files size sizetimertimer_value
```

**files** *number\_of\_files*

Specifies the number of files that go into a directory before it is closed for archiving. The range is an integer from 1 to 10000.

**size**

Specifies the total file size in Megabytes (MB) an Archive Directory can hold. The range is an integer from 1 to 10.

**timer** *timer\_value*

Specifies the timer expiry limit for files to be collected in the directory after which the pending directories are archived. The timer value is specified in seconds.

---

**Usage Guidelines**

The **archive** command is specific to the Cell Traffic Trace. This command is available under the **cell-trace** template under the eNodeB network element.

The **archive** command is used to archive file directories in a cell traffic tracing procedure. The file directories archived are displayed using a C Type file format. The C Type file includes trace information, which are available in the following fields: IMEI, IMSI, eNodeB identity, UE S1 AP identity and the MME UE S1 AP identity.

**Example**

The following configuration archives 100 files that can be stored in a directory of size 2 MB with timer limit of 200 seconds:

```
archive files 100 size 2 timer 200
```

# disk-limit

This command defines the total space reserved for files in the hard-disk.

---

## Product

MME

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Session Trace Template Configuration

```
configure> template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw
| mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sesstrc-template)#
```

---

## Syntax Description

```
[ no ] disk-limit disk_size
```

### no

Disables its following configured options.

### *disk\_size*

Specifies the disk reservation size in megabytes (MB). The disk-limit size ranges from 1 MB to 20480 MB. If disk-limit is not configured, a default size of 200 MB is allocated in the hard disk.

---

## Usage Guidelines

The **disk-limit** command is specific to Cell Traffic Trace. This command is available under the **cell-trace** template under the eNodeB network element.

The **disk-limit** command defines the total space to be reserved on the hard disk. If disk-limit alone is configured then compression is not considered. However, a default size of 200 MB is allocated in the hard disk for storing Cell Traffic Trace files.

## Example

The following configuration reserves 100 MB of space in the hard-disk for storing Cell Traffic Trace files:

```
disk-limit 100
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# interface

This command specifies the name of the interface applicable for a specific Network Element (NE) on which subscriber session traces have to be collected.

---

## Product

GGSN  
MME  
P-GW  
SAEGW  
S-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Session Trace Template Configuration

```
configure > template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw | mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sesstrc-template)#
```

---

## Syntax Description

```
[ no ] interface interface_name
```

### **no**

Disables its following configured options.

### **interface\_name**

Specifies the interface name for tracing. The available interfaces depend on the **network-element** selected.

**GGSN**. The available **ggsn** interfaces are:

- **all**: Specifies that all interfaces are to be traced.
- **gi**: Specifies that the interface where the trace will be performed is the Gi interface between the GGSN and RADIUS server.
- **gmb**: Specifies that the interface where the trace will be performed is the Gmb interface between the GGSN and BM-SC.
- **gn**: Specifies that the interface where the trace will be performed is the Gn interface between the GGSN and the SGSN.
- **gx**: Specifies that the interface where the trace will be performed is the Gx interface between the GGSN and PCRF.
- **gy**: Specifies that the interface where the trace will be performed is the Gy interface between the GGSN and OCS.

**HNBGW**. The available interfaces for **hnbgw** are as follows:

- **all**: Specifies that all **hnbgw** interfaces are to be traced.
- **iucs**: Specifies that the interface where the trace will be performed is the **iucs** interface between the HNB-GW and the Mobile Switching Centre (3G MSC) in a 3G UMTS Femtocell Access Network.

- **iups**: Specifies that the interface where the trace will be performed is the **iups** interface between the HNB-GW and the SGSN.

**MME**. The available interfaces for **mme** are as follows:

- **all**
- **s10**: Specifies that the interface where the trace will be performed is the S10 interface between the MME and another MME.
- **s11**: Specifies that the interface where the trace will be performed is the S11 interface between the MME and the S-GW.
- **s13**: Specifies that the interface where the trace will be performed is the S13 interface between the MME and the EIR.
- **s1mme**: Specifies that the interface where the trace will be performed is the S1-MME interface between the MME and the eNodeB.
- **s3**: Specifies that the interface where the trace will be performed is the S3 interface between the MME and an SGSN.
- **s6a**: Specifies that the interface where the trace will be performed is the S6a interface between the MME and the HSS.

**PGW**. The available interfaces for **pgw** are as follows:

- **all**: Specifies that all interfaces are to be traced.
- **gx**: Specifies that the interface where the trace will be performed is the Gx interface between the P-GW and the PCRF.
- **gy**: Specifies that the interface where the trace will be performed is the Gy interface between the P-GW and OCS.
- **s2a**: Specifies that the interface where the trace will be performed is the S2a interface between the P-GW and the HSGW.
- **s2b**: Specifies that the interface where the trace will be performed is the S2b interface between the P-GW and an ePDG.
- **s2c**: Specifies that the interface where the trace will be performed is the S2c interface between the P-GW and a trusted, non-3GPP access device.
- **s5**: Specifies that the interface where the trace will be performed is the S5 interface between an S-GW and P-GW located within the same administrative domain (non-roaming).
- **s6b**: Specifies that the interface where the trace will be performed is the S6b interface between the P-GW and the 3GPP AAA server.
- **s8**: Specifies that the interface where the trace will be performed is the S8 interface -- an inter-PLMN reference point between the S-GW and the P-GW used during roaming scenarios.
- **sgi**: Specifies that the interface where the trace will be performed is the SGi interface between the P-GW and the PDN.

**SAEGW**: The available interfaces for the SAEGW are as follows:

- **func-pgw interface**: The following interfaces are available for a configured P-GW under an SAEGW service:
  - **all**: Specifies that all interfaces are to be traced.
  - **gx**: Specifies that the interface where the trace will be performed is the Gx interface between the P-GW and the PCRF.
  - **gy**: Specifies that the interface where the trace will be performed is the Gy interface between the P-GW and OCS.



- **s2a**: Specifies that the interface where the trace will be performed is the S2a interface between the P-GW and the HSGW.
  - **s2b**: Specifies that the interface where the trace will be performed is the S2b interface between the P-GW and an ePDG.
  - **s2c**: Specifies that the interface where the trace will be performed is the S2c interface between the P-GW and a trusted, non-3GPP access device.
  - **s5**: Specifies that the interface where the trace will be performed is the S5 interface between an S-GW and P-GW located within the same administrative domain (non-roaming).
  - **s6b**: Specifies that the interface where the trace will be performed is the S6b interface between the P-GW and the 3GPP AAA server.
  - **s8**: Specifies that the interface where the trace will be performed is the S8 interface -- an inter-PLMN reference point between the S-GW and the P-GW used during roaming scenarios..
  - **sgi**: Specifies that the interface where the trace will be performed is the SGi interface between the P-GW and the PDN.
- **func-sgw interface**: The following interfaces are available for a configured S-GW under an SAEGW service:
- **all**: Specifies that all interfaces are to be traced.
  - **gxc**: Specifies that the interface where the trace will be performed is the Gxc interface between the S-GW and the PCRF.
  - **s11**: Specifies that the interface where the trace will be performed is the S11 interface between the S-GW and the MME.
  - **s4**: Specifies that the interface where the trace will be performed is the S4 interface between the S-GW and an SGSN.
  - **s5**: Specifies that the interface where the trace will be performed is the S5 interface between the S-GW and the P-GW.
  - **s8**: Specifies that the interface where the trace will be performed is the S8 interface between the S-GW and the P-GW.

**SGW**. The available interfaces for the S-GW are as follows:

- **all**: Specifies that all interfaces are to be traced.
- **gxc**: Specifies that the interface where the trace will be performed is the Gxc interface between the S-GW and the PCRF.
- **s11**: Specifies that the interface where the trace will be performed is the S11 interface between the S-GW and the MME.
- **s4**: Specifies that the interface where the trace will be performed is the S4 interface between the S-GW and an SGSN.
- **s5**: Specifies that the interface where the trace will be performed is the S5 interface between the S-GW and the P-GW.
- **s8**: Specifies that the interface where the trace will be performed is the S8 interface between the S-GW and the P-GW.

### Usage Guidelines

The **interface** command is specific to Session Tracing. This command is available in the template for the MME NE. This command specifies the interfaces for Session Tracing from the MME.

### Example

The following command selects S1-MME as the interface for session tracing:

```
interface slmme
```

# target-interface

This command specifies the interface for the selected Network Element for session tracing.

---

## Product

GGSN  
 HNMGW  
 MME  
 P-GW  
 SAEGW  
 S-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Session Trace Template Configuration

```
configure > template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw | mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sesstrc-template)#
```

---

## Syntax Description

**target-interface** *interface\_name*

### *interface\_name*

Specifies the interface for the selected Network Element for tracing.

- Available **target-interface** options for **enb** are as follows:
  - **all**
  - **s1mme**: Specifies that the interface where the trace will be performed is the S1-MME interface between the MME and the eNodeB.
  - **uu**: Specifies that the interface where the trace will be performed is the UU interface between the MME and the eNodeB.
  - **x2**: Specifies that the interface where the trace will be performed is the X2 interface between the MME and the eNodeB.
- Available **target-interface** options for **pgw** are as follows:
  - **all**
  - **gx**: Specifies that the interface where the trace will be performed is the Gx interface between the P-GW and the PCRF.
  - **s2a**: Specifies that the interface where the trace will be performed is the S2a interface between the PGW and the HSGW.
  - **s2b**: Specifies that the interface where the trace will be performed is the S2b interface between the PGW and an ePDG.
  - **s2c**: Specifies that the interface where the trace will be performed is the S2c interface between the PGW and a trusted, non-3GPP access device.

- **s5**: Specifies that the interface where the trace will be performed is the S5 interface between the P-GW and the S-GW.
  - **s6b**: Specifies that the interface where the trace will be performed is the S6b interface between the PGW and the 3GPP AAA server.
  - **s8**: Specifies that the interface where the trace will be performed is the S8b interface between the PGW and the S-GW.
  - **sgi**: Specifies that the interface where the trace will be performed is the SGi interface between the PGW and the PDN.
- Available **target-interface** options for **sgw** are as follows:
    - **all**
    - **gxc**: Specifies that the interface where the trace will be performed is the Gx interface between the PGW and the PCRF.
    - **s11**: Specifies that the interface where the trace will be performed is the S11 interface between the MME and the S-GW.
    - **s4**: Specifies that the interface where the trace will be performed is the S4 interface between the S-GW and the SGSN.
    - **s5**: Specifies that the interface where the trace will be performed is the S5 interface between the P-GW and the S-GW.
    - **s8**: Specifies that the interface where the trace will be performed is the S8b interface between the PGW and the S-GW.

---

**Usage Guidelines**

The **target-interface** specifies the interface for tracing for a specified NE. This keyword is prompted only when a specific Network Element is selected using the **target-ne** command.

**Example**

The following configures session tracing for the network element **pgw** and its S8 interface:

```
target-ne pgw target-interface s8
```

# target-ne

This command initiates tracing towards other network elements.

---

## Product

GGSN  
 HNMGW  
 MME  
 P-GW  
 SAEGW  
 S-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Session Trace Template Configuration

```
configure > template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw | mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sesstrc-template)#
```

---

## Syntax Description

```
[ no ] target-ne { all | { enb | pgw | sgw } [ target-interface interface_name ] }
```

### **no**

Disables its following configured options.

### **all**

Selects all interfaces supported under MME for session trace.

### **target-interface** *interface\_name*

Specifies the interface for the selected Network Element for tracing.

- Available **target-interface** options for **enb** are as follows:

- **all**
- **s1mme**: Specifies that the interface where the trace will be performed is the S1-MME interface between the MME and the eNodeB.
- **uu**: Specifies that the interface where the trace will be performed is the UU interface between the MME and the eNodeB.
- **x2**: Specifies that the interface where the trace will be performed is the X2 interface between the MME and the eNodeB.

- Available **target-interface** options for **pgw** are as follows:

- **all**

- **gx**: Specifies that the interface where the trace will be performed is the Gx interface between the P-GW and the PCRF.
  - **s2a**: Specifies that the interface where the trace will be performed is the S2a interface between the PGW and the HSGW.
  - **s2b**: Specifies that the interface where the trace will be performed is the S2b interface between the PGW and an ePDG.
  - **s2c**: Specifies that the interface where the trace will be performed is the S2c interface between the PGW and a trusted, non-3GPP access device.
  - **s5**: Specifies that the interface where the trace will be performed is the S5 interface between the P-GW and the S-GW.
  - **s6b**: Specifies that the interface where the trace will be performed is the S6b interface between the PGW and the 3GPP AAA server.
  - **s8**: Specifies that the interface where the trace will be performed is the S8b interface between the PGW and the S-GW.
  - **sgi**: Specifies that the interface where the trace will be performed is the SGi interface between the PGW and the PDN.
- Available **target-interface** options for **sgw** are as follows:
    - **all**
    - **gxc**: Specifies that the interface where the trace will be performed is the Gx interface between the PGW and the PCRF.
    - **s11**: Specifies that the interface where the trace will be performed is the S11 interface between the MME and the S-GW.
    - **s4**: Specifies that the interface where the trace will be performed is the S4 interface between the S-GW and the SGSN.
    - **s5**: Specifies that the interface where the trace will be performed is the S5 interface between the P-GW and the S-GW.
    - **s8**: Specifies that the interface where the trace will be performed is the S8b interface between the PGW and the S-GW.

### Usage Guidelines

The **target-ne** command is specific to Session Tracing. This command is available in the template for the MME NE. This command initiates tracing towards other network elements. The **target-interface** specifies the interface for tracing for a specified NE.

### Example

The following configures session tracing for the network element **pgw** and its S8 interface:

```
target-ne pgw target-interface s8
```

# trace-extension

This command defines the UE or ENodeB identity extension parameters for C Type file.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Session Trace Template Configuration

```
configure> template-session-trace network-element { { enb template-name cell-trace } | { { ggsn | hnbgw
| mme | pgw | saegw | sgw } template-name template_name } }
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sesstrc-template)#
```

---

**Syntax Description**

```
[ no ] trace-extension enb-id ue-slap-id
```

**enb-id**

Specifies the Global EnodeB identity.

**ue-slap-id**

Specifies the eNodeB UE S1AP Identity and MME UE S1AP Identity

---

**Usage Guidelines**

The **trace-extension** keyword is used to provide additional cell trace information from the global UE identity, eNodeB UE identity and the MME UE identity fields in the C Type files.

**Example**

The following configuration enables trace extension:

```
trace-extension enb-id ue-slap-id
```







## SGSN ASP Configuration Mode Commands

---

### Command Modes

The ASP (application server process) configuration mode defines the M3UA end-point parameters for a specific SS7 routing domain instance. The ASP instance is generated and accessed via the SS7 routing domain configuration mode commands.

Exec > Global Configuration > SS7 Routing Domain Configuration > ASP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **asp instance** *asp\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-asp-inst-instance) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 402
- [end](#), on page 403
- [end-point](#), on page 404
- [exit](#), on page 406

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.


**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current mode and returns to the Exec Mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Change the mode back to the Exec Mode.

# end-point

This command defines or deletes the IP address and/or port number to be associated with the local SCTP end-point for this ASP. At least one address needs to be configured before the end-point can be activated.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

When using the **bind** keyword, this command also activates the end-point once the address has been defined. Once bound, it cannot be reconfigured until it is unbound with the **no end-point bind** command.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > ASP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **asp instance** *asp\_number*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-asp-inst-instance)#
```

## Syntax Description

```
end-point { address ip_address context context_id | bind | port port_number }
no end-point { address ip_address context context_id | bind }
```

### **address** *ip\_address* **context** *context\_id*:

Specifies the IP address and the context associated with the address for this end-point.

*ip\_address*: must be defined using the standard IPv4 dotted decimal notation or the colon notation of IPv6.

**context** *context\_id*: a string of 1 to 79 alphanumeric characters to identify the specific context associated with the end-point address.

### **bind**

Activates (binds) the end-point.



## Important

Only use **bind** after you have configured other parameters.

### **port** *port\_number*

Identifies the M3UA's SCTP port associated with this end-point.

*port\_number*: must be an integer from 1 to 65535. Default is 2905.

**no**

Removes the end-point configuration or deactivates the end-point.

**Caution**

Entering this command will terminate all current subscriber sessions for associated peers.

**Usage Guidelines**

Use this command to manage the ASP end-point. Once the ASP end-point is bound the end-point configuration can not be changed until it is unbound.

**Example**

Activate the end-point with the following command:

```
end-point bind
```

Deactivate or unbind the end-point with the following command:

```
no end-point bind
```

Set the end-point port to default for ASP 1 with the following command:

```
default asp instance 1 end-point port
```

# exit

Exits the current mode and returns to the previous mode.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Returns to the previous mode.



# SGSN Congestion Action Profile Configuration Mode

---

- active calls
- new calls
- SM messages

For more information about the SGSN's MTC congestion control functionality, refer to the *MTC Congestion Control* section in the *SGSN Administration Guide*.

---

## Command Modes

This mode provides the commands to configure the congestion-action-profile, which incorporates the actions to be taken by the SGSN during specified congestion scenario as part of the SGSN's machine type communications (MTC) congestion control responses for the call/messages events.

Exec > Global Configuration > SGSN Global Configuration > Congestion Control Configuration > Congestion Action Profile Configuration

configure > sgsn-global > congestion-control > congestion-action-profile *act\_prof\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-cong-act-prof-act_prof_name)#
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [active-call-policy](#), on page 408
- [do show](#), on page 410
- [end](#), on page 411
- [exit](#), on page 412
- [new-call-policy](#), on page 413
- [sm-messages](#), on page 415

# active-call-policy

This command instructs the SGSN to drop or reject any active call messages when congestion occurs during an active call. The active call instructions in the congestion-action-profile can be refined to only drop or reject active call messages with LAPI.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > SGSN Global Configuration > Congestion Control Configuration > Congestion Action Profile Configuration  configure > sgsn-global > congestion-control > congestion-action-profile <i>act_prof_name</i>  Entering the above command sequence results in the following prompt:  <pre>[local]host_name(config-cong-act-prof-act_prof_name)#</pre>
<b>Syntax Description</b>	<p><b>active-call-policy</b> { <b>rau</b>   <b>service-req</b> } { <b>drop</b>   <b>reject</b> } [ <b>low-priority-ind-ue</b> ] <b>no active-call-policy</b> { <b>rau</b>   <b>service-req</b> }</p> <p><b>no</b></p> <p>When this filter is added to the command, the SGSN deletes the active call policy definitions from the congestion-action-profile.</p> <p><b>rau</b></p> <p>Defines the action, either drop or reject, to be taken when the SGSN receives a Routing Area Update (RAU) message during congestion.</p> <p><b>service-req</b></p> <p>Defines the action, either drop or reject, to be taken when the SGSN receives a Service Request message during congestion.</p> <p><b>drop</b></p> <p>Instructs the SGSN to drop the defined message type as the congestion control response.</p> <p><b>reject</b></p> <p>Instructs the SGSN to reject the defined message type as the congestion control response.</p> <p><b>low-priority-ind-ue</b></p> <p>Instructs the SGSN to only take defined action if messages from the UE include a low priority access indicator (LAPI). This keyword can be use with either message type: RAU or Service Request.</p>
<b>Usage Guidelines</b>	Use the <b>show sgsn-mode</b> command to display the SGSN's congestion control configuration defined with the command listed above. .



This command defines some of the congestion responses for the congestion-action-profile. These responses are a part of the overall SGSN machine type communication (MTC) congestion control functionality. For more information about the SGSN's MTC congestion control functionality, refer to the *MTC Congestion Control* section in the *SGSN Administration Guide*.

### Example

Use a command similar to the following to instruct the SGSN to drop RAU Requests received during an active call if LAPI is set in the request:

```
active-call-policy rau drop low-priority-ind-ue
```

Use a command similar to the following to remove all active-call congestion response definitions, for Service Requests, from the congestion-action-profile :

```
no active-call-policy service-req
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.


**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

## new-call-policy

This command instructs the SGSN to drop or reject any new calls (Attach Request messages or new Inter SGSN RAU messages) if new call messages are received during congestion. The new call instructions in the congestion-action-profile can be refined to only drop or reject new call messages with low access priority indicator (LAPI).

---

### Product

SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > SGSN Global Configuration > Congestion Control Configuration > Congestion Action Profile Configuration

configure > sgsn-global > congestion-control > congestion-action-profile *act\_prof\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-cong-act-prof-act_prof_name) #
```

---

### Syntax Description

**new-call-policy** { **drop** | **reject** } [ **apn-based** ] [ **low-priority-ind-ue** ]  
**no new-call-policy**

#### no

When this filter is added to the command, the SGSN deletes the new call policy definitions from the congestion-action-profile.

#### drop

Instructs the SGSN to drop the any new call messages (Attach Request or new RAU ) if the new call messages are received during congestion.

#### reject

Instructs the SGSN to reject any new call messages (Attach Request or new RAU ) if the new call messages are received during congestion.

#### apn-based

Instructs the SGSN to reject a new call request based on the APN if congestion control is configured for that APN under an applicable Operator Policy.

#### low-priority-ind-ue

Instructs the SGSN to only take defined action if messages from the UE include a low priority access indicator (LAPI).

---

### Usage Guidelines

Use the **show operator-policy full name** *policy\_name* command to display whether congestion control has been implemented for a specific APN.

Use the **show sgsn-mode** command to display the SGSN's congestion control configuration defined with the command listed above. .

This command defines some of the congestion responses for the congestion-action-profile. These responses are a part of the overall SGSN machine type communication (MTC) congestion control functionality. For more information about the SGSN's MTC congestion control functionality, refer to the *MTC Congestion Control* section in the *SGSN Administration Guide*.

### Example

Use a command similar to the following to instruct the SGSN to drop new call messages that include LAPI :

```
new-call-policy drop low-priority-ind-ue
```

Use a command similar to the following to instruct the SGSN to reject new call messages only if the messages includes a LAPI and the APN is configured for congestion-control in an applicable operator policy :

```
new-call-policy reject apn-based low-priority-ind-ue
```

Use a command similar to the following to remove all new-call congestion response definitions from the congestion-action-profile :

```
no new-call-policy
```

## sm-messages

This command instructs the SGSN to reject any SM signaling messages (activation or modification) as a response to congestion. This congestion-action-profile parameter can be refined to only reject SM signaling messages when the low access priority indicator (LAPI) is included in the message.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > SGSN Global Configuration > Congestion Control Configuration > Congestion Action Profile Configuration  configure > sgsn-global > congestion-control > congestion-action-profile <i>act_prof_name</i>  Entering the above command sequence results in the following prompt:  <pre>[local]host_name(config-cong-act-prof-act_prof_name) #</pre>
<b>Syntax Description</b>	<p><b>sm-messages reject [ apn-based ] [ low-priority-ind-ue ]</b> <b>no sm-messages</b></p> <p><b>no</b></p> <p>When this filter is added to the command, the SGSN deletes the sm-messages definition from the congestion-action-profile.</p> <p><b>reject</b></p> <p>Instructs the SGSN to reject any sm-messages received during congestion.</p> <p><b>apn-based</b></p> <p>Instructs the SGSN to reject sm-messages only if congestion control is configured for that APN under an applicable Operator Policy.</p> <p><b>low-priority-ind-ue</b></p> <p>Instructs the SGSN to reject sm-messages from the UE only if the messages includes a low priority access indicator (LAPI).</p>

### Usage Guidelines



#### Important

For SM congestion to work, the **apn-based** option must be configured with the **sm-messages reject** command.

If both the LAPI and APN-based options are included in the action-profile, then the sm-messages will only be rejected if both conditions are matched.

Use the **show operator-policy full name** *policy\_name* command to display whether congestion control has been implemented for a specific APN.

Use the **show sgsn-mode** command to display the SGSN's congestion control configuration defined with the command listed above. .

This command defines some of the congestion responses for the congestion-action-profile. These responses are a part of the overall SGSN machine type communication (MTC) congestion control functionality. For more information about the SGSN's MTC congestion control functionality, refer to the *MTC Congestion Control* section in the *SGSN Administration Guide*.

### Example

Use a command similar to the following to instruct the SGSN to reject sm-messages that include LAPI :

```
sm-messages reject low-priority-ind-ue
```

Use a command similar to the following to instruct the SGSN to reject sm-messages only if the messages includes a LAPI and the APN is configured for congestion-control in an applicable operator policy :

```
sm-messages reject apn-based low-priority-ind-ue
```

Use a command similar to the following to remove all congestion response definitions related to sm-messages from the congestion-action-profile :

```
no sm-messages
```





## SGSN Congestion Control Configuration Mode

---

[this paragraph is needed as a minimum and must be completed as a continuation of the shortdesc]

---

### Command Modes

The SGSN Congestion Control configuration mode provides the commands to access and configure the congestion control for the SGSN globally.

Exec > Global Configuration > SGSN Global Configuration > Congestion Control Configuration

**configure > sgsn-global > congestion-control**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-congestion-ctrl)#
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [congestion-action-profile, on page 418](#)
- [do show, on page 419](#)
- [end, on page 420](#)
- [exit, on page 421](#)

# congestion-action-profile

Creates an instance of a congestion-action-profile, which defines action to be take during congestion control scenario. Command also provides access to the Congestion Action Profile configuration mode commands.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration > Congestion Control Configuration

**configure > sgsn-global > congestion-control**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-congestion-ctrl)#
```

**Syntax Description** [ no ] **congestion-action-profile** *action\_profile\_name*

**no**

When this filter is added to the command, the SGSN deletes the congestion-control-profile from the SGSN-Global configuration.

**congestion-action-profile** *action\_profile\_name*

Create or identify a congestion-action-profile.

*action\_profile\_name*: Enter a string of 1 to 64 alphanumeric characters.

**Usage Guidelines** This command provides access to the Congestion-Action-Profile configuration mode commands which define the SGSN's congestion responses for:

- active calls
- new calls
- SM messages

Use the **show sgsn-mode** command to display the SGSN's congestion-control configuration defined with the command listed above.

## Example

Use a command similar to the following to gain access to the commands to modify an existing congestion-action-profile named *sgsnCongActProf1*:

```
congestion-action-profile sgsnCongActProf1
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

■ exit



# SGSN Global Configuration Mode Commands

## Command Modes

The commands in this mode configure parameters that impact the entire SGSN and that are independent of the GPRS or the IuPS services.

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [aggregate-ipc-msg](#), on page 425
- [apn-resolve-dns-query snaptr](#), on page 427
- [bssgp-message dl-unitdata](#), on page 428
- [bssgp-message ms-flow-control-from-unknown-ms](#), on page 429
- [bssgp-message ptp-bvc-reset](#), on page 431
- [bssgp-timer](#), on page 432
- [bvc-unblock](#), on page 433
- [canonical-node-name](#), on page 435
- [common-ra-paging](#), on page 436
- [congestion-control](#), on page 437
- [do show](#), on page 438
- [dscp-template](#), on page 439
- [dual-address-pdp](#), on page 441
- [ec-gsm](#), on page 443
- [eir-profile](#), on page 444
- [end](#), on page 445
- [exit](#), on page 446
- [gmm-message](#), on page 447
- [gmm-sm-statistics](#), on page 448
- [gprs-mocn](#), on page 449
- [interface-management](#), on page 450

- [ipms-suppress](#), on page 451
- [imsi-range](#), on page 452
- [location-services](#), on page 455
- [map-message](#), on page 456
- [max-pending-attaches](#), on page 457
- [msisdn-group](#), on page 458
- [msisdn-range](#), on page 459
- [old-tlli invalidate tlli](#), on page 460
- [old-tlli hold-time](#), on page 461
- [pdp-deactivation-rate](#) , on page 462
- [qos-arp-rp-map-profile](#), on page 464
- [ranap excess-len ignore](#), on page 465
- [ran-information-management](#), on page 466
- [target-offloading](#), on page 467
- [tlli-cb-audit](#), on page 468
- [umts-aka-r99](#), on page 469



# aggregate-ipc-msg

Configures the number of inter-process communication (IPC) messages that can be aggregated in the various managers and defines the frequency of flushing the messages.



## Important

In Release 20 and later, HNBNW is not supported. This command must not be used for HNBNW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

## Syntax Description

```
aggregate-ipc-msg { gbmgr | linkmgr | sessmgr } { auto-num-msgs | flush-frequency frequency | num-msgs number_msgs } default aggregate-ipc-msg { gbmgr | linkmgr | sessmgr }
```

### default

Resets the managers to default values for flushing.

### gbmgr

Selects the Gb manager to configure the number of IPC messages to be aggregated and frequency of flushing messages to the Session Manager that have been aggregated at the Gb Manager.

### linkmgr

Selects the linkmgr to configure the number of IPC messages to be aggregated and frequency of flushing.

### sessmgr

Selects the sessmgr to configure the number of IPC messages to be aggregated and frequency of flushing.

### auto-num-msgs

Enables the automated aggregation of messages sent from LinkMgr or GbMgr to the SessMgr.

Default is Disabled.

**flush-frequency *frequency***

Configure the frequency, in 100-millisecond intervals, that the aggregated IPC messages will be flushed. Flushing limits the number of messenger calls between managers to transfer the received packets.

*frequency* : Enter an integer from 1 to 3. Default is 1.

**num-msgs *number\_msgs***

Configure the number of IPC messages to aggregate before flushing.

*number\_msgs* : Enter the integer 1 (to disable aggregation) or an integer from 2 to 164 to define the number of messages. Default is 10.

**Important**

Setting **num-msgs** to a value of 1 will disable message packet aggregation.

**Usage Guidelines**

Use this command to enable/disable aggregation of IPC messages in the linkmgr and/or the sessmgr. This command includes options to configure the frequency of aggregated message flushing and the number of packets to be buffered before the flush. This command provides a solution for reducing latency while sending the IPC messages towards the core network (CN).

The flushing limit will be based on either desired flush-frequency or maximum number of messages to be aggregated. Repeat the command to engage multiple limits.

By default, the link manager buffers packets and then send them over the SCCP link if there are events to be sent via SCCP Connection Request (SCCP CR) towards the core node. The HNB-GW/SGSN aggregate packets for 100 msec and send them with whatever aggregation has been done during those 100 msecs.

At the HNB-GW/SGSN, this command can be used to reduce the processing involved in sending every event individually towards the core node in the following manner:

- If aggregation is enabled, then there could be a time delay for sending SCCP CRs depending on configuration of the HNB-GW or SGSN.
- If aggregation is reduced to 1, then there will be no delay for aggregation and events are sent via SCCP CR without delay. This reduces the SCCP connection setup time.

To view aggregate IPC message statistics, use command **show config | grep aggregate-ipc-msg**.

**Example**

Configure the linkmgr to buffer 45 messages before flushing the linkmgr IPC messages:

```
aggregate-ipc-msg linkmgr flush-frequency 45
```

The following command configures the *linkmgr* to flush the IPC messages towards the CN without aggregation:

```
aggregate-ipc-msg linkmgr 1
```

The following command configures the *sessmgr* to flush the IPC messages towards the CN without aggregation:

```
aggregate-ipc-msg sessmgr 1
```

# apn-resolve-dns-query snaptr

Enable/disable sending of SNAPTR DNS query to resolve an APN for a subscriber with an EPS (evolved packet system)-capable handset.



## Important

This command is no longer available in all 12.0 and 12.2 releases. If you do not see this command in your release, look for the **apn-resolve-dns-query snaptr** command in the APN Profile configuration mode to accomplish the same task.

## Product

SGSN

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

## Syntax Description

**[ no ] apn-resolve-dns-query snaptr  
default apn-resolve-dns-query**

### default

Resets the default, the ability to send SNAPTR DNS query is disabled.

### no

Disables the ability to send SNAPTR DNS query.

## Usage Guidelines

By default, sending the SNAPTR DNS query is disabled. Use this command to send SNAPTR DNS query when resolving an APN for an EPS-capable subscriber.

At PDP context activation, the SGSN will use the UE capability as input to select either a GGSN or a P-GW for the EPS-capable subscriber. The SNAPTR DNS query will be used for P-GW resolution. Enabling this feature will give priority to P-GW selection for E-UTRAN-capable UEs.

## Example

Use the following command to enable sending of SNAPTR DNS query for APN resolution:

```
apn-resolve-dns-query
```

Use the following command to disable the use of SNAPTR DNS query for APN resolution:

```
no apn-resolve-dns-query
```

# bssgp-message dl-unitdata

Configure this command to exclude or include RAT/Frequency Selection Priority (RFSP ID) in BSSGP DL-Unitdata messages to the BSC.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

**Syntax Description** **bssgp-message dl-unitdata rfsp-id exclude**  
**default bssgp-message dl-unitdata rfsp-id**

## default

By default, the RFSP-ID IE is included in BSSGP DL-Unitdata message.

## dl-unitdata rfsp-id exclude

Use this keyword to exclude RFSP-ID IE in BSSGP DL-Unitdata message.

**Usage Guidelines** The SGSN can control sending of RAT/Frequency Selection Priority (RFSP ID) from subscription or a local overridden value towards BSC.

## Example

Use this command to exclude the RFSP ID in BSSGP DL-Unitdata message:

```
bssgp-message dl-unitdata rfsp-id exclude
```

Use this command to include the RFSP ID in BSSGP DL-Unitdata message:

```
default bssgp-message dl-unitdata rfsp-id
```

# bssgp-message ms-flow-control-from-unknown-ms

This command determines the SGSN response to MS-Flow-Control messages received from an unknown MS.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

## Syntax Description

```
bssgp-message ms-flow-control-from-unknown-ms { discard-message | send-ack  
| send-status }  
default bssgp-message ms-flow-control-from-unknown-ms
```

### default

Including **default** with the command configures the SGSN to use default behavior so that the SGSN sends BSSGP-Status messages whenever the SGSN receives an MS-Flow-Control message from an unknown MS.

### discard-message

This keyword instructs the SGSN to discard the received BSSGP message. With this option, the SGSN does not send any response to the MS after discarding the received BSSGP message.

### send-ack

This keyword instructs the SGSN to send an acknowledgement message (MS-Flow-Control-ACK) after receiving an MS-Flow-Control message.

### send-status

Default

This keyword instructs the SGSN to send a BSSGP-Status message to the MS whenever the SGSN receives an MS-Flow-Control message from an unknown MS.

## Usage Guidelines

This command allows the operator to specify the action the SGSN needs to take whenever the SGSN receives an MS-Flow-Control message from an unknown mobile station. This configuration determines the response for the SGSN globally.

The list of possible actions are:

- send a BSSGP-Status response message
- send an ACK message (MS-Flow-Control-ACK)
- discard the BSSGP message

To see the statistics for the number of MS-Flow-Control messages that have been discarded, use the **show bssgp statistics** command from the Exec mode.

### Example

Change the default configuration and have the SGSN acknowledge receipt of the MS-Flow-Control message:

```
bssgp-message ms-flow-control-from-unknown-ms send-ack
```

## bssgp-message ptp-bvc-reset

This command determines the SGSN response, per BVCI, to receipt of a peer-to-peer BVC Reset.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration  
**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **bssgp-message ptp-bvc-reset { frc-subscriber-standby | retain-current-state }**  
**default bssgp-message ptp-bvc-reset**

### default

Including **default** with the command configures the SGSN to use default behavior so that the SGSN continues with the current state once a peer-to-peer BVC Reset is received.

### frc-subscriber-standby

This keyword instructs the SGSN to change the state of the subscribers to standby when the peer-to-peer BVC Reset is received.

### retain-current-state

Default

This keyword instructs the SGSN to continue the current state of the subscribers when the BVC Reset message is received.

---

### Usage Guidelines

This command allows the operator to specify the action the SGSN needs to take whenever the SGSN receives a peer-to-peer BVC Reset message for a specific BVCI.

To confirm the configuration for the response to the BVC Reset, use the **show sgsn-mode** command from the Exec mode.

### Example

Change the default configuration and have the SGSN change subscriber states to standby:

```
bssgp-message ptp-bvc-reset frc-subscriber-standby
```

# bssgp-timer

Configures the T2 and TH timers for the BVCs (BSSGP virtual connections) of the NSE (network service entities).

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

**Syntax Description** **bssgp-timer { t2 *T2\_time* | th *TH\_time* }**  
**default bssgp-timer { t2 | th }**

## default

Resets the specified timers to default settings.

## t2 *T2\_time*

Configures the BVC reset guard timer (at the BSSGP layer) in units of 1 second.

*T2\_time* : Enter an integer from 1 to 120. Default is 30 seconds.

## th *TH\_time*

Configures, at the BSSGP layer, the MS flow control parameter validity timeouts in units of 1 second.

*TH\_time* : Enter an integer from 6 to 5999. Default is 500 seconds.

**Usage Guidelines** Use this command to configure timer timeout values for MS flow control and BVC reset timers that control BVCs for the NSEs.

## Example

Set the TH timeout for 20 seconds:

```
bssgp-timer th 20
```



# bvc-unblock

This command enables (disabled by default) or disables the SGSN to unblock blocked BVCs based on the receipt of uplink packets from the BSC.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

**Syntax Description** **bvc-unblock { data-or-flow-control | flow-control | ul-data }**  
**[ default | no ] bvc-unblock**

## default

Include **default** with the command to disable the function.

## no

Include **no** with the command to disable this function.

## data-or-flow-control

Enables the BVC-Unblock function when the SGSN receives either a FLOW-CONTROL-BVC packet or a UL-UNITDATA packet.

## flow-control

Enables the BVC-Unblock function when the SGSN receives a FLOW-CONTROL-BVC packet.

## ul-data

Enables the BVC-Unblock function when the SGSN receives a UL-UNITDATA packet.

## Usage Guidelines

Configurations defined with this command are common to all NSE defined for the SGSN.

This command is useful if there is a BVC status mismatch across different SGSN managers (such as the sessmgr and the linkmgr) when the BSC sends BVC-Block (SGSN should move to BLOCKED) followed by a BVC-Reset (SGSN should move to UNBLOCKED). Such mismatches can easily occur, particularly on Gb-IP network connection, when one link receives the BVC-Block and a different link receives the BVC-Reset with little delay between the two.

If BVC-Unblock function is enabled, the SGSN ensures that BVCs which are in the BLOCKED state move to the UNBLOCKED state upon receipt of the configured packet type(s).

**Example**

Instruct the SGSN to perform BVC-Unblock when a mismatch occurs and the SGSN receives a FLOW-CONTROL-BVC packet:

```
bvc-unblock flow-control
```

# canonical-node-name

Defines the SGSN's canonical node name.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration  
**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** [ **no** ] **canonical-node-name** *canonical\_node\_name*

**no**

Erases the specified canonical node name definition from the SGSN Global configuration.

---

**Usage Guidelines** *canonical\_node\_name* is a fully or properly qualified domain name; for example sgsn.div.bng.kar.3gppnetwork.org.

In order for the Gn/Gp-SGSN to support the topological gateway selection feature, the SGSN's canonical node name must be defined in the SGSN's configuration. (This is not needed for the S4-SGSN). For additional information about this feature, refer to the *Topology-based Gateway Selection* section in the *SGSN Administration Guide*.

## Example

Define the SGSN's canonical node name as *sgsn.div.bng.kar.3gppnetwork.org*:

```
canonical-node-name sgsn.div.bng.kar.3gppnetwork.org
```

## common-ra-paging

This command enables paging across common Routing Area (RA) for 2G and 3G.

---

### Product

SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

---

### Syntax Description

**[ default | no ] common-ra-paging**

#### default

Returns the SGSN to the default state: paging across common Routing Area (RA) is disabled for 2G and 3G.

#### no

Disables paging across common Routing Area (RA) for 2G and 3G after it has been enabled using the **common-ra-paging** command

---

### Usage Guidelines

When this CLI is enabled, the SGSN supports paging initiation in both the RATs (2G and 3G) if paging has to be done in RA which is common across the RATs. SGSN also accepts power-off detach from the MS, which is different from the RAT when the MS is attached.

### Example

Use the following command to enable paging across common Routing Area (RA) for 2G and 3G.

```
common-ra-paging
```

# congestion-control

Sets up the environment on the SGSN to support Machine Type Communications (MTC) congestion control and opens a new SGSN Global Congestion Control command configuration mode.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **congestion-control**

---

**Usage Guidelines** Provides access to the congestion-action-profile configuration command.

## Example

Open the SGSN Global Congestion Control configuration mode.

```
congestion-control
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# dscp-template

Creates and/or deletes DSCP templates that can be configured for use for all GPRS services on the SGSN and provides access to the DSCP Template configuration mode. This command is also supported on HNB-GW service to create a DSCP template.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SGSN Global Configuration  
**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

## Syntax Description

**dscp-template** *template\_name* [ **-noconfirm** ]  
**no dscp-template** *template\_name*

**no**

Deletes the template instance from the SGSN Global configuration.

### **template\_name**

Enter 1 to 64 alphanumeric characters, including dots (.), dashes (-), and forward slashes (/). to identify a unique instance of a DSCP template.

There is no known limit to the number of templates that can be created.

## Usage Guidelines

This command enables the operator to create or delete an instance of a DSCP template and access the DSCP Template configuration mode. The DSCP templates are used to define the DSCP configuration for control packets and data packets for the GPRS services.

### Related commands:

- This command provides access to the mode containing all the configuration commands used to define DSCP markings for the control packets and data packets for a particular GPRS service (see the *DSCP Template Configuration Mode Commands* section).
- To associated a specific DSCP template with a specific GPRS service configuration, for builds prior to release 14.0 use the **associate-dscp-template downlink** command and for builds in releases 14.0 and higher use the **associate dscp-template downlink** command. Both commands are documented in the *GPRS Service Configuration Mode Commands* section.

- To check the list of DSCP templates configured, use the **show sgsn-mode** command documented in the *Exec Mode Commands* section.

This command is also supported on HNB-GW service to create a DSCP template.

#### Related commands for HNB-GW:

- This command provides access to the mode containing all the configuration commands used to define DSCP markings for the control packets and data packets for a particular HNB-GW service (see the *DSCP Template Configuration Mode Commands* chapter).
- To associated a specific DSCP template with a system for a PSP instance in SS7 routing domain, use the **associate-dscp-template downlink** documented in the *SGSN PSP Configuration Mode Commands* chapter.

#### Example

Use a command similar to the following to create a DSCP template with ID *dscp\_london* that can be used specifically for Gb/IP calls from subscribers in London:

```
dscp-template dscp_london
```

Following command creates a DSCP template with ID *dscp\_hnb1* that can be used specifically for HNB-GW services on a chassis:

```
dscp-template dscp_hnb1
```



# dual-address-pdp

This command makes it possible for the operator to enable (default) / disable SGSN support for MS requests for dual PDP type (IPv4v6) addressing.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

**Syntax Description** [ **default** | **no** ] **dual-address-pdp**

## default

Enables dual PDP type address support.

## no

Disables the default behavior so that the SGSN does not honor requests for dual PDP type addresses.

## Usage Guidelines

With release 12.2 and in accordance with 3GPP Release 9.0 specifications, by default the SGSN honors the MS/UE request for dual PDP type addressing (IPv4v6) for PDP context association with one IPv4 address and one IPv6 address/prefix. This support can be disabled by configuration.



### Important

For the dual PDP addressing feature to function, **common-flags** must be enabled with the **gptc send** command in the SGTP service configuration mode *prior* to enabling the feature with the **dual-address-pdp** command.

With this default behavior, the operator has multiple options to refine the level of support for dual PDP type addressing through the use of several related commands.

- **dual-address-pdp** command in the RNC configuration mode disables SGSN support for dual PDP type addressing for a specific RNC that either does or does not support this type of addressing..
- **pdp-type-ipv4v6-override** in the APN profile configuration mode allows the SGSN to override the MS/UE request for dual PDP type addressing.
- Using the **dual-ipv4v6** keyword with the **wildcard-apn pdp-type** command in the APN remap table configuration mode enables the operator to configure a default APN with a wildcard subscription with PDP type IPv4v6.

## Example

Use the following command to disable support for dual PDP type addressing (IPv4v6):

**no dual-address-pdp**

If dual PDP addressing has been disabled, to reenable the feature, move to the SGTP service configuration mode, in the appropriate context, to perform the following as the *first* command needed to re-enable support for dual PDP type addressing in the configuration:

**gtpc send common-flags**

Now in the SGSN global configuration mode, use the following as the second command required to re-enable support for dual PDP type addressing in the configuration:

**dual-address-pdp**

## ec-gsm

This command enables extended coverage class support on the SGSN.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

**Syntax**

[ no ] **ec-gsm**

**no**

Disables EC-GSM support on the SGSN.

---

**Usage Guidelines**

Use this command to enable EC-GSM for all GPRS services on the SGSN.

# eir-profile

Creates an EIR profile and provides access to the EIR profile configuration mode commands that define the parameters of the profile.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **eir-profile** *profile\_name*  
**no eir-profile** *profile\_name*

**no**

Deletes an EIR profile from the SGSN Global configuration.

***profile\_name***

Enter a unique name for the profile, upto 64 alphanumeric characters in length.

---

**Usage Guidelines** This command creates up to 16 instances of EIR profiles and provides access to the EIR Profile configuration mode for the commands to configure the EIR profile parameters.

## Example

Remove the 'testing' EIR profile from the SGSN Global configuration mode:

```
no eir-profile testing
```

# end

Exits the current mode and returns to the Exec Mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Change the mode back to the Exec Mode.

# exit

Exits the current mode and returns to the previous configuration mode.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Change the mode to the Global Configuration Mode.

## gmm-message

This command configures the SGSN to discard (drop) the Attach-Request message received with a random TLLI already in use.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

**Syntax Description** [ default ] **gmm-message attach-with-tlli-in-use discard-message**

### default

Resets the default function allowing multiple MS, using the same random TLLI, to attempt to Attach simultaneously and disables discarding the Attach-Request message for random TLLI already in use.

### Usage Guidelines

Working with the two related commands (noted below), this command is part of a procedure for handling multiple MS Attaches all with the Same Random TLLI. Use this command to configure the SGSN to allow only one subscriber at a time to attach using a fixed random TLLI.

### Related Commands:

- The **old-tlli invalidate tlli** command configures a list of random TLLI to be invalidated from the GMM after the invalidate old-TLLI timer expires.
- The **old-tlli hold-time** command configures the old-TLLI expiry timer.

### Example

Configure the SGSN to drop Attach Request containing TLLI already in use:

```
gmm-message attach-with-tlli-in-use discard-message
```

# gmm-sm-statistics



---

**Important** This command has been deprecated.

---

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration  
**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **gmm-sm-statistics attach-rejects cause network-failure only-internal**  
**no gmm-sm-statistics attach-rejects**



## gprs-mocn

Enables or disables General Packet Radio Service (GPRS) Multi-Operator Core Network (MOCN). With 2G MOCN, the radio network is shared among different operators, while each operator maintains its separate core network.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration  
**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** [ no ] **gprs-mocn**

**no**

Disables GPRS MOCN when it has been previously enabled.

---

**Usage Guidelines** Use this command to enable 2G MOCN, which is disabled by default.

For complete information about the 2G (GPRS) MOCN feature and its configuration, refer to the *MOCN for 2G SGSN* feature section in the *Serving GPRS Support Node Administration Guide*

### Example

The following command enables GPRS MOCN support for SGSN:

```
gprs-mocn
```

# interface-management

This command creates an interface management configuration and provides access to the SGSN Interface Management configuration mode.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

---

**Syntax Description** **interface-management**

---

**Usage Guidelines** Use this command to access the SGSN Interface Management configuration mode to map NSE-ID and NSE-name to the Gb interface and/or to lock and unlock interface by the NSE/BSC identifier.

## Example

Access the SGSN Interface Management configuration mode:

```
interface-management
```

# ipms-suppress

This command enables suppressing of the specified RAT related ipms event reporting.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description**

```
ipms-suppress [ gprs | umts ]  
no ipms-suppress [ gprs | umts ]
```

**no**

Disables suppressing of the specified RAT related ipms event reporting.

**gprs**

This keyword enables suppressing of 2G related ipms-event reporting to the Intracer.

**umts**

This keyword enables suppressing of 3G related ipms-event reporting to the Intracer.

---

**Usage Guidelines**

This command is configured to suppress or allow the IPMS-event reporting to Intracer for the specified RAT. This CLI command helps the operator to change the IPMS-event reporting and manage network load or congestion on the fly.




---

**Note**

- By default the IPMS event reporting will be done by both the services, provided there is a valid IPMS-context and IPMS-server configured.
  - IPMS suppression can be enabled on both the services (GPRS and UMTS service) at the same time. This provides independent control on the suppression of ipms-events from the GPRS and UMTS services.
- 

**Example**

Use this command to enable suppressing of 2G related ipms-event reporting to the Intracer:

```
ipms-suppress gprs
```

# imsi-range

Configure an IMSI range with an optional PLMN ID to associate with an Operator Policy.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description**

```
imsi-range mcc mcc_num mnc mnc_num { msin first start_number last stop_number [ operator-policy policy_name [ description description ] ] | plmnid plmn_id operator-policy policy_name [ description description ] } + no imsi-range mcc mcc_num mnc mnc_num { msin first start_number last stop_number | plmnid plmn_id }
```

**no**

Using **no** in the command deletes the definition from the SGSN Global configuration.

**mcc** *mcc\_num*

**mcc** defines the mobile country code (MCC) of an IMSI.

*mcc\_num*: Enter a 3-digit number from 100 to 999 - 000 to 099 are reserved.

**mnc** *mnc\_num*

**mnc** defines the mobile network code (MNC) of an IMSI.

*mnc\_num*: Enter a 2 or 3-digit number from 00 to 999.

**msin**

MSIN (mobile subscriber international number) portion of the IMSI.

*first start\_num*: Defines first MSIN prefix number in a range

*last stop\_num*: Defines the last or final MSIN prefix number in a range.

**operator-policy** *policy\_name* **description** *description*

Identify the operator policy that the IMSI range definition and/or the PLMN-ID is to be associated.

*policy\_name* : Enter a string of 1 to 64 alphanumeric characters.

*description*: Enter a string of 1 to 100 alphanumeric characters to provide range clarification for converted Release 9.0 configurations.

Description is just an information field. From release 19.0 onwards the length of the string supported for this field has been reduced, the supported range is now "1" up to "50" alphanumeric characters. The reduction of the supported string size results in improvement in boot up time.

If a PLMN-ID is to be included in the definition, enter the **plmnid** before entering the operator policy name.

### **plmnid plmn\_id**

The 5-6 digit PLMN-ID consists of the MCC (mobile country code) plus the MNC (mobile network code) to identify the public land mobile network (PLMN) for a specific operator. This keyword associates a specific PLMN with this specific SGSN operator policy.

*plmn\_id* : Enter 5 to 6 digits.

+

This symbol indicates that command can be repeated to create repeated definitions.

## Usage Guidelines

An IMSI = maximum of 15 digits. An IMSI consists of the MCC (3 digits) + the MNC (2 or 3 digits) + the MSIN (the remaining 10 or 9 digits depending on the length of the MNC ).

MCC and MNC are the minimum amount of information required to identify a unique operator policy with IMSI filtering. The MCC and MNC combine uniquely to identify the country and the network operator, for example: Cingular Wireless in the United States = **mcc 311mnc 180**

To improve the granularity of call handling, an operator policy with additional IMSI filtering parameters can be defined, to include filtering based on the MSIN, by defining a MSIN range - first (or start-of-range) MSIN and last (or end-of-range) MSIN. The range numbers do not include the maximum allowed for the MSIN but should include a sufficient number to enable the operator policy to filter effectively.

For the most efficient IMSI filter, the operator policy should include all of the above parameters and the PLMN ID which defines the current location of the MS -- this parameter is particularly useful for highlighting which calls are roaming.

And if none of the operator policies contain useful filtering information, then the default operator policy will be applied as the information in this command is never defined for the default operator policy.

The following table will illustrate how these filtering parameters determine which operator policy will govern a call:

<b>Operator Policy ID</b>	<b>MCC</b>	<b>MNC</b>	<b>MSINfirst</b>	<b>MSINlast</b>	<b>PLMN ID</b>
OpPol-1	123	45	67890	67898	
OpPol-2	123	45			
OpPol-3	123	45	67890	67898	23232
OpPol-4	123	45			23232
OpPol-5	123	45	6789012	6789019	
OpPol-6	123	45	6789012	6789019	23232
default					

The filtering selects which operator policy will be used to determine how a call is handled - the operator policy that best matches the IMSI. So, a call with IMSI 123456789012345 PLMNID 23232 is best matched with OpPol-6.

In most cases, the operator policy with the most information defined will be used as a combination of PLMNID and IMSI provides the best match. But OpPol-6 won't always be the best match. Using the table above:

OpPol-1 is the best match for IMSI 12345678901111

OpPol-2 is the best match for IMSI 12345678909999

OpPol-5 is the best match for IMSI 123456789012345 if the PLMNID is 12344

### Example

The following associates operator policy *oppol1* with country code *310*, mobile network code of *33*, and IMSI range *1231234 - 1231244*:

```
imsi-range mcc 310 mnc 33 msin first 1231234 last 1231244 operator-policy  
oppol1
```

# location-services

Enable or 'start' Location Services (LCS) on the SGSN.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description**

**location-services**  
**no location-services**

**no**

Disables or 'stops' LCS on the SGSN.

---

**Usage Guidelines**

By default, Location Services is not enabled on the SGSN. This command is mandatory to enable the SGSN to support LCS, which is a license-controlled feature. Multiple other commands are required to configure LCS functionality. For more information about the operation and configuration of LCS on the SGSN, refer to the *Location Services* section of the *SGSN Administration Guide*.

**Example**

Use the following command to disable Location Services once they have been enabled:

```
no location-services
```

## map-message

This command instructs the SGSN to ignore the CAMEL subscription when there is no CAMEL service associated or in existence.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

**Syntax Description** **map-message insert-subscriber-data csi-handling when-camel-not-associated ignore-subscription**  
**default map-message insert-subscriber-data csi-handling**

### default

Resets the SGSN's default behavior. By default, the SGSN validates the CAMEL subscription and rejects an Attach Request when there is no CAMEL service association.

**Usage Guidelines** By default, the SGSN updates the the CAMEL subscription included in the INSERT-SUBSCRIBER-DATA (ISD) messages received from the HLR. While processing the ATTACH request from the CAMEL subscriber, the SGSN checks whether it has a CAMEL service associated with the corresponding service (either GPRS service or SGN service). It drops the ATTACH request if there is no CAMEL service associated with a corresponding service.

Also by default, the SGSN does not allow establishment of a Direct Tunnel (DT) for a CAMEL subscriber. It strictly validates the subscriber against the CAMEL subscription during the Direct Tunnel setup procedure.

This command enables the operator to control the behavior of the SGSN by configuring the SGSN to ignore the CAMEL subscription. This allows the SGSN to successfully complete an ATTACH procedure when there is an ATTACH Request from a CAMEL subscriber and there is no CAMEL service association in the SGSN. As well, during the Direct Tunnel establishment, validation of the CAMEL subscription is ignored to allow the DT to setup when there is no CAMEL service association in the SGSN.

### Example

Instruct the SGSN to validate the CAMEL subscription:

```
default map-message insert-subscriber-data csi-handling
```



# max-pending-attaches

Configure the maximum length of the pending attach queue.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description**

**max-pending-attaches** *limit*  
**default max-pending-attaches**

**default**

Resets the SGSN's Attach queue to a maximum pending value of 10,000.

**limit**

Set the a maximum limit to the pending Attach/RAU messages queue in the LinkMgr. When the limit is reached a message is sent to the IMSIMgr.

*limit* : Enter an integer from 5000 - 50000. Default is 10000.

---

**Usage Guidelines**

With this command, configure the maximum limit to the pending ATTACH/RAU messages queue in the LinkMgr. When the limit is reached, the LinkMgr sends the Query/Forward messages to the IMSIMgr.

As the IMSIMgr gets busier and does not responded to Query/Forward requests, the response to the requests will get slower and slower and the queue size continues inflating if the incoming message rate is high. To avoid this situation, set the **max-pending-attaches** for the pending queue for Attach and RAU messages. All other messages from the HLR will be added to the queue as they cannot be dropped. High and low watermarks are set to the queue at 80% of **max-pending-attaches** " and 60% of **max-pending-attaches** respectively.

Once a high watermark is reached, the new Attach and RAU requests are dropped and relevant statistics are incremented. Once a low watermark is hit, the new Attach/RAU requests are accepted and added to the pending queue. The entries are added to the pending queue only when the window-size between IMSIMgr and LinkMgr becomes zero. This is a very rare occurrence and will not affect the current behavior in normal circumstances.

**Example**

Set the queue length to a maximum of *15000* requests:

```
max-pending-attaches 15000
```

## msisdn-group

This command configures the Mobile Subscriber Integrated Services Digital Network (MSISDN) group to which the operator policy should be associated.

---

**Product** SGSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **msisdn-group** *group\_name* **operator-policy** *policy\_name*  
**no msisdn-group** *group\_name*

**no**

Deletes the configured MSISDN group.

**msisdn-group** *group\_name*

Specifies the MSISDN group name to which the operator policy should be associated. *group\_name* must be an alphanumeric string of 1 through 64 characters. It can have a maximum of 50 groups.

**operator-policy** *policy\_name*

Specifies the operator policy to which the IMSI range should be associated with.

*policy\_name* must be an alphanumeric string of 1 through 64 characters.

---

**Usage Guidelines** Use this command to specify the MSISDN group to which the operator policy should be associated.

# msisdn-range

This command configures the MSISDN range to which operator policy should be associated.

---

**Product** SGSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **msisdn-range cc** *cc\_value* **number first** *start\_range* **last** *end\_range* **operator-policy** *policy\_name*  
**no msisdn-range cc** *cc\_value* **number first** *start\_range* **last** *end\_range* **operator-policy** *policy\_name*

**no**

Deletes the specified MSISDN numbers.

**cc** *cc\_value*

**cc** is the country code of MSISDN. *cc\_value* is a 1 to 3 digit number.

**number first** *start\_range* **last** *end\_range*

Specifies the start and end of MSISDN (combination of Country Code (CC), National Destination Code (NDC) or Number Planning Area (NPA), and Subscriber Number (SN)).

**operator-policy** *policy\_name*

Specifies the operator policy to which the IMSI range should be associated with.

*policy\_name* must be an alphanumeric string of 1 through 64 characters.

---

**Usage Guidelines** Use this command to configure the MSISDN range to which operator policy should be associated.

## Example

The following command configures the MSISDN with CC as *334* and MSISDN range as *918369110173* and *918369110184*, and then associates with operator policy *OPI*:

```
msisdn-range cc 334 number first 918369110173 last 918369110184
operator-policy opi
```

# old-tlli invalidate tlli

This command configures a list of random TLLI to be invalidated (removed) from the GMM after the invalidate old-TLLI timer expires.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** [ no ] **old-tlli invalidate tlli** < hexadecimal >

**no**

Removes a single random TLLI from the configured list.

< *hexadecimal* >

Identifies a single random TLLI to be removed from the GMM after the old-TLLI timer expires.

---

**Usage Guidelines** Use this command to create a list of up to 50 random TLLI to be dropped from the GMM after the old-TLLI timer expires. This command also starts the invalidate old-TLLI timer.




---

**Important**

If the old-TLLI expiry timer is not configured with the **old-tlli hold-time** command, then the SGSN will only drop second Attach Requests using the same random TLLI already in use.

---

**Related Commands:**

- The **gmm-message** configures the SGSN to discard (drop) the Attach-Request message received with a random TLLI already in use
- The **old-tlli hold-time** command configures the old-TLLI expiry timer.

**Example**

Add random TLLI *0x7f05a30a* to the Invalidate List:

```
old-tlli invalidate tlli 0x7f05a30a
```

# old-tlli hold-time

This command configures the old-TLLI expiry timer to be started in GMM when anyone of the listed random TLLI are received.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** [ **default** ] **old-tlli hold-time** < *seconds* >

**default**

Resets the timer to 5 seconds

< **seconds** >

Sets the numbers of seconds before the timer expires; range 1 to 125.

---

**Usage Guidelines**

Use this command to configure the old-TLLI expiry timer to be started in GMM when anyone of the listed random TLLI are received. If the timer expires prior to receiving Attach-Complete then the SGSN invalidates (removes) the TLLI from the GMM.



---

**Important**

For this configuration to work, the list of random TLLI to be removed (invalidated) from the GMM must be defined with the **old-tlli invalidate tlli** command.

---

**Related Commands:**

- The **gmm-message** configures the SGSN to discard (drop) the Attach-Request message received with a random TLLI already in use
- The **old-tlli invalidate tlli** command configures the random invalidate TLLI list.

**Example**

Set the timer for 2 seconds:

```
old-tlli hold-time 2
```

# pdp-deactivation-rate

Set the rate the SGSN deactivates PDP connections per second per SessMgr when GTP-C path failure is detected. Beginning with release 15.0, this command is also supported on the S4-SGSN.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

**Syntax Description** **pdp-deactivation-rate { connected-ready *rate* | idle-standby *rate* }**  
**default pdp-deactivation-rate { connected-ready | idle-standby }**

## default

If this keyword is used with the command, then the default deactivation rates are used.

## connected-ready *rate*

Subscribers that are in the PMM-Connected / GPRS-Ready state and actively using the SGSN service need to be deactivated at a faster rate to facilitate the deactivation/re-activation process.

*rate* -sets the number of subscribers to be deactivated per second per SessMgr and the valid range is 1 to 1000 and the default is 760 connected-ready subscribers deactivated per second.

## idle-standby *rate*

Subscribers that are in the PMM-Idle / GPRS-Standby state are not actively using the SGSN service and can be deactivated at a slower rate. The deactivation process for idle-standby subscribers includes paging before the Deactivate Request is sent.

*rate* - sets the number of subscribers to be deactivated per second per SessMgr and the valid range is 1 to 1000 and the default is 240 idle-standby subscribers deactivated per second.

## Usage Guidelines

Use this command to define a rate at which the SGSN processes PDP deactivations when a GTP-C path failure is detected (and confirmed according to the SGSN's default behavior). The operator can use this command to set a deactivation rate that ensures radio network congestion is avoided.

### Related commands:

- **max-remote-restart-counter-change** - allows the operator to set a maximum variance between stored and received values for restart counter changes coming from the GGSN. For details, refer to the SGSN Global configuration mode documentation.
- **disable-remote-restart-counter-verification** - allows the operator to disable the default behavior. For details, refer to this command in the SGSN Global configuration mode documentation.

**Example**

Use the following command to deactivate PDP connections for *600* PMM-Connected / GPRS-Ready subscribers per second:

```
pdp-deactivation-rate connected-ready 600
```

Use the following command to deactivate PDP connections for *320* PMM-Idle / GPRS-Standby subscribers per second:

```
pdp-deactivation-rate idle-standby 320
```

Use the following command to reset the default *760* per second deactivation rate for PMM-Connected / GPRS-Ready subscribers:

```
default pdp-deactivation-rate connected-ready
```

# qos-arp-rp-map-profile

This command creates an instance of an ARP-RP Mapping Profile and/or access the ARP-RP Mapping Profile configuration mode commands.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

**Syntax Description** **qos-arp-rp-map-profile** *arp-rp\_prof\_name*  
**no qos-arp-rp-map-profile** *arp-rp\_prof\_name*

**no**

Removes the specified ARP-RP Map Profile from the SGSN Global configuration.

***arp-rp\_prof\_name***

Enter a string of 1 to 64 alphanumeric characters to identify the mapping profile and moves into the ARP-RP mapping profile configuration mode. The ARP-RP Map Profiles need to be associated with the SGSN and/or GPRS Services.

## Usage Guidelines

Using the ARP to RP mapping, the SGSN can choose a preferred radio priority according to the ARP values sent by the GGSN and HLR. As well, these mappings will be used by corresponding 2G and/or 3G services to choose the radio priority value while triggering messages (such as those listed below) towards the MS/UE:

- Activate PDP Accept.
- Modify PDP Request during network-initiated PDP modification procedure.
- Modify PDP Accept during MS-initiated PDP modification procedure provided the ARP has been changed by the network.

The profiles will be populated via the **arp** command under the ARP-RP Map Profile configuration mode.

## Example

Create an ARP-RP Map Profile named *arprpmap1* using the following command:

```
qos-arp-rp-map-profile arprpmap1
```



# ranap excess-len ignore

Configure the SGSN to ignore excess length of received RANAP messages.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration  
**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** [ **default** | **no** ] **ranap excess-len ignore**

## **default**

Resets the default behavior - a decode error is generated when received RANAP messages are more than an extra octet in length.

## **no**

Disables the configuration to ignore overly long RANAP messages.

---

**Usage Guidelines** By default, the SGSN issues a decode error when the RANAP messages include extra octets. Use this command to ignore RANAP messages that have excess octets.

## **Example**

Use the following command to enable the SGSN to ignore overly long RANAP messages:

```
ranap excess-len ignore
```

Use the following command to disable ignoring of RANAP messages that are excessive in length:

```
no ranap excess-len ignore
```

# ran-information-management

Enable/disable RAN information management (RIM) support for the SGSN.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global) #
```

---

**Syntax Description**

**[ default | no ] ran-information-management**

**default**

Resets the default so RIM is disabled.

**no**

Disables the RIM support in the configuration file.

---

**Usage Guidelines**

By default, handling of RAN information management (RIM) messages is disabled. This command enables the SGSN to handle RIM messages. When this command is enabled and RIM message handling is enabled on the destination node, then RIM PDUs will be forwarded to the BSC/RNC. If RIM message handling is not enabled on both nodes, then the RIM PDUs will be dropped silently.

Confirm RIM configuration with the **show sgsn-mode** command in the Exec mode.

**Example**

Use the following command to enable RIM support:

```
ran-information-management
```

Use the following command to disable RIM support that has been added to the configuration:

```
no ran-information-management
```

# target-offloading

Selects the subscriber offloading algorithm to be applied to the SessMgr and the IMSIMgr.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description**

```
target-offloading algorithm [ optimized-for-speed |
optimized-for-target-count ]
default target-offloading algorithm
```

**default**

Resets the configuration to default values.

**optimized-for-speed**

Enables faster algorithm to achieve the target count.

**optimized-for-target-count**

Enables a reliable algorithm to achieve the target count.

Default.

---

**Usage Guidelines**

With the SGSN's distributed architecture, there are many SessMgrs and offloading will happen in parallel at all SessMgrs. This command enables the operator to control the total number of subscribers being offloaded.




---

**Important**

The value for this command can not be altered once dynamic offloading has begun - refer to the command description for the **sgsn-offload** command in the *Exec Mode* chapter..

---

**Example**

Set the SGSN to use the faster algorithm for offloading:

```
target-offloading algorithm optimized-for-speed
```

## tlli-cb-audit

This command enable (default is disabled) or disables a periodic (hourly) audit of TLLI-CBs in the BSSGP layer.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **tlli-cb-audit**  
[ **default** | **no** ] **tlli-cb-audit**

### default

Include **default** with the command to disable the audit function.

### no

Include **no** with the command to disable the audit function.

---

### Usage Guidelines

This command is used to clean-up hanging or unassociated TLLI in the BSSGP layer. This configuration defined with this command will be common to all NSE configured for this SGSN.

Independent of this command configuration, the SGSN triggers and audit when the number of TLLI-CBs reaches 35,000.

### Example

Use the following command to enable the hourly audit for unassociated TLLI-CBs:

```
tlli-cb-audit
```

## umts-aka-r99

This command enables the operator to authenticate mobile equipment (MEs) with R99+ USIMs and capable of UMTS AKA.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SGSN Global Configuration

**configure > sgsn-global**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-global)#
```

---

**Syntax Description** **umts-aka-r99**  
**no umts-aka-r99**

**no**

Including **no** with the command disables the authentication.

---

**Usage Guidelines** This command enables operators to authenticate MEs that are attempting to connect to a 2.5G network with R99+ USIMs if the MEs are UMTS AKA capable. For R99 mobiles, the SGSN will continue to perform GSM AKA even if quintuplets are received from the HLR.

### Example

Use the following command to disable UMTS AKA authentication for MEs with R99+ USIMs:

```
no umts-aka-r99
```





## SGSN Interface Management Configuration Mode

---

### Command Modes

The interface management commands, accessed via the SGSN Global configuration mode, are applicable to the SGSN on a global level. They map the NSC/BSC to the SGSN's Gb interface and enable the operator to quickly configure lock or unlock for the BSC interface on the basis of the NSE's ID or name.

Exec > Global Configuration > SGSN Global Configuration > Interface Management Configuration

**configure > sgsn-global > interface-management**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-interface-mgmt) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show, on page 472](#)
- [end, on page 473](#)
- [exit, on page 474](#)
- [interface, on page 475](#)
- [lock-interface, on page 477](#)
- [paging-rlf-template, on page 478](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---



# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Return to the Exec mode.

# exit

Exits the current configuration mode and returns to the SGSN Global configuration mode.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Returns to the SGSN Global configuration mode.

# interface

Maps the Gb interface to an NSE-ID and an NSE-name to facilitate the identification of the peer NSE/BSC. This command also allows the SGSN to configure the mapping between RNC-ID and RNC-NAME which allows the operator to associate rlf-template either by NAME or ID.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; SGSN Global Configuration &gt; Interface Management Configuration

**configure > sgsn-global > interface-management**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-interface-mgmt)#
```

---

**Syntax Description**

```
interface { gb peer-nsei id | iu peer-rnc id } { name <value> | id <value>
}
no interface{ gb peer-nsei id | iu peer-rnc id } { name <value> | id <value>
}
```

**no**

Removes the interface mapping from the configuration.

The "No" option removes the mapping and action configuration from the SGSN and it resets the behavior to default for that RNC. By default, no throttling is done.

**gb peer-nsei id id**

Maps a specific peer NSE/BSC to the Gb interface by the NSEI.

*id* - Enter an integer from 0 to 65535.

**gb peer-nsei name**

Identifies a BSC by name assigned to the NSEI, which is stored in the SCT.

*name* - Enter an alphanumeric string of 1 to 64 characters.

**iu peer-rnc id id**

Maps a specific peer RNC-ID .

*id* - Enter an integer from 0 to 65535.

**iu peer-rnc name**

Maps a specific peer RNC-Name.

*name* - Enter an alphanumeric string of 1 to 64 characters.

---

**Usage Guidelines**

This command configures mapping between an NSE-ID and an NSE name and the SGSN's Gb interface. The mapping allows the operator to use the **lock-interface** command (also in this mode) to more easily configure locking or unlocking of the interface to the BSC by identifying the network service entity by ID or by name.

This command provides a configuration option to create a mapping for RNC to the interface name for the interface identifier which allows the operator to associate rlf-template either by using name or identifier.

**Related Commands:**

**lock-interface**

**Example**

Map NSE with ID of *422* and the name *Dover* to the Gb interface:

```
interface gb peer-nsei id 422 name Dover
```

The following example disables the mapping for NSEI *2321*:

```
no interface gb peer-nsei id 2321
```

# lock-interface

This command enables the operator to configure the SGSN's Gb interface, toward the peer NSE/BSC, as locked or unlocked on the basis of the NSE's name or identifier.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SGSN Global Configuration > Interface Management Configuration

**configure > sgsn-global > interface-management**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-interface-mgmt)#
```

**Syntax Description** [ no ] **lock-interface gb peer-nsei { id nse-id | name nse\_name }**

**no**

Disables a previously configured lock on the interface to the NSE/BSC.

**peer-nsei id nse\_id**

Specifies the numeric identifier of the network service entity mapped to the Gb interface.

*nse\_id* - Enter an integer from 0 to 65535.

**peer-nsei nsei\_name**

Specifies the name of the NSE associated with the BSC, which is stored in the SCT.

*nse\_id* - Enter an alphanumeric string of 1 to 64 characters.

## Usage Guidelines

This command allows the operator to lock/unlock the interface, towards the NSE/BSC, based on the NSE name or NSE identifier.

Lock is configured primarily to avoid the high CPU usage the SGSN can experience when BSCs attempt to reconnect after an SGSN reboot or reload. The lock stops the auto-learn procedure for the locked BSC connected via Gb over IP.

The auto-learn facility can be enabled in a staggered manner for each BSC after reboot/reload by unlocking the BSCs one-by-one.

The NSE unlock state is the default state and the NSE can accept or send any uplink and downlink data.

### Related Commands:

**interface**

### Example

Lockout NSE/BSC ID 319 from the SGSN:

```
lock-interface gb peer-nsei id 319
```

# paging-rlf-template

This command allows the SGSN to associate the RLF template either at global level which limits the paging messages initiated across both 2G (NSE level) and 3G (RNC level) access or at per entity level either at RNC level for 3G access or at NSE level for 2G access.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; SGSN Global Configuration &gt; Interface Management Configuration

**configure > sgsn-global > interface-management**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sgsn-interface-mgmt)#
```

---

**Syntax Description**

```
[no] paging-rlf-template {template-name <template-name>} {gb peer-nsei | iu peer-rnc} {name <value> | id <value>}
```

**no**

The "No" option removes the association of the rlf-template against the global level or at particular NSE/RNC.

**template-name <template-name>**

Specifies the template name.

**gb peer-nsei id**

Maps a specific peer NSE/BSC to the Gb interface by the NSEI.

*id* - Enter an integer from 0 to 65535.

**gb peer-nsei name**

Identifies a BSC by name assigned to the NSEI, which is stored in the SCT.

*name* - Enter an alphanumeric string of 1 to 64 characters.

**iu peer-rnc id**

Maps a specific peer RNC-ID .

*id* - Enter an integer from 0 to 65535.

**iu peer-rnc name**

Maps a specific peer RNC-Name.

*name* - Enter an alphanumeric string of 1 to 64 characters.

---

**Usage Guidelines**

This command helps to limit the paging load sent out from the SGSN as it consumes more bandwidth in the radio interface. The NSE/RNC level rlf-template association overrides the globally associated rlf-template

which throttles the paging messages initiated from that NSE/RNC with the configured message rate. The actual RLF template can be configured under the global configuration mode which provides the option to configure the message-rate, burst-size, threshold and delay-tolerance for throttling or rate-limiting.

### Example

Use the following command to associate a RLF template with name "rlf1":

```
paging-rlf-template template-name rlf1
```







## SGSN Pool Area Configuration Mode Commands

---

### Command Modes

The Pool Area configuration mode configures the parameters used to setup the VLRs to use with a pool area in a Gs service.

Exec > Global Configuration > Context Configuration > Gs Service Configuration > Pool Area Configuration

**configure** > **context** *context\_name* > **gs-service** *service\_name* > **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-gs-pool-area)#
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show, on page 482](#)
- [end, on page 483](#)
- [exit, on page 484](#)
- [hash-value, on page 485](#)
- [lac, on page 487](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Return to the Exec mode.

# exit

Exits the current configuration mode and returns to the previous configuration mode.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Return to the previous configuration mode.

# hash-value

This command configures the load distribution for the VLRs that service this pool area.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Gs Service Configuration > Pool Area Configuration

**configure** > **context** *context\_name* > **gs-service** *service\_name* > **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-gs-pool-area)#
```

---

**Syntax Description**

```
hash-value { hash_value | non-configured-values | range start_value to end_value
} use-vlr vlr_name
```

```
no hash-value { hash_value | non-configured-values | range start_value to
end_value }
```

**no**

Removes the configured Gs procedures from this Gs service.

***hash\_value***

Specifies the specific hash value for VLR(s).

*hash\_value* must be an integer value from 0 through 999.

***range start\_value to end\_value***

Specifies the range of hash values for a VLR.

*start\_value* specifies the start value for range of hash and is an integer value from 0 through 999. *start\_value* must be lower than *end\_value*.

*end\_value* specifies the end value for range of hash and is an integer value from 0 through 999. *end\_value* must be higher than *start\_value*.

**non-configured-values**

This keyword assign all non-configured hash values to use the named VLR.

***use-vlr vlr\_name***

Specifies the name of the VLR to be associated with this pool area.

*vlr\_name* is the name of VLR and must be an alpha and/or numeric string of 1 to 63 characters.

---

**Usage Guidelines**

Use this command to command configures the load distribution for the VLRs that service this pool area as defined in TS 23.236.

The algorithm for selection of VLR from a pool area is based on the hash value computed on the IMSI digits. The SGSN derives a hash value (V) using procedure as defined in TS 23.236. Every hash value from the range 0 to 999 corresponds to a single MSC/VLR node. Typically many hash values may point to the same MSC/VLR node.

This command can be entered multiple times for different hash value.

### Example

Following command configure the all non configured hash values to use VLR named *starv1r1* in this pool area:

```
hash-value non-configured-values use-vlr starv1r1
```

# lac

This command defines a set of location area code (LAC) values for a pool area.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Gs Service Configuration > Pool Area Configuration

**configure** > **context** *context\_name* > **gs-service** *service\_name* > **pool-area** *pool\_area\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-gs-pool-area)#
```

---

**Syntax Description**

**lac** *lac\_id* +  
**no lac** *lac\_id*

**no**

Removes the configured LAC value from this pool area configuration.

**lac** *lac\_id*

Specifies the subscribers' location area code (LAC) to be associated with this pool area and a specific VLR. This LAC is obtained from the radio area identity (RAI).

*lac\_id*: Must be an integer from 1 through 65535.

+

More than one *lac\_id*, separated by a space, can be entered within a single command.

---

**Usage Guidelines**

Use this command to specify a set of LACs to use for a pool area.

This command can be entered multiple times, subject to a limit of 32 LAC definitions (total for **non-pool-area** and **pool-area** configuration) per Gs service.




---

**Important**

LAC values across multiple pool areas and non-pool-areas must be unique within the Gs service.

---

**Example**

The following command configures LACs *101*, *301*, and *222* for the pool area.

```
lac 101 301 222
```

lac





## SGSN PSP Configuration Mode Commands

### Command Modes

The Peer-Server Process (PSP) configuration mode provides the commands to create, configure, bind, and manage a specific PSP instance included in an SS7 routing domain configuration.

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server** *id id* > **psp** **instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [associate](#), on page 491
- [do show](#), on page 493
- [end](#), on page 494
- [end-point](#), on page 495
- [exchange-mode](#), on page 497
- [exit](#), on page 498
- [psp-mode](#), on page 499
- [routing-context](#), on page 500
- [sctp-alpha](#), on page 502
- [sctp-beta](#), on page 503
- [sctp-checksum-type](#), on page 504
- [sctp-cookie-life](#), on page 505
- [sctp-init-rwnd](#), on page 506
- [sctp-max-assoc-retx](#), on page 507
- [sctp-max-data-chunks](#), on page 508
- [sctp-max-in-strms](#), on page 509
- [sctp-max-init-retx](#), on page 510
- [sctp-max-mtu size](#), on page 511
- [sctp-max-out-strms](#), on page 512

- [sctp-max-path-retx](#), on page 514
- [sctp-parameter](#) , on page 515
- [sctp-rto-initial](#), on page 516
- [sctp-rto-max](#), on page 517
- [sctp-rto-min](#), on page 518
- [sctp-sack-frequency](#), on page 520
- [sctp-sack-period](#), on page 521
- [sctp-suppress-alarm](#), on page 522
- [shutdown](#), on page 524
- [timeout](#), on page 525

# associate

Defines an association between the PSP instance and an application server process (ASP) instance and/or a DSCP marking template.



## Important

In Release 20 and later, HNBN is not supported. This command must not be used for HNBN in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server** *id* > **psp** **instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

## Syntax Description

**associate** { **asp** **instance** *asp\_num* | **dscp-template** **downlink** *template\_name* }  
**no associate** [ **asp** | **dscp-template** **downlink** ]

**no**

Removes the association, between the PSP and the ASP or the DSCP marking template, from the routing domain configuration.



## Important

Using the **no associate** command will most likely result in the termination of all current subscriber sessions active through the peer-server.

### **asp** **instance** *asp\_num*

Identifies a specific ASP configuration. Up to four ASP instances can be configured for a single SS7 routing domain.

*asp\_num* is a digit from 1 to 4.

### **dscp-marking** **downlink** *template\_name*

Identifies a specific DSCP marking template to associate with this PSP configuration.

*template\_name* is a string of 1 to 64 characters, including letters, digits, dots (.), dashes (-), and forward slashes (/), to identify a unique instance of a DSCP template. For more information about DSCP marking templates, refer to the *DSCP Template Configuration Commands Mode* chapter.

The DSCP marking template provides a mechanism enabling the SGSN to perform differentiated services code point (DSCP) marking of control packets and signaling messages at the SGSN's M3UA level on the Gb interface. This DSCP marking feature enables the SGSN to perform classifying and managing of network traffic and to determine quality of service (QoS) for the interfaces to an IP network

While enabling DSCP marking of SCTP (control packets) on HNB-GW only **associate dscp-template downlink *template\_name*** command is applicable. This command is used to provides a mechanism enabling the HNB-GW to perform differentiated services code point (DSCP) marking of control packets and signaling messages at the HNB-GW. This DSCP marking feature enables the HNB-GW to perform classifying and managing of network traffic and to determine quality of service (QoS) for the interfaces to an IP network

### Usage Guidelines

Use this command to create an association between a specific peer-server process (PSP) and a specific application server process (ASP) instance or a specific differentiated services code point (DSCP marking template).

Before using the **associate** command, the values for the **psp-mode** and **end-point** commands must be configured.

Before using the **associate** command, the M3UA end-point of the ASP must be configured. Use the commands defined in the *ASP Configuration Mode* chapter of the *Command Line Interface Reference*.

While enabling DSCP marking of SCTP (control packets) on HNB-GW only **associate dscp-template downlink *template\_name*** command is applicable. For more information about DSCP marking templates, refer to the *DSCP Template Configuration Commands Mode* chapter.

### Example

Associate this PSP instance with ASP configuration instance 2 :

```
associate asp instance 2
```

Use the following command to terminate all associations with this PSP instance:

```
no associate
```

Associate this PSP instance with a DSCP marking template identified as *dscptempl* :

```
associate dscp-template downlink dscptempl
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

end

# end

Exits the configuration mode and returns to the Exec mode.

**Product** All

**Privilege** Security Administrator, Administrator

**Syntax Description** end

**Usage Guidelines** Change the mode back to the Exec mode.

# end-point

This command defines or deletes the IP address to be associated with the local SCTP end-point for the application server process (ASP).



## Important

In Release 20 and later, HNBN is not supported. This command must not be used for HNBN in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

## Syntax Description

**end-point** { **address** *ip\_address* | **port** *port\_number* }  
**no end-point** [ **address** *ip\_address* ]

**no**

Removes the ASP end-point association configuration from the PSP configuration.



## Important

This command can not be used as long as the PSP and the ASP are associated. Use the **no associate** command when entering any form of this command, including **no end-point**. When the change is made, re-enter the ASP association with the **association** command.

**address** *ip\_address*

Specifies the IP address for the ASP end-point.

*ip\_address*: Must be defined using the standard IPv4 dotted decimal notation or the colon notation of IPv6.

**port** *port\_number*

Configures the M3UA's SCTP port number for the end-point.

*port\_number*: Must be an integer from 1 to 65535.

Default: 2905.

**Usage Guidelines**

Use this command to manage the ASP end-point. At least one address needs to be configured for the ASP before the end-point can be associated with the PSP.

**Example**

Set the ASP end-point to IP address *192.168.1.1* with the following command:

```
end-point address 192.168.1.1
```



# exchange-mode

Configures the exchange-mode for the PSP communication.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server** *id id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**exchange-mode** [ **double-ended** | **single-ended** ]

**double-ended**

A double exchange of ASPTM and ASPSM messages would typically be needed to change the IPSP states. Either end can request the change and the state changes if the other end acknowledges.

With this configuration, the connections in each direction are managed independently so one could be closed while the other remains active.

**single-ended**

Only a single exchange of ASPTM and ASPSM messages is needed to change the IPSP state. Either end can request the change and the state changes if the other end acknowledges.

---

**Usage Guidelines**



---

**Important**

Before using this command to set a value or reset the default, you must disassociate the PSP instance with the **no associate** command. When you have modified your configuration with this command, then use the **associate** command to setup a new ASP association.

Use this command to toggle the exchange modes for the PSP to match the exchange mode supported by the ASP. The exchange mode specifies what type of ASP messages exchange is used in an IPSP communication.

The **exchange-mode** must be configured for 'single-ended' if the **psp-mode** has been configured for 'client'.

**Example**

Change the exchange mode from the standard double-ended to single-ended:

```
exchange-mode single-ended
```

# exit

Exits the current configuration mode and moves to the previous configuration mode.

**Product** All

**Privilege** Security Administrator, Administrator

**Syntax Description** `exit`

**Usage Guidelines** Return to the Peer-Service configuration mode.

# psp-mode

Configures either client-mode or server-mode as the PSP's operational mode.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure > ss7-routing-domain *routing\_domain\_id* variant *variant\_type* > peer-server id *id* > psp instance *psp\_instance***

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-ppsp-psp_instance)#
```

## Syntax Description

**psp-mode { client | server }**

### client

The PSP operates as a client.

### server

The PSP operates as a server.

## Usage Guidelines



## Important

Before using this command to change the configuration, you must disassociate the PSP instance with the **no associate** command. When you have modified your configuration with this command, then use the **associate** command to setup a new ASP association.

Instruct the peer-server process to operate in either client or server mode.

## Example

Configure the PSP to operate in server mode:

```
psp-mode server
```

# routing-context

Configures the behavior of the routing context in M3UA messages.



## Important

In Release 20 and later, HNBNW is not supported. This command must not be used for HNBNW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN

HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

## Syntax Description

```
routing-context { discard-inbound | process-inbound | m3ua-data {  
insert-outbound | suppress-outbound } }  
default routing-context
```

### default

Include this keyword with the command, to reset the configuration to the system default for routing-context which is a combination of process-inbound and insert-outbound.

### discard-inbound

Sets the routing context received in M3UA messages to be discarded.

### process-inbound

Sets the routing context received in M3UA messages to be processed.

### m3ua-data

This keyword controls the insertion of routing context in outbound M3UA data messages. The default behavior is to insert routing context in management messages and suppress routing context in data messages.

### insert-outbound

Sets the routing context so that it is added in the M3UA messages.

### **suppress-outbound**

Sets the routing context so that it is suppressed in the M3UA messages.

---

#### **Usage Guidelines**



---

##### **Important**

Before using this command to change the configuration or reset the default, you must disassociate the PSP instance with the **no associate** command. When you have modified your configuration with this command, then use the **associate** command to setup a new ASP association.

---

In PSP (singled-ended) configuration mode, the settings for both the local routing context (the SGSN's routing context) and the peer routing context (the RNC's routing context) should be the same. If the routing contexts created at the SGSN and on the peer are different then this can cause the M3UA link to fail.

Routing context is an optional parameter when an M3UA association has only one associated peer-server.

#### **Example**

If the peer does not support routing context, then disable the routing context feature:

```
routing-context discard-inbound suppress-outbound
```

# sctp-alpha

This stream control transmission protocol (SCTP) retransmission time out (RTO) parameter defines the RTO-Alpha value.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description** **sctp-alpha** *value*  
**default** **sctp-alpha**

### **value**

Defines a percentage (%) that represents the RTO portion of the round-trip time (RTT) calculation. This percentage value must be an integer between 0 and 65535.

### **default**

Resets the **sctp-alpha** to the default value of 5%.

---

### **Usage Guidelines**

**sctp-alpha** is used in conjunction with other commands, such as the **sctp-beta** command, to determine the round-trip time (RTT) calculations. The Alpha parameter is used to manage load balancing within the SS7 environment for multi-homed peers.




---

### **Important**

Before using this command to set a value or reset the default, you must disassociate the PSP instance with the **no associate** command. When you have modified your configuration with this command, then use the **associate** command to setup a new ASP association.

---

### **Example**

Set the SCTP RTO-Alpha value to 256% of the RTT calculation:

```
sctp-alpha 256
```

# sctp-beta

This stream control transmission protocol (SCTP) retransmission time out (RTO) parameter defines the RTO-Beta value.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description** **sctp-beta** *value*  
**default sctp-beta**

### **value**

Defines a percentage (%) that represents the RTO portion of the round-trip time (RTT) calculation. This percentage value must be an integer between 0 and 65535.

### **default**

Resets the **sctp-beta** to the default value of 10%.

---

### Usage Guidelines

Use this command in conjunction with other commands, such as the **sctp-alpha** command, to determine the round-trip time (RTT) calculations. The Beta parameter is used to manage load balancing within the SS7 environment for multi-homed peers.




---

### Important

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

### Example

Set the SCTP RTO-Alpha value to 512% of the RTT calculation:

```
sctp-beta 512
```

# sctp-checksum-type

This command selects the type of checksum algorithm to be used.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

```
sctp-checksum-type { adler32 | crc32 }
default sctp-checksum-type
```

**adler32**

Selects the Adler-32 type of algorithm as a faster checksum function.

**crc32**

Selects the CRC-32, a slower but more reliable 32-bit cyclic redundancy check.

**default**

Resets the **sctp-checksum-type** to the default of CRC-32.

---

**Usage Guidelines**

Use this command to set which type of checksum algorithm the SGSN is to use to validate SCTP packets.




---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

Set the checksum type for *CRC32*:

```
sctp-checksum-type crc32
```



# sctp-cookie-life

This command sets the Sctp valid cookie life.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**sctp-cookie-life** *value*  
**default sctp-cookie-life**

**value**

Sets the valid cookie life value in increments of 100 milliseconds. The range is 50 to 1200 .

**default**

Resets the **sctp-cookie-life** value to the default, 600 (= .6 seconds).

---

**Usage Guidelines**

Use this command to set the Sctp cookie life.




---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

Set the Sctp cookie life to 1 second (1000 milliseconds):

```
sctp-cookie-life 1000
```

# sctp-init-rwnd

This command sets the size of the SCTP receiver window .

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**sctp-init-rwnd** *window\_size*  
**default sctp-init-rwnd**

**window\_size**

Sets an integer to configure the window size. The range is 32768 to 1048576.

**default**

Resets the **sctp-init-rwnd** window size to the default, 1048576.

---

**Usage Guidelines**

Use this command to set the receiver window size in the configuration. Configuring this parameter enables the SCTP client to send configured 'sctp-init\_rwnd' as a *\_rwnd* parameter in the INIT message. For the SCTP server, the INIT ACK will be populated with *sctp-init\_rwnd* as a *\_rwnd* parameter per RFC 4960.

The command enables the operator to configure a reduced priority for LinkManager Control messages, thereby giving Timer messages the highest priority. The Timer messages are retained at the highest priority and Data messages are kept at a lower priority.




---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

Use the following command to set the SCTP window size to 32786:

```
sctp-init-rwnd 32768
```

## sctp-max-assoc-retx

This command sets the maximum number of datagram retransmissions to be associated with this peer server configuration.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

**Syntax Description** **sctp-max-assoc-retx** *value*  
**default** **sctp-max-assoc-retx**

### **value**

Defines the maximum number of datagram retransmissions for an association. The value must be an integer between 0 and 255.

### **default**

Resets the default for **sctp-max-assoc-retx** to 10.

### **Usage Guidelines**

Use this command to configure the maximum number of datagram retransmissions for an association. The endpoint will be declared unreachable after **sctp-max-assoc-retx** number of consecutive retransmissions to an endpoint on any transport address.



### **Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

### **Example**

Set the maximum number to 3 datagram retransmissions:

```
sctp-max-assoc-retx 3
```

# sctp-max-data-chunks

This command sets the operator-preferred limit to the number of data chunks that can be bundled in an SCTP message.

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

## Syntax Description

**sctp-max-data-chunks** ( **limit** *max\_chunks* | **mtu-limit** )  
**default sctp-max-data-chunks**

### default

Resets the default for **sctp-max-data-chunks** to the limit set for the MTU with the **sctp-max-mtu-size** command.

### limit *max\_chunks*

Sets the operator-preferred maximum number of data chunks that can be bundled into SCTP messages. Enter an integer from 1 to 65535.

### mtu-limit

Instructs the SGSN to bundle only as many data chunks for the SCTP streams as defined by for the maximum transmission unit (MTU) size configured with the **sctp-max-mtu-size** command.

---

## Usage Guidelines

Use this command to override the default MTU-limit for data chunk bundling and configure a preferred maximum number of data chunks that can be bundled into an SCTP message.




---

### Important

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

### Example

Set *1024* as a maximum number of data chunks to be bundled:

```
sctp-max-data-chunks limit 1024
```

## sctp-max-in-strms

Configures the maximum number of incoming SCTP streams

---

**Product** SGSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-ppsp-ppsp_instance)#
```

---

**Syntax Description** **sctp-max-in-strms** *value*  
**default sctp-max-in-strms**

### default

Returns the configuration to the default of 16.

### value

Default: 16.

Specifies the maximum number of incoming SCTP streams as an integer from 1 to 16. The SGSN restricts the allowable range to 2 to 16. If a value of 1 is entered, a value 2 will be applied for any SGSN service associated with this SCTP parameter template.

---

**Usage Guidelines** Use this command to configure the maximum number of incoming SCTP streams.

### Example

The following command configures the maximum number of incoming SCTP streams to 5:

```
sctp-max-in-strms 5
```

## sctp-max-init-retx

This command sets the maximum number of retries to send the INIT datagram.

---

### Product

SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

### Syntax Description

**sctp-max-init-retx** *value*  
**default sctp-max-init-retx**

#### **value**

Sets the maximum number of retries. This value must be an integer between 0 and 255.

#### **default**

Resets the default for **sctp-max-init-retx** to 5.

---

### Usage Guidelines

Use this command to set the maximum number of retries the SCTP layer should make to send the INIT datagram to the peer to open an association.




---

### Important

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

### Example

```
sctp-max-init-retx 3
```

## sctp-max-mtu size

This command sets the number of bytes that comprise the maximum MTU size.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-ppsp-psp_instance)#
```

---

**Syntax Description**

**sctp-max-mtu-size** *value*  
**default sctp-max-mtu-size**

**value**

Sets the maximum number of bytes for the SCTP MTU size. This value must be an integer between 508 and 65535.

**default**

Resets the default for **sctp-max-mtu-size** to 1500 bytes.

---

**Usage Guidelines**

Use this command to configure the size of the MTU.




---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

Set the maximum size of the MTU to 3000 bytes:

```
sctp-max-mtu-size 3000
```

## sctp-max-out-strms

This command sets the maximum number of outgoing streams through the PSP going towards the peer server.

---

### Product

SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

### Syntax Description

**sctp-max-out-strms** *max#\_out\_streams*  
**default sctp-max-out-strms**

#### default

Resets the SGSN's **sctp-max-out-strms** value to the default of 2.

#### *max#\_out\_streams*

The value must be an integer between 1 and 16. The value should match the peer node's (STP/SG/RNC/HLR) number of in-bound streams.




---

### Important

For releases prior to 14.0, the value range was 1 to 65535. However, the system always capped at 16 so in Release 14.0 the range has been decreased to reflect that fact.

---

### Usage Guidelines

Use this command to balance the stream throughput from the PSP to the peer server. The value for this command is used to validate the incoming packets in the SCTP layer.

If the user tries to configure the value of **sctpmax-out-strms** less than "2", a message is displayed and the default value is set.




---

### Important

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

### Example

Set a maximum SCTP out streams to 12:

```
sctp-max-out-strms 12
```



Set a maximum SCTP out streams to the default of 2 streams:

```
default sctp-max-out-strms
```

# sctp-max-path-retx

This command sets the maximum number of datagram retransmissions for this path.

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

## Syntax Description

**sctp-max-path-retx** *value*  
**default sctp-max-path-retx**

### **value**

Sets the maximum number of datagram retransmission to a destination transport address. This value must be an integer from 0 to 255.

### **default**

Resets the **sctp-max-path-retx** default to 5.

---

## Usage Guidelines

Use this command to set the maximum number of datagram retransmissions to a destination transport address. The destination transport address will be declared unreachable after the SGSN exhausts the **sctp-max-path-retx** number of consecutive retransmissions to a destination transport address.

Depending upon network conditions, lower values typically means faster detection of SCTP-Path failure.




---

### Important

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

## Example

```
sctp-max-path-retx 10
```

## sctp-parameter

This command enables the SGSN administrator to alter the contents of the Optional Address Parameter IE.

**Product** SGSN

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

**Syntax Description** [ **default** | **no** ] **sctp-parameter ipv4-address suppress single-ended**

[ **default** | **no** ]

Either command prefix resets the default behavior to repeat the source IP address in the IE.

**Usage Guidelines** In situations when the endpoint is uni-homed (that is, single transport layer address), this command enables the SGSN administrator to override the default behavior and to configure the SGSN to suppress (not repeat) the source IP address which is typically included as part of the Optional Address Parameter IE in the INIT/INIT-Ack chunk.

### Example

Enable suppression of sending repeated IP address in the OAP IE with this command:

```
sctp-parameter ipv4-address suppress single-ended
```

Repeat sending the source IP address in the OAP IE with the following command:

```
no sctp-parameter ipv4-address suppress single-ended
```

# sctp-rto-initial

This command sets the initial retransmission timeout for the Sctp.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**sctp-rto-initial** *value*  
**default sctp-rto-initial**

**default**

Resets the system to the **sctp-rto-initial** default of 30 (3 seconds).

**value**

The value must be an integer between 1 and 50.

---

**Usage Guidelines**



---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

Use this command to define the initial retransmission timer.

The value set for **sctp-rto-initial** should be greater than or equal to the minimum value set with **sctp-rto-min** (**sctp-rto-initial** => **sctp-rto-min**).

The value set for **sctp-rto-initial** should be less than or equal to the maximum value set with **sctp-rto-max** (**sctp-rto-initial** <= **sctp-rto-max**).

**Example**

```
sctp-rto-initial 240
```

# sctp-rto-max

This command sets the maximum retransmission timeout value for the SCTP.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server** *id id* > **psp** *instance psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**sctp-rto-max** *value*  
**default sctp-rto-max**

**default**

Resets the system to the **sctp-rto-max** default of 600 (60 seconds).

**value**

Set the maximum retransmission timeout value in increments of 100 milliseconds (0.1 seconds) and the value must be an integer between 5 and 1200.

---

**Usage Guidelines**



---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

Use this command to configure the maximum time for retransmissions.

The value set for **sctp-rto-max** should be greater than or equal to the value set for **sctp-rto-initial** (**sctp-rto-max** => **sctp-rto-initial**).

**Example**

The following sets the timeout for 45 seconds:

```
sctp-rto-max 450
```

# sctp-rto-min

This command sets the minimum retransmission timeout (RTO) value for the SCTP.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**sctp-rto-min** [ **units-10ms** ] *value*  
**default sctp-rto-min**

**default**

Resets the **sctp-rto-min** to the default of 10 (1 second).

**units-10ms**

Including this keyword, before entering a value, enables configuration with finer granularity - in 10 millisecond units.

**value**

If the **units-10ms** keyword is included, then set the timeout in increments of 10 milliseconds. The value must be an integer between 1 and 500.

If the **units-10ms** keyword is not included then set the timeout in increments of 100 milliseconds. The value must be an integer between 1 and 50.

---

**Usage Guidelines**



---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

Use this command to set the minimum time for retransmission before timeout.

The value set for **sctp-rto-min** should be less than or equal to the value set for **sctp-rto-initial** (**sctp-rto-min** <= **sctp-rto-initial**)

**Example**

The following sets the timeout for 2 seconds:

```
sctp-rto-min 20
```

# sctp-sack-frequency

This command sets the frequency of transmission of SCTP selective acknowledgements (SACK).

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

**sctp-sack-frequency** [ **units-10ms** ] *value*  
**default sack-frequency**

**units-10ms**

Including this keyword, before entering a value, enables configuration with finer granularity - in 10 millisecond units.

**value**

Sets the maximum number of datagrams to be received prior to sending a SACK to the peer. The value must be an integer between 1 and 5.

**default**

Resets the **sctp-sack-frequency** default value of 2.

---

**Usage Guidelines**



---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

Use this command to set the maximum number of datagrams to be received before a SACK must be sent to the peer. The **sctp-sack-frequency** is used in conjunction with the **sctp-sack-period** to control the generation of SACK, depending on which one occurs first.

**Example**

```
sctp-sack-frequency 3
```



# sctp-sack-period

This command sets the delay before sending an SCTP selective acknowledgement (SACK).

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-ppsp-ppsp_instance)#
```

---

**Syntax Description**

**sctp-sack-period** [ **units-10ms** ] *value*  
**default sack-period**

**units-10ms**

Including this keyword, before entering a value, enables configuration with finer granularity - in 10 millisecond units.

**value**

If the **units-10ms** keyword is included, then set the timeout in increments of 10 milliseconds. The value must be an integer between 0 and 50.

If the **units-10ms** keyword is not included then set the timeout in increments of 100 milliseconds. The value must be an integer between 0 and 5.

**default**

Resets the system to the **sctp-sack-period** default value, 2 (=200 milliseconds).

---

**Usage Guidelines**

Use this command to set the time the SCTP waits to send a SACK.




---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

```
sctp-sack-period 3
```

# sctp-suppress-alarm

This command enables/disables the suppression of alarms for SCTP path failure between two peer endpoints.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

[ **no** ] **sctp-suppress-alarm path-failure self-end-point-address** *orig\_ipv4\_address* **peer-end-point-address** *peer\_ipv4\_address*

**no**

Disables the pre-configured alarm suppression for SCTP path failure.

**path-failure**

This keyword specifies that the alarm suppression is for SCTP path failure between two peer nodes.

**self-end-point-address** *orig\_ipv4\_address*

This keyword specifies the IP address of the originating endpoint.

*orig\_ipv4\_address* is the IP address of originating endpoint in IPv4 dotted decimal notation.

**peer-end-point-address** *peer\_ipv4\_address*

This keyword specifies the IP address of the peer endpoint.

*peer\_ipv4\_address* is the IP address of peer endpoint in IPv4 dotted decimal notation.

---

**Usage Guidelines**

Use this command to configure the path failure alarm suppression. This command ignores the alarms generated on SCTP path failure.




---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

The following command suppresses the path failure alarms occurred in SCTP path between originating peer address *1.2.3.4* and peer endpoint *6.7.8.9*:

```
sctp-suppress-alarm path-failure self-end-point-address 1.2.3.4  
peer-end-point-address 6.7.8.9
```

# shutdown

This command brings down and locks the SCTP association.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

[no] **shutdown**

**no**

On configuring **no shutdown**, the PSP is marked unlocked and the SGSN initiates an association establishment towards the peer, if the SGSN is a client and it honors messages from the peer for association establishment, if SGSN is server. This is the default configuration for a PSP.

The default is **no shutdown**.

---

**Usage Guidelines**

On configuring **shutdown**, the PSP is brought down via a SCTP Shutdown procedure (if association is already ESTABLISHED) or Abort (any other association state) and it is marked LOCKED. The SGSN does not initiate any messages towards the peer and any message from the peer will be responded with a SCTP Abort, when the PSP is in a LOCKED state.

**Example**

The following command brings down and locks the SCTP association:

**shutdown**

# timeout

This command sets the times for various timeout timers.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration > Peer-Server Configuration > PSP Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type* > **peer-server id** *id* > **psp instance** *psp\_instance*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-rd-ss7rd_id-ps-peer-server_id-psp-psp_instance)#
```

---

**Syntax Description**

```
timeout { m3ua-periodic-dest-audit dest_timeout | sctp-bundle [ units-10ms ] timer | sctp-heart-beat hrt_bt_timeout }
[ default | no ] timeout { m3ua-periodic-dest-audit | sctp-bundle | sctp-heart-beat }
```

**default**

Resets the specified command to the default value.

**no**

Removes the selected configuration.

**m3ua-periodic-dest-audit** *dest\_timeout*

Sets the period (in increments of seconds) between the DAUD messages while auditing a destination state.

*dest\_timeout*: Must be an integer from 1 to 65535. Default is 2.

**sctp-bundle** [ **units-10ms** ] *timer*

Specifies that SCTP data chunks are to be queued until this timer expires at which time the data chunks are bundled and committed for transmission. SCTP bundling provides better bandwidth utilization and less traffic, however, there is a packet transmission delay.

*timer* is an integer from 1 through 65535, in 100ms increments (10 = 1000ms or 1 second).

[ **units-10ms** ]: Including this optional keyword specifies that the integer *timer* is to be calculated using 10ms increments (instead of 100ms increments) to allow for finer granularity.




---

**Important**

Peer end should also be configured to support SCTP bundling.

---

Default: SCTP bundling is disabled.

**sctp-heart-beat *hrt\_bt\_timeout***

Sets the number of seconds in the SCTP heart-beat timer

*hrt\_bt\_timeout*: This value is an integer between 1 and 300. Default is 30.

---

**Usage Guidelines**

Use this command to configure timers. Repeat the command with each of the keywords to set values for each.



---

**Important**

Before using this command to set a value, you must disassociate the PSP instance with the **no associate** command. When you have set the value with this command, then use the **associate** command to setup a new association.

---

**Example**

```
timeout m3ua-periodic-dest-audit 120
```



# SGSN Service Configuration Mode Commands

SGSN Service works with MAP Service, SGTP Service, GTPP Group, and IuPS Service. All five of these services must be configured to enable a 3G SGSN to communicate with other elements within a UMTS network.

## Command Modes

The SGSN Service configuration mode is used within the global configuration mode to specify the 3G operations of the SGSN and the available SGSN services for a specific context.

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



## Important

The commands should be added or removed in the startup config only and not when the node is live.

- [accounting](#), on page 529
- [admin-disconnect-behavior](#), on page 531
- [associate](#), on page 533
- [cc profile](#), on page 537
- [check-imei](#), on page 539
- [check-imei-timeout-action](#) , on page 541
- [core-network](#), on page 542
- [disable/enable super-charger](#), on page 543
- [dns israu-mcc-mnc-encoding](#), on page 544
- [dns mcc-mnc-encoding](#), on page 545
- [do show](#), on page 547
- [end](#), on page 548
- [exit](#), on page 549
- [gmm](#), on page 550

- [gs-service](#), on page 556
- [lac](#), on page 558
- [max-pdp-contexts](#), on page 559
- [mobile-application-part](#), on page 560
- [network-sharing cs-ps-coordination](#), on page 562
- [nri length](#), on page 563
- [override-lac-li](#), on page 566
- [override-rac-li](#), on page 567
- [qos-modification](#), on page 568
- [rac](#), on page 570
- [ran-protocol](#), on page 571
- [reporting-action event-record](#), on page 572
- [s4-overcharge-protection](#), on page 573
- [sgsn-number](#), on page 575
- [sgtp-service](#), on page 576
- [sm](#), on page 577



# accounting

This command defines the accounting context name and enables/disables specific types of CDR generation for the accounting in the SGSN service.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure > context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

```
accounting ( cdr-types { mcdr | scdr | sms { mo-cdr | mt-cdr } | lcs { mt-cdr | mo-cdr } | smbmscdr }+ | context cntx_name }
default accounting cdr-types
no accounting ( cdr-types | context )
```

### default

Returns the system to default settings for the selected type of CDR.

### no

Removes the pre-configured type of CDR generation for accounting from the SGSN service.

```
cdr-types { mcdr | scdr | sms { mo-cdr | mt-cdr } | lcs { mt-cdr | mo-cdr } | smbmscdr }
```

Default: enabled

Defines the types of CDRs to be generated within the specified SGSN service for accounting:

- **mcd**r: Enables generation of M-CDRs.
- **s**cdr: Enables generation of S-CDRs.
- **sms**: Enables generation of SMS-type CDRs based on one of the following:
  - **mo-cdr**: SMS CDRs originates from the mobile.
  - **mt-cdr**: SMS CDRs terminates at the mobile.
- **smbmscdr**: This CDR type is currently under development and should not be included in configuration for this release.
- **lcs**: Enables the generation of LCS CDRs, based on:
  - **mt-cdr**: Mobile terminated location request CDR
  - **mo-cdr**: Mobile originated location request CDR

+

Specifies that the specified keywords within the group can be entered multiple times with a single command.

**context *cntx\_name***

Specifies an accounting context to be associated with the SGSN service.

*cntx\_name*: Define a string of 1 to 79 alphanumeric characters.

---

**Usage Guidelines**

Use this command to define the type of CDRs to generate for SGSN service. By default all type of CDRs are generated. Note that change of this configuration will be applied to new call and/or to new PDP contexts only.

By default, the generation of all CDR types is enabled.

**Example**

The following command configures the system to generate CDRs of M-CDR type for accounting in the current SGSN service:

```
accounting cdr-types mcdr
```

# admin-disconnect-behavior

This command defines some of the actions the SGSN will take during an Admin-Disconnect procedure.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

```
admin-disconnect-behavior { clear-subscription | detach-type {
reattach-not-required | reattach-required } }
[ default | no ] admin-disconnect-behavior { clear-subscription |
detach-type }
```

### **clear-subscription**

Including this keyword in the configuration instructs the SGSN to clear subscriber contexts and the subscription data database whenever the **clear subscribers all** command is issued (from the Exec mode) for attached subscribers. As well, the SGSN will issue an appropriate Map-Purge-MS-Req to the HLR if needed.

Default: disabled

### **detach-type**

Including this keyword defines which type of detach instruction to include in the Detach-Request message during an Admin-Disconnect procedure. One of the following options must be included when this command is entered:

- **reattach-not-required**
- **reattach-required**

Default: reattach-required

### **default | no**

Including either **default** or **no** keyword in the command, instructs the SGSN to use the default value for the specified parameter.

---

**Usage Guidelines**

Include the **clear-subscription** keyword with this command configuration to ensure that more than attached MM-context and active PDP-contexts are cleared when the **clear subscribers all** command is issued for attached subscribers.

To clear subscription data for detached subscribers, refer to the **sgsn clear-detached-subscriptions** command described in the *Exec* mode chapter.

Including the **detach-type** keyword with this command instructs the SGSN to include either a 'reattach-required' or a 'reattach-no-required' instruction in the Detach-Request message.

### Example

Configure the SGSN to clear data such as PTMSI allocated, auth-vectors received, and NGAF flag values stored in the subscriber database for attached subscribers:

```
admin-disconnect-behavior clear-subscription
```

# associate

Associates or disassociates supportive services and policies, such as an Evolved GPRS Tunnelling Protocol (eGTP) service, an HSS peer service, or a MAP service.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

```
associate { { camel-service camel_svc_name [ context context_name ] |
egtp-service egtp_svc_name [ context context_name ] | gs-service gs_svc_name [
context context_name ] | hss-peer-service hss_svc_name [ context context_name ] |
| map-service map_svc_name [ context context_name ] |
network-global-mme-id-mgmt-db | sgtp-service sgtp_svc_name [ context
context_name ] | tai-mgmt-db database_name }
no associate { camel-service | egtp-service | gs-service | hss-peer-service
| map-service | network-global-mme-id-mgmt-db | sgtp-service |
tai-mgmt-db database_name }
```

**no**

Disassociates a previously associated service with this SGSN service.

### **camel-service** *camel\_svc\_name*

Associates a CAMEL service with SGSN service.

*camel\_svc\_name* specifies the name for a pre-configured CAMEL service to associate with the SGSN service.

### **egtp-service** *egtp\_svc\_name*

Associates an eGTP service with SGSN service.

*egtp\_svc\_name* specifies the name for a pre-configured eGTP service to associate with the SGSN service. For more information on the eGTP service, refer to the **egtp-service** command in the *Context Configuration Mode Commands* chapter.



## Important

Only one eGTP service can be associated with a SGSN service. The eGTP service should be configured prior to issuing this command.

### **gs-service** *gs\_svc\_name*

Associates a GS service with this SGSN service.

*gs\_svc\_name* specifies the name for a pre-configured GS service to associate with the SGSN service.




---

**Important** Only one Gs service can be associated with a SGSN service. The Gs service should be configured prior to issuing this command.

---

#### **hss-peer-service *hss\_svc\_name***

Associates an HSS peer service with this SGSN service.

*hss\_svc\_name* specifies the name for a pre-configured HSS peer service to associate with the SGSN service as an alphanumeric string of 1 through 63 characters. For more information about the HSS peer service, refer to the **hss-peer-service** command in the *Context Configuration Mode Commands* chapter and the *HSS Peer Service Configuration Mode Commands* chapter.




---

**Important** Only one HSS peer service can be associated to a service in this release. The HSS peer service should be configured prior to issuing this command.

---

#### **map-service *map\_svc\_name***

Associates a MAP service with this SGSN service.

*map\_svc\_name* specifies the name for a pre-configured MAP service to associate with the SGSN service.

The MAP service is created with the **map-service** command in the *Context Configuration Mode Commands* chapter. The MAP service provides Mobile Application Part (MAP) protocol support for the interface between the SGSN and the HLR. For more information on the MAP service, refer to the *MAP Service Configuration Mode Commands* chapter.




---

**Important** Only one MAP service can be associated with a SGSN service. The MAP service should be configured prior to issuing this command.

---

#### **network-global-mme-id-mgmt-db**

On the S4-SGSN, associates a pre-configured network global MME ID management database with the SGSN service. This enables operators to associate a single custom list of MME Group IDs for use in UMTS to E-UTRAN handovers on the S4-SGSN. The global MME ID management database must be configured on the S4-SGSN using the **network-global-mme-id-mgmt-db** command in *LTE Policy Configuration Mode* before it can be associated with an SGSN service.

This command is available on the SGSN only if the *SGSN S4 Interface* license is enabled.

#### **sgtp-service *sgtp\_svc\_name***

Associates an SGTP service with this SGSN service.

*sgtp\_svc\_name* specifies the name for a pre-configured SGTP service to associate with the SGSN service as an alphanumeric string of 1 through 64 characters. For more information on the SGTP service, refer to the

**sgtp-service** command in the *Context Configuration Mode Commands* chapter and/or the *SGTP Service Configuration Mode Commands* chapter.

**Important**

The SGTP service should be configured prior to issuing this command. Only one SGTP service can be associated with an SGSN service. When co-locating an SGSN and an MME, the SGSN Service cannot be associated with the same SGTP Service that is used by the MME.

**context *ctx\_name***

Identifies a specific context name where the named service is configured. If this keyword is omitted, the named service must exist in the same context as the SGSN service.

*ctx\_name* is name of the configured context of the named service expressed as an alphanumeric string of 1 through 63 characters that is case sensitive.

**tai-mgmt-db *database\_name***

Associates this SGSN service with a pre-configured TAI Management Database.

*database\_name* specifies the name of a pre-configured TAI Management Database to associate with the SGSN service as alphanumeric string of 1 through 64 characters. For more information, refer to the **tai-mgmt-db** command in the *LTE Policy Configuration Mode Commands* chapter and the *LTE TAI Management Database Configuration Mode Commands* chapter.

This command is available on the SGSN only if the *SGSN S4 Interface* license is enabled.

**Usage Guidelines**

Use this command to associate a pre-configured service or policy with an SGSN service.

The eGTP service provides eGTP-C protocol interface support between EPS nodes. For more information on the eGTP service and the supported interface type, refer to the *eGTP Service Configuration Mode Commands* chapter.

**Important**

Only one eGTP service can be associated with a service. The eGTP service should be configured prior to issuing this command.

The HSS peer service provides S6d and S13-prime interface support via the Diameter protocol between the SGSN and an HSS (S6d) or EIR (S13-prime). For more information on HSS peer service and other parameters, refer to the *HSS Peer Service Configuration Mode Commands* chapter.

**Important**

Only one HSS peer service can be associated to a service in this release. The HSS peer service should be configured prior to issuing this command.

**Caution**

This is a critical configuration. The SGSN service cannot be started without this configuration. Any change to this configuration would lead to restarting the SGSN service. Removing or disabling this configuration will stop the SGSN service.

**Example**

The following command associates a pre-configured eGTP service called *egtp1* in the *dst\_ctx* context to an SGSN service:

```
associate egtp-service egtp1 context dst_ctx
```

The following command associates a pre-configured HSS peer service called *hss1* in the same context as SGSN service to an SGSN service:

```
associate hss-peer-service hss1
```



# cc profile

Configures the charging characteristic (CC) profile with the triggers for generating various types of CDR as defined with the **accounting** command.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure > context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

```
cc profile profile_bits [ buckets number | interval time | tariff time1 mins
hours [ time2 mins hours ] [ time3 mins hours ] [ time4 mins hours ] | volume {
  downlink down_vol uplink up_vol | total total_vol } ] +
[ no | default ] cc profile profile_bits [ buckets | interval | tariff |
volume ]
```

### no

Removes a previously configured CC profile.

### default

Returns the specified CC profile to the original default system settings.

### *profile\_bits*

Defines the value of the profile bits for the SGSN service.

*index* can be configured to any integer value from 0 to 15. Some of the values have been predefined according to 3GPP standard:

- 1 for hot billing
- 2 for flat billing
- 4 for prepaid billing
- 8 for normal billing

### **buckets** *number*

Specifies the number of statistics container changes in the CDR due to QoS changes or tariff times that can occur before an accounting record (CDR) is closed

Default: 4

*number* : Must be integer from 1 to 4.

**interval time**

Specifies the normal time duration (in seconds) that must elapse before closing an accounting record (CDR) provided that any or all of the following conditions occur:

*time* : Enter any integer from 60 to 40000000.

**tariff time1 mins hours [ time2 mins hours time3 mins hours time4 mins hours ]**

Specifies the time-of-day (based on a 24-hour clock) to close the current statistics container in the CDR, but not necessarily the CDR itself. One tariff time must be defined and up to four tariff times can be specified.

**Important**

The system assumes that the billing system uses the day/date to determine if the statistics container represents an actual tariff period.

- *mins*: The minutes of the hour. Enter an integer from 0 to 59.
- *hours*: The hour of the day. Enter an integer from 0 to 23.

**volume { downlink down\_vol uplink up\_vol | total total\_vol }**

Specifies the downlink, uplink, and total volumes octet counts that must be met for the closure of the CDR.

*down\_vol* : Enter any integer from 100000 to 1345294336.

*up\_vol* : Enter any integer from 100000 to 400000000.

*total\_vol* : Enter any integer from 100000 to 400000000.

**Usage Guidelines**

Charging characteristics consist of a profile index and behavior settings. This command configures the profile index for the SGSN's charging characteristics. The SGSN supports up to 16 profile indexes.

**Example**

The following command configures a profile index of 10 with tariff times of 7:00 AM and 7:30 PM:

```
cc profile 10 tariff time1 0 7 time2 30 19 time3 0 7 time4 30 19
```

# check-imei

This command configures the action the SGSN will take if the route towards the EIR is down.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

```
check-imei { gf-failure-action | gf-timeout-action } { continue | reject
}
default check-imei { gf-failure-action | gf-timeout-action }
```

**default**

Resets the default function to reject the Attach.

**gf-failure-action**

Coupled with either **continue** or **reject**, this keyword instructs the SGSN to take action if a valid EIR configuration exists under the MAP service and if the EIR is temporarily unreachable due to associated DPC/SSN inaccessible/out-of-service.

**gf-timeout-action**

Coupled with either **continue** or **reject**, this keyword instructs the SGSN to take action if a valid EIR configuration exists under the MAP service and the route to the EIR is available, but no response is received from the EIR.

**continue**

Instructs the SGSN to continue the Attach process.

**reject**

Instructs the SGSN to reject the Attach process.

---

**Usage Guidelines**

Typically, the Attach process will be continued when there is an IMEI check timeout based on the configuration under the SGSN service configuration and/or the GPRS service configuration. But this works only if the route towards the EIR is UP and the IMEI request timer expires. This command configures the SGSN to allow the Attach process to continue in the case the route towards the EIR is down, that is the DPC / SSN is out-of-service.

**Example**

Use the following command to reset the default and reject Attach:

```
default check-imei gf-failure-action
```

## check-imei-timeout-action

In Releases 12.0 and higher, this command has been replaced with enhanced functionality in the **check-imei** command, also available in this configuration mode.

## core-network

This command specifies the numeric ID for a core network to identify which CN is to be used by the SGSN service.

---

### Product

SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

### Syntax Description

**core-network id** *cn\_id*  
**no core-network id**

**no**

Removes the currently configured core network ID from the current SGSN configuration.

**id** *cn\_id*

This number identifies the core network to connect the SGSN service.

*cn\_id*: Must be an integer from 0 through 4095.

---

### Usage Guidelines

Use this command to set a global ID to identify this SGSN in the core network.

### Example

The following command sets the core network ID for the current SGSN service to 127:

```
core-network id 127
```

## disable/enable super-charger

This command has been deprecated and replaced by the **super-charger** command. For the commands to configure the SuperCharger feature, refer to the *Call-Control Profile Configuration Mode* chapter.

## dns israu-mcc-mnc-encoding

Configures either decimal or hexadecimal format for the MCC and MNC values in the DNS query which is sent during the ISRAU.

This command is deprecated from release 16.0 onwards, it is replaced by the **dns mcc-mnc-encoding** command. See the **dns mcc-mnc-encoding** command for more information.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > Context Configuration > SGSN Service Configuration <b>configure</b> > <b>context</b> <i>context_name</i> > <b>sgsn-service</b> <i>service_name</i> Entering the above command sequence results in the following prompt: <pre>[context_name]host_name(config-sgsn-service)#</pre>
<b>Syntax Description</b>	<b>dns israu-mcc-mnc-encoding { decimal   hexadecimal }</b> <b>default dns israu-mcc-mnc-encoding</b>

### default

Resets the SGSN to send the MCC and MNC values in decimal format for DNS queries.

### decimal

Default.

Instructs the SGSN to send the MCC and MNC in decimal format in the DNS query.

### hexadecimal

Instructs the SGSN to send the MCC and MNC in hexadecimal format in the DNS query.

### Usage Guidelines

Use this command to determine the type of encoding for the MCC and MNC to be included in the DNS query sent during the inter-SGSN RAU (ISRAU). The choice must match the format of the DNS server. For example:

In decimal, the MNC/MCC in a DNS query would appear like:

```
rac0017.1ac42e3.mnc310.mcc722.gprs
```

In hexadecimal, the MNC/MCC in a DNS query would appear like:

```
rac0017.1ac42e3.mnc0136.mcc02d2.gprs
```

### Example

Use hexadecimal values for the MCC/MNC in the DNS query.

```
dns israu-mcc-mnc-encoding hexadecimal
```



# dns mcc-mnc-encoding

Configures the encoding format for the MCC and MNC values in the DNS query.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

```
dns mcc-mnc-encoding { apn-fqdn | mmec-fqdn | rai-fqdn | rnc-fqdn | tai-fqdn }* { a-query | snaptr-query }* { decimal | hexadecimal }
default dns mcc-mnc-encoding
```

### default

Resets the SGSN to send the MCC and MNC values in decimal format for DNS queries.

### apn-fqdn

This keyword is used for PGW/GGSN selection during PDP activation.

### mmec-fqdn

This keyword is used for Peer MME selection during MME to SGSN ATTACH/RAU procedure and Suspend procedure.

### rai-fqdn

This keyword is used for SGW selection, Peer SGSN selection during RAU/Attach procedure, Suspend procedure and RIM procedure.

### rnc-fqdn

This keyword is used for Peer SGSN selection during SRNS re-location.

### tai-fqdn

This keyword is used for Peer MME selection during SGSN to MME SRNS re-location and RIM procedure.

### a-query

This keyword is used to control the DNS A/AAAA query MCC/MNC encoding format.

### snaptr-query

This keyword is used to control the DNS SNAPTR query MCC/MNC encoding format.

**decimal**

Default

Instructs the SGSN to send the MCC and MNC in decimal format in the DNS query.

**hexadecimal**

Instructs the SGSN to send the MCC and MNC in hexadecimal format in the DNS query.

---

**Usage Guidelines**

In order to provide effective control on DNS queries for particular type of procedures, existing CLI commands in GPRS and SGSN services have been deprecated and replaced with new enhanced commands. The command **dns israu-mcc-mnc-encoding [hexadecimal | decimal]** has been deprecated and this new CLI command is introduced. New keyword options **snaptr-query** and **a-Query** are provided to control different types of queries.

**Example**

Use the following command to configure hexadecimal encoding in the DNS query:

```
dns mcc-mnc-encoding rai-fqdn apn-fqdn mmec-fqdn rnc-fqdn tai-fqdn a-query  
hexadecimal
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

**end**

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Return to the Exec mode.

# exit

Exits the current configuration mode and returns to the context configuration mode.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>exit</b>
<b>Usage Guidelines</b>	Return to the context configuration mode.

# gmm

This command defines the GPRS mobility management parameters for the SGSN service.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

```
gmm { [ Extended-T3312-timeout { value exT3312_minutes | when-subscribed }
      [ low-priority-ind-ue ] ] | T3302-timeout t3302_dur | T3312-timeout t3312_dur
      | T3313-timeout initial t3313_init [ decrease t3313_decrement | increase
      t3313_increment ] | T3322-timeout t3322_dur | T3323-timeout T3323_dur |
      T3350-timeout t3350_dur | T3360-timeout t3360_dur | T3370-timeout t3370_dur |
      implicit-detach-timeout secs | max-auth-retransmission auth_retrans |
      max-identity-retransmission id_retrans | max-page-retransmission page_retrans
      | max-ptmsi-reloc-retransmission ptmsi_reloc_retrans |
      mobile-reachable-timeout ms_reach_dur | paging-failure-action
      downlink-data-lockout-timer seconds [ repeat number_repeats ] |
      perform-identity-on-auth-failure | purge-timeout minutes | t3346 min minimum
      max maximum | trau-timeout trau_dur }
default gmm { T3302-timeout | T3312-timeout | T3313-timeout | T3322-timeout
      | T3323-timeout | T3350-timeout | T3360-timeout | T3370-timeout |
      implicit-detach-timeout | max-auth-retransmission |
      max-identity-retransmission | max-page-retransmission |
      max-ptmsi-reloc-retransmission | mobile-reachable-timeout |
      perform-identity-on-auth-failure | purge-timeout | trau-timeout }
no gmm {Extended-T3312-timeout | implicit-detach-timeout |
      max-auth-retransmission | max-identity-retransmission |
      perform-identity-on-auth-failure | t3346 }
```

**default**

Sets the default value for the specified parameter.

**Extended-T3312-timeout**

This keyword enables the operator to determine how the SGSN handles Extended T3312 timer values in a 3G UMTS network environment.

- **value** : This keyword instructs the SGSN to send the defined Extended T3312 timer value in Attach or RAU Accept messages to the MS if the subscriber has a subscription for the Extended T3312 timer (Subscribed Periodic RAU/TAU Timer in ISD) and indicates support for the extended periodic timer via the MS Network Feature Support.

- *exT3312\_minutes* : Enter an integer from 0 to 18600 to identify the number of minutes for the timeout; default is 186 minutes.
- **when-subscribed**: This keyword instructs the SGSN to only send the extended T3312 period RAU timer value in Attach or RAU Accept messages if the SGSN receives the timeout value in an ISD when the MS has indicated support in MS Network Feature Support.
- **low-priority-ind-ue**: This keyword instructs the SGSN to include the extended T3312 timer value only if the Attach/RAU Request messages include a LAPI (low access priority indicator) in the "MS Device Properties".
- **no**: This command filter instructs the SGSN to remove the extended T3312 configuration from the SGSN Service configuration.

**T3302-timeout *t3302\_dur***

Default: 10

Specifies the retransmission timer value to guard the GPRS attach or RAU procedure on MS side.

*t3302\_dur* is the waiting duration in minutes before retransmitting the specific message and must be an integer from 1 through 186.

**T3312-timeout *t3312\_dur***

Default: 54

Specifies the retransmission timer value to guard the RAU procedure initiation on network side.

*t3312\_dur* is the waiting duration in minutes before retransmitting the specific message and must be an integer from 1 through 186.

**T3313-timeout initial *t3313\_init* [ decrease *t3313\_decrement* | increase *t3313\_increment* ]**

Default: 5

Specifies the retransmission timer value to guard the for paging request procedure initiation on network side.

**initial** *t3313\_init* - Specifies the initial waiting duration in seconds before retransmitting the specific message. *t3313\_init* must be an integer from 1 through 60.

**decrease** *t3313\_decrement* - Specifies the decrement of the initial timer value in seconds. *t3313\_decrement* must be an integer from 1 through 5.

**increase** *t3313\_increment* - Specifies the increment of the initial timer value in seconds. *t3313\_decrement* must be an integer from 1 through 5.

**T3322-timeout *t3322\_dur***

Default: 6

Specifies the retransmission timer value to guard the GPRS detach request procedure on network side.

*t3322\_dur* is the waiting duration in seconds before retransmitting the specific message and must be an integer from 1 through 20.

**T3323-timeout *T3323\_dur***

Default: 54

Specifies that the S4-SGSN Idle Mode Signaling Reduction T3323-timeout deactivation timer will be sent to the UE in Attach Accept and Routing Area Update Accept Messages.

*T3323\_dur* specifies the amount of time, in minutes, that will transpire before the UE deactivates the ISR feature if the UE is no longer in the UMTS coverage area and has not completed a Routing Area Update with the S4-SGSN within the specified time duration. Once the timer expires, the S4-SGSN waits an additional four minutes before beginning an Implicit Detach for the UE and sends a Detach Notification message (cause = local detach) to the MME across the S3 interface. The MME will then deactivate ISR for the UE since it now also is aware that the UE is no longer in the UMTS coverage area. Valid entry is an integer from 1 to 186.

This command is available only if the *Idle Mode Signaling Reduction* license is enabled on the S4-SGSN and the Idle Mode Signaling Reduction feature has been activated via the **idle-mode-signaling-reduction** command in *Call Control Profile Configuration Mode*.

#### **T3350-timeout *t3350\_dur***

Default: 6

Specifies the retransmission timer value to guard the GPRS attach accept/RAU accept/realloc request procedure sent with P-TMSI and/or TMSI on network side.

*t3350\_dur* is the waiting duration in seconds before retransmitting the specific message and must be an integer from 1 through 20.

#### **T3360-timeout *t3360\_dur***

Default: 6

Specifies the retransmission timer value to guard the authentication and cipher request procedure on network side.

*t3360\_dur* is the waiting duration in seconds before retransmitting the specific message and must be an integer from 1 through 20.

#### **T3370-timeout *t3370\_dur***

Default: 6

Specifies the retransmission timer value to guard the identity request procedure on network side.

*t3370\_dur* is the waiting duration in seconds before retransmitting the specific message and must be an integer from 1 through 20.

#### **implicit-detach-timeout *secs***

Default: 3600

Specifies the implicit detach timer (IDT) timeout value for any 3G calls (not specific to ISR activated calls) as part of the implicit detach procedure on the network side. The IDT starts after expiry of the mobile reachable timer (MNR). Soon after IDT expiry, the subscriber is implicitly detached from the SGSN.

*secs* value must be an integer from 1 to 86400.



#### **Important**

From R15.0 release onwards the lowest configurable limit of the IDT timeout is modified to "240" seconds.



**max-auth-retransmission *auth\_retrans***

Default: 4

Specifies the maximum retransmission of authentication requests allowed.

*auth\_retrans* is the number of retries before declaring the authentication failure and must be an integer from 1 through 10.

**max-identity-retransmission *id\_retrans***

Default: 4

Specifies the maximum retransmission of identity requests allowed.

*id\_retrans* is the number of retries before declaring the identity failure and must be an integer from 1 through 10.

**max-page-retransmission *page\_retrans***

Default: 5

Specifies the maximum retransmission of page requests allowed.

*id\_retrans* is the number of retries before declaring the paging request failure and must be an integer from 1 through 5.

**max-ptmsi-reloc-retransmission *ptmsi\_reloc\_retrans***

Default: 5

Specifies the maximum retransmission for P-TMSI relocation procedure allowed.

*id\_retrans* is the number of retries before declaring the P-TMSI relocation procedure failure and must be an integer from 1 through 10.

**mobile-reachable-timeout *ms\_reach\_dur***

Default: 58

Specifies the timeout duration for the mobile reachable timer (MNR) for the mobile reachable procedure on network side.

*impli\_detach\_dur* sets the waiting duration in minutes before retransmitting the specific message and must be an integer from 4 through 1440.

**paging-failure-action downlink-data-lockout-timer *seconds* [ repeat *number\_repeats* ]**

Default: 1000 seconds.

Enables and configures the downlink data lockout timer, for the SGSN services, to reduce the frequency of mobile-initiated keep alive messages.

*seconds* set the number of seconds before timer expire, range of 0 to 10000.

**repeat** *number\_repeats* optionally sets the number of times (1 to 10) that the timer restarts after paging failure.

**Note:** If repeat is not configured then paging proceeds endlessly until the MR timer expires.

[ **default** | **no** ] **gmm paging-failure-action** disables the downlink data lockout timer.

**perform-identity-on-auth-failure**

Default: Enabled

Configures the SGSN service to perform an identity check to ascertain the IMSI after an authentication failure on a PTMSI-based message.

Beginning with Release 19.2, a new default behavior has the SGSN initiate the Identity Procedure

- (1) on receiving authentication failure with cause "GSM Authentication Unacceptable" from a 3G subscriber during an Attach/RAU, or
- (2) on receiving authentication failure with cause "MAC failure" during 2G ISRAU.

**purge-timeout *minutes***

Default: 10080 (7 days)

The purge timer defines the MM-context lifetime, part of the MM-context procedure on the network side. The configured value sets the duration (number of minutes) the SGSN holds the detached subscriber's MM-context profile. If the subscriber does not reattach to the SGSN during this time, then the SGSN purges this detached subscriber's MM-context information from its database and sends a MAP purge request towards the HLR to indicate that the subscribers profile is gracefully purged from SGSN's database.

*minutes* must be an integer from 1 through 20160.

**t3346**

This keyword enables the mobility management (MM) T3346 back-off timer for the 3G service. When the SGSN is confronted by a situation involving congestion, the SGSN can assign the back-off timer value to the UEs and requests the UEs not to access the network for a given period of time.

**min** *minimum*: Enter an integer from 1 to 15 to identify the minimum number of minutes that the timer will run; default is 15 minutes.

**max** *maximum*: Enter an integer from 1 to 30 to identify the maximum number of minutes the timer can run; default is 30 minutes.

- If an Attach Request or RAU Request or Service Request is rejected due to congestion, then the T3346 value will be included in the reject message with GMM cause code 22 (congestion). The MM back-off timer value sent will be chosen randomly from within the configured T3346 timer value range.
- The timer will be ignored if an Attach Request or RAU Request is received after congestion has cleared.
- If T3346 timer value is configured in a Call-Control Profile then that value will override the back-off timer values defined for this SGSN Service configurations.

**trau-timeout *trau\_dur***

This timer is available in releases 9.0 and higher.

Default: 30

Specifies the number of seconds the "old" 3G SGSN waits to purge the MS's data. This timer is started by the "old" SGSN after completion of the inter-SGSN RAU.

*trau\_dur* : Must be an integer from 5 to 60.

**Usage Guidelines**

Repeat this command as needed to configure multiple parameters for GPRS mobility management in a UMTS network. This command provides the configuration of timers for mobility procedures and retries for different messages. GMM layer is defined in the 3GPP TS 24.008 (Release 7).

**Example**

Following command configures the timer to wait for 5 mins before retransmitting the message for GPRS attach or RAU procedure on MS side with maximum number of retries as 6 for authentication:

```
gmm T3302-timeout 5 max-auth-retransmission 6
```

# gs-service

This command associates a previously defined Gs service configuration, for the Gs interface to an MSC/VLR, with this SGSN service.



## Important

This command is used in Releases 12.0 and 12.2. For Release 14.0 refer to the **associate** command.

## Product

SGSN

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

**gs-service** *gs\_srvc\_name* **context** *ctx\_name*  
**no gs-service** *gs\_srvc\_name*

**no**

Removes/disassociates the named Gs service from this SGSN service.

### **gs\_srvc\_name**

Specifies the name of a specific Gs service for which to display information.

*svc\_name* is the name of a configured Gs service and can be from 1 to 63 alpha and/or numeric characters and is case sensitive.

### **context ctx\_name**

Specifies the specific context name where Gs service is configured. If this keyword is omitted, the named Gs service must exist in the same context as the SGSN service.

*ctx\_name* is name of the configured context of Gs service. This can be from 1 to 63 alpha and/or numeric characters and is case sensitive.

## Usage Guidelines

Use this command to associate a specific Gs service interface with this SGSN service instance.



## Important

A single Gs service can be used with multiple SGSN and/or GPRS service.

**Example**

Following command associates a Gs service instance named *stargs1*, which is configured in context named *star\_ctx*, with an SGSN service:

```
gs-service stargs1 context star_ctx
```

# lac

This command defines the location area code (LAC) in hexadecimal format.




---

**Note** This command is new in releases 8.1 and higher.

---



---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service) #
```

---

## Syntax Description

**lac** *hex*  
**no lac**

**no**

Erases the **lac** configuration statement.

**hex**

Enter a hexadecimal number between 0x0 and 0xFFFF

# max-pdp-contexts

Configures the maximum number of PDP contexts for a MS (mobile station) that will be supported on this SGSN service.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure > context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

**Syntax Description** **max-pdp-contexts per-ms** *number*  
**default max-pdp-contexts per-ms**

## default

Resets the maximum number of PDP contexts per mobile station to the default of 11 for the Gs service configuration

## per-ms *number*

Default: 11

Defines the combined total number of primary and secondary PDP contexts for the SGSN service.

*number* can be an integer from 2 to 11.

**Usage Guidelines** The following example defines 5 as the maximum number of primary and secondary PDP contexts that this SGSN will support for any connected MS.

## Example

```
max-pdp-contexts per-ms 5
```

# mobile-application-part

This command identifies an already defined MAP service (Mobile Application Part service) to associate with the SGSN service. Although the MAP service does not need to be defined in the same context as the SGSN service, there is a one-to-one relationship between a MAP service and an SGSN service.



**Important** This command is used in Releases 12.0 and 12.2. For Release 14.0 refer to the **associate** command.

## Product

SGSN

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

**mobile-application-part service** *map\_srvc* [ **context** *ctx\_name* ]  
**no mobile-application-part service**

**no**

Remove the MAP service association from the SGSN service configuration.

**service** *map\_srvc*

Specifies the name of the MAP service to be associated with this SGSN service.

*map\_srvc* must be the name of a MAP service previously configured on the system.

**context** *ctx\_name*

Specifies the name of the context where the MAP service is configured. If the MAP service is not configured in the current context, then the context where it is configured must be specified to enable the SGSN to reach the MAP service.

If this keyword is not specified, the current context is used.

*ctx\_name*: Must be the name of the context where the specified MAP service is configured.

## Usage Guidelines

Use this command to identify the MAP service configuration to be used by the SGSN service configuration. Also use this command to specify the context in which the MAP service configuration was created.

If the MAP service is not identified or if the correct context is not identified, then the SGSN service will not START.



**Example**

The following command specifies a MAP service named `map1` that is configured in the same context as the current SGSN service:

```
mobile-application-part service map1
```

# network-sharing cs-ps-coordination

Enables/disables the SGSN service to perform a CS-PS coordination check.



## Important

This command is no longer available in all 12.0 and 12.2 releases. If you do not see this command in your release, look for the **network-sharing cs-ps-coordination** command in the IuPS Service configuration mode to accomplish the same task. Configuring in the IuPS Service configuration mode allows for the possibility of multiple IuPS services with network-sharing and differing CS-PS coordination requirements.

## Product

SGSN

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

**network-sharing cs-ps-coordination**  
**default network-sharing cs-ps-coordination**  
**no network-sharing cs-ps-coordination**

### default

Including this keyword resets the SGSN service to allow the check to be performed.

### no

Disables this feature for the SGSN service.

## Usage Guidelines

Use this command to facilitate the network sharing functionality. With this command, the SGSN can be instructed to perform a check to determine if CS-PS coordination is needed.

3GPP TS 25.231 section 4.2.5 describes the functionality of the SGSN to handle CS-PS (circuit-switching/packet-switching) coordination for attached networks not having a Gs-interface. In compliance with the standard, the SGSN rejects an Attach in a MOCN configuration with cause 'CS-PS coordination required', after learning the IMSI, to facilitate the RNC choosing the same operator for both CS and PS domains.

## Example

Use the following syntax to disable the CS-PS coordination check:

```
no network-sharing cs-ps-coordination
```

# nri length

This command defines the Network Resource Identifier (NRI) of the SGSN that is stored in the P-TMSI (bits 23 to 18).

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

```
nri length nri_length [ nri-value nri_value | null-nri-value null_nri_value
non-broadcast mcc mcc mnc mnc lac lac_id rac rac_id nri-value value
non-pooled-nri-value value ]
default nri
no nri
```

### default

Release 14.0 and higher.

Resets the nri configuration to **nri length** 6 and **nri-value** 0.

### no

Deprecated in Release 14.0

Releases prior to 14.0, this command removes the configured NRI value and location information in the P-TMSI that would be retrieved by this SGSN.

### nri length *nri\_length*

Specifies the number of bits to be used in the P-TMSI, bits 23 to 18, to define the network resource identifier (NRI). The NRI length configuration also sets the maximum size of the pool. If not configured, the NRI length will be of zero length.

*nri\_length* : Must be an integer from 1 to 6 to identify the number of bits.

### null-nri-value *null\_nri\_value*

This keyword is only available in releases 8.1 and higher.

Configures the null NRI value which must be unique across the pool areas. This keyword is used for the offloading procedure for SGSN pooling (enabled with the **sgsn offloading** command, see the Exec Mode chapter).

*null\_nri\_value* is an integer 0 (zero) to 63 which identifies the SGSN to be used for the offloading procedure for SGSN pooling. There is no default value for this parameter.

**non-broadcast mcc *mcc* mnc *mnc* lac *lac\_id* rac *rac\_id***

This keyword set is only available in releases 8.1 and higher.

Defines the non-broadcast LAC/RAC to be used in combination with the null-NRI for the offloading procedure. Including the MCC and MNC to specify the PLMN because the Iu-Flex feature supports multiple IuPS Services.

*mcc* identifies the mobile country code, the first part of the PLMN ID. Must be an integer between 100 and 999.

*mnc* identifies the mobile network code portion of the PLMN ID. Must be a 2- or 3-digit integer between 01 and 999.

*lac\_id* defines a location area code associated with an RNC. Must be an integer between 1 and 65535.

*rac\_id* defines the remote area code to be associated with an RNC. Must be an integer between 1 and 255.

**nri-value *nri\_value***

Specifies the MS-assigned value of the NRI to retrieve from the P-TMSI. This value must not exceed the maximum possible value specified by the NRI length. The NRI value must be unique across the pool or across all overlapping pools.

*nri\_value* must be an integer from 1 to 63 to identify a specific SGSN in a pool. Use of 0 (zero) value is not recommended.

Multiple NRI values can be identified by providing multiple nri-values separated by a blank space for example:

**nri length 6 nri-value 29 43 61**

The NRIs configured using this keyword will be used only in pooled area if the keyword **non-pooled-nri-value** is configured, else the NRIs configured using the **nri-value** keyword will be used for both pooled and non-pooled areas.

**non-pooled-nri-value *value***

If pooling is supported (the **null-nri-value** keyword is configured) use this keyword to configure values of NRIs to be used for non-pooled area. If the NRI CLI is configured as **nri length *length\_value* nri-value *values* non-pooled-nri-value *values*** (null-nri-value is not configured, that is pooling not supported at SGSN), NRIs will be used from "non-pooled-nri-value" irrespective of RNC/BSC being pooled or non-pooled.

**Note**

The same NRI can be configured using both the keywords **nri-value** and **non-pooled-nri-value**, this implies the NRI can be used either in pooled area or non-pooled area. If an NRI is configured for both pooled and non-pooled areas, then the SGSN re-uses the same NRI when moving from pooled to non-pooled areas and vice versa.

**Usage Guidelines**

Use this command to identify the SGSN identified with the NRI in the MS generated P-TMSI.

This command adds or removes the Iu Flex configuration for this SGSN service. When using Iu Flex, all keywords must be defined. The command can be repeated to specify different values for any of the keyword parameters. If more than one NRI is configured, the SGSN service will round-robin between the available NRIs when new subscribers (re)connect.

Use this command to retrieve the NRI (identity of an SGSN) stored in bits 23 to 18 of the packet-temporary mobile subscriber identity (P-TMSI). If more than one NRI value is configured, the SGSN service will round-robin between the available NRIs when new subscribers (re)connect.

When using MOCN mode for network sharing without SGSN pooling, the NRI length and the NRI value should both be used.



---

**Important**

In Releases prior to 14.0, selection of one of the keywords (**nri-value** or **null-nri-value**) was mandatory. With Release 14.0 use of the keywords is optional.

---

**Example**

The following command specifies the NRI length as 5 bits, identifies SGSN 23 with MCC 123 and MNC 22 and LAC 222 and RAC 12 for offloading procedure with NRIs 6 and 41:

```
nri length 5 null-nri-value 34 non-broadcast mcc 123 mnc 22 lac 222 rac  
12 nri-value 6 41
```

## override-lac-li

Refer to the *Lawful Intercept Configuration Guide* for a description of this command.

## override-rac-li

Refer to the *Lawful Intercept Configuration Guide* for a description of this command.

# qos-modification

This command provides the operator the flexibility to control RAB setup and negotiations based on the RNC.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

```
qos-modification { inform-rnc-before-ue | allow-s4-rab-negotiation
[inform-pgw] }
no qos-modification [ inform-rnc-before-ue | allow-s4-rab-negotiation
[inform-pgw] ]
```

**no**

The SGSN uses the default behavior

- to inform the UE before the RNC or
- to reject PDP Context Activation (in compliance with TS 23.00 section 9.2.2.1A), if the RNC negotiates QoS in the RAB assignment response when the S4 interface is used for the PDP context.

**inform-rnc-before-ue**

When this keyword is used the SGSN informs the RNC of new QoS before informing the UE. On execution of the command with this keyword, the SGSN initiates a RAB assignment to inform the RNC followed by UPCQ towards the GGSN / Modify towards the UE based on whether or not the RNC downgrades the QoS.

**allow-s4-rab-negotiation**

With this keyword used as part of the configuration, if the S4 interface is used for PDP activation then the SGSN locally accepts what the RNC sends as QoS in the RAB Assignment Response and sends that QoS in the Activate Response.

This CLI is applicable only for PDP activation. For any other scenario, if the RNC negotiates the QoS then the SGSN ignores this configuration and locally accepts the change and continues with the call.

**inform-pgw**

This CLI option is used to enable or disable sending of Modify Bearer Command to the PGW. By default this option is disabled. When this option is enabled, the S4-SGSN triggers a Modify Bearer Command if QoS is downgraded by the RNC in RAB Assignment Procedure. To avoid looping of messages between S4-SGSN and PGW, PCRF should be configured to "NOT" upgrade QoS when RAT-Type is 3G.

---

**Usage Guidelines**

This command enables the operator the flexibility to accommodate legacy RNCs that don't meet the parameters set by TS 23.060.



With **allow-s4-rab-negotiation**, this keyword is needed for activation cases only as the default behaviour, per 3GPP spec, is to reject activation, which is service impacting. Hence to avoid such service impacts a configuration is added to control the behavior

### Example

Use this command to override the SGSN default behavior during the PDP modification procedure.

```
qos-modification inform-rnc-before-ue
```

Use this command to override the SGSN default behavior and accept PDP activation with legacy RNCs using the S4 interface for context activation:

```
qos-modification allow-s4-rab-negotiation
```

## rac

Refer to the *Lawful Intercept Configuration Guide* for a description of this command.

# ran-protocol

This command specifies the IuPS service for the SGSN service to use for communication with the RAN.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

**ran-protocol iups-service** *iups\_srvc* [ **context** *ctx\_name* ]  
**no ran-protocol iups-service**

**no**

Removes the IuPS service information from the SGSN service configuration.

**iups-service** *iups\_srvc*

Specifies the name of an IuPS service already configured on the system.

*iups\_srvc* : Enter an alphanumeric string of 1 to 63 characters.

**ctx\_name**

*ctx\_name* : Enter the name of the IuPS context, an alphanumeric string of 1 to 63 characters.

---

**Usage Guidelines**

Use this command to configure the IuPS service context that the current SGSN service will use to communicate with the RAN. Up to 8 definitions can be defined for a single SGSN service to allow for multiple PLMNs support.

**Example**

The following command configures the SGSN service to use an IuPS service named **iups1** that has been configured. in the same context as the SGSN service:

```
ran-protocol iups-service iups1
```

# reporting-action event-record

This command enables the SGSN to log GMM/SM events in EDR files for 3G services.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

**reporting-action event-record**  
**[ default | no ] reporting-action event-record**

**default**

Disables the logging function.

**no**

Removes the logging function from the configuration file.

---

**Usage Guidelines**

This command is one of the steps needed to enable the SGSN to create a log for events such as Attach, RAU, and Activations. The log is an EDR (event data record) in CSV format. For details about how this feature works, refer to the *GMM-SM Event Logging* chapter in the *SGSN Administration Guide*.

**Related Commands:**

- To enable GMM/SM event logging for 2G services, the **reporting-action event-record** command must be configured in the GPRS service configuration.
- To enable a log to be generated in an EDR file, the **edr-module active-charging-service** command must be enabled in the Context configuration mode.
- To configure parameters for the logging file characteristics and for file transfer, use the commands in the EDR Module Configuration Mode.

**Example**

Enable GMM/SM event logging for 3G services:

```
reporting-action event-record
```

# s4-overcharge-protection

This command enables or disables Subscriber Overcharging Protection functionality for the S4-SGSN in the 3G network *and* associates a RANAP cause code group with the SGSN Service configuration.

---

## Product




---

### Important

We recommend that you enable Release Access Bearer, with the **release-access-bearer** command in the Call-Control Profile configuration mode, *before* this **s4-overcharge-protection** command is used to enable Subscriber Overcharging Protection.

---

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

## Syntax Description

**s4-overcharge-protection** **ranap-cause-code-group** *group\_name*  
**no s4-overcharge-protection**

**no**

Disables Subscriber Overcharging Protection functionality for 3G. Disabled is the default.

**ranap-cause-code-group** *group\_name*

Associates a RANAP cause code group with the SGSN Service configuration. You can enter a group's name before the cause code group is actually created but the names must match.

*group\_name*Enter an alphanumeric string up to 16 characters long to identify the cause code group.

---

## Usage Guidelines

The cause code group is created with the **cause-code-group** command in the LTE Policy configuration mode.

To see the name of the defined cause code group(s) or the configuration of the RANAP cause code groups, use the **show lte-policy cause-code-group [ name | summary ]** command in Exec mode.

To see the status of the Subscriber Overcharging Functionality and the associated RANAP cause code group, use Exec command **show gprs-service name** *service\_name*.




---

### Important

If Release Access Bearer is enabled and going out of the S4-SGSN, the ARRL bit will be included if this CLI is enabled and if LORC (loss of radio coverage) is detected.

---

**Example**

Enable Subscriber Overcharging Protection and associated cause code group *3Gccgp1* with a command similar to the following:

```
s4-overcharge-protection bssgp-cause-code-group 3Gccgp1
```

Disable Subscriber Overcharging Protection and automatically disassociate the cause code group with the SGSN Service configuration by using a command similar to the following:

```
no s4-overcharge-protection
```

# sgsn-number

This command defines the E.164 number that identifies this particular SGSN service context.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

---

**Syntax Description**

**sgsn-number** *E.164\_number*  
**no sgsn-number**

**no**

Removes the SGSN number configuration from the SGSN service configuration.

***E.164\_number***

Enter a maximum of 15 digits to define the 'phone' number associated with this SGSN service in the specified context.

---

**Usage Guidelines**

The SGSN supports multiple SGSN numbers – different numbers in the 2G GPRS service configuration and the the 3G SGSN service configuration. If an HLR-initiated dialog is received, the SGSN will perform a lookup based on the IMSI and find the correct SGSN number with which the MS is associated. Subsequent messaging will use this address.

**Example**

To delete the sgsn-number associated with this SGSN service context, enter:

```
no sgsn-number
```

# sgtp-service

This command creates an instance of an SGTP service and associates the SGTP service instance with this SGSN service.



## Important

This command is used in Releases 12.0 and 12.2. For Release 14.0 refer to the **associate** command.

## Product

SGSN  
PDG/TTG

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure** > **context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

## Syntax Description

**sgtp-service** *sgtp\_srvc\_name*  
**no sgtp-service**

### **sgtp\_srvc\_name**

Enter the name of an SGTP service that will be used by this SGSN service

*sgtp\_srvc\_name* : Enter a string of 1 to 63 alphanumeric characters.

## Usage Guidelines

Use this command to access the SGTP Service configuration mode to configure SGTP parameters.

## Example

```
sgtp-service sgtp1
```



## sm

This command configures session management parameters for this SGSN service. This command can be repeated multiple times to configure each parameter individually.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGSN Service Configuration

**configure > context** *context\_name* > **sgsn-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgsn-service)#
```

### Syntax Description

```
sm { T3385-timeout time | T3386-timeout time | T3395-timeout time |
guard-timer guard_seconds | ignore-asi | max-actv-retransmission number |
max-deactv-retransmission number | max-modf-retransmission number |
radio-priority from-arp arp-rp_prof_name | t3396 min minimum max maximum cause
cause_code | ue-3gpp-compliance-unknown restrict-16mbps }
default sm { T3385-timeout | T3386-timeout | T3395-timeout | guard-timer
| max-actv-retransmission | max-deactv-retransmission |
max-modf-retransmission }
no sm { ignore-asi | radio-priority from-arp | t3396 |
ue-3gpp-compliance-unknown [restrict-16mbps] }
```

#### default

Resets the selected timer to the system default value.

#### no

Removes the specified parameter configuration from this SGSN service configuration.

#### T3385-timeout

Retransmission timer for network-initiated Activate Request.

Default is 8 sec

#### T3386-timeout

Retransmission timer for network-initiated Modify Request.

Default is 8 sec

#### T3395-timeout

Retransmission timer for network-initiated Deactivate Request.

Default is 8 sec

**guard-timer guard\_seconds**

Sets the number of seconds before the session manager resources are cleared.

*guard\_seconds* is an integer from 30 to 150.

Default: 80 seconds

**ignore-asi**

Enables the operator to modify the SGSN service default configuration and instructs the SGSN to ignore the ASI bit in the SGSN Context Response during RAU-based handovers over Gn interfaces and to ignore establishing a RAB for any PDPs.

**radio-priority from-arp**

This keyword associates an ARP-RP Mapping Profile with the SGSN service. The profile is created and configured via the ARP-RP Mapping Profile configuration mode under the SGSN-Global configuration mode.

*arp-rp\_prof\_name* - Enter a string of 1 to 64 alphanumeric characters to identify the mapping profile and moves into the ARP-RP mapping profile configuration mode.

Use the **show configuration** command to display the association.

**max-actv-retransmission**

Configures maximum retries for activate PDP ctxt request.

Default is 4

**max-deactv-retransmission**

Configures maximum retries for deactivate PDP ctxt request.

Default is 4

**max-modf-retransmission**

Configures maximum retries for modify PDP ctxt request.

Default is 4

**t3396**

This keyword enables the session management (SM) T3396 back-off timer for the 3G service. When the SGSN is confronted by a situation involving congestion, the SGSN can assign the back-off timer value to the UEs and request the UEs not to access the network for a given period of time.

**min** *minimum*: Enter an integer from 1 to 15 to identify the minimum number of minutes that the timer will run; default is 15 minutes.

**max** *maximum*: Enter an integer from 1 to 30 to identify the maximum number of minutes the timer can run; default is 30 minutes.

**cause** *cause\_code*: Enter an integer from 1 to 255 to identify the appropriate rejection cause code. The default is 26. During congestion, the configured value is ignored and 26 is sent.

- During congestion, the SGSN randomly chooses a T3396 value from the configured range and sends that timer value to the UE in the Reject message with the cause code #26.

- The command can be repeated to define a maximum of 16 cause codes.

**ue-3gpp-compliance-unknown restrict-16mbps**

If this keyword is configured, the SGSN caps the APN-AMBR for non-GBR bearers to "16" Mbps and rejects the activation of GBR bearers with GBR higher than "16" Mbps.

If the **no** form of this keyword is configured, the APN-AMBR and GBR higher than "16" Mbps are allowed.

By default, the SGSN does not cap APN-AMBR or reject GBR bearer activation with bitrates higher than "16" Mbps.

---

**Usage Guidelines**

Repeat the command to configure multiple session management parameters for the SGSN service.

**Example**

Use a command similar to the following to set the expiry for 5 seconds for the session manager's T3385-timeout:

```
sm T3385-timeout 5
```





## SGTP Service Configuration Mode Commands

### Command Modes

The SGSN GPRS Tunneling Protocol (SGTP) Service configuration mode provides the configuration of GTP-C and GTP-U related parameters.

Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [direct-tunnel-disabled-ggsn](#), on page 582
- [disable-remote-restart-counter-verification](#), on page 584
- [do show](#), on page 586
- [end](#), on page 587
- [exit](#), on page 588
- [ggsn-fail-retry-timer](#), on page 589
- [gn-delay-monitoring](#) , on page 590
- [gtpc](#), on page 592
- [gtpu](#), on page 597
- [ignore-remote-restart-counter-change](#), on page 600
- [max-remote-restart-counter-change](#), on page 601
- [mbms](#), on page 603
- [path-failure](#), on page 604
- [pool](#), on page 605

# direct-tunnel-disabled-ggsn

This command makes it possible for the operator to disable direct tunneling on the basis of a GGSN.

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

---

## Syntax Description

**direct-tunnel-disabled-ggsn** *ipv4/ipv6\_address*  
**no direct-tunnel-disabled-ggsn** [ *ipv4/ipv6\_address* ]

### no

Deletes the direct-tunnel-disabled-ggsn configuration which results in re-enabling direct tunneling to the GGSN.

- Including an IPv4 or IPv6 address for a specific GGSN, re-enables direct tunneling for that specific GGSN.
- Excluding any IPv4 or IPv6 address from this command removes all direct-tunnel-disabled-ggsn definitions from the SGTP service configuration.

---

## Usage Guidelines

By default, GGSNs and RNCs are assumed to be capable of direct tunneling.

This command disables direct tunneling for a specified GGSN. The command can be repeated to disable direct tunneling for multiple GGSNs, thereby creating a 'disabled GGSN' list. Checking for a direct-tunnel-disabled GGSN is actually the last step in the PDP Activation procedure.

Restricting direct tunneling by a GGSN for an entire APN would be configured with the appropriate command in the APN profile configuration mode.

Restricting direct tunneling at the RNC level would be configured with the appropriate command in the IuPS service configuration mode.

This command can only be used if:

- The Direct Tunnel license has been purchased and applied.
- The Direct Tunnel feature is appropriately enabled via configurations of the IMEI profile and/or the Call-Control and APN profiles.
- The RNC does not restrict direct tunnel.
- The subscriber is not requesting CAMEL services.

**Example**

Use the following command to disable direct tunnel for the GGSN with the IP address of *141.21.4.20*:

```
direct-tunnel-disabled-ggsn 141.21.4.20
```

# disable-remote-restart-counter-verification

This command disables the SGSN's default behavior for verification of the remote peer's (GGSN) restart counter change values.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

**Syntax Description** [ **default** | **no** ] **disable-remote-restart-counter-verification**

## default

Enables the default behavior for verification of the GGSN's restart counter change values.

## no

Disables the command configuration and enables the default behavior of verification.

## Usage Guidelines

This command disables the default behavior used to minimize PDP deactivations resulting from path failure detection due to erroneous restart counter change messages.

With the execution of this command, the SGSN stops verifying restart counters received in Create PDP Context Response or Update PDP Context Response or Update PDP Context Request (CPCR, CPCPR, and UPCQ) messages. When the SGSN detects GTP-C path failure between the SGSN and the GGSN, the SGSN assumes PDP sessions at the GGSN are lost and the SGSN deactivates those PDP sessions towards the UE with an indication that the UE should activate the PDP session again. Potentially, this scenario could cause unnecessary traffic increases within the operator's network.

The SGSN default behavior provides the ability to manage GTP-C path failures detected as a result of spurious restart counter change value messages received from the GGSN. With the default behavior, path failure detection is based on receipt of restart counter change values in CPCR, CPCPR, and UPCQ messages. The session manager informs the SGTPC manager about a changed restart counter value. The SGTPC manager verifies the PDP context status by performing an echo request and echo response with the GGSN. Only then is the path failure confirmed if the echo response contains a new restart counter value. Then the SGTPC manager informs all session managers about the path failure and the session managers begin deactivation of the PDP contexts.

## Related commands:

- **max-remote-restart-counter-change**, also part of the SGTP service configuration mode, allows the operator to set a maximum variance between stored and received values for restart counter changes coming from the GGSN.
- **pdp-deactivation-rate**, in the SGSN Global configuration mode, allows the operator to modify the rate the SGSN deactivates PDP connections when GTP-C path failure is detected.



- **ignore-remote-restart-counter**, also part of the SGTP service configuration mode.

### Example

Disable the default behavior and stop verification with echo request/response process:

```
disable-remote-restart-counter-verification
```

Use either of the following commands to enable the default verification behavior:

```
no disable-remote-restart-counter-verification
```

```
default disable-remote-restart-counter-verification
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Changes the mode to the Exec mode.

# exit

Exits the SGTP Service configuration mode and returns to the Context configuration mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>exit</b>
<b>Usage Guidelines</b>	Return to the previous mode.

## ggsn-fail-retry-timer

This command sets the amount of time that a GGSN will be unavailable.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure > context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

**Syntax Description** **ggsn-fail-retry-timer** *value*  
**no ggsn-fail-retry-timer**

**no**

Removes the timer setting and disables the Local DNS feature.

**value**

Defines the amount of time, in seconds, that the GGSN is to be considered unavailable.

Enter an integer from 60 to 600. Default is 300.

**Usage Guidelines**

Setting this timer to a valid value enables the Local DNS feature - described in the *SGSN Administration Guide*. Setting this timer marks a GGSN in the primary GGSN pool as unavailable for PDP context creation and causes the SGSN to forward a PDP Context Activation Request to a remote pool GGSN, identified via a local (on the SGSN) DNS check. Marking a GGSN unavailable can be done if there is a reason to believe the GGSN is unavailable; for example, lack of response to GTP messages. Marking a GGSN as unavailable is usually done for a limited period to allow the GGSN time to recover.

**Example**

Enable the Local DNS feature and mark the GGSNs in the primary pool as unavailable for 4 minutes (240 seconds):

```
ggsn-fail-retry-timer 240
```

# gn-delay-monitoring

This command configures monitoring of Gn/Gp interface to check for the delay of packets between the SGSN and the GGSN.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

**Syntax Description**

```
gn-delay-monitoring [ num-delay number_delayed | num-no-delay-for-clear
number_normal | tolerance-seconds number_seconds ]
default gn-delay-monitoring [ num-delay | num-no-delay-for-clear |
tolerance-seconds ]
no gn-delay-monitoring
```

## default

Resets the specified parameter to the default value.

## no

Disables Gn/Gp monitoring for delayed GTP-C packets.

## num-delay *number\_delayed*

Defines the number of response messages, coming from the GGSN, that can be delayed (delay time defined by tolerance-seconds parameter) before the delay is flagged to generate an SNMP trap.

*number\_delayed*: Enter an integer from 1 to 500, default is 30.

## num-no-delay-for-clear *number\_normal*

Defines the number of consecutive response messages, coming from the GGSN, that must be received without delay (in normal response time) to clear the flag towards the GGSN.

*number\_normal*: Enter an integer from 1 to 500, default is 15.

## tolerance-seconds *number\_seconds*

Defines the 'normal' number of seconds the SGSN should wait for a response from the GGSN. After this time, the response would be considered 'delayed'.

*number\_seconds*: Enter an integer from 1 to 20, default is 4 seconds.

**Important**

The value for this parameter should be less than the value set for the **retransmission-timeout** parameter of the **gtpc** command, also in this configuration mode.

**Usage Guidelines**

With this command, the SGSN can monitor the control plane packet delay for GTP-C signaling messages on the SGSN's Gn/Gp interface towards the GGSN. If the delay crosses this configurable threshold, an alarm will be generated to prompt the operator.

A delay trap is generated when the GGSN response to an ECHO message request is delayed more than a configured amount of time and for a configured number of consecutive responses. When this occurs, the GGSN will be flagged as experiencing delay.

A clear delay trap is generated when successive ECHO Response (number of successive responses to detect a delay clearance is configurable), are received from a GGSN previously flagged as experiencing delay.

This functionality can assist with network maintenance, troubleshooting, and early fault discovery.

**Example**

Enable Gn/Gp monitoring for GTP-C packets that arrive from the GGSN with a delay greater than 5 seconds:

```
gn-delay-monitoring tolerance-seconds 5
```

# gtpc

Configure the GPRS Tunneling Protocol Control (GTP-C) settings for the SGTP service.

---

## Product

eWAG  
MME  
PDG/TTG  
SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

---

## Syntax Description

```
gtpc { bind address ipv4_address | dns-sgsn context context_name | echo-interval
interval_seconds | echo-retransmission { exponential-backoff [ [ min-timeout
timeout_seconds ] [ smooth-factor smooth_factor ] + ] | timeout timeout_seconds
} | guard-interval interval_seconds | ignore response-port-validation | ip
qos-dscp dscp_marking | max-retransmissions max_retransmissions |
retransmission-timeout timeout_seconds | send { common flags | rab-context
| target-identification-preamble } | sync-echo-with-peer }
no gtpc { bind address | dns-sgsn context | echo-interval | send {
common-flags | rab-context | target-identification-preamble } |
sync-echo-with-peer }
default gtpc { echo-interval | echo-retransmission | guard-interval |
ignore response-port-validation | ip qos-dscp | max-retransmissions |
retransmission-timeout | send { common-flags | rab-context |
target-identification-preamble } | sync-echo-with-peer }
```

### no

Disables the configured GTP-C setting.

### default

Resets the specified parameter to its default value.

### **bind address** *ipv4\_address*

Binds SGTP service to the IP address of the interface.

The bind address for the **gtpc** and **gtpu** commands should be the same.

*ipv4\_address* must be a standard IPv4 address.



**dns-sgsn context *context\_name***

Identify the context where the DNS client is configured to send the DNS query to get the peer SGSN address. If nothing is configured, the system assumes the DNS client is configured in the same context where the SGTP service is configured.

*context\_name*: Enter a string of 1 to 79 alphanumeric characters to identify the context.

There is a `dns-sgsn` command option in the call-control profile, which, if configured, would override the configuration in this SGTP service configuration.

**echo-interval *interval\_seconds***

Configures the duration between echoes.

*seconds* Enter an integer from 0 through 3600.

Default: 60

**echo-retransmission { exponential-backoff [ [ min-timeout *timeout\_seconds*] [ smooth-factor *smooth\_factor*] + ] | timeout *timeout\_seconds* }**

Configures the retransmission parameters for GTP-C echo messages. The operator can choose to use either an "exponential-backoff" timers or a "fixed-retransmission" timer:

- The **exponential-backoff** timer uses an exponential backoff algorithm to better manage the GTP-C path during periods of network congestion and to perform exponential-backoff echo timing. The exponential-backoff timer uses a calculated round-trip time (RTT), as well as a configurable factor or a multiplier to be applied to the RTT statistic. Different paths can each have a different RTT, so the exponential-backoff timer can be configured for multiple paths. One or both of the following parameters can be configured to refine the exponential-backoff timer configuration:
  - **min-timeout *timeout\_seconds***: Specifies the minimum time period (in seconds) for the exponential-backoff echo timer. If the RTT multiplied by the smooth factor is less than this minimum timeout value, then the node uses the value set with this keyword. Range is 1-20. Default is 5.
  - **smooth-factor *smooth\_factor***: Specifies the multiplier that the exponential-backoff echo timer uses when calculating the time to wait to send retries, when the gateway has not received a response from the peer within value defined for the path echo interval. Range is 1-5. Default is 2.
- **timeout *timeout\_seconds***: Configures the number of seconds for the fixed retransmission timeout value for GTP-C echo messages. Range from 1 to 20. Default is 5.

**guard-interval *interval\_seconds***

Configures the interval (in seconds) for which the SGTP maintains responses sent to gateway. This optimizes the handling of retransmitted messages. This value should be configured to be greater than the gateway's configuration for max-retries multiple by retry-interval.

*interval\_seconds*: Enter an integer from 10 to 3600.

Default: 100

**ignore response-port-validation**

This keyword instructs the gateway to ignore the response port validation.

For the gateway to process incoming GTP responses to an *incorrect* port, this keyword must be entered, and the same **bind address** must be configured for GTPC and GTPU in the SGTP service.

Default: Disabled. To reset the default for this parameter, you must enter the following command: **no gtpc ignore response-port-validation**.

### **ip qos-dscp *dscp\_marking***

Configures the diffserv code point marking to be used per hop behavior (PHB) when sending GTP-C messages originating from the session manager and SGTPC manager.

Note that CS (class selector) mode options below are provided to support backward compatibility with the IP precedence field used by some network devices. CS maps one-to-one to IP precedence, i.e., CS1 is IP precedence value 1. If a packet is received from a non-DSCP aware router, that used IP precedence markings, then the DSCP router can still understand the encoding as a Class Selector code point.

*dscp\_marking*: Enter one of the following values:

- **af11**: Marks traffic as Assured Forwarding 11 PHB (high throughput data)
- **af12**: Marks traffic as Assured Forwarding 12 PHB (high throughput data)
- **af13**: Marks traffic as Assured Forwarding 13 PHB (high throughput data)
- **af21**: Marks traffic as Assured Forwarding 21 PHB (low latency data)
- **af22**: Marks traffic as Assured Forwarding 22 PHB (low latency data)
- **af23**: Marks traffic as Assured Forwarding 23 PHB (low latency data)
- **af31**: Marks traffic as Assured Forwarding 31 PHB (multimedia streaming)
- **af32**: Marks traffic as Assured Forwarding 32 PHB (multimedia streaming)
- **af33**: Marks traffic as Assured Forwarding 33 PHB (multimedia streaming)
- **af41**: Marks traffic as Assured Forwarding 41 PHB (multimedia conferencing).
- **af42**: Marks traffic as Assured Forwarding 42 PHB (multimedia conferencing)
- **af43**: Marks traffic as Assured Forwarding 43 PHB (multimedia conferencing)
- **be** : Designates use of Best Effort forwarding PHB. This is the default value.
- **cs0** : Designates use of class selector mode 0 PHB.
- **cs1** : Designates use of class selector mode 1 PHB.
- **cs2** : Designates use of class selector mode 2 PHB.
- **cs3** : Designates use of class selector mode 3 PHB.
- **cs4** : Designates use of class selector mode 4 PHB.
- **cs5** : Designates use of class selector mode 5 PHB.
- **cs6** : Designates use of class selector mode 6 PHB.
- **cs7** : Designates use of class selector mode 7 PHB.
- **ef** : Designates use of Expedited Forwarding PHB

Default: **be** (best effort)

#### **max-retransmissions** *max\_retransmissions*

Configures the maximum number of retries for packets.

*max\_retransmissions*: Enter an integer from 0 to 15.

Default: 4

#### **retransmission-timeout** *timeout\_seconds*

Configures the control packet retransmission timeout in GTP, in seconds.

*timeout\_seconds*: Enter an integer value from 1 through 20.

Default: 5

#### **send { common-flags | rab-context | target-identification-preamble }**

- **common-flags** : This option configures the SGTP service to include or exclude the common flags IE during an Inter-SGSN RAU. When selected, the default is to send the common flags IE.



#### **Important**

Sending of common flags must be enabled to configure dual PDP type (IPv4v6) addressing with the **dual-address-pdp** command in the SGSN global configuration mode.

- **rab-context** : This option configures the SGTP service to include/exclude the radio access bearer (RAB) context IE in SGSN 'context response' message during Inter-SGSN Routing Area Update procedure. Default is to send the RAB context IE.
- **target-identification-preamble** : This option configures the SGTP service to include the Target Identification IE preamble byte in the target-id of Relocation Requests that it sends. By default, the preamble is not included. In accordance with 3GPP TS 29.060, v9.2.0, if the preamble is included then multiple optional parameters, such as Extended RNC ID, are encoded. Extended RNC ID expands the ID range from 4095 to 65535.

In situations of MME interaction with the SGSN during SRNS procedures via GTPv1, the SGSN can use this Extended RNC ID field to indicate the Target RNC ID associated with the MME and vice versa.

Default: sending RAB context IE.

#### **sync-echo-with-peer**

This keyword is applicable to the SGSN only.

This keyword enables the SGSN to synchronize path management procedures with the peer after a GTP service restart recovery.

After GTP service recovery, the SGSN restarts the timers for GTP echo transmission, hence a drift in echo request transmission time (from the pre-recovery time) can occur causing the SGSN to be out of sync with the peer. By using this keyword, when the SGSN receives the first Echo Request (GTPC or GTPU) from the peer after the GTP service restart, in addition to replying with an ECHO Response, the SGSN transmits an ECHO Request to the peer and the SGSN restarts the timers associated with the path management procedures. This causes the path management procedure at SGSN to synchronize with the peer node.

Default: Enabled

---

**Usage Guidelines**

Use this command to configure GTP-C settings for the current SGTP service. Repeat the command as needed to configure all required GTP-C parameters.

**Example**

Following command excludes the radio access bearer (RAB) context IE in the SGSN Context Response message during the inter-SGSN RAU procedure:

```
no gtpc send rab-context
```

Configure the SGSN to send *common flags* with all GTP-C messages:

```
gtpc send common-flags
```

Set the SGSN to use GTPC echo-retransmission with exponential-backoff and both filters set for default:

```
gtpc echo-retransmission exponential-backoff
```

# gtpu

This command configures the GPRS Tunneling Protocol user data plane parameters (GTP-U) for this SGTP service.

---

**Product**

eWAG  
PDG/TTG  
SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

---

**Syntax Description**

```
gtpu { bind address ipv4_address | echo-interval interval_seconds |
echo-retransmission { exponential-backoff [ [ min-timeout timeout_seconds ]
[ smooth-factor smooth_factor ] + ] | timeout timeout_seconds } |
max-retransmissions max_retransmissions | retransmission-timeout timeout_seconds
| sync-echo-with-peer
no gtpu { bind address ipv4_address | echo-interval | sync-echo-with-peer }
default gtpu { echo-interval | echo-retransmission | max-retransmissions
| retransmission-timeout | sync-echo-with-peer }
```

**no**

Removes the configuration for the specified parameter from the current SGTP service configuration.

**default**

Resets the specified GTP-U parameter to its factory default.

**bind address** *ipv4\_address*

Defines the GTP-U Gn' interface IP address that binds to this SGTP service.

The **gtpu** and the **gtpc** commands should be configured with the same bind address.

*ipv4\_address*: Enter a standard dotted-quad IPv4 address.

**echo-interval** *interval\_seconds*

Configures the echo interval.

*interval\_seconds*: Enter an integer from 60 through 3600.

Default: 60

**echo-retransmission { exponential-backoff [ [ min-timeout *timeout\_seconds* ] [ smooth-factor *smooth\_factor* ] + ] | timeout *timeout\_seconds***

Configures the retransmission parameters for GTP-U echo messages. The operator can choose to use either an "exponential-backoff" timers or a "fixed-retransmission" timer:

- The **exponential-backoff** timer uses an exponential backoff algorithm to better manage the GTP-U path during periods of network congestion and to perform exponential-backoff echo timing. The exponential-backoff timer uses a calculated round-trip time (RTT), as well as a configurable factor or a multiplier to be applied to the RTT statistic. Different paths can each have a different RTT, so the exponential-backoff timer can be configured for multiple paths. One or both of the following parameters can be configured to refine the exponential-backoff timer configuration:
  - **min-timeout *timeout\_seconds***: Specifies the minimum time period (in seconds) for the exponential-backoff echo timer. If the RTT multiplied by the smooth factor is less than this minimum timeout value, then the node uses the value set with this keyword. Range is 1-20. Default is 5.
  - **smooth-factor *smooth\_factor***: Specifies the multiplier that the exponential-backoff echo timer uses when calculating the time to wait to send retries, when the gateway has not received a response from the peer within value defined for the path echo interval. Range is 1-5. Default is 2.
- **timeout *timeout\_seconds*** Configures the number of seconds for the fixed retransmission timeout value for GTP-U echo messages. Range from 1 to 20. Default is 5.

**max-retransmissions *max\_retransmissions***

Configures the maximum number of retries for retransmitting packets.

*max\_retransmissions*: Must be an integer from 0 through 15.

Default: 4

**retransmission-timeout *timeout\_seconds***

Configures the retransmission timeout of packets, in seconds.

*timeout\_seconds*: Must be an integer from 1 through 20.

Default: 5

**sync-echo-with-peer**

This keyword is applicable to the SGSN only.

This keyword enables the SGSN to synchronize path management procedures with the peer after a GTP service restart recovery.

After GTP service recovery, the SGSN restarts the timers for GTP echo transmission, hence a drift in echo request transmission time (from the pre-recovery time) can occur causing the SGSN to be out of sync with the peer. By using this keyword, when the SGSN receives the first Echo Request (GTPC or GTPU) from the peer after the GTP service restart, in addition to replying with an ECHO Response, the SGSN transmits an ECHO Request to the peer and the SGSN restarts the timers associated with the path management procedures. This causes the path management procedure at SGSN to synchronize with the peer node.

Default: Enabled

**Usage Guidelines**

Use this command to configure the GTP-U settings for the SGTP service.

**Example**

Set the GTPU echo-interval for 5 seconds:

```
gtpu echo-interval 5
```

Set the gateway to use GTP-U echo-retransmission with exponential-backoff and the smooth-factor set for 4:

```
gtpc echo-retransmission exponential-backoff smooth-factor 4
```

## ignore-remote-restart-counter-change

With the inclusion of the **disable-remote-restart-counter-verification** command, this command has been deprecated.



## max-remote-restart-counter-change

Use this command to set a restart counter change window to avoid service deactivations and activations that could cause large bursts of network traffic if the restart counter change messages from the GGSN are erroneous.

---

### Product

eWAG  
SGSN

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

---

### Syntax Description

**max-remote-restart-counter-change** *variance*  
**default max-remote-restart-counter-change**

#### default

If this keyword is used or if a variance window is not configured, then the default value will be 255 and the default behavior will be to detect a restart on any change.

#### variance

Set a number (an 8-bit value) that will define the variance range for restart counter change values compared between the gateway's stored value and the value received in messages from the GGSN. Valid entry is an integer from 1 to 255; default is 255.

Value of 32 is recommended as it provides a sufficient window to allow the gateway to handle delayed messages with old restart counters.

---

### Usage Guidelines

When the gateway detects GTP-C path failure between the gateway and the GGSN, the gateway assumes PDP sessions at the GGSN are lost and the gateway deactivates corresponding PDP sessions towards the UE with an indication that the UE should activate the PDP session again. Detection is based on receipt of restart counter change values in Create PDP Context Response or Update PDP Context Response or Update PDP Context Request (CPCR/UPCR/UPCQ) messages. Potentially, this scenario can cause major traffic increases within the operator's network. It is possible that the messages received from the GGSN are spurious.

The gateway default behavior provides the ability to verify possible GTP-C path failures detected as a result of spurious restart counter change messages received from the GGSN. With the default behavior, the session manager informs the SGTPC manager about a changed restart counter value. The SGTPC manager responds by verifying the PDP context status by performing an Echo Request / Echo Response with the GGSN. If the Echo Response includes a new restart counter change value, then the session manager considers the path failure confirmed and begins the PDP context deactivation sequence.

Use this command to avoid unnecessary path failures and deactivations by setting a restart counter change value 'window' or range of values. With this window, the gateway only accepts linearly increasing values for restart counter change values that are within the specified range of accepted changes before the SGTPC manager verifies. For example, if the allowed window for restart counter change value is set to 32 and the

last learnt restart counter change value from the GGSN is 15, then the gateway should detect a restart only if the new restart counter value is between 16 and 47 (range of 32) and then the gateway would verify with the Echo Request/Response. If the received restart counter change value was 200 and the current learnt value was 15 with a window of 32, then the 200 would be ignored as a spurious value.

Also, use this command to set a restart counter change values window to avoid possible 'race conditions' (as defined in 3GPP TS 23.007 v8.7.0) where a new message arrives prior to an older message. This 'race condition' occurs when the gateway's stored restart counter value for the GGSN is larger than the restart counter value received in the messages received from the GGSN.

**Related commands:**

- **disable-remote-restart-counter-verification** - also part of the SGTP service configuration mode, this command allows the operator to disable the default behavior.
- **pdp-deactivation-rate**, in the SGSN Global configuration mode, this allows the operator to modify the rate the gateway deactivates PDP connections when GPT-C path failure is detected.
- **ignore-remote-restart-counter**, also part of the SGTP service configuration mode.

**Example**

Use the following command to configure an allowed restart counter change value window of 32:

```
max-remote-restart-counter-change 32
```

# mbms

Enables / disables the Multimedia Broadcast Multicast Service.



---

**Important**

The **mbms** command and parameter-configuring keywords are under development for future release and should not be used or included in your configuration at this time.

---

# path-failure

This command specifies the method for determining if path failure has occurred.

---

## Product

eWAG  
SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure** > **context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

---

## Syntax Description

**path-failure detection-policy gtp { echo | non-echo } +  
{ default | no } path-failure detection-policy**

### default

Resets the specified path failure parameter to default.

Default: echo (for both GTPC and GTPU)

### no

Deletes the path-failure definition from the configuration.

### echo

Path failure is detected when the retries of echo messages time out.

### non-echo

Path failure is detected when the retries of non-echo messages time out.

---

## Usage Guidelines

Use this command to define the policy to detect gtp path failure.

### Example

Set *echo* as the policy detection type:

```
path-failure detection-policy gtp echo
```

# pool

This command enables the default SGSN functionality for (flex) pooling and enables inclusion of the configured pool hop-counter count in new SGSN context/identify request messages.

---

**Product** SGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > SGTP Service Configuration

**configure > context** *context\_name* > **sgtp-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgtp-service)#
```

---

**Syntax Description**

```
pool { default-sgsn | hop-counter count }
no pool { default-sgsn | hop-counter }
default pool hop-counter
```

## **no**

Disables the default SGSN pooling functionality or removes the SGSN pool hop-counter IE from the GTP Identity/context requests.

## **default**

Removes the SGSN pool hop-counter IE from the GTP Identity/context requests.

## **default-sgsn**

Enables default SGSN pooling functionality.

## **hop-counter** *count*

Enables and configures the SGSN pool hop-counter to set the number of hops and to include the configured count in the **new** SGSN Context Requests or the **new** SGSN Identify Requests.

If **default-sgsn** is enabled, then any messages relayed will have the default value of 4 for the counter if the message does not include this hop-counter ID.

*count*: Enter an integer from 1 to 255.

Default: 4

---

## **Usage Guidelines**

Use this command to enable the default flex functionality without exposing the pool (flex) structure. This functionality provides a means for SGSNs outside of the pool to reach a pooled SGSN on the basis of its NRI.

Once the pooling has been enabled. Repeat the command using the **hop-counter** keyword to enable inclusion of the hop-counter IE in SGSN context/identify request messages and to configure the count for the pooling hop-counter. If the SGSN is behaving as the 'default SGSN', this SGSN will forward (relay) requests with the hop-count included to the target SGSN.

**Example**

Enable the default pooling functionality which allows an outside SGSN to reach a pooled SGSN:

```
pool default-sgsn
```

Set the hop-count to be included in messages to 25:

```
pool hop-count
```



## S-GW Access Peer Profile Configuration Mode Commands

---

MME restoration is a 3GPP specification-based feature designed to gracefully handle the sessions at S-GW once S-GW detects that the MME has failed or restarted. If the S-GW detects an MME failure based on a different restart counter in the Recovery IE in any GTP Signaling message or Echo Request / Response, it will terminate sessions and not maintain any PDN connections.

As a part of this feature, if a S-GW detects that a MME or S4-SGSN has restarted, instead of removing all the resources associated with the peer node, the S-GW shall maintain the PDN connection table data and MM bearer contexts for some specific S5/S8 bearer contexts eligible for network initiated service restoration, and initiate the deletion of the resources associated with all the other S5/S8 bearers.

---

### Command Modes

This configuration mode enables operators to configure a peer profile for the Network Triggered Service Restoration feature.

Exec > Global Configuration > Peer Profile Configuration

**configure** > **peer-profile service-type sgw-access name** *profile\_name*

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-peer-profile-sgw-access)#
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [description, on page 608](#)
- [do show, on page 609](#)
- [end, on page 610](#)
- [exit, on page 611](#)
- [ntsr, on page 612](#)

# description

Creates a textual description for this S-GW access peer profile.

---

**Product** S-GW

---

**Privilege** Administrator, Security Administrator

---

**Command Modes** Exec > Global Configuration > Peer Profile Configuration

**configure > peer-profile service-type sgw-access name** *profile\_name*

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-peer-profile-sgw-access)#
```

---

**Syntax Description** **description** *string*

**description** *string*

A text string that describes this S-GW access peer profile. The description can be from 1 to 64 alphanumeric characters in length.

---

**Usage Guidelines** Use this command to create a textual string that describes this S-GW access peer profile.

## Example

To create a description titled SGWACCESS:

```
description SGWACCESS
```



# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

**end**

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** **end**

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ntsr

Enables network triggered service restoration (NTSR) and identifies the Pool ID to use for the feature.

---

## Product

S-GW

---

## Privilege

Administrator, Security Administrator

---

## Command Modes

Exec > Global Configuration > Peer Profile Configuration

**configure** > **peer-profile service-type sgw-access name** *profile\_name*

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-peer-profile-sgw-access)#
```

---

## Syntax Description

**ntsr pool-id** *number*  
**no ntsr-pool-id** *number*  
**default ntsr-pool-id** *number*

### default

The specified NTSR pool ID will be used as the default.

### no

Disables the specified option.

### ntsr pool-id

Specifies the NTSR pool ID to use for the NTSR feature. NTSR pool IDs and pool types are configured in Global Configuration Mode using the **ntsr pool-id** command.

---

## Usage Guidelines

Use this command to configure an SGW Access Peer Profile for the NTSR feature.

### Example

To enable NTSR for NTSR pool ID 1

```
ntsr pool-id 1
```



## S-GW Paging Profile Configuration Mode Commands

---

When some operators add an additional IMS service besides VoLTE such as RCS, they can use the same IMS bearer between the two services. In this case, separate paging is supported at the MME using an ID which can be assigned from the S-GW according to the services, where the S-GW distinguishes IMS services using a small DPI function to inspect where the traffic comes from using an ID which is assigned from SGW according to the services. The S-GW distinguishes IMS services using a small DPI function to inspect where the traffic comes from (for example IP, Port and so on). After the MME receives this ID from the S-GW after IMS service inspection, the MME will do classified separate paging for each of the services as usual.

---

### Command Modes

This chapter describes SGW paging profile configuration mode commands. These commands support Separate Paging for IMS Service Inspection.

Exec > Global Configuration > S-GW Paging Profile Configuration

**configure > sgw-paging-profile three tuple**

Entering the above command sequence results in the following prompt:

```
[local] host_name(sep-paging-default) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [do show, on page 614](#)
- [end, on page 615](#)
- [exit, on page 616](#)
- [ipv4 | ipv6, on page 617](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.


**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.



## ipv4 | ipv6

Enables operators to specify a 3-tuple lookup (source IP address, source port and protocol) on the inner IP packet of the GTPU data packet at the S-GW. This configuration is to support the Separate Paging for IMS Service Inspection feature on the S-GW.

**Product** S-GW

**Privilege** Administrator, Security Administrator

**Command Modes** Exec > Global Configuration > S-GW Paging Profile Configuration

**configure > sgw-paging-profile three tuple**

Entering the above command sequence results in the following prompt:

```
[local] host_name(sep-paging-default)#
```

**Syntax Description** [ **no** ] { [ **ipv4** *ipv4\_address* | **ipv6** *ipv6\_address* ] **port** *source\_port\_num* **protocol** { [ **tcp** | **udp** ] } **paging-identifier** *integer*

**no**

Removes the specified paging profile configuration.

**ipv4** *ipv4\_address*

Specifies the IPv4 address to use for Separate Paging for IMS. Must be in IPv4 address format.

**ipv6** *ipv6\_address*

Specifies the IPv6 address to use for Separate Paging for IMS. Must be in IPv6 address format.

**port** *source\_port\_num*

Specifies the source port on the S-GW to use for Separate Paging for IMS. Must be an integer from 1 to 65535.

**protocol** *tcp | udp*

Specifies the protocol type to which this SGW paging profile applies. Must be either **tcp** or **udp**.

**paging-identifier** *integer*

Specifies a service identifier for this SGW paging profile (for example, Data 0, VoLTE 1, RCS 2, and so on). Must be an integer from 0 to 255.

### Usage Guidelines

Use this command to identify an IMS specific paging procedure by performing a 3-tuple lookup (source IP address, Source Port and Protocol [TCP/UDP]) on the inner IP packet of the GTPU data packet at Serving Gateway. The Downlink Data Notification (DDN) message from the S-GW would carry a private extension IE with an identifier, which would denote if the paging procedure is for a data, Volte or RCS packet. This identifier helps the MME to apply different paging policies.

This configuration must be associated with an APN Profile by using the **associate** command in APN Profile Configuration Mode.

### Example

The following example configures a paging procedure consisting of an IPv4 address, source port, protocol, and paging identifier.

```
ipv4 1.1.1.1 port 10 protocol tcp paging-identifier 0
```



## S-GW Service Configuration Mode Commands

The S-GW (Serving Gateway) Service Configuration Mode is used to create and manage the relationship between an eGTP service used for either ingress or egress control plane and user data plane network traffic.

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [accounting context, on page 621](#)
- [accounting mode, on page 622](#)
- [accounting stop-trigger, on page 623](#)
- [associate, on page 624](#)
- [ddn failure-action, on page 627](#)
- [ddn isr-sequential-paging, on page 628](#)
- [ddn success-action no-user-connect ddn-retry-timer, on page 629](#)
- [ddn temp-ho-rejection mbr-guard-timer, on page 630](#)
- [ddn throttle, on page 632](#)
- [do show, on page 635](#)
- [egtp-service, on page 636](#)
- [end, on page 637](#)
- [exit, on page 638](#)
- [gtpc handle-collision upc nrupe, on page 639](#)
- [gtpu-error-ind, on page 640](#)
- [mag-service, on page 642](#)
- [ntsr session-hold timeout, on page 643](#)
- [page-ue, on page 644](#)
- [paging-policy-differentiation, on page 645](#)
- [path-failure, on page 647](#)
- [pgw-fteid-in-relocation-cs-rsp, on page 649](#)

- [plmn](#), on page 650
- [reporting-action](#), on page 651
- [timeout idle](#), on page 652

# accounting context

Configures the GTPP accounting context and group selection for S-GW service.

---

**Product**

S-GW  
SAEGW

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

**Syntax Description**

**accounting context** *name* [ **gtp group** *name* ]  
**no accounting context**

**no**

Removes the configured accounting context from this service.

**context name**

Specifies the context where GTPP accounting is performed.

*name* must be an existing context configured on the system expressed as an alphanumeric string of 1 through 79 characters.

If an accounting context name is not configured in the S-GW service, the context where the S-GW service resides is considered the accounting context and the default GTPP group is used.

**gtp group name**

Specifies a GTPP group used to perform GTPP accounting.

*name* must be an existing GTPP group configured on the system expressed as an alphanumeric string of 1 through 79 characters.

If a GTPP group is not configured, the system will use the default GTPP group in the specified accounting context. If the accounting context is not specified, the system will use default GTPP group in the context where the S-GW service resides.

---

**Usage Guidelines**

Use this command to specify the accounting context and/or GTPP accounting group the S-GW service will use to perform GTPP accounting.

**Example**

The following command specifies a GTPP accounting context named *acct-2* and a GTPP accounting group named *gtp-grp-3* as the context and group the S-GW service will use:

```
accounting context acct-2 gtp group gtp-grp-3
```

## accounting mode

Configures the mode to be used for accounting – GTPP (default), RADIUS/Diameter or None for S-GW service.

---

### Product

S-GW  
SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

[ **default** ] **accounting mode** { **gtp** | **none** | **radius-diameter** }

#### **default**

Sets the accounting mode to GTPP.

#### **gtp**

Specifies that GTPP accounting is performed. This is the default mode.

#### **none**

Specifies that no accounting will be performed for the S-GW service.

#### **radius-diameter**

Specifies that RADIUS/Diameter will be performed for the S-GW service.

---

### Usage Guidelines

Use this command to specify the accounting mode for the S-GW service. However, an accounting mode configured for the call-control profile will override this setting. For additional information on accounting mode and its relationship to operator policy, refer to the *Serving Gateway Administration Guide*.

#### **Example**

The following command specifies that RADIUS/Diameter accounting will be used for the S-GW service:

```
accounting mode radius-diameter
```

# accounting stop-trigger

Configures the trigger point for accounting stop CDR. Default is on session deletion request.

---

## Product

S-GW  
SAEGW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

## Syntax Description

**accounting stop-trigger custom**  
**default accounting stop-trigger**

### default

Accounting stop CDR triggered once Delete Session/Delete Bearer Request is received at S-GW.

### custom

Synchronizes the timestamp in the SGWRECORD CDR and PGWRECORD CDR if the MME cannot reach the UE. When configured, the SGW will also trigger the Accounting stop CDR after receiving the answer (accept for Delete session request) from the MME.

---

## Usage Guidelines

Use this command to specify the trigger point for accounting stop CDR for this S-GW service.

### Example

The following command specifies that accounting stop trigger would be at response of session deletion:

```
accounting stop-trigger custom
```

# associate

Associates the S-GW service with QoS and policy control and charging configurations.

---

## Product

S-GW  
SAEGW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

## Syntax Description

```
associate { access-peer-map | accounting-policy name | egress-proto { gtp
| gtp-pmip | pmip } [ egress-context name | emps-profile emps_profile_name
| gtpc-load-control-profile name | gtpc-overload-control-profile name
| egtp-service name ] [ mag-service name ] ] | ims-auth-service name |
ingress egtp-service name | peer-map name | qci-qos-mapping name |
subscriber-map name
no associate { access-peer-map | accounting-policy | egress-proto [
egress-context [ egtp-service ] [ mag-service ] ] | emps-profile |
ims-auth-service | ingress egtp-service | peer-map | qci-qos-mapping |
subscriber-map }
```

### **no**

Removes the specified association from the S-GW service.

### **access-peer-map** *name*

Associates the access/ingress side of the peer-map to the configured S-GW service.

*name* must be an existing peer-map expressed as an alphanumeric string of 1 through 63 characters.

### **accounting-policy** *name*

Associates the S-GW service with an accounting policy configured in the same context.

*name* must be an existing accounting policy expressed as an alphanumeric string of 1 through 63 characters.

Accounting policies are configured through the **policy accounting** command in the Context Configuration Mode.

### **egress-proto** { **gtp** | **gtp-pmip** | **pmip** } [ **egress-context** *name* [ **egtp-service** *name* ] [ **mag-service** *name* ] ]

Associates and configures the egress protocol for this S-GW service.

**gtp**: Specifies that GTP is to be used for the S-GW service egress.

**gtp-pmip**: Specifies that either GTP or PMIP is to be used for the S-GW service egress.



**pmip:** Specifies that PMIP is to be used for the S-GW service egress.

**egress-context *name*:** Specifies that the context in this keyword is to be used for the S-GW service egress.  
*name* must be an existing context on this system expressed as an alphanumeric string of 1 through 63 characters.

**egtp-service *name*:** Specifies that the service in this keyword is to be used for the S-GW service egress.  
*name* must be an existing eGTP service on this system expressed as an alphanumeric string of 1 through 63 characters.

**mag-service *name*:** Specifies that the service in this keyword is to be used for the S-GW service egress.  
*name* must be an existing MAG service on this system expressed as an alphanumeric string of 1 through 63 characters.

**emps-profile *emps\_profile\_name***

Specifies that an eMPS profile is to be associated with an existing S-GW service in this context.

*emps\_profile\_name* must be a string of size 1 to 63 and treated as case insensitive.

**gtpc-load-control-profile *name***

Associates a configured GTPC Load Control Profile with this S-GW service.

*name* must be an existing GTPC Load Control Profile on this system expressed as an alphanumeric string of 1 through 64 characters.

**gtpc-overload-control-profile *name***

*name* must be an existing GTPC Overload Control Profile on this system expressed as an alphanumeric string of 1 through 64 characters.

**ims-auth-service *name***

Associates the S-GW service with an IMS authorization service configured in the same context.

*name* must be an existing IMS auth service and be from 1 to 63 alphanumeric characters.

IMS authorization services are configured through the **ims-auth-service** command in the Context Configuration Mode.

**ingress egtp-service *name***

Associates and configures the eGTP service ingress for this S-GW service.

*name* must be an existing eGTP service on this system expressed as an alphanumeric string of 1 through 63 characters.

**peer-map *name***

Associates the access/ingress side of the peer-map to the configured S-GW service

*name* must be an existing peer-map configuration expressed as an alphanumeric string of 1 through 63 characters.

**qci-qos-mapping *name***

Associates the S-GW service with QCI to QoS mapping parameters.

*name* must be an existing QCI-QoS mapping configuration expressed as an alphanumeric string of 1 through 63 characters.

QCI-QoS mapping is configured through the **qci-qos-mapping** command in the Global Configuration Mode.

**subscriber-map *name***

Associates the S-GW service with subscriber map parameters.

*name* must be an existing subscriber map configuration expressed as an alphanumeric string of 1 through 63 characters.

Subscriber maps are configured through the **subscriber-map** command in the LTE Policy Configuration Mode.

**Usage Guidelines**

Use this command to select a pre-configured QoS mapping and/or policy control and charging configuration to be used by the S-GW service.

**Example**

The following command associates the S-GW service with an IMS authorization service named *ims-23*:

```
associate ims-auth-service ims-23
```

## ddn failure-action

Configures a timer value to delay paging for this UE when the S-GW has initiated a Downlink Data Notification (DDN) to the MME and has received back a DDN failure.

---

### Product

S-GW  
SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

**ddn failure-action pkt-drop-time** *seconds*  
**default ddn failure-action pkt-drop-time**

#### default

Resets the command to its default setting of 300 seconds.

#### failure-action pkt-drop-time *seconds*

Default: 300

Configures a timer that determines how long the S-GW will discard downlink data packets so the MME has enough time to receive the Modify Bearer Request and prevent further errors being sent to the S-GW in the DDN Ack message.

*seconds* must be an integer value from 1 to 300.

---

### Usage Guidelines

Use this command to set a timer value to delay the sending of excessive Downlink Data Notification messages to the MME (and receiving excessive DDN Ack message with errors from the MME) in cases when downlink data is arriving before the Modify Bearer Request is received. During the delay, downlink data packets are discarded until the timer has expired. This timer is triggered upon receiving the first error in a DDN Ack message from the MME.

#### Related Functionality

DDN Delay: By default, the S-GW supports the delay value IE included in a DDN acknowledgement message. The S-GW automatically multiplies this value by 50 ms, then applies the calculated delay for DDN for the UE.

#### Example

The following command configures the S-GW to discard downlink data packets for 200 seconds after the S-GW receives an error in a DDN Ack message from the MME :

```
ddn failure-action pkt-drop-time 200
```

## ddn isr-sequential-paging

Configures the delay time in 100 millisecond increments between paging of different RAT types in support of the Intelligent Paging for ISR feature.

---

### Product

S-GW  
SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

**ddn isr-sequential-paging delay-time** *delay*  
**default ddn isr-sequential-paging**

#### default

Returns the delay time to its default value of 10 ( 10 \* 100 ms = 1 second).

#### delay-time *delay*

Configures delay between paging of different RAT types.

*delay* must be an integer from 1 to 255, representing increments of 100 milliseconds (*delay* = 1-255 \* 100 ms).

Default: 10 (10 \* 100 ms = 1 second)

---

### Usage Guidelines

Use this command to configure the delay time in (100 millisecond increments) between paging of different RAT types in support of the Intelligent Paging for ISR feature.

#### Example

The following command configures the delay timer to 5 seconds.

```
ddn isr-sequential-paging delay-timer 50
```

# ddn success-action no-user-connect ddn-retry-timer

Use this command to resend DDN if no MBR or DDN Failure is received within the specified timer value.

---

**Product**

S-GW  
SAEGW

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

**Syntax Description**

**ddn success-action no-user-connect ddn-retry-timer** *value\_sec*  
**default ddn success-action no-user-connect ddn-retry-timer**

**default**

Resets the command to its default setting of 60 seconds.

**ddn success-action no-user-connect ddn-retry-timer** *value\_sec*

Resends DDN if no MBR or DDN Failure is received within the specified timer value.

*value\_sec*: Valid entries are from 60 to 300 seconds.

---

**Usage Guidelines**

After receiving DDN Ack, this timer is started and when it expires, S-GW sends one DDN and restarts the timer for same value. If no MBR is received within this time, S-GW clears the data buffers and waits for new data to trigger a new DDN.

This configuration is applicable only for non-ISR calls. If ISR is active, this configuration will be ignored. This extra DDN is sent under extreme circumstances. So, neither DDN delay nor throttling will be applied on it.

**Example**

The following command configures the DDN retry timer to 180 seconds.

```
ddn success-action no-user-connect ddn-retry-timer 180
```

## ddn temp-ho-rejection mbr-guard-timer

Sets the guard timer to wait for a MBR when DDN Ack with Cause #110 (temp-ho-rejection) is received.

If the guard timer expires and if no MBR of any type or DDN Failure Indication is received, all the buffered downlink data is flushed out and paging flags are reset. If the guard timer is running and any MBR is received, the timer is stopped and no further action is taken. If the guard timer is running and DDN Failure Indication is received, the timer is stopped and standard DDN failure action is taken. By default, this CLI command is always enabled.

---

### Product

S-GW

SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

**ddn temp-ho-rejection mbr-guard-timer** *time\_in\_seconds*

#### **no**

Disables the guard timer.

#### **default**

Enables the guard timer and sets it to the default value, 60 seconds.

#### **temp-ho-rejection**

Action to be taken when peer node indicates temporary rejection of paging due to handover-in-progress.

#### **mbr-guard-timer**

Sets the guard timer for a MBR when DDN Ack with Cause #110 (temp-ho-rejection) is received. When the timer expires, S-GW flushes all the buffered downlink data packets. The range of this timer is from 60 seconds to 300 seconds. Default timer value is 60 seconds.

---

### Usage Guidelines

Use this CLI command to enable guard timer to wait for MBR once the DDN Ack with cause#110 (Temporary Handover In Progress) is received. If the guard timer expires and if no MBR of any type or DDN Failure Indication is received, all the buffered downlink data is flushed out and paging flags are reset. If the guard timer is running and DDN Failure Indication is received, the timer is stopped and standard DDN failure action is taken.

By default, this CLI command is always enabled.

**Example**

The following CLI command sets the guard timer for 200 seconds to wait for a MBR when DDN Ack with Cause #110 (temp-ho-rejection) is received.

```
ddn temp-ho-rejection mbr-guard-timer 200
```

# ddn throttle

Configures Downlink Data Notification throttle parameters.

---

## Product

S-GW  
SAEGW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

## Syntax Description

```
ddn throttle arp-watermark arp_value [ rate-limit limit time-factor seconds
throttle-factor percent increment-factor percent [ poll-interval seconds ]
throttle-time-sec seconds [ throttle-time-min minutes ] [ throttle-time-hour
hour ] stab-time-sec seconds [ stab-time-min minutes ] [ stab-time-hour hour
]
no ddn-throttle
```

**no**

Disables the DDN throttling feature.

**throttle arp-watermark** *arp\_value*

If ARP watermark is configured and if an MME/SGSN sends the throttling factor and delay in a DDN ACK message, all the DDNs which have an ARP value greater than the configured value will be throttled by the throttle factor for the specified delay.

*arp\_value* is an integer from 1 through 15.

**rate-limit** *limit*

Configures the rate limit (Use this and subsequent tokens to rate-limit only if the MME is a Non-Release 10 MME).

*limit* is an integer from 1 through 999999999.

**time-factor** *seconds*

Configures the time duration during which the S-GW makes throttling decisions.

*seconds* is an integer from 1 to 300.

**throttle-factor** *percent*

Configures the DDN throttling factor. Enter the percentage of the DDN to be dropped upon detecting a DDN surge.



*percent* is an integer from 1 through 100.

**increment-factor *percent***

Configures the DDN throttling increment factor. Enter the percentage by which the DDN throttling should be increased.

*percent* is an integer from 1 through 100.

**poll-interval *seconds***

Configures the polling interval in DDN throttling.

*seconds* is an integer from 2 through 999999999.

**throttle-time-sec *seconds***

Configures the DDN throttling time in seconds. Enter time period in seconds over which DDN are throttled at the S-GW.

*seconds* is an integer from 0 through 59.

**throttle-time-min *minutes***

Configures the DDN throttling time in minutes. Enter time period in minutes over which DDN are throttled at the S-GW.

*minutes* is an integer from 0 through 59.

**throttle-time-hour *hour***

Configures the DDN throttling time in hours. Enter time period in hours over which DDN are throttled at the S-GW.

*hour* is an integer from 0 through 310.

**stab-time-sec *seconds***

Configures the DDN throttling stabilization time in seconds. Enter a time period in seconds over which if the system is stabilized, throttling will be disabled.

*seconds* is an integer from 0 through 59.

**stab-time-min *minutes***

Configures the DDN throttling stabilization time in minutes. Enter a time period in minutes over which if the system is stabilized, throttling will be disabled.

*minutes* is an integer from 0 through 59.

**stab-time-hour *hour***

Configures the DDN throttling stabilization time in hours. Enter a time period in hours over which if the system is stabilized, throttling will be disabled.

*hour* is an integer from 0 through 310.

**Usage Guidelines**

Use this command to throttle DDNs to allow for the creation of the tunnel and avoid unnecessary DDNs.

For a UE in idle mode, S1U bearers are not established. In such a case, if a downlink packet arrives for the UE, the S-GW initiates a paging procedure towards the MME. The MME in turn pages the UE in its tracking area to search for the UE. Upon receiving the paging request, the UE establishes S1U bearers. Too many DDN requests towards the MME from the S-GW could overload the MME. To reduce this load, the MME can dynamically request S-GW to reduce a certain percentage of DDN messages sent towards it for a given period time.

The S-GW supports the following IEs for this feature:

- ARP IE in Downlink Data Notification
- DL Low Priority Traffic Throttling IE in DDN Acknowledge Message

More information is available in Release 10 of 3GPP 29.274, section 5.3.4.3.

The S-GW supports DDN throttling for up to 24 MMEs. DDNs for additional MMEs (25+) will be sent as normal and will not be throttled.

Throttling statistics can be viewed by issuing the Exec mode command:

```
show sgw-service statistics all
```

**Example**

The following command sets the ARP watermark lowest priority to *10* seconds:

```
ddn throttle arp-watermark 10
```

If the ARP value provided is 10, all bearers with ARP value between 10-15 are treated as low priority bearers and are given throttling treatment. Throttling would not be enabled if the ARP value is not provided through S-GW service configuration. Also, the ARP IE in DDN message towards MME would not be included unless DDN throttling is configured in S-GW service.

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

## egtp-service

Configures an eGTP service to use as either an ingress (S1-U) or egress (S5/S8) service for the S-GW.

---

### Product

S-GW  
SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

**egtp-service** { **egress** { **context** *name* | **service** *name* } | **ingress** **service** *name* }

**no egtp-service** { **egress** { **context** | **service** } | **ingress** **service** }

**no**

Removes the selected eGTP service from this service.

**egress** { **context** *name* | **service** *name* }

Specifies the egtp-service to be used as the egress eGTP service on a GTP-based S5/S8 interface.

**context** *name*: Specifies the name of the context where the eGTP service resides.

*name* must be an existing context name where an eGTP service resides expressed as an alphanumeric string of 1 through 63 characters.

**service** *name*: Specifies the name of the egress eGTP service.

*name* must be an existing eGTP service name expressed as an alphanumeric string of 1 through 63 characters.

**ingress** **service** *name*

Specifies the egtp-service to be used as the ingress eGTP service on the S11 interface.

*name* must be an existing eGTP service name expressed as an alphanumeric string of 1 through 63 characters.

---

### Usage Guidelines

Use this command to configure the eGTP service to use with this S-GW service. The eGTP service must be existing and be configured with the appropriate parameters supporting the intended service type.

### Example

The following command configures the S-GW service to use an eGTP service named *slu-egtp* as its ingress service:

```
egtp-service ingress service slu-egtp
```

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# gtpc handle-collision upc nrupc

This command helps in enabling or disabling collision handling between SGSN initiated UPC and NRUPC request.

---

**Product** S-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

**Syntax Description** [ **no** | **default** ] **gtpc handle-collision upc nrupc**

## **no**

Disables collision handling between SGSN initiated UPC and NRUPC request.

## **default**

Sets default collision handling behavior between SGSN initiated UPC and NRUPC request. By default, collision handling is enabled.

## **handle-collision upc nrupc**

Enables/Disables collision handling between SGSN initiated UPC and network requested UPC. By default, collision handling is enabled.

---

**Usage Guidelines** This command is used to enable or disable collision handling between SGSN initiated UPC and NRUPC request.

## **Example**

The following example disables collision handling between SGSN initiated UPC and NRUPC request.

```
no gtpc handle-collision upc nrupc
```

## gtpu-error-ind

Configures the actions to be taken upon receiving a GTP-U error indication from an RNC, eNodeB, SGSN, or P-GW.

---

### Product

S-GW  
SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

```
gtpu-error-ind { { s12 | s1u | s11u } { local-purge | page-ue [ custom1-behavior ] } | { s4u | s5u } { local-purge | signal-peer } }  
default gtpu-error-ind { s12 | s1u | s11u | s4u | s5u }
```

#### default

Resets the command to the default action for the specified interface. For S12 and S1-U, **page-ue** is the default action. For S4-U and S5-U, **local-purge** is the default action.

#### { **s12** | **s1u** | **s11u** } { **local-purge** | **page-ue** [ **custom1-behavior** ] }

Specifies the action to take when a GTP-U error indication is received from a Radio Network Controller (RNC) over an S12 interface or from an eNodeB over the S1-U interface.

**local-purge**: The S-GW clears the affected bearer (or PDN if error-indication is received on default bearer) locally without informing peer.

**page-ue** [ **custom1-behavior** ]: The S-GW moves the complete UE state to S1-Idle and starts paging for this UE. If the custom1-behavior option is specified, the S-GW will guard the paging attempt with a timer of 60 seconds. Within this time the bearer must have the eNodeB TEID refreshed by an MME. Otherwise, the S-GW will clear the affected bearer with signaling. This is the default action for GTP-U error indication messages received on the S12 and S1-U interfaces.

#### { **s4u** | **s5u** } { **local-purge** | **signal-peer** }

Specifies the action to take when a GTP-U error indication is received from an SGSN over an S4-U interface or from a P-GW over the S5-U interface.

**local-purge**: The S-GW clears the affected bearer (or PDN if error-indication is received on a default bearer) locally without informing the peer. This is the default action for GTP-U error indication messages received on the S4-U and S5-U interfaces.

**signal-peer**: The S-GW initiates control signalling towards the peer MME and P-GW. When signalling:

- For a bearer deletion, the S-GW sends a Delete-Bearer-Command message to the P-GW and a Delete-Bearer-Request (with EBI) message to the MME.



- For PDN deletion, the S-GW sends a Delete-Session-Request message to the P-GW and a Delete-Bearer-Request (with LBI) message to the MME.
- The S-GW will not wait for Delete replies from the peer. The request will be sent only once and local resources will be reset.

**Usage Guidelines**

Use this command to specify the action to taken upon receiving a GTP-U error indication from an RNC over an S12 interface, an eNodeB across an S1-U interface, an SGSN over an S4-U interface, or from a P-GW across an S5-U interface.

**Example**

The following command sets the action to take upon receipt of a GTP-U error indication from the eNodeB to clear affected bearer:

```
gtpu-error-ind slu local-purge
```

# mag-service

Identifies the Mobile Access Gateway (MAG) egress service through which calls are to be routed for this S-GW service.

---

**Product** S-GW

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure > context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

**Syntax Description** **mag-service egress service** *name*  
**no mag-service egress service**

**no**

Removes the configured MAG egress service from this service.

**egress service** *name*

Specifies the MAG service name to be used as the egress MAG service on a Proxy Mobile IPv6 (PMIP) based S5/S8 interface.

*name* must be an existing MAG service expressed as an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines** Use this command to specify the name of the MAG service where calls are to be routed.

## Example

The following command specifies that an existing MAG service named *mag3* is to be used to route call through for this S-GW service:

```
mag-service egress service mag3
```

# ntsr session-hold timeout

Configures a timer to hold the session after path failure is detected at the MME (for Network Triggered Service Restoration).

---

**Product** S-GW

---

**Privilege** Administrator, Security Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

**Syntax Description** [ **no** ] **ntsr session-hold timeout** *seconds*

**no**

Disables the NTSR session-hold timeout.

**ntsr session-hold timeout** *seconds*

Configures the timer duration, in seconds, that determines how long the session will be held after path failure is detected during MME restoration. Valid entries are from 1 to 3600 seconds.

---

**Usage Guidelines** Use this command to configure the timer duration, in seconds, that determines how long the session will be held after path failure is detected during MME restoration.

## Example

To configure the ntsr session-hold timeout for 10 seconds.

```
ntsr session-hold timeout 10
```

## page-ue

Allows the S-GW to page the UE for P-GW-initiated procedures (Create Bearer Request (CBR)/Modify Bearer Request (MBR)/Update Bearer Request (UBR)) when the UE is idle, and sends a failure response to the P-GW with the cause code 110 (Temporary Failure) when the UE is idle or a collision is detected at the S-GW.

---

### Product

S-GW  
SAEGW

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

### Syntax Description

[ **default** | **no** ] **page-ue pgw-initiated-proc**

#### **default**

Returns the command to its default setting of disabled.

#### **no**

Disables the feature.

#### **pgw-initiated-proc**

Sets the command to page the UE for P-GW initiated MBR, UBR, and CBR procedures.

---

### Usage Guidelines

Use this command to allow the S-GW to page a UE for P-GW-initiated procedures (CBR/MBR/UBR) when the UE is idle, and sends a failure response to the P-GW with the cause code 110 (Temporary Failure) when the UE is idle or a collision is detected at the S-GW.

#### **Example**

The following command enable the S-GW to page the UE

```
page-ue pgw-initiated-proc
```

# paging-policy-differentiation

Controls Paging Policy Differentiation (PPD) functionality on the S-GW.

**Product** S-GW

**Privilege** Administrator, Security Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

**Syntax Description** [ **default** | **no** ] **paging-policy-differentiation**

## default

Restores the PPD functionality to its default setting of disabled.

## no

Disables this option. This is the default setting.

## paging-policy-differentiation

When S-GW supports the PPD feature, it shall include Paging and Service Information IE in the Downlink Data Notification message triggered by the arrival of downlink data packets at the S-GW. The Paging Policy Indication value within this IE will contain the value of the DSCP in TOS (IPv4) or TC (IPv6) information received in the IP payload of the GTP-U packet from the P-GW.

It is up to MME/S4-SGSN to use the Paging and Service Information IE of DDN message.

To support PPD feature in SAEGW, both S-GW and P-GW configuration is required.

**Usage Guidelines** Use this command to enable/disable PPD functionality on S-GW.



### Important

P-GW and S-GW should apply the PPD feature for both Default and Dedicated bearers. As per the specifications, P-GW transparently passes the user-datagram packet towards S-GW. This means, if PPD feature is enabled, operator can't apply different behavior for Default and Dedicated bearers.

Once the PPD feature is enabled, it is applicable for both existing and new calls.

If PPD feature is enabled at S-GW service, it is applicable for all calls irrespective of the APN profiles.

The PPD feature is license controlled under the license for S-GW Paging Profile. Once the license is enabled, both features co-exist together and work independently. That means, DDN message might carry both DSCP marking specified by PPD feature and Priority DDN value specified by S-GW Paging Profile feature.

At S-GW, the user-datagram packet DSCP value is used to send in DDN. S-GW can't change the DSCP, as per the local configuration (APN profile or service level). At eNodeB, the scheduling of the packet is based on the QCI instead of DSCP, however, any EPC node should not change/modify the inner DSCP value.



---

**Important** For the PPD feature to work, it must be enabled for P-GW and S-GW.

Both P-GW and S-GW services apply PPD configuration independently. Therefore, for any downlink data packet from an APN, there could be a case where P-GW does not have PPD configuration but S-GW has PPD configuration. To avoid such a conflict, you must configure the PPD functionality on both P-GW (APN level granularity) and S-GW (service level granularity).

---

See the *Paging Policy Differentiation* chapter in the *S-GW Administration Guide* for detailed information on PPD functionality.

### Example

To enable PPD functionality on S-GW, enter the following command:

```
paging-policy-differentiation
```

# path-failure

Configures the action to take upon the occurrence of a path failure between the S-GW and the MME, P-GW, RNC, SGSN, or eNodeB.

---

**Product**

S-GW  
SAEGW

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

**Syntax Description**

```
path-failure { s11 | s11u | s12 | s1u | s4 | s4u | s5 | s5u } ( local-purge
| signal-peer )
default path-failure { s11 | s11u | s12 | s1u | s4 | s4u | s5 | s5u } (
local-purge | signal-peer )
```

**default**

Returns the command to the default setting of "local purge" for the selected interface.

**{ s11 | s12 | s1u | s4 | s4u | s5 | s5u }**

Specifies the interface to which the action will be applied.

**s11**: Applies the path failure action to the S11 interface between the S-GW and the MME.

**s11u**: Applies the path failure action to the S11-U interface between the S-GW and the MME.

**s12**: Applies the path failure action to the S12 interface between the S-GW and the RNC.

**s1u**: Applies the path failure action to the S1-U interface between the S-GW and the eNodeB.

**s4**: Applies the path failure action to the S4 control plane interface between the S-GW and the SGSN.

**s4u**: Applies the path failure action to the S4-U user plane interface between the S-GW and the SGSN.

**s5**: Applies the path failure action to the S5 interface between the S-GW and the P-GW.

**s5u**: Applies the path failure action to the S5-U user plane interface between the S-GW and the P-GW.

**{ local-purge | signal-peer }**

Specifies the action to apply to the selected interface.

**local-purge**: The S-GW clears the affected bearer (or PDN if path failure is received on a default bearer) locally without informing the peer. This is the default action for all interface.

**signal-peer**: The S-GW initiates control signalling towards the peer MME and P-GW. When signalling:

- For a bearer deletion, the S-GW sends a Delete-Bearer-Command message to the P-GW and a Delete-Bearer-Request (with EBI) message to the MME.
- For PDN deletion, the S-GW sends a Delete-Session-Request message to the P-GW and a Delete-Bearer-Request (with LBI) message to the MME.
- The S-GW will not wait for Delete replies from the peer. The request will be sent only once and local resources will be reset.

---

**Usage Guidelines**

Use this command to specify the type of action to take when a path failure occurs on one of the supported interfaces.

**Example**

The following command sets the path failure action for the S5 interface to "signal peer":

```
path-failure s5 signal-peer
```



## pgw-fteid-in-relocation-cs-rsp

Controls the sending of the PGW Fully Qualified Tunnel Endpoint Identifier (FTEID) for relocation Create Session Response procedures with an S-GW change.

**Product** S-GW

**Privilege** Administrator, Security Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service) #
```

**Syntax Description** [ **no** ] **pgw-fteid-in-relocation-cs-rsp**

**no**

Disables the sending of the P-GW FTEID in Create Session Response procedures where there is an S-GW relocation change. This is the default setting.

**pgw-fteid-in-relocation-cs-rsp**

Enables the sending of the P-GW FTEID in Create Session Response procedures where there is an S-GW relocation change.

**Usage Guidelines**

Use this command to control the sending of the PGW Fully Qualified Tunnel Endpoint Identifier (FTEID) for relocation Create Session Response procedures with an S-GW change. For backward compatibility with earlier 3GPP release peer nodes requiring the P-GW FTEID in the Create Session Response procedures, this configurable can be enabled.

**Example**

To enable the sending of the FTEID for relocation Create Session REsponse procedures with an S-GW change:

```
pgw-fteid-in-relocation-cs-rsp
```

# plmn

Configures the public land mobile network (PLMN) identifiers for this S-GW. service

---

## Product

S-GW  
SAEGW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

## Syntax Description

**plmn id** *mcc number mnc number* [ **primary** ]

**no plmn id** *mcc number mnc number*

### **no**

Removes the configured PLMN ID for this S-GW service.

### **mcc number**

Configures the Mobile Country Code for this PLMN ID.

*number* must be an integer from 100 through 999.

### **mnc number**

Configures the Mobile Network Code for this PLMN ID.

*number* must be a 2- or 3-digit integer from 00 through 999,

### **primary**

Specifies that this is the primary PLMN ID for this S-GW service.

---

## Usage Guidelines

The PLMN identifier is used by the S-GW service to determine whether or not a mobile station is visiting, roaming, or home. Multiple S-GW services can be configured with the same PLMN identifier. Up to five PLMN IDs can be configured for each S-GW Service. In Release 15.0 and later, up to 15 PLMN IDs can be configured.

## Example

The following command configures a "primary" PLMN ID for this S-GW service with an MCC of 123 and an MNC of 12:

```
plmn id mcc 123 mnc 12 primary
```

# reporting-action

Configures the system to start reporting session events.

---

## Product

S-GW  
SAEGW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

## Syntax Description

```
[ no ] reporting-action event-record [ trigger active-idle ]
default reporting-action event-record
```

### default

Returns the command to its default setting of disabled.

### no

Disables session event reporting.

### trigger active-idle

Specifies that the event is only to be reported upon the going from active to idle.

---

## Usage Guidelines

Use this command to enable the session event reporting feature on the S-GW.

### Example

The following command enables event reporting but does not limit it to events triggered by going active to idle:

```
reporting-action event-record
```

# timeout idle

This command removes S-GW sessions that remain idle for longer than the configured time limit.

---

## Product

S-GW  
SAE-GW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > S-GW Service Configuration

**configure** > **context** *context\_name* > **sgw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sgw-service)#
```

---

## Syntax Description

```
timeout idle dur_seconds [ micro-checkpoint-periodicitytime_in_seconds | micro-checkpoint-deemed-idletime_in_seconds ]  
{ default | no } timeout idle
```

### default

Indicates the timeout specified is to be returned to its default behavior.

### no

Disables the timeout idle functionality.

### timeout idle

Enables the S-GW session idle timer.

### *dur\_seconds*

Specifies the time limit, in seconds, after which the S-GW session will be torn down. Valid entries are from 0 to 4294967295.

### **micro-checkpoint-periodicity***time\_in\_seconds*

Specifies the micro-checkpoint periodicity for idlesecs, in seconds.

*time\_in\_seconds* must be an integer from 10 to 10000 seconds.

Default: 10




---

## Important

The **micro-checkpoint-periodicity** value should be less than **idle timeout** value.

---

**micro-checkpoint-deemed-idle***time\_in\_seconds*

Specifies the time duration, in seconds, after which a session state is deemed to have changed from active to idle or idle to active, and a micro-checkpoint is then sent from the active to the standby chassis.

*time\_in\_seconds* must be an integer from 10 to 1000.

Default: 180

**Important**

The **micro-checkpoint-deemed-idle** value should be less than the **timeout idle** value.

**Usage Guidelines**

The S-GW session idle timer removes stale sessions in those cases where the session is removed on the other nodes but due to some issue remains on the S-GW. Once configured, the session idle timer will tear down such sessions that remain idle for longer than the configured time limit. The implementation of the session idle timer allows the S-GW to more effectively utilize system capacity.

Optionally, ICSR micro-checkpoint periodicity for idlesecs is configurable instead of using the default periodicity of 10 seconds. Operators can configure this setting to a large value to suit their need to reduce the number of micro-checkpoints on the SRP link. When this CLI command is configured, idleseconds micro-checkpoints are sent at configured regular intervals to the standby chassis. If not configured, micro-checkpoints are sent at intervals of 10 seconds, which is the default.

Finally, the operator can choose to configure **micro-checkpoint-deemed-idle**. This process enables the active and standby chassis to be synchronized with respect to when a particular session became active or idle. Since this feature is event-based, it enables the chassis to send micro-checkpoints only when an event is deemed to have occurred, as opposed to sending micro-checkpoints based on a configured time duration, which sends the micro-checkpoints regardless of whether a session state change occurred or not. Using **micro-checkpoint-deemed-idle** results in a more efficient event-based sending of micro-checkpoints to the standby chassis and also increases SRP bandwidth.

**Important**

Either the **micro-checkpoint-deemed-idle** or **micro-checkpoint-periodicity** value can be configured for idle time duration. Any change from **micro-checkpoint-deemed-idle** to **micro-checkpoint-periodicity**, or vice versa, requires removing the first configuration before adding the new configuration.

**Example**

The following example configures the S-GW session idle timer 3600 seconds (one minute).

```
timeout idle 3600
```

timeout idle



## SLs Service Configuration Mode Commands

The SLs interface is used to convey Location Services Application Protocol (LCS-AP) messages and parameters between the MME to the E-SMLC. It is also used for tunnelling LTE Positioning Protocols (LPP between the E-SMLC and the target UE, LPPa between the E-SMLC and the eNodeB), which are transparent to the MME.

### Command Modes

Exec > Global Configuration > Context Configuration > SLs Service Configuration

**configure** > **context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [bind](#), on page 656
- [do show](#), on page 658
- [end](#), on page 659
- [esmlc](#), on page 660
- [exit](#), on page 662
- [ip](#), on page 663
- [max-retransmissions](#), on page 664
- [t-3x01](#), on page 665
- [t-3x02](#), on page 666

# bind

Binds the SLs service to a local SCTP IP address, configures the SCTP port number, and associates an SCTP parameter template. This interface is used by the SLs service to communicate with the E-SMLC.

---

**Product** MME

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > SLs Service Configuration

**configure > context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service)#
```

---

**Syntax Description**

**bind** { **ipv4-address** *ipv4\_address\_value1* [ **ipv4-address** *ipv4\_address\_value2* ] | **ipv6-address** *ipv6\_address\_value1* [ **ipv6-address** *ipv6\_address\_value2* ] [ **port** *port\_num* ] } **sctp-template** *sctp\_param\_template\_name*  
**no bind**

**no**

Removes the interface binding from this SLs service.

**ipv4-address** *ipv4\_address\_value1* [ **ipv4-address** *ipv4\_address\_value2* ]

Specifies the IPv4 address of an interface in the current context through which communication with the E-SMLC occurs.

A second IPv4 address can be specified for multi-homing purposes with the optional **ipv4-address** keyword.

**ipv6-address** *ipv6\_address\_value1* [ **ipv6-address** *ipv6\_address\_value2* ]

Specifies the IPv6 address of an interface in the current context through which communication with the E-SMLC occurs.

A second IPv6 address can be specified for multi-homing purposes with the optional **ipv6-address** keyword.

**port** *port\_num*

Specifies the SCTP port through which communication with the E-SMLC occurs.

*port\_num* must be an integer from 1 through 65535. Default: 9082.

**sctp-template** *sctp\_param\_template\_name*

Associates an existing SCTP Parameter Template with this SCTP connection.

The SCTP template is mandatory for the SLs Service to start.

---

**Usage Guidelines**

Use this command to bind the SLs service to an IP address.

This command is service critical; removing the configuration will stop the SLs service.



Up to 2 IPv4 or 2 IPv6 addresses can be specified for multi homing purposes.

### Example

The following command configures 2 IPv4 addresses for the SCTP connection (for multi-homing), assumes the default SCTP port of 9082, and associates this connection with an SCTP parameter template named *sctp\_sls*:

```
bind ipv4-address 10.1.1.100 ipv4-address 10.1.1.200 sctp-template sctp_sls
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# esmlc

Configures an Evolved Serving Mobile Location Center (E-SMLC) within this SLs service. The E-SMLC provides location information to the MME.

**Product** MME

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SLs Service Configuration

**configure > context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service)#
```

**Syntax Description**

```
esmlc esmlc-id esmlc_id_value { ipv4-address ipv4_address_value1 [ ipv4-address ipv4_address_value2 ] | ipv6-address ipv6_address_value1 [ ipv6-address ipv6_address_value2 ] } port port_num weight weight-val  
no esmlc-id esmlc_id_value
```

## **esmlc-id** *esmlc\_id\_value*

Specifies an ID to uniquely identify this E-SMLC within this SLs service.

*esmlc\_id\_value* must be an integer from 0 through 255.

## **ipv4-address** *ipv4\_address\_value1* [ **ipv4-address** *ipv4\_address\_value2* ]

Specifies the IPv4 address of the E-SMLC to be used by this SLs service.

A second IPv4 address can be specified for multi-homing purposes with the optional **ipv4-address** keyword.

## **ipv6-address** *ipv6\_address\_value1* [ **ipv6-address** *ipv6\_address\_value2* ]

Specifies the IPv6 address of the E-SMLC to be used by this SLs service.

A second IPv6 address can be specified for multi-homing purposes with the optional **ipv6-address** keyword.

## **port** *port\_num*

Specifies the SCTP port number of the E-SMLC server.

*port\_num* must be an integer from 1 through 65535. Default: 9082.

## **weight** *weight-val*

The MME performs a weighted round robin selection of E-SMLC based on this weight factor.

*weight-val* must be an integer from 1 through 5, where 1 represents the least available capacity and 5 represents the greatest.

## **Usage Guidelines**

Use this command to configure an E-SMLC within this SLs service. The E-SMLC provides location information to the MME.

Up to 8 E-SMLC entries can be configured per SLs service.

The SLs service is started when the first E-SMLC is configured. The SLs service is stopped when the last E-SMLC is removed.

A single E-SMLC can be configured to serve multiple MMEs or multiple SLs services within the same MME.

### Example

The following command creates an E-SMLC entry for this SLs service for an E-SMLC with an IPv6 address, a port value of 9082 (default), and a round robin selection weight value of 5 (highest capacity).

```
esmlc esmlc-id 1 ipv6-address fe80::2e0:b6ff:fe01:3b7a port 9082 weight 5.
```

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# ip

This command configures the IP parameters on the SLs interface.

---

**Product**

MME

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SLs Service Configuration

**configure** > **context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service) #
```

---

**Syntax Description**

[ **no** ] **ip qos-dscp** *dscp\_value*

**no**

Removes IP parameter configuration from the SLs service/interface.

**qos-dscp** *dscp\_value*

The **qos-dscp** keyword designates the Quality of Service - Differentiated Services Code Point value to the packet leaving through the SLs interface.

*dscp\_value* is a value assigned to the packet for DSCP marking. The value can be a pre-defined DSCP value or an arbitrary value ranging from 0x01 to 0x3F.

---

**Usage Guidelines**

SLs interface allows Differentiated Services Code Point (DSCP) marking functionality. DSCP marking helps in packet traffic management. DSCP marking can be performed on both IPv4 and IPv6 packets leaving the SLs interface.

Either the pre-defined DSCP values can be used for marking, or any arbitrary value ranging from 0x01 to 0x3F can be assigned. The default DSCP value is 0x00 or be (Best Effort). The default DSCP value is automatically set when the configuration is disabled.

**Example**

The following command shows the IP configuration for DSCP marking on the SLs service.

```
ip qos-dscp ef
```

## max-retransmissions

Configures the maximum number of times the MME will resend messages to the E-SMLC.

---

### Product

MME

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > SLS Service Configuration

**configure** > **context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service)#
```

---

### Syntax Description

**max-retransmissions** **reset** *retries*  
**default** **max-retransmissions** **reset**

#### default

Resets the command to the default of 0 (zero).

#### reset

Configures the maximum number of times the MME will resend the RESET REQUEST to the E-SMLC

*retries* must be an integer from 1 to 5. The default setting is 0.

---

### Usage Guidelines

Use this command to configure the maximum number of times the MME will resend the RESET REQUEST to the E-SMLC.

Refer to the **t-3x02** command to configure the timer settings for resending the Reset Request message to the E-SMLC.



# t-3x01

Configures timer settings for "low delay" and "delay tolerant" response times from the E-SMLC.

---

**Product**

MME

---

**Privilege**

Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SLS Service Configuration

**configure** > **context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service)#
```

---

**Syntax Description**

**t-3x01** **low-delay** *seconds* **delay-tolerant** *seconds*  
**default** **t-3x01**

**default**

Resets the timer to the default setting of 20 seconds for both low delay and delay tolerant requests.

**low-delay**

Indicates the number of seconds within which the MME expects to receive a "low delay" response from the E-SMLC, where fulfillment of the response time requirement takes precedence over fulfillment of the accuracy requirement.

*seconds* must be an integer from 10 to 30. The default setting is 20 seconds.

**delay-tolerant**

Indicates the number of seconds within which MME expects to receive a "delay tolerant" response from the E-SMLC, where fulfillment of the accuracy requirement takes precedence over fulfillment of the response time.

*seconds* must be an integer from 10 to 40. The default setting is 20 seconds.

---

**Usage Guidelines**

These timer options can be configured to prioritize location request response times from the E-SMLC. The T-3x01 timer is started by the MME on sending a location-request to the E-SMLC, and is stopped when either the requested is responded, aborted, or reset by either the MME or the E-SMLC.

A location procedure ends after the Delay Tolerant timer expires and no response is received from an E-SMLC.

More details about these settings are available in 3GPP TS 22.071.

**Example**

The following command configures the low-delay timer for 15 seconds and the delay-tolerant timer for 25 seconds.

```
t-3x01 low-delay 15 delay-tolerant 25
```

## t-3x02

Configures timer settings for resending the Reset Request message to the E-SMLC.

---

### Product

MME

---

### Privilege

Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > SLS Service Configuration

**configure** > **context** *context\_name* > **sls-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-sls-service)#
```

---

### Syntax Description

**t-3x02** *seconds*  
**default** **t-3x02**

#### **default**

Resets the timer to the default setting of 3 seconds.

#### **seconds**

*seconds* must be an integer from 1 to 5. The default setting is 3 seconds.

---

### Usage Guidelines

The T-3x02 timer is started on the MME when the MME sends a RESET REQUEST to the E-SMLC. Once the T3x02 timer expires, the MME can resend the RESET REQUEST to the E-SMLC.

Refer to the **max-retransmissions** command to configure the maximum number of times the MME will resend a RESET REQUEST to the E-SMLC.



## SMS Service Configuration Mode Commands

The SGSN uses the SMS Service component to communicate via the Gd interface with a gateway message service controller (GMSC) to send short text messages (up to 140 octets in length) to a mobile (SMS-MT) and/or receive messages from a mobile (SMS-MO) .

### Command Modes

The SMS (short message service) Service configuration mode is used to create and manage properties of the SMS Service configuration.

Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure** > **context** *context\_name* > **map-service** *service\_name* > **short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [cp-data](#), on page 668
- [do show](#), on page 669
- [end](#), on page 670
- [exit](#), on page 671
- [mo-message-forwarding-destination](#), on page 672
- [sm-sc-address-restriction-list](#), on page 673
- [sm-sc-address-restriction-type](#), on page 674
- [sm-sc-address-selection-prioritization](#), on page 675
- [sm-sc-routing](#), on page 677
- [timeout](#), on page 679

# cp-data

Enables the SGSN to send and/or receive cp-data (text messages).

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure > context *context\_name* > map-service *service\_name* > short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

---

## Syntax Description

**cp-data max-retransmission *retries\_num***  
**default cp-data max-retransmissions**

### default

This keyword resets the SGSN's max-retransmission to the default number of retries.

### max-retransmission *retries\_num*

*retries\_num*: enter an integer from 1 to 3.

---

## Usage Guidelines

Use this command to configure the number of times the SGSN will attempt to retransmit a message.

### Example

```
cp-data max-retransmission 2
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# mo-message-forwarding-destination

This command defines the SGSN's handling policy for MO (mobile originating) message.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure > context *context\_name* > map-service *service\_name* > short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

---

**Syntax Description**

```
[ default ] mo-message-forwarding-destination { gsmc-selected-from-imsi
| smsc-supplied-by-subscriber }
```

**default**

Resets the SMS service configuration to the default message forwarding technique.

**gsmc-selected-from-imsi**

Entering this keyword enables SMS-MO messages to be forwarded on the basis of their IMSI prefix.

**smsc-supplied-by-subscriber**

Entering this keyword enables SMS-MO messages to be forwarded on the basis of the SMSC (SMS controller) address provided by the subscriber.

---

**Usage Guidelines**

Use this command to define how the mobile originated SMS are to be routed.

**Example**

```
mo-message-forwarding-destination gsmc-selected-from-imsi
```



# sm-sc-address-restriction-list

Define the list of SMS-C addresses to be screened.

---

**Product**

SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure** > **context** *context\_name* > **map-service** *service\_name* > **short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

---

**Syntax Description**

**sm-sc-address-restriction-list** *isdn-no +*  
**no sm-sc-address-restriction-list** *isdn-no*

**no**

Delete an SMS-C address (ISDN number) from the list.

**isdn-no +**

Enter up to 10 ISDN numbers, each up to 15 digits. Put a single space, without a comma, between each ISDN number being added to the list with one command.

---

**Usage Guidelines**

Use this command to identify a list of SMS-C that are to be screened and restricted from receiving forwarded SMS. This list is part of the SMS-C address denial mechanism. For the mechanism to actually function, a second command must be configured, the **sm-sc-address-restriction-list** command.

**Example**

Add 3 ISDN numbers to the list of restricted SMS-C addresses.

```
sm-sc-address-restriction-list 443719933751427 422311198977765 901231445513131
```

Remove an ISDN number from the list of restricted SMS-C addresses.

```
no sm-sc-address-restriction-list 443719933751427
```

# smc-address-restriction-type

Define the list of SMS-C addresses to be screened.

---

## Product

SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure > context *context\_name* > map-service *service\_name* > short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

---

## Syntax Description

**smc-address-restriction-type { mo-mt-sms | mo-sms | mt-sms }**  
**default smc-address-restriction-type**

### default

Resets the restriction type to the default of both MT and MO types.

### mo-mt-sms

Sets the restriction for both types of messages - mobile-originated (MO-SMS) and mobile-terminated (MT-SMS).

### mo-sms

Sets the restriction for the mobile-originated (MO-SMS) messages.

### mo-mt-sms

Sets the restriction for the mobile-terminated (MT-SMS) messages.

---

## Usage Guidelines

Use this command to identify the types of messages that are to be denied to the SMS-C identified in the **smc-address-restriction-type**. Both commands must be configured for the SMS-C address denial mechanism to function.

### Example

Restrict MO-SMS messages from being forwarded to the SMS-C listed in the restriction list:

```
smc-address-restriction-type mo-sms
```

Reset the restriction to both types of messages:

```
default smc-address-restriction-type
```

# sm-sc-address-selection-prioritization

Define the routing selection priority for the SMSC (short message service center) address to be used for all MO-SMS.

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure > context** *context\_name* > **map-service** *service\_name* > **short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

**Syntax Description** **sm-sc-address-selection-prioritization from-ms** *priority* **imsi-prefix** *priority* **msisdn-prefix** *priority* **default sm-sc-address-selection-prioritization**

## **from-ms** *priority*

Configures a priority for the SMSC address send from the MS.

*priority* : Value must be a single digit, range 1-3.

## **imsi-prefix** *priority*

Configures a priority for the SMSC address that is based on the IMSI-prefix.

*priority* : Value must be a single digit, range 1-3.

## **msisdn-prefix** *priority*

Configures a priority for the SMSC address that is based on the MSISDN-prefix.

*priority* : Value must be a single digit, range 1-3.

## **default**

By including the **default** keyword with the command, the SGSN knows to use the encoded default priorities for SMSC address selection for SMSC routing:

- *from-ms* priority 1,
- *imsi-prefix* priority 2,
- *msisdn-prefix* priority 3.

## **Usage Guidelines**

Use this command to define SMSC address routing priorities. Priorities must be defined for all parameters, all keywords, but they can be entered in any order. The addresses for the SMSCs are defined with the **sm-sc-routing** command.

An operator can use this configuration to prevent subscribers from using unauthorized SMSC addresses, for example, an unauthorized international SMSC.

### Example

The keywords can be entered in any order but all keywords must be included in the command:

```
smc-address-selection-prioritization msisdn-prefix 3 from-ms 1 imsi-prefix  
2
```

# smc-routing

This command configures the routing to the short message service center (SMSC).

**Product** SGSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure > context** *context\_name* > **map-service** *service\_name* > **short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

**Syntax Description** [ **no** ] **smc-routing** { { **any** | **imsi-starts-with** | **msisdn-starts-with** } { **isdn** *isdn\_number* | **mobile-global-title** *mgt\_number* [ **max-gt-address-len** *max\_gt\_length* ] | **point-code** *pt\_code* } }

## **any**

Configures routing according to any IMSI prefix.

## **imsi-starts-with** *IMSI\_prefix*

Defines the IMSI prefix. Enter a string of up to 15 digits.

## **msisdn-starts-with** *msisdn\_prefix*

Defines the MSISDN prefix. Enter a string of up to 15 digits.

## **isdn** *isdn\_number*

Defines the ISDN E.164 number (up to 15 digits) of the SMSC.

## **mobile-global-title** *mgt\_number* [ **max-gt-address-len** *max\_gt\_length* ]

Defines the mobile global title (MGT) E.214 address to be used for IMSI conversion.

Optionally, the maximum length of the GT address can be defined. If the length of the MGT string is greater than the defined max, then the least significant digits will be omitted.

*mgt\_number* is a string of digits, up to 18 digits.

*max\_gt\_address* is an integer from 1 to 32.

## **point-code** *pt\_code*

Defines the point code for the SMSC. Enter a string of up to 11 digits in SS7 dotted decimal or decimal format

## **Usage Guidelines**

This command defines the address format (IMSI, point code, mobile global title) and the address for SMSC routing.

**Example**

Use this command to define routing to the SMSC based on any point code.

```
smc-routing any point-code 1.222.1
```

# timeout

This command defines the SMS service timers.

<b>Product</b>	SGSN
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > Context Configuration > MAP Service Configuration > SMS Service Configuration

**configure > context *context\_name* > map-service *service\_name* > short-message-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-map-service-service_name-sms-service)#
```

<b>Syntax Description</b>	<b>timeout { tc1n-timer <i>time</i>   tr1n-timer <i>time</i>   tr2n timer <i>time</i> }</b> <b>default timeout { tc1n-timer   tr1n-timer   tr2n timer }</b>
---------------------------	--

## default

Resets the configuration to the default value for the specified timer.

## tc1n-timer *time*

Configures the TC1N timer in seconds.

*time*: Must an integer from 1 to 255. The default is 5 seconds.

## tr1n-timer *time*

Configures the TR1N timer in seconds.

*time*: Must an integer from 1 to 255. The default is 30 seconds.

## tr2n-timer *time*

Configures the TR2N timer in seconds.

*time*: Must an integer from 1 to 255. The default is 30 seconds.

<b>Usage Guidelines</b>	Use this command to set SMS service timers. The command can be repeated to set all of the timers, one-at-a-time.
-------------------------	--

## Example

```
tr1n-timer 25
```

■ timeout





# SS7 Routing Domain Configuration Mode Commands

## Command Modes

The SS7 Routing Domain configuration mode is used to configure Signaling System 7 (SS7) parameters. For convenience in configuration management, all SS7 parameters have been collected into a proprietary grouping called an *SS7 routing domains*.

Exec > Global Configuration > SS7 Routing Domain Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [asp](#), on page 682
- [description](#), on page 683
- [do show](#), on page 684
- [end](#), on page 685
- [exit](#), on page 686
- [inbound-asp-identifier validate](#), on page 687
- [linkset](#), on page 688
- [MTU-size](#), on page 689
- [peer-server](#), on page 690
- [route](#), on page 691
- [routing-context](#), on page 693
- [ssf](#), on page 694

# asp

This command creates or removes an M3UA Application Server Process (ASP) instance and enters the ASP configuration mode. See the *SGSN ASP Configuration Mode* chapter in the *Command Line Interface Reference* for command details.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

## Syntax Description

**asp instance** *asp\_inst*  
**no asp instance** *asp\_inst*  
**default asp instance** *asp\_inst* **end-point** **port**

### no

Deletes the ASP instance for the SS7 routing domain configuration.

### default

Sets the ASP instance parameters to the end-point port value of 2905.

### instance *asp\_inst*

Identifies a specific ASP configuration. Up to four ASP instances can be configured for a single SS7 routing domain.

*asp\_inst* : instance must be an integer from 1 through 4. For SGSN with release 15.0, the instance must be an integer from 1 to 12.

## Usage Guidelines

Use this command to create an ASP instance or enter the ASP configuration mode.

## Example

The following command enters the ASP configuration mode for a specific ASP.

```
asp instance 1
```

# description

This command defines an alphanumeric string that describes the current SS7 routing domain. This is used for operator reference only.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration  
**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

## Syntax Description

**description** *string*  
**no description**

**no**

Removes the description string from the current SS7 routing domain configuration.

**string**

Specifies the alphanumeric string that is stored. Strings with spaces must be enclosed in double-quotes (see the example below).

*string*: Must be from 1 to 255 alphanumeric characters.

## Usage Guidelines

Use this command to set a description for reference by operators.

## Example

The following command sets the description to identify a routing domain for messages transmitted within a national boundary.

```
description "National Service Routing Domain"
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.


**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# inbound-asp-identifier validate

This command enables validation of ASP identifiers inbound to the SGSN via routes defined with this SS7 routing domain.

**Important**

This command is only available in Release 8.1 and higher releases.

**Product**

SGSN

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > SS7 Routing Domain Configuration

**configure > ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

**Syntax Description**

**inbound-asp-identifier validate**  
**default inbound-asp-identifier validate**  
**no inbound-asp-identifier validate**

**default**

Validates the inbound ASP Id.

**no**

Disables validation of the inbound ASP Id.

**Usage Guidelines**

The standard is to validate the ASP Id. However, in some circumstances it is necessary to skip such validation. For example, if the same ASP Id is assigned to more than one RNC (peer-server).

**Example**

Use the following command to skip validation of inbound ASP Ids:

```
no inbound-asp-identifier validate
```

Use either of the following commands to enable validation if it has been disabled:

```
default inbound-asp-identifier validate  
inbound-asp-identifier validate
```

# linkset

This command creates an instance of an MTP3 linkset and enters the Linkset configuration mode. See the Linkset configuration mode chapter for the commands to configure the linkset.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration  
**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

## Syntax Description

**linkset** *id id*  
**no linkset** *id id*

**no**

Removes the identified linkset definition from the system configuration.

**id**

This value uniquely identifies a linkset for the specific SS7 routing domain.

*id* : Must be an integer of 1 to 49.

## Usage Guidelines

This command creates instances of linkset configurations and provides access to the linkset configuration mode.

## Example

Use the following command to create the 12th linkset:

```
linkset id 12
```



## MTU-size

This command has been deprecated.

## peer-server

This command creates a peer-server instance to setup a SIGTRAN peer for sending and receiving M3UA traffic. Completing the command automatically enters the peer-server configuration mode. To define 1 or more (up to 145) peer servers, use the commands documented in the *Peer-Server Configuration Mode* chapter in this reference.



### Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

### Product

SGSN  
HNB-GW

### Privilege

Security Administrator, Administrator

### Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration  
**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

### Syntax Description

**peer-server** *id* *svr\_id*  
**no peer-server** *id* *svr\_id*

**no**

Removes the identified peer-server definition from the system configuration.

**svr\_id**

*svr\_id* uniquely identifies a peer-server. The id must be an integer from 1 to 144. For SGSN Release 15.0, the id must be an integer from 1 to 256.

### Usage Guidelines

Use the following command to create a definition for peer-server 2 and enter the configuration mode to configure the communication parameters for peer-server 12.

### Example

```
peer-server id 12
```

# route

This command configures SS7 routes for the current SS7 routing domain.



## Important

In Release 20 and later, HNBNW is not supported. This command must not be used for HNBNW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

## Syntax Description

```
route destination-point-code dp_code { linkset id id [ priority pri_value ]  
| peer-server-id svr_id }  
no route destination-point-code dp_code { linkset id id | peer-server-id  
svr_id }
```

### no

Removes the SS7 route from the current SS7 routing domain configuration.

### destination-point-code *dp\_code*

Specifies the SS7 destination point code for this route.

Reminder: the point-code structure must match the variant defined for the SS7 routing domain when the SS7RD was configured in the global configuration mode.

### linkset id *id*

This keyword identifies a linkset instance, created and configured with the **linkset** command.

This keyword identifies a linkset instance, created and configured with the **linkset** command.

*id*: Must be an integer from 1 to 49.

### peer-server-id *svr\_id*

This keyword identifies a peer-server configuration instance, created and configured with the **peer-server** command.

*svr\_id* must be an integer from 1 to 49.

**Usage Guidelines**

This command associates the previously configured linksets and peer servers and the destination point codes with a specified SS7 route.

**Example**

Define a route setting an ITU-type destination point-code address for the linkset Id 12:

```
route destination-point-code 6.211.6 linkset id 12
```

# routing-context

Identifies the routing context for this SS7 routing domain.



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

## Syntax Description

**routing-context** *value*  
**default routing-context**

### default

Resets the local routing context value to the index (instance ID) for this SS7 routing domain.

### value

An integer that uniquely identifies the routing context for this SS7 routing domain.

*value* : Must be integers from 1 to 65535 (for releases 8.0) or 1 to 4294967295 (for releases 8.1 to 17.0) or 0 to 4294967295 (for releases 17.1 and higher) .

## Usage Guidelines

Use this command to set the routing context IDs for a specific SS7 routing domain configuration.

## Example

```
routing-context 2355
```

# ssf

This command sets the network indicator in the subservice field for SS7 message signal units (MSUs).



## Important

In Release 20 and later, HNBNW is not supported. This command must not be used for HNBNW in Release 20 and later. For more information, contact your Cisco account representative.

## Product

SGSN  
HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > SS7 Routing Domain Configuration

**configure** > **ss7-routing-domain** *routing\_domain\_id* **variant** *variant\_type*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-ss7-routing-domain-ss7rd_id)#
```

## Syntax Description

**ssf** ( **international** | **national** | **reserved** | **spare** )

### international

The network indicator identifies the message as international with a point code structure that does not match the national point code structure,

### national

The network indicator identifies the messages as having a national point code structure.

### reserved

Provides an alternate network indicator for national messages.

### spare

Provides an alternate network indicator for international messages.

## Usage Guidelines

In SS7 signaling, the Message Transfer Part (MTP) Level 2 message signal units (MSUs) contain a service information octet (SIO). The SIO field in an MSU contains a 4-bit subservice field (SSF) followed by a 4-bit service indicator. The indicator carried in the message's routing information typically identifies the structure of the point code as a message from within a nation or as a message coming from outside the nation - international. As well, the 4-bit SSF determines the point code structure of the messages transmitted from the SGSN.

**Example**

For messages being transmitted within a country, set the indicator to national with the following command.

```
ssf national
```







## SSH Configuration Mode Commands

The Secure Shell Configuration Mode is used to manage the SSH server options for the current context.



### Important

You must use the **ssh generate key** command in Context Configuration Mode to generate the sshd keys before you can configure the sshd server

### Command Modes

Exec > Global Configuration > Context Configuration > SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-sshd) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [allowusers add](#), on page 698
- [authorized-key](#), on page 700
- [ciphers](#), on page 701
- [client-alive-countmax](#), on page 703
- [client-alive-interval](#), on page 705
- [do show](#), on page 706
- [end](#), on page 707
- [exit](#), on page 708
- [listen](#), on page 709
- [macs](#), on page 710
- [max servers](#), on page 712
- [subsystem](#), on page 713

# allowusers add

Specifies and controls which users can access SSH services.

---

## Product

All

---

## Privilege

Security Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > SSH Configuration

**configure** > **context** *context\_name* > **server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

## Syntax Description

```
[ default | no ] allowusers add user_list
```

### **default**

Unrestricted access for all users.

### **no**

Removes the list of user name patterns resulting in unrestricted access by all users.

### **user\_list**

Specifies a list of user name patterns, separated by spaces, as an alphanumeric string of 1 through 999 characters. If the pattern takes the form 'USER' then login is restricted for that user. If the pattern is in the format 'USER@IP\_ADDRESS' then USER and IP address are separately checked, restricting logins to those users from that particular iIP address.

The following limits apply to the *user\_string*:

- The maximum length of this string is 3000 bytes including spaces.
- The maximum number of allowusers, which is counted by spaces, is 256, which is consistent with the limit from OpenSSH.




---

### Important

If you exceed either of the above limits, an error message is displayed. The message prompts you to use a regular expression pattern to shorten the string, or remove all the allowusers with **no allowusers add** or **default allowusers add** and re-configure.




---

### Important

For more details about how to create complex rules, see the OpenSSH sshd\_config man page. **add** - Add more users to the list of user name patterns.

---

## Usage Guidelines

Use this command to specify and control which users can access SSH services.

Access to a service may be restricted to users having a legitimate need. This restriction applies on a white-list basis: only explicitly allowed users shall connect to a host via SSH and possibly from a specified source IP addresses. Under OpenSSH, the AllowUsers directive of sshd\_config specifies a list of SSH authorized users and groups.

### Example

The following command specifies an AllowUsers list of four users:

```
allowusers add user1 user2@10.1.1.1 user3@10.1.1.2 user4
```

# authorized-key

Sets or removes a user name having authorized keys for access to the sshd server in the current context.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

**Syntax Description**

**authorized-key username *user\_name* host *host\_ip* [ type { v2-dsa | v2-rsa } ]**

**default**

Resets the parameter to the default value.

**username *user\_name***

Sets a username as having authorized keys for access to the sshd server. Specifies the username as an alphanumeric string of 1 through 255 characters.

**host *host\_ip***

Associates an SSH host having the authorization keys for the username as an host IP address in IPv4 dotted decimal or IPv6 colon-separated-hexadecimal notation.

**[ type { v2-dsa | v2-rsa } ]**

Specifies which type of SSH authorization key will be accepted instead of all key types. The options are: **v2-dsa** (SSHv2 Digital Signature Algorithm), or **v2-rsa** (SSHv2 Rivest, Shamir and Adleman).

---

**Usage Guidelines**

Use this command to set a username with authorized keys for access to the sshd server within the current context.

Usernames should be created using the **nopassword** option to prevent bypassing of the sshd keys (**administrator** command in Context Configuration mode).




---

**Important**

Only 10 sshd authorization-keys can be configured per context.

---

**Example**

The following command specifies that username *dbailey* with authorization keys at host IP address *10.1.1.1* can access the system with all types of authorization keys:

```
authorized-key username dbailey host 10.1.1.1
```

# ciphers

Configures the cipher priority list in sshd for SSH symmetric encryption. It changes the cipher option for that context.

**Product** All

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

**Syntax Description** [ **default** ] **ciphers** *algorithm*

## default

### Release 20.x to 21.15 (Normal build only)

Resets the value of *algorithm* in a Normal build to:

```
blowfish-cbc,3des-cbc,aes128-cbc,aes128-ctr,aes192-ctr,aes256-ctr,aes128-gcm@openssh.com,aes256-gcm@openssh.com,chacha20-poly1305@openssh.com
```

Resets the value of *algorithm* in a Trusted build as follows:

```
aes256-ctr,aes192-ctr,aes128-ctr
```

### Release 21.16 onwards: Post OpenSSH to CiscoSSH Upgrade and Migration

#### Default Algorithms in a Normal Build:

```
aes256-ctr,aes192-ctr,aes128-ctr,aes256-gcm@openssh.com,aes128-gcm@openssh.com,chacha20-poly1305@openssh.com
```

#### Available Algorithms in a Normal Build:

```
aes256-ctr,aes192-ctr,aes128-ctr,aes256-gcm@openssh.com,aes128-gcm@openssh.com,chacha20-poly1305@openssh.com,aes128-cbc
```

#### Default and Available Algorithms in Trusted Builds:

```
aes256-ctr,aes192-ctr,aes128-ctr
```



**Note** There is no change in the default and configurable Ciphers for Trusted builds.

## *algorithm*

Specifies the algorithm to be used as a single string of comma-separated variables (no spaces) in priority order from those shown below:

- **blowfish-cbc** – symmetric-key block cipher, Cipher Block Chaining, CBC



---

**Note** This algorithm is removed post the OpenSSH to CiscoSSH upgrade and migration.

---

- **3des-cbc** – Triple Data Encryption Standard, CBC
- **aes128-cbc** – Advanced Encryption Standard, 128-bit key size, CBC
- **aes128-ctr** – Advanced Encryption Standard, 128-bit key size, Counter-mode encryption, CTR
- **aes192-ctr** – Advanced Encryption Standard, 192-bit key size, CTR
- **aes256-ctr** – Advanced Encryption Standard, 256-bit key size, CTR
- **aes128-gcm@openssh.com** – Advanced Encryption Standard, 128-bit key size, Galois Counter Mode [GCM], OpenSSH
- **aes256-gcm@openssh.com** – Advanced Encryption Standard, 256-bit key size, GCM, OpenSSH
- **chacha20-poly1305@openssh.com** – ChaCha20 symmetric cipher, Poly1305 cryptographic Message Authentication Code [MAC], OpenSSH

*algorithm* is a string of 1 through 511 alphanumeric characters.



---

**Important**

For release 20.0 and higher Trusted builds, only the AES128-CTR, AES-192-CTR and AES-256CTR ciphers are available.

---

---

**Usage Guidelines**

Use this command to configure the cipher priority list in sshd for SSH symmetric encryption.

**Example**

The following command sets the supported SSH algorithms and their priority.

```
ciphers blowfish-cbc,aes128-cbc,aes128-ctr,aes192-ctr,aes256-ctr
```

# client-alive-countmax

Sets the number of client-alive messages which may be sent without sshd receiving any messages back from the SSH client. If this threshold is reached while the client-alive messages are being sent, sshd disconnects the SSH client thus terminating the session.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SSH Configuration

**configure** > **context** *context\_name* > **server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

**Syntax Description**

[ **default** | **no** ] **client-alive-countmax** *count\_number*

**default**

Sets the default value for this parameter to 3.




---

**Important**

For higher security, Cisco recommends at least a client-alive-countmax of 2 and client-alive-interval of 5. Smaller session logout values may lead to occasional ssh session logouts. Adjust values to balance security and user friendliness.

**no**

Disables the client-alive-countmax parameter.

**count\_number**

Specifies the number of times a client-alive message will be sent as an integer from 1 through 3. The messages are sent following the expiry of each client-alive interval. Default = 3

Unresponsive SSH clients will be disconnected when the maximum number of client-alive-intervals have expired.

---

**Usage Guidelines**

Use this command to set the number of client-alive messages which may be sent without sshd receiving any messages back from the SSH client. If this threshold is reached while client-alive messages are being sent, sshd will disconnect the SSH client, terminating the session. The client-alive messages are sent through the encrypted channel and, therefore, are not spoofable. The client-alive mechanism is valuable when the client or server depend on knowing when a connection has become inactive.




---

**Important**

This parameter applies to SSH protocol version 2 only.

**Example**

The following command sets the SSH client-alive-countmax to 2.

```
client-alive-countmax 2
```



# client-alive-interval

Sets a timeout interval in seconds after which if no data has been received from the SSH client, sshd sends a message through the encrypted channel to request a response from the client.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

**Syntax Description** [ **default** | **no** ] **client-alive-interval** *seconds*

## default

Sets the client-alive-interval to 15 seconds.



---

**Important**

For higher security, Cisco recommends at least a client-alive-interval of 5 and client-alive-countmax of 2. Smaller session logout values may lead to occasional ssh session logouts. Adjust values to balance security and user friendliness.

---

## no

Disables the client-alive-interval parameter.

---

## seconds

Specifies the amount of time in seconds that sshd waits to receive a response from the SSH client as an integer from 1 through 15. Default = 15

---

**Usage Guidelines**

Use this command to set a timeout interval in seconds after which if no data has been received from the client, sshd sends a message through the encrypted channel to request a response from the client. The number of times that the message is sent is determined by the client-alive-countmax parameter. The approximate amount of time before sshd disconnects an SSH client disconnect = client-alive-countmax X client-alive-interval.



---

**Important**

This parameter applies to SSH protocol version 2 only.

---

## Example

The following command sets the SSH client-alive-interval to 5 seconds.

```
client-alive-interval 5
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# listen

Configures the SSH server in the current context to only listen for connections from the interface with the specified IP address. The default behavior is to listen on all interfaces.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

**Syntax Description****listen** *ip\_address*  
**no listen****no**

Disable listening for a specific interface address and enable listening on all interfaces.

***ip\_address***Enables listening only on the interface with the specified IP address. *ip\_address* must be entered using IPv4 dotted-decimal notation.

---

**Usage Guidelines**

Use this command to configure the SSH server for the current context to only listen for connections from the interface with the specified IP address. Only one IP address may be set for listening.

**Example**The following command specifies that the Server should only listen for connections in the interface with the IP address of *192.168.0.10*:

```
listen 192.168.0.10
```

# macs

Configures the MAC algorithm priority list in sshd for SSH symmetric encryption. It changes the MAC algorithm for that context.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

**Syntax Description** **macs***algorithm*

**default macs**

## default

### Release 20.x to 21.15

Resets the value of *algorithm* in a Normal build and Trusted build to:

```
hmac-sha2-512-etm@openssh.com,hmac-sha2-256-etm@openssh.com,hmac-sha1-etm@openssh.com,hmac-sha2-512,hmac-sha2-256,hmac-sha1
```

Available algorithms in a Normal build are:

```
hmac-sha2-512-etm@openssh.com,hmac-sha2-256-etm@openssh.com,hmac-sha1-etm@openssh.com,hmac-sha2-512,hmac-sha2-256,hmac-sha1,umac-128-etm@openssh.com,umac-128@openssh.com,umac-64-etm@openssh.com,umac-64@openssh.com
```

Available algorithms in a Trusted build are:

```
hmac-sha2-512-etm@openssh.com,hmac-sha2-256-etm@openssh.com,hmac-sha1-etm@openssh.com,hmac-sha2-512,hmac-sha2-256,hmac-sha1
```

### Release 21.16 onwards: Post OpenSSH to CiscoSSH Upgrade and Migration

#### Default and Available Algorithms in Normal Builds:

```
hmac-sha2-512-etm@openssh.com,hmac-sha2-256-etm@openssh.com,hmac-sha1-etm@openssh.com,hmac-sha2-512,hmac-sha2-256,hmac-sha1
```

#### Default Algorithms in Trusted Builds:

```
hmac-sha2-512,hmac-sha2-256,hmac-sha1
```

#### Available Algorithms in Trusted Builds:

```
hmac-sha2-512,hmac-sha2-256,hmac-sha1
```




---

**Note** hmac-sha2-512-etm@openssh.com,hmac-sha2-256-etm@openssh.com,hmac-sha1-etm@openssh.com are removed from the Trusted builds.

---

**algorithm**

- Specifies the algorithms to be used as a single string of comma-separated variables (no spaces) in priority order (left to right) from those listed as follows:
  - HMAC = hash-based message authentication code
  - SHA2 = Secure Hash Algorithm 2
  - SHA1 = Secure Hash Algorithm 1
  - ETM = Encrypt-Then-MAC
  - UMAC = message authentication code based on universal hashing

*algorithm* is a string of 1 through 511 alphanumeric characters.

---

**Usage Guidelines**

Use this command to configure the priority of MAC algorithms in `sshd` for SSH symmetric encryption.

**Example**

The following command sets the supported MAC algorithms and their priority.

**MACs**

```
mac-sha2-512-etm@openssh.com,mac-sha2-256-etm@openssh.com,mac-sha1-etm@openssh.com,mac-sha2-512,mac-sha2-256,mac-sha1
```

## max servers

Configures the maximum number of SSH servers that can be started within any 60-second interval. If this limit is reached, the system waits two minutes before trying to start any more servers.

---

### Product

All

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

### Syntax Description

**max servers** *number*

#### *number*

Default: 40

Specifies the maximum number of servers that can be spawned in any 60-second interval. *number* must be an integer from 1 through 100.

In 16.0 and later releases, this range is increased to 1-4000 to support the Stranded CDR feature. For more information on this feature, see the "**gtpp push-to-active url**" CLI command in the Global Configuration mode.

---

### Usage Guidelines

Set the number of servers to tune the system response as a heavily loaded system may need more servers to support the incoming requests.

The converse would be true as well in that a system can benefit by reducing the number of servers such that telnet services do not cause excessive system impact to other services.

### Example

```
max servers 50
```



# subsystem

Configures the system to perform file transfers using Secure FTP (SFTP) over ssh v2. Administrators must be configured with the FTP attribute privilege to issue this command. This command also supports creation of SFTP subsystem root directories with access privileges. Administrators can assign an SFTP subsystem to local users.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; SSH Configuration

**configure > context *context\_name* > server sshd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-sshd)#
```

---

**Syntax Description**

```
subsystem { cli | sftp [ name sftp_name root-dir pathname mode { read-only |
  readwrite } ] }
```

**no**

```
subsystem { cli | sftp }
```

```
no subsystem sftp name sftp_name
```

**no**

Disables the SFTP ssh file transfer method or access to the CLI via ssh or a specified SFTP subsystem.




---

**Important**

An SFTP subsystem can only be removed if the subsystem is not currently assigned to any local user.

---

**cli**

Default: Enabled

Configures the SSH system for the current context to allow access to the CLI.

**sftp**

Default: Disabled

Enables the SSH system for the current context to perform file transfers using Secure FTP (SFTP) over ssh v2.

**name *sftp\_name***

Assigns a name for this SFTP subsystem. *sftp\_name* is an alphanumeric string that uniquely identifies this subsystem.

**root-dir *pathname***

Specifies the root directory to which SFTP files can be transferred. Options include:

- /hd-raid/records/cdr
- /flash

**mode { read-only | readwrite }**

Specifies the SFTP transfer mode. Options include:

- read-only
- read-write

---

**Usage Guidelines**

Use this command to enable or disable file transfers using SFTP over an ssh v2 tunnel.

You can also create multiple SFTP subsystems with an associated pathname and access privilege (read-only or read-write). When creating a local user, an administrator can assign the user an SFTP subsystem. If the user is not an administrator, he or she will only be able to access the subsystem with read-only privilege. The SFTP subsystem directory becomes the SFTP user's root directory with associated access privileges.

Also use this command to enable or disable access to the CLI over an SSH connection.

**Example**

The following command enables SFTP for the current context:

```
subsystem sftp
```

The following command disables access to the CLI through an SSH session for the current context:

```
no subsystem cli
```

The following command creates an SFTP subsystem for CDR records with read-write privileges:

```
subsystem sftp name cdr-rw-server root-dir /hd-raid/records/cdr mode  
readwrite
```



## Stats Profile Configuration Mode Commands

The Stats Profile Configuration Mode Commands allow operators to support the collection and viewing of QoS statistics on a Quality of Service Class Index (QCI) and Allocation and Retention Priority (ARP) basis.

Specifically, this mode enables operators to monitor QoS statistics that identify multiple services running with the same QCI value. In addition, packet drop counters provide the specific reason the Enhanced Charging Service (ECS) dropped a packet. The packet drop counters provide output on a per ARP basis. This provides additional information that operators can use to troubleshoot and identify network issues that may be affecting service.

### Command Modes

Exec > Global Configuration > Stats-Profile

**configure** > **stats-profile** > *stats\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-stats-profile)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 716
- [end](#), on page 717
- [exit](#), on page 718
- [packet-drop](#), on page 719
- [qci](#), on page 720
- [rat-type](#), on page 722

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# packet-drop

Enables the collection of detailed packet drop counters.



---

**Important**

ARP Granularity for QCI Level Counters is a license-controlled feature. Per QCI Packet Drop Counters functionality does not require a license. Contact your Cisco account or support representative for licensing details.

---

---

**Product**

GGSN  
P-GW  
SAEGW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Stats-Profile

**configure** > **stats-profile** > *stats\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-stats-profile)#
```

---

**Syntax Description**

[ **no** ] **packet-drop**

**no**

Disables the collection of packet drop statistics.

**packet-drop**

Enables the collection of packet drop statistics.

---

**Usage Guidelines**

Use this command to enable the collection of packet drop statistics.

---

**Example**

The following command enables the collection of packet drop statistics:

```
packet-drop
```

# qci

Enables the collection of QCI level statistics for a configured Stats Profile.



## Important

ARP Granularity for QCI Level Counters is a license-controlled feature. Per QCI Packet Drop Counters functionality does not require a license. Contact your Cisco account or support representative for licensing details.

## Product

GGSN  
P-GW  
SAEGW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Stats-Profile

**configure** > **stats-profile** > *stats\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-stats-profile)#
```

## Syntax Description

```
[ no ] qci { all | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | [ non-std { non-gbr  
| gbr } ] } { arp { all | [ 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | 9 | 10 | 11  
| 12 | 13 | 14 | 15 ] + } }
```

### no

Disables the collection of the specified QCI level statistics.

### qci

Enables the collection of QCI level statistics:

- **qci**: enables the collection of ARP priority level statistics for the specified QCIs. Valid entries are standard QCI values 1 through 9 or **all**.
- **non-std**: enables the collection of ARP priority level statistics for non-standard QCIs.
- **non-gbr**: enables the collection of ARP priority level statistics for non-standard non-guaranteed bit rate (GBR) QCIs.
- **gbr**: enables the collection of ARP priority level statistics for non-standard GBR QCIs.
- **arp**: enables the collection of ARP priority level statistics for the specified ARP values. Valid entries are from 1 to 15 or **all**.

## Usage Guidelines

Use this command to enable the collection of QCI and ARP level statistics.



**Example**

The following command enables the collection of ARP priority level statistics for all QCI and ARP values:

```
qci all arp all
```

# rat-type

Configures collection of RAT level statistics.

---

## Product

GGSN  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Stats-Profile

**configure** > **stats-profile** > *stats\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-stats-profile)#
```

---

## Syntax Description

```
[ no ] rat-type { [geran | utran | eutran]* }
```

### no

Disables statistics collection based on RAT type.

### rat-type

Configures collection of RAT level statistics.

### geran

Configures collection of statistics for RAT Type GERAN.

### utran

Configures collection of statistics for RAT Type UTRAN.

### eutran

Configures collection of statistics for RAT Type EUTRAN.

---

## Usage Guidelines

Use this command to configure collection of RAT level statistics.

## Example

The following command configures collection of statistics for RAT type GERAN:

```
rat-type geran
```



## Subscriber Configuration Mode Commands

The Subscriber Configuration Mode is used to create local subscribers as well as to set default subscriber options for the current context.

### Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [aaa](#), on page 727
- [access-link ip-fragmentation](#), on page 729
- [accounting-mode](#), on page 730
- [active-charging bandwidth-policy](#), on page 732
- [active-charging link-monitor tcp](#), on page 733
- [active-charging radio-congestion](#), on page 735
- [active-charging rulebase](#), on page 736
- [always-on](#), on page 737
- [asn-header-compression-rohc](#), on page 738
- [asn nspid](#), on page 739
- [asn-pdfid](#), on page 740
- [asn-policy](#), on page 741
- [associate accounting-policy](#), on page 744
- [authorized-flow-profile-id](#), on page 745
- [content-filtering category](#), on page 746
- [credit-control-client](#), on page 748
- [credit-control-group](#), on page 750
- [credit-control-service](#), on page 751
- [data-tunneling ignore df-bit](#), on page 752
- [dcca peer-select](#), on page 753
- [default](#), on page 754

- description, on page 757
- dhcp dhcpv6, on page 758
- dhcp options, on page 759
- dhcp parameter-request-list-option, on page 760
- dhcp service, on page 761
- dns, on page 762
- do show, on page 763
- eap, on page 764
- encrypted password, on page 765
- end, on page 766
- exit, on page 767
- external-inline-server, on page 768
- firewall policy, on page 769
- gtp, on page 771
- idle-timeout-activity, on page 772
- ikev2 tsr, on page 773
- ims application-manager, on page 774
- ims-auth-service, on page 775
- inter-pdsn-handoff, on page 776
- ip access-group, on page 777
- ip address, on page 778
- ip address pool, on page 779
- ip address secondary-pool, on page 781
- ip allowed-dscp, on page 782
- ip context-name, on page 785
- ip header-compression, on page 786
- ip hide-service-address, on page 789
- ip local-address, on page 790
- ip multicast discard, on page 791
- ip qos-dscp, on page 792
- ip route, on page 794
- ip source-validation, on page 796
- ip user-datagram-tos copy, on page 797
- ip vlan, on page 799
- ipv6 access-group, on page 800
- ipv6 address, on page 801
- ipv6 dns, on page 802
- ipv6 dns-proxy, on page 803
- ipv6 egress-address-filtering, on page 804
- ipv6 initial-router-advt, on page 805
- ipv6 interface-id, on page 807
- ipv6 minimum-link-mtu, on page 808
- ipv6 secondary-address, on page 809
- l2tp send accounting-correlation-info, on page 810
- l3-to-l2-tunnel address-policy, on page 811
- loadbalance-tunnel-peers, on page 813

- long-duration-action, on page 814
- max-pdn-connections, on page 816
- mediation-device, on page 817
- mobile-ip, on page 819
- mobile-ip ha, on page 823
- mobile-ip reg-lifetime-override, on page 824
- mobile-ip send access-technology, on page 825
- mobile-ip send accounting-correlation-info, on page 826
- mobile-ip send bsid, on page 827
- mobile-ip send pcf-address, on page 828
- mobile-ip send service-option, on page 829
- mobile-ip send subnet-id, on page 830
- mobile-ipv6, on page 831
- nai-construction-domain, on page 833
- nbns, on page 834
- nexthop-forwarding-address, on page 835
- npu qos, on page 836
- nw-reachability-server, on page 838
- outbound, on page 840
- overload-disconnect, on page 841
- password, on page 843
- pdif mobile-ip, on page 845
- permission, on page 846
- policy ipv6 tunnel, on page 847
- policy-group, on page 848
- ppp, on page 849
- prepaid 3gpp2, on page 853
- prepaid custom, on page 855
- prepaid unclassify, on page 857
- prepaid voice-push, on page 858
- prepaid wimax, on page 859
- proxy-dns intercept list-name, on page 860
- proxy-mip, on page 861
- qos apn-ambr, on page 862
- qos rate-limit, on page 864
- qos traffic-police, on page 869
- qos traffic-shape, on page 872
- radius accounting, on page 875
- radius group, on page 878
- radius returned-framed-ip-address, on page 879
- radius rulebase-format, on page 880
- rohc-profile-name, on page 882
- secondary ip pool, on page 883
- send-destination-pgw, on page 884
- simultaneous, on page 885
- timeout absolute, on page 886

- [timeout idle](#), on page 887
- [timeout long-duration](#), on page 889
- [tpo policy](#), on page 890
- [tunnel address-policy](#), on page 891
- [tunnel ipip](#), on page 893
- [tunnel ipsec](#), on page 894
- [tunnel l2tp](#), on page 895
- [w-apn](#), on page 897

# aaa

Configures authentication, authorization and accounting (AAA) functionality at the subscriber level.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
[ no ] aaa { accounting interim { interval-timeout interval_timeout | normal
| suppress } | group aaa_group_name | secondary-group aaa_secondary_group_name
}
default aaa { accounting interim [ interval-timeout ] | group |
secondary-group }
no aaa { accounting interim [ interval-timeout ] | group [ aaa_group_name ]
| secondary-group }
```

**default**

Configures the default setting for the specified parameter.

- **accounting**: Enables AAA accounting for subscribers.
- **group**: Uses the default AAA group—the one specified at the context level or in the default subscriber profile.
- **secondary-group**: Removes the secondary AAA group from the subscriber configuration.

**no**

- **accounting**: Disables AAA accounting for subscribers.
- **group**: Uses the default AAA group—the one specified at the context level or in the default subscriber profile.
- **secondary-group**: Removes the secondary AAA group from the subscriber configuration.

**accounting interim { interval-timeout *interval\_timeout* | normal | suppress }**

Specifies when system should send an interim accounting record to the server.

- **interval-timeout**: Specifies the time interval (in seconds) at which to send an interim accounting record. *interval\_timeout* must be an integer from 50 through 40000000.
- **normal**: If RADIUS accounting is enabled, send this Acct-Status-Type message when normally required by operation.

- **suppress**: If RADIUS accounting is enabled, suppress the sending of Acct-Status-Type message.

**group *aaa\_group\_name***

Specifies the AAA server group for the subscriber for authentication and/or accounting.

*aaa\_group\_name* must be an alphanumeric string of 1 through 63 characters.

**secondary-group *aaa\_secondary\_group\_name***

Specifies the secondary AAA server group for the subscriber.

*aaa\_secondary\_group\_name* must be an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines**

Use this command to configure AAA functionality at the subscriber level.

Instead of having a single list of servers per context, this feature configures multiple server groups within a context and applies individual server group for subscribers in that context. Each server group consists of a list of AAA servers for each AAA function (accounting, authentication, charging, etc.).

The AAA secondary server group supports the No-ACK RADIUS Targets feature in conjunction with PDSN/HA for secondary accounting (with different RADIUS accounting group configuration) to the RADIUS servers without expecting the acknowledgement from the server, in addition to standard RADIUS accounting. This secondary accounting will be an exact copy of all the standard RADIUS accounting message (RADIUS Start/Interim/Stop) sent to the standard AAA RADIUS server.

If the same AAA group is configured with both the **aaa group *aaa\_group\_name*** and the **aaa secondary-group *aaa\_group\_name*** commands, then this configuration will have no effect and secondary accounting will not happen.

The AAA secondary server group configuration takes effect only when used with subscriber accounting-mode set to radius-diameter. The RADIUS accounting triggers for both standard RADIUS accounting and secondary accounting will be taken from the AAA group configured with the **aaa group *aaa\_group\_name*** command. On the fly change of this configuration is not supported. Any change to the configuration will have effect only for new calls.

**Example**

The following command applies the AAA server group *star1* to subscribers:

```
aaa group star1
```



# access-link ip-fragmentation

Configures IP fragmentation processing over the Access-link.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

**access-link ip-fragmentation** { **normal** | **df-ignore** | **df-fragment-and-icmp-notify** }

**df-ignore**

Default: Enabled

Ignores the DF (Don't Fragment) bit setting. Fragments and forwards the packet over the access link.

**df-fragment-and-icmp-notify**

Default: Disabled

Partially ignores the DF bit. Fragments and forwards the packet, but also returns an ICMP error message to the source of the packet. The number of ICMP errors sent like this is rate-limited to one ICMP error packet per second per session.

**normal**

Default: Disabled

Normal processing. Drops the packet and sends an ICMP unreachable message to the source of packet. This is the default behavior.

---

**Usage Guidelines**

If the IP packet to be forwarded is larger than the access-link MTU and if the DF (Don't Fragment) bit is set for the packet, then the fragmentation behavior configured by this command is applied. Use this command to fragment packets even if they are larger than the access-link MTU.

**Example**

Set fragmentation so that the DF bit is ignored and the packet is forwarded anyway by entering the following command:

```
access-link ip-fragmentation df-ignore
```

# accounting-mode

Sets the accounting mode for the current local subscriber configuration.

---

## Product

PDSN  
HA  
ASN-GW  
SAEGW  
S-GW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**accounting-mode** { **flow-based** | **gtp** [ **radius-diameter** ] | **none** | **radius-diameter** [ **gtp** ] | **rf-style** }  
**default** **accounting-mode**

### default

Sets the type of accounting to be performed for the current local subscriber to the default setting.

Default: **radius-diameter**

### flow-based

Diameter flow-based accounting is enabled for the current local subscriber.

### gtp [ radius-diameter ]

GTPP CDR RADIUS accounting is enabled for the current local subscriber. The **radius-diameter** keyword is available if both GTPP RADIUS and RADIUS-Diameter accounting are to be used.

### none

Accounting is disabled for the current local subscriber and no charging records will be generated.

### radius-diameter [ gtp ]

RADIUS-Diameter accounting is enabled for the current local subscriber. The **gtp** keyword is available if both GTPP RADIUS and RADIUS-Diameter accounting are to be used.

### rf-style

Diameter Rf interface accounting is enabled for the current local subscriber.

---

**Usage Guidelines**

This command specifies which protocol, if any, will be used to provide accounting for PDP contexts accessing the APN profile.

Use this command to enable or disable RADIUS/Diameter accounting for any subscribers that use the current local subscriber configuration.

If the **gtp** option is used, then GTP RADIUS is used as configured in the Context Configuration mode or the AAA Server Group Configuration mode and GTP charging records will be enabled.

If the **radius-diameter** option is used, either the RADIUS or the Diameter protocol is used as configured in the Context Configuration mode or the AAA Server Group Configuration mode.

RADIUS accounting can also be enabled and disabled at the context level with the **aaa accounting** command in the Context Configuration Mode. If RADIUS accounting is enabled at the context level, the **accounting-mode** command can be used to disable RADIUS accounting for individual local subscriber configurations.

If the accounting mode is set to **rf-style**, then BM will generate accounting records corresponding to AIMS RF.

**Example**

To disable accounting for the current subscriber, enter the following command:

```
accounting-mode none
```

# active-charging bandwidth-policy

Configures the bandwidth policy to be used for the subscriber.

---

**Product**

ACS

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**active-charging bandwidth-policy** *bandwidth\_policy\_name*  
 { **default** | **no** } **active-charging bandwidth-policy**

**default**

Specifies that the default bandwidth policy configured in the rulebase be used for this subscriber.

**no**

Disables bandwidth control for this subscriber.

**active-charging bandwidth-policy** *bandwidth\_policy\_name*

Specifies name of the bandwidth policy.

*bandwidth\_policy\_name* must be an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines**

Use this command to configure bandwidth policy to be used for subscribers.

**Example**

The following command configures a bandwidth policy named *standard* for the subscriber:

```
active-charging bandwidth-policy standard
```

# active-charging link-monitor tcp

Enables the TCP link monitoring feature on the Mobile Video Gateway. This command can be configured in either APN Configuration Mode or Subscriber Configuration Mode.



## Important

In release 20.0, MVG is not supported. This command must not be used in release 20.0. For more information, contact your Cisco account representative.

## Product

MVG

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

```
configure > context context_name > subscriber { default | name subscriber_name }
```

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

```
[ default | no ] active-charging link-monitor tcp [ log [ rtt [ histogram | time-series ] [ bitrate [ histogram | time-series ] ] | bitrate [ histogram | time-series ] [ rtt [ histogram | time-series ] ] ] ] [ -noconfirm ]
```

### default

Sets TCP link monitoring to its default value, which is the same as [ **no** ].

### no

Deletes the TCP link monitoring settings and disables TCP link monitoring if previously configured.

### active-charging link-monitor tcp

Enables the TCP link monitoring feature on the Mobile Video Gateway. Note that TCP link monitoring is not enabled by default. Also note that when this command is configured without the **log** option, TCP link monitoring is enabled without logging, and the output from TCP link monitoring is only used by the dynamic translating feature.

```
log [ rtt [ histogram | time-series ] [ bitrate [ histogram | time-series ] ] | bitrate [ histogram | time-series ] [ rtt [ histogram | time-series ] ] ]
```

This option enables statistical logging for TCP link monitoring.

The **rtt** option can be used to enable either **histogram** or **time-series** logging for round-trip time (RTT).

Similarly, the **bitrate** option can be used to enable either **histogram** or **time-series** logging for bit rate.

When **rtt** and **bitrate** options are used without additional options, histogram and time-series logging are enabled for round-trip time (RTT) and/or bit rate respectively.

**-noconfirm**

Specifies that the command must execute without prompting for confirmation.

---

**Usage Guidelines**

Use this command to enable TCP link monitoring on the Mobile Video Gateway.

**Examples**

The following command enables TCP link monitoring with statistical logging, with histogram and time-series logging enabled for both RTT and bit rate:

```
active-charging link-monitor tcp log
```

The following command enables TCP link monitoring with statistical logging, with histogram and time-series logging enabled for RTT:

```
active-charging link-monitor tcp log rtt
```

The following command enables TCP link monitoring with statistical logging, with histogram logging enabled for RTT:

```
active-charging link-monitor tcp log rtt histogram
```

The following command enables TCP link monitoring with statistical logging, with histogram logging enabled for RTT and time-series logging enabled for bit rate:

```
active-charging link-monitor tcp log rtt histogram bitrate time-series
```

# active-charging radio-congestion

Enables the Congestion Management feature on the Mobile Video Gateway. This command can be configured in either APN Configuration Mode or Subscriber Configuration Mode.

**Important**

In release 20.0, MVG is not supported. This command must not be used in release 20.0. For more information, contact your Cisco account representative.

**Product**

MVG

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description**

**active-charging radio-congestion policy** *policy\_name*

[ **default** | **no** ] **active-charging radio-congestion policy**

**default**

Sets congestion management to its default value, which is the same as [ **no** ].

Default: Disabled

**no**

Deletes the settings and disables congestion management if previously configured.

**active-charging radio-congestion policy** *policy\_name*

Enables the Congestion Management feature on the Mobile Video Gateway.

*policy\_name* must be an alphanumeric string of 1 through 63 characters.

**Usage Guidelines**

Use this command to enable or disable congestion management on the Mobile Video Gateway at either APN or subscriber. As congestion management makes use of the Link Monitoring feature, this must also be enabled along with the congestion monitoring feature.

**Example**

The following command enables radio congestion for a policy named *test123* for the subscriber:

```
active-charging radio-congestion policy test123
```

# active-charging rulebase

Specifies the rulebase to be used for this subscriber.

---

## Product

ACS

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**active-charging rulebase** *rulebase\_name*

**no active-charging rulebase**

**no**

Removes the previously configured rulebase for the subscriber.

**active-charging rulebase** *rulebase\_name*

Specifies name of the ACS rulebase.

*rulebase\_name* must be the name of an ACS rulebase expressed as an alphanumeric string of 1 through 63 characters.

---

## Usage Guidelines

This command specifies the name of the rulebase for specific subscriber (reals).

If the specified rulebase does not exist in the Active Charging service, the call will be rejected.

## Example

The following command configures the ACS rulebase named *rule1* for the subscriber:

```
active-charging rulebase rule1
```



# always-on

Once the idle timeout limit is reached, keeps the current subscriber session connected as long as the subscriber is reachable.



**Caution** When `always-on` is enabled, the subscriber must have an idle time-out period configured (default is 0, no time-out). Failure to configure an idle time-out results in a subscriber session that is indefinite.

Two timers and a counter are associated with this feature. Refer to the `timeout` command in this chapter and the `ppp echo-retransmit-timeout msec` and `ppp echo-max-retransmissions num_retries` commands.

Default: Disabled.

---

**Product**

PDSN

ASN-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

[ **no** ] **always-on**

**always-on**

Specifies that the user will remain connected after the idle time expires.

**no**

Disables **always-on**. The user is disconnected after the idle time expires.

---

**Usage Guidelines**

If this parameter is enabled for a subscriber, when the idle time-out limit is reached the subscribers IP/PPP session remains connected as long as the subscriber is reachable. This is true even if the airlink between the mobile device and the RN (Radio Node) is moved from active to dormant (inactive) status. When the idle timeout limit is reached, the PDSN determines availability using link control protocol (LCP) keepalive messages. A response to these messages indicates that the "always-on" status should be maintained. Failure to respond to a predetermined number of LCP keepalive messages causes the PDSN to tear-down (disconnect) the subscriber session.

**Example**

Enable always on for the current subscriber by entering the following command:

```
always-on
```

# asn-header-compression-rohc

Negotiates Robust Header Compression (ROHC) support for subscriber calls with AAA and WiMAX. This configuration indicates the type of header compression supported and enabled on the ASN.

---

**Product** ASN-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description** [ **no** | **default** ] **asn-header-compression rohc**

**no**

Removes or disables the configured identifiers for ROHC in ASN-GW service.

**default**

The default is *disabled*.

---

**Usage Guidelines** Network Attached Storage (NAS) uses this configuration to indicate ROHC support of the subscriber TLV in the WiMAX-capability attribute within the Access Request. ROHC is applied only when ROHC is supported on the ASNGW and ROHC support is indicated by the AAA.

## Example

The following command enables ROHC:

```
asn-header-compression rohc
```

# asn nspid

Specifies the network service provider (NSP) associated with a WiMAX subscriber in an ASN-GW service. When configured, the NSP ID is sent in the Access-Request and Accounting messages.

---

**Product**

ASN-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** ] **asn nspid** *nsp\_id*

**no**

Removes or disables the configured identifiers for this network service provider in ASN-GW service.

**asn nspid** *nsp\_id*

Specifies the network service provider for this subscriber. This enables the MS to discover all accessible NSPs, and to indicate the NSP selection during connectivity to the ASN.

---

**Usage Guidelines**

Use this command to specify the NSP associated with a subscriber in an ASN-GW service.

*nsp\_id* is three bytes in hexadecimal format. For example: FF-EE-01

**Example**

The following command specifies the NSP for a subscriber in an ASN service:

```
asn nspid 0F-01-FE
```

# asn-pdfid

Configures the identifiers for packet data flow, service data flow, and service profile in an ASN-GW service.

---

## Product

ASN-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **asn-pdfid** *pdf\_id* **asn-service-profile-id** *svc\_profile\_id* **asn-sdfid** *sdf\_id*

**no**

Removes/disables the configured identifiers for this subscriber in ASN-GW service.

### **asn-pdfid** *pdf\_id*

Specifies the an unique ASN Packet Data Flow identifier for this subscriber.

*pdf\_id* must be an integer from 1 through 65535.

### **asn-service-profile-id** *svc\_profile\_id*

Specifies a unique ASN Service Profile Identifier for this subscriber.

*svc\_profile\_id* is a Service Profile Identifier configured in the Context Configuration Mode.

### **asn-sdfid** *sdf\_id*

Specifies the an unique ASN Service Data Flow identifier for this subscriber.

*sdf\_id* must be an integer from 1 through 65535.

---

## Usage Guidelines

Use this command to configure subscriber profile for QoS parameters in an ASN-GW service.

A maximum of four QoS profiles can be configured for a subscriber.

## Example

The following command configures the QoS profile for a subscriber as PDF id 1, Service Profile id 3, and Service Data Flow id 2:

```
asn-pdfid 1 asn-service-profile-id 3 asn-sdfid 2
```

# asn-policy

Configures the identifiers for packet data flow, service data flow, and service profile in an ASN-GW service.

---

**Product**

ASN-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
asn-policy [classifiers downlink { strict | loose} | idle-mode { allow | disallow } | notification-idle-mode {allow | disallow} | notification-handoff { allow | disallow }auth-only {allow | disallow } | ms-requested-classifiers {allow | dissalow}]
```

```
[ default ] asn-policy classifiers downlinkidle-mode
```

**no**

Removes or disables the configured policy for this subscriber in ASN-GW service.

**default**

Sets the ASN policy to default for this subscriber.

For downlink traffic classifier default policy is "loos" and for idle mode policy the default action is to allow idle mode operation in an ASN-GW service.

**idle-mode**

Sets the idle mode policy for this subscriber in an ASN-GW service. If enabled, Interim-Update is sent with the BSID and WiMAX-Idle\_Mode Transition as Idle. If disabled, the Interim can be sent when the call is in the idle mode based on the interim timer. At this point, the last known BSID is reported to the RADIUS server.

**notification-idle-mode**

Default: allow

Use to enable or disable Idle-Mode-Notification capabilities. When you enable this command, when the call moves from active to idle, or idle to active, Accounting Interim is sent.

**notification-handoff**

Default: allow

If enabled, the Interim-Update is sent with the BSID and SN-Handoff-Indicator as Active Handoff.

**allow**

Default: enabled

Enables the policy for this subscriber to allow idle mode operation in an ASN-GW service.

**disallow**

Default: disabled

Enable the policy for this subscriber to disallow idle mode operation in an ASN-GW service.

**classifiers downlink**

Sets the classifier policy for all service flows coming from HA to FA for this subscriber's matching classifier.

**strict**

Default: disabled

This option discards all the service flows coming from HA to FA and any other packets not matching to any of the classifiers set for this subscriber.

**loose**

Default: enabled

This option allows all the service flows coming from HA to FA and any other packet does not matching to any of the classifiers set for this subscriber and sent to the BS/MS over downlink flow

**auth-only**

Specifies whether the call is Auth only or not.

**allow**

Enables the policy for this subscriber to allow auth-only in an ASN-GW service.

**disallow**

Default

Disables the policy for this subscriber to allow auth-only in an ASN-GW service.

**ms-requested classifiers**

Default: allow

By default ASNGW allows dynamic addition of classifiers by the MS during MS-initiated service flow creation or modification.

---

**Usage Guidelines**

Use this command to configure subscriber policy to allow/disallow the idle mode operation or the downlink traffic flow for a subscriber in an ASN-GW service.

For authentication configuration, the ASN-GW supports the Initial Network Entry (INE) for Ethernet CS calls. The base station supports Ethernet CS traffic to the network. The INE procedure includes the

Authentication of the service flows and IP-Address allocation through DHCP. Authentication is based on the Extensible Authentication Protocol (EAP).

This command allows MS to transition to idle mode with an ASN-GW.

### Example

The following command configures the policy to allow the idle mode for an MS with an ASN-GW:

```
default asn-policy idle-mode
```

# associate accounting-policy

Associates the subscriber with specific pre-configured policies configured in the same context.

---

## Product

P-GW  
SAEGW

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **associate accounting-policy** *name*

### **no**

Removes the selected association from this subscriber.

### **name**

Associates the subscriber with an accounting policy configured in the same context.

*name* must be an existing accounting policy expressed as a string of 1 through 63 characters.

Accounting policies are configured through the **policy accounting** command in the Context Configuration mode.

---

## Usage Guidelines

Use this command to associate the subscriber with an accounting policy configured in this context.

### **Example**

The following command associates this subscriber with an accounting policy called *acct1*:

```
associate accounting-policy acct1
```



# authorized-flow-profile-id

When a profile ID is requested by the Mobile Node (MN), this command sets the value that is authorized by the Access Gateway (AGW).

---

## Product

PDSN  
ASN-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**authorized-flow-profile-id** *profile\_id* **direction** { **bidirectional** | **forward** | **reverse** }

**no** **authorized-flow-profile-id** *profile\_id*

### no

Removes the existing profile ID setting specified by *profile\_id*. *profile\_id* must be an integer from 0 through 65535.

### **authorized-flow-profile-id** *profile\_id*

The profile ID number that is authorized for the current subscriber. *profile\_id* must be an integer from 0 through 65535.

### **direction** { **bidirectional** | **forward** | **reverse** }

This specifies in which data direction the profile ID should be applied.

- **bidirectional**: This profile ID pertains to both the forward and reverse directions.
- **forward**: This profile ID pertains to data going to the MN.
- **reverse**: This profile ID pertains to data coming from the MN.

---

## Usage Guidelines

Use this command to set the profile ID that the AGW will authorize for a subscriber.

### Example

Set the profile ID for both directions to 3 for the current subscriber by entering the following command:

```
authorized-flow-profile-id 3 direction bidirectional
```

# content-filtering category

Enables or disables the specified preconfigured Category Policy Identifier for policy-based Content Filtering support to the subscriber.

**Product** CF

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description** **content-filtering category policy-id** *cf\_policy\_id*

**no content-filtering category policy-id**

**no**

Disables the configured category policy ID for content filtering support to the subscriber. This is the default setting.

**content-filtering category policy-id** *cf\_policy\_id*

Applies the content filtering category policy ID, configured in ACS Configuration Mode, to this subscriber.

*cf\_policy\_id* must be a category policy ID expressed as an integer from 1 through 4294967295.

If the specified category policy ID is not configured in the ACS Configuration Mode, all packets will be passed regardless of the categories determined for such packets.



**Important**

Category Policy ID configured through this mode overrides the Category Policy ID configured using the **content-filtering category policy-id** command in the ACS Rulebase Configuration Mode.

**Usage Guidelines**

Use this command to enter the Content Filtering Policy Configuration Mode and enable or disable the Content Filtering Category Policy ID for a subscriber.



**Important**

If Content Filtering Category Policy ID is not specified here, the similar command in the ACS Rulebase Configuration Mode determines the policy.

Up to 64 different policy identifier can be defined in a Content Filtering support service.

**Example**

The following command enters the Content filtering Policy Configuration Mode and enables the Category Policy ID *101* for Content Filtering support:

```
content-filtering category policy-id 101
```

# credit-control-client

Configures the credit-control client parameters for the subscriber.

---

## Product

GGSN  
HA  
IPSG  
PDSN  
P-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
credit-control-client { event-based-charging | override session-mode {  
per-sub-session | per-subscriber } }
```

```
no credit-control-client { event-based-charging | override session-mode  
}
```

```
default credit-control-client event-based-charging
```

### no

Disables the configured setting.

### default

Resets the command to its default setting of disabled.

### event-based-charging

Enables event-based charging.

### override session-mode { per-sub-session | per-subscriber }

Overrides the session-mode configured through the CLI command "**require ecs credit-control session-mode per-subscriber**" in Global Configuration mode so that different subscriber groups can operate in different modes. For example, one subscriber group can be configured to work in per-subscriber mode, while another in per-sub-session mode.

This keyword is used to switch between subscriber level Gy and sub-session level Gy.




---

## Important

This CLI can be changed on the fly. The modified values will be reflected only in the new subscriber session.

---

The **no** command removes the override CLI and makes the subscriber group fall back to the configuration specified through the CLI command "**require ecs credit-control session-mode per-subscriber**".

---

**Usage Guidelines**

Use this command to configure the credit-control client parameters for the subscriber.

This configuration should be enabled to report UE's PLMN, timezone and ULI changes through Event-based-Gy session. In the event that both Gy Online charging and Gy event reporting are enabled, the P-GW shall send only CCR-Update requests to the OCS and shall not send CCR-Event requests.

With the inclusion of this keyword **override session-mode ...** in 14.1 release, it is possible to seamlessly change the configuration from bearer level to subscriber level and vice-versa without requiring a system reboot.

**Example**

The following command enables event-based Gy support for the subscriber:

```
credit-control-client event-based-charging
```

# credit-control-group

Configures the credit-control group for this subscriber.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**credit-control-group** *cc\_group\_name*

**no credit-control-group**

**no**

Removes the credit-control group from the subscriber configuration, if configured.

**credit-control-group** *cc\_group\_name*

Specifies name of the credit-control group.

*cc\_group\_name* must be an alphanumeric string of 1 through 63 characters.

---

## Usage Guidelines

Use this command to configure the credit-control group for the subscriber.

### Example

The following command configures the credit-control group named *test12* for the subscriber:

```
credit-control-group test12
```

# credit-control-service

Configures the credit-control service for this subscriber.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

[ **no** ] **credit-control-service** *cc\_service\_name*

**no**

Disables the credit-control service, if configured.

**credit-control-service** *cc\_service\_name*

Specifies the name of the credit-control service.

*cc\_service\_name* must be an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines**

Use this command to configure the credit-control service for subscribers.

**Example**

The following command configures the credit-control service named *test12* for the subscriber:

```
credit-control-service test12
```

## data-tunneling ignore df-bit

Controls the handling of the DF (Don't Fragment) bit present in the user IPv4/IPv6 packet for GRE, IP-in-IP tunneling used for the MIP data path. If this feature is enabled, and fragmentation is required for the tunneled user IPv4/IPv6 packet, then the DF bit is ignored and the packet is fragmented. Also the DF bit is not copied to the outer header. Default is enabled.

---

### Product

PDSN  
HA  
FA  
ASN-GW

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

### Syntax Description

[ **no** ] **data-tunneling ignore df-bit**

#### **no**

Disables this option. The DF bit in the tunneled IP packet header is not ignored during tunneling.

#### **data-tunneling ignore df-bit**

Ignores the DF bit in the tunneled IP packet header.

---

### Usage Guidelines

Use this command to configure a user so that during Mobile IP tunneling the DF bit is not ignored and packets are not fragmented.

#### **Example**

To disable fragmentation of a subscribers packets over a MIP tunnel even when the DF bit is present, enter the following command:

```
no data-tunneling ignore df-bit
```



# dcca peer-select

Specifies the Diameter credit control primary and secondary peer for credit control.

---

**Product**

ACS

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
dcca peer-select peer host_name [ realm realm_name ] [ secondary-peer host_name
[ realm realm_name ] ]
```

```
no dcca peer-select
```

**no**

Removes the previously configured Diameter credit control peer selection.

**peer** *host\_name*

Specifies a unique name for the peer. *peer\_name* must be an alphanumeric string of 1 through 63 characters that allows punctuation marks.

**secondary-peer** *host\_name*

Specifies a back-up host that is used for fail-over processing. When the route-table does not find an available route, the secondary host performs a fail-over processing. *host\_name* must be an alphanumeric string of 1 through 63 characters that allows punctuation marks.

**realm** *realm\_name*

The *realm\_name* must be an alphanumeric string of 1 through 63 characters that allows punctuation marks. The realm may typically be a company or service name.

---

**Usage Guidelines**

Use this command to select a Diameter credit control peer and realm.




---

**Caution**

This configuration completely overrides all instances of **diameter peer-select** that have been configured with in the Credit Control Configuration Mode for an Active Charging service.

---

**Example**

The following command selects a Diameter credit control peer named *test* and a realm of *companyx*:

```
dcca peer-select peer test realm companyx
```

# default

Restores the default value for the option specified for the current subscriber.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
default { access-link ip-fragmentation | accounting-mode | data-tunneling
  ignore df-bit | idle-timeout-activity dormant-downlink-data |
inter-pdsn-handoff | ip { alloc-method | allowed-dscp | header-compression
  | hide-service-address | multicast discard | qos-dscp | source-validation
  } | loadbalanace-tunnel-peers | long-duration-action | mobile-ip {
home-agent | mn-aaa-removal-indication | mn-ha-hash-algorithm |
reverse-tunnel | security-level | send { dns-address |
terminal-verification } } | permission | ppp { always-on-vse-packet |
data-compression { mode | protocols } | keepalive | min-compression-size
  | mtu } | radius accounting interim interval-timeout | timeout { absolute
  | idle } }
```

### access-link ip-fragmentation

Sets the method for fragmenting packets over the MN access link to its default of normal. Drop the packet and send ICMP unreachable to the source of packet.

### accounting-mode

Enables Radius accounting for the current local subscriber configuration.

### data-tunneling ignore df-bit

Sets this option to the default behavior, which is to send an *ICMP unreachable - need to frag* message back to the sender and drop the packet, in the case that fragmentation is required but the DF bit is set.

### idle-timeout-activity dormant-downlink-data

Sets this option to the default behavior. When downlink data packets are transmitted to the Mobile node and the session is in dormant mode the session idle timer is reset.

### inter-pdsn-handoff

During a handoff from one PDSN to another, if the Mobile requests an IP address of 0.0.0.0 or a mismatched IP address the PDSN will not disconnect the session immediately. The PDSN tries to assign the proposed address of the session in the IPCP configuration NAK.

**ip { | allowed-dscp | dhcp-relay | header-compression | hide-service-address | multicast discard | qos-dscp | source-validation | user-datagram-tos copy }**

**allowed-dscp:** resets the allowed DSCP parameters to the system defaults: class none, max-class be.

**hide-service-address:** specifies the default setting for hide the ip-address of the service from the subscriber. Default is Disabled

**dhcp-relay:** Configured with the DHCP server address during MS authentication. The AAA server sends the address of the DHCP server in the Access-Accept message. The DHCP relay uses this address to relay the DHCP messages from the MS to the DHCP server.

**multicast discard:** Configures the default multicast settings which is to discard PDUs

**qos-dscp:** Sets the quality of service setting to the system default.

**source-validation:** Specifies the default IP source validation. Default is Enabled.

**user-datagram-tos copy:** Disables copying of the IP TOS octet value to all tunnel encapsulation IP headers.

### **loadbalance-tunnel-peers**

Sets the tunnel load balancing algorithm to the system default.

### **long-duration-action**

Sets the action that is taken when the long duration timer expires to the default: detection.

**mobile-ip { home-agent | mn-aaa-removal-indication | mn-ha-hash-algorithm | reverse-tunnel | security-level | send { dns-address | terminal-verification } }**

**allow-aaa-address-assignment:** Disables the FA from accepting a home address assigned by an AAA server.

**home-agent:** Sets home agent IP address to its default of 0.0.0.0.

**match-aaa-assigned-address:** Disables the FA validating the home address in the RRQ against the one assigned by AAA server.

**mn-aaa-removal-indication:** Sets this parameter to its default of disabled.

**mn-ha-hash-algorithm:** Sets the encryption algorithm to the default of hmac-md5.

**reverse-tunnel:** Sets this parameter to its default of enabled.

**security-level:** Sets this parameter to its default of none.

**send dns-address:** Disables the HA from sending the DNS address NVSE in the RRP.

**send terminal-verification:** Disables the FA from sending the terminal verification NVSE in the RRQ.

### **permission**

Restores the subscriber's service usage defaults.

**ppp { always-on-vse-packet | data-compression { mode | protocols } | ip-header-compression negotiation | keepalive | min-compression-size | mtu }**

Sets the point-to-point protocol option defaults.

**always-on-vse-packet:** Re-enables the PDSN to send special 3GPP2 VSE PPP packets to the Mobile Node with a max inactivity timer value for always on sessions. This configuration is applicable only for PDSN or PDSNCLOSED-RP sessions.

**data-compression { mode | protocols }:** restores the default value for either the data compression **mode** or compression **protocols** as follows:

- mode stateless
- all protocols enabled

**ip-header-compression negotiation:** Sets the IP header compressions negotiation to the system default: force.

**keepalive:** sets the subscriber's PPP keep alive option to the system default: 30 seconds.

**min-compression-size:** Restores the PPP minimum packet size for compression: 128 octets.

**mtu:** Sets the maximum message transfer unit packet size to the system default: 1500 octets.

#### **radius accounting interim interval-timeout**

Disables the RADIUS accounting interim interval for the current subscriber.

#### **timeout [ absolute | idle | long-duration ]**

When a keyword is entered, this command resets the specified timeout to the system default: 0. When no keyword is specified, all timeouts are reset to the system defaults: 0.

#### **Usage Guidelines**

Use this keyword to reset subscriber data to the system defaults. This is useful in setting the subscriber back to the basic values to possibly aid in trouble shooting or tuning a subscriber's access and options.

#### **Example**

The following CLI commands restore default values for various options:

```
default ip qos-dscp
default permission
default data-compression mode
```

# description

Allows you to enter descriptive text for this configuration.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**description** *text*

**no description**

**no**

Clears the description for this configuration.

***text***

Enter descriptive text as an alphanumeric string of 1 to 100 characters.

If you include spaces between words in the description, you must enclose the text within double quotation marks (" "), for example, "AAA BBBB".

---

**Usage Guidelines**

The description should provide useful information about this configuration.

**Example**

The following command enters the text description: *EO134 Anaheim*.

```
description "EO134 Anaheim"
```

# dhcp dhcpv6

Specifies the DHCPv6 service to be used for this subscriber.

---

## Product

GGSN  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context *context\_name* > subscriber { default | name *subscriber\_name* }**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**dhcp dhcpv6 *service-name* *service\_name***

**no dhcp dhcpv6 *service-name***

**no**

Removes the DHCPv6 service for the subscriber.

**dhcpv6 *service-name* *service\_name***

Specifies the name of an existing DHCPv6 service to be used for this subscriber.

*service\_name* must be the name of a DHCPv6 service expressed as an alphanumeric string of 1 through 63 characters.

---

## Usage Guidelines

Use this command to apply or remove an existing DHCPv6 service to a subscriber template.

### Example

The following command applies a previously configured DHCPv6 service named *dhcpv6\_1* to a subscriber template:

```
dhcp dhcpv6 service-name dhcpv6_1
```

# dhcp options

Specifies the DHCP options which can be sent from the DHCP server for this subscriber.

---

## Product

GGSN  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber) #

---

## Syntax Description

**dhcp options code 43 hex-values** *hex\_values*  
**no dhcp options**

### no

Removes the DHCP options for the subscriber.

### options code 43 hex-values *hex\_values*

Specifies hex values for DHCP option 43.

*hex\_values* must be a dash-delimited list of hex data of size smaller than 506 datum.

---

## Usage Guidelines

Use this command to specify the DHCP options which can be sent from the DHCP server for this subscriber.

### Example

The following command applies hex values *ff-fe* for DHCP option 43:

```
dhcp options code 43 hex-values ff-fe
```

# dhcp parameter-request-list-option

Enables the sending of DHCP parameter request list option(s) in all outgoing messages for this subscriber.

---

## Product

P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **dhcp parameter-request-list-option** [ *options* ]

### **no**

Disables the sending of DHCP parameter request list option(s) in all outgoing messages.

### **options**

Specifies the value of particular DHCP parameter request list option(s).

*options* must be an integer from 1 through 254.




---

## Important

Multiple options may be selected in the same command.

---



---

## Usage Guidelines

Use this command to enable or disable the sending of DHCP parameter request list option(s) in all outgoing messages for this subscriber.

### **Example**

The following command enables DHCP parameter request list option inclusion in outgoing messages:

```
dhcp parameter-request-list-option
```



# dhcp service



## Important

In Release 20 and later, HNBGW is not supported. This command must not be used for HNBGW in Release 20 and later. For more information, contact your Cisco account representative.

Enables DHCP service configuration accessible to the Se-GW context for subscriber. The specified DHCP service will be used for performing DHCP procedures between HNB-GW and HMS.

## Product

HNB-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

**dhcp service** *dhcp\_svc\_name* **context** *ctxt\_name*  
**no dhcp service**

**no**

Removes the specified DHCP service from the subscriber template configuration.

### **dhcp\_svc\_name**

Specifies name of the DHCP service configured in Context configuration mode for DHCP proxy support on HNB-GW.

*dhcp\_svc\_name* must be an alphanumeric string of 1 through 63 characters preconfigured within the same context of this subscriber.

### **context ctxt\_name**

Specifies the name of the context where DHCP service is configured for HNB-GW subscribers. *ctxt\_name* must be an alphanumeric string of 1 through 79 characters.

## Usage Guidelines

This command associates the subscriber template with pre-configured DHCP service configuration to provide accessibility to Se-GW with HNB-GW.

## Example

Following command applies a previously configured DHCP service named *dhcp\_hnb1* to a subscriber template within the context named *femto\_hnb*.

```
dhcp service dhcp_hnb1 context femto_hnb
```

# dns

Configures the domain name servers for the current subscriber.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **dns** { **primary** | **secondary** } *ip\_address*

### **no**

Indicates the IP address is to be removed as either a primary or secondary domain name server.

### **dns primary | secondary**

**dns primary**: Updates the primary domain name server for the subscriber.

**dns secondary**: Updates the secondary domain name server for the subscriber.

### **ip\_address**

Specifies the IP address of the domain name server using IPv4 dotted-decimal notation.

---

## Usage Guidelines

Set the subscriber DNS server lists as not all users will have the same set of servers.

### **Example**

The following commands enable primary and secondary DNS servers for the subscriber:

```
dns primary 10.2.3.4
```

```
dns secondary 10.2.5.6
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

## eap

Specifies the lifetime for a master session key (MSK) for extensible authentication protocol (EAP) authentication.

---

**Product** ASN-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description** [ **default** ] **eap msk-lifetime** *dur*

### default

Sets the lifetime duration to default value of 3600 seconds for master session key.

### msk-lifetime *dur*

Specifies the lifetime duration (in seconds) on Master Session Key (MSK) in seconds for a WiMAX subscriber EAP authentication.

*dur* is an integer from 60 through 65535.

---

**Usage Guidelines** This command is used to set the lifetime for MSK in EAP authentication for WiMAX subscriber.

### Example

The following command sets the lifetime for MSK key to *4800* seconds for a WiMAX subscriber through EAP authentication:

```
eap msk-lifetime 4800
```

# encrypted password

Designates use of password encryption.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

**encrypted password** *password*

**encrypted password** *password*

*password* is the encrypted password and must be an alphanumeric string of 1 through 132 characters.

---

**Usage Guidelines**

This command is normally used only inside configuration files.

**Example**

The following command sets an encrypted password of *qsdf12d4*:

```
encrypted password qsdf12d4
```

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

## external-inline-server

This is a restricted command.



# firewall policy



## Important

This command is only available in StarOS 8.0. In StarOS 8.1 and later releases, this configuration is available in the ACS Rulebase Configuration Mode.

Enables or disables Stateful Firewall support for the subscriber.

## Product

All

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

**firewall policy firewall-required**

{ **default** | **no** } **firewall policy**

**no**

Disables Stateful Firewall support for this subscriber.

**default**

Configures the default setting for Stateful Firewall support.

Default: Disabled

**firewall-required**

Enables Stateful Firewall support for this subscriber.

## Usage Guidelines

Use this command to enable or disable Stateful Firewall support for this subscriber.



## Important

Unless Stateful Firewall support for this subscriber is enabled using this command, firewall processing for this subscriber is disabled.



## Important

If firewall is enabled, and the rulebase has no firewall configuration, Stateful Firewall will cause all packets to be discarded.

**Example**

The following command enables Stateful Firewall support for this subscriber:

```
firewall policy firewall-required
```

The following command disables Stateful Firewall support for this subscriber:

```
no firewall policy
```

# gtp

Configures GTP-P related parameters for a subscriber.

---

**Product**

IPSG

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
[ default | no ] gtp { group | secondary-group } group_name [ accounting-context context_name ]
```

**default**

Resets the GTP group name to the default group.

**no**

Deletes the specified group name.

**group**

Specifies primary group parameters.

**secondary-group**

Specifies secondary group parameters.

***group\_name***

Specifies the name of the GTP-P group as an alphanumeric string of 1 through 63 characters.

**accounting-context *context\_name***

Specifies the GTP accounting context as an alphanumeric string of 1 through 79 characters. Default is the GGSN service context.

---

**Usage Guidelines**

Use this command to enable or disable the generation of eG-CDRs for CDMA traffic observed in the customer network during IPSG deployment.

**Example**

The following command establishes the primary GTP group *gtp22*:

```
gtp group gtp22
```

# idle-timeout-activity

Defines whether downlink (towards Mobile Node) data packets transmitted when the session is dormant are treated as activity for the idle-timer (inactivity timer).

By default, downlink data transmitted over a dormant session restarts the idle-timer for that session; it is treated as activity for the session.

---

## Product

PDSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **idle-timeout-activity dormant-downlink-data**

### **no**

Dormant mode downlink data is not treated as activity for the session idle-timer. The session idle timer is not reset.

### **idle-timeout-activity dormant-downlink-data**

Treats dormant mode downlink data as activity for the session idle-timer. The session idle timer is reset.

---

## Usage Guidelines

Use this command to disable or re-enable restarting the session idle timer when downlink data packets are transmitted to the Mobile Node when the session is in dormant mode.

### **Example**

Use the following command to disable restarting the session idle timer when downlink data packets are transmitted to the Mobile Node when the session is in dormant mode:

```
no idle-timeout-activity dormant-downlink-data
```

Use the following command to re-enable restarting the session idle timer when downlink data packets are transmitted to the Mobile Node when the session is in dormant mode:

```
idle-timeout-activity dormant-downlink-data
```

# ikev2 tsr

Configures the Traffic Selector responder (TSr) negotiation behavior during IKEv2 Security Association (SA) establishment.

---

**Product**

PDG/TTG

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
[ default ] ikev2 tsr { wildcard | user-specified }
```

**default**

Specifies the default behavior, which is wildcard TSr negotiation.

**ikev2 tsr**

Enables TSr negotiation.

**wildcard**

Specifies that during TSr negotiation, the PDG/TTG always returns an any-to-any IP address range, an any-to-any port range, and allows any protocol, irrespective of the traffic selector ranges received from the UE. This is the default behavior.

**user-specified**

Specifies that during TSr negotiation, the PDG/TTG responds to each UE request with the UE-specified IP address ranges. This enables split tunneling on the PDG/TTG, and enables the UE to tunnel only a specified traffic range to the PDG/TTG and send other traffic directly out the WLAN.

---

**Usage Guidelines**

Use this command to specify the TSr negotiation behavior on the PDG/TTG.

**Example**

The following command enables user-specified TSr negotiation on the PDG/TTG:

```
ikev2 tsr user-specified
```

# ims application-manager

Specifies the IP Multimedia Subsystem (IMS) application manager for the subscriber.

---

## Product

PDSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
[ no ] ims application-manager { domain-name domain-name | ipv4-address ipv4_address }
```

### no

Disables the IMS application manager for this subscriber.

### ims application-manager

Enables the IMS application manager for this subscriber.

### domain-name *domain-name*

Specifies the domain name of the application manager.

*domain-name* must be an alphanumeric string of 1 through 63 characters.

### ipv4-address *ipv4\_address*

Specifies the IP address of the application manager using IPv4 dotted-decimal notation.

---

## Usage Guidelines

The IMS application manager address is returned by HA to MN in DHCP Ack when it receives the DHCP inform from an AIMS subscriber.

### Example

The following commands specify IMS application managers by domain name and IPv4 address:

```
ims application-manager domain-name domain23
```

```
ims application-manager ipv4-address 192.168.23.1
```

# ims-auth-service

Enables IP Multimedia Subsystem (IMS) authorization support for subscriber. The specified IMSA service will be used for performing IMS authorization and flow-based charging procedures.

---

## Product

PDSN  
GGSN  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **default** | **no** ] **ims-auth-service** *auth\_svc\_name*

### default

Configures default setting.

Default: Disabled or as specified at the context or network access service level or in subscriber template.

### no

Removes the specified IMS authorization service from the subscriber configuration.

### ims-auth-service *auth\_svc\_name*

Specifies name of the IMS authorization service.

*auth\_svc\_name* must be an alphanumeric string of 1 through 63 characters preconfigured within the same context of this subscriber.

---

## Usage Guidelines

This feature provides the IMS authorization service configuration for Gx interface in IMS service node.

### Example

The following command applies a previously configured IMS authorization service named *ims\_interface1* to a subscriber within the specific context.

```
ims-auth-service ims_interface1
```

# inter-pdsn-handoff

Configure the system to force the MN to use its assigned IP address during Internet Protocol Control Protocol (IPCP) negotiations resulting from inter-PDSN handoffs.

**Product** PDSN

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description** [ **no** ] **inter-pdsn-handoff require ip-address**

**no**

Disables the rejecting of sessions when the MN uses a non-allocated IP address during IPCP re-negotiations.

**inter-pdsn-handoff require ip-address**

Rejects sessions when the MN uses a non-allocated IP address during IPCP re-negotiations.

**Usage Guidelines**

This command is used to configure the system to reject sessions that are re-negotiating IPCP after an inter-PDSN handoff if the IP address they propose does not match the one initially provided by the PDSN. The session would be rejected even if the proposed address was 0.0.0.0.

If this parameter is disabled, the PDSN will attempt to re-assign the IP address initially provided.

**Example**

To set the PDSN to not allow a mismatched IP address during a PDSN to PDSN handoff of a MIP call, use the following command:

```
inter-pdsn-handoff require ip-address
```

To set the PDSN so that it will not disconnect the session immediately, if the Mobile requests an IP address of 0.0.0.0 or a mismatched IP address after inter-pdsn handoff, use the following command:

```
no inter-pdsn-handoff require ip-address
```



# ip access-group

Configures IP access group for the current subscriber.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **ip access-group** *group\_name* [ **in** | **out** ]

### no

Indicates the access group specified is to be cleared from the subscribers configuration.

### **ip access-group** *group\_name*

Specifies the name of the IPv4/IPv6 access group. *acl\_group\_name* is a configured ACL group expressed as an alphanumeric string of 1 through 79 characters.

### **in** | **out**

Default: both (in and out)

Specifies the access-group as either inbound or outbound by the keywords **in** and **out**, respectively. If neither of these key words is specified, the command associates the *group\_name* access group with the current subscriber for both inbound and outbound access.

---

## Usage Guidelines

Set the subscriber access group to manage the access control for subscribers as a logical group.

### Example

The following command associates the *sampleGroup* access group with the current subscriber for both inbound and outbound access:

```
ip access-group sampleGroup
```

The following removes the outbound access group flag for *sampleGroup*:

```
no ip access-group sampleGroup out
```

# ip address

Configures a static IPv4 address for use by the subscriber.

---

## Product

PDSN  
GGSN  
HA  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **ip address** *ip\_address netmask*

### **no**

Removes a previously configured IP address assignment.

### **ip address** *ip\_address*

Specifies the IP address assigned to the subscriber using IPv4 dotted-decimal notation.

### **netmask**

The subnet mask that corresponds to the assigned IPv4 address.

---

## Usage Guidelines

Use this command to assign a static IPv4 address to the subscriber. This address will be used each time the subscriber establishes data sessions.

### **Example**

The following command configures a static IP address of *192.168.1.15* with a subnet mask of *255.255.255.0* to the subscriber:

```
ip address 192.168.1.15 255.255.255.0
```

# ip address pool

Configures IP address pool properties for the subscriber.

---

## Product

PDSN  
GGSN  
HA  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **ip address pool name** *pool\_name*

### **no**

Removes a previously configured static address.

### **ip address pool name** *pool\_name*

Specifies the IP address pool or IP address pool group from which the subscribers IP address is assigned.

*pool\_name* must be the name of an existing IP pool or IP pool group expressed as an alphanumeric string of 1 through 31 characters.

---

## Usage Guidelines

Use this command to specify the name of an IP address pool configured on the system from which IP addresses are to be dynamically assigned to sessions from this subscriber.

This command can be issued multiple times to specify multiple address pools for the subscriber. If multiple pools are specified, addresses are assigned for subscriber sessions from the pools based on the order in which the pools were configured.

If an address cannot be provided from the first-specified pool for whatever reason, the system attempts to assign an address from the second-specified pool, and so on. This operation is independent of the priorities configured for the pools. For example, if pool1 was specified for the subscriber first, and pool2 second, the system always attempts to assign addresses from pool1. If an address can not be assigned from pool1 (i.e. all addresses are in use), the system then attempts to assign an address from pool2.

## Example

The following command configures the subscriber to receive IP addresses from an IP address pool named *public1*:

```
ip address pool name public1
```

# ip address secondary-pool

Configures secondary IP address pool properties for the subscriber to provide multiple IP host configuration behind one WiMAX Customer Premise Equipment (CPE).

---

**Product**

ASN-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** ] **ip address secondary-pool name** *aux\_pool\_name*

**no**

Removes a previously configured auxiliary pool named *aux\_pool\_name* for multiple host support in ASN-GW service.

**ip address secondary-pool name *aux\_pool\_name***

Specifies the secondary/auxiliary IP address pool or IP address pool group from which the IP address is assigned to host behind a WiMAX CPE having primary IP address.

*pool\_name* must be the name of an existing IP pool or IP pool group expressed as an alphanumeric string of 1 through 31 characters.

---

**Usage Guidelines**

Use this command to specify the name of an IP address pool configured on the system from which IP addresses are to be dynamically assigned to host behind a WiMAX CPE for multiple host session support.

This command designates the IP address to secondary hosts from locally configured secondary IP address pool. To enable multiple host support behind a WiMAX CPE and configure maximum number of supported hosts use **secondary-ip-host** command in ASN Gateway Service Configuration mode.

**Example**

The following command configures the subscriber to receive IP addresses from a secondary IP address pool named *auxiliary1* for secondary hosts behind the WiMAX CPE:

```
ip address secondary-pool name auxiliary1
```

# ip allowed-dscp

Sets the Quality of Service (QoS) Differentiated Services (DiffServ) marking that a subscriber session is allowed. The DSCP is disabled by default.

**Product** All

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description** **ip allowed-dscp class** *class* **max-class** *maxclass* [ **rt-marking** *marking* ]  
**no ip allowed-dscp class**

**no**

Resets the parameters to the defaults: class none, max-class **be**. This indicates that all packets are let through without any dscp checking

## **ip allowed-dscp class** *class*

Specifies the Differentiated Services Codepoint (DSCP) class with which the subscriber session may mark its packets. If the subscriber sessions packets request a code point class higher than the code point class specified, the PDSN service re-marks the packets with the QOS-DSCP value specified by the **ip qos-dscp** command.

Default: none

*class* must be one of the following;

**a**: allow packets with AF DSCPs

**e**: allow packets with EF DSCP

**o**: allow packets for experimental or local use

**ae**: allow packets with AF and EF DSCPs

**ao**: allow packets with AF DSCPs or packets for experimental or local use

**eo**: allow packets with EF DSCPs or packets for experimental or local use

**aeo**: allow packets with AF or EF DSCPs or packets for experimental or local use

**none**: allow only the **be** and **sc1** through **sc7** code points

## **max-class** *maxclass*

This parameter specifies the maximum code point with which a subscriber session may mark its packets. The subscriber sessions packets must be marked with a code point equal to or less than the code point specified. If the subscriber sessions packets request a code point higher than the code point specified, the PDSN service

re-marks the packets with the QOS-DSCP value specified by the lower of the max-class and the **ip qos-dscp** command.

The list below identifies the code points from lowest to highest precedence. For example, if the **maxclass** is set to **af22**, that becomes the maximum code point that the subscriber session may mark its packets with and only **be**, **af13**, **af12**, **af11**, **af23**, and **af22** are allowed. If a subscriber session marks its packets with anything after **af22** in this list, the PDSN service re-marks the packets with the QOS-DSCP value specified by the lower of the maxclass and the **ip qos-dscp** command.

If class is set to none only the **be** and **sc1** through **sc7** codepoints are allowed. For example; if **class** is set to none and you set **max-class** to **sc1**, only the **sc1** and **be** codepoints are allowed.

Default: **be**

*maxclass* must be one of the following;

**be**: best effort forwarding

**af13**: assured Forwarding 13

**af12**: assured Forwarding 12

**af11**: assured Forwarding 11

**af23**: assured Forwarding 23

**af22**: assured Forwarding 22

**af21**: assured Forwarding 21

**af31**: assured Forwarding 31

**af32**: assured Forwarding 32

**af33**: assured Forwarding 33

**af41**: assured Forwarding 41

**af42**: assured Forwarding 42

**af43**: assured Forwarding 43

**ef**: expedited forwarding

**sc1**: selector class 1

**sc2**: selector class 2

**sc3**: selector class 3

**sc4**: selector class 4

**sc5**: selector class 5

**sc6**: selector class 6

**sc7**: selector class 7

### **rt-marking** *marking*

This parameter is used for Mobile IP (MIP) reverse tunnels. When MIP session packets do not have a DSCP marking, the Foreign Agent (FA) marks the packets with the value specified by **rt-marking** *marking*.

If MIP sessions packets have a DSCP marking, the marking is subjected to the conformance rules for the values of class and max-class; the final DSCP marking is then copied from the inner IP header to the outer IP header.

Default: **be**

*marking* must be one of the following;

**be**: best effort forwarding

**af11**: assured Forwarding 11

**af12**: assured Forwarding 12

**af13**: assured Forwarding 13

**af21**: assured Forwarding 21

**af22**: assured Forwarding 22

**af23**: assured Forwarding 23

**af31**: assured Forwarding 31

**af32**: assured Forwarding 32

**af33**: assured Forwarding 33

**af41**: assured Forwarding 41

**af42**: assured Forwarding 42

**af43**: assured Forwarding 43

**ef**: expedited forwarding

**sc1**: selector class 1

**sc2**: selector class 2

**sc3**: selector class 3

**sc4**: selector class 4

**sc5**: selector class 5

**sc6**: selector class 6

**sc7**: selector class 7

### Usage Guidelines

Use this command to configure Quality of Service (QoS) for a subscriber session to allow a Differentiated Services (DiffServ) Code Point (DSCP) marker in the header of each IP packet that prompts network routers to apply differentiated grades of service to various packet streams.

This command uses **class** and type of marker (**rt-marking** for reverse tunnels) for configuration with **max-class** maximum code point that a subscriber session may mark its packets with.

### Example

The following command will allow *o* packets for experimental or local use with best effort forwarding *be*:

```
ip allowed-dscp class o max-class be
```



## ip context-name

Configures the context to which the subscriber is assigned upon authentication. The assigned context is considered the destination context that provides the configuration options for the services the subscriber is allowed to access.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
[ no ] ip context-name name
```

**no**

Removes the current assigned context from the subscriber's data.

**ip context-name *name***Specifies the name of the context to assign the subscriber to once authenticated. *name* must be an alphanumeric string of 1 through 79 characters.

---

**Usage Guidelines**

Set the subscriber IP context to a common context when all subscribers from one or more contexts will use the same egress context.

**Example**The following command specifies the IP context name *egress2*:

```
ip context-name egress2
```

# ip header-compression

Configures the IP packet header compression options for the current subscriber. Although this command configures IP header compression algorithms, the Internet Protocol Control Protocol (IPCP) negotiations determine when the header compression algorithm is applied.

**Product** All

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description**

```
ip header-compression { rohc [ any [ mode { optimistic | reliable | unidirectional } ] | cid-mode { { large | small } [ marked-flows-only | max-cid | max-hdr value | mrru value ] } | marked flows-only | max-hdr value | mrru value | downlink | uplink ] | vj } +  

[ default | no ] ip header-compression
```

## default

Restores this command's default setting to the Van Jacobsen (VJ) header compression algorithm.

## no

Disables all IP header compression.

```
ip header-compression { rohc [ any [ mode { optimistic | reliable | unidirectional } ] | cid-mode { { large | small } [ marked-flows-only | max-cid | max-hdr value | mrru value ] } | marked flows-only | max-hdr value | mrru value | downlink | uplink ] | vj }
```

Specifies that the Robust Header Compression (ROHC) algorithms is used for data.



**Important** ROHC is only supported for use with the PDSN.

**any**: Apply ROHC header compression in both the uplink and downlink directions.

**mode** { **optimistic** | **reliable** | **unidirectional** }:

- **optimistic**: Sets the ROHC mode to Bidirectional Optimistic mode (O-mode). In this mode packets are sent in both directions. A feedback channel is used to send error recovery requests and (optionally) acknowledgments of significant context updates from decompressor to compressor. Periodic refreshes are not used in the Bidirectional Optimistic mode.
- **reliable**: Sets the ROHC mode to Bidirectional Reliable mode (R-mode). This mode applies an intensive usage of a feedback channel and a strict logic at both the compressor and the decompressor that prevents

loss of context synchronization between the compressor and the decompressor. Feedback is sent to acknowledge all context updates, including updates of the sequence number field.

- **unidirectional**: Sets the ROHC mode to Unidirectional mode (U-mode). With this mode packets are sent in one direction only, from the compressor to the decompressor. This mode therefore makes ROHC usable over links where a return path from the decompressor to the compressor is unavailable or undesirable.

**cid-mode** { { **large** | **small** } [ **marked-flows-only** | **dm** | **max-hdr** *value* | **mrru** *value* ] }: Specifies the ROHC packet type to be used.

- **large** | **small** [ **marked-flows-only** | **max-cid** | **max-hdr** *value* | **mrru** *value* ]: Defines the ROHC packet type as large or small and optionally sets the following parameters for the packet type selected:
- **marked-flows-only**: Specifies that ROHC is to be applied only to marked flows.
- **max-cid** *integer*: Default: 0 The highest context ID number to be used by the compressor. *integer* must be an integer from 0 through 15 when small packet size is selected and must be an integer from 0 through 31 when large packet size is selected.
- **max-hdr** *value*: Specifies the maximum header size to use. Default: 168. *value* must be an Integer from 0 through 65535.
- **mrru** *value*: Specifies the maximum reconstructed reception unit to use. Default: 65535. *value* must be an Integer from 0 through 65535.

**marked-flows-only**: Specifies that ROHC is to be applied only to marked flows.

**max-hdr** *value*: Specifies the maximum header size to use. Default: 168. *value* must be an Integer from 0 through 65535.

**mrru** *value*: Specifies the maximum reconstructed reception unit to use. Default: 65535. *value* must be an Integer from 0 through 65535.

**downlink**: Apply the ROHC algorithm only in the downlink direction.

**uplink**: Apply the ROHC algorithm only in the uplink direction.




---

**Important**

When ROHC is enabled for downlink or uplink only the operational mode is Unidirectional.

---

**vj**

Specifies that the VJ algorithm is used for header compression.

+

Either one or both of the keywords may be entered in a single command.

If both **vj** and **rohc** are specified, **vj** must be specified first.




---

**Important**

If both VJ and ROHC header compression are specified, the optimum header compression algorithm for the type of data being transferred is used for data in the downlink direction.

---

**Usage Guidelines**

Header compression can be used to provide a higher level of security in IP traffic enhance bandwidth usage and lower bit errors.

By default the header compression algorithm is set to **vj**.

**Example**

The following command disables all IP packet header compression:

```
no ip header-compression
```

The following command sets IP header compression to default vj algorithm:

```
default ip header-compression
```

The following command also sets the IP header compression to the vj algorithm:

```
ip header-compression vj
```

The following command enables the Internet Protocol Control Protocol (IPCP) to determine which protocol is the optimum algorithm for data in the downlink direction and use either VJ or ROHC as needed:

```
ip header-compression vj rohc
```

The following command enables ROHC for the downlink direction only:

```
ip header-compression rohc downlink
```

The following command enables ROHC in any direction using Bidirectional Optimistic mode:

```
ip header-compression rohc any mode Optimistic
```

# ip hide-service-address

Hides the IP address of the service from the subscriber.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** ] **ip hide-service-address**

**no**

Does not hide the IP address of the service from the subscriber. This is the default behavior.

**ip hide-service-address**

Hides the IP address of the service from the subscriber.

---

**Usage Guidelines**

Use this command to prevent subscribers from using traceroute to discover the network addresses that are in the public domain and configured on services. This prevent users from pinging such addresses.

**Example**

The following command hides the IP address of the service from the subscriber:

```
ip hide-service-address
```

# ip local-address

Configures the local-side IP address of the subscriber's point-to-point connection.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**ip local-address** *ip\_address*  
**no ip local-address**

**no**

Removes a previously configured IP local-address.

**ip\_address** *ip\_address*

Specifies an IP address configured in a destination context on the system through which a packet data network can be accessed. *ip\_address* is entered using IPv4 dotted-decimal notation.

---

**Usage Guidelines**

This parameter specifies the IPv4 address on the system that the MS uses as the remote-end of the PPP connection. If no local address is configured, the system uses an "unnumbered" scheme for local-side addresses.

**Example**

The following command configures a local address of 192.168.1.23 for the MS:

```
local-address 192.168.1.23
```

# ip multicast discard

Configures the IP multicast discard packet behavior.

---

**Product**

GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

[ **no** ] **ip multicast discard**

**no**

Does not discard IP multicast packets.

**ip multicast discard**

Discards IP multicast packets.

---

**Usage Guidelines**

This command specifies if IP multicast packets will be discarded.

**Example**

The following command discards IP multicast packets:

```
ip multicast discard
```

# ip qos-dscp

Configures quality of service (QoS) options for the current subscriber using the differentiated services code point (DSCP) method. This functionality is disabled by default.

**Product** All

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description** **ip qos-dscp** *option*  
**no ip qos-dscp**

**no**

Sets the quality of service option to its default value.

## **ip qos-dscp** *option*

Default: be (Best Effort)

Specifies the subscriber's per hop quality of service setting as one of:

- **af11**: assured Forwarding 11
- **af12**: assured Forwarding 12
- **af13**: assured Forwarding 13
- **af21**: assured Forwarding 21
- **af22**: assured Forwarding 22
- **af23**: assured Forwarding 23
- **af31**: assured Forwarding 31
- **af32**: assured Forwarding 32
- **af33**: assured Forwarding 33
- **af41**: assured Forwarding 41
- **af42**: assured Forwarding 42
- **af43**: assured Forwarding 43
- **be**: best effort forwarding
- **ef**: expedited forwarding



---

**Usage Guidelines**

Set the quality of service for a subscriber based upon the service level agreements.

**Example**

The following command specifies the QoS as expedited forwarding:

```
ip qos-dscp ef
```

# ip route

Configures the static route to use to reach the subscriber's network.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** ] **ip route** *ip\_address ip\_mask* [ *gateway\_address* ]

**no**

Removes the configured route information from the subscriber data.

**ip route *ip\_address***

Specifies the target IP address for which the route information applies using IPv4 dotted-decimal notation.

***ip\_mask***

Specifies the networking mask for the route.

1 bits in the *ip\_mask* indicate that bit position in the *ip\_address* must also have a value of 1.

0 bits in the *ip\_mask* indicate that bit position in the *ip\_address* does not need to match, such as the bit can be either a 0 or a 1.

For example, if the IP address and mask were specified as 172.168.10.0 and 255.255.255.224, respectively, the network mask will be 172.168.0.0 (obtained by logically ANDing the IP address with the IP mask).

***gateway\_address***

Default: assigned remote IP address will be used as the gateway address.

Specifies the IP address of the next hop gateway for the route using IPv4 dotted-decimal notation.

---

**Usage Guidelines**

The static routes are also known as framed IP routes for subscribers. Static routes are typically applicable for subscribers connecting via other networks or when the mobile device acts as a gateway to a network on the far side of the device.

For example, if the mobile device is assigned IP address 10.2.3.4 and it acts as a gateway for the network 10.2.3.0 (with a network mask of 255.255.255.0) a static route would be configured with the *ip\_address* being 10.2.3.0, *ip\_mask* being 255.255.255.0, and *gateway\_address* being 10.2.3.4.

**Example**

The following command disables the static route at IP address *10.2.3.4 255.255.255.0*.

```
no ip route 10.2.3.4 255.255.255.0
```

# ip source-validation

Enables or disables packet source validation for the current subscriber. Source validation requires that the source address of the received packets match the IP address assigned to the subscriber (either statically or dynamically) during the session.

If an incorrect source address is received from the mobile node, the system attempts to renegotiate the PPP session. The parameters for IP source validation can be set by the **ip source-violation** command.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **ip source-validation**

### **no**

Disables source validation.

### **ip source-validation**

Enables source validation.

---

## Usage Guidelines

Source validation is useful if packet spoofing is suspected or for verifying packet routing and labeling within the network.

### **Example**

The following command enables IP source validation:

```
ip source-validation
```

The following command disables IP source validation:

```
no ip source-validation
```

# ip user-datagram-tos copy

Controls copying of the IP TOS octet value from IPv4/IPv6 datagrams to the IP header in tunnel encapsulation. This is disabled by default.

---

**Product**

PDSN  
HA

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**ip user-datagram-tos copy** [ **access-link-tunnel** | **both** | **data-tunnel** ]  
**no ip user-datagram-tos copy**

**no**

Disable copying of the IP TOS octet value to all tunnel encapsulation IP headers.

**ip user-datagram-tos copy**

Enables copying of the IP TOS octet value to all tunnel encapsulation IP headers.

**access-link-tunnel**

Copies the IP TOS octet value to the tunnel encapsulation IP header on the access side (RP) tunnel.

**both**

Uses both the access-link-tunnel and data-tunnel.

**data-tunnel**

Copies the IP TOS octet value to the tunnel encapsulation IP header on the MIP data tunnel or L3 tunnel (IP-in-IP, GRE).

---

**Usage Guidelines**

Use this command to enable the copying of the IP TOS octet value to the tunnel encapsulation IP header. This functionality allows PCF to detect special TOS marking in the outer IP header of A11 packets and to identify certain packets as QChat control messages. The Base Station Controller/Packet Control Function (BSC/PCF) must give higher priority to QChat control messages.

**Example**

The following command enables copying of the IP TOS octet value to the tunnel encapsulation IP header for the access side tunnel:

```
ip user-datagram-tos copy access-link-tunnel
```

The following command disables copying of the IP TOS octet value to all tunnel encapsulation IP headers:

```
no ip user-datagram-tos copy
```

# ip vlan

Configures subscriber-to-Virtual LAN (VLAN) associations.

---

**Product**

PDSN

HA

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

**ip vlan** *vlan-id*

[ **default** | **no** ] **ip vlan**

**default**

Resets the VLAN ID to the default setting.

**no**

Disables the VLAN ID for the subscriber.

**ip vlan *vlan-id***

Specifies the VLAN ID that is associated with the IP address for that session. *vlan-id* is an integer from 1 through 4094.

---

**Usage Guidelines**

This command configures the subscriber vlan ID which is used with the assigned address for the subscriber session to receive packets. If the IP pool from which the address is assigned is configured with a VLAN ID, this subscriber configured VLAN ID overrides it.

Subscriber traffic can be routed to specific VLANs based on the configuration of their user profile. Using this functionality provides a mechanism for routing all traffic from a subscriber over the specified VLAN. All packets destined for the subscriber must also be sent using only IP addresses valid on the VLAN or they will be dropped.

**Example**

Set the vlan ID to the default setting by entering the following command:

```
default ip vlan
```

# ipv6 access-group

Configures the IPv6 access group for a subscriber.

---

**Product**

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
Entering the above command sequence results in the following prompt:  
*[context\_name]*host\_name(config-subscriber)#

---

**Syntax Description**

**ipv6 access-group** *name* [ **in** | **out** ]

**ipv6 access-group** *name*

Defines the access group name. *name* is an alphanumeric string of 1 through 47 characters.

**in**

Defines the access group as inbound.

**out**

Defines the access group as outbound.

---

**Usage Guidelines**

Used to create an access group for a subscriber.

**Example**

The following command provides an example of an IPv6 access group with the name *list\_1*:

```
ipv6 access-group list_1
```



# ipv6 address

Configures a static IP address for use by the subscriber.

---

## Product

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber)#

---

## Syntax Description

[ **no** ] **ipv6 address** { **prefix** *address* | **prefix-pool** *name* }

### **no**

Deletes a previously configured ipv6 address.

### **ipv6 address address**

Specifies an IPv6 address. *address* is entered using IPv6 colon-separated-hexadecimal notation.

### **prefix**

Specifies a static IPv6 address.

### **prefix-pool name**

Specifies an IPv6 prefix pool name. *name* is an alphanumeric string of 1 through 31 characters.

---

## Usage Guidelines

Use this command to assign a static IPv6 address to the subscriber. This address will be used each time the subscriber establishes data sessions.

### **Example**

The following command configures a static IP address of *2001:4A2B::1f3F* with a mask length of *24* to the subscriber:

```
ipv6 address 2001:4A2B::1f3F/24
```

# ipv6 dns

Configures the IPv6 Domain Name Service (DNS) servers.

---

## Product

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
[ no ] ipv6 dns { primary | secondary } { ipv6_dns_address }
```

### no

Deletes a previously configured DNS server.

### **ipv6 dns *ipv6\_dns\_address***

Specifies an IP address for the DNS server. *ipv6\_dns\_address* is entered using IPv6 colon-separated-hexadecimal notation.

### **primary**

Configures the primary DNS server for the subscriber.

### **secondary**

Configures the secondary DNS server for the subscriber. Only one secondary DNS server can be configured.

### ***ipv6\_dns\_address***

Configures the IP address of the DNS server.

---

## Usage Guidelines

DNS servers are configured on a per subscriber basis. This allows each subscriber to use specific servers.

## Example

The following command provides an example of setting the primary IPv6 DNS server:

```
ipv6 dns primary fe80::c0a8:a04
```

# ipv6 dns-proxy

Configures the system to act as a domain name server proxy for the current subscriber.

---

**Product**

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
Entering the above command sequence results in the following prompt:  
`[context_name]host_name(config-subscriber)#`

---

**Syntax Description**

[ **default** | **no** ] **ipv6 dns-proxy**

**default**

Disables IPv6 DNS proxy functionality for a subscriber.

**no**

Removes the pre-enabled functionality of IPv6 DNS proxy for a subscriber.

**ipv6 dns-proxy**

Enables IPv6 DNS proxy functionality for a subscriber. If enabled, the system will act as a proxy DNS server.  
Default: disabled.

---

**Usage Guidelines**

Used to enable or disable IPv6 DNS proxy for the subscriber. When enabled, the PDSN acts as a proxy DNS server for DNS IPv6 queries coming from the mobile station to the PDSN's local PPP link address.

**Example**

The following command disables the IPv6 DNS proxy function for the subscriber:

```
no ipv6 dns-proxy
```

# ipv6 egress-address-filtering

Configures the system to perform egress address filtering for the subscriber.

---

## Product

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber)#

---

## Syntax Description

[ **no** ] **ipv6 egress-address-filtering**

### **no**

Disables IPv6 egress address filtering.

### **ipv6 egress-address-filtering**

Enables IPv6 egress address filtering.

---

## Usage Guidelines

Used to enable the filtering of packets that arrive from the Internet to a particular site.

### **Example**

The following command disables egress address filtering:

```
no ipv6 egress-address-filtering
```

# ipv6 initial-router-adv

Creates an IPv6 initial router advertisement interval for the subscriber.

## Product

PDSN  
GGSN  
ASN-GW  
HSGW  
P-GW  
SAEGW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

```
ipv6 initial-router-adv { interval value | num-advts value |
router-solicit-wait-timeout value }
default ipv6 initial-router-adv { interval | num-advts |
router-solicit-wait-timeout }
no ipv6 initial-router-adv router-solicit-wait-timeout
```

### default

Resets the command to its default settings.

### no ipv6 initial-router-adv router-solicit-wait-timeout

Disables running timer to wait for router solicit and sends the initial router advertisement immediately once session is up.

### ipv6 initial-router-adv

Enables an initial router advertisement interval in milliseconds.

### interval *value*

Default: 3000

The time interval the initial IPv6 router advertisement is sent to the mobile node in milliseconds.

*value* is an integer between 100 and 16000 milliseconds.

### num-advts *value value*

Default: 3

The number of initial IPv6 router advertisements sent to the mobile node. *value* is an integer between 1 to 16.

**router-solicit-wait-timeout *value***

Default: 3000

The time interval to wait for router solicit before sending the initial IPv6 router advertisement.

*value* is an integer between 1 and 30000 milliseconds.

---

**Usage Guidelines**

This command is used to set the advertisement interval and the number of advertisements. Using a smaller advertisement interval increases the likelihood of router being discovered more quickly when it first becomes available.

If timer is enabled and router solicit is received before timeout, then RA will be sent in response to RS and no further RA will be sent. If timer is enabled and no router solicit is received after timeout, initial RAs will be sent as configured and IPv6 capability indication will be sent in S2a to P-GW to indicate that P-GW should drop any IPv6 traffic for this PDN.

**Example**

The following command specifies the initial ipv6 router interval to be 2000ms:

```
ipv6 initial-router-adv interval 2000
```

# ipv6 interface-id

Provides an IPv6 interface identifier for the subscriber.

---

**Product**

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
Entering the above command sequence results in the following prompt:  
*[context\_name]host\_name(config-subscriber)#*

---

**Syntax Description**

**ipv6 interface-id** *ifid*  
**[ default | no ] ipv6 interface-id**

**default**

No interface ID set for IPv6CP negotiation to subscriber.

**no**

Deletes a previously configured IPv6 interface ID.

**interface-id** *ifid*

Specifies the interface ID assigned to the Mobile during IPv6 Control Protocol (IPv6CP) negotiation. *ifid* is a 64-bit unsigned integer.

---

**Usage Guidelines**

Used to provide a IPv6 ifid for the subscriber when using IPv6-to-IPv4 (6to4) routing.

**Example**

The following command provides an example of assigning an IPv6 interface ID of *00-00-00-05-47-00-37-44* to the subscriber:

```
ipv6 interface-id 00-00-00-05-47-00-37-44
```

# ipv6 minimum-link-mtu

Configures the IPv6 minimum link maximum transmission unit (MTU) value.

---

## Product

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber)#

---

## Syntax Description

**ipv6 minimum-link-mtu** *value*  
**default ipv6 minimum-link-mtu**

### default

Resets minimum link MTU to its default setting: 1280.

### ipv6 minimum-link-mtu *value*

Specifies the MTU (in bytes) as a minimum link value. *value* is an integer between 100 and 2000.

---

## Usage Guidelines

Used to override the IPv6 minimum link MTU values recommended by the standard.

### Example

The following command provides an example of assigning an IPv6 minimum link MTU to *1580* to the subscriber:

```
ipv6 minimum-link-mtu 1580
```



# ipv6 secondary-address

Configures additional IPv6 4-bit prefixes to the subscriber session.

---

## Product

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **ipv6 secondary-address** { **prefix** *ipv6\_address\_prefix* | **prefix-pool** *pool\_name* }

### **no**

Deletes a previously configured ipv6 secondary address.

### **ipv6 secondary-address** *ipv6\_address\_pref*

Specifies the secondary IPv6 address using IPv6 colon-separated-hexadecimal notation.

### *pool\_name*

Specifies the name given to the secondary address prefix pool as an alphanumeric string of 1 through 31 characters.

---

## Usage Guidelines

An IPv6 prefix pool name may be configured for a dynamic prefix, while the prefix is static. This command may be executed multiple times to configure multiple prefixes.

### **Example**

The following command assigns an IPv6 secondary address prefix-pool name of *eastcoast* to the subscriber:

```
ipv6 secondary-address prefix-pool eastcoast
```

## l2tp send accounting-correlation-info

Enables the sending of accounting correlation information (Correlation-Id, NAS-IP-Address and NAS-ID) by the L 2TP Access Concentrator (LAC) in L2TP control messages (ICRQ) during session setup to an L2TP Network Server (LNS).

---

**Product**

PDSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** | **default** ] **l2tp send accounting-correlation-info**

**no**

Disables the sending of accounting correlation information by the LAC.

**default**

Sets the setting to default mode: disable.

**l2tp send accounting-correlation-info**

Enables the sending of accounting correlation information by the LAC.

---

**Usage Guidelines**

Use this command to enable the LAC to send accounting correlation information (Correlation-Id, NAS-IP-Address and NAS-ID) in L2TP control message (ICRQ) during session setup to LNS for this subscriber. LNS can be configured to include this information in ACS billing records, so that billing servers can easily correlate accounting records from PDSN/LAC and LNS.

By default, this mode is disabled.

**Example**

The following command disables the inclusion of accounting correlation information in control messages during session setup to an LNS for a subscriber:

```
default l2tp send accounting-correlation-info
```

# l3-to-l2-tunnel address-policy

Configures the subscriber address allocation/validation policy, when subscriber Layer 3 (IPv4) sessions are tunneled using Layer 2 tunneling protocol (L2TP).

---

## Product

HA  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**l3-to-l2-tunnel address-policy** { **alloc-only** | **alloc-validate** | **no-alloc-validate** }

**default** **l3-to-l2-tunnel address-policy**

### default

Restores the default value for Layer 3-to-Layer 2 tunnel addressing: **no-alloc-validate**.

### l3-to-l2-tunnel address-policy

Sets the policy for Layer 3-to-Layer 2 sessions to one of the following options.

### alloc-only

Only allocates an address in the case of dynamic address assignment. Does not validate static addresses.

### alloc-validate

Locally allocates and validates the subscriber addresses.

### no-alloc-validate

Does not allocate or validate subscriber addresses locally for current subscribers sessions. Passes the address between the remote tunnel terminator and the Mobile Node. This is the default behavior.

---

## Usage Guidelines

Use this command to configure the L3 to L2 tunnel address policy for MIP HA sessions tunneled from the system using L2TP tunnels or for GGSN IP Context sessions tunneled using L2TP to a remote LNS. Also refer to the **resource** keyword of the Context Configuration mode **ip pool** command.

### Example

the following command sets the L3-to-L2 tunnel address policy so that the current subscriber must have IP addresses allocated and validated locally on the system:

```
13-to-12-tunnel address-policy alloc-validate
```

# loadbalance-tunnel-peers

Configures the load balancing of traffic bound for L2TP tunnels configured on the system for the selected subscriber.

**Product** L2TP

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description** **loadbalance-tunnel-peers** { **balanced** | **prioritized** | **random** }

## **loadbalance-tunnel-peers**

Enables load balancing of L2TP traffic using one of the methods described below.

### **balanced**

Enables the equal use of all configured tunnel peers (LNSs) for the selected subscriber.

### **prioritized**

Enables the use of all configured tunnel peers (LNSs) for the selected subscriber based on the preference number assigned to the peer address.

### **random**

Default: Enabled

Enables the random use of all configured tunnel peers (LNSs) for the selected subscriber.

## **Usage Guidelines**

Use to manage traffic loads on L2TP Access Concentrator (LAC) ports and their respective L2TP Network Servers (LNSs).

## **Example**

Use the following command to randomly use all configured tunnel peers (LNSs):

```
loadbalance-tunnel peers random
```

# long-duration-action

Specifies what action is taken when the long duration timer expires.

---

**Product**

All

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**long-duration-action** { **detection** | **disconnection** [ **dormant-only** ] [ **suppress-notification** ] }

**detection**

Default: Enabled

Detects long duration sessions and sends SNMP TRAP and CORBA notification. This is the default behavior.

Use this command to detect a session exceeding the limit set by the long duration timer.

**disconnection** [ **dormant-only** ] [ **suppress-notification** ]

Default: Disabled

Detects a long duration session and disconnects the session after sending SNMP trap and CORBA notification.

**suppress-notification**: Suppresses the SNMP trap and CORBA notification after detecting and disconnecting a long duration session. Default: Disabled

**dormant only**: Disconnects the dormant sessions after long duration timer and inactivity time with idle time-out duration expires. If the long duration timeout is fired and the call is not dormant, the call is disconnected when the call later moves to dormancy.




---

**Important**

For HA calls, the inactivity-time is considered as gauge for dormancy.

---

It sends the SNMP trap and CORBA notification after disconnecting a long duration session. Default: Disabled

---

**Usage Guidelines**

Use this command to determine what action is taken when a session exceeds the limit set by the long duration timer.

**Example**

Use the following command to enable disconnecting sessions that exceed the long duration timer:

```
long-duration-action disconnection
```

Use the following command to disconnect the session that exceed the long duration timer without sending SNMP trap and CORBA notification:

```
long-duration-action disconnection suppress-notification
```

Use the following command to disconnect the session that is in dormant and exceed the long duration timer and send SNMP trap and CORBA notification:

```
long-duration-action disconnection dormant-only
```

Note that in case of HA calls, the inactivity-time is considered as gauge for dormancy.

# max-pdn-connections

Specifies the maximum number of connections to packet data networks (PDNs) supported per eHRPD session.

---

## Product

HSGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**max-pdn-connections** *eHRPD\_PDNs*

**default** **max-pdn-connections**

### default

Resets the maximum number of PDN connections supported per eHRPD session to 3.

### max-pdn-connections *eHRPD\_PDNs*

Specifies the maximum number of PDN conceitedness allowed per eHRPD session. *eHRPD\_PDNs* must be an integer from 1 to 14. Default is 3.

---

## Usage Guidelines

This command is used to specify the maximum number of PDN connections supported per eHRPD session.

### Example

The following command specifies a maximum of 5 PDNs per eHRPD session:

```
max-pdn-connections 5
```



# mediation-device

Enables the use of a mediation device for subscribers, and specifies the system context to use for communicating with the device. A mediation device can be the initial point of contact for all IT systems that need to receive Charging Data Records (CDRs). Mediation devices can also be deep-packet inspection servers or transaction control servers.

---

## Product

GGSN  
P-GW  
PDG/TTG  
SAEGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**mediation-device context-name** <*context-name*> [ **no interims** ]

[ **no** | **default** ] **mediation-device**

### **no**

Deletes the mediation-device configuration.

### **default**

Changes the mediation device to no context-name configured and restores the mediation device's default properties.

### **mediation-device context-name** *context-name*

Default: The subscriber's destination context.

Configures the mediation VPN context for the subscriber.

*context-name* must be an alphanumeric string of 1 through 79 characters that is case sensitive. If not specified, the mediation context is same as the destination context of the subscriber.

### **no-interims**

Disables sending of Interim messages to the mediation device.

Default: Disabled

---

## Usage Guidelines

This command is used to enable mediation device support for subscribers.

Keywords to this command can be used in combination to each other, depending on configuration requirements.

**Example**

The following command enables mediation device support for the subscriber and uses the protocol configuration located in an system context called *ggsnl*:

```
mediation-device context-name ggsnl
```

# mobile-ip

Enables or disables access to mobile IP services by the subscriber.

---

## Product

HA  
FA

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
[ no ] mobile-ip { allow-aaa-address-assignment | dns-address
source-priority { aaa | home-agent } | gratuitous-arp aggressive |
home-agent ip_address [alternate] | match-aaa-assigned-address |
min-reg-lifetime-override [value | infinit ] | mn-aaa-removal-indication
| mn-ha-hash-algorithm { hmac-md5 | md5 | rfc2002-md5 } | mn-ha-shared-key
key | mn-ha-spi spi_num | reverse-tunnel | security-level { ipsec | none
} | send {access-technology | accounting-correlation-info bsid |
dns-address | host-config | imsi | terminal-verification } }
```

### no

Disables the mobile IP option specified.

### allow-aaa-address-assignment

Default: Disabled.

Enables the FA to accept a home address assigned by an AAA server. This should only be configured on the FA side.

### dns-address source-priority { aaa | home-agent }

Sets the priority behavior on the FA to use either the DNS IP address information from the HA or the AAA server to include in the RRP to the MN.

When the **no** keyword is used in conjunction with the **dns-address** keyword, information received from both the home-agent and the AAA server is sent if available.

DNS IP address information from the HA comes from the DNS Normal Vendor/Organization Specific Extension (NVSE) in the Registry Registrar Protocol (RRP).

DNS IP address information from the AAA server is in the access accept message.

**home-agent:** If the DNS address is received from the home-agent only that information is sent to the MN. Otherwise the DNS address received from the AAA server is sent.

**aaa:** If the DNS address is received from the AAA server only that information is sent to MN. Otherwise the DNS address received from the home-agent is sent.

**gratuitous-arp aggressive**

Default: Disabled.

When enabled, this mode will cause the HA to send out gratuitous ARP (Address Resolution Protocol) messages for all Mobile IP (MIP) registration renewals and handoffs.

To disable this mode, use the **no** form of this command.

**Important**


---

This mode will only work for IP addresses that have been assigned from a static IP address pool.

---

**home-agent *ip\_address* [alternate]**

Specifies the IP address of the mobile IP user's home agent. *ip\_address* must be entered using IPv4 dotted-decimal or IPv6 colon -separated notation.

**alternate** - Specifies the secondary, or alternate, Home Agent to use when Proxy Mobile IP HA Failover is enabled.

**match-aaa-assigned-address**

Default: Disabled.

Enables the FA to validate the home address in the RRQ against the one assigned by AAA server. This should only be configured on the FA side.

**min-reg-lifetime-override [*value* | *infinite* ]**

Default: 0.

Configures the subscriber for minimum registration lifetime parameter on HA service. By default it uses the value configured on HA service where *value* must be the minimum registration lifetime that the HA service allows in any Registration Request message from the mobile node. An infinite registration lifetime can be configured by setting the value as "infinite".

*value* is a minimum registration lifetime value in seconds and must be an integer between 1 through 65534.

**mn-aaa-removal-indication**

Default: Disabled.

When enabled, the MN-FA challenge and MN-AAA Authentication extensions are removed when relaying a Registration Request (RRQ) to the Home Agent (HA)

**mn-ha-hash-algorithm { *hmac-md5* | *md5* | *rfc2002-md5* }**

Specifies the encryption algorithm to use.

Default: **hmac-md5**

**hmac-md5**: Uses HMAC-MD5 hash algorithm, as defined in RFC-2002bis. This is the default algorithm.

**md5**: Uses the MD-5 hash algorithm.

**rfc2002-md5**: Uses the MD-5 hash algorithm variant as defined in RFC-2002.

**mn-ha-shared-key *key***

Verifies the MN-HA Authentication for a local subscriber in the current context. *key* is an alphanumeric string or a hexadecimal number beginning with "0x" up to 127 bytes

**mn-ha-spi *spi\_num***

Specifies the Security Parameter Index (SPI) number. *spi\_num* must be an integer from 256 through 4294967295.

**reverse-tunnel**

Default: enabled.

All the mobile IP user to use reverse IP tunnels. The **no** keyword disables this option.

**security-level { ipsec | none }**

Default: none

Configures the security level needed for the subscriber's traffic.

**ipsec**: secures both MIP control and data traffic with IPsec.

**none**: none of the traffic is secured

**Important**

This keyword corresponds to the 3GPP2-Security-Level RADIUS attribute. This attribute indicates the type of security that the home network mandates on the visited network.

**Important**

For this attribute, the integer value "3" enables IPsec for tunnels and registration messages, "4" Disables IPsec

**send {access-technology | accounting-correlation-info *bsid* | dns-address | host-config | imsi | terminal-verification }**

**access-technology**: Configures FA to send the access-technology type extension in the RRQ, by default it is disabled.

**accounting-correlation-info**: Configures whether the FA sends the correlation info to the NVSE in the RRQ. Default is disabled.

**dns-address**: Enables the HA to send the DNS address NVSE in the RRP. Default is disabled. This should only be enabled on the HA side.

**host-config**: Configures by sending the Host Config NVSE in RRQ. By default it is disabled.

**imsi**: Configures sending the IMSI NVSE in the RRQ. Default is sending IMSI in custom-1 format.

**terminal-verification**: Enables the FA to send the terminal verification NVSE in the RRQ. Default is disabled. This should only be enabled on the FA side.



---

**Important**

**send dns-address** is a proprietary feature developed for a specific purpose and requires the MN to be able to renegotiate IPCP for DNS addresses and reregister MIP if necessary. Since this feature needs the MN to support certain PPP/MIP behavior, and not all MNs support that particular behavior, **send dns-address** should be enabled only after careful consideration.

---

---

**Usage Guidelines**

Use as subscriber service contracts change.

**Example**

The following command specifies the Home Agent at *10.2.3.4* for this subscriber:

```
mobile-ip home-agent 10.2.3.4
```

# mobile-ip ha

Accommodates two Mobile IP (MIP) Home Agent (HA) options in subscriber mode.

---

## Product

PDSN  
HA  
ASN-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber) #

---

## Syntax Description

```
[ no ] mobile-ip ha { assignment-table name | ignore-unknown-ha-addr-error }
}
```

### no

Disables the mobile IP HA option specified.

### assignment-table *name*

Specifies the name of an existing MIP HA Assignment table. *name* must be an alphanumeric string of 1 through 63 characters.

### ignore-unknown-ha-addr-error

Default is disabled.

Enables or disables the HA to accept or reject the RRQ from a particular subscriber.

---

## Usage Guidelines

Use this command to assign a MIP HA Assignment table to the current subscriber.

Use this command to disable or enable the HA to accept or reject the RRQ from a particular subscriber when the HA address in the incoming MIP RRQ is not the same as the HA service address. The feature is off by default which causes the RRQ to be rejected with the error code UNKNOWN\_HOME\_AGENT.

## Example

The following command assigns the MIP HA Assignment table named *Atable1* to the current subscriber:

```
mobile-ip ha assignment-table Atable1
```

The following command sets **ignore-unknown-ha-addr-error** to its default disabled state:

```
no mobile-ip ha ignore-unknown-ha-addr-error
```

# mobile-ip reg-lifetime-override

Overrides the Mobile IP (MIP) registration lifetime from HA with value configured for subscriber.

---

## Product

PDSN  
HA  
ASN-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber)#

---

## Syntax Description

**mobile-ip reg-lifetime-override** [ *dur* | **infinite** ]  
 [ **default** | **no** ] **mobile-ip reg-lifetime-override**

### **mobile-ip reg-lifetime-override** *dur*

Default: 100 seconds.

Overrides the MIP registration lifetime from HA for the specified period of time in seconds. *dur* must be an integer from 1 through 65534.

### **infinite**

Sets the MIP registration lifetime override value to infinite for a particular subscriber.

### **default**

Sets the value of mobile IP registration lifetime override option to 100 seconds.

### **no**

Disables the MIP registration lifetime override option.

---

## Usage Guidelines

Use this command to configure MIP registration-lifetime per realm/domain. This value overrides the default lifetime configured under HA service.

### **Example**

The following command overrides the MIP registration lifetime value from HA service and defaults the MIP registration lifetime to 100 seconds for the current subscriber:

```
default mobile-ip reg-lifetime-override
```



# mobile-ip send access-technology

Enables the sending of the RAT (Radio Access Technology) of the MS to the HA in a PMIP RRQ (Proxy MIP Register Request) message.

---

**Product**

PDIF  
PDSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **default** | **no** ] **mobile-ip send access-technology**

**default**

Disables the support for sending the RAT to the HA in a PMIP RRQ.

This is the default mode.

**no**

Removes the configured support for sending the RAT to the HA in a PMIP RRQ.

---

**Usage Guidelines**

Use this command to send the RAT to the HA in a PMIP RRQ.

**Example**

The following command enables sending the RAT to the HA in a PMIP RRQ:

```
mobile-ip send access-technology
```

# mobile-ip send accounting-correlation-info

Enables the sending call correlation information Normal Vendor/Organization Specific Extensions (NVSEs) to the HA in the MIP Registry Registrar Protocol (RRP).

---

## Product

PDSN  
HA

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **default** | **no** ] **mobile-ip send accounting-correlation-info**

### **default**

Disables the support for sending call correlation information NVSEs to the HA in MIP RRQ.

This is the default mode.

### **no**

Removes the configured support for sending call correlation information.

---

## Usage Guidelines

Use this command to support PDSN-Correlation-ID VSE and send the call correlation information.

### **Example**

The following command enables sending call correlation information NVSEs to the HA in MIP RRQ:

```
mobile-ip send accounting-correlation-info
```

# mobile-ip send bsid

Enables the sending of the BSID (Base Station Identifier) of the WiFi access point/Radio Access Network (RAN) to the HA in a PMIP RRQ (Register Request) message.

---

**Product**

PDIF  
PDSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**mobile-ip send bsid** [ **custom-2** ]  
[ **default** | **no** ] **mobile-ip send bsid**

**default**

Disables the support for sending the BSID to the HA in a PMIP RRQ.

This is the default mode.

**no**

Removes the configured support for sending the BSID to the HA in a PMIP RRQ.

**custom-2**

NVSE to send service option attribute in the PMIP RRQ.



---

**Important**

This is a customer-specific keyword and needs customer-specific license to use this feature.

---

---

**Usage Guidelines**

Use this command to send the BSID to the HA in a PMIP RRQ.

**Example**

The following command enables sending the BSID to the HA in a PMIP RRQ:

```
mobile-ip send bsid
```

# mobile-ip send pcf-address

Configures whether the FA sends the PCF address NVSE in the RRQ.

## Product



### Important

This command is customer specific. For more information contact your Cisco account representative.

HA

PDSN

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

**mobile-ip send pcf-address** [ **custom-2** ]

[ **default** | **no** ] **mobile-ip send pcf-address**

### default

Disables the support for sending the PCF address to the HA in a PMIP RRQ.

This is the default mode.

### no

Removes the configured support for sending the PCF address to the HA in a PMIP RRQ.

### custom-2

NVSE to send PCF address attribute in the PMIP RRQ.

## Usage Guidelines

Use this command to send the PCF address to the HA in a PMIP RRQ.

### Example

The following command enables sending the PCF address to the HA in a PMIP RRQ:

```
mobile-ip send pcf-address
```

# mobile-ip send service-option

Configures whether the FA sends the service option NVSE in the PMIP RRQ.

---

## Product



---

### Important

This command is customer specific. For more information contact your Cisco account representative.

---

HA

PDSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

## Syntax Description

**mobile-ip send service-option [ custom-2 ]**

**[ default | no ] mobile-ip send service-option**

### default

Disables the support for sending the service option to the HA in a PMIP RRQ.

This is the default mode.

### no

Removes the configured support for sending the service option to the HA in a PMIP RRQ.

### custom-2

NVSE to send service option attribute in the PMIP RRQ.

---

## Usage Guidelines

Use this command to send the service option to the HA in a PMIP RRQ.

### Example

The following command enables sending the service option to the HA in a PMIP RRQ:

```
mobile-ip send service-option
```

# mobile-ip send subnet-id

Configures whether the FA sends the subnet-id NVSE in the PMIP RRQ.

---

## Product



### Important

This command is customer specific. For more information contact your Cisco account representative.

---

HA

PDSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
mobile-ip send subnet-id [ custom-2 ]  
[ default | no ] mobile-ip send subnet-id
```

### default

Disables the support for sending the subnet-id to the HA in a PMIP RRQ.

This is the default mode.

### no

Removes the configured support for sending the subnet-id to the HA in a PMIP RRQ.

### custom-2

NVSE to send subnet-id attribute in the PMIP RRQ.

---

## Usage Guidelines

Use this command to send the subnet-id to the HA in a PMIP RRQ.

### Example

The following command enables sending the subnet-id to the HA in a PMIP RRQ:

```
mobile-ip send subnet-id
```

# mobile-ipv6

Configures Mobile IPv6 related parameters for a subscriber.

---

**Product**

PDSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
[ default | no ] mobile-ipv6 { home-address ipv6_address | home-agent ipv6_address | home-link-prefix ipv6_address | tunnel mtu value }
```

**default**

Disables the support for sending call correlation information NVSEs to the HA in MIP RRQ.

This is the default mode.

**no**

Removes the configured support for sending call correlation information.

**home-address *ipv6\_address***

Specifies the home address for the subscriber. *ipv6\_address* must be entered using IPv6 colon-separated-hexadecimal notation.

**home-agent *ipv6\_address***

Specifies the IPv6 address of the mobile IP user's home agent. *ipv6\_address* must be entered using IPv6 colon-separated-hexadecimal notation.

**home-link-prefix *ipv6\_address***

Specifies the IPv6 address of the mobile IP user's home link. *ipv6\_address* must be entered using IPv6 colon-separated-hexadecimal notation.

**tunnel mtu *value***

Configures the tunnel MTU (in bytes) for the IPv6 tunnel between the HA and the mobile node. *value* must be an integer from 1024 through 2000. The default is 1500.

---

**Usage Guidelines**

This command sets the mobile-ipv6 parameters for a subscriber. Use this command to set the home-address, home-agent, and home-link prefix

**Example**

Use the following command to set the tunnel MTU value to *1800*:

```
mobile-ipv6 tunnel mtu 1800
```



# nai-construction-domain

After authentication, the domain name specified by this command replaces the Network Access Identifier (NAI) constructed for the subscriber.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description** **nai-construction-domain** *domain\_name*

**no nai-construction-domain**

**nai-construction-domain** *domain\_name*

Defines the domain name to use to replace the NAI constructed domain name. *domain\_name* must be an alphanumeric string of 1 through 79 characters.

**no**

Deletes the defined domain name.

---

**Usage Guidelines** Define or delete a domain name to use to replace the NAI constructed domain name after authentication.

## Example

the following command sets the domain name to *private1*:

```
nai-construction-domain private1
```

To delete the previously configured domain name, use the following command:

```
no nai-construction-domain
```

# nbns

Configures and enables use of NetBIOS Name Service (NBNS) for the subscriber.

---

**Product**

GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** ] **nbns** { **primary** *IPv4-address* | **secondary** *IPv4-address* }

**nbns primary**

Designates primary NBNS server. Must be followed with IPv4 address in dotted-decimal notation.

**nbns secondary**

Designates secondary/failover NBNS server. Must be followed with IPv4 address in dotted-decimal notation.

**IPv4-address**

Specifies the IP address used for this service using IPv4 dotted-decimal notation.

**no**

Removes/disables use of a previously configured NetBios Name Service.

---

**Usage Guidelines**

This command specifies NBNS parameters. The NBNS option is present for both PDP type IP and PDP type PPP for GGSN.

The system can be configured to use of NetBIOS Name Service for the Access Point Name (APN).

**Example**

The following command configures the subscriber's NetBIOS Name Service to primary IP *192.168.1.15*:

```
nbns primary 192.168.1.15
```

# nexthop-forwarding-address

Configures the next hop forwarding address for the subscriber.

---

**Product**

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**nexthop-forwarding-address** *ip\_address*

**no nexthop-forwarding-address**

**nexthop-forwarding-address** *ip\_address*

Configures the IP address of the nexthop forwarding address. *ip\_address* must be entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

**no**

Disables this function. This is the default setting.

---

**Usage Guidelines**

Use this command to configure the next hop forwarding address for the subscriber.

**Example**

The following command configures the next hop forwarding address to *10.1.1.1* (IPv4):

```
nexthop-forwarding-address 10.1.1.1
```

## npu qos

Configures an Network Processing Unit (NPU) QoS priority queue for packets from the subscriber.

---

### Product

PDSN  
GGSN  
ASN-GW  
P-GW  
SAEGW

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }  
 Entering the above command sequence results in the following prompt:  
 [*context\_name*]*host\_name*(config-subscriber)#

---

### Syntax Description

**npu qos traffic priority** { **best-effort** | **bronze** | **derive-from-packet-dscp**  
 | **gold** | **silver** }

#### **best-effort**

Assigns the best-effort queue priority. This is the lowest priority.

#### **bronze**

Assigns the bronze queue priority. This is the third-highest priority.

#### **derive-from-packet-dscp**

Default: Enabled

Specifies that the priority is to be determined from the DS field in the packet's TOS octet.

#### **gold**

Assigns the gold queue priority. This is the highest priority.

#### **silver**

Assigns the silver queue priority. This is the second-highest priority.

---

### Usage Guidelines

This command is used in conjunction with the Network Processing Unit (NPU) Quality of Service (QoS) functionality.

The system can be configured to determine the priority of a subscriber packet either based on the configuration of the subscriber, or from the differentiated service (DS) field in the packet's TOS octet (representing the differentiated service code point (DSCP) value).

Refer to the *System Administration Guide* for additional information on NPU QoS functionality.



---

**Important**

This functionality is not supported for use with the PDSN at this time.

---

**Example**

The following command configures the subscriber's priority queue to be gold:

```
npu qos traffic priority gold
```

# nw-reachability-server

Binds the name of a configured network reachability server to the current subscriber and enables network reachability detection.

**Product** HA

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description** **nw-reachability server** *server\_name*

**no nw-reachability server**

**nw-reachability server** *server\_name*

Specifies the name of a network reachability server that has been defined in the current context. *server\_name* is an alphanumeric string of 1 through 16 characters.

**no nw-reachability server**

Deletes the name of the network reachability server from the current subscribers configuration and disable network reachability failure detection for the current subscriber.

**Usage Guidelines** Use this command to define the network reachability server for the current subscriber and enable network reachability failure detection for the current subscriber. If a network reachability server is defined in an IP pool, that setting takes precedence over this command.



**Important** Refer to the HA configuration mode command **policy nw-reachability-fail** to configure the action that should be taken when network reachability fails.



**Important** Refer to the context configuration mode command **nw-reachability server** to configure network reachability servers.



**Important** Refer to the **nw-reachability server** *server\_name* keyword of the **ip pool** command in the *Context Configuration Mode Commands* chapter to bind the network reachability server to an IP pool.

**Example**

To bind a network reachability server named *InternetDevice* to the current subscriber, enter the following command:

```
nw-reachability server InternetDevice
```

# outbound

Configures the subscriber host password for use when authenticating PPP sessions.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**outbound** [ **encrypted** ] **password** *pwd*

**no outbound password**

**[ outbound encrypted ] password *pwd***

Specifies the password to use for point-to-point protocol session host authentication. The **encrypted** keyword indicates the password specified uses encryption.

The password specified as *pwd* must be an alphanumeric string of 1 through 63 characters without encryption, or 1 through 127 characters with encryption.

The **encrypted** keyword is intended only for use by the chassis while saving configuration scripts. The system displays the **encrypted** keyword in the configuration file as a flag that the variable following the **password** keyword is the encrypted version of the plain text password. Only the encrypted password is saved as part of the configuration file.

**no outbound password**

Clears the outbound password configuration from the subscriber data.

---

**Usage Guidelines**

Sets the outbound (egress) password for increased security.

**Example**

```
outbound password secretPwd
```

```
outbound encrypted password scrambledPwd
```

```
no outbound password
```



# overload-disconnect

Sets the threshold parameter for overload disconnect.

---

## Product

ASN-GW  
HA  
PDIF  
PDSN  
PHSGW  
PDG/TTG

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**overload-disconnect** [ **threshold** { **inactivity-time** *inactivity\_time\_threshold* | **connect-time** *connect\_time\_threshold* } ]

[ **default** | **no** ] **overload-disconnect** [ **threshold** { **inactivity-time** | **threshold** **connect-time** } ]

### **threshold inactivity-time** *inactivity\_time\_threshold*

Sets the inactivity time threshold (in seconds) as an integer from 0 through 4294967295. The default value of zero disables this feature. If *inactivity-time* for the subscriber's session is greater than *inactivity\_time\_threshold*, the session becomes a candidate for disconnection.

### **threshold connect-time** *connect\_time\_threshold*

Sets the connection time threshold (in seconds) as an integer from 0 through 4294967295. A value of zero disables this feature. If connect-time for the subscriber's session is greater than *connect\_time\_threshold*, the session becomes a candidate for disconnection.

### **default**

Enables the default condition for this subscriber.

### **no**

Disables the overload disconnect feature for this subscriber. This is the default condition for PDIF.

---

## Usage Guidelines

Set a subscriber's overload disconnect threshold in seconds, based on either inactivity or connection time. When this threshold is exceeded during a session, the subscriber's session becomes a candidate for

disconnection. To set overload-disconnect policies for the entire chassis, see **congestion-control** **overload-disconnect** in the *Global Configuration Mode Commands* chapter.

### Example

```
overload-disconnect threshold inactivity-time 120
default overload disconnect threshold connect-time
no overload-disconnect threshold connect-time
no overload disconnect
```

# password

Configures the subscribers password for the current context.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **encrypted** ] **password** *pwd*

**no password**

## **encrypted**

Indicates the password provided is encrypted.

The **encrypted** keyword is intended only for use by the chassis while saving configuration scripts. The system displays the **encrypted** keyword in the configuration file as a flag that the variable following the **password** keyword is the encrypted version of the plain text password. Only the encrypted password is saved as part of the configuration file.

## **pwd**

Specifies the user's password for authentication. *pwd* must be an alphanumeric string of 1 through 63 characters without encryption, or from 1 through 127 characters with encryption. A "null" password is allowed and is entered as consecutive double quotes (" "). See Example(s) for correct syntax.


**Important**

Subscribers configured with a null password will be authenticated using PAP and CHAP (MD5) only. Subscribers configured without a password (**no password**) will only be able to access services if the service is configured to allow no authentication.

## **no**

Used to clear the subscriber password configuration from the subscriber data.


**Important**

Subscribers with no password will only be able to access services if the service is configured to grant access with no authentication.

---

**Usage Guidelines**

Password management is critical to system security and all precautions should be taken to ensure passwords are not shared or to easily deciphered.

**Example**

```
password secretPwd
```

```
password ""
```

```
no password
```

# pdif mobile-ip

Configures PDIF subscriber call setup parameters.

---

**Product**

PDIF

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
[ default | no ] pdif mobile-ip { release-tia | required | simple-ip-fallback }
```

**[ default | no ]**

Disables the option specified.

**release-tia**

Specifies that after subscriber call setup is complete, the tunnel inner address (TIA) is released. If Simple IP is enabled, the TIA becomes the principal communications tunnel and the restriction that it is only to be used to set up a Mobile-IP call is lifted. This parameter is disabled by default.

**required**

Specifies that Mobile IP is required for this subscriber whenever a call is set up. This parameter is disabled by default.

**simple-ip-fallback**

Specifies that Simple IP should be used when Mobile IP could not be established. This parameter is disabled by default.

---

**Usage Guidelines**

Use this command to configure specific behavior for the PDIF subscriber during call setup.

**Example**

The following command enables the system to fall back to Simple IP when Mobile IP fails for this subscriber during call setup:

```
pdif mobile-ip simple-ip-fallback
```

# permission

Enables or disables the subscriber's ability to access wireless data services.

---

## Product

PDSN

HA

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
[ no ] permission { ha-mobile-ip | pdsn-mobile-ip | pdsn-simple-ip |
pmipv6-interception }
```

**default permission**

**no | default**

Disables the usage of the specified service.

**ha-mobile-ip | pdsn-mobile-ip | pdsn-simple-ip**

**ha-mobile-ip**: Enables or disables the Home Agent (HA) support for Mobile IP (MIP) service.

**pdsn-mobile-ip**: Enables or disables packet data and Foreign Agent (FA) support for MIP service.

**pdsn-simple-ip**: Enables or disables packet data support for simple IP service.

**pmipv6-interception**: Allows subscribers to access the external Local Mobility Anchor (LMA) over PMIPv6.

---

## Usage Guidelines

Grants the subscriber access to services in the current context.

### Example

The following command Grants the subscriber access to PDSN/HA services:

```
permission pdsn-mobile-ip
```

# policy ipv6 tunnel

Sets maximum transmission unit (MTU) behavior for the IPv6 tunnel between the HA and Mobile Node.

---

**Product**

PDSN

HA

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**policy ipv6 tunnel mtu exceed { fragment | notify-sender }**

**mtu exceed { fragment | notify-sender }**

**fragment**: Adjusts tunnel MTU for fragmented packets

**notify-sender**: Sends an ICMPv6 Packet Too Big message to the original sender

---

**Usage Guidelines**

Use this command to configure MTU behavior for an IPv6 tunnel between the HA and Mobile Node.

**Example**

The following command configures adjustments to tunnel MTU for fragmented packets:

```
policy ipv6 tunnel mtu exceed fragment
```

# policy-group

Assigns or removes a flow-based traffic policy group to a subscriber.

---

## Product

PDSN  
HA  
ASN-GW  
HSGW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **policy-group** *policy\_group\_name* **direction** { **in** | **out** }

### **no**

Removes assigned policy group from a subscriber configuration.

### **policy-group** *policy\_group\_name*

Specifies the traffic policy group name for a subscriber session flow pre-configured within a destination context. *policy\_group\_name* is an alphanumeric string of 1 through 15 characters that is case sensitive.

### **direction** { **in** | **out** }

Specifies the direction of flow in which the traffic policies need to be applied.

- **in**: specifies the incoming traffic
- **out**: specifies the outgoing traffic

---

## Usage Guidelines

Use this command to assign a traffic policy group to a subscriber for traffic policing.

### Example

The following command assigns inbound traffic policy group *tp-group1* to this subscriber:

```
policy-group tp-group1 direction in
```



# ppp

Configures the point-to-point protocol (PPP) options for the current subscriber.

---

## Product

PDSN  
PDSN Closed R-P  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
ppp { accept-peer-ipv6-iframe | always-on-vse-packet | data-compression {
mode { normal | stateless } | protocols { protocols [ protocols ] } |
ip-header-compression negotiation { detect | force | vj compress-slot-id
{ both | none | receive | transmit } } | ipv4 { disable | enable | passive
} | ipv6 { disable | enable | passive } | keepalive seconds |
min-compression-size min_octets | mtu max_octets | remote-renegotiation
disconnect { always | nai-prefix-msid-mismatch } }

default ppp { accept-peer-ipv6-iframe | always-on-vse-packet |
data-compression { mode | protocols } | ip-header-compression negotiation
[ vj compress-slot-id ] | ipv4 | ipv6 | keepalive | min-compression-size
| mtu | remote-renegotiation disconnect }

no ppp { accept-peer-ipv6-iframe | always-on-vse-packet | data-compression
protocols | ipv4 | ipv6 | keepalive | mtu | remote-renegotiation
disconnect }
```

### default

Restores the default value for the option specified.

### no

Resets the option specified to its default.

### always-on-vse-packet

Default: Enabled

If this feature is enabled, the PDSN sends special 3GPP2 VSE PPP packets to the Mobile Node with a maximum inactivity timer value. This configuration is applicable only for PDSN or PDSNCLOSED-RP sessions.

### accept-ipv6-peer-iframe

Default: None

Configures an IPv6-to-IPv4 (6to4) tunnel and controls the behavior of IPv6CP negotiation for the Interface ID. If enabled, PDSN will accept a valid interface-id proposed by the peer.

**data-compression { mode { normal | stateless } | protocols { protocols [ protocols ] }**

Default: all protocols enabled.

Specifies the subscriber's mode of data compression or the compression protocol to use.

**mode:** sets the mode of compression where *modes* must be one of:

- **normal:** Packets are compressed using the packet history for automatic adjustment for best compression.
- **stateless:** Each packet is compressed individually.

**protocols protocols:** sets the compression protocol where *protocols* must be one of:

- **deflate:** DEFLATE algorithm
- **mppc:** Microsoft PPP algorithm
- **stac:** STAC algorithm

**ip-header-compression negotiation { detect | force | vj compress-slot-id { both | none | receive | transmit } }**

Default: **force**

**detect:** The local side does not include the Van Jacobson (VJ) Compression option in its IPCP configuration request unless the peer sends an Internet Protocol Control Protocol (IPCP) NAK including a VJ compression option. If the peer requests the VJ compression option in its IPCP request the local side will ACK/NAK.

**force:** The IP header compression negotiation in IPCP happens normally. The local side requests the VJ compression option in its IPCP configure request. If the peer side requests VJ compression in its IPCP request, the local side will ACK/NAK the option.

**vj compress-slot-id [ both | none | receive | transmit ]:** Configures the direction in which VJ slotid compression should be negotiated.

- **both** - If the client proposes VJ slotid compression, accept it and propose slotid compression for the downlink and uplink.
- **none** - If the client proposes VJ slotid compression, NAK the offer, do not propose slotid compression for the downlink.
- **receive** - (Default) If the client proposes VJ slotid compression in the uplink direction accept the configuration.
- **transmit** - Propose VJ slotid compression for uplink.

**ipv4 { disable | enable | passive }**

Default: enable

Controls IPCP negotiation during PPP negotiation.

**disable:** The PDSN does not negotiate IPCP with the mobile.

**enable:** The PDSN negotiates IPCP with the mobile.

**passive:** The PDSN initiates IPCP only when the mobile sends an IPCP request.

**ipv6 { disable | enable | passive }**

Default: enable

Controls IPv6CP negotiation during PPP negotiation.

**disable:** The PDSN does not negotiate IPCP with the mobile.

**enable:** The PDSN negotiates IPCP with the mobile.

**passive:** The PDSN initiates IPCP only when the mobile sends an IPCP request.

**keepalive seconds**

Default: 30

Specifies the frequency of sending the Link Control Protocol keepalive messages. *seconds* must be either 0 or an integer from 5 through 14400. The special value 0 disables the keepalive messages entirely.

**min-compression-size min\_octets**

Default: 128

Specifies the smallest packet (in octets) to which compression may be applied. *min\_octets* must be an integer from 0 through 2000.

**mtu max\_octets**

Default: 1500

Specifies the maximum transmission unit (MTU) [in octets] for packets. *max\_octets* must be an integer from 100 through 2000.

**remote-renegotiation disconnect { always | nai-prefix-msid-mismatch }**

Default: Disabled

Terminates the already established PPP sessions if they are renegotiated by the remote side by sending LCP Conf-req/nak/ack. The following termination conditions are available:

- **always:** Automatically disconnects the session.
- **nai-prefix-msid-mismatch:** Disconnects the session only if the MSID of the session does not match NAI-Prefix (prefix before "@" for the NAI). The configuration of the renegotiated (new) NAI is used for the matching process.

---

**Usage Guidelines**

Adjust packet sizes and compression to improve bandwidth utilization. Each network may have unique characteristics such that determining the best packet size and compression options may require system monitoring over an extended period of time.

**Example**

The following sequence of CLI commands sets PPP parameters for this subscriber:

```
ppp data-compression protocols mode stateless
```

```
ppp mtu 500
no ppp data-compression protocols
no ppp keepalive
```

# prepaid 3gpp2

Enables 3GPP2 compliant prepaid billing support for a subscriber to be configured by 3GPP2 attributes sent from a RADIUS server. If not enabled, prepaid attributes received from the RADIUS server are ignored.

---

**Product**

PDSN  
HA

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
prepaid 3gpp2 { accounting [ no-final-access-request ] | duration-quota
final-duration-algorithm { current-time | last-airlink-activity-time |
last-user-layer3-activity-time } | preference { duration | volume } }
```

```
default prepaid 3gpp2 { duration-quota final-duration-algorithm |
preference }
```

```
no prepaid 3gpp2 accounting
```

```
default prepaid 3gpp2 { duration-quota final-duration-algorithm | preference }
```

Sets the 3GPP2 Pre-paid settings to the default values.

**duration-quota final-duration-algorithm:** Resets the end of billing duration quota algorithm to the default of current-time.

**preference:** Resets the preference to duration, If both duration and volume attributes are present.

**no prepaid 3gpp2 accounting**

Disables 3GPP2 prepaid accounting. All 3GPP2 Prepaid attributes received from a RADIUS server are ignored.

**accounting [ no-final-access-request ]**

Default: Disabled

Enables 3GPP2 prepaid accounting behavior.

Sets the low-watermark for remaining byte credits. *percentage* is a percentage of the subscriber sessions total credits. When the low-watermark is reached a new RADIUS access-request is sent to the RADIUS server to retrieve more credits. *percentage* must be an integer from 1 through 99.

**no-final-access-request:** Stops sending final online access-request on termination of 3GPP2 prepaid sessions. By default, this option is disabled.

**duration-quota final-duration-algorithm { current-time | last-airlink-activity-time | last-user-layer3-activity-time }**

Defines what behavior marks the end of the billing duration for duration-based quota usage accounting. The default behavior sets the duration quota algorithm to current-time.

Default: current-time

**current-time:** Selects the duration quota as the difference between the session termination timestamp and the session setup timestamp.

**last-airlink-activity-time:** Selects the duration quota as the difference between the last-user-activity timestamp (G17) and the session setup timestamp.

**last-user-layer3-activity-time:** Selects the duration quota as the difference between the timestamp of the last layer-3 packet sent to or received from the user and the session setup timestamp.

**preference { duration | volume }**

If both duration and volume RADIUS attributes are present this keyword specifies which attribute has precedence.

Default: duration

**duration:** The duration attribute takes precedence.

**volume:** The volume attribute takes precedence

---

**Usage Guidelines**

Use this command to enable prepaid support for a default user or for the default user of a domain alias.

**Example**

The following command enables 3GPP2 prepaid support for the default user:

```
prepaid 3gpp2 accounting
```

# prepaid custom

Enables custom prepaid billing support for a subscriber to be configured by attributes sent from a RADIUS server. If not enabled, prepaid attributes received from the RADIUS server are ignored. The keywords set prepaid values that are used if the corresponding RADIUS attribute is not present. If the RADIUS attribute is present, it takes precedence over these values.

---

**Product**

PDSN  
HA

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
prepaid custom { accounting | byte-count compressed | low-watermark percent  
percentage | renewal interval seconds } | preference { duration | volume }
```

```
default prepaid custom { byte-count | low-watermark }
```

```
no prepaid custom { accounting | byte-count compressed | low-watermark |  
renewal }
```

```
default prepaid custom { byte-count | low-watermark }
```

Resets custom prepaid settings to the default values.

**byte-count**: Resets to the default of basing the prepaid byte credits on the flow of uncompressed traffic.

**low-watermark**: Disables sending an access request to retrieve more credits when a low watermark is reached.

```
no prepaid custom { accounting | byte-count compressed | low-watermark | renewal}
```

**byte-count compressed**: The prepaid byte credits are based on the flow of uncompressed traffic. This is the default.

**low-watermark**: Disables the low watermark feature. An access-request is not sent to the RADIUS server until the credits granted for the subscriber session are depleted.

**renewal**: Disables time-based renewals for prepaid accounting.

**accounting**

Default: Disabled

Enables custom prepaid accounting behavior.

**byte-count compressed**

Default: uncompressed.

When compression is used, the prepaid byte credits are based on the flow of compressed traffic. The default is to base the prepaid byte credits on the flow of uncompressed traffic.

**low-watermark percent *percentage***

Default: Disabled.

Sets the low-watermark for remaining byte credits. *percentage* is a percentage of the subscriber sessions total credits. When the low-watermark is reached a new RADIUS access-request is sent to the RADIUS server to retrieve more credits. *percentage* must be an integer from 1 through 99.

**renewal interval *seconds***

Default:

The time in seconds to wait before sending a new RADIUS access-request to the RADIUS server to retrieve more credits. *seconds* must be an integer from 60 through 65535.

**preference { *duration* | *volume* }**

If both duration and volume RADIUS attributes are present this keyword specifies which attribute has precedence.

Default: duration

**duration:** The duration attribute takes precedence.

**volume:** The volume attribute takes precedence

---

**Usage Guidelines**

Use this command to enable prepaid support for a default user or for the default user of a domain alias.

**Example**

The following command enables custom prepaid support for the default user:

```
prepaid custom accounting
```



# prepaid unclassify

This command provides customer specific functionality.

## prepaid voice-push

This command provides customer specific functionality.

# prepaid wimax

Enables WiMAX prepaid accounting for this subscriber. This feature is disabled by default.

---

**Product**

ASN-GW

---

**Privilege**

Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

[ **no** ] **prepaid wimax accounting**

**no**

Disables WiMAX prepaid accounting for this subscriber.

---

**Usage Guidelines**

Use this command to enable WiMAX prepaid accounting for this subscriber.

**Example**

The following command enables WiMAX prepaid accounting for this subscriber:

```
prepaid wimax accounting
```

# proxy-dns intercept list-name

Identifies a proxy DNS intercept rules list for the selected subscriber.

---

## Product

HA

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

[ **no** ] **proxy-dns intercept list-name** *name*

### **no**

Removes the intercept list from the subscribers profile.

### **proxy-dns intercept list-name** *name*

Specifies a name of a proxy DNS intercept list used for the selected subscriber.

*name* is the name of the intercept list expressed as an alphanumeric string of 1 through 63 characters.

---

## Usage Guidelines

Use this command to identify a proxy DNS rules list for the selected subscriber. For a more detailed explanation of the HA Proxy DNS Intercept feature, see the **proxy-dns intercept-list** command in the *Context Configuration Mode Commands* chapter.

## Example

The following command specifies the proxy DNS intercept list named *dns-Intercept-list*:

```
proxy-dns intercept list-name dns-Intercept-list
```

# proxy-mip

Configures support for Proxy Mobile IP for the subscriber.

---

**Product**

PDSN  
GGSN  
ASN-GW  
PDIF

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

[ **no** ] **proxy-mip required**

**no**

Disables support for Proxy Mobile IP.

**required**

Enables support for Proxy Mobile IP.

---

**Usage Guidelines**

When enabled through the session license and feature use key, the system supports Proxy Mobile IP to provide a mobility solution for subscribers with mobile nodes (MNs) capable of supporting only Simple IP.

For subscriber sessions using Proxy Mobile IP, R-P and PPP sessions are established as they would for a Simple IP session. However, the AGW/FA performs Mobile IP operations with an HA (identified by information stored in the subscriber's profile) on behalf of the MN while the MN performs only Simple IP processes.

**Example**

The following command enables proxy mobile IP for the current subscriber:

```
proxy-mip required
```

# qos apn-ambr

Configures the rate limit according to the APN-AMBR to do the session level bandwidth control per direction, according to the QoS information provided by the PCRF on the Gx interface.

---

## Product




---

### Important

This command is customer specific. For more information contact your Cisco account representative.

---

PDSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**qos apn-ambr rate-limit** { **downlink** | **uplink** } [ **burst-size** *bytes* ] [ **violate-action** { **drop** | **lower-ip-precedence** | **transmit** } ] ]

**no qos apn-ambr rate-limit**

**no**

Disables the QoS data rate limit configuration for the subscriber.

**downlink**

Applies the specified limits and actions to the downlink (to the data coming from the GGSN over the Gn' interface).

**uplink**

Applies the specified limits and actions to the uplink (to the data coming from the UE over the IPsec tunnel).




---

### Important

If this keyword is omitted, the same values are used for all classes.

---

**burst-size** *bytes*

Default: See the *Usage* section for this command

The burst size allowed (in bytes) for peak data rate and committed data rate.

*bytes* must be an integer from 1 through 6000000.

**Important**

The minimum value of this parameter should be configured to the greater of the following two values: 1) three times greater than the packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate. If the committed-data-rate parameter is specified, the burst-size is applied to both the committed and peak rates.

**violate-action { drop | lower-ip-precedence | transmit }**

Default: See the *Usage* section for this command

Specifies the action to take on packets that exceed both the committed-data-rate and the peak-data-rate. The following actions are supported:

- **drop**: Drops the packets.
- **lower-ip-precedence**: Transmits the packets after lowering the IP precedence.
- **transmit**: Transmits the packet.

**Usage Guidelines**

This command configures the rate limit according to the APN-AMBR to do the session level bandwidth control per direction, according to the QoS information provided by the PCRF on the Gx interface. This command specifies the actions to take on subscriber flows exceeding or violating allowed peak or committed data rates.

**Example**

The following example configures the rate limit and burst size according to the APN-AMBR for the uplink direction. Policing is done for the traffic based on PCRF value received and traffic is dropped as the violate action is specified as drop.

```
qos apn-ambr rate-limit direction uplink burstsize 1 violate-action drop
```

## qos rate-limit

Configure the action on subscriber traffic flow that violates or exceeds the peak/committed data rate under traffic policing functionality. When configured, the PDG/TTG performs traffic policing for the subscriber session. If the GGSN changes the QoS via an Update PDP Context Request, the PDG/TTG uses the new QoS values for traffic policing.

---

**Product** PDG/TTG

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
qos rate-limit { downlink | uplink } [ qci qci_val ] [ burst-size { bytes | auto-readjust [ duration dur ] } ] [ exceed-action { drop | lower-ip-precedence | transmit } [ violate-action { drop | lower-ip-precedence | shape [ transmit-when-buffer-full ] | transmit } ] ] | [ violate-action { drop | lower-ip-precedence | shape [ transmit-when-buffer-full ] | transmit } [ exceed-action { drop | lower-ip-precedence | transmit } ] ] +
```

```
no qos rate-limit direction { downlink | uplink } [ qci qci_val ]
```

**no**

Disables the QoS data rate limit configuration for the subscriber.

**downlink**

Applies the specified limits and actions to the downlink (to the data coming from the GGSN over the Gn' interface).

**uplink**

Applies the specified limits and actions to the uplink (to the data coming from the UE over the IPsec tunnel).




---

**Important** If this keyword is omitted, the same values are used for all classes.

---

**qci** *qci\_val*

*qci\_val* is the QoS Class identifier (QCI) for which the negotiate limit is being set expressed as an integer from 1 through 9. If no *qci-val* is configured, it will be taken as undefined-qci (same as undefined-qos class).

**burst-size** { *bytes* | **auto-readjust** [ **duration** *dur* ] }

Default: See the *Usage* section for this command



The burst size allowed (in bytes) for peak data rate and committed data rate.

*bytes* must be an integer from 1 through 6000000.



### Important

The minimum value of this parameter should be configured to the greater of the following two values: 1) three times greater than the packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate. If the committed-data-rate parameter is specified, the burst-size is applied to both the committed and peak rates.

**auto-readjust [ duration *dur* ]** provides the option to calculate the Burst size dynamically while configuring rate-limit. When enabled, the system calculates the burst size using the GGSN QoS-negotiated rate that will be enforced.

Every time there is a change in the rates (due to an updated QoS), the burst sizes will be updated accordingly. This keyword also provides two different burst sizes. One burst size for peak rate and another for committed rate.

By default this keyword is disabled.

**duration *dur*** specifies the duration of burst in seconds. If the duration is not specified, the default is 1 second. *dur* must be an integer from 1 through 30.

### **exceed-action { drop | lower-ip-precedence | transmit }**

Default: See the *Usage* section for this command

Specifies the action to take on packets that exceed the committed-data-rate but do not violate the peak-data-rate. The following actions are supported:

- **drop**: Drops the packets.
- **lower-ip-precedence**: Transmits the packets after lowering the ip-precedence.
- **transmit**: Transmits the packets.

### **violate-action { drop | lower-ip-precedence | transmit }**

Default: See the *Usage* section for this command

Specifies the action to take on packets that exceed both the committed-data-rate and the peak-data-rate. The following actions are supported:

- **drop**: Drops the packets.
- **lower-ip-precedence**: Transmits the packets after lowering the IP precedence.
- **transmit**: Transmits the packet after lowering the IP precedence.

**shape [transmit-when-buffer-full]**: Enables traffic shaping and buffers user packets when subscriber traffic violates the allowed peak/committed data rate. The **[transmit-when-buffer-full]** keyword allows the packets to be transmitted when buffer memory is full.

**transmit**: Transmits the packet

**Usage Guidelines**

This command configures APN quality of service (QoS) data rate shaping through traffic policing. This command specifies the actions to take on subscriber flows exceeding or violating allowed peak or committed data rates. The shaping function also provides an enhanced function to buffer the excessive user packets and send them to the subscriber when subscriber traffic drops below the committed or peak data rate limit.

**Important**

The buffering of user packets in traffic shaping does not apply for real-time traffic.

**Important**

If the exceed/violate action is set to "lower-ip-precedence", this command may override the configuration of the **ip qos-dscp** command in the GGSN service Configuration mode for packets from the GGSN to the PDG/TTG. In addition, the GGSN service **ip qos-dscp** command configuration can override the APN setting for packets from the GGSN to the Internet. Therefore, it is recommended that this command not be used in conjunction with this action.

The command can be entered multiple times to specify different combinations of direction and class. If this command is not configured at all, the GGSN does not perform traffic policing or QoS negotiation with the PDG/TTG; it accepts all of the PDG/TTG-provided values for the PDP context.

**Important**

This command should be used in conjunction with the max-contexts command to limit the maximum possible bandwidth consumption by the APN.

For additional information on QoS traffic shaping and policing, see the *System Administration Guide*.

**Default Values**

The following table displays the default values for each of the traffic classes:

<b>Class: Conversational</b>	
Downlink Traffic: Disabled	Uplink Traffic: Disabled
Peak Data Rate (in bps): 16000000	Peak Data Rate (in bps): 8640000
Committed Data Rate (in bps): 16000000	Committed Data Rate (in bps): 8640000
Exceed Action: lower-ip-precedence	Exceed Action: lower-ip-precedence
Violate Action: drop	Violate Action: drop
<b>Class: Streaming</b>	
Downlink Traffic: Disabled	Uplink Traffic: Disabled
Peak Data Rate (in bps): 16000000	Peak Data Rate (in bps): 8640000
Committed Data Rate (in bps): 16000000	Committed Data Rate (in bps): 8640000
Exceed Action: lower-ip-precedence	Exceed Action: lower-ip-precedence
Violate Action: drop	Violate Action: drop
<b>Class: Interactive, Traffic Handling Priority: 1</b>	

Downlink Traffic: Disabled Peak Data Rate (in bps): 16000000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop	Uplink Traffic: Disabled Peak Data Rate (in bps): 8640000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop
<b>Class: Interactive, Traffic Handling Priority: 2</b>	
Downlink Traffic: Disabled Peak Data Rate (in bps): 16000000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop	Uplink Traffic: Disabled Peak Data Rate (in bps): 8640000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop
<b>Class: Interactive, Traffic Handling Priority: 3</b>	
Downlink Traffic: Disabled Peak Data Rate (in bps): 16000000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop	Uplink Traffic: Disabled Peak Data Rate (in bps): 8640000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop
<b>Class: Background</b>	
Downlink Traffic: Disabled Peak Data Rate (in bps): 16000000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop	Uplink Traffic: Disabled Peak Data Rate (in bps): 8640000 Committed Data Rate (in bps): n/a Exceed Action: n/a Violate Action: drop

**Usage Guidelines**

This command configures the APN quality of service (QoS) data rate shaping through traffic policing/shaping. This command specifies the actions to take on subscriber flows exceeding or violating allowed peak/committed data rates. The shaping function also provides an enhanced function to buffer the excessive user packets and send them to the subscriber when subscriber traffic drops below the committed or peak data rate limit.

**Important**

The buffering of user packets in traffic shaping does not apply for real-time traffic.

**Important**

If the exceed/violate action is set to "lower-ip-precedence", this command may override the configuration of the **ip qos-dscp** command in the GGSN service configuration mode for packets from the GGSN to the SGSN. In addition, the GGSN service **ip qos-dscp** command configuration can override the APN setting for packets from the GGSN to the Internet. Therefore, it is recommended that command not be used in conjunction with this action.

The command can be entered multiple times to specify different combinations of direction and class. If this command is not configured at all, the GGSN does not perform traffic policing or QoS negotiation with the SGSN (i.e. it accepts all of the SGSN-provided values for the PDP context).

**Important**

This command should be used in conjunction with the **max-contexts** command to limit the maximum possible bandwidth consumption by the APN.

**Default Values:**

To calculate the burst size dynamically a new optional keyword **auto-readjust** [ **duration** *dur* ] is provided with **burst-size** keyword. By default the burst size is fixed if defined in bytes with this command. In other words irrespective of the rate being enforced, burst-size fixed as given in the **burst-size** *bytes* parameter.

For the need of variable burst size depending on the rate being enforced this new keyword **auto-readjust** [ **duration** *dur* ] is provided. Use of this keyword enables the calculation of burst size as per token bucket algorithm calculation as  $T=B/R$ , where T is the time interval, B is the burst size and R is the Rate being enforced.

It also provides different burst size for Peak and Committed data rate-limiting.

If **auto-readjust** keyword is not used a fixed burst size must be defined which will be applicable for peak data rate and committed data rate irrespective of rate being enforced.

If **auto-readjust** keyword is provided without specifying the duration a default duration of 1 second will be taken for burst size calculation.

**Example**

The following command lowers the IP precedence when the committed-data-rate and the peak-data-rate are violated in uplink direction:

```
qos rate-limit direction uplink violate-action lower-ip-precedence
```

The following command buffers the excess user packets when the subscriber traffic violates the configured peak or committed data-rate bps in uplink direction. Once the peak/committed data rate for that subscriber goes below the configured limit it transmits them. It also transmits them if buffer memory is full:

```
qos rate-limit direction uplink violate-action shape
transmit-when-buffer-full
```

# qos traffic-police

Enables and configures traffic policing through bandwidth limitations and action for the subscriber traffic if it exceeds or violates the peak or committed data rate. Uplink and downlink limits are configured separately.

---

## Product

PDSN  
HA  
GGSN  
ASN-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
qos traffic-police direction { downlink | uplink } [ burst-size bytes ] [ committed-data-rate bps ] [ exceed-action { drop | lower-ip-precedence | transmit } ] [ peak-data-rate bps ] [ violate-action { drop | lower-ip-precedence | transmit } ]
```

```
no qos traffic-police direction { downlink | uplink }
```

### downlink

Applies the specified limits and actions to the downlink (data to the subscriber).

### uplink

Apply the specified limits and actions to the uplink (data from the subscriber).

### burst-size *bytes*

Default: 3000

Specifies the allowed peak burst size allowed in bytes.

*bytes* must be an integer from 0 through 4294967295.




---

## Important

This parameter should be configured to at least the greater of the following two values: 1) three times greater than packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate.

### committed-data-rate *bps*

Default: 144000

Specifies the committed data rate (guaranteed-data-rate) in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**exceed-action { drop | lower-ip-precedence | transmit }**

Default: lower-ip-precedence

Specifies the action to take on packets that exceed the committed-data-rate but do not violate the peak-data-rate. The following actions are supported:

**drop:** Drops the packet

**lower-ip-precedence:** Transmits the packet after lowering the ip-precedence

**transmit:** Transmits the packet

**peak-data-rate *bps***

Default: 256000

Specifies the peak data-rate for the subscriber in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**violate-action { drop | lower-ip-precedence | transmit }**

Default: drop

Specifies the action to take on packets that exceed both the committed-data-rate and the peak-data-rate. The following actions are supported:

**drop:** Drops the packet

**lower-ip-precedence:** Transmits the packet after lowering the IP precedence

**transmit:** Transmits the packet

**no**

Disables traffic policing in the specified direction for the current subscriber.

## Usage Guidelines

Use this command to limit the bandwidth a subscriber uses in the uplink and downlink directions.



### Important

If the exceed/violate action is set to "lower-ip-precedence", the TOS value for the outer packet becomes "best effort" for packets that exceed/violate the traffic limits regardless of what the **ip user-datagram-tos copy** command is configured to. In addition, the "lower-ip-precedence" option may also override the configuration of the **ip qos-dscp** command. Therefore, it is recommended that command not be used when specifying this option.

Details on the QoS traffic policing can be found in the *System Administration Guide*.

### Example

The following command sets an uplink peak data rate of *128000* bps and lowers the IP precedence when the committed-data-rate and the peak-data-rate are exceeded:

```
qos traffic-police direction uplink peak-data-rate 128000 violate-action  
lower-ip-precedence
```

The following command sets a downlink peak data rate of *256000* bps and drops packets when the committed-data-rate and the peak-data-rate are exceeded:

```
qos traffic-police direction downlink peak-data-rate 256000 violate-action  
drop
```

# qos traffic-shape

Enables and configures traffic shaping functionality when buffering the data packets during congestion or when the subscriber exceeds the configured peak or committed data rate limit. The system buffers the data packets during an instantaneous burst and deliver them to the subscriber when traffic flow drops below the peak or committed data rate. Uplink and downlink traffic shaping are configured separately.




---

**Important** This feature is NOT supported for real-time traffic.

---



---

## Product

PDSN  
HA  
GGSN  
ASN-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

```
qos traffic-shape direction { downlink | uplink } [ burst-size bytes ] [ committed-data-rate bps ] [ exceed-action { drop | lower-ip-precedence | transmit } ] [ peak-data-rate bps ] [ violate-action { drop | lower-ip-precedence | buffer [ transmit-when-buffer-full ] | transmit } ] +
```

```
no qos traffic-shape direction { downlink | uplink }
```

### **downlink**

Applies the specified limits and actions to the downlink (data to the subscriber).

### **uplink**

Applies the specified limits and actions to the uplink (data from the subscriber).

### **burst-size** *bytes*

Default: 3000

Specifies the allowed peak burst size in bytes.

*bytes* must be an integer from 0 through 4294967295.



**Important**

It is recommended that this parameter be configured to at least the greater of the following two values: 1) three times greater than packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate.

**committed-data-rate *bps***

Default: 144000

Specifies the committed data rate (guaranteed-data-rate) in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**exceed-action { drop | lower-ip-precedence | transmit }**

Default: lower-ip-precedence

Specifies the action to take on packets that exceed the committed-data-rate but do not violate the peak-data-rate. The following actions are supported:

**drop:** Drops the packet

**lower-ip-precedence:** Transmits the packet after lowering the ip-precedence

**transmit:** Transmits the packet

**peak-data-rate *bps***

Default: 256000

Specifies the peak data-rate for the subscriber in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**violate-action { drop | lower-ip-precedence | buffer [transmit-when-buffer-full] | transmit }**

Default: See the *Usage* section for this command

The action to take on the packets that exceed both the committed-data-rate and the peak-data-rate. The following actions are supported:

**drop:** Drops the packet

**lower-ip-precedence:** Transmits the packet after lowering the IP precedence

**buffer [transmit-when-buffer-full]:** Enables traffic shaping and buffers user packets when subscriber traffic violates the allowed peak/committed data rate. The **[transmit-when-buffer-full]** keyword allows the packet to be transmitted when buffer memory is full.

**transmit:** Transmits the packet

**+**

More than one of the above keywords can be entered within a single command.

**no**

Disables traffic policing for the specified direction for the current subscriber.

---

**Usage Guidelines**

Use this command to provide the traffic shaping function to a subscriber in the uplink and downlink directions. This feature is providing a traffic flow control different to QoS traffic policing. When a subscriber violates or exceeds the peak data rate instead of dropping the packets, as in QoS traffic policing, this feature buffers subscriber data packets and sends the buffered data when the traffic flow is low or not in congestion state.



---

**Important**

If the exceed or violate action is set to "lower-ip-precedence", the TOS value for the outer packet becomes "best effort" for packets that exceed or violate the traffic limits regardless how the **ip user-datagram-tos copy** command is configured. In addition, the "lower-ip-precedence" option may also override the configuration of the **ip qos-dscp** command. Therefore, this command should not be used when specifying this option.

---

**Example**

The following command sets an uplink peak data rate of *128000* bps and lowers the IP precedence when the committed-data-rate and the peak-data-rate are exceeded:

```
qos traffic-shape direction uplink peak-data-rate 12800 violate-action  
lower-ip-precedence
```

The following command buffers the excess user packets when the subscriber traffic violates the configured peak-data-rate *256000* bps in downlink direction. Once the peak/committed data rate for that subscriber goes below the configured limit it transmits them. It also transmits them if buffer memory is full:

```
qos traffic-shape direction downlink peak-data-rate 256000 violate-action  
buffer transmit-when-buffer-full
```

# radius accounting

Sets the RADIUS accounting parameters for the subscriber or domain. This command takes precedence over the similar Context Configuration command and is disabled by default.

**Product** All

**Privilege** Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

```
radius accounting { interim { interval-timeout timeout | normal | suppress } | ip remote-address list-id list_id | mode { session-based | access-flow-based { none | auxillary-flows | all-flows | main-a10-only } } | start { normal | suppress } | stop { normal | suppress } }
```

```
no radius accounting { ip remote-address list-id list_id | interim [ interval-timeout ] }
```

```
interim { interval-timeout timeout | normal | suppress }
```

**interval-timeout** *timeout*: Indicates the time (in seconds) between updates to session counters (log file on RADIUS or AAA event log) during the session. *timeout* must be an integer from 50 to 40000000.



### Caution

Interim interval settings received from the RADIUS server take precedence over this setting on the system. While the low limit of this setting on the system is a minimum of 50 seconds, the low limit setting on the RADIUS server can be as little as 1 second. To avoid increasing network traffic unnecessarily and potentially reducing network and system performance, do not set this parameter to a value less than 50 on the RADIUS server.

**normal**: If RADIUS accounting is enabled, sends this Acct-Status-Type message when required by normal operation

**suppress**: If RADIUS accounting is enabled, suppresses the sending of this Acct-Status-Type message.

### **ip remote-address list-id** *list\_id*

Specifies the identification number of the IP address list to use for the subscriber for remote address-based accounting.

*list\_id*: Specifies the RADIUS accounting remote IP address list identifier for remote-address accounting for the subscriber. *list\_id* must be an integer from 1 through 65535.

This command is used as part of the Remote Address-based accounting feature and associates the subscriber with a list of remote addresses. Remote address accounting data is collected each time the subscriber communicates with any of the addresses specified in the list.

Remote address lists are configured using the **list** keyword in the **radius accounting ip remote-address** command in the Context Configuration mode.

**mode { session-based | access-flow-based { none | auxiliary-flows | all-flows | main-a10-only } }**

Default: **session-based**

Specifies if the radius accounting mode is either session-based or access-flow-based.

**session-based**: configures session-based RADIUS accounting behavior for the subscriber - which means a single radius accounting message generated for the subscriber session not separate accounting messages for individual A10 connections or flows.

**access-flow-based**: configures access-flow-based RADIUS accounting behavior for the subscriber. This offers flexibility by generating separate accounting messages for flows and A10 sessions.

- **all-flows**: Generates separate RADIUS accounting messages per access flow. Separate accounting messages are not generated for data path connections. (For example, separate messages are not sent for the main A10 or auxiliary connections.)
- **auxiliary-flows**: Generates RADIUS accounting records for the main data path connection and for access-flows for all auxiliary data connections. (For example, separate RADIUS accounting messages are generated for the main A10 session and for access-flows within auxiliary A10 connections. The main A10 session accounting does not include octets or other accounting information from the auxiliary flows.)
- **main-a10-only**: Configures access-flow-based single accounting messages (for example only single start/interim/stop) are generated for the main A-10 flows only.
- **none**: Generates separate RADIUS accounting messages for all data path connections (for example, PDSN main or auxiliary A10 connections) but not for individual access-flows. This is essentially A10 connection-based accounting.

**start { normal | suppress }**

**normal**: If RADIUS accounting is enabled, sends this Acct-Status-Type message when required by normal operation

**suppress**: If RADIUS accounting is enabled, suppresses the sending of this Acct-Status-Type message.

**stop { normal | suppress }**

**normal**: If RADIUS accounting is enabled, sends this Acct-Status-Type message when required by normal operation

**suppress**: If RADIUS accounting is enabled, suppresses the sending of this Acct-Status-Type message.

**no**

**ip remote-address list-id *list\_id***: Deletes the entry for the specified *list\_id*.

**interim [ interval-timeout ]**: Disables the interim interval setting.

### Usage Guidelines

Use this command to allow a per-domain setting for the RADIUS accounting.

**Example**

Set the accounting interim interval to one minute (60 seconds) for all sessions that use the current subscriber configuration:

```
radius accounting interim interval-timeout 60
```

Do not send RADIUS interim accounting messages:

```
radius accounting interim suppress
```

Sets the accounting message start normal for main A-10 flows only.

```
radius accounting mode main-a10-only start normal
```

# radius group

Applies a RADIUS server group at the subscriber level for AAA functionality.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
radius group group_name  
{ default | no } radius group
```

**radius group\_name**

Specifies the name of the server group that is used for authentication and/or accounting for the specific subscriber. *group\_name* must be an alphanumeric string of 1 through 63 characters. It must have been preconfigured within the same context of subscriber.

**default**

Sets or restores the default RADIUS server group specified at the context level or in the default subscriber profile.

**no**

Disables the applied RADIUS group for specific subscriber.

---

**Usage Guidelines**

This feature provides the RADIUS configurables under radius group node. Instead of having a single list of servers per context, this feature configures multiple server groups within a context and applies individual RADIUS server group for subscriber in that context. Each server group consists of a list of AAA servers.

IF no RADIUS group is applied for this subscriber or the default subscriber profile, the default server group available at context level is used for accounting and authentication of the subscriber.

**Example**

Following command applies a previously configured RADIUS server group named *star1* to a subscriber within the specific context:

```
radius group star1
```

Following command disables the applied RADIUS server group for the specific subscriber.

```
no radius group
```

# radius returned-framed-ip-address

Sets the policy whether or not to reject a call when the RADIUS server supplies 255.255.255.255 as the framed IP address and the MS does not supply an address.

---

**Product** GGSN

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description** **radius returned-framed-ip-address 255.255.255.255-policy** {  
**accept-call-when-ms-ip-not-supplied** | **reject-call-when-ms-ip-not-supplied**  
}

**default radius returned-framed-ip-address 255.255.255.255-policy**

## **accept-call-when-ms-ip-not-supplied**

Accepts calls when the RADIUS server supplies framed IP address as 255.255.255.255 and the MS does not supply an address.

## **reject-call-when-ms-ip-not-supplied**

Rejects calls when the RADIUS server supplies framed IP address as 255.255.255.255 and the MS does not supply an address.

## **default**

Sets the policy to its default of rejecting calls when the RADIUS server supplies framed IP address as 255.255.255.255 and the MS does not supply an address.

---

**Usage Guidelines** Use this command to set the behavior for the current subscriber when the RADIUS server supplies 255.255.255.255 as the framed IP address and the MS does not supply an address.

## **Example**

The following command sets the subscriber profile to reject calls when the RADIUS server supplies framed IP address as 255.255.255.255 and the MS does not supply an address:

```
radius returned-framed-ip-address 255.255.255.255-policy  
reject-call-when-ms-ip-not-supplied
```

# radius rulebase-format

This command enables/disables the Rulebase Concatenation feature at subscriber level. This feature is used to merge the prepaid attribute and SN1-Rulebase as a new rulebase and then apply the new rulebase to the session. If the Rulebase Concatenation feature is not enabled, the last received rulebase is applied to the session.



## Important

This command is license dependent. For more information, contact your Cisco account representative.

## Product

GGSN  
PDSN  
P-GW

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

**radius rulebase-format** { **custom1** | **standard** }

**default radius rulebase-format standard**

### default

Disables the Rulebase Concatenation feature. The default setting is **standard**.

### custom1

Specifies the rulebase as a custom value derived from multiple RADIUS attributes in the RADIUS Access-Accept response message.

### standard

Specifies the rulebase as a single attribute value as obtained in RADIUS Access-Accept response message. This is the default setting.

## Usage Guidelines

Currently, the Wireless Mobile Private Network (MPN) configures a dedicated rulebase per service. The Enterprise that utilizes this service has the rulebase per subscriber in 3G or signaled from AAA server with SN1-Rulebase attribute. In the case of a prepaid service, the rulebase name will be the customer-specific prepaid policy attribute received from the AAA server.

When both the RADIUS attributes are received, the last received attribute is considered and applied to the subscriber session. This CLI command is used to merge prepaid attribute and SN1-Rulebase as a new rulebase and then apply the new rulebase to the session on the gateway.



**Important**

Rulebase Concatenation is a customer-specific feature and it requires a valid license to enable the feature. For more information, contact your Cisco account representative.

In 18 and earlier releases, rulebase was a single attribute value as obtained in the RADIUS Access-Accept response message. That is, only one rulebase can be applied with either SN1-Rulebase AVP or customer-specific prepaid policy AVP, whichever comes last.

In 19 and later releases, when both the attributes are received, the rulebase name will be a concatenation of the attributes as received in the Access-Accept response message. If only one of the attributes is received, the current behavior is applicable i.e. the last received attribute will be selected as the rulebase and it will be applied to the session.

If the concatenated rulebase is not matching with the rulebase configured on the gateway, and/or if both the attributes are present more than once, then the session is rejected.

This feature implementation helps the MPN to customize the rulebase and combine prepaid service with additional services like Service Based Access (SBA).

**Example**

The following command merges the RADIUS attributes and installs the new concatenated rulebase.

```
radius rulebase-format custom1
```

# rohc-profile-name

Identifies the robust header compression (RoHC) profile configuration that will be applied to bearer sessions belonging to this subscriber.

---

**Product** HSGW  
PDSN

---

**Privilege** Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration  
**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description** **rohc-profile-name** *name*

## *name*

Specifies the name of the RoHC profile that the system will use to apply header compression and decompression parameters to bearer session data for this subscriber. *name* must be an existing RoHC profile expressed as an alphanumeric string of 1 through 63 characters.

---

**Usage Guidelines** Use this command to specify a RoHC configuration profile to be applied to bearer sessions belonging to this subscriber. RoHC profiles are configured through the Global Configuration Mode using the **rohc-profile** command.

## Example

The following command specifies that the RoHC profile named *rohc-cfg1* is to be applied to all bearer sessions belonging to this subscriber:

```
rohc-profile-name rohc-cfg1
```

# secondary ip pool

Specifies a secondary IP pool to be used as backup pool for Network Address Translation (NAT).

**Important**

This command requires the purchase and installation of a license. Please contact your Cisco sales representative for more information.

**Product**

NAT

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

**Syntax Description**

**secondary ip pool** *pool\_name*

**no secondary ip pool**

**no**

Removes the previous secondary IP pool configuration.

**secondary ip pool** *pool\_name*

Specifies the secondary IP pool name.

*pool\_name* must be an alphanumeric string of 1 through 31 characters.

**Usage Guidelines**

Use this command to configure a secondary IP pool for NAT subscribers, which is not overwritten by the RADIUS supplied list. The secondary pool will be appended to the RADIUS supplied IP pool list or subscriber template provided IP pool list, as applicable, during call setup.

**Example**

The following command configures a secondary IP pool named *test123*:

```
secondary ip pool test123
```

# send-destination-pgw

Configures how the HSGW selects a P-GW address for the "Destination-PGW" AVP.

---

**Product**

HSGW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

**send-destination-pgw** { **all** | **explicit-only** | **implicit-only** }

**no send-destination-pgw**

**no**

Removes the configuration for this command.

**all**

P-GW address is obtained either by explicit or implicit mechanism.

**explicit-only**

The UE performs LCP/PPP procedures, and attaches with a specific APN. The HSGW queries the AAA over the STa interface and receives a MIP6-Agent-Info AVP that includes a sub AVP of Destination-Host. The HSGW copies the value of the Destination-Host AVP in the Destination-PGW AVP which is sent in the CCR-I to the PCRF.

**implicit-only**

The UE performs LCP/PPP procedures, and attaches with a specific APN. The AAA does not return the P-GW to use, so the HSGW performs NAPTR procedures to determine the P-GW which will be used.

---

**Usage Guidelines**

Use this command to configure how the HSGW selects a P-GW address for the "Destination-PGW" AVP. This AVP is sent over Gxa to the PCRF.

**Example**

Configures the HSGW to select either implicit or explicit selection method.

```
send-destination-pgw all
```

# simultaneous

Enables or disables the simultaneous use of both Mobile and Simple IP services.

---

**Product**

PDSN  
FA  
HA  
ASN-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**

[ **no** ] **simultaneous simple-and-mobile-ip**

**no**

Disables the simultaneous use.

---

**Usage Guidelines**

Subscribers with mobile devices that concurrently support mobile and simple IP services require this option to be set.

**Example**

The following command enables simultaneous use of both Simple and Mobile IP services:

```
simultaneous simple-and-mobile-ip
```

# timeout absolute

Configures the maximum duration of the session before the system automatically terminates the session.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**timeout absolute** *seconds*

{ **default** | **no** } **timeout absolute**

### **default | no**

Indicates the timeout specified is to be returned to its default behavior. If a timeout value is not specified, all timeouts are set to their default values.

### **timeout absolute**

Default: 0

Specifies the absolute maximum time a session may exist (in seconds) in any state (active or dormant).

### **seconds**

Specifies the maximum amount of time (in seconds) before the specified timeout action is activated. *seconds* must be an integer from 0 through 4294967295. The special value 0 disables the timeout specified.

---

## Usage Guidelines

Use this command to set the absolute maximum time a session may exist in any state.

### **Example**

The following command configures the absolute maximum timeout to 18000 seconds (300 minutes):

```
timeout absolute 18000
```

# timeout idle

Configures the idle timeout duration for the long duration timer associated with a subscriber session.

**Product** All

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

## Syntax Description

**timeout idle** *idle\_dur* [ **micro-checkpoint-deemed-idle** [ *time\_in\_seconds* ] | **micro-checkpoint-periodicity** *time\_in\_seconds* ]

{ **default** | **no** } **timeout idle**

### default | no

Indicates the timeout specified is to be returned to its default behavior. If no specific timeout is specified, then all are set to their default behavior.

### timeout idle

Default: 0

Specifies the maximum duration of the session (in seconds) can remain idle before the system automatically terminates the session due to inactivity.

### idle\_dur

Specifies the maximum amount of time (in seconds) before the specified timeout action is activated. *idle\_dur* must be an integer from 0 through 2147483647. The special value 0 disables the timeout specified.

### micro-checkpoint-deemed-idle *time\_in\_seconds*

Configures micro-checkpoint duration when UE transitions from Idle to Active and vice versa. *time\_in\_seconds* must be an integer from 10 through 1000. Default: 180.



### Important

Micro-checkpoint-deemed-idle value should be less than idle timeout value.

### micro-checkpoint-periodicity *time\_in\_seconds*

Configures periodic idle seconds micro checkpoint timer on a per-subscriber basis. Idle seconds micro checkpoints are sent at the configured regular intervals to the standby chassis; otherwise, they are sent at intervals of 10 seconds, which is the default value. *time\_in\_seconds* must be an integer value in the range from 10 through 10000. Default: 10.

**Important**

Micro-checkpoint-periodicity value should be less than idle timeout value.

**Usage Guidelines**

Use this command to set the idle time duration, micro-checkpoint-deemed-idle and micro-checkpoint-periodicity timer for a subscriber session to identify a dormant session.

**Important**

On the fly change from **micro-checkpoint-deemed-idle** to **micro-checkpoint-periodicity**, and vice-versa, is not supported.

**Example**

The following command sets the idle timeout duration to 60 seconds:

```
timeout idle 60
```

The following command sets the idle timeout duration to 20 seconds and micro-checkpoint-deemed-idle to 15 seconds:

```
timeout idle 20 micro-checkpoint-deemed-idle 15
```



# timeout long-duration

Configures the long duration timeout and optionally the inactivity duration of HA subscriber session.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
timeout long-duration ldt_timeout [ inactivity-time inact_timeout ]
[ no | default ]timeout long-duration
```

**no**

Indicates the timeout specified is to be returned to its default behavior. If no specific timeout is specified then all are set to their default behavior.

**long-duration** *ldt\_timeout*

Default: 0

Designates the maximum duration of the session (in seconds) before the system automatically reports/terminates the session.

*ldt\_timeout* must be a value in the range from 0 through 4294967295. The special value 0 disables the timer.

**inactivity-time** *inact\_timeout*

Specifies the maximum amount of time (in seconds) before the specified session is marked as dormant.

*inact\_timeout* must be a value in the range from 0 through 4294967295. The special value 0 disables the inactivity time specified.

---

**Usage Guidelines**

Use this command to set the long duration timeout period and inactivity timer for subscriber sessions. Reduce the idle timeout to free session resources faster for use by new requests.

Refer to the **long-duration-action detection** and **long-duration-action disconnection** commands for more information.

**Example**

The following command sets the long duration timeout duration to 300 seconds and inactivity timer for subscriber session to 45 seconds:

```
timeout long-duration 300 inactivity-time 45
```

## tpo policy

The Traffic Performance Optimization (TPO) in-line service is not supported in this release.

# tunnel address-policy

Specifies the policy for address allocation and validation for all tunneled calls (IP-IP, IP-GRE) except L2TP calls. With this command enabled, GGSN IP address validation could be disabled for specified incoming calls.

For GGSN systems, this command can also be specified in the APN Configuration mode (**tunnel address-policy**) which would mean the system defers to the old **l3-to-l2-tunnel address policy** command for calls coming through L2TP tunnels.

---

**Product**

PDSN

GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

```
configure > context context_name > subscriber { default | name subscriber_name }
```

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
tunnel address-policy { alloc-only | alloc-validate | no-alloc-validate }
```

```
default tunnel address-policy
```

**alloc-only**

Allocates IP addresses locally without validation.

**alloc-validate**

Default.

The VPN Manager allocates and validates all incoming IP addresses from a static pool of IP addresses.

**no-alloc-validate**

No IP address assignment or validation is done for calls coming in via L3 tunnels. Incoming static IP addresses are passed. This option allows for the greatest flexibility.

**default**

Resets the tunnel address-policy to **alloc-validate**.

---

**Usage Guidelines**

This command supports scalable solutions for Corporate APN deployment as many corporations handle their own IP address assignments. In some cases this is done to relieve the customer or the mobile operators from the necessity of reconfiguring the range of IP addresses for the IP pools at the GGSN.

**Example**

The following command resets the IP address validation policy to validate against a static pool of address:

```
default tunnel address-policy
```

The following command disables IP address validation for calls coming through tunnels:

```
tunnel address-policy no-alloc-validate
```

# tunnel ipip

Configures IP-in-IP tunnelling parameters for the current subscriber.

---

## Product

PDSN  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

## Syntax Description

**tunnel ipip peer-address** *peer\_address* **local-address** *local\_addr* ]  
**no tunnel ipip**

**peer-address** *peer\_address*

Specifies the IP address of the external gateway terminating the IP-in-IP tunnel.

**local-address** *local\_addr*

Specifies the IP address of the interface in the destination context originating the IP-in-IP tunnel.

**no**

Disables IP-in-IP tunneling for the current subscriber.

---

## Usage Guidelines

Subscriber IP payloads are encapsulated with IP-in-IP headers and tunneled by the GGSN or PDSN to an external gateway.

### Example

The following command configures the system to encapsulate subscriber traffic using IP-in-IP and tunnel it from a local address of *192.168.1.100* to a gateway with an IP address of *192.168.1.225*:

```
tunnel ipip peer-address 192.168.1.225 local-address 192.168.1.100  
preference 1
```

# tunnel ipsec

Configures sessions for the current subscriber to use an IPSec tunnel based on the IP pool corresponding to the subscriber's assigned IP address.

---

## Product

PDSN  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure > context *context\_name* > subscriber { default | name *subscriber\_name* }**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

## Syntax Description

**tunnel ipsec use-policy-matching-ip-pooler-address**

**no tunnel ipsec use-policy-matching-ip-pooler-address**

**no**

Disables the use of the IPSec policy that matches the IP pool that the assigned IP address relates to.

---

## Usage Guidelines

Use this command to set the current subscribers sessions to use an IPSec policy that is assigned to the IP pool that the subscribers assigned IP address relates to.

### Example

The following command enables the use of the policy that matches the IP pool address:

```
tunnel ipsec use-policy-matching-ip-pooler-address
```

# tunnel l2tp

Configures L2TP tunnel parameters for the subscriber.

---

**Product**

All products supporting L2TP

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Subscriber Configuration

**configure** > **context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber)#
```

---

**Syntax Description**

```
tunnel l2tp [ peer-address ip address [ [ encrypted ] [secret secret] ] [ preference number] [ tunnel-context context ] [ local-address ip_address ] [ crypto-map map_name { [ encrypted ] isakmp-secret secret } ] ]
no tunnel l2tp [ peer-address ip_address ]
```

**peer-address** *ip\_address*

A peer L2TP Network Server (LNS) associated with this LAC (L2TP Access Concentrator). *ip\_address* must be an IP address entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal format.

**[ encrypted ] secret** *secret*

Specifies the shared key (secret) between the L2TP Network Server (LNS) associated with this LAC (L2TP Access Concentrator). *secret* must be an alphanumeric string of 1 through 63 characters that is case sensitive.

**encrypted**: Specifies the encrypted shared key between the L2TP Network Server (LNS) associated with this LAC (L2TP Access Concentrator). *secret* must be an alphanumeric string of 1 through 128 characters that is case sensitive.

The **encrypted** keyword is intended only for use by the system while saving configuration scripts. The system displays the encrypted keyword in the configuration file as a flag that the variable following the **secret** keyword is the encrypted version of the plain text secret. Only the encrypted secret is saved as part of the configuration file.

**preference** *number*

Default: 1

Specifies the order in which a group of tunnels configured for this subscriber will be tried. *number* must be an integer from 1 through 65535.

**tunnel-context** *context*

Specifies the name of the context containing ports through which this subscriber's data traffic is to be communicated between this LAC and the LNS. *context* must be an alphanumeric string of 1 through 79 characters.

**local-address *ip\_address***

Specifies a LAC service bind address which is given as a hint that is used to select a particular LAC service. *ip\_address* must be an IP address entered using IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.

**crypto-map *map\_name* { [encrypted] isakmp-secret *secret* }**

Specifies the name of a crypto map that has been configured in the current context. *map\_name* must be an alphanumeric string from 1 to 127 alphanumeric characters.

**isakmp-secret *secret***: Specifies the pre-shared key for the Internet Key Exchange (IKE). *secret* must be an alphanumeric string of 1 through 127 characters.

**encrypted isakmp-secret *secret***: Specifies the pre-shared key for IKE. Encryption must be used when sending the key. *secret* must be an alphanumeric string of 1 through 127 characters.

**no**

Disables tunneling for the current subscriber. When peer-address is included, the tunneling for that specific L2TP Network Server (LNS) is disabled but tunneling to other configured LNSs is still enabled.

---

**Usage Guidelines**

Use this command to configure specific L2TP tunneling parameters for the current subscriber.

**Example**

To specify L2tp tunneling to the LNS peer at the IP address *198.162.10.100* with a shared secret of *bigco* and preference of *1*, enter the following command:

```
tunnel l2tp peer-address 198.162.10.100 secret bigco preference 1
```



## w-apn

This command allows you to configure the default APN to be used for the UE connections when the AAA server does not return the subscriber APN name in the service-selection AVP in RADIUS Access-Accept message.

---

**Product**

eWAG

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; Subscriber Configuration

**configure > context** *context\_name* > **subscriber** { **default** | **name** *subscriber\_name* }

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-subscriber) #
```

---

**Syntax Description**
**w-apn** *apn\_name***no w-apn****no**

If previously configured, removes the specified configuration.

**apn-name** *apn\_name*

Specifies the APN name.

*apn\_name* must be the name of an APN and must be a string of 1 to 62 characters in length consisting of alphabetic characters (A-Z and a-z), digits (0-9), dot(.) and the dash (-).

---

**Usage Guidelines**

Use this command to configure the default APN to be used for UE connections when the AAA server does not return the subscriber APN name in the Service-Selection AVP in RADIUS Access-Accept message. This APN will be considered as the network to which the UE is connecting and used in the CPC request message towards GGSN.

**Example**

The following command configures an APN named *apn123*:

```
w-apn apn123
```





# TACACS+ Configuration Mode Commands



## Important

TACACS Configuration Mode is available in releases 11.0 and later.

## Command Modes

This chapter describes all commands available in the TACACS+ Configuration Mode. TACACS+ (Terminal Access Controller Access-Control System Plus) is a secure, encrypted protocol. By remotely accessing TACACS+ servers that are provisioned with the administrative user account database, the ASR 5500 support TACACS+ accounting and authentication services for system administrative users.

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-tacacs) #
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [accounting](#), on page 900
- [authorization](#), on page 901
- [do show](#), on page 902
- [end](#), on page 903
- [exit](#), on page 904
- [idle-session threshold](#), on page 905
- [max-sessions](#), on page 906
- [on-authen-fail](#), on page 907
- [on-network-error](#), on page 908
- [on-unknown-user](#), on page 909
- [priv-lvl](#), on page 911
- [rem\\_addr client-ip](#), on page 913
- [server](#), on page 914
- [user-id](#), on page 917

# accounting

Enables the recording of the start and the stop time each command issued during a TACACS+-authenticated CLI session.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description** [ no ] **accounting** { **command** | **start-stop** }

**no**

Disables a specified TACACS+ accounting setting.

**command**

Enables accounting on a command-by-command basis. The TACACS+ server is contacted prior to the execution of the command and the command which is about to be executed is recorded. Only commands which are valid for the user privilege and context (mode) in which they are about to be executed will be recorded. StarOS does not record whether the command itself succeeded or failed. For security reasons, some secure or restricted commands are not recorded. In such cases, the accounting record will record the command as three asterisks ("\*\*\*").

**start-stop**

Records the time at which the session starts (the time at which the user passes authentication) and the time at which the user exits. If a user exits before passing authentication, only a stop time is recorded.

---

**Usage Guidelines** Use this command to configure the accounting method for TACACS+-based CLI sessions.




---

**Important** *For releases after 15.0 MR4, TACACS+ accounting (CLI event logging) will not be generated for Lawful Intercept users with privilege level set to 15 and 13.*

---

**Example**

The following command enables TACACS+ accounting for commands:

```
accounting command
```

# authorization

Enables the authorization of TACACS+ CLI users on a command-by-command, command + command argument, or command prompt basis. If the user is not authorized to execute the command, the command will fail.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description**

```
[ no ] authorization { arguments | command | prompt }
```

**no**

Disables a specified TACACS+ authorization type.

**arguments**

Enables per-command and command + argument authorization. The TACACS+ server authorizes each command and its arguments for the user. If the user is not authorized to execute the command and the corresponding arguments, the command fails. If the command does not contain any arguments, then the command only is passed to the authorization server.

**command**

Enables per-command authorization. The TACACS+ server is contacted for each command and each command is authorized for the user. If the user is not authorized to execute the command, then the command fails. If the user is authorized for the command, the command is executed.

**prompt**

Enables per-command authorization, as described for the **command** option above. However, since commands may be duplicated in different CLI modes, this version of the command authorization also passes the command prompt string to the server. The TACACS+ server is contacted for each prompt and command and must have a matching string for the prompt/command combination. Enabling **prompt** authorization supersedes **command** authorization, since the prompt and command must be authorized together.

---

**Usage Guidelines**

Use this command to configure the authorization method for TACACS+-based CLI sessions.

**Example**

The following command requires per-command TACACS+ authorization:

```
authorization command
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.



# idle-session threshold

Configures the idle session threshold available for TACACS+ sessions.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description**

```
idle-session threshold number user-id tacacs_userid  
default idle-session threshold user-id tacacs_userid
```

**threshold *number***

Configures the idle sessions threshold value in minutes. If a session is idle, the CLI flags it as being in an idle state when it has been inactive for a specific amount of time. *number* specifies the idle-session threshold number in minutes. This setting must be an alphanumeric integer from 0 to 10 minutes. The default value is 5 minutes. 0 indicates that there is no idle session threshold for the user. When a CLI session has reached the threshold, then the session is in the idle state but it will not be in the idle state indefinitely.

**user-id *tacacs\_userid***

Identifies a valid TACACS+ user as an alphanumeric string of 1 through 144 characters.

**default *tacacs\_userid***

Configures the default number for idle sessions to 5 minutes.

---

**Usage Guidelines**

Use this command to configure the idle session threshold in minutes for a specific TACACS+ user.

The default value of 5 minutes is used if the idle-session threshold is not configured for a user.

After upgrading to 21.2.0, the default maximum sessions number is assigned to all users. After downgrading to a previous release, the maximum sessions configuration is lost.

While using the **user-id TACACS+ Configuration Mode** command without the **idle session threshold** command, the system will keep the existing configured value or the default value if nothing is configured.

**Example**

The following command configures the threshold for this user to be 5 minutes:

```
idle-session threshold 5 user-id admin
```

# max-sessions

Configures the maximum number of sessions available for a TACACS+ user.

---

## Product

All products

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

## Syntax Description

**max-sessions** *number* **user-id** *tacacs\_userid*  
**default max-sessions** **user-id** *tacacs\_userid*

### **number**

Specifies the maximum number of simultaneous CLI sessions. It must be alphanumeric integer from 0 to 100. The default number is 100.

### **user-id tacacs\_userid**

Identifies a valid TACACS+ user as an alphanumeric string of 1 through 144 characters.

### **default**

Configures the default number of simultaneous CLI sessions to 100.

---

## Usage Guidelines

Use this command to configure the maximum number of sessions available for a TACACS+ user.

After upgrading to 21.2.0, the default maximum sessions number is assigned to all users. After downgrading to a previous release, the maximum sessions configuration is lost.

### **Example**

The following command configures 50 CLI sessions for a specific TACACS user:

```
max-sessions 50 user-id admin
```

The following command configures 100 CLI sessions for a specific TACACS user:

```
default max-sessions user-id admin
```

# on-authen-fail

Defines system behavior when an administrative login fails due to a TACACS+ authentication failure. This command also can be used to configure system behavior separately for TACACS+ authentication failures for administrative users accessing the system via the StarOS Console port.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > TACACS+ Configuration  
**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description** **on-authen-fail { continue | stop } [ tty console ]**

## **continue**

After a TACACS+ authentication failure, the system will continue with authentication using non-TACACS+ authentication services.

## **stop**

After a TACACS+ authentication failure, the system forces the failed TACACS+ user to exit.

## **tty console**

*Release 12 and later systems only:* Used after the **stop** or **continue** parameters to specify system behavior for users being authenticated via the StarOS Console port:

- **stop tty console:** Forces the failed TACACS+ user to exit.
- **continue tty console:** The system will continue with authentication using non-TACACS+ authentication services.

---

**Usage Guidelines** Use this command to configure system behavior for users that fail TACACS+ authentication.

## **Example**

The following command instructs the system to stop upon TACACS+ authentication failure:

```
on-authen-fail stop
```

## on-network-error

Configures StarOS behavior when a TACACS+ login fails due to a network error. This command also can be used to configure system behavior separately for TACACS+ network error login failures for administrative users accessing the system via the Console port.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > TACACS+ Configuration  
**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description** `on-network-error { continue | stop } [ tty console ]`

### **continue**

The system will continue with authentication using non-TACACS+ authentication services.

### **stop**

The system forces the failed TACACS+ user to exit.

### **tty console**

*Release 12 and later systems only:* Can be used after the **continue** or **stop** options to specify system behavior for TACACS+ CLI users being authenticated via the StarOS Console port:

- **stop tty console:** Forces the failed user to exit when authentication fails.
- **continue tty console:** The system will continue with authentication using non-TACACS+ authentication services.

---

**Usage Guidelines** Use this command to configure system behavior for users who fail TACACS+ authentication due to a network error.

### **Example**

The following command configures the system to stop when a TACACS+ login fails due to a network error:

```
on-network-error stop
```

# on-unknown-user

Configures StarOS behavior when a TACACS+ server cannot authenticate a given user name. This command also can be used to configure system behavior separately for TACACS+ unknown user login failures for administrative users accessing the system via the StarOS console port.



## Important

Some TACACS+ server implementations will not send a Reply message indicating that the user name is invalid. Instead, these types of implementations will accept the username, whether valid or not, and then examine the username and password in combination before sending a Reply message indicating a failed TACACS+ login. In these cases, specifying **on-unknown-user** will continue the login process. To avoid this scenario, determine the method the configured TACACS+ servers will use to validate user names before deciding whether specifying the **on-unknown-user** command will provide the desired result.

## Product

All

## Privilege

Security Administrator, Administrator

## Command Modes

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs) #
```

## Syntax Description

**on-unknown-user { continue | stop } [ tty console ]**

### continue

The system will continue with authentication using non-TACACS+ authentication services.

### stop

The system forces the failed TACACS+ user to exit.

### tty console

**Release 12 and later systems only:** Can be used after the **continue** or **stop** options to specify the behavior of the system for TACACS+ CLI users being authenticated via the StarOS console port.

- **stop tty console:** The system forces the failed user to exit when authentication fails.
- **continue tty console:** The system will continue with authentication using non-TACACS+ authentication services.

## Usage Guidelines

Use this command to configure StarOS behavior for users who fail TACACS+ user name authentication.

TACACS+ authentication is also performed on non-local VPN context logins, if TACACS+ is configured and enabled. If TACACS+ is enabled with the **on-unknown-user stop** option, the VPN context name into which the user is attempting a login must match the VPN name specified in the username string. If the context name does not match, the login fails and exits out.

**Example**

The following command forces users who fail TACACS+ user name authentication to exit StarOS:

```
on-unknown-user stop
```

# priv-lvl

Configures authorized StarOS privileges for a specified TACACS+ privilege level.

---

**Product**

All products

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description**

```
priv-lvl lvl_number authorization-level { administrator | inspector | operator | security-admin } [ cli | ecs | ftp | li-administration | nocli | noecs | noftp | nocli-administration ]
```

***lvl\_number***

Specifies the TACACS+ privilege level with which StarOS authorizations will be associated. as an integer from 1 through 15.

**authorization-level { administrator | inspector | operator | security-admin }**

Specifies the StarOS administrative authorization level for this privilege level.

- **administrator** – Allows user to execute Administrator level configuration commands.
- **inspector** – Allows user to execute Inspector commands.
- **operator** – Allows user to execute Operator commands.
- **security-admin** – Allows user to execute Security Administrator commands

For detailed information about StarOS administration levels, refer to the *System Settings* chapter of the *System Administration Guide*.

**[ cli | ecs | ftp | li-administration | nocli | noecs | noftp | nocli-administration ]**

Specifies a set of access privileges or restrictions for this TACACS+ privilege level. Multiple options may be specified.

- **cli** – Permits access to the StarOS command line interface.
- **ecs** – Permits access to Enhanced Charging Services (ECS) commands.
- **ftp** – Permits of File Transfer Protocol (FTP).
- **li-administration** – Permits access to Lawful Intercept (LI) administrative commands.
- **nocli** – Denies access to the StarOS CLI.
- **noecs** – Denies access to ECS commands
- **noftp** – Denies use of FTP.
- **nocli-administration** – Denies access to StarOS Administrator and Security Administrator commands.

---

**Usage Guidelines**

Use this command to customize StarOS access authorization for users at various TACACS+ privilege levels.

**Example**

The following command sequence authorizes a TACACS+ priv-level 13 user to execute StarOS Administrator commands but denies access to LI administrative commands and FTP.

```
priv-lvl 13 authorization-level administrator cli noftp
```



# rem\_addr client-ip

Sends a remote client IPv4 address field in the TACACS+ protocol for use by a Cisco Secure ACS server.

---

**Product**

All products

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

**Syntax Description**

```
[ default | no ] rem_addr client-ip
```

**default**

Disables the sending of a remote client IP address field to a Cisco Secure ACS server for a TACACS+ login request.

**no**

Disables the sending of a remote client IP address field to a Cisco Secure ACS server for a TACACS+ login request.

---

**Usage Guidelines**

A Cisco Secure ACS server can be configured to explicitly check the NAS source address for TACACS+ connections. StarOS may not properly set the rem\_addr field in the TACACS+ protocol packet when initiating a connection with the Cisco Secure ACS server. This may cause the Cisco Secure ACS server to reject the TACACS+ login request.



---

**Important**

The default behavior is to not fill in the rem\_addr field.

---

This CLI command enables the setting and sending of the remote address to the IPv4 address associated with the local context management interface for customers who require this field to be verified via the Cisco Secure ACS server.

When enabled the rem\_addr field contains the ssh client IP address in ASCII form. If the IP address cannot be retrieved, the length is set to zero.

**Example**

The following command enables the sending of the rem\_addr field to a Cisco Secure ACS server for a TACACS+ login request:

```
rem_addr client-ip arg1
```

## server

Configures TACACS+ AAA service-related parameters for use in authenticating StarOS administrative users via a TACACS+ server.



### Important

Once a TACACS+ server is configured with the **server** command, TACACS+ AAA services for StarOS must be enabled using the **aaa tacacs+** command in Global Configuration mode.

### Product

All

### Privilege

Security Administrator, Administrator

### Command Modes

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

### Syntax Description

```
server priority priority_number ip-address ip_address [ { encrypted password
shared_secret ] [ key text_password ] [ nas-source-address ip_address ] [ password
text_password ] [ port port_number ] [ retries num_retries ] [ service {
accounting | authentication | authorization } ] ] [ timeout seconds ]
no server priority priority_number
```

**no**

Removes a specified server (by priority number) from the TACACS+ server list.

#### **priority** *priority\_number*

Specifies the order in which TACACS+ servers are to be tried. The priority number corresponds to a configured TACACS+ server.

*For releases prior to 18.2, priority\_number can be an integer from 1 (highest priority) to 3 (lowest priority).*

*For releases 18.2+, priority\_number can be an integer from 1 (highest priority) to 4 (lowest priority).*

If no server with priority 1 is specified, the next highest priority is used. If the specified priority matches that of a TACACS+ server already configured, any previously defined server configuration parameter(s) for that priority are returned to the default setting(s).

#### **ip-address**

Specifies the IP address of the TACACS+ server in IPv4 or IPv6 dotted-decimal notation. Only one IP address can be defined for a given **server priority**

#### **encrypted password** *shared\_secret*

Specifies the encrypted value of the shared secret key. The server-side configuration must match the decrypted value for the protocol to work correctly. If **encrypted password** is specified, specifying **password** is invalid.

No encryption is used if this value is null (""). The encrypted password can be an alphanumeric string of 1 through 100 characters. If neither an **encrypted password** or **password** is specified, StarOS will not use encryption

#### **key text\_password**

**Release 11.0 systems only.** Instead of using an encrypted password value, the user can specify a plain-text key value for the password. If the **key** keyword is specified, then specifying **encrypted password** is invalid. A null string represents no encryption. The password can be from 1 to 32 alphanumeric characters in length. If neither an **encrypted password** or **key** is specified, then StarOS will not use encryption.

#### **nas-source-address ip\_address**

**Release 12 and later systems only:** Sets the IPv4 or IPv6 address to be specified in the Source Address of the IP header in the TACACS+ protocol packet sent from the NAS to the TACACS+ server. *ip\_address* is entered using IPv4 dotted-decimal notation and must be valid for the interface.

#### **password text\_password**

**Release 12.0 and later systems.** Instead of using an encrypted password value, the user can specify a plain-text value for the password. If the **password** keyword is specified, specifying **encrypted password** is invalid. A null string ("") represents no encryption. The password can be an alphanumeric string of 1 through 32 characters. If neither an **encrypted password** or **password** is specified, then StarOS will not use encryption.

#### **port port\_number**

Specifies the TCP port number to use for communication with the TACACS+ server. *port\_number* can be an integer from 1 through 65535. If a port is not specified, StarOS will use port 49.

#### **retries number**

**Release 12 and later systems only:** Specifies the number of retry attempts at establishing a connection to the TACACS+ server if the initial attempt fails. *retries number* can be an integer from 0 through 100. The default is 3. Specifying 0 (zero) retries results in StarOS trying only once to establish a connection. No further retries will be attempted.

#### **service { accounting | authentication | authorization }**

**Release 12 and later systems only:** Specifies one or more of the AAA services that the specified TACACS+ server will provide. Use of the **service** keyword requires that at least one of the available services be specified. If the **service** keyword is not used, StarOS will use the TACACS+ server for all AAA service types. The default is to use authentication, authorization and accounting. Available service types are:

- **accounting:** The specified TACACS+ server should be used for accounting. If TACACS+ authentication is not used, TACACS+ accounting will not be used. If no accounting server is specified and the user is authenticated, no accounting will be performed for the user.
- **authentication:** The specified TACACS+ server should be used for authentication. If a TACACS+ authentication server is not available, TACACS+ will not be used for authorization or accounting.
- **authorization:** The specified TACACS+ server should be used for authorization. If TACACS+ authentication is not used, TACACS+ authorization will not be used. If no authorization server is specified and the user is authenticated, the user will remain logged in with minimum privileges (Inspector level).

**timeout *seconds***

Specifies the number of seconds to wait for a connection timeout from the TACACS+ server. *seconds* can be an integer from 1 through 1000. If no timeout is specified, StarOS0 will use the default value of 10 seconds.

---

**Usage Guidelines**

Use this command to specify TACACS+ service parameters for a specified TACACS+ server.

**Example**

The following command configures a priority 2, TACACS+ authentication server at IP address 192.156.1.1:

```
server priority 2 ip-address 192.156.1.1 authentication
```

# user-id

Configures additional profile attributes for a specific TACACS+ user identifier.

---

## Product

All products

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > TACACS+ Configuration

**configure > tacacs mode**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tacacs)#
```

---

## Syntax Description

**user-id tacacs\_userid [ li-admin | noli-admin ]**

**[ default ] user-id tacacs\_userid**

**user-id tacacs\_userid**

Identifies a valid TACACS+ user as an alphanumeric string of 1 through 144 characters.

**[ li-admin | noli-admin ]**

Grants or denies access to Lawful Intercept (LI) configuration commands.

**default**

Configures default profile attributes for a specific TACACS+ user identifier.

---

## Usage Guidelines

Use this command to grant LI access to a specified TACACS+ user identifier.

After upgrading to 21.2.0, the default maximum sessions number is assigned to all users. After downgrading to a previous release, the maximum sessions configuration is lost.

### Example

The following command sequence grants TACACS+ user *victor134* access to LI administration commands:

```
user-id victor134 li-admin
```

user-id



## Telnet Configuration Mode Commands

The Telnet Configuration Mode is used to manage the telnet server options for the current context.

### Command Modes

Exec > Global Configuration > Context Configuration > Telnet Configuration

**configure** > **context** *context\_name* > **server telnet**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-telnetd) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



### Caution

For maximum system security, you should not enable telnet functionality. SSH is the recommended remote access protocol. In release 20.0 and higher Trusted StarOS builds, telnet is not supported.

- [do show](#), on page 920
- [end](#), on page 921
- [exit](#), on page 922
- [max servers](#), on page 923

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---



# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

## max servers

Configures the maximum number of telnet servers that can be started within any 60-second interval. If this limit is reached, the system waits two minutes before trying to start any more servers.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Telnet Configuration

**configure > context *context\_name* > server telnet**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-telnetd) #
```

---

**Syntax Description** **max servers** *count*

***count***

Specifies the maximum number of telnet servers that can be spawned in any 6- second interval. *count* must be an integer from 1 through 100. Default: 40

---

**Usage Guidelines** Use this command to set the number of telnet servers to tune the system response, as a heavily loaded system may need more servers to support the incoming requests.

The converse would be true in that a system can benefit by reducing the number of servers such that telnet services do not cause excessive system impact to other services.

### Example

The following command sets the maximum number of telnet servers to 30:

```
max servers 30
```





## TFTP Configuration Mode Commands

---

The TFTP configuration mode is used to manage the TFTP (Trivial File Transfer Protocol) servers for the current context.

---

### Command Modes

Exec > Global Configuration > Context Configuration > Tunnel TFTP Configuration

**configure** > **context** *context\_name* > **server tftpd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tftpd) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [do show, on page 926](#)
- [end, on page 927](#)
- [exit, on page 928](#)
- [max servers, on page 929](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.



## max servers

Configures the maximum number of TFTP servers that can be started within any 60-second interval. If this limit is reached, the system waits two minutes before trying to start any more servers.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Tunnel TFTP Configuration

**configure > context *context\_name* > server tftpd**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-tftpd)#
```

---

**Syntax Description** **max servers** *count*

***count***

Specifies the maximum number of TFTP servers that can be spawned in any 60-second interval. *count* must be an integer from 1 through 100. Default: 40

---

**Usage Guidelines** Use this command to set the number of servers to tune the system response, as a heavily loaded system may need more servers to support the incoming requests.

The converse would be true in that a system can benefit by reducing the number of servers such that TFTP services do not cause excessive system impact to other services.

### Example

The following command sets the maximum number of TFTP servers to 30:

```
max servers 30
```

**max servers**



# Throttling Override Policy Configuration Mode Commands

Throttling Override Policy mode allows an operator to configure the Throttling Override Policy that can be used at the GGSN/P-GW nodes to selectively bypass throttling for a configured message type or for all messages in emergency call or priority call or call for the configured APN.



## Important

RLF Bypass Feature (enhancement to the GTP Throttling feature), used in the Throttling Override Policy config mode, is a license-controlled feature. A valid feature license must be installed prior to configuring this feature. Contact your Cisco account representative for more information.

## Command Modes

This chapter describes the GTPC Throttling Override Policy Configuration Mode commands.

Exec > Global Configuration > Throttling Override Policy

```
configure > throttling-override-policy policy_name
```

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-throttling-override-policy)#
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 932
- [egress bypass-rlf](#), on page 933
- [end](#), on page 936
- [exit](#), on page 937

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# egress bypass-rlf

Configures message types which can bypass the rate limiting function.

---

## Product

GGSN

P-GW

---

## Privilege

Administrator, Security Administrator

---

## Command Modes

Exec > Global Configuration > Throttling Override Policy

**configure > throttling-override-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-throttling-override-policy)#
```

---

## Syntax Description

```
egress bypass-rlf { ggsn { msg-type { dpc | ipca | nrupc | emergency-call
| arp { 1 | 2 | 3 }+ | apn-names <apn-name1> <apn-name2> <apn-name3> } } |
pgw { msg-type { cbr | dbr | ubr | emergency-call | earp-pl-list {1 | 2
| 3 | 4 | 5 ... | 15 }+ | apn-names <apn-name1> <apn-name2> <apn-name3> }
} }
```

```
default egress bypass-rlf { ggsn { msg-type { dpc | ipca | nrupc |
emergency-call | arp { 1 | 2 | 3 }+ | apn-names <apn-name1> <apn-name2>
<apn-name3> } } | pgw { msg-type { cbr | dbr | ubr | emergency-call |
earp-pl-list {1 | 2 | 3 | 4 | 5 ... | 15 }+ | apn-names <apn-name1>
<apn-name2> <apn-name3> } } }
```

```
no egress bypass-rlf { ggsn { msg-type { dpc | ipca | nrupc |
emergency-call | arp { 1 | 2 | 3 }+ | apn-names <apn-name1> <apn-name2>
<apn-name3> } } | pgw { msg-type { cbr | dbr | ubr | emergency-call |
earp-pl-list {1 | 2 | 3 | 4 | 5 ... | 15 }+ | apn-names <apn-name1>
<apn-name2> <apn-name3> } } }
```

### default

Resets the default attribute values for egress bypass configuration. If an empty throttling-override-policy is created then the default values for all the configurables are zeros/disabled.

### no

Disables the egress bypass rlf throttling configuration.

### ggsn

Configures GGSN specific message types to bypass rlf throttling.

### pgw

Configures P-GW specific message types to bypass rlf throttling

**msg-type**

Configures GGSN or P-GW message type to bypass rlf throttling.

```
ggsn msg-type { dpc | ipca | nrupc | emergency-call | arp { 1 | 2 | 3 }+ | apn-names <apn-name1> <apn-name2> <apn-name3> }
```

Configures GGSN specific message types to bypass rlf throttling. Following are the message types that can be configured:

- **dpc:** Bypasses RLF throttling for network initiated Delete PDP Context message type. By default, dpc is not bypassed.
- **ipca:** Bypasses RLF throttling for network initiated Delete PDP Context message type. By default, dpc is not bypassed.
- **nrupc:** Bypasses RLF throttling for Network Requested Update PDP Context message type. By default, nrupc is not bypassed.
- **emergency-call:** Bypasses rlf throttling for all request messages initiated by GGSN emergency call. By default, emergency-call is NOT bypassed.
- **arp:** Configures Allocation-Retention-Policy (ARP) values associated with priority calls to be bypassed rlf throttling. By default, none of the ARP values are set. This option accepts the PL (Priority Level) values. The outgoing control messages of the calls with specified priority levels will bypass throttling.  
+: More than one of the previous keywords can be entered within a single command.
- **apn-names:** Configures GGSN APN names to bypass rlf throttling. You can configure upto three apn-names.

```
pgw { msg-type { dpc | ipca | nrupc | emergency-call | earp-pl-list { 1 | 2 | 3 | 4 | 5 ... | 15 }+ | apn-names <apn-name1> <apn-name2> <apn-name3> }
```

Configures P-GW specific message types to bypass rlf throttling. Following are the message types that can be configured:

- **cbr:** Bypasses RLF throttling for create-bearer-request message type. By default, cbr is not bypassed.
- **dbr:** Bypasses RLF throttling for delete-bearer-request message type. By default, dbr is not bypassed.
- **ubr:** Bypasses RLF throttling for update-bearer-request message type. By default, ubr is not bypassed.
- **emergency-call:** Bypasses RLF throttling for all request messages initiated by P-GW emergency call. By default, emergency-call is NOT bypassed.
- **earp-pl-list:** Configures the list of Priority Levels(PL) associated with priority calls to be bypassed rlf throttling. By default none of the PLs are set. The outgoing control messages of the calls with specified priority levels will be bypassed throttling.  
+: More than one of the previous keywords can be entered within a single command.
- **apn-names:** Configures P-GW APN names to bypass rlf throttling. You can configure upto three apn-names.

**Usage Guidelines**

Use this command to configure message types that can bypass throttling. If no parameters are specified, the system will use the default settings.

**Example**

The following command configures Delete PDP message type at the GGSN node to bypass throttling.

```
egress bypass-rlf ggsn msg-type dpc
```

The following command configures create bearer request message type at the P-GW node to bypass throttling.

```
egress bypass-rlf pgw msg-type cbr
```

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

exit



## Traffic Optimization Policy Configuration

---

- [bandwidth-mgmt](#), on page 940
- [curbing-control](#), on page 942
- [do show](#), on page 944
- [end](#), on page 945
- [exit](#), on page 946
- [heavy-session](#), on page 947
- [link-profile](#), on page 948
- [session-params](#), on page 949

# bandwidth-mgmt

This command configures bandwidth management parameters for a traffic optimization policy.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Policy Configuration

**active-charging service** *service\_name* > **traffic-optimization-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-opt-policy)#
```

---

**Syntax Description**

```
bandwidth-mgmt { backoff-profile [ managed | unmanaged ] [
min-effective-rate effective_rate [ min-flow-control-rate flow_rate ] |
min-flow-control-rate flow_rate [ min-effective-rate effective_rate ] ] |
min-effective-rate effective_rate [ backoff-profile [ managed | unmanaged ]
[ min-flow-control-rate flow_rate ] | min-flow-control-rate control_rate [
backoff-profile [ managed | unmanaged ] ] | min-flow-control-rate [ [
backoff-profile [ managed | unmanaged ] [ min-effective-rate effective_rate
] | [ min-effective-rate effective_rate ] [ backoff-profile [ managed |
unmanaged ] ] ] }
[ no ] bandwidth-mgmt
```

**no**

Overwrites the traffic-optimization configured parameter(s) with default values. Before deleting a policy profile, all policies associated to the policy profile should be removed. If policy associations are not removed before deletion, the following error message will be displayed:

```
Failure: traffic-optimization policy in use, cannot be deleted.
```

**backoff-profile**

Determines the overall aggressiveness of the back off rates.

**managed**

Enables both traffic monitoring and traffic optimization.

**unmanaged**

Only enables traffic monitoring.

**min-effective-rate** *effective\_rate*

Configures minimum effective shaping rate in Kbps. The shaping rate value is an integer ranging from 100 to 10000.

**min-flow-control-rate *flow\_rate***

Configures the minimum rate allowed in Kbps to control the flow of heavy-session-flows during congestion. The control rate value is an integer ranging from 100 to 10000.

**Usage Guidelines**

Use this command to configure bandwidth management parameters for a traffic optimization policy.

# curbing-control

This command configures curbing flow control related parameters.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Policy Configuration

**active-charging service** *service\_name* > **traffic-optimization-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-opt-policy)#
```

---

**Syntax Description**

```
curbing-control { max-phases max_phase_value [ rate curbing_control_rate [ threshold-rate threshold_rate [ time curbing_control_duration ] ] ] | rate curbing_control_rate [ max-phases [ threshold-rate threshold_rate [ time curbing_control_duration ] ] ] | threshold-rate [ max-phases max_phase_value [ rate curbing_control_rate [ time curbing_control_duration ] ] ] | time [ max-phases max_phase_value [ rate curbing_control_rate [ threshold-rate threshold_rate ] ] ] }
[ no ] curbing-control
```

**no**

Overwrites the traffic-optimization configured parameter(s) with default values. Before deleting a policy profile, all policies associated to the policy profile should be removed. If policy associations are not removed before deletion, the following error message will be displayed:

```
Failure: traffic-optimization policy in use, cannot be deleted.
```

**max-phases** *max\_phase\_value*

Configures consecutive phases where target shaping rate is below threshold-rate to trigger curbing flow control. The maximum phase value is an integer ranging from 2 to 10.

**rate** *curbing\_control\_rate*

Configures the curbing flow-control at a fixed rate in Kbps instead of a dynamic rate. The control rate value is an integer ranging from 0 to 10000. To disable fixed flow control rate, set the flow control rate value to 0.

**threshold-rate** *threshold\_rate*

Configures the minimum target shaping rate in kbps to trigger curbing. The threshold rate is an integer ranging from 100 to 10000.

**time** *curbing\_control\_detection*

Configures the duration of a flow control phase in milliseconds. The flow control duration value is an integer ranging from 0 to 600000. To disable flow control, set the flow control duration value to 0.

---

**Usage Guidelines** Use this command to configure curbing control parameters for a traffic optimization policy.

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---



# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# heavy-session

This command configures heavy session detection parameters.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Policy Configuration

**active-charging service** *service\_name* > **traffic-optimization-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-opt-policy)#
```

---

**Syntax Description**

```
heavy-session { standard-flow-timeout [ threshold threshold_value | threshold
threshold_value [ standard-flow-timeout timeout_value ] }
[ no ] heavy-session
```

**no**

Overwrites the traffic-optimization configured parameter(s) with default values. Before deleting a policy profile, all policies associated to the policy profile should be removed. If policy associations are not removed before deletion, the following error message will be displayed:

```
Failure: traffic-optimization policy in use, cannot be deleted.
```

**standard-flow-timeout** *timeout\_value*

Configures the idle timeout in milliseconds, for expiration of standard flows. The timeout value is an integer ranging from 100 to 3000.

**threshold** *threshold\_value*

Configures heavy-session detection threshold in bytes. On reaching the threshold, the flow will be monitored and potentially managed. The threshold value is an integer ranging from 0 to 100000000.

---

**Usage Guidelines**

Use this command to configure heavy session detection for a traffic optimization policy.

# link-profile

This command configures link profile parameters for a traffic optimization policy.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Policy Configuration

**active-charging service** *service\_name* > **traffic-optimization-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-opt-policy)#
```

---

**Syntax Description**

```
link-profile { initial-rate initial_seed_value [ max-rate max_peak_rate_value [ peak-lock ] ] | max-rate [ initial-rate initial_seed_value [ peak-lock ] ] | peak-lock [ initial-rate initial_seed_value [ max-rate max_peak_rate_value ] ] }
[ no ] link-profile
```

**no**

Overwrites the traffic-optimization configured parameter(s) with default values. Before deleting a policy profile, all policies associated to the policy profile should be removed. If policy associations are not removed before deletion, the following error message will be displayed:

```
Failure: traffic-optimization policy in use, cannot be deleted.
```

**initial-rate** *initial\_seed\_value*

Configures the initial seed value of the acquired peak rate in Kbps for a traffic session. The initial seed value is an integer ranging from 100 to 30000.

**max-rate** *max\_peak\_value\_rate*

Configures the maximum learned peak rate allowed in Kbps for a traffic session. The max rate value is an integer ranging from 100 to 30000.

**peak-lock**

Confirms with the link peak rate available at the initial link peak rate setting.

---

**Usage Guidelines**

Use this command to configure a link profile for a traffic optimization policy.

# session-params

This command configures session parameters for a traffic optimization policy.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Policy Configuration

**active-charging service** *service\_name* > **traffic-optimization-policy** *policy\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-opt-policy)#
```

---

**Syntax Description**

```
session-params { tcp-ramp-up tcp_rampup_duration [ udp-ramp-up udp_rampup_duration ] | udp-ramp-up udp_rampup_duration [ tcp-ramp-up tcp_rampup_duration ] }
[ no ] session-params
```

**no**

Overwrites the traffic-optimization configured parameter(s) with default values. Before deleting a policy profile, all policies associated to the policy profile should be removed. If policy associations are not removed before deletion, the following error message will be displayed:

```
Failure: traffic-optimization policy in use, cannot be deleted.
```

**tcp-ramp-up** *tcp\_rampup\_duration*

Configures the ramp-up-phase duration in milliseconds, for TCP traffic. The TCP ramp-up duration is an integer ranging from 0 to 5000.

**udp-ramp-up** *udp\_rampup\_duration*

Configures the ramp-up-phase duration in milliseconds, for UDP traffic. The UDP ramp-up duration is an integer ranging from 0 to 5000.

---

**Usage Guidelines**

Use this command to configure session parameters for a traffic optimization policy.





# Traffic Optimization Profile Configuration Mode Commands

---

The Traffic Optimization Profile Configuration Mode allows you to configure and manage properties of Cisco Ultra Traffic Optimization solution.

---

## Command Modes

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service *service\_name* > traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-traffic-optim) #
```



---

## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [data-record](#), on page 952
- [efd-flow-cleanup-interval](#), on page 953
- [end](#), on page 954
- [exit](#), on page 955
- [heavy-session detection-threshold](#), on page 956
- [mode](#), on page 957
- [stats-interval](#), on page 958
- [stats-options](#), on page 959

# data-record

This command enables Traffic Optimization Data Record (TODR) generation.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service** *service\_name* > **traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-optim)#
```

---

**Syntax Description**

**data-record** [ **large-flows-only** | **managed-large-flows-only** ]  
**no data record**

**no**

If previously configured, disables generation of TODR.

**data-record**

Enables the Traffic Optimization Data Record (TODR) generation

- **large-flows-only**: Enables the traffic optimization data record generation for large flows.

**managed-large-flows-only**: Enables the traffic optimization data record generation for managed large flows.

The keywords - **large-flows-only** and **managed-large-flows-only** when configured along with **data-record** enables the CUTO library to stream the respective statistics as part of the **stats-options** command, to the external server. The user can configure a combination of the **stats-options** keywords **flow-trace** and **flow-analyst** and the **data-record** command to notify the CUTO library accordingly.




---

**Note** One of the above the two keywords can be configured as part of the data-record, which will enable the CUTO library to stream the respective statistics.

---

The default behavior of the **data-record** command is not affected with the above implementation . If it is configured without any of the options, then TODR's will be generated for all standard and large flows, which is the existing behavior.

---

**Usage Guidelines**

Use this command to generate TODR.



# efd-flow-cleanup-interval

This configures EFD flow command cleanup interval.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service** *service\_name* > **traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-optim) #
```

---

**Syntax Description**

[ **no** ] **efd-flow-cleanup-interval**

**no**

If previously configured, disables EFD flow cleanup interval.

**efd-flow-cleanup-interval**

Configures EFD flow cleanup interval. The interval value is an integer that ranges from 10 to 5000 milliseconds.

---

**Usage Guidelines**

Use this command to configure EFD flow cleanup interval.

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# heavy-session detection-threshold

Configures the threshold value for the TCP flow to be considered for the Traffic Optimization.

---

## Product

P-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service** *service\_name* > **traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-optim)#
```

---

## Syntax Description

**heavy-session detection-threshold** *bytes*

### heavy-session

Specifies the heavy session configuration for the Traffic Optimization.

### detection-threshold *bytes*

Specifies the detection threshold, in bytes. Beyond which, it is considered as heavy session. The *bytes* must be an integer from 1 to 4294967295.

To get optimum Traffic Optimization benefit, it is recommended to not set it less than 3 MB.

---

## Usage Guidelines

Use this command to set the threshold value for the TCP flow.

### Example

The following command sets the threshold value to *3145728* bytes:

```
heavy-session detection-threshold 3145728
```

# mode

Configures the operating mode for the Cisco Ultra Traffic Optimization engine.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service** *service\_name* > **traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-optim) #
```

---

**Syntax Description**

**mode [ active | passive ]**

**mode**

Sets the mode of operation for Traffic Optimization.

**active**

The mode where both Traffic Optimization and flow monitoring is done on the packet.

**passive**

The mode where no flow-control is performed but monitoring is done on the packet.

---

**Usage Guidelines**

Use this command to set the operating mode for the Cisco Ultra Traffic Optimization engine.

**Example**

The following command sets the operating mode to **active**:

```
mode active
```

# stats-interval

This command configures the flow statistics collection and reporting interval.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service** *service\_name* > **traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-optim)#
```

---

**Syntax Description**

[ no ] **stats-interval**

**no**

If previously configured, disables collection of flow statistics.

**stats-interval**

Configures the flow statistics collection and reporting interval in seconds. The interval value is an integer that ranges from 1 to 60 seconds.

---

**Usage Guidelines**

Use this command to collect and report flow statistics.

# stats-options

This command configures options to collect the flow statistics.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > Traffic Optimization Profile Configuration

**active-charging service** *service\_name* > **traffic-optimization-profile**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-optim) #
```

---

**Syntax Description**

```
[ no ] stats-options { flow-analyst [ flow-trace ] | flow-trace [ flow-analyst ] }
```

**no**

If previously configured, disables trace collection and reporting.

**flow-analyst**

Enables flow analysis, and large trace collection and reporting.

**flow-trace**

Enables flow trace collection and reporting.

---

**Usage Guidelines**

Use this command to enable trace collection and reporting.







## Traffic Policy-Map Configuration Mode Commands

---

A Policy-Map imposes a flow-based traffic policy for Traffic Policy feature within a destination context. It designates the flow treatment based on the classification rules configured in Class-Map mode for a subscriber session flow.

---

### Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [3gpp2 data-over-signaling](#), on page 962
- [access-control](#), on page 963
- [accounting suppress](#), on page 964
- [accounting trigger](#), on page 965
- [class-map](#), on page 967
- [description](#), on page 968
- [do show](#), on page 969
- [end](#), on page 970
- [exit](#), on page 971
- [flow-tp-trigger](#), on page 972
- [ip header-compression](#), on page 973
- [qos encaps-header](#), on page 974
- [qos traffic-police](#), on page 976
- [qos user-datagram dscp-marking](#), on page 978
- [sess-tp-trigger](#), on page 979
- [type](#), on page 980

# 3gpp2 data-over-signaling

Configures 3GPP2-related flow treatment policy for the flow-based traffic policing of subscriber sessions.

---

## Product

HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

**3gpp2 data-over-signaling marking** [ **class-map** *class\_name* ]  
**no 3gpp2 data-over-signaling marking**

**no**

Disables configured 3GPP2-related flow treatment policy.

**class-map** *class\_name*

Associates class map to be used for selective data over signaling (DOS) marking. *class\_name* is an alphanumeric string of 1 through 15 characters.

**marking**

Indicates 3GPP2-related traffic flow for data over signaling channel.

---

## Usage Guidelines

Use this command to mark traffic flows for 3GPP2-related policy.

## Example

```
3gpp2 data-over-signaling marking
```

# access-control

Configures the access control action for traffic flows matching the Class-Map rules.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

## Syntax Description

**access-control { allow | discard }**

### allow

Allows the packets, if the policy matches with the criteria defined in the Class-Map assigned to the specific traffic policy.

### discard

Discards the packets, if the policy matches with the criteria defined in the Class-Map assigned to the specific traffic policy.

---

## Usage Guidelines

Configures the action or treatment for traffic flows match criteria specified in the assigned Class-Map.

### Example

The following command allows the packets or traffic flow on matching with criteria specified in assigned Class-Map for specific traffic policy.

```
access-control allow
```

# accounting suppress

Suppresses accounting action for traffic flows matching the policy map.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

[ **no** ] **accounting suppress**

**no**

Removes the suppression of accounting for traffic flow matching this policy map.

---

## Usage Guidelines

Use this command to suppress accounting action on traffic flow matching this policy map.

Policy maps configured for accounting suppression are used to implement the QChat Billing Suppression feature that selectively starts and terminates accounting sessions based on the categorization of traffic as being interesting or non-interesting. See the **accounting trigger** command.

## Example

The following command configures suppression of accounting on traffic flows matching this policy map:

```
accounting suppress
```

# accounting trigger

Configures an accounting trigger policy map to selectively start and terminate accounting sessions based on the categorization of traffic as being interesting or non-interesting. This command supports the QCHAT Billing Suppression feature.

---

## Product

HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map** *name map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

```
[ no | default ] accounting trigger { inactivity-timeout | interesting-traffic | intra-service-handoff }
```

### default

Sets or restores the default value assigned for specified parameter.

### no

Disables previously configured triggers.

### inactivity-timeout

Generates an accounting Stop message if there has been no data activity on the session for the interim accounting timeout interval.

Default: disabled

### interesting-traffic

Generates an accounting Start message upon arrival of interesting traffic.

Default: disabled

### intra-service-handoff

Generates accounting Start and Stop messages during intra-service handoffs.

Default: enabled

If disabled, the messages are suppressed during the handoffs. The current accounting session continues and no Stop or Start messages are generated during the intra-service handoff.

---

**Usage Guidelines**

Use this command to configure an accounting trigger policy map (ATPM) to selectively start and terminate accounting sessions based on the categorization of traffic as being interesting or non-interesting. This command supports the QChat Billing Suppression feature.

Interesting traffic is identified as traffic that does not match any of the other Accounting Policy Maps (APMs) configured for accounting suppression. See the **accounting suppress** command.

An ATPM is similar to an APM, but without the class map rules. The ATPM is configured as of type accounting using the **type accounting** command.

Optionally, timeout can be triggered when there is no data traffic for the interim accounting timeout interval using the **accounting trigger inactivity-timeout stop** command. On timeout, the accounting session is terminated and an Accounting Stop message is sent. A new accounting session is created if interesting traffic resumes.

In the ATPM, the trigger to start accounting for interesting traffic is configured using the **accounting trigger interesting-traffic** command. Accounting Start is triggered on arrival of interesting traffic, or change in airlink parameters conveyed through active-start airlink record. If an active-start record was included in the initial connection setup, Accounting Start is not triggered. But if the active-start comes separately and is the first one for the session, it is treated as airlink change and an Accounting Start is sent.

The ATPM should have the lowest precedence among the APMs.

As the airlink events are generated on the ingress side, the ATPM must be included in a policy group that is applied to the ingress direction in the subscriber profile. The configuration is applicable only for standard trigger policy and session based accounting mode.

**Example**

The following command sets the trigger to generate accounting start message upon arrival of interesting traffic:

```
accounting trigger interesting-traffic
```

# class-map

Assigns a traffic classification rule (Class-Map) to the policy map.

---

**Product**

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

**Syntax Description**

[ **no** ] **class-map** *name*

**no**

Enables or disables **class-map**.

**name**

Specifies the name of the class map assigned for this policy map. The class map should have been preconfigured via the Class Map Configuration Mode.

*name* must be an alphanumeric a string of 1 through 15 characters.

---

**Usage Guidelines**

Use this command to assign a class map to the policy map for traffic policing. The class map is configured in the Class Map Configuration Mode.

**Example**

The following command assigns the class map *classification1* to the current policy map:

```
class classification1
```

# description

Allows you to enter descriptive text for this configuration.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `description text`  
`no description`

**no**

Clears the description for this configuration.

**text**

Enter descriptive text as an alphanumeric string of 1 to 100 characters.

If you include spaces between words in the description, you must enclose the text within double quotation marks (" "), for example, "AAA BBBB".

---

**Usage Guidelines** The description should provide useful information about this configuration.



# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# flow-tp-trigger

This command specifies that the traffic volume will be calculated based on the traffic on the flow.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

**flow-tp-trigger volume** *traffic\_volume\_threshold*  
**no flow-tp-trigger volume**

### *traffic\_volume\_threshold*

Specifies the volume threshold to trigger traffic policing. *volume* must be an integer from 1 through 4294967295.

---

## Usage Guidelines

This command is available if you have purchased and installed the Intelligent Traffic Control License on your system. Use this command to calculate the traffic volume based on the traffic on the flow.

### Example

```
flow-tp-trigger volume 500
```

# ip header-compression

Enables the system to mark IP flows for Robust Header Compression (RoHC).

---

**Product**

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

**Syntax Description**

[ **no** ] **ip header-compression rohc flow-marking**

**no**

Disables the setting.

**rohc flow-marking**

Marks the IP flow for SO67 and PPP RoHC.

---

**Usage Guidelines**

Use this command to mark IP flows for SO67 and PPP RoHC.

**Example**

```
ip header-compression rohc flow-marking
```

## qos encaps-header

Enables and configures Quality of Service (QoS) policy to use Differentiated Service Code Point (DSCP) marking in IP header fields for the flow-based traffic policing to subscriber session flow.

---

### Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

### Syntax Description

```
qos encaps-header dscp-marking { dscp_code | copy-from-user-datagram [ ignore-pcf-signaled-dscp ] | user-datagram }
no qos encaps-header dscp-marking { dscp_code | copy-from-user-datagram [ ignore-pcf-signaled-dscp ] }
```

#### **no**

Enables/Disables the **qos encaps-header**.

The value must be expressed as a hexadecimal value from 0x00 through 0x3F.

#### **dscp-marking** *dscp\_code*

Uses the DSCP code value marked in the IP header of packet/flow to determine the QoS for traffic policing. *dscp\_code* must be expressed as a hexadecimal number from 0x00 through 0x3F.

#### **copy-from-user-datagram**

Uses the DSCP code value from the user datagram (UDP header) to determine the QoS for traffic policing.

#### **ignore-pcf-signaled-dscp**

Overrides the highest priority DSCP value signaled by the PCF.

#### **user-datagram**

Uses the DSCP value copied from the user datagram.

---

**Usage Guidelines**

Use this command to apply the QoS policy based on the DSCP value encapsulated in the IP packet header to police subscriber session traffic flows.



---

**Important**

For more information on the QoS traffic policing, see the *System Administration Guide*.

---

**Example**

The following command sets QoS policy with DSCP code value to *0x0C* for Class 1, silver (AF12):

```
qos encaps-header dscp-marking 0x0c
```

# qos traffic-police

Enables and configures Quality of Service (QoS) policy for flow-based traffic policing of subscriber session flows on a per-flow basis.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

```
qos traffic-police committed bps peak bps burst-size byte exceed-action {  
drop | lower-ip-precedence | allow } violate-action { drop |  
lower-ip-precedence | allow }  
no qos traffic-police
```

**no**

Enables/Disables the **qos traffic-police**




---

### Important

This parameter should be configured to be greater than the following two values: 1) three times greater than packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate.

---

### burst-size *bytes*

Default: 3000

Specifies the allowed peak burst size in bytes. *bytes* must be an integer from 0 through 4294967295.




---

### Important

This parameter should be configured to be greater than the following two values: 1) three times greater than the packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate.



**committed bps**

Default: 144000

Specifies the committed data rate (guaranteed-data-rate) in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**exceed-action { drop | lower-ip-precedence | allow }**

Default: **lower-ip-precedence**

Specifies the action to take on packets that exceed the committed-data-rate but do not violate the peak-data-rate. The following actions are supported:

**drop**: Drops the packet

**lower-ip-precedence**: Transmits the packet after lowering the ip-precedence

**allow**: Transmits the packet

**peak bps**

Default: 256000

Specifies the peak data-rate for the subscriber in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**violate-action { drop | lower-ip-precedence | allow }**

Default: drop

Specifies the action to take on the packets that exceed both the committed-data-rate and the peak-data-rate. The following actions are supported:

**drop**: Drops the packet

**lower-ip-precedence**: Transmits the packet after lowering the IP precedence

**allow**: Transmits the packet

**Usage Guidelines**

Use this command to apply the QoS policy to a subscriber session flow for flow-based traffic policing.

**Important**

For additional information on the QoS traffic policing, see the *System Administration Guide*.

**Example**

The following command sets the committed data rate to *102400* bps with a peak data rate of *128000* bps and a burst size of *2048* bytes. This lowers the IP precedence when the committed-data-rate is exceeded and drops the packets when the peak-data-rate are violated:

```
qos traffic-police committed 102400 peak 128000 burst-size 2048
exceed-action lower-ip-precedence violate-action drop
```

## qos user-datagram dscp-marking

Enables and configures Quality of Service (QoS) policy related to differentiated service code point (DSCP) marking in the user datagrams of subscriber session flows on a per-flow basis.

---

### Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

### Syntax Description

**qos user-datagram dscp-marking** *dscp\_code*  
**no qos user-datagram dscp-marking**

#### *dscp\_code*

Specifies the use of the DSCP code value marked in the IP header of packet/flow to determine the QoS for traffic policing. *dscp\_code* must be expressed as a hexadecimal number from 0x00 through 0x3F.

---

### Usage Guidelines

Use this command to apply the QoS policy to subscriber session flow by DSCP marking in user datagram.

#### Example

The following command sets DSCP marking for user datagram as *0x01* for QoS to subscriber session flow:

```
qos user-datagram dscp-marking 0x01
```

# sess-tp-trigger

Configures the trigger for traffic policing based on the traffic volume for a subscriber session.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

## Syntax Description

**sess-tp-trigger** **volume** *volume* **direction** { **both** | **downlink** | **uplink** }  
**no sess-tp-trigger**

**no**

Enables or disables the **sess-tp-trigger**

**volume**

Specifies the traffic volume threshold (in bytes) that triggers traffic control. *volume* is an integer from 1 through 4294967295.

---

## Usage Guidelines

Use this command to trigger traffic control based on the traffic volume for a subscriber session. This command requires the purchase and installation of a license.

### Example

```
sess-tp-trigger 500
```

# type

Specifies the type of traffic policy within a specific Policy-Map.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

```
type { accounting | dynamic { three-gpp2 rev-A profile-id { any | id
profile_id | range low_value to high_value } flow-id { any | id flow_id | range
low_value to high_value } | pre-provisioned wimax asn-service-profile-id {
any | id service_id } asn-pdfid { any | id pdf_id } | static | template }
```

### accounting

Specifies the type of traffic policing as accounting for this specific policy map. This configuration is used for enabling/disabling the accounting of different flows matching conditions within this Policy-Map.

### dynamic

Identifies the type of policy map as dynamic.

### three-gpp2 rev-A

Configures the dynamic policy map type for CDMA2000-3GPP2 RevA service.

### profile-id { any | id *profile\_id* | range *low\_hex* to *high\_hex* }

Specifies the profile id matching within this policy map.

**any**: allows any profile identifier matching this policy map.

**id** *profile\_id*: allows specific profile identifier matching with in this policy map. *profile\_id* must be a hexadecimal number from 0x0 to 0xFFFF.

**range** *low\_value* **to** *high\_value*: identifies a range in which a profile identifier must fall within to be considered a match. *low\_value* and *high\_value* must be either a hexadecimal number from 0x0 to 0xFFFF, or an integer from 0 through 65535 characters.

**flow-id { any | id *flow\_id* | range *low\_hex* to *high\_hex* }**

Specifies the flow id matching in this policy map.

**any** allows any flow identifier matching with in this policy map.

**id** *flow\_id* allows specific flow identifier matching with in this policy map. *flow\_id* must be either a hexadecimal number from 0x0 to 0xFFFF, or an integer from 0 to 65535.

**range** *low\_value* **to** *high\_value*: identifies a range in which a flow identifier must fall within to be considered a match. *low\_value* and *high\_value* must be either a hexadecimal number from 0x0 to 0xFFFF, or an integer 0 to 65535.

**pre-provisioned**

Identifies the type of policy map as pre-provisioned.

**wimax**

Configures WiMAX service policy map in an ASN-GW service.

**asn-service-profile { any | id *service\_id* }**

Specifies the ASN Service profile identifier to match with in this policy map.

**any**: Allows any ASN Service Profile Identifier matching within this policy map.

**id** *service\_id*: Allows specific Service Profile matching to a specified identifier. *service\_id* must be an integer from 1 to 65535 that matches a service ID that was configured in the Subscriber Configuration Mode.

**asn-pdfid { any | id *pdf\_id* }**

Specifies the ASN Packet Data Flow Identifier to match with in this policy map.

**any**: Allows any ASN Packet Data Flow Identifier matching within this policy map.

**id** *pdf\_id*: Allows specific Packet Data Flow matching to a specified identifier. *pdf\_id* must be an integer from 1 to 255 that matches a PDF ID that was configured in the Subscriber Configuration Mode.

**static**

Specifies the type of traffic policing as static for this specific Policy Map. In this type of policy, the traffic flow classification and flow treatment is pre-defined with classification rules through Class-Map configuration.

This is the detailed type of policy map.

**template**

Specifies the type of traffic policy to as a template to all subscribers associated with this policy map.

**Usage Guidelines**

Specifies the type of traffic policy within the specific Policy-Map.

**Example**

The following commands configures the traffic policy for this Policy-Map as static:

```
type static
```

The following commands configures the traffic policy for this Policy-Map as pre-provisioned for WiMAX service requiring a match of any service profile and PDF id of 3:

```
type pre-provisioned wimax asn-service-profile any asn-pdfid id 3
```



## Traffic Policy Group Configuration Mode Commands

---

Policy-Group is used to form a set of configured Policy-Maps for the Traffic Policy feature. Multiple policies can be applied for a subscriber session flow within a destination context.

### Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Group Configuration

**configure** > **context** *context\_name* > **policy-group name** *group\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-group)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [3gpp2 data-over-signaling](#), on page 984
- [access-control](#), on page 985
- [accounting suppress](#), on page 986
- [accounting trigger](#), on page 987
- [class-map](#), on page 989
- [description](#), on page 990
- [do show](#), on page 991
- [end](#), on page 992
- [exit](#), on page 993
- [flow-tp-trigger](#), on page 994
- [ip header-compression](#), on page 995
- [qos encaps-header](#), on page 996
- [qos traffic-police](#), on page 998
- [qos user-datagram dscp-marking](#), on page 1000
- [sess-tp-trigger](#), on page 1001
- [type](#), on page 1002

# 3gpp2 data-over-signaling

Configures 3GPP2-related flow treatment policy for the flow-based traffic policing of subscriber sessions.

---

## Product

HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

**3gpp2 data-over-signaling marking** [ **class-map** *class\_name* ]  
**no 3gpp2 data-over-signaling marking**

**no**

Disables configured 3GPP2-related flow treatment policy.

**class-map** *class\_name*

Associates class map to be used for selective data over signaling (DOS) marking. *class\_name* is an alphanumeric string of 1 through 15 characters.

**marking**

Indicates 3GPP2-related traffic flow for data over signaling channel.

---

## Usage Guidelines

Use this command to mark traffic flows for 3GPP2-related policy.

## Example

```
3gpp2 data-over-signaling marking
```



# access-control

Configures the access control action for traffic flows matching the Class-Map rules.

---

**Product**

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

**Syntax Description**

**access-control { allow | discard }**

**allow**

Allows the packets, if the policy matches with the criteria defined in the Class-Map assigned to the specific traffic policy.

**discard**

Discards the packets, if the policy matches with the criteria defined in the Class-Map assigned to the specific traffic policy.

---

**Usage Guidelines**

Configures the action or treatment for traffic flows match criteria specified in the assigned Class-Map.

**Example**

The following command allows the packets or traffic flow on matching with criteria specified in assigned Class-Map for specific traffic policy.

```
access-control allow
```

# accounting suppress

Suppresses accounting action for traffic flows matching the policy map.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

[ **no** ] **accounting suppress**

**no**

Removes the suppression of accounting for traffic flow matching this policy map.

---

## Usage Guidelines

Use this command to suppress accounting action on traffic flow matching this policy map.

Policy maps configured for accounting suppression are used to implement the QChat Billing Suppression feature that selectively starts and terminates accounting sessions based on the categorization of traffic as being interesting or non-interesting. See the **accounting trigger** command.

## Example

The following command configures suppression of accounting on traffic flows matching this policy map:

```
accounting suppress
```

# accounting trigger

Configures an accounting trigger policy map to selectively start and terminate accounting sessions based on the categorization of traffic as being interesting or non-interesting. This command supports the QCHAT Billing Suppression feature.

---

## Product

HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map** *name map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

## Syntax Description

```
[ no | default ] accounting trigger { inactivity-timeout | interesting-traffic | intra-service-handoff }
```

### default

Sets or restores the default value assigned for specified parameter.

### no

Disables previously configured triggers.

### inactivity-timeout

Generates an accounting Stop message if there has been no data activity on the session for the interim accounting timeout interval.

Default: disabled

### interesting-traffic

Generates an accounting Start message upon arrival of interesting traffic.

Default: disabled

### intra-service-handoff

Generates accounting Start and Stop messages during intra-service handoffs.

Default: enabled

If disabled, the messages are suppressed during the handoffs. The current accounting session continues and no Stop or Start messages are generated during the intra-service handoff.

### Usage Guidelines

Use this command to configure an accounting trigger policy map (ATPM) to selectively start and terminate accounting sessions based on the categorization of traffic as being interesting or non-interesting. This command supports the QChat Billing Suppression feature.

Interesting traffic is identified as traffic that does not match any of the other Accounting Policy Maps (APMs) configured for accounting suppression. See the **accounting suppress** command.

An ATPM is similar to an APM, but without the class map rules. The ATPM is configured as of type accounting using the **type accounting** command.

Optionally, timeout can be triggered when there is no data traffic for the interim accounting timeout interval using the **accounting trigger inactivity-timeout stop** command. On timeout, the accounting session is terminated and an Accounting Stop message is sent. A new accounting session is created if interesting traffic resumes.

In the ATPM, the trigger to start accounting for interesting traffic is configured using the **accounting trigger interesting-traffic** command. Accounting Start is triggered on arrival of interesting traffic, or change in airlink parameters conveyed through active-start airlink record. If an active-start record was included in the initial connection setup, Accounting Start is not triggered. But if the active-start comes separately and is the first one for the session, it is treated as airlink change and an Accounting Start is sent.

The ATPM should have the lowest precedence among the APMs.

As the airlink events are generated on the ingress side, the ATPM must be included in a policy group that is applied to the ingress direction in the subscriber profile. The configuration is applicable only for standard trigger policy and session based accounting mode.

### Example

The following command sets the trigger to generate accounting start message upon arrival of interesting traffic:

```
accounting trigger interesting-traffic
```

# class-map

Assigns a traffic classification rule (Class-Map) to the policy map.

---

**Product**

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

**Syntax Description**

[ **no** ] **class-map** *name*

**no**

Enables or disables **class-map**.

**name**

Specifies the name of the class map assigned for this policy map. The class map should have been preconfigured via the Class Map Configuration Mode.

*name* must be an alphanumeric a string of 1 through 15 characters.

---

**Usage Guidelines**

Use this command to assign a class map to the policy map for traffic policing. The class map is configured in the Class Map Configuration Mode.

**Example**

The following command assigns the class map *classification1* to the current policy map:

```
class classification1
```

# description

Allows you to enter descriptive text for this configuration.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `description text`  
`no description`

**no**

Clears the description for this configuration.

**text**

Enter descriptive text as an alphanumeric string of 1 to 100 characters.

If you include spaces between words in the description, you must enclose the text within double quotation marks (" "), for example, "AAA BBBB".

---

**Usage Guidelines** The description should provide useful information about this configuration.

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

■ end

# end

Exits the current configuration mode and returns to the Exec mode.

**Product** All

**Privilege** Security Administrator, Administrator

**Syntax Description** end

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# flow-tp-trigger

This command specifies that the traffic volume will be calculated based on the traffic on the flow.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

**flow-tp-trigger volume** *traffic\_volume\_threshold*  
**no flow-tp-trigger volume**

### *traffic\_volume\_threshold*

Specifies the volume threshold to trigger traffic policing. *volume* must be an integer from 1 through 4294967295.

---

## Usage Guidelines

This command is available if you have purchased and installed the Intelligent Traffic Control License on your system. Use this command to calculate the traffic volume based on the traffic on the flow.

### Example

```
flow-tp-trigger volume 500
```

# ip header-compression

Enables the system to mark IP flows for Robust Header Compression (RoHC).

---

**Product**

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

**Syntax Description**

[ **no** ] **ip header-compression rohc flow-marking**

**no**

Disables the setting.

**rohc flow-marking**

Marks the IP flow for SO67 and PPP RoHC.

---

**Usage Guidelines**

Use this command to mark IP flows for SO67 and PPP RoHC.

---

**Example**

```
ip header-compression rohc flow-marking
```

## qos encaps-header

Enables and configures Quality of Service (QoS) policy to use Differentiated Service Code Point (DSCP) marking in IP header fields for the flow-based traffic policing to subscriber session flow.

---

### Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

### Syntax Description

```
qos encaps-header dscp-marking { dscp_code | copy-from-user-datagram [ ignore-pcf-signaled-dscp ] | user-datagram }
no qos encaps-header dscp-marking { dscp_code | copy-from-user-datagram [ ignore-pcf-signaled-dscp ] }
```

#### **no**

Enables/Disables the **qos encaps-header**.

The value must be expressed as a hexadecimal value from 0x00 through 0x3F.

#### **dscp-marking** *dscp\_code*

Uses the DSCP code value marked in the IP header of packet/flow to determine the QoS for traffic policing. *dscp\_code* must be expressed as a hexadecimal number from 0x00 through 0x3F.

#### **copy-from-user-datagram**

Uses the DSCP code value from the user datagram (UDP header) to determine the QoS for traffic policing.

#### **ignore-pcf-signaled-dscp**

Overrides the highest priority DSCP value signaled by the PCF.

#### **user-datagram**

Uses the DSCP value copied from the user datagram.

---

**Usage Guidelines**

Use this command to apply the QoS policy based on the DSCP value encapsulated in the IP packet header to police subscriber session traffic flows.



---

**Important**

For more information on the QoS traffic policing, see the *System Administration Guide*.

---

**Example**

The following command sets QoS policy with DSCP code value to *0x0C* for Class 1, silver (AF12):

```
qos encaps-header dscp-marking 0x0c
```

# qos traffic-police

Enables and configures Quality of Service (QoS) policy for flow-based traffic policing of subscriber session flows on a per-flow basis.

---

## Product

ASN-GW  
 HA  
 HSGW  
 PDSN  
 P-GW  
 SAEGW  
 SCM

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

```
qos traffic-police committed bps peak bps burst-size byte exceed-action {  

drop | lower-ip-precedence | allow } violate-action { drop |  

lower-ip-precedence | allow }  

no qos traffic-police
```

**no**

Enables/Disables the **qos traffic-police**




---

### Important

This parameter should be configured to be greater than the following two values: 1) three times greater than packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate.

---

### burst-size *bytes*

Default: 3000

Specifies the allowed peak burst size in bytes. *bytes* must be an integer from 0 through 4294967295.




---

### Important

This parameter should be configured to be greater than the following two values: 1) three times greater than the packet MTU for the subscriber connection, OR 2) three seconds worth of token accumulation within the "bucket" for the configured peak-data-rate.

**committed bps**

Default: 144000

Specifies the committed data rate (guaranteed-data-rate) in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**exceed-action { drop | lower-ip-precedence | allow }**

Default: **lower-ip-precedence**

Specifies the action to take on packets that exceed the committed-data-rate but do not violate the peak-data-rate. The following actions are supported:

**drop**: Drops the packet

**lower-ip-precedence**: Transmits the packet after lowering the ip-precedence

**allow**: Transmits the packet

**peak bps**

Default: 256000

Specifies the peak data-rate for the subscriber in bits per second (bps).

*bps* must be an integer from 0 through 4294967295.

**violate-action { drop | lower-ip-precedence | allow }**

Default: drop

Specifies the action to take on the packets that exceed both the committed-data-rate and the peak-data-rate. The following actions are supported:

**drop**: Drops the packet

**lower-ip-precedence**: Transmits the packet after lowering the IP precedence

**allow**: Transmits the packet

**Usage Guidelines**

Use this command to apply the QoS policy to a subscriber session flow for flow-based traffic policing.

**Important**

For additional information on the QoS traffic policing, see the *System Administration Guide*.

**Example**

The following command sets the committed data rate to *102400* bps with a peak data rate of *128000* bps and a burst size of *2048* bytes. This lowers the IP precedence when the committed-data-rate is exceeded and drops the packets when the peak-data-rate are violated:

```
qos traffic-police committed 102400 peak 128000 burst-size 2048
exceed-action lower-ip-precedence violate-action drop
```

## qos user-datagram dscp-marking

Enables and configures Quality of Service (QoS) policy related to differentiated service code point (DSCP) marking in the user datagrams of subscriber session flows on a per-flow basis.

---

### Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

### Privilege

Security Administrator, Administrator

---

### Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

### Syntax Description

**qos user-datagram dscp-marking** *dscp\_code*  
**no qos user-datagram dscp-marking**

#### *dscp\_code*

Specifies the use of the DSCP code value marked in the IP header of packet/flow to determine the QoS for traffic policing. *dscp\_code* must be expressed as a hexadecimal number from 0x00 through 0x3F.

---

### Usage Guidelines

Use this command to apply the QoS policy to subscriber session flow by DSCP marking in user datagram.

#### Example

The following command sets DSCP marking for user datagram as *0x01* for QoS to subscriber session flow:

```
qos user-datagram dscp-marking 0x01
```



# sess-tp-trigger

Configures the trigger for traffic policing based on the traffic volume for a subscriber session.

---

**Product**

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map) #
```

---

**Syntax Description**

**sess-tp-trigger** **volume** *volume* **direction** { **both** | **downlink** | **uplink** }  
**no sess-tp-trigger**

**no**

Enables or disables the **sess-tp-trigger**

**volume**

Specifies the traffic volume threshold (in bytes) that triggers traffic control. *volume* is an integer from 1 through 4294967295.

---

**Usage Guidelines**

Use this command to trigger traffic control based on the traffic volume for a subscriber session. This command requires the purchase and installation of a license.

**Example**

```
sess-tp-trigger 500
```

# type

Specifies the type of traffic policy within a specific Policy-Map.

---

## Product

ASN-GW  
HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SCM

---

## Privilege

Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > Traffic Policy Map Configuration

**configure** > **context** *context\_name* > **policy-map name** *map\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-policy-map)#
```

---

## Syntax Description

```
type { accounting | dynamic { three-gpp2 rev-A profile-id { any | id
profile_id | range low_value to high_value } flow-id { any | id flow_id | range
low_value to high_value } | pre-provisioned wimax asn-service-profile-id {
any | id service_id } asn-pdfid { any | id pdf_id } | static | template }
```

### accounting

Specifies the type of traffic policing as accounting for this specific policy map. This configuration is used for enabling/disabling the accounting of different flows matching conditions within this Policy-Map.

### dynamic

Identifies the type of policy map as dynamic.

### three-gpp2 rev-A

Configures the dynamic policy map type for CDMA2000-3GPP2 RevA service.

### profile-id { any | id *profile\_id* | range *low\_hex* to *high\_hex* }

Specifies the profile id matching within this policy map.

**any**: allows any profile identifier matching this policy map.

**id** *profile\_id*: allows specific profile identifier matching with in this policy map. *profile\_id* must be a hexadecimal number from 0x0 to 0xFFFF.

**range** *low\_value* **to** *high\_value*: identifies a range in which a profile identifier must fall within to be considered a match. *low\_value* and *high\_value* must be either a hexadecimal number from 0x0 to 0xFFFF, or an integer from 0 through 65535 characters.

#### **flow-id { any | id *flow\_id* | range *low\_hex* to *high\_hex* }**

Specifies the flow id matching in this policy map.

**any** allows any flow identifier matching with in this policy map.

**id** *flow\_id* allows specific flow identifier matching with in this policy map. *flow\_id* must be either a hexadecimal number from 0x0 to 0xFFFF, or an integer from 0 to 65535.

**range** *low\_value* **to** *high\_value*: identifies a range in which a flow identifier must fall within to be considered a match. *low\_value* and *high\_value* must be either a hexadecimal number from 0x0 to 0xFFFF, or an integer 0 to 65535.

#### **pre-provisioned**

Identifies the type of policy map as pre-provisioned.

#### **wimax**

Configures WiMAX service policy map in an ASN-GW service.

#### **asn-service-profile { any | id *service\_id* }**

Specifies the ASN Service profile identifier to match with in this policy map.

**any**: Allows any ASN Service Profile Identifier matching within this policy map.

**id** *service\_id*: Allows specific Service Profile matching to a specified identifier. *service\_id* must be an integer from 1 to 65535 that matches a service ID that was configured in the Subscriber Configuration Mode.

#### **asn-pdfid { any | id *pdf\_id* }**

Specifies the ASN Packet Data Flow Identifier to match with in this policy map.

**any**: Allows any ASN Packet Data Flow Identifier matching within this policy map.

**id** *pdf\_id*: Allows specific Packet Data Flow matching to a specified identifier. *pdf\_id* must be an integer from 1 to 255 that matches a PDF ID that was configured in the Subscriber Configuration Mode.

#### **static**

Specifies the type of traffic policing as static for this specific Policy Map. In this type of policy, the traffic flow classification and flow treatment is pre-defined with classification rules through Class-Map configuration.

This is the detailed type of policy map.

#### **template**

Specifies the type of traffic policy to as a template to all subscribers associated with this policy map.

### Usage Guidelines

Specifies the type of traffic policy within the specific Policy-Map.

**Example**

The following commands configures the traffic policy for this Policy-Map as static:

```
type static
```

The following commands configures the traffic policy for this Policy-Map as pre-provisioned for WiMAX service requiring a match of any service profile and PDF id of 3:

```
type pre-provisioned wimax asn-service-profile any asn-pdfid id 3
```



# Traffic Steering Configuration Mode Commands

The Traffic Steering Configuration Mode, which works on StarOS, is used to forward user data streams to external appliances or servers through an alternate SGi interface. This mode enhances user experience by performing tasks, such as optimizing traffic streams and segregating traffic.

## Command Modes

Exec > Global Configuration > Traffic Steering

**configure > traffic-steering**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-steering) #
```

- [appliance-group, on page 1006](#)
- [do show, on page 1007](#)
- [end, on page 1008](#)
- [exit, on page 1009](#)
- [service-chain, on page 1010](#)

# appliance-group

This command allows you to configure appliance group for traffic steering.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Traffic Steering

**configure > traffic-steering**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-steering)#
```

---

**Syntax Description**

**appliance-group** *appliance\_group\_name*

***appliance\_group\_name***

Specifies the name of the appliance group. The name is a string ranging from 1 to 63 characters.

---

**Usage Guidelines**

Use this command to configure an appliance group.

**Example**

The following command sets the appliance group name to *appliance1*:

```
appliance-group appliance1
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# service-chain

This command allows you to configure service chain.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Traffic Steering

**configure > traffic-steering**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-steering)#
```

---

**Syntax Description**

**service-chain** *service\_chain\_name*

***service\_chain\_name***

Specifies the name of the service chain. The name is a string ranging from 1 to 63 characters.

---

**Usage Guidelines**

Use this command to configure a service chain.

**Example**

The following command sets the service chain to *sch1*:

```
service-chain sch1
```



# Traffic Steering Appliance Group Configuration Mode Commands

---

The Traffic Steering Appliance Group is used to define the appliances to which the user traffic is forwarded. You can configure an Appliance Group under the Traffic-Steering mode.

## Command Modes

Exec > Global Configuration > Traffic Steering > Appliance Group

**configure > traffic-steering > appliance-group**

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-traffic-steering-app-grp) #
```

- [do show, on page 1012](#)
- [end, on page 1013](#)
- [exit, on page 1014](#)
- [ip, on page 1015](#)
- [nsh-format, on page 1016](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# ip

This command allows you to configure details related to an IP address.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Traffic Steering > Appliance Group

**configure > traffic-steering > appliance-group**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-steering-app-grp)#
```

---

**Syntax Description**

**ip address { ip\_address (IPv4/IPv6) | preserve-orig-addr }**

**address**

Specifies the IP address; either IPv4 or IPv6.

**preserve-orig-addr**

This keyword when configured uses the same Destination IP as that of original packet.

---

**Usage Guidelines**

Use this command to define the IP address of an external appliance. If you wish to use same IP addresses for both source and destination as that of the original packet, then you need to configure the **preserve-orig-addr** value for IP.




---

**Note**

You can configure either the IP address of the external appliance or preserve same IP addresses for both source and destination. Both the IP configurations do not work at the same time.

---

**Example**

The following command sets the IP address of an external appliance to *1.1.1.1*:

```
ip address 1.1.1.1
```

The following command sets the same Destination IP as that of original packet:

```
ip address preserve-orig-addr
```

# nsh-format

This command allows you to associate NSH format with the appliance group.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Traffic Steering > Appliance Group

**configure > traffic-steering > appliance-group**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-traffic-steering-app-grp) #
```

---

**Syntax Description**

**nsh-format** *nsh\_format\_name*

***nsh\_format\_name***

Specifies the NSH format name. The name is a string ranging from 1 to 63 characters.

---

**Usage Guidelines**

Use this command to configure NSH format for each appliance. With this configuration, Star-OS communicates with the appliances through NSH protocol.

**Example**

The following command configures the NSH format for an appliance to *nsh1*:

```
nsh-format nsh1
```





# Traffic Steering Service Chain Configuration Mode Commands

---

Traffic Steering uses the concept of service-chaining. Hence, define a Service Chain in the Traffic Steering mode.

## Command Modes

Exec > Global Configuration > Traffic Steering > Service Chain

Entering the above command sequence results in the following prompt:

```
[local] host_name(config-service-chain) #
```

- [do show, on page 1018](#)
- [end, on page 1019](#)
- [exit, on page 1020](#)
- [load-balancing, on page 1021](#)
- [sfp, on page 1022](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `do show`

---

**Usage Guidelines** Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# load-balancing

This command allows you to choose an algorithm to balance load among the appliances.

---

**Product** P-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Traffic Steering > Service Chain

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain) #
```

---

**Syntax Description** **load-balancing round-robin**

**round-robin**

Specifies the round robin algorithm. By default, round-robin is used as the load-balancing algorithm.

---

**Usage Guidelines** Use this command to choose an algorithm to load balance among the appliances.

## Example

The following command sets the default load balancing algorithm:

```
load-balancing round-robin
```

# sfp

This command allows you to configure a Service Function Path (SFP). The SFP is a path that an NSH packet takes in the service-chain.

---

**Product** P-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Traffic Steering > Service Chain

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain)#
```

---

**Syntax Description** **sfp direction uplink service-index** *service\_index\_value* **appliance-group** *appliance\_group\_name*

## direction

Moves the packet to the specified direction. The options for directions are listed as follows:

- Uplink—Applies the service function path to an uplink packet.

## service-index

Specifies the sequence of an appliance in SFP. A maximum of 4 appliances can be configured in an SFP.

For example, **service-index 1** indicates the first appliance in SFP.

---

## Usage Guidelines

Use this command to configure the SFP for an NSH packet that it should take in the service-chain. The **sfp direction** field defines the SFP path for uplink or downlink packets. For example, **sfp direction uplink** defines an SFP for uplink user packets.

The SFP contains multiple appliances. Details of the sequence of these appliances in SFP is available with StarOS. .

Configure the sequence of appliances by using service-index. For example, **service-index 1** indicates the first appliance in SFP.

## Example

The following command configures the SFP for a uplink packet in which the appliance group *firewall* is set to 2 as the service index:

```
sfp direction uplink service-index 2 appliance-group firewall
```



## TSI Server Configuration Mode Commands

---

### Command Modes

Exec > Global Configuration > Security Configuration > TSI Server Configuration

**configure > security > server talos-intelligence** *server-name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-server-tsi)#
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show, on page 1024](#)
- [end, on page 1025](#)
- [exit, on page 1026](#)
- [ip, on page 1027](#)
- [logging, on page 1028](#)
- [sftp, on page 1029](#)
- [update-time, on page 1030](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---



# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**end**

---

**Usage Guidelines**

Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ip

Configures the IP address and port number used to communicate with the Talos Security Intelligence (TSI) database server (Mediator).

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Security Configuration &gt; TSI Server Configuration

**configure > security > server talos-intelligence** *server-name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-server-tsi)#
```

---

**Syntax Description**

**ip address** *ip\_address* **port** *port\_number*  
**no ip**

**no ip**

Removes the configured TSI server.

**address** *ip\_address*

Specifies the IP address of the TSI database server (Mediator) from which security updates are received.

*ip\_address* must be specified in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation.**port** *port\_number*

Specifies the port number used to communicate with the TSI server (Mediator).

*port\_number* must be specified as **5341** for successful communication with the TSI database server..

---

**Usage Guidelines**

Use this command to configure the IP address and port number for the system to connect to the TSI database server.

**Example**

The following command configures the system to connect to a TSI server with the IP address of 10.1.10.10 on port number 5341:

```
ip address 10.1.10.10 port 5341
```

# logging

Configures the logging level for connection events to the TSI database server events and transactions.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Security Configuration > TSI Server Configuration

**configure > security > server talos-intelligence** *server-name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-server-tsi)#
```

---

**Syntax Description**

**logging level { error | warning | unusual | info | debug }**  
**no logging**

**no logging**

Removes the configured event logging level and returns the system to the default logging level of **error**.

**level { error | warning | unusual | info | debug }**

Specifies the level of information to be logged for TSI database server connectivity events. The following severities are supported:

- **error** – log error events and all events with a higher severity level
- **warning** – log warning events and all events with a higher severity level
- **unusual** – log unusual events and all events with a higher severity level
- **info** – log info events and all events with a higher severity level
- **debug** – log all events.

The default logging level severity is **error**.

---

**Usage Guidelines**

Use this command to set the logging level for events and transactions with the TSI database server.

# sftp

Configures the SFTP port number used to pull database updates from the Talos Security Intelligence (TSI) database server (Mediator).

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Security Configuration > TSI Server Configuration

**configure** > **security** > **server talos-intelligence** *server-name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-server-tsi)#
```

---

**Syntax Description**

[ **no** ] **port** *port\_number*

**no**

Removes the configured port number.

***port\_number***

Specifies the SFTP port number used to retrieve updates from the TSI database server (Mediator).

*port\_number* must specified as **2222** for successful communication with the TSI database server.

---

**Usage Guidelines**

Use this command to configure the SFTP port number for the system to retrieve update files from the TSI database server.

Update files are stored locally in /hd-raid/tsi/update.

# update-time

Configures the time of day when the system shall contact the Talos Security Intelligence (TSI) database server (Mediator) for security updates.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Security Configuration > TSI Server Configuration

**configure > security > server talos-intelligence** *server-name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-server-tsi)#
```

---

**Syntax Description** **update-time** **hour** *value* **minute** *value*  
**no update-time**

## **no update-time**

Removes the configured time of day when the system retrieves security updates.

## **hour** *value*

Specifies the hour of the day when the system retrieves security updates.

*value* must be an integer from 0 through 23.

The default is a value of zero for both hour and minute which results in a UTC of midnight.

## **minute** *value*

Specifies the hour of the day when the system retrieves security updates.

*value* must be an integer from 0 through 59.

The default is a value of zero for both hour and minute which results in a UTC of midnight.

---

## **Usage Guidelines**

Use this command to configure time of day when the system shall connect to the TSI database server to retrieve security updates. The security databases are updated once a day.

## **Example**

The following command configures the system to connect to a TSI server at 11:00 PM:

```
update-time hour 23 minute 0
```



# Tunnel Interface Configuration Mode Commands

## Command Modes

The Tunnel Interface Configuration Mode is used to create and manage the L2TP interface parameters within a specified context.

Exec > Global Configuration > Context Configuration > Ethernet Interface Configuration

**configure > context** *context\_name* > **interface** *interface\_name* **tunnel**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-if-tunnel) #
```



## Important

Available commands or keywords/variables vary based on platform type, product version, and installed license(s).

- [description, on page 1032](#)
- [end, on page 1033](#)
- [exit, on page 1034](#)
- [ip address, on page 1035](#)
- [ip ospf authentication-key, on page 1036](#)
- [ip ospf authentication-type, on page 1037](#)
- [ip ospf bfd, on page 1038](#)
- [ip ospf cost, on page 1039](#)
- [ip ospf dead-interval, on page 1040](#)
- [ip ospf hello-interval, on page 1041](#)
- [ip ospf message-digest-key, on page 1042](#)
- [ip ospf network, on page 1043](#)
- [ip ospf priority, on page 1044](#)
- [ip ospf retransmit-interval, on page 1045](#)
- [ip ospf transmit-delay, on page 1046](#)
- [ip vrf, on page 1047](#)
- [ipv6 address, on page 1048](#)
- [tunnel-mode, on page 1049](#)

# description

Sets the descriptive text for the current interface.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `description text`  
`no description`

**no**

Clears the description for the interface.

**text**

Specifies the descriptive text as an alphanumeric string of 0 through 79 characters.

---

**Usage Guidelines** Set the description to provide useful information on the interface's primary function, services, end users, etc. Any information useful may be provided.

## Example

```
description sampleInterfaceDescriptiveText
```



# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ip address

Specifies the primary and optional secondary IPv4 addresses and subnets for this interface.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip address ip_address { mask | /mask } [ secondary ip_address ] [ srp-activate ]
```

```
no ip address ip_address
```

---

**no**

Removes the IPv4 address from this interface.

---

***ip\_address*{ **mask** | /*mask* }**

Configures the IPv4 address and mask for the interface. *ip\_address* must be entered using IPv4 dotted-decimal notation. IPv4 dotted-decimal or CIDR notation is accepted for the mask.

**Important**

For IPv4 addresses, 31-bit subnet masks are supported per RFC 3021.

---

***secondary ip\_address***

Configures a secondary IPv4 address on the interface.

**Important**

You must configure the primary IPv4 address before you will be allowed to configure a secondary address.

---

**srp-activate**

Activates the IP address for Interchassis Session Recovery (ICSR). Enable this IPv4 address when the Service Redundancy Protocol (SRP) determines that this chassis is ACTIVE. Requires an ICSR license on the chassis to activate.

---

**Usage Guidelines**

The following command specifies the primary IP address and subnets for this interface.

---

**Example**

The following example configures an IPv4 address for this interface:

```
ip address 192.154.3.5/24
```

# ip ospf authentication-key

Configures the password for authentication with neighboring Open Shortest Path First (OSPF) routers.

---

**Product**

PDSN  
HA  
GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip ospf authentication-key [ encrypted ] password auth_key  
no ip ospf authentication-key
```

**no**

Deletes the authentication key.

**encrypted**

Use this keyword if you are pasting a previously encrypted authentication key into the CLI command.

**password *auth\_key***

Specifies the password to use for authentication as an alphanumeric string of 1 through 16 characters entered in clear text format.

---

**Usage Guidelines**

Use this command to set the authentication key used when authenticating with neighboring routers.

**Example**

To set the authentication key to 123abc, use the following command;

```
ip ospf authentication-key password 123abc
```

Use the following command to delete the authentication key;

```
no ip ospf authentication-key
```

# ip ospf authentication-type

Configures the OSPF authentication method to be used with OSPF neighbors over the logical interface.

---

**Product**

PDSN  
HA  
GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip ospf authentication-type { message-digest | null | text }  
no ip ospf authentication-type { message-digest | null | text }
```

**no**

Disable this function.

**message-digest**

Uses the message digest (MD) authentication method.

**null**

Uses no authentication, thus disabling either MD or clear text methods.

**text**

Uses the clear text authentication method.

---

**Usage Guidelines**

Use this command to set the type of authentication to use when authenticating with neighboring routers.

**Example**

To set the authentication type to use clear text, enter the following command;

```
ip ospf authentication-type text
```

# ip ospf bfd

Enables or disables OSPF Bidirectional Forwarding Detection (BFD) on this interface.

---

**Product**

PDSN  
HA  
GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip ospf bfd [ disable ]  
no ip ospf cost
```

**no**

Disable this function.

**disable**

Disables OSPF BFD on this interface.

---

**Usage Guidelines**

Enable or disable OSPF Bidirectional Forwarding Detection (BFD) on this interface.

**Example**

Use the following command to enable OSPF BFD;

```
ip ospf bfd
```

# ip ospf cost

Configures the cost associated with sending a packet over the OSPF logical interface.

---

**Product**

PDSN  
HA  
GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip ospf cost value  
no ip ospf cost
```

**no**

Disable this function.

**value**

Specifies the cost to assign to OSPF packets as an integer from 1 through 65535. Default: 10

---

**Usage Guidelines**

Use this command to set the cost associated with routes from the interface.

**Example**

Use the following command to set the cost to 20;

```
ip ospf cost 20
```

Use the following command to disable the cost setting;

```
no ip ospf cost
```

## ip ospf dead-interval

Configures the interval that the router should wait, during which time no packets are received and after which the router considers a neighboring router to be off-line.

---

**Product**

PDSN

HA

GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
[ no ] ip ospf dead-interval seconds
```

**no**

Returns the value to its default of 40 seconds.

***seconds***

Specifies the interval (in seconds) as an integer from 1 through 65535. This number is typical four times the hello-interval. Default: 40

---

**Usage Guidelines**

Use this command to set the dead intervals for OSPF communications.

**Example**

To set the dead-interval to *100*, use the following command;

```
ip ospf dead-interval 100
```



# ip ospf hello-interval

Configures the interval (in seconds) between sending OSPF hello packets.

---

**Product**

PDSN

HA

GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**ip ospf hello-interval** *seconds*

**no ip ospf hello-interval**

**no**

Returns the value to its default of 10 seconds.

***seconds***

Specifies the number of seconds between sending hello packets as an integer from 1 through 65535. Default: 10

---

**Usage Guidelines**

Specify the interval (in seconds) between sending OSPF hello packets.

**Example**

To set the hello-interval to 25, use the following command;

```
ip ospf hello-interval 25
```

# ip ospf message-digest-key

Enables or disables the use of MD5-based OSPF authentication.

---

## Product

PDSN  
HA  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Syntax Description

```
ip ospf message-digest-key key_id md5 [ encrypted ] password authentication_key  
no ip ospf message-digest-key key_id
```

### **no**

Deletes the key.

### **message-digest-key** *key\_id*

Specifies the key identifier number as an integer from 1 through 255.

### **encrypted**

Use this if you are pasting a previously encrypted authentication key into the CLI command.

### **password** *authentication\_key*

Specifies the password to use for authentication as an alphanumeric string of 1 through 16 characters entered in clear text format.

---

## Usage Guidelines

Use this command to create an authentication key that uses MD5-based OSPF authentication.

### **Example**

To create a key with the ID of 25 and a password of 123abc, use the following command;

```
ip ospf message-digest-key 25 md5 password 123abc
```

To delete the same key, enter the following command;

```
no ip ospf message-digest-key 25
```

# ip ospf network

Configures the Open Shortest path First (OSPF) network type.

---

## Product

PDSN  
HA  
GGSN

---

## Privilege

Security Administrator, Administrator

---

## Syntax Description

```
ip ospf network { broadcast | non-broadcast | point-to-multipoint |
point-to-point }
no ip ospf network
```

### no

Disable this function.

### broadcast

Sets the network type to broadcast.

### non-broadcast

Sets the network type to non-broadcast multi access (NBMA).

### point-to-multipoint

Sets the network type to point-to-multipoint.

### point-to-point

Sets the network type to point-to-point.

---

## Usage Guidelines

Use this command to specify the OSPF network type.

### Example

To set the OSPF network type to *broadcast*, enter the following command;

```
ip ospf network broadcast
```

To disable the OSPF network type, enter the following command;

```
no ip ospf network
```

# ip ospf priority

Designates the OSPF router priority.

---

**Product**

PDSN

HA

GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**ip ospf priority** *value*  
**no ip ospf priority** *value*

**no**

Disable this function.

**value**

Sets the priority value as an integer from 0 through 255.

---

**Usage Guidelines**

Use this command to set the OSPF router priority.

**Example**

To set the priority to 25, enter the following command:

```
ip ospf priority 25
```

To disable the priority, enter the following command:

```
no ip ospf priority
```

# ip ospf retransmit-interval

Configures the interval in (seconds) between LSA (Link State Advertisement) retransmissions.

---

**Product**

PDSN  
HA  
GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip ospf retransmit-interval seconds  
no ip ospf retransmit-interval
```

**no**

Returns the value to its default of 5 seconds.

***seconds***

Specifies the number of seconds between LSA (Link State Advertisement) retransmissions as an integer from 1 through 65535. Default: 5

---

**Usage Guidelines**

Configure the interval in (seconds) between LSA (Link State Advertisement) retransmissions.

**Example**

To set the retransmit-interval to *10*, use the following command;

```
ip ospf retransmit-interval 10
```

## ip ospf transmit-delay

Configures the interval (in seconds) that the router should wait before transmitting an OSPF packet.

---

**Product**

PDSN  
HA  
GGSN

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
ip ospf transmit-delay seconds  
no ip ospf transmit-delay
```

**no**

Returns the value to its default of 1 second.

***seconds***

Specifies the number of seconds that the router should wait before transmitting a packet as an integer from 1 through 65535. Default: 1

---

**Usage Guidelines**

Configure the interval (in seconds) that the router should wait before transmitting an OSPF packet.

**Example**

To set the transmit-delay to 5, use the following command;

```
ip ospf transmit-delay 5
```

# ip vrf

Associates this interface with a specific Virtual Routing and Forwarding (VRF) table.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**[ no ] ip vrf forwarding** *vrf\_name*

**no**

Removes the specified VRF table from this interface.

***vrf\_name***

Specifies the name of an existing VRF table as an alphanumeric string of 1 through 63 characters.

Use the Context Configuration mode **ip vrf forwarding** command to preconfigure the VRF name.

---

**Usage Guidelines**

The following command specifies a ranged IP address for this interface.

**Example**

The following example associates this interface with VRF named *vrf\_012*:

```
ip vrf forwarding vrf_012
```

# ipv6 address

Specifies an IPv6 address and subnet mask.

---

**Product**

PDSN

HA

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

[ **no** ] **ipv6 address** *ipv6\_address/mask*

**no**

Removes the IPv6 address from this interface.

***ipv6\_address/mask***

Specifies an individual host IP address to add to this host pool in IPv6 colon-separated-hexadecimal CIDR notation.




---

**Important**

On the ASR 5000, routes with IPv6 prefix lengths less than /12 and between the range of /64 and /128 are not supported.

---



---

**Usage Guidelines**

Configures the IPv6 address and subnet mask for a specific interface.

**Example**

The following example configures an IPv6 address for this interface:

```
ipv6 address 2002:0:0:0:0:0:c014:101/128
```



# tunnel-mode

Configures mode (transport protocol) of the tunnel.

---

**Product**

All products that support IPSec

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

```
tunnel-mode { gre | ipv6ip }
default tunnel-mode
```

**default**

Sets the default tunnel mode for this interface which is IPv6-to-IPv4 type.

**gre**

Sets the tunnel interface mode to Generic Routing Encapsulation (GRE) type and enters the GRE Tunnel Configuration mode, if required.




---

**Important**

This keyword is only available if an optional GRE Interface Tunneling license is installed to create IP-GRE tunnels.

---

**ipv6ip**

Sets the tunnel interface mode to IPv6-to-IPv4 type and creates the IPv6-to-IPv4 Tunnel Configuration mode, if required. This is the default mode.

---

**Usage Guidelines**

Use this command to set the tunnel mode type of GRE or IPv6-to-IPv4 for the tunneling interface. For SaMOG (S2a Mobility Over GTP), use the **tunnel-mode gre** command to configure a GRE tunnel for the IP-over-GRE feature.

**Example**

The following example configures GRE tunnel-mode for this interface:

```
tunnel-mode gre
```

tunnel-mode



## TWAN Profile Configuration Mode Commands

### Command Modes

The TWAN Profile Configuration Mode is used to configure the Radius client addresses (WLC) and access-type corresponding to the Radius clients to enable SaMOG to attach a session to a specific WiFi Access Network.

Exec > Global Configuration > Context Configuration > TWAN Profile Configuration

**configure** > **context** *context\_name* > **twan-profile** *twan\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-twan-profile)#
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [access-type](#), on page 1052
- [dictionary](#), on page 1054
- [do show](#), on page 1055
- [end](#), on page 1056
- [exit](#), on page 1057
- [radius](#), on page 1058
- [session-trigger](#), on page 1060
- [ue-address](#), on page 1062

# access-type

This command allows you to specify the access-type for the RADIUS client or specify a default access type for all RADIUS clients under a TWAN profile.

**Product** SaMOG

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > TWAN Profile Configuration

**configure** > **context** *context\_name* > **twan-profile** *twan\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-twan-profile)#
```

**Syntax Description**

```
access-type client { ipv4 | ipv6_address[/mask] } { eogre | ip | pmip }
access-type { eogre | ip [ vrf vrf_name ] | pmip }
no access-type { client { ipv4/ipv6_address[/mask] } | eogre | ip [ vrf ]
| pmip }
```

**no**

Removes the previously configured access type for the TWAN profile.

**client { *ipv4* | *ipv6\_address*[/*mask*] }**

Specifies the IP address of the RADIUS client.

*ipv4* | *ipv6\_address* must be an IP address in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation. *mask* must be a subnet mask bit of the IP address. The mask bit is a numeric value which corresponds to the number of bits in the subnet mask.

**ip [ vrf *vrf\_name* ]**

Specifies that all RADIUS clients under this TWAN profile will use the Layer 3 IP (L3IP) access type.

**vrf**: Specifies to use the VRF name to install the IP flow for L3IP subscriber session.

*vrf\_name* must be an alphanumeric string between 1 and 63 characters.

**eogre**

Specifies that all RADIUS clients under this TWAN profile will use the Ethernet over GRE (EoGRE) access type.

**pmip**

Specifies that all RADIUS clients under this TWAN profile will use the Proxy Mobile IP version 6 (PMIPv6) access type.

**Usage Guidelines**

Use this command to configure the access type for a specific NAS/WLC IP address or IP address with a subnet mask, or a common access type for the entire TWAN profile.

**Example**

The following command sets the default access type for the TWAN profile to EoGRE

```
access-type eogre arg1
```

The following command configures a RADIUS client with IP address *192.168.15.50* with access type as *eogre*, and a client with IP address *192.168.16.50* with access type as *pmip* under the current TWAN profile.

```
access-type client 192.168.15.50 eogre
```

```
access-type client 192.168.16.50 pmip
```

# dictionary

Configure the dictionary to be used to forward the permanent identity of the subscriber to the AAA server.

**Product**

SaMOG

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > TWAN Profile Configuration

**configure** > **context** *context\_name* > **twan-profile** *twan\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-twan-profile)#
```

**Syntax Description**

```
dictionary { custom70 | custom71 }  
default dictionary
```

**default**

Configures the dictionary to its default value.

Default: custom70

**Usage Guidelines**

Use this command to configure the dictionary to forward the permanent identity of the subscriber to the AAA server. The dictionary configuration at the TWAN profile level will be applied to all the RADIUS clients under that TWAN profile.

Configure the custom71 dictionary when Cisco WLC is used with PMIPv6 as the access-type. Configuring the custom71 dictionary enables attributes like the UE's permanent identity (NAI), subscribed APN, network protocol (PMIPv6), and LMA address (CGW service's bind address) to be sent in the Cisco Vendor-specific attributes to WLC. The WLC uses this information to build the PMIPv6 PBU to the SaMOG gateway when the **aaa-override** option is enabled on the Cisco WLC. These attributes are not sent when the custom70 dictionary is configured.

To configure the dictionary to use for individual RADIUS clients, use the **dictionary** keyword in the **radius client** command under the TWAN Profile Configuration Mode.

**Example**

The following command configures the TWAN profile to use custom71 dictionary:

```
dictionary custom71
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>exit</b>
<b>Usage Guidelines</b>	Use this command to return to the parent configuration mode.

# radius

This command allows you to specify the IP address and shared secret of the RADIUS accounting and authentication client from which RADIUS accounting and authentication requests are received or configure the Radius VRF for an IPoVLAN model.

**Product** SaMOG

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > TWAN Profile Configuration

**configure > context *context\_name* > twan-profile *twan\_profile\_name***

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-twan-profile)#
```

**Syntax Description**

```
radius { client ipv4 | ipv6_address[/mask] [ encrypted ] key value [ disconnect-message [ dest-port destination_port_number] ] [ dictionary { custom70 | custom71 } ] | ip vrf vrf_name }  
no radius { client ipv4/ipv6_address[/mask] | ip vrf vrf_name }
```

**no**

Removes the previously configured RADIUS client address or IP VRF under this TWAN profile.

**client{ *ipv4* | *ipv6\_address*[/*mask*] }**

Specifies the IP address of the RADIUS client (WLC).

*ipv4* | *ipv6\_address* must be an IP address in IPv4 dotted-decimal or IPv6 colon-separated-hexadecimal notation. *mask* must be a subnet mask bit of the IP address. The mask bit is a numeric value which corresponds to the number of bits in the subnet mask.



**Important**

A maximum of 16 RADIUS clients can be configured under one TWAN profile.

**[ encrypted ] key *value***

Specifies the shared secret key used to authenticate the client to the servers. The **encrypted** keyword indicates that the key specified is encrypted.

The key *value* must be an alphanumeric string of 1 through 127 characters without encryption, and 1 through 288 characters with encryption enabled.

The **encrypted** keyword is intended only for use by the chassis while saving configuration scripts. The system displays the encrypted keyword in the configuration file as a flag that the variable following the **key** keyword is the encrypted version of the plaint text key. Only the encrypted key is saved as part of the configuration file.

**disconnect-message**

Specifies to send RADIUS disconnect message to the configured RADIUS accounting client in call failure scenarios.

**dest-port *destination\_port\_number***

Specifies the port number to which the disconnect message must be sent.

*destination\_port\_number* must be an integer from 1 through 65535.

**dictionary { *custom70* | *custom71* }**

Specifies to forward the permanent identity of the subscriber to the AAA server using the *custom70* or *custom71* dictionary.

Configure the *custom71* dictionary when Cisco WLC is used with PMIPv6 as the access-type. Configuring the *custom71* dictionary enables attributes like the UE's permanent identity (NAI), subscribed APN, network protocol (PMIPv6), and LMA address (CGW service's bind address) to be sent in the Cisco Vendor-specific attributes to WLC. The WLC uses this information to build the PMIPv6 PBU to the SaMOG gateway when the **aaa-override** option is enabled on the Cisco WLC. These attributes are not sent when the *custom70* dictionary is configured.

To configure the dictionary to use for all RADIUS clients belonging to a specific TWAN profile, use the **dictionary** command under the TWAN Profile Configuration Mode.

Default: *custom70*

**ip vrf *vrf\_name***

Associates the specific TWAN profile with a Virtual Routing and Forwarding (VRF) Context instance for RADIUS communication.

*vrf\_name* must be an alphanumeric string from 1 through 63 characters.

**Usage Guidelines**

Use this command to specify the IP address and shared secret of the RADIUS accounting and authentication client from which RADIUS accounting and authentication requests are received or configure the VRF for RADIUS communication.

**Example**

The following example configures a RADIUS client with an IP address of *193.14.23.1* and an encrypted key of value *enc32*

```
radius client 193.14.23.1 encrypted key enc32
```

# session-trigger

This command specifies the protocol type that will trigger session creation on the SaMOG Gateway.

**Product**

SaMOG

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > TWAN Profile Configuration

**configure** > **context** *context\_name* > **twan-profile** *twan\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-twan-profile)#
```

**Syntax Description**

```
session-trigger { dhcp [ location { circuit-id | remote-id } ] | radius
[ acct ] | pmip }
default session-trigger
no session-trigger dhcp location
```

**default**

Resets the configuration to its default value.

Default: RADIUS (authentication)-based session trigger.

**no**

If previously configured, removes the DHCP configuration.

**dhcp [ location { circuit-id | remote-id } ]**

Specifies the session trigger protocol as DHCP, and the sub-option to choose the UE location from the DHCP-Relay-Agent-Info option (DHCP option 82).

At least one TWAN profile must have a DHCP session trigger enabled. If multiple TWAN profiles have DHCP session trigger enabled, the first configured TWAN profile with DHCP session trigger is used.

**radius [ acct ]**

Specifies the session trigger protocol as RADIUS messages. The default configuration is RADIUS (authentication)-based session trigger.

**acct**: Specifies to trigger session on receiving RADIUS accounting messages.

**pmip**

Specifies the session trigger protocol as PMIP. SaMOG can create sessions based on the PMIPv6 (PBU) messages from the Access Point (AP).

**Usage Guidelines**

Use this command to specify the protocol type that will trigger session creation on the SaMOG Gateway.

**Important**

If this TWAN profile is configured with a DHCP session trigger, the access type must be EoGRE.

**Example**

The following command sets the session trigger to DHCP:

```
session-trigger dhcp location circuit-id
```

The following command sets the session trigger to PMIP:

```
session-trigger pmip
```

# ue-address

This command allows you to specify how the UE address allocation should be handled.

**Product**

SaMOG

**Privilege**

Security Administrator, Administrator

**Command Modes**

Exec > Global Configuration > Context Configuration > TWAN Profile Configuration

**configure** > **context** *context\_name* > **twan-profile** *twan\_profile\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-twan-profile)#
```

**Syntax Description**

```
ue-address { dhcp | twan }  
no ue-address
```

**no**

If previously configured, disables the UE allocation configuration.

**dhcp**

Specifies that the UE address will be assigned at SaMOG by P-GW or GGSN, and sent to the UE using DHCP.

**twan**

Specifies that the UE address will be assigned at TWAN also. SaMOG receives the TWAN UE address through the Accounting Start Framed-IP-Address message, and NAT is performed between the two UE addresses.

**Usage Guidelines**

Use this command to specify how the UE address allocation should be handled. This configuration can be used to detect whether a DHCP request is expected or if the configuration setup is an IP@WLAN (no DHCP required) model.



**Important**

If the configured access-type is PMIP or EoGRE, the ue address configuration is ignored.

If the configured access-type is IP, and no ue address is configured, the call setup will fail.



## UDR Format Configuration Mode Commands

---

The UDR Format Configuration Mode enables configuring User Detail Record (UDR) formats.

---

### Command Modes

Exec > ACS Configuration > UDR Format Configuration

**active-charging service** *service\_name* > **udr-format** *format\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-acs-udr) #
```



---

### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

---

- [attribute](#), on page 1064
- [do show](#), on page 1070
- [end](#), on page 1071
- [event-label](#), on page 1072
- [exit](#), on page 1073
- [rule-variable](#), on page 1074

# attribute

This command allows you to specify the fields and their order in UDRs.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > UDR Format Configuration

**active-charging service** *service\_name* > **udr-format** *format\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-acs-udr)#
```

---

**Syntax Description**

```
attribute attribute { [ format { MM/DD/YY-HH:MM:SS | MM/DD/YYYY-HH:MM:SS | YYYY/MM/DD-HH:MM:SS | YYYYMMDDHHMMSS | seconds } [ localtime ] | [ { bytes | pkts } { downlink | uplink } ] ] priority priority }
no attribute attribute [ priority priority ]
```

**no**

If added previously, removes the specified attribute from the UDR format.

**attribute *attribute***

Specifies the attribute.

*attribute* must be one of the following:

Attribute	Description
<b>diameter-session-id</b>	This attribute reports Diameter session identifier. <b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.
<b>failure-handling-mode</b>	This attribute reports failure handling mode in case the Online Charging System (OCS) goes abnormal.
<b>nemo-prefix-list</b>	This attribute reports the VRF names associated with the base session of NEMO, and NEMO MR Prefixes. <b>Important</b> This attribute is customer specific, and is available only with NEMO license.
<b>num-nemo-prefix</b>	This attribute reports the number of NEMO MR Prefixes. <b>Important</b> This attribute is customer specific, and is available only with NEMO license.



Attribute	Description
<b>radius-called-station-id</b>	This attribute reports the Called Station ID of the mobile handling the flow.
<b>radius-calling-station-id</b>	This attribute reports the Calling Station ID of the mobile handling the flow.
<b>radius-fa-nas-identifier</b>	This attribute reports the RADIUS NAS identifier of Foreign Agent (FA).
<b>radius-fa-nas-ip-address</b>	This attribute reports the RADIUS IP address of Foreign Agent (FA).
<b>radius-nas-identifier</b>	This attribute reports the RADIUS NAS identifier.
<b>radius-nas-ip-address</b>	This attribute reports the RADIUS NAS IP address. Note that this attribute is interchangeable with <b>sn-st16-ip-addr</b> for the user.
<b>radius-user-name</b>	This attribute reports the user name associated with the flow.
<b>sn-3gpp2-bsid</b>	This option has been deprecated. To configure this attribute see the <b>rule-variable</b> command.
<b>sn-3gpp2-carrier-id</b>	This option has been deprecated. To configure this attribute see the <b>rule-variable</b> command.
<b>sn-3gpp2-esn</b>	This option has been deprecated. To configure this attribute see the <b>rule-variable</b> command.
<b>sn-3gpp2-meid</b>	This option has been deprecated. To configure this attribute see the <b>rule-variable</b> command.
<b>sn-3gpp2-service-option</b>	This option has been deprecated. To configure this attribute see the <b>rule-variable</b> command.
<b>sn-acct-beginning-session</b>	This attribute reports the Session Beginning information. <b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.

Attribute	Description
<b>sn-acct-session-continue</b>	<p>This attribute reports the Session Continue information.</p> <p><b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.</p>
<b>sn-acct-session-id</b>	<p>This attribute reports the Accounting Session identifier.</p>
<b>sn-acct-session-time</b>	<p>This attribute reports the duration from acct-status-type:start to acct-status-type:stop.</p> <p><b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.</p>
<b>sn-acct-status-type</b>	<p>This attribute reports the Accounting Status identifier.</p> <p><b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.</p>
<b>sn-charging-type</b>	<p>This attribute reports the charging type: offline or online.</p> <p><b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.</p>
<b>sn-closure-reason</b>	<p>This attribute reports the reason for termination of the flow/UDR:</p> <ul style="list-style-type: none"> <li>• 0 = CALL_TERMINATION — normal, such as subscriber session ended</li> <li>• 1 = PDSN_HO — handoff control processing specified</li> <li>• 2 = TIME_LIMIT</li> <li>• 3 = VOLUME_LIMIT</li> <li>• 4 = MGMT_INTERVENTION</li> <li>• 5 = ACCT_SESS_START</li> <li>• 6 = CCRU_RESPONSE</li> <li>• 7 = OFFLINE_CHARGING — for UDRs generated when offline charging trigger is received from DCCA</li> </ul>
<b>sn-content-id</b>	<p>This attribute reports the unique identifier for the content-id.</p>

Attribute	Description
<b>sn-content-label</b>	This attribute reports the identifier for text label for content-id.
<b>sn-content-vol</b>	This attribute reports the identifier for content volume.
<b>sn-correlation-id</b>	This attribute reports the RADIUS correlation identifier.
<b>sn-duration</b>	This attribute reports the time difference between the first and last packet of a single data flow accounted in the UDR record.  For example, the time difference between the first ICMP echo request and the last ICMP echo response before the record gets written for the content-id.
<b>sn-end-time [ format <i>format</i>]</b>	This attribute reports the timestamp for last packet of flow in UTC.
<b>sn-fa-correlation-id</b>	This attribute reports the RADIUS Correlation Identifier of the Foreign Agent (FA).
<b>sn-fa-ip-address</b>	This attribute reports IP address of the FA.
<b>sn-filler-blank</b>	This attribute inserts a blank filler field, generates an empty UDR field.
<b>sn-filler-zero</b>	This attribute inserts a "0" in the UDR field.
<b>sn-format-name</b>	This attribute reports name of the UDR format used.
<b>sn-group-id</b>	This attribute reports the sequence group identifier for the records.
<b>sn-ha-ip-address</b>	This attribute reports IP address of the Home Agent (HA).  <b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.
<b>sn-local-seq-no</b>	This attribute reports unique local sequence number of UDR identifier per ACSMgr/SessMgr and linearly increasing in UDR file.
<b>sn-ocs-ip-address</b>	This attribute reports IP address of the Online Charging Server.  <b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.
<b>sn-rulebase</b>	This attribute reports name of the ACS rulebase used.

Attribute	Description
<b>sn-sequence-no</b>	This attribute reports unique sequence number (per <b>sn-sequence-group</b> and <b>radius-nas-ip-address</b> ) of UDR identifier and linearly increasing in UDR file.
<b>sn-served-bsa-addr</b>	This attribute reports address of Base Station Area being served.
<b>sn-service-name</b>	This attribute reports name of the ACS service.
<b>sn-st16-ip-addr</b>	This option has been deprecated. This attribute reports IP address of the chassis handling this flow. This attribute is interchangeable with <b>radius-nas-ip-address</b> for other systems.
<b>sn-start-time</b> [ <i>format format</i> ]	This attribute reports timestamp for first packet of flow in UTC.
<b>sn-stream-number</b>	This attribute reports unique UDR billing record identifier. <b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.
<b>sn-subscriber-id</b>	This attribute reports subscriber ID.
<b>sn-subscriber-ipv4-address</b>	This attribute reports the IPv4 address of the subscriber.
<b>sn-subscriber-ipv6-address</b>	This attribute reports the IPv6 address of the subscriber.
<b>sn-subscriber-nat-flow-ip</b>	This attribute reports NAT IP address(es) of NAT-enabled subscriber.
<b>sn-timestamp</b>	This attribute reports timestamp when the UDR is actually generated. <b>Important</b> This attribute is customer specific, and is only available in 8.3 and later releases.
<b>sn-vrf-name</b>	This attribute indicates the VRF name associated with the base session of NEMO. <b>Important</b> This is a customer-specific attribute.

**format** { MM/DD/YY-HH:MM:SS | MM/DD/YYYY-HH:MM:SS | YYYY/MM/DD-HH:MM:SS | YYYYMMDDHHMMSS | seconds }

Specifies the timestamp format.

**localtime**

Specifies the local time. By default, timestamps are displayed in Coordinated Universal Time (UTC).

**{ bytes | pkts }{ downlink | uplink }**

Specifies bytes/packets sent/received from/by mobile.

**priority *priority***

Specifies the position priority of the field within the UDR. Lower numbered priorities (across all attribute, event-label, and rule-variable) occur first.

*priority* must be an integer from 1 through 65535. Up to 50 position priorities (across all attribute, event-label, and rule-variable) can be configured.

---

**Usage Guidelines**

Use this command to set the attributes and priority for UDR file format.

A particular field in UDR format can be entered multiple times at different priorities. While removing the UDR field using the **no attribute** command, you can either remove all occurrences of a particular field by specifying the field name or remove a single occurrence by additionally specifying the optional **priority** keyword.

Consider the following scenario. If the volume/time threshold interval is large enough (or disabled). At time  $t=0$ , 10 ICMP packets are sent, which takes 9 seconds. There is nothing for the next 100 seconds, and then again 10 ICMP packets are sent which takes 10 seconds, and then again nothing for next the 60 seconds and then the session is terminated.

In this scenario:

- sn-start-time should be  $t = 0$ .
- sn-end-time should be  $t = 0+9+100+10$  (sn-end-time would be the last ICMP packet sent).
- sn-duration should be sn-end-time minus sn-start-time, i.e.  $0+9+100+10 - 0 = 119$  seconds (since the ICMP flow would exist between the two intervals of sending ICMP packets, the sn-start-time would be that of the first packet of the flow and sn-end-time of the last packet (20th packet). Hence, sn-duration would take into account all the seconds between the first and last packet of the flow).

**Example**

The following is an example of this command:

```
attribute radius-user-name priority 12
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# event-label

This command allows you to specify an optional event label/identifier to be used as an attribute in the UDRs.

---

## Product

All

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > ACS Configuration > UDR Format Configuration

**active-charging service** *service\_name* > **udr-format** *format\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-acs-udr)#
```

---

## Syntax Description

**event-label** *event\_label* **priority** *priority*  
**no event-label**

**no**

If previously configured, removes the event label configuration.

### **event\_label**

Specifies the event label/identifier to be used as UDR attribute.

*event\_label* must be an alphanumeric string of 1 through 63 characters.

### **priority priority**

Specifies the Comma Separated Value (CSV) position of the attribute (label/identifier) in the UDR.

*priority* must be an integer from 1 through 65535.

---

## Usage Guidelines

Use this command to configure an optional event label/identifier as an attribute in the UDR and its position in the UDR.

### **Example**

The following is an example of this command:

```
event-label radius_csv1 priority 23
```



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# rule-variable

This command allows you to specify fields and their order in UDRs.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > ACS Configuration > UDR Format Configuration

**active-charging service** *service\_name* > **udr-format** *format\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-acs-udr)#
```

---

**Syntax Description**

**rule-variable** *rule\_variable* **priority** *priority*  
**no rule-variable** *rule\_variable* [ **priority** *priority* ]

**no**

If previously configured, removes the specified rule variable configuration.

**rule-variable** *rule\_variable*

Specifies the rule variable for the UDR format.

*rule\_variable* must be one of the following options:

- **bearer 3gpp2**: Bearer-related configuration:

- **always-on**
- **bsid**
- **carrier-id**
- **esn**
- **ip-qos**
- **ip-technology**
- **meid**
- **release-indicator**
- **serv-MDN**
- **service-option**
- **session-begin**
- **session-continue**

**Important**

For more information on protocol-based rules see the *ACS Ruledef Configuration Mode Commands* chapter.

**priority *priority***

Specifies the CSV position of the field (protocol rule) in the UDR.

*priority* must be an integer from 1 through 65535.

**Usage Guidelines**

Use this command to specify what field appears in which order in the UDR.

A particular field in UDR format can be entered multiple times at different priorities. While removing the UDR field using the **no rule-variable** command, you can either remove all occurrences of a particular field by specifying the field name, or remove a single occurrence by additionally specifying the optional priority keyword.

**Example**

The following is an example of this command:

```
rule-variable bearer 3gpp2 bsid priority 36
```





## UDR Module Configuration Mode Commands

The UDR Module Configuration Mode allows you to configure Usage Data Record (UDR) file transfer parameters.

### Command Modes

Exec > Global Configuration > Context Configuration > UDR Module Configuration

**configure > context *context\_name* > udr-module active-charging-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-udr) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [cdr, on page 1078](#)
- [do show, on page 1083](#)
- [end, on page 1084](#)
- [exit, on page 1085](#)
- [file, on page 1086](#)

# cdr

This command allows you to configure EDR/UDR file transfer parameters.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > UDR Module Configuration

**configure** > **context** *context\_name* > **udr-module active-charging-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-udr)#
```

---

**Syntax Description**

```
cdr { purge { storage-limit storage_limit | time-limit time_limit } [ max-files
max_records_to_purge ] | push-interval push_interval | push-trigger
space-usage-percent trigger_percentage | remove-file-after-transfer |
transfer-mode { pull [ module-only ] | push primary { encrypted-url
encrypted_url | url url } [ [ max-files max_records ] [ max-tasks task_num ] [
module-only ] [ secondary { encrypted-secondary-url encrypted_secondary_url |
secondary-url secondary_url } ] [ source-address ip_address ] [ via
local-context ] + ] | use-harddisk }
default cdr [ purge | push-interval | push-trigger space-usage-percent |
remove-file-after-transfer | transfer-mode [ pull [ module-only] | push
primary via ] | use-harddisk ] +
no cdr [ purge | remove-file-after-transfer | use-harddisk ] +
```

**default**

Configures the default setting for the specified keyword(s):

- **purge**: Disabled
- **push-interval**: 300 seconds
- **push-trigger**: 80 percent
- **remove-file-after-transfer**: Disabled
- **transfer mode**: Pull
- **push via**: line cardMIO is used for push
- **use-harddisk**: Disabled




---

**Important**

The **use-harddisk** keyword is only available on ASR 5000 chassis.

---

**no**

If previously configured, disables the specified configuration:

- **purge**: Disables purging of records.
- **remove-file-after-transfer**: Retains a copy of the file even after it has been pushed or pulled to another server.
- **use-harddisk**: Disables data storage on the SMC hard disk.

**Important**

The **use-harddisk** keyword is available only on the ASR 5000 chassis.

**purge { storage-limit *storage\_limit* | time-limit *time\_limit* } [ max-files *max\_records\_to\_purge* ]**

Specifies to purge/delete the UDR records based on "time" or "volume" limit.

When the configured threshold limit is reached on the hard disk drive, the records that are created dynamically in the `/mnt/hd-raid/data/records/` directory are automatically deleted. Files that are manually created should be deleted manually.

- **storage-limit *storage\_limit***: Specifies to start deleting files when the specified megabytes of space is used for storage.  
*storage\_limit* specifies the volume limit for the record files, in megabytes, and must be an integer from 10 through 143360.
- **time-limit *time\_limit***: Specifies to start deleting files older than the specified time limit.  
*time\_limit* specifies the time limit for the record files, and must be an integer from 600 through 2592000.
- **max-files *max\_records\_to\_purge***: Specifies the maximum number of records to purge.  
*max\_records\_to\_purge* can be 0, or an integer from 1000 through 10000. If the value is set to 0, during each cycle, the records will be deleted until the purge condition is satisfied. If the value is set between 1000 and 10000, during each cycle, the records will be deleted until either the purge condition is satisfied or the number of records deleted equals the configured **max-files** value.

Default: 0

**push-interval *value***

Specifies the transfer interval (in seconds) to push UDR/EDR files to an external file server.

*value* must be an integer from 60 through 3600.

Default: 300

**push-trigger space-usage-percent *trigger\_percentage***

Specifies the UDR/EDR disk space utilization percentage, upon reaching which an automatic push is triggered and files are transferred to the configured external server.

*trigger\_percentage* specifies the UDR/EDR disk utilization percentage for triggering push, and must be an integer from 10 through 80.

Default: 80%

**remove-file-after-transfer**

Specifies that the system must delete UDR/EDR files after they are transferred to the external file server.

Default: Disabled

**transfer-mode** { **pull** [ **module-only** ] | **push primary** { **encrypted-url** *encrypted\_url* | **url** *url* } [ [ **max-files** *max\_records* ] [ **max-tasks** *task\_num* ] [ **module-only** ] [ **secondary** { **encrypted-secondary-url** *encrypted\_secondary\_url* | **secondary-url** *secondary\_url* } ] [ **source-address** *ip\_address* ] [ **via local-context** ] + ]

Specifies the UDR/EDR file transfer mode.

- **pull**: Specifies that the L-ESS is to pull the UDR files.
- **push**: Specifies that the system is to push UDR files to the configured L-ESS.
- **max-files** *max\_records*: Specifies the maximum number of files sent per iteration based on configured file size.
- **max-tasks** *task\_num*: Specifies the maximum number of tasks (child processes) that will be spawned to push the files to the remote server. The *task\_num* must be an integer from 4 through 8.

Default: 4000

Default: 4

**Important**

Note that increasing the number of child processes will improve the record transfer rate. However, spawning more child will consume additional resource. So, this option needs to be used with proper resource analysis.

- **module-only**: Specifies that the transfer-mode is only applicable to the UDR module; if not configured it is applicable to both EDR and UDR modules. This enables support for individual record transfer-mode configuration for each module.
- **primary encrypted-url** *encrypted\_url*: Specifies the primary location in encrypted format to which the system pushes the UDR files.  
*encrypted\_url* must be the primary location name in an encrypted format, and must be an alphanumeric string of 1 through 1024 characters.
- **primary url** *url*: Specifies the primary location to which the system pushes the UDR files.  
*url* must be the primary location, and must be an alphanumeric string of 1 through 1024 characters in the format: *//user:password@host:[port]/directory*.
- **secondary encrypted-secondary-url** *encrypted\_secondary\_url*: Specifies the secondary location in encrypted format to which the system pushes the UDR files when the primary location is unreachable or fails.  
*encrypted\_secondary\_url* must be the location in an encrypted format, and must be an alphanumeric string of 1 through 1024 characters.
- **secondary secondary-url** *secondary\_url*: Specifies the secondary location to which the system pushes the UDR files when the primary location is unreachable or fails.



*secondary\_url* must be the secondary location, and must be an alphanumeric string of 1 through 1024 characters in the format: *//user:password@host:[port]/directory*.

- **source-address** *ip\_address*: Configures the source IP address to be used to establish the connection for the SFTP/SSH file-transfer operation.
- **via local-context**: Selects the LC/SPIO for transfer of UDRs. The system pushes the UDR files via SPIO in the local context.
- **via local-context**: Selects the MIO for transfer of UDRs. The system pushes the UDR files via the MIO in the local context.

### use-harddisk



#### Important

The **use-harddisk** keyword is available only on the ASR 5000 chassis.

Specifies that on an ASR 5000 chassis, the hard disk on the SMC will be used to store UDR/EDR files. When configured to use the hard disk for UDR/EDR storage, UDR/EDR files are transferred from packet processing cards to the hard disk on the SMC.

Specifies that on an ASR 5500 chassis, the hard disk array on the FSCs will be used to store UDR/EDR files. On configuring to use the array for UDR/EDR storage, UDR/EDR files are transferred from DPCs to the array.

Default: Disabled

+

Indicates that more than one of the previous keywords can be entered within a single command.

#### Usage Guidelines

Use this command to configure how UDRs are moved and stored.

On the ST16 chassis, run this command only from the context where the UDR/EDR module is configured. Running this command in any other context will fail and deliver an error message.

On the ASR 5000/ASR 5500 chassis, run this command only from the local context. Running in any other context would fail and deliver an error message.

If PUSH transfer mode is configured, the L-ESS server URL to which the UDR files need to be transferred to must be specified. The configuration allows a primary and a secondary server to be configured. Configuring the secondary server is optional. Whenever a file transfer to the primary server fails for four consecutive times, the files will be transferred to the secondary server. The transfer will switch back to the original primary server when:

- Four consecutive transfer failures to the secondary server occur
- After switching from the primary server, 30 minutes elapses

When changing the transfer-mode from pull to push, disable the PULL from L-ESS and then change the transfer mode to push. Make sure that the push server URL configured is accessible from the local context. Also, make sure that the base directory that is mentioned contains udr directory created within it.

When changing the transfer-mode from push to pull, after changing, enable PULL on the L-ESS. Any of the ongoing PUSH activity will continue till all the scheduled file transfers are completed. If there is no PUSH

activity going on at the time of this configuration change, all the PUSH related configuration is nullified immediately.

The **cdr use-harddisk** command is available only on the ASR 5000/ASR 5500 chassis. This command can be run only in a context where CDRMOD is running. Configuring in any other context will result in failure with the message *"Failure: Please Check if CDRMOD is running in this context or not."*

The **cdr use-harddisk** command can be configured either in the UDR or EDR module, but will be applicable to both record types. Configuring in one of the modules will prevent the configuration to be applied in the other module. Any change to this configuration must be done in the module in which it was configured, the change will be applied to both record types.

The VPNMgr can send a maximum of 4000 files to the remote server per iteration. However if the individual file size is big (say when compression is not enabled), then while transferring 4000 files SFTP operation takes a lot of time. To prevent this, the **cdr transfer-mode push** command can be configured with the keyword **max-files**, which allows operators to configure the maximum number of files sent per iteration based on configured file size.

### Example

The following command configures the system to retain a copy of the data file after it has been transferred to the storage location:

```
no cdr remove-file-after-transfer
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# file

This command allows you to configure UDR file parameters.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; Context Configuration &gt; UDR Module Configuration

**configure** > **context** *context\_name* > **udr-module active-charging-service**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-udr)#
```

---

**Syntax Description**

```
file [ charging-service-name { include | omit } ] [ compression { gzip | none } ] [ current-prefix string ] [ delete-timeout seconds ] [ directory directory_name ] [ exclude-checksum-record ] [ field-separator { hyphen | omit | underscore } ] [ file-sequence-number rulebase-seq-num ] [ headers ] [ name file_name ] [ reset-indicator ] [ rotation [ num-records number | time seconds | volume bytes ] ] [ sequence-number { length length | omit | padded | padded-six-length | unpadded } ] [ storage-limit limit ] [ time-stamp { expanded-format | rotated-format | unix-format } ] [ trailing-text string ] [ trap-on-file-delete ] [ udr-seq-num ] [ xor-final-record ] +
default file [ charging-service-name ] [ compression ] [ current-prefix ] [ delete-timeout ] [ directory ] [ field-separator ] [ file-sequence-number ] [ headers ] [ name ] [ reset-indicator ] [ rotation { num-records | time | volume } ] [ sequence-number ] [ storage-limit ] [ time-stamp ] [ trailing-text ] [ udr-seq-num ]
```

**default**

Configures the default setting for the specified keyword(s). Using the **default file** command will reset some but not all keyword parameters to their default values. To ensure that the default is reset for a specific parameter, include the corresponding keyword in the command.

**charging-service-name { include | omit }**

Specifies to include/exclude name of the charging service in the file name.

- **include**: Includes name of the charging service in the UDR file name.
- **omit**: Excludes name of the charging service in the UDR file name.

Default: **include**

**compression { gzip | none }**

Configures gzip compression of the UDR file.

- **gzip**: Enables GNU zip compression of the UDR file at approximately 10:1 ratio.

- **none**: Disables Gzip compression.

Default: **none**

#### **current-prefix *string***

Specifies a string to add to the beginning of the UDR file that is currently being used to store UDR records. *string* must be an alphanumeric string of 1 through 31 characters.

Default: curr

#### **delete-timeout *seconds***

Specifies a timeout period (in seconds) when completed UDR files are deleted. By default, files are never deleted.

*seconds* must be an integer from 3600 through 31536000.

Default: Disabled

#### **directory *directory\_name***

Specifies a subdirectory in the default directory in which to store UDR files.

*directory\_name* must be an alphanumeric string of 1 through 191 characters.

Default: /records/udr

#### **exclude-checksum-record**

When entered, this keyword excludes the final record containing #CHECKSUM followed by the 32-bit Cyclic Redundancy Check (CRC) of all preceding records from the UDR file.

Default: Disabled, inserts checksum record into the UDR file header.

#### **field-separator { hyphen | omit | underscore }**

Specifies the field separators to be used between two fields of a UDR file name.

- **hyphen**: Specifies to use '-' (hyphen) as the field separator.
- **omit**: Excludes the field separator.
- **underscore**: Specifies to use '\_' (underscore) as the field separator.

Default: **underscore**

#### **file-sequence-number rulebase-seq-num**

Generates unique file sequence numbers for different rulebase-format-name combinations.

#### **headers**

Includes a file header summarizing the record layout.

**name *file\_name***

Default: udr

Specifies a string to use as the base file name for UDR files.

*file\_name* must be an alphanumeric string of 1 through 31 characters. The file name format is as follows:

*base\_rulebase\_format\_sequencenum\_timestamp*

- *base*: Specifies type of record in file or contains the operator-specified string. Default: udr
- *rulebase*: Specifies the name of the ACS rulebase. UDRs from different rulebases go into different UDR files.
- *format*: Specifies the name of the UDR format if **single-udr-format** is specified, else the format field (and the trailing underscore) is omitted from the file name.
- *sequencenum*: This is a 5-digit sequence number to detect the missing file sequence. It is unique among all UDR files on the system.
- *timestamp*: Contains a timestamp based on file creation time in UTC formatted as: MMDDYYYYHHMMSS.

UDR files that have not been closed have a string added to the beginning of their file names.

File name for a UDR file in CSV format that contains information for a rulebase named *rulebase1* and a UDR schema named *udr\_schema1* appears as follows:

*udr\_rulebase1\_udr\_schema1\_00005\_01302006143409*

If file name is not configured, the system creates files for EDRs/UDRs/FDRs (xDRs) using the following name template with limits to 256 characters:

*basename\_ChargSvcName\_timestamp\_SeqNumResetIndicator\_FileSeqNumber*

- *basename*: A global-based configurable text string that is unique per system that uniquely identifies the global location of the system running ACS.
- *ChargSvcName*: A system context-based configurable text string that uniquely identifies a specific context-based charging service.
- *timestamp*: Date and time at the instance of file creation. Date and time in the format: "MMDDYYYYHHmmSS", where HH is a 24-hour value from 00-23.
- *SeqNumResetIndicator*: A one-byte counter used to discern the potential for duplicated FileSeqNumber with a range of 0 through 255, which is incremented by a value of 1 for the following conditions:
  - Failure of an ACS software process on an individual packet processing card
  - Failure of the system such that a second system takes over (for example, a standby or backup chassis put in place according to Inter-chassis Session Recovery)
  - File Sequence Number (FileSeqNumber) rollover from 999999999 to 0
- *FileSeqNumber*: unique file sequence number for the file is a 9-digit integer from 000000000 through 999999999. It is unique on each chassis.



File name for a closed xDR file in CSV format that contains information for ACS *xyz\_city1* and charging service name *prepaid2* with timestamp *12311969190000*, and file sequence number counter reset indicator to *002* for file sequence number *034939002* appears as follows:

```
xyz_city1_prepaid2_12311969190000_002_034939002
```

File name for a running xDR file in CSV format that contains information for the same parameters for file sequence number *034939003* prefixed with *curr\_* and appears as follows:

```
curr_xyz_city1_prepaid2_12311969190000_002_034939002
```



### Important

When the "rulebase name" and "edr-format-name" options are enabled through this **file** command, if the "field-separator" value is "underscore" (default value) then, in the filename, the fields Rulebase name and EDR format name will be separated by "hyphen". If the "field-separator" value is "hyphen" then, in the filename, the fields Rulebase name and EDR format name will be separated by "underscore". This will ensure that the number of the fields in the filename is not increased and does not affect the backend billing system.

### reset-indicator

Specifies to include the reset indicator counter value, from 0 to 255, in the UDR file name and is incremented (by one) whenever any of the following conditions occur:

- An ACSMgr/SessMgr process fails.
- An Inter-chassis Session Recovery (ICSR) peer chassis has transitioned from standby to active.
- The sequence number in sequence-number keyword has rolled over to zero.

### rotation { num-records *records* | time *seconds* | volume *bytes* }

Specifies when to close a UDR file and create a new one.

- **num-records** *records*: Specifies the number of records that should be added to the file. When the number of records in the file reaches this specified value, the file is complete.

*records* must be an integer from 100 through 10240.

Default: 1024

- **time** *seconds*: Specifies the period of time to wait before closing the UDR file and creating a new one.

*seconds* must be an integer from 30 through 86400.

Default: 3600 seconds

- **volume** *bytes*: Specifies the maximum size of the UDR file before closing it and creating a new one.

*bytes* must be an integer from 51200 through 62914560.

Default: 102400 bytes

Note that higher settings may provide the best compression ratio when the **compression** keyword is set to *gzip*.

**sequence-number { length *length* | omit | padded | padded-six-length | unpadded }**

Specifies including or excluding the sequence number in the file name.

- **length *length***: Includes the sequence number with the specified length.

*length* must be the length of the file sequence number with preceding zeroes in the file name, and must be an integer from 1 through 9.




---

**Important** The **length** configuration is applicable in both UDR and EDR modules. When applied in both modules without the **file udr-seq-num** configuration, the minimum among the two values will come into effect for both modules. With the **file udr-seq-num** config, each module will use its own value of length.

---

- **omit**: Excludes the sequence number from the file name.
- **padded**: Includes the padded sequence number with preceding zeros in the file name. This is the default setting.
- **padded-six-length**: Includes the padded sequence number with six preceding zeros in the file name.
- **unpadded**: Includes the unpadded sequence number in the file name.

Default: **padded**

**storage-limit *limit***

Specifies deleting files when the specified amount of space, in bytes, is used up for UDR/EDR file storage on packet processing card RAM.

On an ST16 chassis, *limit* must be an integer from 10485760 through 268435456.

On ASR 5500 chassis, *limit* must be an integer from 10485760 through 536870912.

Default: 33554432




---

**Important** On the ST16 chassis, the total storage limit is 268435456 bytes (256 MB). This limit is for both UDR and EDR files combined.

---




---

**Important** On the ASR 5500 chassis, the total storage limit is 536870912 bytes (512 MB). This limit is for both UDR and EDR files combined.

---

**time-stamp { expanded-format | rotated-format | unix-format }**

Specifies the timestamp of when the file was created be included in the file name.

- **expanded-format**: Specifies the UTC MMDDYYYYHHMMSS format.
- **rotated-format**: Specifies the YYYYMMDDHHMMSS format.

- **unix-format**: Specifies the UNIX format of *x.y*, where *x* is the number of seconds since 1/1/1970 and *y* is the fractional portion of the current second that has elapsed.

**trailing-text string**

Specifies the inclusion of arbitrary text string in the file name.

*string* must be an alphanumeric string of 1 through 30 characters.

**trap-on-file-delete**

Instructs the system to send an SNMP notification (starCDRFileRemoved) when an UDR/EDR file is deleted due to lack of space.

Default: Disabled

**udr-seq-num**

Specifies that the file sequence numbers that are part of the UDR file names be independently generated. If disabled, a single set of sequence numbers are shared by both UDR and EDR files.

Default: Disabled

**xor-final-record**

Specifies inserting an XOR checksum (in place of the CRC checksum) into the UDR file header if the **exclude-checksum-record** keyword is left at its default setting.

Default: Disabled

+

More than one of the previous keywords can be entered within a single command.

---

**Usage Guidelines**

Use this command to configure UDR file characteristics.

**Example**

The following command sets the prefix of the current active UDR file to *current*:

```
file current-prefix current
```

The following command sets the base file name to *UDRfile*:

```
file name UDRfile
```

file



## UIDH Server Configuration Mode Commands

The UIDH Server Configuration Mode commands are used to configure the parameters when a connection is established with the UIDH Server.

### Command Modes

Exec > Global Configuration > Context Configuration > UIDH Server Configuration Mode Configuration

**configure** > **context** *context\_name* > **uidh-server** *uidh\_server\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(uidh-server) #
```

- [end, on page 1094](#)
- [exit, on page 1095](#)
- [refresh-interval, on page 1096](#)
- [remote-address, on page 1098](#)
- [response-timeout, on page 1099](#)

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# refresh-interval

This command allows you to configure the refresh interval for a UIDH key.

---

**Product**

P-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > UIDH Server Configuration Mode Configuration

**configure** > **context** *context\_name* > **uidh-server** *uidh\_server\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(uidh-server)#
```

---

**Syntax Description**

**refresh-interval** *refresh\_interval\_time*  
**default refresh-interval**  
**no refresh-interval**

**no**

Deletes the refresh interval parameter from the UIDH server configuration.

**default**

Configures the default interval value in the UIDH server configuration.

**refresh\_interval\_time**

The refresh interval time is configured in hours and is an integer ranging from 8 to 168 hours. The default interval value is 8 hours.

---

**Usage Guidelines**

Use this command to configure the refresh interval in the UIDH sever configuration.

When a session is attached to P-GW, the P-GW queries the UIDH server. If there is no response from the UIDH server, the UIDH service is not enabled for this session. If there is a Whitelisted subscriber, the UIDH server sends the UIDH string to P-GW. The P-GW queries the UIDH string after the refresh interval.

- On querying, if P-GW does not receive a response, it uses the existing key and sends another request after the refresh interval.
- If P-GW receives a response with an empty string – subscriber moving from OPT-IN to OPT-OUT, it does not perform a key refresh and UIDH insertion is disabled until the subscriber re-attaches.
- Any status change of a subscriber from OPT-OUT to OPT-IN is applied only on subscriber attach. However, the status changes from OPT-IN to OPT-OUT is applied only after refresh interval.
- When a subscriber moves to the OPT-OUT status, it is indicated with the following response: 200 OK Blank Response. This indicates that the request has been processed successfully at the UIDH server and that the subscriber has opted out.

In case of UIDH service failure, either because of a failure in service or because of failure in connection to the UIDH server, the P-GW continues to process the session without inserting the UIDH hash value.



**Example**

The following command sets the refresh interval in the UIDH server as 6 hours::

```
refresh-interval 6
```

# remote-address

This command allows you to configure the remote address of the UIDH server.

---

## Product

P-GW

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > UIDH Server Configuration Mode Configuration

**configure** > **context** *context\_name* > **uidh-server** *uidh\_server\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(uidh-server)#
```

---

## Syntax Description

**remote-address** *uidh\_address* **port** *uidh\_port\_number* **local-address** *local\_address*  
**no remote-address**

### no

Deletes the remote address configuration from the UIDH Server.

### port

Configures the remote port address to connect to the UIDH server. The port address is an integer ranging from 1 to 65535.

### local-address

Configures a local IP address (IPv4/IPv6) to be used to connect to a UIDH server.

---

## Usage Guidelines

Use this command to configure the remote address of the UIDH server.

### Example

The following command sets the remote address as 1.1.1.1, port number as 600 and local address as 2.2.2.2:

```
remote-address 1.1.1.1 port 600 local-address 2.2.2.2
```

# response-timeout

This command allows you to configure the response timeout for UIDH requests.

---

**Product** P-GW

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > UIDH Server Configuration Mode Configuration

**configure** > **context** *context\_name* > **uidh-server** *uidh\_server\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(uidh-server)#
```

---

**Syntax Description** **response-timeout** *timeout\_value*  
**default refresh-interval**  
**no remote-address**

**no**

Deletes the response timeout configuration for UIDH requests.

**default**

Configures the default response timeout value for UIDH requests.

***response\_timeout***

The timeout value is configured in seconds and is an integer ranging from 1 to 10. The default timeout value is 2 seconds.

---

**Usage Guidelines** Use this command to configure the response timeout value for UIDH requests.

**Example**

The following command sets the response timeout value as 10 seconds in the UIDH requests:

```
response-timeout 10
```

**response-timeout**



# Unnumbered Interface Configuration Mode Commands

---

## Command Modes

The Unnumbered Interface Configuration Mode creates an unnumbered IP interface within a specified context. An unnumbered interface enables IP processing without assigning an explicit IP address to the interface. In StarOS this type of interface supports an untagged BFD port. The only parameter for this type of interface is a text description.

Exec > Global Configuration > Context Configuration > Ethernet Interface Configuration

**configure** > **context** *context\_name* > **interface** *interface\_name* **unnumbered**

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-if-unnumbered)#
```



## Important

Available commands or keywords/variables vary based on platform type, product version, and installed license(s).

- [description, on page 1102](#)
- [end, on page 1103](#)
- [exit, on page 1104](#)

# description

Sets the descriptive text for the current interface.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `description text`  
`no description`

**no**

Clears the description for the interface.

**text**

Specifies the descriptive text as an alphanumeric string of 0 through 79 characters.

---

**Usage Guidelines** Set the description to provide useful information on the interface's primary function, services, end users, etc. Any information useful may be provided.

## Example

```
description sampleInterfaceDescriptiveText
```

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.





## Video Group Configuration Mode

The Video Group Configuration Mode is used to add CAEs to a CAE group and configure the CAEs for load balancing and health-check monitoring. The CAE (Content Adaptation Engine) is an optional component of the Mobile Videoscape. For additional information, refer to the *Mobile Video Gateway Administration Guide*.



### Important

In release 20.0, MVG is not supported. Commands in this configuration mode must not be used in release 20.0. For more information, contact your Cisco account representative.

### Command Modes

Exec > Global Configuration > Context Configuration > Video Group Configuration

**configure** > **context** *context\_name* > **cae-group** *group\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-vgroup) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show](#), on page 1106
- [end](#), on page 1107
- [exit](#), on page 1108
- [keepalive-server](#), on page 1109
- [local-address](#), on page 1111
- [server](#), on page 1112

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# keepalive-server

Specifies keep-alive messaging information for Content Adaptation Engine (CAE) health-check monitoring, which is part of CAE load balancing on the Mobile Video Gateway. Note that this command and its options configure settings that apply to all CAEs in the CAE group, not to an individual CAE.

**Product** MVG

**Privilege** Security Administrator, Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > Video Group Configuration

**configure** > **context** *context\_name* > **cae-group** *group\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-vgroup)#
```

**Syntax Description** [ **default** ] **keepalive-server** **deadtime** *seconds* **interval** *seconds* **num-retry** *num-retries* **port** *port\_number* **timeout** *seconds* [ **-noconfirm** ]

## default keepalive-server

Sets the CAE keep-alive settings to their default values.

**keepalive-server** **deadtime** *seconds* **interval** *seconds* **num-retry** *num-retries* **port** *port\_number* **timeout** *seconds* [ **-noconfirm** ]

Specifies keep-alive messaging information for CAE health-check monitoring.

## deadtime *seconds*

Specifies the periodic retry interval (in seconds) after a CAE is detected down. *seconds* is an integer from 1 through 1800. The default value is 120 seconds.

## interval *seconds*

Specifies the interval (in seconds) for how often the Mobile Video Gateway sends a keep-alive message to the CAEs. *seconds* is an integer from 0 through 120. The default value is 10 seconds. A value of 0 turns off keep-alive detection and marks the state of all CAEs to Up.

## num-retry *num\_retries*

Specifies the number of keepalive retries after a CAE does not respond. *num\_retries* is an integer from 1 through 20. The default value is 3 retries.

## port *port\_number*

Specifies the TCP port number for health-check monitoring, which is an integer from 1 through 65535. The default value is 5100.

**timeout *seconds***

Specifies the keep-alive timeout (in seconds) which is an integer from 1 through 30. The default value is 3 seconds.

**-noconfirm**

Specifies that the command must execute without prompting for confirmation.

---

**Usage Guidelines**

Use this command to specify keep-alive messaging information for CAE health-check monitoring, which is part of CAE load balancing on the Mobile Video Gateway.

**Example**

The following command specifies keep-alive messaging information for the CAEs in the CAE group:

```
keepalive-server deadtime 120 interval 10 num-retry 3 port 5100 timeout 3
```

# local-address

Specifies the local IPv4 address on the Mobile Video Gateway for the keepalive TCP connection used for Content Adaptation Engine (CAE) load balancing.

---

**Product** MVG

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Video Group Configuration

**configure** > **context** *context\_name* > **cae-group** *group\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-vgroup) #
```

---

**Syntax Description** [ **no** ] **local-address** *IPv4\_address* [ **-noconfirm** ]

**no local-address *IPv4\_address***

Deletes the local IPv4 address if previously specified.

**local-address *IPv4\_address***

Specifies the local IPv4 address on the Mobile Video Gateway for the keep-live TCP connection used for CAE load balancing. *IPv4\_address* must be in dotted decimal notation.

**-noconfirm**

Specifies that the command must execute without prompting for confirmation.

---

**Usage Guidelines** Use this command to specify the local IPv4 address on the Mobile Video Gateway, in dotted-decimal notation.

## Example

The following command specifies the local IPv4 address on the Mobile Video Gateway:

```
local-address 10.2.3.4
```

## server

Adds a CAE (Content Adaptation Engine) and its IPv4 address and port number to the associated CAE group. The Mobile Video Gateway uses this information for CAE load balancing. The Mobile Video Gateway has a system limit of 64 CAEs.

---

**Product** MVG

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > Video Group Configuration  
**configure > context** *context\_name* > **cae-group** *group\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-vgroup)#
```

---

**Syntax Description** [ **no** ] **server** *cae\_name* **address** *IPv4\_address* **port** *port\_number* [ **-noconfirm** ]

**no server cae\_name**

Deletes the CAE from the CAE group if previously configured.

**server cae\_name address IPv4\_address port port\_number**

Adds a CAE and its IPv4 address and port number to the associated CAE group. *cae\_name* is an alphanumeric string of 1 through 15 characters. *IPv4\_address* must be in dotted-decimal notation. *port\_number* is an integer from 1 through 65535. The default value is 80.

**-noconfirm**

Specifies that the command must execute without prompting for confirmation.

---

**Usage Guidelines** Use this command to add a CAE and its IPv4 address and port number to the associated CAE group.

### Example

The following command adds a CAE named *cae\_1* and its IPv4 address and port number to the associated CAE group:

```
server cae_1 address 10.2.3.4 port 80
```





## VLAN Configuration Mode Commands

The VLAN Configuration Mode is used to create and manage Virtual LANs and their bindings with contexts.

### Command Modes

Exec > Global Configuration > Port Configuration > VLAN Configuration

**configure** > **port ethernet** *slot\_number/port\_number* > **vlan** *vlan\_tag\_id*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number-vlan-vlan-id) #
```



### Important

Available commands or keywords/variables vary based on platform type, product version, and installed license(s).

- [bind interface](#), on page 1114
- [do show](#), on page 1115
- [end](#), on page 1116
- [exit](#), on page 1117
- [ingress-mode](#), on page 1118
- [priority](#), on page 1119
- [shutdown](#), on page 1120
- [vlan-map](#), on page 1121

# bind interface

Associates a VLAN interface with a context.

---

## Product

HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Port Configuration > VLAN Configuration

**configure** > **port ethernet** *slot\_number/port\_number* > **vlan** *vlan\_tag\_id*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number-vlan-vlan-id)#
```

---

## Syntax Description

[ **no** ] **bind interface** *interface\_name context\_name*

### **no**

Disassociates the VLAN interface from the context.

### ***interface\_name context\_name***

Specifies the name of the virtual interface and the context to which it will be bound.

*interface\_name* must be an alphanumeric string of 1 through 79 characters.

*context\_name* must refer to a previously configured context expressed as an alphanumeric string of 1 through 79 characters.

---

## Usage Guidelines

Bind a VLAN interface to a context to support VLAN service.

### Example

```
bind interface sampleVirtual sampleContext
no bind interface sampleVirtual sampleContext
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# ingress-mode

Enables or disables port ingress (incoming) mode for this VLAN ID on this port.

---

## Product

HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Port Configuration > VLAN Configuration

**configure** > **port ethernet** *slot\_number/port\_number* > **vlan** *vlan\_tag\_id*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number-vlan-vlan-id) #
```

---

## Syntax Description

[ **no** ] **ingress-mode**

**no**

Disables the port ingress mode.

---

## Usage Guidelines

Use this command to enable or disable the VLAN ingress mode for this port.

### Example

```
ingress-mode
```

# priority

Sets the 802.1p VLAN priority bit.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Port Configuration > VLAN Configuration

**configure > port ethernet slot\_number/port\_number > vlan vlan\_tag\_id**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number-vlan-vlan-id)#
```

---

**Syntax Description**

**priority** *value*  
**no priority**

**no**

Disables the setting of the 802.1p priority bit.

**value**

Sets the value of the 802.1p priority bit as an integer from 0 through 7, with 7 being the highest priority.

---

**Usage Guidelines**

Set a value for the VLAN priority bit.

**Example**

To set a VLAN priority bit value, use the following command:

```
priority 3
```

To disable the use of a VLAN priority bit, use the following command:

```
no priority
```

# shutdown

Disables or enables traffic over this VLAN.

---

## Product

HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SGSN

---

## Privilege

Security Administrator, Administrator

---

## Command Modes

Exec > Global Configuration > Port Configuration > VLAN Configuration

**configure** > **port ethernet** *slot\_number/port\_number* > **vlan** *vlan\_tag\_id*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number-vlan-vlan-id) #
```

---

## Syntax Description

[ **no** ] **shutdown**

**no**

Enables the VLAN. When omitted the VLAN is shutdown.

---

## Usage Guidelines

Shut down a VLAN.

To bring a VLAN into service, execute this command using the **no** keyword.

### Example

To disable a VLAN from sending or receiving network traffic use the following command:

```
shutdown
```

To enable a VLAN use the following command:

```
no shutdown
```



# vlan-map

Associates an IP interface having a VLAN ID with a context.

---

**Product**

HA  
HSGW  
PDSN  
P-GW  
SAEGW  
SGSN

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Port Configuration > VLAN Configuration

**configure** > **port ethernet slot\_number/port\_number** > **vlan vlan\_tag\_id**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-port-slot_number/port_number-vlan-vlan-id)#
```

---

**Syntax Description**

**vlan-map interface** *if\_name context\_name*

**interface if\_name context\_name**

Associates the specified VLAN interface with a context.

*if\_name* is an existing interface name specified as an alphanumeric string of 1 through 79 characters.

*context\_name* is an existing context name specified as an alphanumeric string of 1 through 79 characters.

---

**Usage Guidelines**

Use **vlan-map** to associate multiple VLAN interfaces with a single context. This feature is used in conjunction with nexthop forwarding and overlapping IP pools.

**Example**

```
vlan-map interface vlan234 ingress
```





# WSG Lookup Priority List Configuration Mode Commands

---

## Command Modes

The Wireless Security Gateway Lookup Priority List Configuration Mode is used to set the priority of subnet components for site-to-site tunnels. This is a Security Gateway (SecGW) feature [VPC-VSM only].

Exec > Global Configuration > WSG-Lookup Priority List Configuration

**configure > wsg-lookup**

Entering the above command sequence results in the following prompt:

```
host_name(config-wsg-lookup) #
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [do show, on page 1124](#)
- [end, on page 1125](#)
- [exit, on page 1126](#)
- [priority, on page 1127](#)

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

# priority

Sets the priority level for a WSG subnet combination (source and destination netmasks). It also disables an existing priority for a specified subnet combination. (VPC-VSM only).

---

**Product**

SecGW

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec &gt; Global Configuration &gt; WSG-Lookup Priority List Configuration

**configure > wsg-lookup**

Entering the above command sequence results in the following prompt:

---

**Syntax Description**

```
[ no ] priority priority_level source-netmask subnet_size destination netmask
subnet_size
```

**no**

Disables the priority for the specified subnet combination.

**priority *priority\_level***

Specifies the priority level for the subnet combination as an integer from 1 through 6.

**source-netmask *subnet\_size***

Specifies the subnet size for the source netmask as an integer from 1 through 128.

**destination netmask *subnet\_size***

Specifies the subnet size for the destination netmask as an integer from 1 through 128.

---

**Usage Guidelines**

Use this command to set the priority level for a WSG subnet combination (source and destination netmasks). It can also be used to disable an existing priority for a specified subnet combination.

**Example**

The following command sets a priority of 2 for a subnet combination with a /32 subnet size.

```
priority 2 source-netmask 32 destination netmask 32
```

priority





# WSG Service Configuration Mode Commands

## Command Modes

The Wireless Security Gateway Configuration Mode is used to define the operating parameters for IPSec-based access control and handling of Encapsulating Security Payload (ESP) packets.

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).



### Important

Any changes made to a WSG service require that the service be restarted to apply any changed parameters. You restart the service by unbinding and binding the IP address to the service context.

- [associate subscriber-map, on page 1130](#)
- [bind address, on page 1131](#)
- [deployment-mode, on page 1132](#)
- [dhcp, on page 1133](#)
- [dns-server, on page 1134](#)
- [do show, on page 1135](#)
- [duplicate-session-detection, on page 1136](#)
- [end, on page 1137](#)
- [exit, on page 1138](#)
- [initiator-mode-duration, on page 1139](#)
- [ip, on page 1140](#)
- [ipv6, on page 1142](#)
- [peer-list, on page 1144](#)
- [pre\\_fragment mtu, on page 1145](#)
- [responder-mode-duration, on page 1146](#)
- [Server dhcp, on page 1147](#)

# associate subscriber-map

Binds the WSG service to the specified IPv4 or IPv6 address and crypto template (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

**associate subscriber-map** *subscriber\_map\_name*

***subscriber\_map\_name***

Specifies the name of an subscriber map as an alphanumeric string of 0 through 127 characters.

---

**Usage Guidelines**

Associates the WSG service to Subscriber Map.

**Example**

The following command associates SecGW to subscriber map1.

```
associate subscriber-map subscriber_map1
```

# bind address

Binds the WSG service to the specified IPv4 or IPv6 address and crypto template (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

**bind address** *IPv4 / IPv6* **crypto-template** *template\_name* | **Secure-tunnel** [**Max-sessions** *sessions* ]  
**no bind address**

**no**

Unbinds the WSG service from the IP address.

**IPv4 / IPv6**

IPv4 *##.##.##.##* or IPv6 *#####.#####.#####.#####.#####.#####.#####.#####* (IPv6 also supports *::* notation).

**template\_name**

Specifies the name of an existing crypto template as an alphanumeric string of 0 through 127 characters.

---

**Usage Guidelines**

Bind the WSG service to an IPv4 or IPv6 address.

**Example**

The following command binds the WSG service to 10.1.1.1.

```
bind address 10.1.1.1 crypto template tplt01
```

# deployment-mode

Specifies the deployment mode for the WSG service (VPC only).

---

## Product

SecGW (WSG)

---

## Privilege

Security Administrator

---

## Command Modes

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

## Syntax Description

**deployment-mode** { **remote-access** | **site-to-site** }  
**no deployment-mode**

**no**

Deletes deployment mode from the configuration.

**{ remote-access | site-to-site }**

Specifies the deployment mode as either:

- **remote-access** – support direct user communication with this WSG
- **site-to-site** – support bidirectional communication with two or more WSGs

---

## Usage Guidelines

Specify remote access or site-to-site communication as the deployment mode for this WSG.

## Example

This command deploys this WSG for remote access:

```
deployment-mode remote-access
```

# dhcp

Specifies the DHCPv4 context and service name to be used when the IP address allocation method is set **dhcp-proxy** (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

```
dhcp { context-name context_name | service-name service_name }
no dhcp { context-name | service-name }
```

**no**

Deletes the specified parameter.

**context-name** *context\_name*

Specifies the context in which the DHCPv4 service is configured as an alphanumeric string of 1 through 79 characters.

**service-name** *service\_name*

Specifies which DHCPv4 service to use for the **dhcp-proxy** as an alphanumeric string of one through 63 characters. Only one DHCPv4 service can be configured as the **dhcp-proxy**.

---

**Usage Guidelines**

Specifies the DHCPv4 context and service name to be used when the IP address allocation method is set to **dhcp-proxy**. The specified DHCPv4 service is designated via the **ip address alloc-method dhcp-proxy** command.

The WSG service must be restarted to apply the parameters. You restart the service by doing an unbind and bind.

**Example**

The following command sequence enables a DHCPv4 service as an allocation method for IP addresses:

```
dhcp context-name wsg01
dhcp service-name dhcp1
```

# dns-server

Enables the WSG service (SecGW) to send the IP Address of the DNS server to the peer. A new request will overwrite the existing entries.

**Product** SecGW (WSG service)

**Privilege** Security Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

**Syntax Description** **dns-server primary** *ip\_address* [ **secondary** *ip\_address* ]  
**no dns-server primary** *ip\_address*

**no**

Disables sending the primary IP address of the DNS server.

**primary ip\_address**

Specifies the IP Address, in IPv4 dotted-decimal or IPv6 colon-separated hexadecimal notation, of the primary DNS server to be sent to the peer.

**secondary ip\_address**

Specifies the IP Address, in IPv4 dotted-decimal or IPv6 colon-separated hexadecimal notation, of the secondary DNS server to be sent to the peer.

**Usage Guidelines** Use this command to configure an IPv4 or IPv6 address of a DNS server. The same CLI can be configured twice with different IP address type. However, both primary and secondary IP address should be of the same type (IPv4 or IPv6) for a CLI.

A new request will overwrite the existing entries of the same IP address type.

**Example**

The following command enables the WSG service to send the IPv4 address of the primary DNS server to the peer:

```
dns-server primary 10.1.1.1 secondary 10.1.1.2
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# duplicate-session-detection

Enables or disables allowing only one IKE-SA per remote IKE-ID. A new request will overwrite the existing tunnel.

**Product** SecGW (WSG service)

**Privilege** Security Administrator

**Command Modes** Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure > context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

**Syntax Description**

**duplicate-session-detection**  
**no duplicate-session-detection**

**no**

Disables duplicate session detection and allows multiple IKE-SAs per remote IKE-ID. This is the default behavior.

**Usage Guidelines** Enables or disables allowing only one IKE-SA per remote IKE-ID. A new request will overwrite the existing tunnel. For a complete description of this feature, refer to the *IPSec Reference*.

## Example

The following command enables duplicate session detection:

```
duplicate-session-detection
```



# end

Exits the current configuration mode and returns to the Exec mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>end</b>
<b>Usage Guidelines</b>	Use this command to return to the Exec mode.

# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `exit`

---

**Usage Guidelines** Use this command to return to the parent configuration mode.

# initiator-mode-duration

Specifies the interval during which the WSG service (SecGW) will try to initiate a call with an IKE peer. A peer list must be configured in this WSG service for this command to be available (VPC only).

---

**Product** SecGW (WSG)

---

**Privilege** Security Administrator, Administrator

---

**Command Modes** Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure > context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description** **initiator-mode-duration** *seconds*  
**default initiator-mode-duration**

## default

Sets the initiator mode duration to 10 seconds.

## seconds

Specifies the duration interval in seconds as an integer from 5 through 250.

---

**Usage Guidelines**

Use this command to specify the interval during which the WSG service (SecGW) will try to initiate an IKE call when a peer list is activated (default is 10 seconds).

This command is only available when a peer-list has been configured for the WSG service.

See the *IPSec Reference* for additional information on configuring an SecGW as an IKE initiator.

## Example

The following command sets the initiator mode duration to 15 seconds:

```
initiator-mode-duration 15
```

# ip

Specifies the IPv4 access group and address allocation method for this WSG service (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

```
ip { access-group group_name | address { alloc-method { dhcp-proxy | local } | pool name pool_name }
no ip access-group group_name
no ip address alloc-method pool_name
no ip address pool name pool_name
```

**no**

Deletes the specified parameter.

**access-group** *group\_name*

Specifies an existing IPv4 ACL access group as an alphanumeric string of 1 through 47 characters. For additional information, see *ACL Configuration Mode Commands*.

**address alloc-method** { **dhcp-proxy** | **local** }

Specifies the method to be used when allocating IPv4 addresses:

- **dhcp-proxy** – allocates via a DHCP server
- **local** – allocates from a local pool (default)

**pool name** *pool\_name*

Specifies an existing IPv4 access pool as an alphanumeric string of 1 through 31 characters. Up to 16 named IPv4 pools can be configured. For additional information, see *APN Configuration Mode Commands*.

---

**Usage Guidelines**

Use this command to specify the IPv4 access group and IPv4 address allocation method for this WSG service.

This command and its keywords are subject to the following limitations:

- The WSG service configuration takes precedence over the equivalent configuration in Subscriber mode or the template payload.
- The WSG service must be restarted to apply the parameters. You restart the service by doing an unbind and bind.

- Up to 16 named IPv4 pools can be configured. The list is sorted, and the addresses are allocated from the first pool in the list with available addresses.
- One IPv4 ACL can be configured.
- The IPv4 pools will only be used for IPv4 calls.

**Example**

This command specifies the IPv4 address pool named *pool401*:

```
ip address pool name pool401
```

This command specifies the use of a previously configure DHCPv4 service to allocate IPv4 addresses:

```
ip address alloc-method dhcp-proxy
```

# ipv6

Specifies the IPv6 access group and prefix pool for this WSG service (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

```
ipv6 { access-group group_name | address prefix-pool pool_name }
no ipv6 access-group group_name
no ipv6 address prefix-pool
```

**no**

Deletes the specified parameter.

**access-group** *group\_name*

Specifies an existing IPv6 ACL access group as an alphanumeric string of 1 through 47 characters. For additional information, see *IPv6 ACL Configuration Mode Commands*.

**address prefix-pool** *pool\_name*

Specifies an existing IPv6 prefix pool as an alphanumeric string of 1 through 31 characters. For additional information, see *Subscriber Configuration Mode Commands*.

---

**Usage Guidelines**

Specify the IPv6 access group and prefix pool for this WSG service.

This command and its keywords are subject to the following limitations:

- The WSG service configuration takes precedence over the equivalent configuration in Subscriber mode or the template payload.
- The WSG service must be restarted to apply the parameters. You restart the service by doing an unbind and bind.
- One named IPv6 pool can be configured.
- One named IPv6 ACL can be configured.
- The IPv6 pools will only be used for IPv6 calls.

**Example**

This command specifies the IPv6 prefix pool named pool601:

```
ipv6 prefix-pool name pool601
```

# peer-list

Configures an SecGW to initiate an IKEv2 session setup request when the peer does not initiate a setup request within a specified time interval. This command is only available for a WSG service configured for site-to-site (S2S) deployment mode (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

**peer-list** *peer\_list\_name*  
**no peer-list**

---

**no**

Disables the current peer list and SecGW as an IKE initiator functionality.

---

***peer\_list\_name***

Specifies the name of an existing peer list as an alphanumeric string of 1 through 79 characters. The crypto peer list must have been previously created using the Global Configuration mode **crypto peer-list** command.

---

**Usage Guidelines**

Enables the use of a peer list so that the SecGW can act as an initiator of an IKEv2 call session. The WSG service deployment mode must be configured as site-to-site for the **peer-list** command to execute.

The following limitations apply when the SecGW as initiator feature is enabled:

- The SecGW will only support up to 1,000 peers. This restriction is applied when configuring a crypto peer list.
- SecGW will not support the modification of an IPv4/IPv6 peer list on the fly (call sessions in progress). The modification will be allowed only after all the calls are removed.

When a peer list has been configured in the WSG service, the initiator and responder mode timer intervals each default to 10 seconds. The SecGW will wait for 10 seconds in the responder mode for a peer session initiation request before switching to the initiator mode and waiting 10 seconds for a peer response.

You can change the default settings for the initiator and/or responder mode intervals using the WSG Service mode **initiator-mode-duration** and **responder-mode-duration** commands.

See the *IPSec Reference* for additional information on configuring an SecGW as an IKE initiator.

---

**Example**

The following command enables the user of a peer list named *peer1*.

```
peer-list peer1
```



## pre\_fragment mtu

Specifies the Maximum Transmission Unit (MTU) size which when exceeded initiates pre-tunnel (before encryption) fragmentation of IPSec Encapsulated Security Payload (ESP) packets within this WSG service (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

```
pre_fragment mtu size
no pre_fragment size
default pre_fragment size
```

**no**

Disables this function.

**default**

Sets the MTU size to the default value of 1400 bytes.

**mtu size**

Specifies the MTU size in bytes as an integer from 576 through 2048. Default = 1400

---

**Usage Guidelines**

Specify the MTU size which when exceeded initiates pre-tunnel fragmentation of IPSec ESP packets within this WSG service.

Pre-Tunnel-Fragmentation improves packet processing performance as compared to post-tunnel-fragmentation.

If a clear IPv4 packet is longer than the predefined MTU size, it will be fragmented before the packet is encrypted and transmitted to internet.

If a clear IPv6 packet is longer than the predefined MTU size, it is dropped and an ICMP packet with the maximum length is sent back to the source. The source will then fragment the IPv6 packet and retransmit.

**Example**

The following command sets MTU size to 2048 bytes.

```
pre_fragment mtu 2048
```

# responder-mode-duration

Specifies the interval during which the WSG service (SecGW) will wait for a response from an IKE peer before switching to initiator mode. A peer list must be configured in this WSG service for this command to be available (VPC only).

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

**responder-mode-duration** *seconds*  
**default responder-mode-duration**

**default**

Sets the responder mode duration to 10 seconds.

**seconds**

Specifies the duration interval in seconds as an integer from 5 through 250.

---

**Usage Guidelines**

Use this command to specify the interval during which the WSG service (SecGW) will wait for a response from an IKE peer before switching to initiator mode (default is 10 seconds).

This command is only available when a peer-list has been configured for the WSG service.

See the *IPSec Reference* for additional information on configuring an SecGW as an IKE initiator.

**Example**

The following command sets the responder mode duration to 15 seconds:

```
responder-mode-duration 15
```

# Server dhcp

Specifies the dhcp server addresses to be sent to the peer in authentication response.

---

**Product**

SecGW (WSG)

---

**Privilege**

Security Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > WSG-Service Configuration

**configure** > **context** *context\_name* > **wsg-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[context_name]host_name(config-wsg-service)#
```

---

**Syntax Description**

```
server dhcp { ipv4 ipv4_address [ IP-ADDRESS | IP-ADDRESS ] | ipv6 ipv6_address
 [ IPv6-ADDRESS | IPv6-ADDRESS ] }
no server dhcp { ipv4 [ ipv6 ] | ipv6 [ ipv4 ] }
```

**no**

Deletes the specified parameter.

**ipv4\_address**

Specifies the ipv4 address of the dhcp-server to be sent to the peer. The IPV4 address should be in the format `##.##.##.##` which is the first ipv4 dhcp-server's address.

**IP-ADDRESS**

Specifies ipv4 address of the dhcp-server to be sent to the peer.

**ipv6\_address**

Specifies the ipv6 address of the dhcp-server to be sent to the peer. The IPV6 address should be in the format `#####.#####.#####.#####.#####.#####.#####` (IPv6 also supports `::` notation).

**IPv6-ADDRESS**

Specifies ipv6 address of the dhcp-server to be sent to the peer.

---

**Usage Guidelines**

This command specifies the dhcp server addresses to be sent to the peer in authentication response

**Example**

The following command specifies the dhcp server ipv4 addresses to be sent to the peer in authentication response:

```
server dhcp ipv4 123.234.345.567
```





## X2-GW Service Configuration Mode Commands



### Important

In Release 20, 21.0 and 21.1, HeNBGW is not supported. Commands in this configuration mode must not be used in these releases. For more information, contact your Cisco account representative.

The X2 Gateway Service Configuration Mode is associated with HeNBGW-access-service.

### Command Modes

Exec > Global Configuration > Context Configuration > X2 GW Service Configuration

**configure** > **context** *context\_name* > **x2gw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-x2gw-service) #
```



### Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [bind](#), on page 1150
- [do show](#), on page 1151
- [end](#), on page 1152
- [exit](#), on page 1153
- [x2-c](#), on page 1154

# bind

This command binds X2GW service to IP address of interface.

---

**Product**

HeNB-GW

---

**Privilege**

Security Administrator, Administrator

---

**Command Modes**

Exec > Global Configuration > Context Configuration > X2 GW Service Configuration

**configure** > **context** *context\_name* > **x2gw-service** *service\_name*

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-x2gw-service)#
```

---

**Syntax Description**

**bind x2-c ipv4-address** *IPv4\_address*  
**no bind x2-c**

**no**

Removes the X2GW service to IP address of interface.

**x2-c**

Configure the X2-C parameters.

**ipv4-address** *IPv4\_address*

Configure the X2-C IPV4 address.

*IPv4\_address* is an ip\_address that must be entered in IPv4 dotted-decimal notation.

---

**Usage Guidelines**

Use this command to bind/associate X2GW service to IP address of interface

**Example**

Following command binds X2GW service to IP address of interface.

```
bind x2-c ipv4-address 123.234.500.6
```

# do show

Executes all **show** commands while in Configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**do show**

---

**Usage Guidelines**

Use this command to run all Exec mode **show** commands while in Configuration mode. It is not necessary to exit the Config mode to run a **show** command.

The pipe character | is only available if the command is valid in the Exec mode.



---

**Caution**

There are some Exec mode **show** commands which are too resource intensive to run from Config mode. These include: **do show support collection**, **do show support details**, **do show support record** and **do show support summary**. If there is a restriction on a specific **show** command, the following error message is displayed:

```
Failure: Cannot execute 'do show support' command from Config mode.
```

---

# end

Exits the current configuration mode and returns to the Exec mode.

---

**Product** All

---

**Privilege** Security Administrator, Administrator

---

**Syntax Description** `end`

---

**Usage Guidelines** Use this command to return to the Exec mode.



# exit

Exits the current mode and returns to the parent configuration mode.

---

**Product**

All

---

**Privilege**

Security Administrator, Administrator

---

**Syntax Description**

**exit**

---

**Usage Guidelines**

Use this command to return to the parent configuration mode.

## x2-c

This command configures the X2-C parameters.

---

### Product

HeNB-GW

---

### Privilege

Security Administrator, Administrator

---

### Syntax Description

```
x2-c sctp port value
default x2-c sctp port
```

#### **default**

Sets/Restores the default value assigned for X2-C parameters. The default value of SCTP port is 36422.

#### **sctp**

Configure the X2-C sctp parameters.

#### **portvalue**

Designates SCTP port.

*value* is an integer ranging from 1 to 65535.

---

### Usage Guidelines

Use this to configure the X2-C parameters.

#### **Example**

Following command configures the parameter X2-C sctp port to 345 .

```
x2-c sctp port 345
```