



Enabling USB Port on Access Points

- [USB Port as Power Source for Access Points, on page 1](#)
- [Configuring an AP Profile \(CLI\), on page 2](#)
- [Configuring USB Settings for an Access Point \(CLI\), on page 2](#)
- [Monitoring USB Configurations for Access Points \(CLI\), on page 3](#)

USB Port as Power Source for Access Points

Some Cisco APs have a USB port that can act as a source of power for some USB devices. The power can be up to 2.5W; if a USB device draws more than 2.5W of power, the USB port shuts down automatically. The port is enabled when the power draw is 2.5W and lower. Refer to the datasheet of your AP to check if the AP has a USB port that can act as a source of power.



Note The controller records the last five power-overdrawn incidents in its logs.



Caution When unsupported USB device is connected to the Cisco AP, the following message is displayed:

```
The inserted USB module is not a supported device. The behavior of this
USB device and the impact to the Access Point is not guaranteed. If Cisco
determines that a fault or defect can be isolated due to the use of
third-party USB modules installed by a customer or reseller, Cisco may
withhold support under warranty or support program under contract. In the
course of providing support for Cisco networking products, the end user
may be required to install Cisco-supported USB modules in the event Cisco
determines that removing third-party parts will assist Cisco in diagnosing
root cause for troubleshooting purposes. Cisco also reserves the right
to charge the customer per then-current time and material rates for
services provided to the customer when Cisco determines, after having
provided such services, that an unsupported device caused the root cause
of the defective product
```

Configuring an AP Profile (CLI)

Procedure

| | Command or Action | Purpose |
|---------------|--|---|
| Step 1 | configure terminal Example: Device# <code>configure terminal</code> | Enters global configuration mode. |
| Step 2 | ap profile <i>ap-profile</i> Example: Device(config)# <code>ap profile xyz-ap-profile</code> | Configures an AP profile and enters the AP profile configuration mode. Note When you delete a named profile, the APs associated with that profile will not revert to the default profile. |
| Step 3 | usb-enable Example: Device(config-ap-profile)# <code>usb-enable</code> | Enables USB for each AP profile. Note By default, the USB for each AP profile is enabled. Use the no usb-enable command to disable USB for each AP profile. |
| Step 4 | end Example: Device(config-ap-profile)# <code>end</code> | Returns to privileged EXEC mode. Alternatively, you can also press Ctrl-Z to exit global configuration mode. |

Configuring USB Settings for an Access Point (CLI)

Procedure

| | Command or Action | Purpose |
|---------------|---|---|
| Step 1 | enable Example: Device# <code>enable</code> | Enters privileged EXEC mode. |
| Step 2 | ap name <i>ap-name</i> usb-module Example: Device# <code>ap name AP44d3.xy45.69a1 usb-module</code> | Enables the USB port on the AP. Use the ap name <i>ap-name</i> no usb-module command to disable the USB port on the AP. |

| | Command or Action | Purpose |
|---------------|---|---|
| Step 3 | <p>ap name <i>ap-name</i> usb-module override</p> <p>Example:</p> <pre>Device# ap name AP44d3.xy45.69a1 usb-module override</pre> | <p>Overrides USB status of the AP profile and considers the local AP configuration.</p> <p>Use the ap name <i>ap-name</i> no usb-module override command to override USB status of the AP and consider the AP profile configuration.</p> <p>Note You can configure the USB status for an AP only if you enable USB override for it.</p> |

Monitoring USB Configurations for Access Points (CLI)

- To view the inventory details of APs, use the following command:

show ap name *ap-name* inventory

The following is a sample output:

```
Device# show ap name AP500F.8059.1620 inventory
NAME: AP2800 , DESCR: Cisco Aironet 2800 Series (IEEE 802.11ac) Access Point
PID: AIR-AP2802I-D-K9 , VID: 01, SN: XXX1111Y2ZZZZ2800
NAME: SanDisk , DESCR: Cruzer Blade
PID: SanDisk , SN: XXXX1110010, MaxPower: 224
```

- To view the summary of an AP module, use the following command:

show ap module summary

The following is a sample output:

```
Device# show ap module summary
AP Name           External Module      External Module PID   External Module
Description
-----
AP500F.1111.2222   Enable                SanDisk                 Cruzer Blade
```

- To view the USB configuration details for each AP, use the following command:

show ap name *ap-name* config general

The following is a sample output:

```
Device# show ap name AP500F.111.2222 config general
.
.
.
USB Module Type..... USB Module
USB Module Status..... Disabled
USB Module Operational State..... Enabled
USB Override ..... Enabled
```

- To view status of the USB module, use the following command:

show ap profile name *xyz* detailed

The following is a sample output:

```
Device# show ap profile name xyz detailed
USB Module           : ENABLED
```