



CPS vDRA Configuration Guide, Release 20.2.0 (1)

First Published: 2020-08-27

Last Modified: 2021-01-27

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses and phone numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/c/en/us/about/legal/trademarks.html>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2020–2021 Cisco Systems, Inc. All rights reserved.



CONTENTS

PREFACE

Preface	ix
About This Guide	ix
Audience	ix
Additional Support	ix
Conventions (all documentation)	x
Communications, Services, and Additional Information	xi
Important Notes	xi

CHAPTER 1

Introduction	1
CPS vDRA Overview	1
Functions of DRA	1
CPS vDRA Architecture	2
Types of CPS vDRA	2

CHAPTER 2

User Configuration	5
Basic Configuration	5
Configure Systems	5
Configure Diameter Application	6
Configure Multiple Diameter Applications for a Peer Connection	6
Configure Routing AVP Definitions	7
Enable Mediation	8
Enable DOIC	9
Configure Interfaces for SCTP Multi-homing	9
Routing Techniques	10
Configure Destination Host Routing	10
Configure SRK Based Routing	11

Configure Table Driven Routing	14
Advanced Features	15
Configure Rate Limiting	15
Configure Error Result Code Profile	16
Configure Peer Group Answer Timeout	16
Configure Peer Load Balancing	17
Configure Message Retries	20
Configure Reserved IMSIs	21
Configure Multiple Lookup in SLF Trigger Profile	22
Modify Result Code for AVPs Using Mediation Rules	22
Hide Topology Using Mediation Rules	23
Configure Mediation Rule for Proxy-Unaware Endpoints	24
Add Prefix to an AVP Using Mediation Rules	25
Configure Throttling of Diameter Messages Using DOIC	26
Configure Throttling of Diameter Messages Using DRMP	27
Configure vDRA for eMPS	28
Configure Topology Hiding for S6a/d Diameter Application	29
Manual Peer Disconnection using REST API	30
Policy DRA Relay Configuration	31
Relay Endpoint Configuration	31
Control Plane Configuration	31
DNS Host Configuration	32
Virtual-IP Configuration	32
Relay Configuration for a 6-Site Policy DRA System	32
Configuring Application based Sharding	33
Configuring Binding Database Overload	36
Change Admin User Password for MongoDB Authentication	36
Configuring MongoDB Authentication	37
Disabling MongoDB Authentication	39
Configuring Zone Aware Sharding	41
Modifying Zone Aware Sharding	43

CHAPTER 3

Policy Builder Configuration 45

Plug-in Configuration 45

Threading Configuration	46
Async Threading Configuration	47
Custom Reference Data Configuration	48
DRA Configuration	50
Settings	53
Rate Limits	58
DRA Feature	60
DRA Inbound Endpoints	63
DRA Outbound Endpoints	65
Relay Endpoints	67
Policy Routing for Real IPs with Relay Endpoints	67
SLF Configuration	72
Diameter Application	73
Sd Application	73
Gx Application	75
Rx Application	76
Sh Application	77
S6a Application	78
Routing AVP Definition	80
Gx Session	80
Rx Session	80
Rx New Session Rules - CRD Table	80
Gx New Session Rules - CRD Table	81
Sd New Session Rules - CRD Table	81
Logical APN List - CRD Table	82
Dynamic AVP Retriever for Routing	82
Configure Dynamic AVP Retriever	83
Custom Reference Data Tables	84
Search Table Groups	84
Peer Rate Limit Profile	84
Peer Group Mapping	86
Message Retry Profile	86
Message Mediation Profile	87
Peer Group Answer Timeout	89

Error Result Code Profile	89
Gx Session Routing	90
SLF Trigger Profile	91
SLF Routing	92
S6/Sh Table Driven Rules	93
Custom Reference Data Tables	93
APN Mapping	93
Peer Access Control List	94
Peer Routes	95
Peer Group SRK Mapping	95
Peer Routing	96
PCRF Session Query Peers	97
IPv6 Ranges System ID Mapping	98
Binding Key Profile	99
AppId Key Profile Mapping	100
Message Rate Limit Profile	100
Reserved IMSI	101
Trusted Realm Profile	102
Protected Realm Trusted Profile Mapping	102
MME Alias Map	103
HSS Aliases	103
HSS Alias Map	104
Binding Key Profile Creation Map	104
Binding Key Profile Read Map	105
Best Effort Binding	106

CHAPTER 4
Custom Reference Data Configuration 107

Logical APN List	108
Avp Condition Profile	108
Avp Action Profile	109
APN Mapping Table	110
Peer Rate Limit Profile	111
DOIC Profile	111
Diameter Avp Dictionary	112

Peer Access Control List	113
Peer Routes	114
Peer Group Mapping	114
Peer Group SRK Mapping	115
Peer Routing	115
IPv6 Ranges System ID Mapping	116
Binding Key Profile	117
AppId Key Profile Mapping	117
Message Class Profile	118
Message Retry Profile	118
Message Mediation Profile	119
Peer Group Answer Timeout	120
Message Rate Limit Profile	121
Error Result Code Profile	122
Gx New Session Rules	122
Rest API Error Code Profile	123
SLF Trigger Profile	124
SLF Routing	125
S6/Sh Table Driven Rules	125
Range Based Routing	126
IMSI Range	127
MSISDN Range	127
Binding Key Profile Creation Map	128
Binding Key Profile Read Map	129

CHAPTER 5

DRA Distributor Configuration	131
DRA Distributor Configuration Overview	131
Configuring DRA Distributor	131
Configuration Status Check	134



Preface

- [About This Guide, on page ix](#)
- [Audience, on page ix](#)
- [Additional Support, on page ix](#)
- [Conventions \(all documentation\), on page x](#)
- [Communications, Services, and Additional Information, on page xi](#)
- [Important Notes, on page xi](#)

About This Guide

This document is a part of the Cisco Policy Suite documentation set.

For information about available documentation, see the *CPS Documentation Map* for this release at [Cisco.com](https://www.cisco.com).

Audience

This guide is best used by these readers:

- Network administrators
- Network engineers
- Network operators
- System administrators

This document assumes a general understanding of network architecture, configuration, and operations.

Additional Support

For further documentation and support:

- Contact your Cisco Systems, Inc. technical representative.
- Call the Cisco Systems, Inc. technical support number.
- Write to Cisco Systems, Inc. at support@cisco.com.

- Refer to support matrix at <https://www.cisco.com/c/en/us/support/index.html> and to other documents related to Cisco Policy Suite.

Conventions (all documentation)

This document uses the following conventions.

Conventions	Indication
bold font	Commands and keywords and user-entered text appear in bold font .
<i>italic font</i>	Document titles, new or emphasized terms, and arguments for which you supply values are in <i>italic font</i> .
[]	Elements in square brackets are optional.
{x y z }	Required alternative keywords are grouped in braces and separated by vertical bars.
[x y z]	Optional alternative keywords are grouped in brackets and separated by vertical bars.
string	A nonquoted set of characters. Do not use quotation marks around the string or the string will include the quotation marks.
courier font	Terminal sessions and information the system displays appear in courier font.
< >	Nonprinting characters such as passwords are in angle brackets.
[]	Default responses to system prompts are in square brackets.
!, #	An exclamation point (!) or a pound sign (#) at the beginning of a line of code indicates a comment line.



Note

Means reader take note. Notes contain helpful suggestions or references to material not covered in the manual.



Caution

Means reader be careful. In this situation, you might perform an action that could result in equipment damage or loss of data.

**Warning****IMPORTANT SAFETY INSTRUCTIONS.**

Means danger. You are in a situation that could cause bodily injury. Before you work on any equipment, be aware of the hazards involved with electrical circuitry and be familiar with standard practices for preventing accidents. Use the statement number provided at the end of each warning to locate its translation in the translated safety warnings that accompanied this device.

SAVE THESE INSTRUCTIONS

**Note**

Regulatory: Provided for additional information and to comply with regulatory and customer requirements.

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions and services, visit [Cisco Marketplace](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.

Important Notes

**Important**

Any feature or GUI functionality that is not documented may not be supported in this release or may be customer specific, and must not be used without consulting your Cisco Account representative.



CHAPTER 1

Introduction

- [CPS vDRA Overview, on page 1](#)
- [Functions of DRA, on page 1](#)
- [CPS vDRA Architecture, on page 2](#)
- [Types of CPS vDRA, on page 2](#)

CPS vDRA Overview

CPS Diameter Routing Agent (vDRA) is the functional element in a network that routes messages to the destination node based on routing algorithms.

CPS vDRA is primarily responsible for routing messages and sending responses back to the origin node.

CPS vDRA is compliant with IETF RFC 3588 and 3GPP 29.212 and 29.213 message AVPs.

Functions of DRA


DRA performs the following functions in the network:

- Peer Aggregation:
 - Provides an aggregation point to eliminate full mesh of endpoint peer connections.
 - Addition of endpoint does not require reconfiguration of endpoints. Requires only the configuration of a new endpoint on DRA.
- Intelligent Routing:
 - Provides intelligent load balancing behavior for endpoints (PGW, AF).
 - Endpoints typically only route to primary/secondary peer connections.
 - Route requests to servers (PCRF, OCS) based on content of Diameter AVPs (Called-Station-ID, IPv4 Address, IPv6 Address and IMSI-APN combined).
 - Weighted routing of requests to diameter servers (PCRF, OCS).
- Binding:

- Route requests for related diameter sessions to the same Diameter server (PCRF, OCS). For example, DRA binds Gx and Rx to the same IP session using the framed IPs.
- Relay:
 - DRA provides mechanism to relay request to another DRA. In certain cases, when route for the request is found on a remote DRA, the request is relayed to the remote DRA.

CPS vDRA Architecture

The following figure illustrates the components of CPS vDRA architecture.



DRA Director is stateless node. DRA Director has diameter stack running on it, which connects to the external network functions (for example, PCEF, PCRF, AF). DRA Director receives request messages from origin peer, applies routing algorithm, forwards messages to the destination peer. DRA Director then gets answer messages for the requests, which are forwarded back to the origin peer.

DRA Processor is also stateless node that interacts with session and binding databases in the persistence tier to store session and bindings.

DRA Database is used to store bindings and sessions, with MongoDB database running on them. DRA Database uses application based client sharding to distribute data among multiple databases. MongoDB replicates data across multiple databases within the replica set to provide high availability.

Each of these tiers can be scaled horizontally by deploying more virtual machines.

Types of CPS vDRA

CPS vDRA can be deployed as IMS or Policy or a combination of both.

- Policy DRA is a functional element that supports Gx, Rx, Gy, Sy, and Sd diameter interfaces.
Policy DRA has a binding function that ensures diameter messages for Gx and Rx sessions for the same IP-CAN session are routed to the same PCRF when multiple and separately addressable PCRFs have been deployed.
- IMS DRA is a functional element that supports many diameter interfaces including S6a/S6d, S6b, Sh, Cx, SLh, SLg, SWm, SWx, SWa, and STa.
IMS DRA supports SLF-based routing to ensure Diameter messages are routed to an HSS and AAA server that can provide service for a UE based on a subscriber key (that is, IMSI or MSISDN).
- Combination DRA is a functional element that supports both Policy DRA and IMS DRA functionality.



CHAPTER 2

User Configuration

- [Basic Configuration, on page 5](#)
- [Routing Techniques, on page 10](#)
- [Advanced Features, on page 15](#)

Basic Configuration

Before you begin using CPS vDRA, perform the following basic configurations in CPS DRA:

- Configure Systems
- Configure Diameter Application
- Configure Routing AVP Definitions

Configure Systems

In CPS DRA, navigate to the **System and Plugin Configuration**.

Configure the stack in **DRA Configuration** plugin.


Configure the **DRA Inbound Endpoints** for incoming peer connections and **DRA Outbound Endpoints** for outgoing peer connection.

You can choose the Transport Protocol as TCP and SCTP depending on your requirement.

You can also specify the IPv4 or IPv6 address configuration for the stack connection.

The following image shows a sample configuration.

Figure 1: Sample Systems Configuration




For more information, see [DRA Configuration](#).

Configure Diameter Application

Configure the Diameter applications that are required to be connected over various interfaces with CPS vDRA. The following image is a sample of a Gx application configuration:

Figure 2: Sample Diameter Application Configuration



For more information, see [Diameter Application, on page 73](#).

Configure Multiple Diameter Applications for a Peer Connection

Previously, vDRA supported a single application on a peer connection. In this release, vDRA supports multiple applications on a peer connection.

To configure multiple applications for a peer connection, go to vDRA Inbound Endpoints in DRA Plugin configuration. In the Applications field, select the button as shown:

Figure 3: DRA Inbound Endpoints


DRA Inbound Endpoints

*Vm Host Name	*Ip Address	*Realm	*Fqdn	Transport Protocol	Multi-Homed IP's	*Application	Enabled
AMUKEWAR-M-P01E	10.142.148.142	gx-dra1.cisco.com	gx-dra1	TCP			<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	rx-dra1.cisco.com	rx-dra1	TCP		Rx Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	gx-dra2.cisco.com	gx-dra2	TCP		Gx Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	sd-dra1.cisco.com	sd-dra1	TCP		Sd Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	gx-dra3.cisco.com	gx-dra3	TCP		Gx Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	rx-dra2.cisco.com	rx-dra2	TCP		Rx Application	<input checked="" type="checkbox"/>

Add Remove [Icons]

Select all the applications you require.

Figure 4: Application Selection



The following example shows multiple Diameter applications for a peer connection:

Figure 5: Multiple Applications

DRA Inbound Endpoints

*Vm Host Name	*Ip Address	*Realm	*Fqdn	Transport Protocol	Multi-Homed IP's	*Application	Enabled
AMUKEWAR-M-P01E	10.142.148.142	gx-dra1.cisco.com	gx-dra1	TCP		Rx Application, Gx Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	rx-dra1.cisco.com	rx-dra1	TCP		Rx Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	gx-dra2.cisco.com	gx-dra2	TCP		Gx Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	sd-dra1.cisco.com	sd-dra1	TCP		Sd Application	<input checked="" type="checkbox"/>
AMUKEWAR-M-P01E	10.142.148.142	gx-dra3.cisco.com	gx-dra3	TCP		Gx Application	<input checked="" type="checkbox"/>

Configure Routing AVP Definitions

Configure the Routing AVP definitions to route calls on the basis of the AVPs that are present in diameter message.

In the **Routing AVP Definition** page, you specify the Application name and the table for table-driven routing.

In the **Diameter Application** page, configure the Application Route for table-driven routing.

The following screenshots show a sample configuration:

Figure 6: Routing Avp Definition

Routing Avp Definition

Name

Routing Avp Lookup

```
*Search Table Group
apn_mapping_table
TB_GX_NEW_SESSION_1
```

Actions

Figure 7: Diameter Application

Diameter Application

Name ***Application Id**

Vendor Ids

10415
 8164
 9

Type Application

Application Route

Name	*Priority	*Command Code	Request Type	*Destination Hk	Action Tables
Gx_Initial	1	272	1	<input checked="" type="checkbox"/>	Gx_Application
Gx_Terminate	1	272	3	<input checked="" type="checkbox"/>	Gx_Application
Gx_Update	1	272	2	<input checked="" type="checkbox"/>	Gx_Application
RAR	1	258	0	<input checked="" type="checkbox"/>	Gx_Application


Enable Mediation

By default, mediation feature is disabled.

To enable the mediation, log in to Policy builder, select the “Enable Mediation” checkbox in **Systems > DRA Configuration > DRA Feature**.

Finally, publish the configuration changes.

Figure 8: Enable Mediation



Enable DOIC

By default, DOIC feature is disabled.

To enable the DOIC, log in to Policy Builder, select the “Enable DOIC” checkbox in **Systems > DRA Configuration > DRA Feature**.

You must also enable DOIC for the group in Peer Group SRK Mapping table as described in [Peer Group SRK Mapping, on page 115](#).

Configure throttling using DOIC. For more information, see [Configure Throttling of Diameter Messages Using DOIC, on page 26](#).

Publish the configuration changes.

Configure Interfaces for SCTP Multi-homing

As a pre-requisite for SCTP multi-homing, you must first move the physical interfaces of Director VM inside the diameter-endpoint container.

To move the IPv4 interfaces, perform the following commands in vDRA Master CLI mode:

```
config diameter host dra-director-0-dra-director-52wumnq512y1
  interface ens3 ipv4 address 10.77.87.79 broadcast 10.77.87.255 prefix-length 24
diameter host dra-director-0-dra-director-52wumnq512y1 interface ens3
route default gateway 10.77.87.1
diameter host dra-director-0-dra-director-52wumnq512y1 interface ens5
  ipv4 address 10.225.115.199 broadcast 10.225.115.255 prefix-length 24
diameter host dra-director-0-dra-director-52wumnq512y1 interface ens5
route default gateway 10.225.115.1
```

To move the IPv6 interfaces, perform the following commands in vDRA Master CLI mode:

```
config diameter host dra-director-0-dra-director-52wumnq512y1
  interface ens6 ipv6 address 2003:3051::114 prefix-length 64
diameter host dra-director-0-dra-director-52wumnq512y1 interface
ens6 route default gateway 2003:3051::1
diameter host dra-director-0-dra-director-52wumnq512y1 interface
ens7 ipv6 address 2003:3052::114 prefix-length 64
diameter host dra-director-0-dra-director-52wumnq512y1 interface
ens7 route default gateway 2003:3052::1
```

Commit the configuration.

Routing Techniques

You can define the routing of calls based on destination host, SRK, or a table.

Configure Destination Host Routing

Destination host based routing is the basic and default routing technique used by CPS vDRA.

When the incoming diameter request contains the destination-host AVP that has the direct connection with the CPS vDRA, vDRA routes the message directly to that connected host.

Before you begin

Stack must be up and running.

For more information, see [Basic Configuration, on page 5](#).

After configuring the stacks, Diameter endpoints are ready to initiate/accept Diameter connections for the defined IP address, Port, and Application-ID.

Policy DRA





For Policy DRA, you must configure the binding keys for Gx sessions.





Binding helps Policy DRA route the related Gx/Rx sessions to the same PCRF or destined PCRF.

A binding database is needed to map search keys to PCRF binding information. Each binding has a search key and binding data associated with it. The supported search keys are:

- IMSI + APN
- IPv6
- IPv4
- MSISDN + APN

Figure 9: Policy DRA Sample Configuration

binding_key_profile					
					Filter CRD Tables
Profile Name * (key)	IMSI APN Key Enabled	MSISDN APN Key Enabled	Framed IPv6 Enabled	Framed IPv4 Enabled	Actions
DefaultProfile	true	false	false	false	 
Rx_Profile	false	false	true	false	 

app_id_key_profile_mapping		
		Filter CRD Tables
Application Id * (key)	Profile Name	Actions
16777238	DefaultProfile	 
16777216	Qv_Profile	 

If the Binding Key Profile and mapping to Application ID is not configured properly, the following errors may occur:

- Gx Calls – Session binding failure in database resulting in call failures.
- Rx Calls – Binding Retrieval failure resulting in call failures.



Note IMS DRA does not require bindings. Hence, Binding Key Profile is only valid for Policy DRA.

Configure SRK Based Routing

You can configure SRK based routing in one of the following ways:

Configure Secondary Peer Fallback



Note This configuration is valid for both Policy and IMS DRA.

In SRK based routing, you can configure routing to a set of peers. This can be used for alternate routing (secondary and tertiary routes) when the Destination Host routing fails, and for binding data to select a peer for related diameter sessions. The Session Routing Table is configured within a “Peer Group SRK Mapping” Table. If a routing with dest-host fails, CPS vDRA will try to find out secondary routes on the basis of SRK.

Once the SRK of failed peer is determined by CPS vDRA, it will try to find an UP peer that is a member of:

- A peer group matching the entire SRK label. If it finds one, it will route the message to that peer.

- If it cannot find one and it is a two-label SRK, then it will try to find an UP peer in a peer group whose label2 part of its SRK matches the label2 part of the lookup SRK (where the label 1 part may be different). If it finds one, then it will route the message to that peer.

The following screenshot shows an example of SRK configuration:

Figure 10: SRK Configuration

Peer Group * (key)	Session Routing Key	Destination Host Routing Rule *	Destination Host Replace	Destination Realm Replace	Actions
GX_DC_1		preferred			
SD_DC_2		preferred			
GX_DC_2		preferred			
GX_DC_3	clusterb.dc1	preferred			
SD_DC_3	clusterb.dc2	preferred			
RX_DC_2	clusterb.dc1	preferred			

Configure Binding Retriever for Rx Calls



Note This configuration is valid for Policy only.

Rx (AAR) Message processing: Policy DRA receives the AAR request from Application Function (AF). AAR messages does not have destination host and the destination PCRF has to be found out by vDRA using the keys such as:

1. Framed Ipv6 Address
2. Framed IP address
3. IMSI APN key
4. MSISDN APN key

Binding is created by vDRA when Gx-CCRI is received at DRA. DRA creates the bindings on the basis of CRD configurations and the availability of AVPs in Gx message. If the configured keys are present in Gx message, vDRA creates and stores the binding in Binding Database. On receiving AAR request, vDRA searches for the session stored in bindings on the basis of Rx profile, and will determine the SRK of Gx-PCRF peer. DRA will then forward the Rx request to the Rx peer having the same SRK. [SRK will be configured as mentioned in following section].

Configure SLF Based Routing



Note This configuration is valid for IMS DRA only.

SLF Routing works with two major configurations and tables within CRD:

1. SLF Trigger Profile: For the incoming Diameter requests where Destination-Host is not present (or Destination-Host is present with same of DRA-Host Name) this SLF Trigger table is triggered. In this Table, there are three inputs that you need to configure:

- Application-Id: Diameter Application ID for which the SLF Query is to happen.
- Command-Code: Diameter Command Code for which the SLF query is to happen.



Note If this field is configured with a '*', it indicates that SLF query is expected to happen for all the command codes for the specific application.

- Destination-Realm: Destination-Realm of the Diameter Endpoint (that is, HSS/AAA) or the Destination Realm of vDRA.

Based on the Input keys (Application-Id, Command-Code and Destination-Realm) configured, if all the entries (as mentioned above) matches with the incoming message then vDRA(SLF) picks the "SLF Lookup Type" and "SLF-Destination-Type" as configured in the SLF Trigger Table.

- SLF LookupType- Currently the SLF LookupType can be configured as IMSI or MSISDN. Based on the configured value of IMSI or, MSISDN, vDRA (SLF) further makes a query towards the SLF-DB.
- SLF Destination-Type-Based on the configured value in the 'SLF Destination Type', vDRA (SLF) makes a further query towards the SLF-DB.


Figure 11: SLF Trigger Profile

slf_trigger_profile						
Application ID * (key)	Command Code * (key)	Destination Realm * (key)	Primary Lookup Type *	Secondary Lookup Type	SLF Destination Type *	Actions
16777291	*	slh-hss.com			LTE-HSS	
16777217	*	sh-hss.com			LTE-HSS	
16777251	*	slh-hss.com			LTE-HSS	
16777217	*	sh-hs.com	MSISDN		Sh-HSS	
16777251	*	mnc286.mcc311.dranetwork.org	IMSI		S6a-HSS	











2. SLF Routing: After vDRA(SLF) makes the query in SLF-DB based on SLF-LookupType and SLF-Destination-Type, an SLF-Destination is obtained.

SLF Mapping table consists a mapping of 'SLF-Destination' which is obtained from the SLF database and a SLF-Session-Route-Key(SLF-SRK). In the SLF Mapping Table, based on the SLF-Destination an SLF-Session-Route-Key (SLF-SRK) is derived and further Peer group is derived for routing from the Peer-Group-Peer table as the next step for Routing.

Figure 12: SLF Routing



The screenshot shows a web interface for configuring SLF routing. At the top, there is a search bar containing 'sif_routing' and a 'Filter CRD Tables' button. Below this is a table with three columns: 'SLF Destination * (key)', 'SLF Session Route Key *', and 'Actions'. The table contains five rows of configuration data.

SLF Destination * (key)	SLF Session Route Key *	Actions
lle_hss_a	hss_cluster_dct	 
S6a-HSS1	LTE.S6a.HSS	 
SLF-Sh-HSS	LTE.Sh.HSS	 
SLF-S6a-HSS	LTE.S6a.HSS	 
SLF-Swm-AAA	LTE.Swm.AAA	 

Configure Table Driven Routing

CPS vDRA has the ability to use AVPs within the Diameter messages to help determine how to route the traffic.

The AVP being evaluated is customer configurable, through the CPS DRA GUI. The addition, subtraction, or modification of the evaluation AVP is dynamic and affected real time.

Trigger Condition for Table-driven Routing:

- After Destination-Host based routing (first priority) and SRK routing (second priority) conditions are not met, vDRA goes for Table-driven routing as third priority.
- Typically, for Table-driven Routing to trigger, a Diameter message contains a Destination-Realm AVP, but no Destination-Host AVP. So, If the Dest-Host AVP is absent, empty, or equal to the DRA FQDN, then we skip Dest-Host routing altogether and proceed directly to Table-Driven routing.



Note For IMS-DRA only, the router will try to do the SLF routing (if all conditions are met), before moving to table-driven routing.

vDRA can parse and has the ability to route based on the following AVPs:

- Destination-Host
- Destination-Realm
- Origin-Host
- Origin-Realm
- APN (from Called-Station-ID)
- IMSI (from Subscription-ID)
- MSISDN (from Subscription-ID)

Regular-expression matching and combinations of AVPs are also supported. The following configuration is required in Policy Builder:

1. Application Route: For more information, see [Basic Configuration, on page 5](#).

2. Routing AVP definitions: For more information, see [Basic Configuration, on page 5](#).
3. Search table group configurations: For more information, see [Search Table Groups, on page 84](#).
4. CRD configuration: For more information, see [Custom Reference Data Tables, on page 84](#).

Advanced Features

Configure Rate Limiting

You can use CPS vDRA to set rate limiting of traffic coming from and going towards a particular peer. You can configure this for both Ingress and Egress traffic. Rate limit is currently supported at peer level and message level.

1. Configure the Message Rate Limit Profile CRD table.

Create the rate limit profile with the rate limit profile name, application ID, command code, message type, and message rate limit. For more information, see [Search Table Groups – Message Rate Limit Profile table](#).

Figure 13: Message Rate Limit Profile

Rate Limit Profile Name * (key)	Application Identifier * (key)	Command Code * (key)	Message/Request Type * (key)	Message Rate Limit *	Actions
GX-CCR-I	Gx	272	1	7	Edit Delete

[+ Add Row](#)

Show 10 rows | 1 out of 1

2. Configure the Peer Rate Limiting CRD table.

Define the peer group, peer fqdn, message direction (ingress or egress), rate limit profile (created in step 1), peer rate limit, discard behavior (whether to silently drop or send error message). For more information, see [Search Table Groups – Peer Rate Limit Profile table](#).

If you want the discard behavior sent in the error answer, also configure the Result Code, Error String to be sent in the answer.

Figure 14: Peer Rate Limit Profile

Peer Group * (key)	Peer FQDN * (key)	Message Direction * (key)	Rate Limit Profile	Peer Rate Limit	Discard Behavior *	Result Code	Error String	Actions
match=GX_DC.*	*	Ingress	GX-CCR-I	3	Send Error Answer	3002	OVERLOAD_GX	✎ 🗑️

+ Add Row

Show 10 rows | 1 out of 1

Configure Error Result Code Profile

CPS vDRA generates several internal errors that are not generic, for example, errors such as Timeout triggered, Peer not found, DB error, and so on.

You can configure error codes and error messages for internally generated errors in CPS vDRA.

To configure this error code, add entry in the Error Result Code Profile table as shown in the following image:

Figure 15: Error Result Code Profile

Application Id * (key)	Error * (key)	Result Code	Exp Result Code	Vendor Id	Err Msg	Actions
*	No Available Peer	4004	5004	10415	Peer not available	✎ 🗑️
*	No Peer Group	4005		10415	No Peer Group Available	✎ 🗑️
*	No Binding Found	3024		10415	No Binding found for request	✎ 🗑️
*	Message Loop Detected	4007		10415	Loop Detected in Message	✎ 🗑️
*	No Binding Key For Lookup		4008	10415	No Binding Key for Lookup	✎ 🗑️

+ Add Row

Show 10 rows | 1 out of 1

For a particular Application ID, if DRA generates an internal error, the error code defined in this table along with the Error Message is sent back in the answer.

If the result code is not configured and the Experimental Result Code is present, then the Experimental Result-Code is sent back in the answer along with Vendor-Id AVP. Between the Result-Code and the Experimental Result code, the Result-code is of higher priority.

Configure Peer Group Answer Timeout

You can set the different request timeout durations for different application ID and peer group. In CPS vDRA, timeout is the amount of time that vDRA waits for the answer from the destination.

To configure this feature, add an entry in the Peer Group Answer Timeout table. The timeout value is in milliseconds.

The default timeout is 1.7 seconds. You can also override the timeout for specific interface in this table as shown in the following image:

Figure 16: Peer Group Answer Timeout

Application Id * (key)	Peer Group * (key)	Timeout Milliseconds	Actions
16777238	GX_DC_1	25000	
16777238	GX_DC_2	22000	
16777238	GX_DC_3	20000	
16777236	RX_DC_1	20000	
16777303	SD_DC_1	25000	
16777303	SD_DC_2	25000	
16777236	RX_DC_2	22000	

+ Add Row

Show 10 rows | 1 out of 1



















Configure Peer Load Balancing

CPS vDRA has capabilities to route messages based on weight and precedence of the peer. Perform the following steps to define the peer load balancing:

1. Configure the Peer Routes table:

- This table defines the name of the Peer Routes that are then used in the Peer Routing table.
- This table is mainly used in Table-driven routing where the peer route is derived from the application table-driven rule tables.

Figure 17: Peer Routes

Peer Routes	
Peer Route * (key)	Actions
GX_CONSUMER	 
GX_ENTERPRISE	 
RX_CONSUMER	 
RX_CONSUMER_SITE	 
GX_CONSUMER_C	 
SD_CONSUMER	 
SD_CONSUMER_1	 
RX_ENTERPRISE	 
SD_CONSUMER_2	 

+ Add Row

Show 10 rows out of 1

- Configure the Peer Group Mapping table. This table defines the mapping of peers and realm with peer group.
 - Once the peer group is derived, CPS vDRA looks up this table to find the peers that belong to the derived peer group. Once DRA lists the peers in the peer group, it tries to match these peers with the Active Peer list, that is, peers which are currently connected to CPS vDRA.

If multiple peers are up in a peer group, CPS vDRA load balances the traffic in a round-robin manner according to peer weight.





















The peer weight range is 0-1000 and the default weight is 100. If a peer weight is 0, then that peer is skipped.

For example, if there are two peers up in a peer group with weights 100 and 200 respectively, then CPS vDRA load balances traffic between the two peers in the ratio of 33% and 67% respectively.
 - This table is applicable to SRK and Table driven routing only and is not used in Destination Host routing.

Figure 18: Peer Group Mapping

Peer Group Mapping

Filter CRD Tables

Realm Pattern * (key)	FQDN Pattern * (key)	Peer Group	Actions
gx-pcef.cisco.com	gx-pcef	GX_DC_3	 
gx-pcrf.cisco.com	gx-pcrf	GX_DC_1	 
rx-pcrf.cisco.com	rx-pcrf	RX_DC_2	 
*	sd-pcrf	SD_DC_1	 
*	gx-pcrf	GX_DC_1	 
*	gx-pcrf2	GX_DC_2	 
*	gx-pcrf3	GX_DC_1	 
*	gx-pcrf4	GX_DC_2	 
*	pcrf2-gx2	GX_DC_1	 
*	rx-af	RX_DC_1	 

+ Add Row

Show 10 rows out of 2

3. Configure the Peer Routing table.

This table requires the following inputs:

- Peer Route – derived from the Peer Route table
- System Id – the current system ID of the CPS vDRA system
- Peer Group – derived from the Peer Group Mapping table

The outputs of this table are:

- Precedence
- Weight

Weight and Precedence are used to load balance the traffic among peers.

Figure 19: Peer Routing

Peer Routing					
Peer Route * (key)	System Id * (key)	Peer Group * (key)	Precedence *	Weight *	Actions
SD_CONSUMER_2	system-1	SD_DC_1	1	1	✎ 🗑
GX_CONSUMER	system-1	GX_DC_1	1	1	✎ 🗑
RX_CONSUMER	system-1	GX_DC_1	1	1	✎ 🗑
RX_CONSUMER	system-1	GX_DC_2	1	1	✎ 🗑
SD_CONSUMER	system-1	SD_DC_2	1	1	✎ 🗑
GX_CONSUMER_C	system-1	GX_DC_3	1	1	✎ 🗑
SD_CONSUMER_1	system-1	SD_DC_2	1	1	✎ 🗑

+ Add Row

Show 10 rows out of 1

Configure Message Retries

CPS vDRA has the capability of retrying messages to multiple connected peers, in case the destination peer is not up. Retry mechanism works completely on the basis of SRK.

To configure message retries, you need to configure the Message Retry Profile table.

Figure 20: Message Retry Profile

Message Retry Profile						
Peer Group * (key)	Application Id * (key)	Command Code * (key)	Result Code * (key)	Experimental RC	Number Of Retries	Actions
GX_DC_1	16777238	272	3003	false	6	✎ 🗑
GX_DC_1	16777238	272	3004	false	6	✎ 🗑
GX_DC_2	16777238	272	3003	false	6	✎ 🗑
GX_DC_2	16777238	272	3004	false	6	✎ 🗑
match=SD_DC.*	16777303	8388637	3004	false	6	✎ 🗑
RX_DC_1	16777236	258	7000	false	6	✎ 🗑
GX_DC_2	16777238	272	7000	false	6	✎ 🗑

+ Add Row

Show 10 rows out of 1

You can configure message retry on the basis of the following inputs:

- Peer Group
- Application Id
- Command Code

- Result-Code

The outputs of this table are:

- Number of retries
- Experimental RC

When the retry criteria matches, then:

1. First, the retry is done on any connected peer in the same peer group.
2. If no peer is found in the same peer group, the next priority is given to the peers in the peer group having the same SRK as the peer group to which the request was originally sent.
3. If the above condition also fails to find a peer, the last priority is given to the peers in the peer group that share the same second label as that of the original peer group.



Note CPS vDRA uses the Peer Group Mapping table to find the peer in the same peer group. Hence, the Peer Group Mapping table configuration is a prerequisite.

At the end, if no peer is found, retries stop. The retry also stops when the number of retries is exhausted and no response is received.

Configure Reserved IMSIs

You can now specify a reserved MCC range so that vDRA validates a parsed IMSI for SLF routing against a configured list of reserved MCC. If the IMSI matches a reserved IMSI, the value is ignored for SLF routing.

Configure the Reserved IMSI CRD table with columns for MCC Start Range and MCC End Range.

Figure 21: Reserved IMSI CRD Table

*Name	Display Name	*Use In Condit*	*Type
mcc_start	MCC Start	<input checked="" type="checkbox"/>	Number
mcc_end	MCC End	<input checked="" type="checkbox"/>	Number

For more information, see [Reserved IMSI, on page 101](#).

In DRA, configure the MCC Start Range and MCC End Range.

Figure 22: MCC Range

Reserved MCC		
MCC Start	MCC End	
300	311	

Any calls within Reserved IMSI range are either routed by alternate means such as table-driven routing or result with an error.

Configure Multiple Lookup in SLF Trigger Profile

Previously, in vDRA, the SLF lookup Type in the SLF trigger table had options only to support two types of lookup, that is, IMSI, MSISDN.

You can now specify Primary and Secondary Lookup Keys in the SLF Trigger Profile Table.

First, configure the columns in the CRD table as shown:

Figure 23: CRD Table Configuration

Application ID	Command Code	Destination Realm	Primary Lookup Type	Secondary Lookup Type	
16777251	*	slf-hss.com	IMSI		LTE→
16777291	*	slf-hss.com	IMSI		LTE→
16777217	*	ims.mnc286.mcc311.3gppnetwork.org	MSISDN	IMSI	LTE→
16777251	*	mnc286.mcc311.3gppnetwork.org	IMSI		S6a-H
16777217	*	mnc286.mcc311.3gppnetwork.org			

In the SLF Trigger Profile, you can select the Primary Lookup key from the drop down list. Similarly, you can select the Secondary Lookup key.

Figure 24: SLF Trigger Profile

Custom Reference Data Table (Read Only)			
Name	Display Name	Cache Results	Evaluation Order
slf_trigger_profile	SLF Trigger Profile	<input checked="" type="checkbox"/>	0

Name	Display Name	*Use In Conditio	*Type
application_id	Application ID	<input checked="" type="checkbox"/>	Text
cmd_code	Command Code	<input checked="" type="checkbox"/>	Text
dest_realm	Destination Realm	<input checked="" type="checkbox"/>	Text
primary_lookup_type	Primary Lookup Type	<input checked="" type="checkbox"/>	Text
secondary_lookup_type	Secondary Lookup Type	<input checked="" type="checkbox"/>	Text
slf_destination_type	SLF Destination Type	<input checked="" type="checkbox"/>	Text

Modify Result Code for AVPs Using Mediation Rules

You can configure CRDs to modify the result code of AVPs and overwrite them with a specified value.

1. Define the AVPs in the Diameter Avp Dictionary as shown in the following example for ResultCode:

Figure 25: ResultCode AVP in Diameter Avp Dictionary

Name * (key)	Avp Code	Vendor Id	Avp Type	Actions
ResultCode	268	10415	Unsigned32	

2. Add the condition that is used to match AVPs with a particular result code. In this example, ResultCodeIs3xxx matches the result code AVP with regular expression 3.* and checks for any 3xxx result code.

Figure 26: Add Result Code Condition in Avp Condition Profile

Profile Name * (key)	Avp * (key)	Avp Value *	Actions
ResultCodeIs3xxx	ResultCode	match=3.*	

3. Define the action to be performed in the Avp Action Profile. In this case, ChangeResultcode is used to overwrite AVP values with the value 3002.

Figure 27: Define Action in Avp Action Profile

Profile Name * (key)	Avp * (key)	Avp Action	Avp Value	Actions
ChangeResultCode	ResultCode	Overwrite with value	3002	

4. Add the mediation rule in the Message Mediation Profile.

In the following example, the mediation rule is considered on answer in ingress direction, when application is 16777251, command is 318, and condition profile ResultCode3xxx is met. When all criteria are satisfied, the “ChangeResultCode” action profile is applied.

Figure 28: Mediation Rule

Application Id * (key)	Command Code * (key)	Message Type * (key)	Peer Group * (key)	Message Direction * (key)	Condition Profile * (key)	Action Profile * (key)	Actions
16777251	318	Answer	*	Ingress	ResultCodeIs3xxx	ChangeResultCode	

Hide Topology Using Mediation Rules

Define mediation rules to hide topology.

1. Define the AVPs in the Diameter Avp Dictionary as shown in the following example for OriginHost and OriginRealm:

Figure 29: Diameter Avp Dictionary

Name * (key)	Avp Code	Vendor Id	Avp Type	Actions
OriginHost	264	10415	OctetString	✎ 🗑
OriginRealm	296	10415	OctetString	✎ 🗑

2. Define the action to be performed in the Avp Action Profile. In this case, Hiding is used to overwrite the Origin Host AVP with the value “dra” and to overwrite the Origin Realm AVP with the value “dra.cisco.com”.

Figure 30: Define Action in Avp Action Profile

Profile Name * (key)	Avp * (key)	Avp Action	Avp Value	Actions
Hiding	OriginHost	Overwrite with value	dra	✎ 🗑
Hiding	OriginRealm	Overwrite with value	dra.cisco.com	✎ 🗑

3. Add the mediation rule in the Message Mediation Profile.

In the following example, mediation rule is considered on request and answer in egress direction. It is applicable to all application, all commands, all peer groups and all message types (request/answer). When criteria satisfied, the “Hiding” action profile is applied.

Figure 31: Mediation Rule

Application Id * (key)	Command Code * (key)	Message Type * (key)	Peer Group * (key)	Message Direction * (key)	Condition Profile * (key)	Action Profile * (key)	Actions
*	*	*	*	Egress	*	Hiding	✎ 🗑

Configure Mediation Rule for Proxy-Unaware Endpoints

When endpoints are not proxy-aware, PCRF may send an RAR to the vDRA without Destination Host AVP because it is not proxy friendly.

In such cases, you can configure vDRA to modify the Destination-Host of the RAR based on a regex match of the Diameter Session-ID.

1. Define the AVPs in the Diameter Avp Dictionary as shown in the following example for DestinationHost and SessionId:

Figure 32: Diameter Avp Dictionary

Name * (key)	Avp Code	Vendor Id	Avp Type	Actions
DestinationHost	293	10415	OctetString	✎ 🗑
SessionId	263	0	OctetString	✎ 🗑

- Define the action to be performed in the Avp Action Profile. In this case, ExtractHostFromSessionId is used to overwrite the DestinationHost AVP with the value dynamically derived from the regex string:

```
SubString("${SessionId}", "([^;]+);.*" , 1)
```

The session ID is taken from the message, then regex ([^;]+);.* is applied on the session ID and host is extracted.

For example, if the session ID is “pcef;1450914337;172.30.96.2;0”.

Regex ([^;]+);.* is applied on session ID and it will get 2 groups:

- group1= “pcef”
- group2 = “1450914337;172.30.96.2;0”

Hence, the Destination Host is set with value pcef.

Figure 33: Define Action in Avp Action Profile

Profile Name * (key)	Avp * (key)	Avp Action	Avp Value	Actions
ExtractHostFromSessionId	DestinationHost	Overwrite with value	SubString("\${SessionId}", "[^;]+;.*" , 1)	✎ 🗑

- Add the mediation rule in the Message Mediation Profile.

In the following example, mediation rule is considered on Gx RAR in ingress direction. When all the criteria are met, the “ExtractHostFromSessionId” action profile is applied. Action will set the DestinationHost AVP just after receiving message.

Figure 34: Mediation Rule

Application Id * (key)	Command Code * (key)	Message Type * (key)	Peer Group * (key)	Message Direction * (key)	Condition Profile * (key)	Action Profile * (key)	Actions
16777236	258	Request	*	Ingress	*	ExtractHostFromSessionId	✎ 🗑

Add Prefix to an AVP Using Mediation Rules

You can define a prefix for an AVP.

- First, define the AVPs in the Diameter Avp Dictionary as shown in the following example for the AVP, DestinationHost:

Figure 35: Defining DestinationHost in Diameter Avp Dictionary

Name * (key)	Avp Code	Vendor Id	Avp Type	Actions
DestinationHost	293	10415	OctetString	✎ 🗑
SessionId	263	0	OctetString	✎ 🗑

- Define the PrependLabel profile in the Avp Action Profile that adds the prefix "core-" to the DestinationHost AVP.

Figure 36: Define PrependLabel Profile in Avp Action Profile

Profile Name * (key)	Avp * (key)	Avp Action	Avp Value	Actions
PrependLabel	DestinationHost	Add Prefix	core-	✎ 🗑

- Add the mediation rule in Message Mediation Profile as shown in the following example.

In this example, the mediation rule is applied on s6 AIR request message in egress direction. When the peer group also matches hss-g, it will apply the “PrependLabel” action profile. Action will add the prefix “core-“ to destination host.

Figure 37: Mediation Rule in Message Mediation Profile

Application Id * (key)	Command Code * (key)	Message Type * (key)	Peer Group * (key)	Message Direction * (key)	Condition Profile * (key)	Action Profile * (key)	Actions
1677251	318	Request	hss-g	Egress	x	PrependLabel	✎ 🗑

Configure Throttling of Diameter Messages Using DOIC

About DOIC

vDRA can throttle or divert Diameter requests towards PCRF, HSS, AAA, and OCS servers based on reporting of overloaded conditions using the architecture described in RFC 7683 Diameter Overload Indication Conveyance (DOIC).

The DOIC feature in vDRA involves the following high-level processes:

DOIC Enablement

DOIC feature is enabled/disabled in vDRA and also for the peer group.

DOIC Capability Exchange

If the DOIC feature is enabled, then for every request received, vDRA adds the OC-Supported-Features AVP to the request message to announce the DOIC support for loss of algorithm.

OCS Map

The OCS Map is the local vDRA cache, which contains the information of each reporting node with its latest overload control state information. On receipt of OC-OLR AVP from the peer, vDRA looks for the entry in OCS Map and updates the overload control state object.

Peer Overload Detection

vDRA checks the OCS entry from the OCS Map to determine whether the overload treatment is required or not.

Table Lookup

vDRA queries the Message Class Profile table to retrieve the Message classification. The message classification is used to query the DOIC Profile table to determine the Abatement Action that must be applied.

Overload Treatment

There are three types of overload treatment supported: Forward, Divert, and Drop. For more information, see [DOIC Profile, on page 111](#).

Configuring DOIC in vDRA

To configure vDRA for throttling, perform the following steps:

1. Enable DOIC feature in vDRA in the Policy Builder as described in [Enable DOIC, on page 9](#).
2. Enable DOIC for the peer group using the Peer Group SRK mapping table as described in [Peer Group SRK Mapping, on page 115](#).
3. Define the AVP condition in the Diameter AVP Dictionary table. For more information, see [Diameter Avp Dictionary, on page 112](#).
4. Configure the Message Class Profile table to get the message classification as output. For more information, see [Message Class Profile, on page 118](#).

If AVP conditions are evaluated to be true, then get Message Class. Message Class can be one of P0, P1, P2, P3, P4.
5. Use the Message class to define the abatement action in the DOIC Profile table. For more information, see [DOIC Profile, on page 111](#).

Configure Throttling of Diameter Messages Using DRMP

vDRA can throttle Diameter requests based on the message priority sent in the Diameter request using the architecture described in RFC 7944 Diameter Routing Message Priority (DRMP).

To configure vDRA to use DRMP, perform the following steps as described in [Configure Throttling of Diameter Messages Using DOIC, on page 26](#). Ensure you use the DRMP AVP in the Diameter Avp Dictionary table.

With this configuration, messages with Message Class P0 are not throttled in either rate limiter or by DOIC. For the rest of the messages, the throttling is applied as configured in DOIC table or in rate limiter.

Rate limiter currently throttles message regardless of the message class/ DRMP value. However, it will not throttle the message with message class P0.

Configure vDRA for eMPS

You can configure vDRA to recognize Diameter messages as Enhanced Multimedia Priority Services (eMPS) based on Diameter Application-Id, Command-Code, and AVP values.

An eMPS request is marked as a Priority 0 (or P0 in message classification) request and is not throttled or dropped.

1. Specify the AVP in the Diameter Avp Dictionary as shown in the following example:

Figure 38: Diameter Avp Dictionary

Name * (key)	Avp Code	Vendor Id	Avp Type	Actions
*				✎ ✖
Called-Station-Id	30	10415	OctetString	✎ ✖
MPS-Identifier	528	10415	OctetString	✎ ✖

2. Specify the AVP condition in the Avp Condition Profile table.

Figure 39: Avp Condition Profile

Profile Name * (key)	Avp * (key)	Avp Value *	Actions
*	*		✎ ✖
IsEmergency	Called-Station-Id	911	✎ ✖

3. In Message Class Profile, configure the Message/Request Type as 'None', Message Class as P0, and Ingress Peer Group as '*', so that the message is treated as eMPS irrespective of the type of message (request or response) and the peer group it is sent to.

Figure 40: Message Class Profile

Ingress Peer Group *	Application Id *	Command Code *	Message/Request Type *	Condition Profile *	Message Class	Actions
*	1677238	272	None	IsEmergency	P0	✎ ✖

+ Add Row

Show 10 rows | 1 out of 1

Configure Topology Hiding for S6a/d Diameter Application

Configure topology hiding for the S6a/d Diameter application (Diameter interface between the MME/SGSN and the HSS).

1. Configure a trusted realm profile: Define the name of a Trusted Profile and associate a realm which can be trusted with it.

Figure 41: Trusted Realm Profile

Trusted Profile Name *	Trusted Realm *	Actions
HSS_TRUSTED_PROFILE	imstrusted2.mnc287.mcc312.3gppnetwork.org	Edit Delete
MME_Trusted_Profile	mme trusted.mnc33.mcc404.3gppnetwork.org	Edit Delete

2. Configure the Protected realm (where vDRA is to provide the topology hiding) and link it to the trusted profile.

Depending on the requests, if the destination/origin realm is trusted, vDRA skips the topology hiding. If the realm is not trusted, vDRA provides topology hiding.

Figure 42: Protected Realm Trusted Profile

Protected Realm *	Profile Name *	Actions
imsprotected2.mnc33.mcc404.3gppnetwork.org	HSS_TRUSTED_PROFILE	Edit Delete

3. In the MME Alias Map, define the MME FQDN, which needs to be protected, and bind it to the Aliases that are used for topology hiding.

Figure 43: MME Alias Map

MME FQDN *	Alias 1 *	Alias 2	Alias 3	Actions
mme1foreign.s6a.ims.mnc287.mcc312.3gppnetwork.org	foreign_mme_alias.mnc287.mcc312.3gppnetwork.org	foreign_mme_alias_2		Edit Delete

4. Define all the HSS Aliases that are used for HSS topology hiding by vDRA in the HSS Aliases table. Specify whether the defined alias is shared or not by multiple protected HSSs.

Figure 44: HSS Aliases

HSS Aliases		
Filter CRD Tables		
HSS Alias FQDN *	Shared Alias *	Actions
hss_alias_1.s6a.ims.mnc33.mcc404.3gppnetwork.org	true	✎ 🗑
hss_alias_2.s6a.ims.mnc33.mcc404.3gppnetwork.org	false	✎ 🗑

- In the HSS Alias Map, map the protected HSS FQDN with the HSS ALIAS defined in previous HSS Aliases table. These aliases are used for the topology hiding of the protected HSSs.

Figure 45: HSS Alias Map

HSS Alias Map				
Filter CRD Tables				
HSS FQDN *	Alias 1 *	Alias 2	Alias 3	Actions
hss33protected.s6a.ims.mnc33.mcc404.3gppnetwork.org	hss_alias_1.s6a.ims.mnc33.mcc404.3gppnetwork.org			✎ 🗑
hss34protected.s6a.ims.mnc33.mcc404.3gppnetwork.org	hss_alias_1.s6a.ims.mnc33.mcc404.3gppnetwork.org			✎ 🗑

Manual Peer Disconnection using REST API

CPS vDRA provides a REST API that you can use to manually disconnect peer connections from vDRA. To disconnect a single peer connection, you need to provide the peer connection key information in the API method.

Disconnect a single peer connection

To disconnect a single peer, provide the peer-connection-key (that you can find in the peer endpoint details) in the PUT method as shown:

```
PUT localActivePeerEndpoints/disconnect/key/<peer-connection-key>
```

Responses:

```
200 OK
{
  "success": {
    "code": 0,
    "message": "Request completed successfully"
  }
}
```

Note that success means the request is accepted, and vDRA attempts to disconnect the peer connection. The success response does not indicate that the peer connection has been disconnected.

Failure response:

```
404 Not Found
{
  "error": {
    "code": 2014,
    "message": "Data for key <peer-connection-key> is not found"
  }
}
```

Policy DRA Relay Configuration

Policy DRA requires a full-mesh topology to be able to send traffic between different sites. In a multi-site DRA network, relay connections are required between every pair of relay endpoints.

Relay Endpoint Configuration

Relay endpoint is used to indicate the IP address/port combination at which vDRA listens for diameter connections. These connections are used to send/receive diameter traffic between sites.

Relay endpoints for vDRA can be configured using the Policy Builder vDRA configuration plugin.

The following fields are required for the configuration:

Vm Host Name

VM Host Name is the host name of the VM. The value '*' can be used to match any host name.

Instance Id

The Instance ID field should be set to '1'. Currently, no other value is supported.

Ip Address

IPv4 or IPv6 address of the interface used to listen for relay connections. Currently, only physical IP addresses are supported. VIP addresses are not supported.

Realm

Supports configurable relay endpoint realm name.

Port

Port that is used to listen for relay connections. The default value is '4868'. Currently, the range of ports supported is '4868-4878'.

Fqdn

FQDN is the string that is used to send the relay endpoint information to the other sites.

Enabled

Used to enable or disable the relay endpoint. It should be enabled for the relay endpoint to start listening on the configured port and IP address.

Control Plane Configuration

The control plane configuration performs the following functions:

- If the IP address is a site-local address, a global Control Plane server is created that listens to connections.
- If the IP address not a site-local address, the connections are initiated from diameter-endpoint containers to the global Control Plane server running at specified IP/port. These connections are used to send and receive global control plane information between sites.



Note It is recommended not to use VIP address. Instead use physical IP address for control-plane relay link.

The following example illustrates control plane configuration:

```
admin@orchestrator# show running-config control-plane
control-plane relay gx-dra1-relay-v6-1
address [2001:421:27c1:913:250:56ff:fea6:12]
port 6379
```



Note The IPv6 address must be encapsulated with square [] brackets.

DNS Host Configuration

The following entities must be DNS resolvable and must have DNS Host configuration entries:

- Control Plane servers from all sites
- Relay Endpoint FQDNs from all sites

The following command is an example of DNS Host configuration:

```
admin@orchestrator# show running-config network dns host
network dns host gx-dra1-relay-v6 local
address 2001:421:27c1:913:250:56ff:fea6:48
```

Virtual-IP Configuration

The following entities must have virtual-IP configuration entries:

- Control Plane Servers with VIP addresses

Relay Configuration for a 6-Site Policy DRA System

The following example describes how to configure the relay configuration for a six site Policy DRA system.

Relay Endpoints

There must be two relay endpoint entries configured in Policy Builder per site; one entry each for the two diameter-endpoint containers.

Control Plane Configuration

There must be at least two global Control Plane servers configured per site; one on each diameter-endpoint for redundancy.

The global Control Plane servers must have connections between each other. This means that every site must have control plane configuration entries for the control plane servers of every other site.

For a six site system, every site must have 12 Control Plane configuration entries (6 sites x 2 global Control Plane servers per site) configured in CLI.

DNS Host Configuration

There should be one DNS Host entry for each of the global Control Plane configuration entries. In a six site system, every site should have 12 DNS Host entries related to global Control Plane entries of all sites.

There should be one DNS Host entry for each Relay endpoints of every site. In a six site system, every site should have 12 DNS Host entries related to Relay Endpoint entries of all sites.

Virtual-IP Configuration

If any global Control Plane servers have VIP addresses, they should have Virtual-IP Configuration.

Every site should have Virtual-IP Configuration for any VIP addresses that are associated to that site.

Configuring Application based Sharding



Restriction

- Migration from hash-based sharding to zone based sharding is not supported.
- Since this feature supports only static sharding configurations, all database configurations needs to be committed with single commit operation.
- Currently, dynamic addition of new shards after initial configuration is not supported as it supports only static shard configurations. If one needs to add new shards or edit existing shards, it is mandatory to clean up the complete database and reconfigure again.

Step 1

Login to Binding VNF CLI to configure application sharding on Binding VNF.

- a) Configure sharded cluster master.

```
database cluster session sharded-cluster-master <true | false>
```

true: enables sharded cluster master. Internally sharding metadata creation gets triggered.

false: Sharding metadata creation is not enabled.

Example:

```
database cluster session sharded-cluster-master true
```

Note Only one site among the mated pair which initially gets configured has to be enabled (true) so that sharding metadata creation happens from that site. For rest of the sites, it just adds members and uses existing sharding metadata.

- b) Configure multi-database collections: This configuration enables the creation of internal logical shards.

```
database cluster session multi-db-collections <1..4>
```

Default: 1

For example, if configured with 2, each sharding database metadata creates an extra logical shard for the shard configured as a part of database creation. So total number of shards will be double the number.

```
database cluster session multi-db-collections 2
```

- c) Configuring sharding database.

```
database cluster <cluster name> sharding-db <sharding-db-name> address <ip address> [port <port>]
```

```
database cluster <cluster name> sharding-db-seed <shardingdb name>
```

Example:

```
database cluster session sharding-db shdb-4 address 192.168.11.43
```

```
database cluster session sharding-db shdb-5 address 192.168.11.44
```

```
database cluster session sharding-db-seed shdb-4
```

Note Port is optional. By default, sharding database uses port 27019.

- d) Configure shards.

```
database cluster <cluster-name> shard <shard-name>
```

Non-arbiter shard member:

```
database cluster <cluster-name> shard <shard-name> shard-server <server-name> storage-engine MMAPv1
address <ipaddress> port <port> priority <priority>
```

Arbiter shard member:

```
database cluster <cluster-name> shard <shard-name> shard-server <server-name> arbiter true
storage-engine MMAPv1 address <ipaddress> port <port>
```

Shard seed:

```
database cluster <cluster-name> shard <shard-name> shard-server-seed <seed-server>
```

Note Seed server has to be one of the non-arbiter member from the same shard.

Example:

```
database cluster session shard shard-21
database cluster session shard shard-21 shard-server server-x storage-engine MMAPv1 address
192.168.11.43 port 27026 priority 10
database cluster session shard shard-21 shard-server server-y storage-engine MMAPv1 address
192.168.11.44 port 27026 priority 5
database cluster session shard shard-21 shard-server arbiter-21 arbiter true storage-engine MMAPv1
address 192.168.11.42 port 27026
database cluster session shard shard-21 shard-server-seed server-x
```

- e) Make sure all the databases are UP with appropriate status using `show database status` command.

Sample output:

```
admin@orchestrator[an-dbmaster]# show database status cluster-name session
ADDRESS          PORT    NAME          STATUS    TYPE          CLUSTER
NAME          SHARD    REPLICA SET
-----
192.168.11.42    27026    arbiter-21    ARBITER    replica_set    session    shard-21    rs-shard-21
192.168.11.43    27026    server-x      PRIMARY    replica_set    session    shard-21    rs-shard-21
192.168.11.44    27026    server-y      SECONDARY  replica_set    session    shard-21    rs-shard-21
192.168.11.42    27027    arbiter-22    ARBITER    replica_set    session    shard-22    rs-shard-22
192.168.11.43    27027    server-x      SECONDARY  replica_set    session    shard-22    rs-shard-22
192.168.11.44    27027    server-y      PRIMARY    replica_set    session    shard-22    rs-shard-22
192.168.11.43    27019    session       PRIMARY    shard_db       session    shdb-4      session-sharddb
192.168.11.44    27019    session       SECONDARY  shard_db       session    shdb-5      session-sharddb

admin@orchestrator[an-dbmaster]#
```

Step 2 Login to DRA VNF CLI to configure application sharding on DRA VNF.

- a) Configure shard metadata database connection.

```
binding shard-metadata-db-connection <dbName> <address> <port>
```

Example:

```
binding shard-metadata-db-connection drasession 182.22.31.207 27019
```

- **<dbName>**: Database name for which connection URI needs to be set.
Possible values are: all, drasession, imsiapn, ipv4, ipv6, msisdnapn, range.
- **<address>**: Address of the binding shard metadata database. This is either an IP address or an FQDN.
- **<port>**: Port of the binding shard metadata database.

Step 3 Login to DRA VNF CLI to configure same connection pool on imsiapn-msisdnapi database.

Note We do not recommended configuring connection pool for small setups. It is required for setups whose database spans across 48 shards or more.

a) Configure same connection pool on imsiapn-msisdnapi database transactions.

```
binding cluster-binding-dbs imsiapn-msisdnapi
```

Example:

```
binding cluster-binding-dbs imsiapn-msisdnapi
```

Example

The following are the examples for complete set of database cluster configuration on Binding VNF.

```
config
database cluster session sharded-cluster-master true
database cluster session multi-db-collections 2
database cluster session sharding-db shdb-4 address 192.168.11.43 port 27019
database cluster session sharding-db shdb-5 address 192.168.11.44 port 27019
database cluster session sharding-db-seed shdb-4

database cluster session shard shard-21
database cluster session shard shard-21 shard-server server-x storage-engine MMAPv1 address
 192.168.11.43 port 27026 priority 10
database cluster session shard shard-21 shard-server server-y storage-engine MMAPv1 address
 192.168.11.44 port 27026 priority 5
database cluster session shard shard-21 shard-server arbiter-21 arbiter true storage-engine
 MMAPv1 address 192.168.11.42 port 27026
database cluster session shard shard-21 shard-server-seed server-x

database cluster session shard shard-22
database cluster session shard shard-22 shard-server server-y storage-engine MMAPv1 address
 192.168.11.44 port 27027 priority 10
database cluster session shard shard-22 shard-server server-x storage-engine MMAPv1 address
 192.168.11.43 port 27027 priority 5
database cluster session shard shard-22 shard-server arbiter-22 arbiter true storage-engine
 MMAPv1 address 192.168.11.42 port 27027
database cluster session shard shard-22 shard-server-seed server-y
commit
```

The following is an example to configure shard metadata database connection for session and all bindings on DRA VNF.

```
config
binding shard-metadata-db-connection drasession 182.22.31.207 27019
binding shard-metadata-db-connection ipv6 182.22.31.207 27019
binding shard-metadata-db-connection ipv4 182.22.31.208 27019
binding shard-metadata-db-connection imsiapn 182.22.31.208 27019
binding shard-metadata-db-connection msisdnapi 182.22.31.208 27019
commit
```

Configuring Binding Database Overload

Login to DRA VNF CLI to configure maximum record limit on session and bindings database.

```
binding db-max-record-limit <db-Name> <limit>
```

<db-Name>: Database name on which maximum record limit has to be set.

Possible values are drasession, imsiapn, ipv4, ipv6, msisdnappn.

<limit>: Numeric value indicating maximum records that could be stored in given database.

Example:

```
binding db-max-record-limit drasession 10000
```

Example

The following is an example for setting maximum record limit on session and all bindings database:

```
config
binding db-max-record-limit drasession 10000
binding db-max-record-limit ipv6 10000
binding db-max-record-limit ipv4 5000
binding db-max-record-limit imsiapn 5000
binding db-max-record-limit msisdnappn 5000
commit
```

Change Admin User Password for MongoDB Authentication



Caution The following procedure is service impacting and needs to be execute on all sites at the same time.

Step 1 Execute the following step on all binding VNF of all sites.

```
db-authentication change-password database mongo user adminuser
```

When prompt is displayed, enter the current password and new password.

```
admin@orchestrator[binding-master]# db-authentication change-password database mongo user
adminuser
Value for 'current-password' (<string>): *****
Value for 'new-password' (<string>): *****
result SUCCESS
```

Step 2 Execute the following step on all DRA VNF of all sites.

```
db-authentication change-password database mongo user adminuser
```

When prompt is displayed, enter the current password and new password.

```
db-authentication change-password database mongo user
adminuser
Value for 'current-password' (<string>): *****
```

```
Value for 'new-password' (<string>): *****
result SUCCESS
```

Step 3 Execute `db-authentication sync-password database mongo` command on all binding VNF of all sites.

```
admin@orchestrator[binding-master]# db-authentication sync-password database mongo
result
SUCCESS : Mongo password sync successful
```

Step 4 Execute `db-authentication sync-password database mongo` command on all DRA VNF of all sites.

```
db-authentication sync-password database mongo
result
SUCCESS : Mongo password sync successful
```

Configuring MongoDB Authentication

Before you begin

- Currently, MongoDB authentication is supported only for fresh deployments of vDRA where application sharding has been implemented.
- MongoDB authentication is not supported for MongoDB sharding deployments.
- Make sure every shard of database cluster has Primary member present. Execute the following command to verify the same.

```
show database status | tab | include PRIMARY
```

- Make sure all the VMs are in CONNECTED state.

```
show docker engine
```

- Make sure there are no IP_NOT_REACHABLE alerts present on the system.

```
show alert status | tab | include IP_NOT_REACHABLE
```

- Make sure the network cache is up to date with all IPs present on each VM.

```
show network ips
```

Step 1 Login to Binding VNF CLI and configure MongoDB authentication on single node setup:

a) Set password.

```
db-authentication set-password database mongo password *****
```

Example:

```
admin@orchestrator[an-dbmaster]# db-authentication set-password database mongo password
Value for 'password' (<string>): *****
result SUCCESS
admin@orchestrator[an-dbmaster]#
```

b) Enable transition authentication.

```
db-authentication enable-transition-auth database mongo
```

Example:

```
admin@orchestrator[an-dbmaster]# db-authentication enable-transition-auth database mongo
admin@orchestrator[an-dbmaster]#
```

- c) Rolling restart of mongod instances.

```
db-authentication rolling-restart database mongo
```

Example:

```
admin@orchestrator[an-dbmaster]# db-authentication rolling-restart database mongo
admin@orchestrator[an-dbmaster]#
```

- d) Monitor rolling restart status.

```
db-authentication rolling-restart-status database mongo
```

Example:

```
admin@orchestrator[an-dbmaster]# db-authentication rolling-restart-status database mongo
result
Rolling Restart: Not Scheduled/Completed
admin@orchestrator[an-dbmaster]#
```

- e) Disable transition authentication.

```
db-authentication disable-transition-auth database mongo
```

Example:

```
admin@orchestrator[an-dbmaster]# db-authentication disable-transition-auth database mongo
admin@orchestrator[an-dbmaster]#
```

- f) Rolling restart of mongod instances.

```
db-authentication rolling-restart database mongo
```

Example:

```
admin@orchestrator[an-dbmaster]# db-authentication rolling-restart database mongo
admin@orchestrator[an-dbmaster]#
```

Note During db-authentication rolling-restart command execution mongod instances are restarted.

- g) Make sure all the databases are UP with correct status.

```
show database status
```

Sample output:

```
admin@orchestrator[an-dbmaster]# show database status
```

ADDRESS	PORT	NAME	STATUS	TYPE	CLUSTER		
					NAME	SHARD	REPLICA SET
192.168.11.42	27036	arbiter-1	ARBITER	replica_set	binding	shard-1	rs-shard-1
192.168.11.43	27036	server-a	PRIMARY	replica_set	binding	shard-1	rs-shard-1
192.168.11.44	27036	server-b	SECONDARY	replica_set	binding	shard-1	rs-shard-1
192.168.11.42	27037	arbiter-2	ARBITER	replica_set	binding	shard-2	rs-shard-2
192.168.11.42	27038	arbiter-3	ARBITER	replica_set	binding	shard-2	rs-shard-2
192.168.11.43	27037	server-a	SECONDARY	replica_set	binding	shard-2	rs-shard-2
192.168.11.44	27037	server-b	PRIMARY	replica_set	binding	shard-2	rs-shard-2
192.168.11.41	27030	binding	SECONDARY	shard_db	binding	shdb-1	binding-sharddb
192.168.11.42	27030	binding	PRIMARY	shard_db	binding	shdb-2	binding-sharddb

- h) DRA VNF Site-A and Site-B.

```
db-authentication set-password database mongo password *****
```

Example:

```
admin@orchestrator[an-master]# db-authentication set-password database mongo password
Value for 'password' (<string>): *****
```

```
result SUCCESS
admin@orchestrator[an-master]#
```

Step 2 Login to Binding VNF CLI and configure MongoDB authentication in mated pair deployments.

Note During `db-authentication rolling-restart` command execution mongod instances are restarted.

- a) On Site A, configure session-AB, imsi-msisdn databases.
- b) On Site B, configure session-AB, imsi-msisdn databases.
- c) On Site A, configure the password and enable-transition-auth and run rolling-restart.
- d) On Site B, configure the password and enable-transition-auth and run rolling-restart.
- e) On Site A, disable transition-auth and run rolling-restart
- f) Make sure all the databases are UP with appropriate status.

```
show database status
```

Sample output:

```
admin@orchestrator[an-dbmaster]# show database status
```

ADDRESS	PORT	NAME	STATUS	TYPE	CLUSTER NAME	SHARD	REPLICA SET
192.168.11.42	27036	arbiter-1	ARBITER	replica_set	binding	shard-1	rs-shard-1
192.168.11.43	27036	server-a	PRIMARY	replica_set	binding	shard-1	rs-shard-1
192.168.11.44	27036	server-b	SECONDARY	replica_set	binding	shard-1	rs-shard-1
192.168.11.42	27037	arbiter-2	ARBITER	replica_set	binding	shard-2	rs-shard-2
192.168.11.42	27038	arbiter-3	ARBITER	replica_set	binding	shard-2	rs-shard-2
192.168.11.43	27037	server-a	SECONDARY	replica_set	binding	shard-2	rs-shard-2
192.168.11.44	27037	server-b	PRIMARY	replica_set	binding	shard-2	rs-shard-2
192.168.11.41	27030	binding	SECONDARY	shard_db	binding	shdb-1	binding-sharddb
192.168.11.42	27030	binding	PRIMARY	shard_db	binding	shdb-2	binding-sharddb

- g) DRA VNF Site-A and Site-B.

```
db-authentication set-password database mongo password *****
```

Example:

```
admin@orchestrator[an-master]# db-authentication set-password database mongo password
Value for 'password' (<string>): *****
result SUCCESS
admin@orchestrator[an-master]#
```

Disabling MongoDB Authentication



Note This section is used to disable MongoDB authentication in mated pair deployments.

Step 1 Login to Binding VNF CLI and perform the following steps:

Note The steps need to be performed on all binding VNFs.

- a) Enable transition authentication.

```
db-authentication enable-transition-auth database mongo
```

- b) Rolling restart of mongod instances.

```
db-authentication rolling-restart database mongo
```

- c) Rolling restart status.

```
db-authentication rolling-restart-status database mongo
```

Step 2 Login to DRA VNF CLI and remove the password by using `db-authentication remove-password database mongo` command.

Note The step needs to be performed on all DRA VNFs.

```
admin@orchestrator[an-master]# db-authentication remove-password
Value for 'password' (<string>): *****
result SUCCESS
admin@orchestrator[an-master]#
```

Step 3 Login to binding VNF CLI and remove the password by using `db-authentication remove-password database mongo` command.

Note The step needs to be performed on all binding VNFs.

Step 4 Login to binding VNF CLI and perform the following steps:

Note The steps need to be performed on all binding VNFs.

- a) Disable transition authentication.

```
db-authentication disable-transition-auth database mongo
```

- b) Rolling restart of mongod instances.

```
db-authentication rolling-restart database mongo
```

- c) Rolling restart status.

```
db-authentication rolling-restart-status database mongo
```

Step 5 Make sure all the databases are UP with appropriate status.

```
show database status
```

Sample output:

```
admin@orchestrator[an-dbmaster]# show database status
```

ADDRESS	PORT	NAME	STATUS	TYPE	CLUSTER NAME	SHARD	REPLICA SET
192.168.11.42	27036	arbiter-1	ARBITER	replica_set	binding	shard-1	rs-shard-1
192.168.11.43	27036	server-a	PRIMARY	replica_set	binding	shard-1	rs-shard-1
192.168.11.44	27036	server-b	SECONDARY	replica_set	binding	shard-1	rs-shard-1
192.168.11.42	27037	arbiter-2	ARBITER	replica_set	binding	shard-2	rs-shard-2
192.168.11.42	27038	arbiter-3	ARBITER	replica_set	binding	shard-2	rs-shard-2
192.168.11.43	27037	server-a	SECONDARY	replica_set	binding	shard-2	rs-shard-2
192.168.11.44	27037	server-b	PRIMARY	replica_set	binding	shard-2	rs-shard-2
192.168.11.41	27030	binding	SECONDARY	shard_db	binding	shdb-1	binding-sharddb
192.168.11.42	27030	binding	PRIMARY	shard_db	binding	shdb-2	binding-sharddb

Configuring Zone Aware Sharding



Restriction

- Migration from hash-based sharding to zone based sharding is not supported.
- Database reconfigure steps must be followed to enable zone aware sharding on existing database cluster.
- Configure the databases on Binding VNF site by site. Not recommended to apply database configurations on all sites in parallel.
- Within single commit all the database configurations needs to be committed.
- Currently, dynamic addition of new shards after initial configuration is not supported.
- You should make sure that there are no overlapping IPv6 addresses within a zone or across multiple zones within a database cluster (or) across multiple database clusters while doing the database configuration. IPv6 address mentioned as the start/end values while configuring the ranges should be unique.
- If you want to add new shards or edit existing shards, it is mandatory to clean up the complete database and reconfigure again.

Step 1

Login to Binding VNF CLI to configure database for zone sharding.

a) Configuring sharding database.

```
database cluster <cluster name> sharding-db <shardingdb name> address <VM ip address> [port <portNum>]
database cluster <cluster name> sharding-db-seed <shardingdb name>
```

Example:

```
admin@orchestrator[an-dbmaster]#
database cluster binding sharding-db shdb-1 address 182.22.31.10 port 27020
database cluster binding sharding-db shdb-2 address 182.22.31.11
database cluster binding sharding-db shdb-3 address 182.22.31.12
database cluster binding sharding-db-seed shdb-1
```

Note <portNum> is optional. By default, the port number is 27019.

b) Enable IPv6 zone sharding.

```
database cluster <cluster name> ipv6-zone-sharding true
```

Example:

```
admin@orchestrator[an-dbmaster]# database cluster binding ipv6-zone-sharding true
```

c) Create zone and its range(s).

```
database cluster <cluster name> ipv6-zones-range <zone-name> zone-range <range-name> start <pool starting Prefix> end <pool ending Prefix>
```

Example:

```
admin@orchestrator[an-dbmaster]# database cluster binding ipv6-zones-range pune zone-range range1
start 2003:3051:0000:0001 end 2003:3051:0000:0500
```

Note It is possible to create multiple ranges for each zone. Configure the ranges in 64-bit Framed IPv6 Prefixes only.

d) Mapping of zone to shard.

```
database cluster <cluster name> shard <shard name> zone-name <zone-name>
```

Example:

```
admin@orchestrator[an-dbmaster]# database cluster binding shard shard-1 zone-name pune
```

e) Sample database configuration with two shards (two zones with two ranges per zone).

Step 2

Login to the master(primary/seed) mongo sharding database and check configured ranges, zones, shard/range mapping information.

```
database cluster binding sharded-cluster-master true
database cluster binding ipv6-zone-sharding true
database cluster binding ipv6-zones-range mumbai zone-range r1 start 2008:5000:0000:0100 end 2008:5000:0000:0500
database cluster binding ipv6-zones-range mumbai zone-range r2 start 2009:5000:0000:0100 end 2009:5000:0000:0500
database cluster binding ipv6-zones-range pune zone-range r1 start 2011:6000:0000:0001 end 2011:6000:0000:0500
database cluster binding ipv6-zones-range pune zone-range r2 start 2012:6000:0000:0001 end 2012:6000:0000:0500
database cluster binding sharding-db shdb-1 address 182.22.31.10
database cluster binding sharding-db shdb-2 address 182.22.31.11
database cluster binding sharding-db shdb-3 address 182.22.31.12
database cluster binding sharding-db-seed shdb-1

database cluster binding shard shard-1
database cluster binding shard shard-1 shard-server server-a storage-engine MMAPv1 address 182.22.31.13 port 27017 priority 10
database cluster binding shard shard-1 shard-server server-b storage-engine MMAPv1 address 182.22.31.14 port 27017 priority 5
database cluster binding shard shard-1 shard-server arbiter-1 arbiter true storage-engine MMAPv1 address 182.22.31.11 port 27017
database cluster binding shard shard-1 shard-server-seed server-a

database cluster binding shard shard-2
database cluster binding shard shard-2 shard-server server-b storage-engine MMAPv1 address 182.22.31.14 port 27018 priority 10
database cluster binding shard shard-2 shard-server server-a storage-engine MMAPv1 address 182.22.31.13 port 27018 priority 5
database cluster binding shard shard-2 shard-server arbiter-2 arbiter true storage-engine MMAPv1 address 182.22.31.11 port 27018
database cluster binding shard shard-2 shard-server-seed server-b

database cluster binding shard shard-1 zone-name mumbai
database cluster binding shard shard-2 zone-name pune
```

a) Check configured ranges.

Example:

```
use ipv6ShardDB
switched to db ipv6ShardDB
binding-sharddb:PRIMARY>
binding-sharddb:PRIMARY> db.shards.find()
```

```
binding-sharddb:PRIMARY> db.shards.find()
{ "_id" : 1, "name" : "shard-1", "hosts" : "182.22.31.13:27017,182.22.31.14:27017", "zone" : "mumbai" }
{ "_id" : 2, "name" : "shard-2", "hosts" : "182.22.31.13:27018,182.22.31.14:27018", "zone" : "pune" }
{ "_id" : 3, "name" : "shard-3", "hosts" : "182.22.31.13:27020,182.22.31.14:27020", "zone" : "hyd" }
{ "_id" : 4, "name" : "shard-4", "hosts" : "182.22.31.13:27021,182.22.31.14:27021", "zone" : "bglr" }
{ "_id" : 5, "name" : "shard-5", "hosts" : "182.22.31.13:27022,182.22.31.14:27022", "zone" : "chennai" }
{ "_id" : 6, "name" : "shard-6", "hosts" : "182.22.31.13:27023,182.22.31.14:27023", "zone" : "hyd" }
{ "_id" : 7, "name" : "shard-7", "hosts" : "182.22.31.13:27024,182.22.31.14:27024", "zone" : "bglr" }
{ "_id" : 8, "name" : "shard-8", "hosts" : "182.22.31.13:27025,182.22.31.14:27025", "zone" : "pune" }
binding-sharddb:PRIMARY>
```

b) Checking configured zones.

Example:

```
binding-sharddb:PRIMARY> db.zoneinfo.find()
{ "_id" : 1, "name" : "r1", "start" : "2017:6000:0000:0001", "end" : "2017:6000:0000:0500", "zone" : "bglr" }
{ "_id" : 2, "name" : "r2", "start" : "2018:6000:0000:0001", "end" : "2018:6000:0000:0500", "zone" : "bglr" }
{ "_id" : 3, "name" : "r1", "start" : "2013:6000:0000:0001", "end" : "2013:6000:0000:0500", "zone" : "chennai" }
{ "_id" : 4, "name" : "r2", "start" : "2014:6000:0000:0001", "end" : "2014:6000:0000:0500", "zone" : "chennai" }
{ "_id" : 5, "name" : "r1", "start" : "2015:6000:0000:0001", "end" : "2015:6000:0000:0500", "zone" : "hyd" }
{ "_id" : 6, "name" : "r2", "start" : "2016:6000:0000:0001", "end" : "2016:6000:0000:0500", "zone" : "hyd" }
{ "_id" : 7, "name" : "r1", "start" : "2008:5000:0000:0100", "end" : "2008:5000:0000:0500", "zone" : "mumbai" }
{ "_id" : 8, "name" : "r2", "start" : "2009:5000:0000:0100", "end" : "2009:5000:0000:0500", "zone" : "mumbai" }
{ "_id" : 9, "name" : "r1", "start" : "2011:6000:0000:0001", "end" : "2011:6000:0000:0500", "zone" : "pune" }
{ "_id" : 10, "name" : "r2", "start" : "2012:6000:0000:0001", "end" : "2012:6000:0000:0500", "zone" : "pune" }
```

- c) Checking shard/range mapping.

Example:

```
binding-sharddb:PRIMARY> db.buckets.find()
{ "_id" : ObjectId("5cb9845c63ebec62ea803d42"), "bucket-id" : 1, "shard" : 4, "migration" : false, "zone" : "bglr" }
{ "_id" : ObjectId("5cb9845c63ebec62ea803d43"), "bucket-id" : 2, "shard" : 4, "migration" : false, "zone" : "bglr" }
{ "_id" : ObjectId("5cb9845c63ebec62ea803d44"), "bucket-id" : 3, "shard" : 4, "migration" : false, "zone" : "bglr" }
{ "_id" : ObjectId("5cb9845c63ebec62ea803d45"), "bucket-id" : 4, "shard" : 4, "migration" : false, "zone" : "bglr" }
{ "_id" : ObjectId("5cb9845c63ebec62ea803d46"), "bucket-id" : 5, "shard" : 4, "migration" : false, "zone" : "bglr" }
{ "_id" : ObjectId("5cb9845c63ebec62ea803d47"), "bucket-id" : 6, "shard" : 4, "migration" : false, "zone" : "bglr" }
{ "_id" : ObjectId("5cb9845c63ebec62ea803d48"), "bucket-id" : 7, "shard" : 4, "migration" : false, "zone" : "bglr" }
```

Modifying Zone Aware Sharding



Note This section is applicable when you want to add/update/delete zones and ranges after performing initial database configuration.

If you have modified already configured zones and ranges in database, you need to perform the following steps to have sharding database metadata updated with new modified configuration commits.

- Step 1** Connect to session database cluster sharding primary database for which configuration changes have been committed.
- Use `show database status` command to get the sharding database primary IP address and port number of a particular database cluster.
 - Use `docker exec -it orchestrator bash` command to connect to sharding database.
 - Connect to sharding database.

If MongoDB authentication is enabled, execute `mongo --ipv6`
`mongo://adminuser:password@[IPAddress]:Port/admin` command.

OR

If MongoDB authentication is disabled, execute `mongo --ipv6 mongo://[IPAddress]:Port` command.

- Verify that after completing [1.c, on page 43](#), the prompt is redirected to mongo shell of the same.

- Step 2** Remove the zone collection information using the following commands from inside mongo shell:

```
use ipv6ShardDB
db.zoneinfo.remove({})
```

- Step 3** Wait for 30 seconds and verify that zone collection information is updated with the new committed configurations.

```
db.zoneinfo.find()  
exit
```



CHAPTER 3

Policy Builder Configuration

- [Plug-in Configuration](#), on page 45
- [Diameter Application](#), on page 73
- [Routing AVP Definition](#), on page 80
- [Custom Reference Data Tables](#), on page 84

Plug-in Configuration


Cisco Policy Builder provides core plug-ins for customizing and optimizing your installation.

- Configurations set at the system level are system-wide except as noted in the bullet items below.
- Configurations set at the cluster level apply to that cluster and the instances in it. A value set here overrides the same value set at the system level.
- Configurations set at the instance level apply to the instance only and override the same value set at the cluster or system level.

Select the **Create Child** action in a **Plug-in Configuration** node in the **Systems** tree to define them. You can change any of the variables from the default, or choose not to use a plug-in, as necessary.

When you create a system from the example, the following configuration stubs appear at the cluster and instance level:

Figure 46: Create Child Action



215166

Threading Configuration


A threading configuration utility is provided for advanced users.

Click **Threading Configuration** in the right pane to add the threading configuration to the system. If you are planning to run the system with higher TPS, then you need to configure Threading Configuration. For further information, contact your Cisco Technical Representative.

The Threading Plug-in having thread pools controls the total number of threads in CPS vDRA that are executing at any given time. Each of these thread pools have a queue associated with it.

A configuration example is shown below:

Figure 47: Thread Pool Configuration



215173

The following parameters can be configured under Threading Configuration:

Table 1: Threading Configuration Parameters

Parameter	Description
Thread Pool Name	Name of the thread pool. For more information on the thread pool names and recommended values that can be configured, refer to <i>Threading Configuration</i> section in the <i>CPS vDRA Advanced Tuning Guide</i> .
Threads	Number of threads to set in the thread pool.
Queue Size	Size of the queue before they are rejected.
Scale By Cpu Core	Select this check box to scale the maximum number of threads by the processor cores.

Async Threading Configuration

Click **Async Threading Configuration** in the right pane to add the configuration in the system.

Use the default values for the Async Threading Plug-in. The Async configuration controls the number of asynchronous threads.



Note Currently, CPS vDRA does not have any asynchronous threads. However, you must add “Async Threading Configuration” and keep this table empty.

Figure 48: Async Threading Configuration

Async Threading Configuration

***Default Processing Threads**

***Default Action Priority**

***Default Action Threads**

***Default Action Queue Size**

Default Action Drop Oldest When Full

Action Configurations

*Action Name	*Action Priority	*Action Threads	*Action Queue Size	*Action Drop Oldest When Full

Add
Remove
↑
↓

215174

The following parameters can be configured under Async Threading Configuration.

Table 2: Async Threading Configuration

Parameter	Description
Default Processing Threads	The number of threads that are allocated to process actions based on priority.
Default Action Priority	The priority assigned to an action if it is not specified in the Action Configurations table.
Default Action Threads	The number of threads assigned to process the action if it is not specified in the Action Configurations table.
Default Action Queue Size	The number of actions that can be queued up for an action if it is not specified in the Action Configurations table.
Default Action Drop Oldest When Full	When checked, the oldest queued action is dropped from the queue when a new action is added to a full queue. Otherwise, the new action to add is ignored. This check box applies to all the threads specified. To drop a specific thread, leave this unchecked and use the Action Configurations table.
Action Configurations Table	
Action Name	The name of the action. This must match the implementation class name.
Action Priority	The priority of the action. Used by the default processing threads to determine which action to execute first.
Action Threads	The number of threads dedicated to processing this specific action.
Action Queue Size	The number of actions that can be queued up.
Action Drop Oldest When Full	For the specified action only: When checked, the oldest queued action is dropped from the queue when a new action is added to a full queue. Otherwise, the new action to add is ignored.

Custom Reference Data Configuration

Configure your system, cluster, and instance for the first time to use Custom Reference Data Table plug-in. Then you can create as many tables as needed.

Click **Custom Reference Data Configuration** from right pane to add the configuration in the system.

- HA example:
 - Primary Database Host/IP Address: sessionmgr01
 - Secondary Database Host/IP Address: sessionmgr02
 - Database Port: 27717
- AIO example:

- Primary Database Host/IP Address: localhost or 127.0.0.1
- Secondary Database Host/IP Address: NA (leave blank)
- Database Port: 27017

The following parameters can be configured under Custom Reference Data Configuration.

Table 3: Custom Reference Data Configuration Parameters

Parameter	Description
Primary Database Host/IP Address	IP address or a host name of the sessionmgr database. For example, sessionmgr01.
Secondary Database Host/IP Address	(Optional) This field is the IP address or a host name of a secondary, backup, or failover sessionmgr database. For example, sessionmgr02.
Database Port	Port number of the sessionmgr. Note Make sure that the value for this field is same as filled in for both the Primary Database Host/IP Address and Secondary Database Host/IP Address fields. Default value is 27717.
Db Read Preference	Describes how sessionmgr clients route read operations to members of a replica set. Select one of the following options from drop-down list: <ul style="list-style-type: none"> • Primary: All operations read from the current replica set primary member. • PrimaryPreferred: In most situations, operations read from the primary database host. However, if this host is unavailable, operations read from the secondary database host. • Secondary: All operations read from the secondary members of the replica set. • SecondaryPreferred: In most situations, operations read from secondary members. However, if a secondary database host is unavailable, operations read from the primary database host. Default value is Primary. For more information, see http://docs.mongodb.org/manual/core/read-preference/ .
Connection Per Host	Number of connections that are allowed for each database host. Default value is 100. Connection Per Host is a performance tuning parameter and can be changed in case of a performance issue according to the call model and hardware.

Parameter	Description
Avp Persists	<p>Use this table to configure certain AVPs that you want to store in the session database. AVPs that are not configured as part of this table, are not persisted.</p> <ul style="list-style-type: none"> • Name: Enter the name for the AVP value. • Avp Name: The name of the CRD/policy derived AVP. <p>To retrieve the stored AVPs from the session, use the Customer Reference Data Debug AVPs. This retriever is used to send the stored AVPs in any diameter message, and available in the PolicyState/Session data to Custom AVP Mapping under Custom AVP Profiles.</p> <p>Restriction When you configure the AVP Persists table in the Policy Builder, for each AVP, configure both the AVP name and name. If no values are added for these fields, then the particular AVP is not added to the Gx session. This scenario leads to unavailability of the specific AVP and hence, no custom AVP are sent.</p>

For more information on Custom Reference Data API Usage, see the *CPS Operations Guide* for this release.

DRA Configuration

Click **DRA Configuration** from the right pane in Policy Builder to add the configuration in the system.

Figure 49: DRA Configuration

D R A Configuration

*Stale Session Timer Minutes	Rate Limiter
<input type="text" value="1"/>	<input type="text" value="10"/>
Stale Session Expiry Count	*Binding DB Read Preference
<input type="text" value="6"/>	<input type="text" value="Nearest"/>
Stale Binding Expiry Minutes	Stale Binding Refresh Minutes
<input type="text" value="10080"/>	<input type="text" value="2880"/>

Binding DB Retries

Binding Creation, Primary Alternate System

Binding Creation, Secondary Alternate System

Binding Routing, Primary Alternate System

Binding Routing, Secondary Alternate System

The following parameters can be configured under DRA Configuration:

Table 4: DRA Configuration Parameters

Parameter	Description
Stale Session Timer Minutes	<p>Indicates the time after which the audit RAR should be generated (in the subsequent audit RAR process cycle that runs every minute in CPS vDRA) for sessions that are stale.</p> <p>Default: 180 minutes (recommended value)</p> <p>Minimum: 10 minutes</p> <p>Maximum: 10080 minutes</p>
Rate Limiter	<p>Indicates the number of audit RARs per second that should be sent out by CPS vDRA.</p> <p>Rate Limiter value is per worker value. Total number of audit RAR processed is calculated as Rate Limiter value * number of workers.</p> <p>Note</p> <ul style="list-style-type: none"> If primary database is Mongo Shard DB, then rate limiter value should be set as follows: The value to be set in the Rate Limit would be = 1000 If primary database is Application Shard DB, then rate limiter value should be set as follows: The value to be set in the Rate Limit would be = 1000/No. of workers <p>Minimum: 1</p> <p>Maximum: 1000 (maximum number of RAR messages per second from vDRA to PCEF)</p> <p>For information on recommended value, refer to <i>Audit Rate Limiter</i> section in the <i>CPS vDRA Advanced Tuning Guide</i>.</p>
Stale Session Expiry Count	<p>Specifies the number of retries vDRA should do for a stale session if there is no response of audit RAR or if there is Result-Code in RAA (for audit RAR) other than 5002 or 2001.</p> <p>Default: 6</p> <p>Minimum: 0 (Session deleted without sending RAR)</p> <p>Maximum: 10</p> <p>For information on recommended value, refer to <i>Audit Rate Limiter</i> section in the <i>CPS vDRA Advanced Tuning Guide</i>.</p>
Binding DB Read Preference	<p>Used to select the mode when reading from Binding DB. Use "nearest" mode for better performance of traffic that needs only read operation on Binding DB.</p> <p>Default: Nearest</p> <p>For information on recommended value, refer to <i>Audit Rate Limiter</i> section in the <i>CPS vDRA Advanced Tuning Guide</i>.</p>

Parameter	Description
Stale Binding Expiry Minutes	<p>Duration after which a binding record is validated against a session record to see if the binding should be deleted because it is stale</p> <p>The timer is initialized when the session is created.</p> <p>The records are deleted when binding expiry time is reached and no active session is found. Otherwise, the timer is updated so the binding record can be audited after another Stale Binding Expiry Minutes.</p> <p>Default: 10080 minutes (168 hours or one week) (recommended value)</p> <p>Minimum: 10 minutes</p> <p>Maximum: 43200 minutes (28 days)</p> <p>For more information about binding DB audits and stale records, see Binding DB Audit, on page 56.</p>
Stale Binding Refresh Minutes	<p>Duration for which the expiry time of the binding database records is refreshed.</p> <p>Default: 2880 minutes (48 hours or 2 days - recommended value).</p> <p>Minimum: 10 minutes</p> <p>Maximum: 10080 minutes (one week)</p> <p>Note Stale Binding Refresh Minutes should be greater than Stale Session Timer Minutes.</p> <p>Important Stale Binding Refresh Minutes parameter has been deprecated from CPS 19.5.0 and later releases. It is recommended to not set this value as zero.</p>
Binding Creation, Primary Alternative System	<p>Name of vDRA system to retry Gx CCR-i</p> <p>When vDRA tries to route a Gx CCR-i request, but is unable to reach the database, the configured values of first the primary, then the secondary systems are used to route the Gx CCR-i to a different vDRA to try the database.</p> <p>The retry is stopped if that vDRA also cannot reach the database.</p> <p>Note The primary system and the current vDRA system must share a common session database.</p>
Binding Creation, Secondary Alternative System	<p>Name of secondary vDRA system to retry Gx CCR-i</p> <p>Note The secondary system and the current vDRA must share a common session database.</p>

Parameter	Description
Binding Routing, Primary Alternative System	Name of vDRA system to retry Rx AAR When vDRA tries to route a Rx AAR request, but is unable to reach the database, the configured values of first the primary, then the secondary systems are used to route the Rx AAR to a different vDRA to try the database. The retry is stopped if that vDRA also cannot reach the database.
Binding Routing, Secondary Alternative System	Name of secondary vDRA system to retry Rx AAR
Settings	Refer to Settings.
Rate Limits	Refer to Rate Limits.
DRA Feature	Refer to DRA Feature.
DRA Inbound Endpoints	Refer to DRA Inbound Endpoints, on page 63 .
DRA Outbound Endpoints	Refer to DRA Outbound Endpoints, on page 65 .
Relay Endpoints	Refer to Relay Endpoints, on page 67 .

Settings

Click **Settings** check box to open the configuration pane.

The following parameters can be configured under **Settings**:

Table 5: DRA Configuration - Settings Parameters


Parameter	Description
Stop Timeout Ms	Determines how long the stack waits for all resources to stop. The delay is in milliseconds. Default: 10000 ms (recommended value) Minimum: 1000 ms Maximum: 60000 ms (one minute)
Cea Timeout Ms	Determines how long it takes for CER/CEA exchanges to timeout if there is no response. The delay is in milliseconds. Default: 10000 ms (recommended value) Minimum: 1000 ms Maximum: 60000 ms (one minute)

Parameter	Description
Iac Timeout Ms	<p>Determines how long the stack waits before initiating a DWR message exchange on a peer connection from which no Diameter messages have been received. The timeout value is in milliseconds.</p> <p>Default: 5000 ms (recommended value)</p> <p>Minimum: 1000 ms</p> <p>Maximum: 30000 ms (30 seconds)</p>
Dwa Timeout Ms	<p>Determines how long the stack waits for a DWA message in response to a DWR message. If no Diameter message (DWA or other message) is received on the peer connection during the first timeout period, the stack counts a failure, sends another DWR message, and restarts the Dwa timer. If no Diameter messages are received during the second timeout period, the stack counts a second failure. After two consecutive failures, the stack considers the peer connection as failed, and closes the connection.</p> <p>The delay is in milliseconds.</p> <p>Default: 10000 ms (recommended value)</p> <p>Minimum: 1000 ms</p> <p>Maximum: 60000 ms (one minute)</p>
Dpa Timeout Ms	<p>Determines how long it takes for a DPR/DPA exchange to timeout if there is no response. The delay is in milliseconds.</p> <p>Default: 5000 ms (recommended value)</p> <p>Minimum: 1000 ms</p> <p>Maximum: 30000 ms (30 seconds)</p>
Rec Timeout Ms	<p>Determines how long it takes for the reconnection procedure to timeout. The delay is in milliseconds.</p> <p>Default: 10000 ms (recommended value)</p> <p>Minimum: 1000 ms</p> <p>Maximum: 60000 ms (one minute)</p>

Parameter	Description
Drain Timeout Ms	<p>Indicates the time that a peer connection remains open for responses to be sent to peers even if DPR is sent or received by vDRA.</p> <p>If a DPR is sent or received by vDRA, vDRA does not route requests to the disconnecting peer connection via any routing (Dest-Host, SRK, Binding, Table-Driven). However, responses and in-flight requests sent to the corresponding peers till the duration of Drain Timeout. This allows vDRA to gracefully shut down when any remote peer sends a DPR so as to minimize the diameter message loss.</p> <p>Default: 2000 ms</p> <p>Maximum: Must be less than Dpa timeout Ms</p> <p>Note When vDRA initiates DPR and the remote end PCRF/PGW disconnects TCP connection immediately after sending DPA, response for the in-flight requests are dropped before reaching the configured drain timeout value.</p>
Response Timeout Ms	<p>Response timeout in milliseconds.</p> <p>Default: 1700 ms</p>

The following figure illustrates the timers in peer detection:

Figure 50: vDRA Peer Detection Failure




Binding DB Audit

The Binding DB Audit automatically deletes stale records from the binding DBs. When a Gx session record is created, binding records for the session binding keys are also created. When each binding record is created, the binding record expiry time is initialized to the sum of the session creation time and the Stale Binding Expiry Minutes (that you can configure in Policy Builder).

A binding record is deleted when the corresponding session record is deleted. A binding may become stale if it cannot be deleted when its associated session record is deleted (this occurs typically due to database communication failures). The binding records are audited using a binding audit background process. If the audit process finds a binding record with an expiry time in the past, the binding record is checked for staleness by checking the session database for the corresponding session record. If an active session record is found, the binding record expiry time is updated with sum of current time and the Stale Binding Expiry Minutes. If an active session is not found, the binding is considered stale and is deleted. Note that the binding audit process does not perform any Diameter signaling with the GW before deletion.

The following figures illustrate the working of binding DB:

Figure 51: DRA Binding Audit, Stale Binding Cleanup





Note There is a housekeeping thread to process stale sessions/bindings which does the following tasks in sequential order:

1. Process Stale Session Expiration: Generate Audit RAR OR delete the session if stale session expiry count has reached 0.
2. Process expiration of binding: Remove the bindings for which there is no corresponding session.

The stale session expiry task is scheduled to run every minute. This means that the stale session expiry processing is not guaranteed to happen exactly at the configured stale session expiry minutes interval. The stale session expiry processing can happen at any time within the configured stale session expiry minutes to configured stale session expiry minutes + 1 min interval.

However, if the previous task execution of the above mentioned three points takes longer time to complete due to large number of stale sessions/stale bindings, the stale session expiry would run post the previous task completion which can lead to a longer delay than expected 1 minute.

Rate Limits

Rate limit per process instance on Policy Director (lb) VM can be managed using this configuration.

Default is unchecked, that is, no rate limits for Diameter traffic (recommended setting).

If enabled, the following parameters can be configured under **Rate Limits**:

Table 6: DRA Configuration - Rate Limits

Parameter	Description
Rate Limit per Instance on Policy Director	Allowable TPS on a single instance of policy server (QNS) process running on the Policy Director. Minimum: 1 Maximum: 5000 Note Contact your Cisco representative for usecase-specific recommended values.
Result-Code in Response	Indicates the error code that must be used while rejecting requests, due to rate limits being reached. Default: 3004
Error Message in Response	Select the check box to drop the rate-limited messages without sending error response. If the check box is not selected, then the rate limited message are dropped with error response as configured.

Parameter	Description
Drop Requests Without Error Response	<p>Select the check box to drop rate limited messages without sending error response.</p> <p>If the check box is unchecked, then the rate limited messages are dropped with error response as configured.</p> <p>To accommodate configuration to either drop the request or send an error response, a column <i>Discard Behavior</i> can be added under Peer Rate Limit Profile. The column may have one of the two possible values:</p> <ul style="list-style-type: none"> • Send Error Response • Drop Message <p>Default: Unchecked (recommended setting)</p> <p>For more information, refer to Peer Rate Limit.</p> <p>Important If both Rate Limit Error Code and Rate Limit Error String are provided along with Rate Limit Action as "Drop Message", the Rate Limit Action will take precedence and the other two fields will be ignored.</p>

Here is the list of the available combinations for rate limiting:

Table 7: Rate Limiting Combinations

Rate Limiting Type	With Error Code	With Error Code and Error Message	Without Error Code (Drop)
Instance Level	Yes	Yes	Yes
Peer Level Egress	Yes	Yes	Yes
Peer Level Egress with Message Level	Yes	Yes	Yes
Egress Message Level (No Peer Level RL)	Yes	Yes	Yes
Peer Level Ingress	Yes	Yes	Yes
Peer Level Ingress with Message Level	Yes	Yes	Yes
Ingress Message Level (No Peer Level RL)	Yes	Yes	Yes

DRA Feature

Click **DRA Feature** check box to open the configuration pane.

The following parameters can be configured under **DRA Feature**:

Table 8: DRA Features

Parameter	Description
Gx Session Tear Down On5065	<p>By default, Gx Session Tear Down On5065 flag is enabled (recommended setting).</p> <p>When the PCRF responds with a Experimental Result Code of 5065 in AAAnswer on Rx Interface, DRA deletes its internal binding and session created for the transaction. A RAR with appropriate Session-Release-Cause AVP will also be sent to the PCEF.</p> <p>Important When using this flag, there will always be a database query to fetch Gx session id. So this means that the database transactions will linearly increase with AAR traffic on Rx Interface.</p>
Update Time Stamp On Success R A A	<p>When this check box is selected, session timestamp will be updated on receipt of success RAA (Result-Code: 2001) from PCEF. ¹</p> <p>Default is checked (recommended setting).</p> <p>Important When using this flag, there will always be a database query to fetch Gx session id. So this means that the database transactions will linearly increase with AAR traffic on Rx Interface.</p>
Update Time Stamp On Success C C R U	<p>When this check box is selected, session timestamp will be updated on receipt of success CCR-U (Result-Code: 2001) from PCEF. ²</p> <p>Default is unchecked (recommended setting).</p> <p>Important When using this flag, there will always be a database query to fetch Gx session id. So this means that the database transactions will linearly increase with AAR traffic on Rx Interface.</p>
Enable Proxy Bit Validation	<p>Enables P bit validation.</p> <p>vDRA validates the P bit in the Diameter request and, if set, the message maybe proxied, relayed, or redirected.</p> <p>If this option is disabled, the P bit in the request is not checked and the request is not considered proxiable.</p> <p>Default: Enabled.</p>

Parameter	Description
Enable Mediation	<p>Enable advanced mediation capabilities in both egress and ingress direction.</p> <p>This feature allows you to configure vDRA to change the value of the Result-Code in Diameter Answer, use mediation to hide topology, prepend label to Destination Host AVP, etc.</p>
Enable Doic	<p>Enable or disable abatement action for Diameter requests towards PCRF, HSS, AAA, and OCS servers based on reporting of overloaded conditions using the architecture described in RFC 7683 Diameter Overload Indication Conveyance (DOIC).</p> <p>DOIC can be enabled/disabled at peer group level in Peer Group SRK Mapping table. If the destination peer is congested or overloaded, you can choose to either forward, divert, or drop messages.</p>
Enable PCRF Session Query	<p>Enables or disables the PCRF session query. If you enable this, Policy DRA then supports a fallback routing for Rx AARs for VoLTE using the PCRF session query. This ensures that VoLTE calls can complete in the event that IPv6 binding is not found in the binding database.</p> <p>For an Rx AAR with an IPv6 binding query, vDRA provides the ability to route the Rx AAR based on an API query to the PCRF to determine if it has a session for the IPv6. The queries can be made in parallel to a configured set of query points on PCRFs.</p> <p>The Framed-IPv6 AVP from the Rx must be provided in the request to the PCRF. PCRF returns an SRK to be used for routing, similar to existing binding lookups.</p>
Create IPv6 Bindings based on PCRF Session Query	<p>Enables creation of IPv6 binding record in the database based on PCRF session query.</p> <p>When PCRF session query result (success) is received and if IPv6 record is not present in the database, vDRA creates an IPv6 binding record based on the response from the PCRF.</p> <p>If any CCR-I is received for the same IPv6 record, then it overwrites the IPv6 binding record. For any CCR-T, vDRA deletes the IPv6 binding record from database.</p> <p>Note Ensure you also enable PCRF Session Query for this feature to work.</p> <p>The Stale Binding Expiry and Refresh Minutes are used to clear these binding records from the database. For more information, see Binding DB Audit, on page 56.</p>

Parameter	Description
Enable Best Effort Binding	<p>When selected allows the operator to enable the best effort binding creation configuration on a per APN basis. The configuration is enabled on a per APN basis and controls any or all of the following bindings (for best effort):</p> <ul style="list-style-type: none"> • IPv6 • IPv4 • MSISDN/APN • IMSI/APN • Session <p>Default is unchecked.</p> <p>Best effort bindings are those bindings for which DRA does not wait for DB write operations to be completed. DRA forwards the CCR without waiting for DB write and there is an asynchronous write call for best effort bindings.</p> <p>If there is no matching APN found in the best effort binding table from CCR-I, DRA takes the legacy behavior and treats all bindings as mandatory. The bindings to be created is primarily decided by binding creation profile and then DRA examines the best effort table to find the best effort and mandatory bindings. The session can be marked as best effort and in such cases session is not created if session Db is down but the CCR is forwarded.</p>
Slf Max Bulk Provisioning TPS	<p>Rate at which subscribers are provisioned in the SLF database.</p> <p>SLF bulk provisioning generates high number of database write operations in a short duration of time. To spread out the operations over a period of time and mitigate the performance issue, configure the TPS. The rate limit adds delay between transactions and thereby limits the number of transactions executed per second.</p> <p>For more information about SLF bulk provisioning, see the <i>CPS vDRA Operations Guide</i>.</p>
A A R Priority Processing	<p>In vDRA 19.4.0 and later release, this parameter has been deprecated and no longer supported.</p> <p>By default, when application-based client sharding is used, AAR processing is prioritized on workers.</p>

¹ The time stamp is updated on generation of Stale RAR. Also, if a success RAR/RAA(2001) comes after generation of Stale RAR, then the Stale RAR counter is reset.

² The time stamp is updated on generation of Stale RAR. Also, if a success CCR(U)/CAA(2001) comes after generation of Stale RAR, then the Stale RAR counter is reset.

DRA Inbound Endpoints

The following parameters can be configured under **DRA Inbound Endpoints**:



Note To handle loads of 15 K TPS or more, create multiple TCP connections with PCRF and apply the same configuration to all DRA Directors.

Table 9: DRA Configuration - DRA Inbound Endpoints Parameters

Parameter	Description
Vm Host Name	Host Name of the VM that hosts this CPS vDRA endpoint.
Ip Address	Address on which this CPS vDRA endpoint should bind to.
Realm	Realm of the CPS vDRA endpoint.
Fqdn	Fully Qualified Domain Name of the CPS vDRA endpoint.
Transport Protocol	Allows you to select either 'TCP' or 'SCTP' for the selected DRA endpoint. Default value is TCP. If the DRA/relay endpoint is to be configured for SCTP, the Transport Protocol should be selected as SCTP for those endpoints.

Parameter	Description
Multi-Homed IPs	<p>This is a comma separated list of IP addresses that CPS vDRA will use to start the diameter stack with multi-homing enabled for SCTP transport. Diameter stack with TCP transport will still use the existing 'Local Bind Ip' field to specify any specific IP address for TCP stack.</p> <p>CPS vDRA will use the 'Local Bind Ip' to bring up SCTP stack and use it along with the 'Multi Homing Hosts' to start the SCTP transport with multi-homing support.</p> <p>Note While using SCTP multi-homing functionality review the Linux network and gateway configurations for supporting multiple networks on different subnets. CPS supports Centos 6 release and reverse path filtering kernel parameter (<code>rp_filter</code>) values can be set for allowing packets from different subnets on Policy Director VMs. The default behavior in Centos 6 is to discard the packets in such scenarios.</p> <p>Note Both IPv4 and IPv6 are supported in vDRA endpoint configuration. For IPv6, you can enter either short or long format.</p> <p>The configuration for multi-homing is validated by netstat command on lb01:</p> <pre>netstat -apn grep 3898</pre>
Application	<p>Refers to 3GPP Application ID of the interface.</p> <p>You can select multiple applications on a peer connection.</p> <p>For example, S6a and SLg on a single IPv4/SCTP Multi-homed peer connection.</p>
Enabled	Check to enable the endpoint.
Base Port	Refers to the port on which the CPS vDRA listens for incoming connections.

An example configuration is shown below:

Figure 52: DRA Inbound Endpoints - Example Configuration

DRA Inbound Endpoints								
*Vm Host Name	*Ip Address	*Realm	*Fqdn	Transport Protocol	Multi-Homed IP's	*Application	*Enabled	*Base Port
lab	10.1.1.1	gx-dra1.cisco.com	gx-dra1	TCP		Gx Application	<input type="checkbox"/>	3868
lab	10.1.1.1	gx-dra2.cisco.com	gx-dra2	TCP		Gx Application	<input type="checkbox"/>	3869
lab	10.1.1.1	gx-dra3.cisco.com	gx-dra3	TCP		Gx Application	<input checked="" type="checkbox"/>	3870
lab	10.1.1.1	rx-dra1.cisco.com	rx-dra1	TCP		Rx Application	<input type="checkbox"/>	4868
lab	10.1.1.1	rx-dra2.cisco.com	rx-dra2	TCP		Rx Application	<input checked="" type="checkbox"/>	4869
lab	10.1.1.1	sd-dra1.cisco.com	sd-dra1	TCP		Sd Application	<input checked="" type="checkbox"/>	6868

Add Remove ↑ ↓

DRA Outbound Endpoints

The following parameters can be configured under **DRA Outbound Endpoints**:

Table 10: DRA Configuration - DRA Outbound Endpoints Parameters

Parameter	Description
Vm Host Name	Host Name of the VM that hosts this CPS vDRA endpoint.
Ip Address	Address on which this CPS vDRA endpoint should bind to.
Realm	Realm of the CPS vDRA endpoint.
Fqdn	Fully Qualified Domain Name of the CPS vDRA endpoint.
Transport Protocol	Allows you to select either 'TCP' or 'SCTP' for the selected CPS vDRA endpoint. Default value is TCP. If the DRA/relay endpoint is to be configured for SCTP, the Transport Protocol should be selected as SCTP for those endpoints.

Parameter	Description
Multi-Homed IPs	<p>This is a comma separated list of IP addresses that CPS vDRA will use to start the diameter stack with multi-homing enabled for SCTP transport. Diameter stack with TCP transport will still use the existing 'Local Bind Ip' field to specify any specific IP address for TCP stack.</p> <p>CPS vDRA will use the 'Local Bind Ip' to bring up SCTP stack and use it along with the 'Multi Homing Hosts' to start the SCTP transport with multi-homing support.</p> <p>Note While using SCTP multi-homing functionality review the Linux network and gateway configurations for supporting multiple networks on different subnets. CPS supports Centos 6 release and reverse path filtering kernel parameter (<code>rp_filter</code>) values can be set for allowing packets from different subnets on Policy Director VMs. The default behavior in Centos 6 is to discard the packets in such scenarios.</p> <p>Note Both IPv4 and IPv6 are supported in vDRA endpoint configuration. For IPv6, you can enter either short or long format.</p> <p>The configuration for multi-homing is validated by netstat command on lb01:</p> <pre>netstat -apn grep 3898</pre>
Application	Refers to 3GPP Application ID of the interface.
Enabled	Check to enable the endpoint.
Peer Realm	Diameter server realm.
Peer Host	<p>Diameter server host.</p> <p>By default, the connection is initiated on the standard diameter port (3868). If a different port needs to be used than the peer name must be defined using the host:port format.</p>

An example configuration is shown below:

Figure 53: DRA Outbound Endpoints - Example Configuration

*Vm Host Name	*Ip Address	*Realm	*Fqdn	Transport Protocol	Multi-Homed IP's	*Application	*Enabled	*Peer Realm	*Peer Host
lab	10.1.1.1	gx-dra1.cisco.com	gx-dra9	TCP		Gx Application	<input checked="" type="checkbox"/>	pcrf2-gx2.cisco.com	gx-pcrf
lab	10.1.1.1	rx-dra1.cisco.com	rx-dra9	TCP		Rx Application	<input checked="" type="checkbox"/>	rx-pcrf.cisco.com	rx-pcrf:4868

Add Remove ↑ ↓

Relay Endpoints

The following parameters can be configured under **Relay Endpoints**:

Table 11: DRA Configuration - Relay Endpoints Parameters

Parameter	Description
Vm Host Name	Host Name of the VM that hosts this Relay endpoint.
Instance Id	Instance Identifier is the ID of the current Instance.
Ip Address	Address on which this DRA endpoint should bind to. Note The relay endpoints must be configured on physical IPs and not on virtual IPs.
Port	Port is the listening port for this instance.
Fqdn	Fully Qualified Domain Name of the DRA end point.
Enabled	Check to enable endpoint.

An example configuration is shown below:

Figure 54: Relay Endpoints - Example Configuration

*Vm Host Name	*Instance Id	*Ip Address	*Port	*Fqdn	*Enabled
lab	3	10.10.1.1	4868	dra3.rx	<input checked="" type="checkbox"/>

Add Remove ↑ ↓

Policy Routing for Real IPs with Relay Endpoints

vDRA relay links consist of a control plane and a data plane.

The control plane uses virtual IPs and the data plane uses real IPs.


If the control and data plane use the same links, and those links are configured with VIPs, by default, the data plane uses the VIP as its source address for outgoing connections. The data plane uses the VIP as the source address only if the VIP is active on the data plane's outgoing interface.

To avoid this situation, policy routing is used to force the data plane to use the real IP address of the outgoing interface instead of the VIP.

Example of a vDRA Relay Endpoints

In the following example network, only the DRA director VMs and their relay links are displayed. In a real scenario, many more links may exist on the DRA director VMs.

Figure 55: Example of Relay Endpoints



Policy Routing

Linux policy routing includes rules and routing tables. The rules identify traffic and point to a user-defined routing table. The routing table contains customized routes.

To prevent the Relay Link's data plane from using the VIP as a source address, a rule is created to identify the real IP in the destination address and identify the desired routing table.

Configure Policy Routing

The following configuration procedure is performed on Site 1 dra1-director-1. Repeat the procedure for all other dra-directors and modify the IP addresses accordingly.

Perform the following steps on each dra-director VM to configure policy routing:

1. Create a custom routing table
2. Create an IP rule for each remote relay endpoint's real IP address
3. Add a route to the custom routing table that specifies the real IP source address

Set up Custom Routing Table

Set up the custom routing table as shown in the following example:

```
echo "200 dra.relay" | sudo tee --append /etc/iproute2/rt_tables
```

Define IP Rules

The following rules match the packets destined to the real IPs of interface ens224 on dra2-director1 and dra2-director2:

```
ip -6 rule add to 2006:db8:2001:2425::13 table dra.relay
ip -6 rule add to 2006:db8:2001:2425::14 table dra.relay
```

Define the Route

The following example of the route uses the router's interface as the next hop and specifies ens224's real IP address as the source address for outgoing packets.

```
ip route add 2006:db8:2001:2425::/112 via
2001:db8:2040:202::1 src 2001:db8:2040:202::13 table dra.relay
```

Validate the Routing

Use the following example commands to validate the route selection for remote relay real IP and VIP addresses.

```
ip -6 route show table dra.relay
ip -6 route get 2006:db8:2001:2425::13
ip -6 route get 2006:db8:2001:2425::14
ip -6 route get 2006:db8:2001:2425::50
```

Persistent Configuration

In order for the Policy Routing configuration to survive a reboot, add the configuration commands to `/etc/network/interfaces` under interface ens224 as shown below:

```
auto ens224
iface ens224 inet static
address 192.169.22.13
netmask 255.255.255.0
iface ens224 inet6 static
address 2001:db8:2040:202::13
netmask 112
up ip route add 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1
up ip -6 rule add to 2006:db8:2001:2425::13 table dra.relay
up ip -6 rule add to 2006:db8:2001:2425::14 table dra.relay
up ip route add 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1 src 2001:
db8:2040:202::13 table dra.relay
down ip route del 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1
down ip -6 rule del to 2006:db8:2001:2425::13 table dra.relay
down ip -6 rule del to 2006:db8:2001:2425::14 table dra.relay
down ip route del 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1 src
2001:db8:2040:202::13 table dra.relay
```

Configure Policy Routing with Deployer/Installer

Configure the VM artifacts and the cloud config to set up policy routing using the deployer.

VM Artifacts

Add Policy Route configuration to the DRA director VM's `interfaces.esxi` file as shown in the following example:

```
cps@installer:/data/deployer/envs/dra-vnf/vms/dra-director
/dra-director-1$ cat interfaces.esxi
auto lo
iface lo inet loopback

auto ens160
```

```

iface ens160 inet static
address 10.81.70.191
netmask 255.255.255.0
gateway 10.81.70.1

auto ens192
iface ens192 inet static
address 192.169.21.13
netmask 255.255.255.0

auto ens224
iface ens224 inet static
address 192.169.22.13
netmask 255.255.255.0
iface ens224 inet6 static
address 2001:db8:2040:202::13
netmask 112
up ip route add 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1
up ip -6 rule add to 2006:db8:2001:2425::13 table dra.relay
up ip -6 rule add to 2006:db8:2001:2425::14 table dra.relay
up ip route add 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1 src
2001:db8:2040:202::13 table dra.relay
down ip route del 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1
down ip -6 rule del to 2006:db8:2001:2425::13 table dra.relay
down ip -6 rule del to 2006:db8:2001:2425::14 table dra.relay
down ip route del 2006:db8:2001:2425::/112 via 2001:db8:2040:202::1 src
2001:db8:2040:202::13 table dra.relay

auto ens256
iface ens256 inet static
address 192.169.23.13
netmask 255.255.255.0
cps@installer:/data/deployer/envs/dra-vnf/vms/dra-director/dra-director-1$

```

Cloud Config

Create the dra.relay routing table on the dra-directors by adding the following bootcmd: to user_data.yml and storing the file at /data/deployer/envs/dra-vnf/vms/dra-director/user_data.yml. The sed command prevents adding a routing table every time the VM boots.

```

bootcmd:
- "sed -i -e '/^200 *dra.relay/d' /etc/iproute2/rt_tables"
- "sh -c \"echo '200      dra.relay' >> /etc/iproute2/rt_tables\""

```

Example of user_data.yml:

```

#cloud-config
debug: True
output: {all: '| tee -a /var/log/cloud-init-output.log'}

users:
- name: cps
  sudo: ['ALL=(ALL) NOPASSWD:ALL']
  groups: docker
  ssh-authorized-keys:
    - ssh-rsa AAAAB3NzaC1yc2EAAAADAQABAAQDzjJjndIvUiBta4VSIbd2gJm1MWcQ8wtejgAbi
XtoFZdtMdo9G0ZDEOtXHNDPwWujMiYakZhZWX/zON9raavU8lgD9+YcRopWUtujIC71YjtoxIjWIBBbrtqt
PlUXMUXQsi9lRQbUtslENP+tSatS3awoQupyBMMSutyBady/7Wq0UTwFsnYs5Jfs8jIQuMfVQ9uJ4mNn7wJ0
N+Iaf27rE0t3oiY5DRN6j07WhauM6lCnZ1JDlZqmTnTHQkgJ3uKmQa5x73tJ1OW89Whf+R+dfslVn/yUwK/
vf4extHTn32Dtsxkjz7kQeEDgCe/y7owimaEFcCIfeWEaj/50jegN cps@root-public-key

resize_rootfs: true

write_files:

```

```

- path: /root/swarm.json
  content: |
    {
      "role": "{{ ROLE }}",
      "identifier": "{{ IDENTIFIER }}",
      "master": "{{ MASTER_IP }}",
      "network": "{{ INTERNAL_NETWORK }}",
      {% if WEAVE_PASSWORD is defined %}"weavePw": "{{ WEAVE_PASSWORD }}",
      {% endif %}
      "zing": "{{ RUN_ZING | default(1) }}",
      "cluster_id": "{{ CLUSTER_ID }}",
      "system_id": "{{ SYSTEM_ID }}"
    }
  owner: root:root
  permissions: '0644'
- path: /home/cps/.bash_aliases
  encoding: text/plain
  content: |
    # A convenient shortcut to get to the Orchestrator CLI
    alias cli="ssh -p 2024 admin@localhost"
    alias pem="wget --quiet http://171.70.34.121/microservices/latest/cps.pem ;
    chmod 400
cps.pem ; echo 'Retrieved \"cps.pem\" key file'"
  owner: cps:cps
  permissions: '0644'
- path: /etc/pam.d/common-password
  content: |
    #
    # /etc/pam.d/common-password - password-related modules common to all services
    #
    # This file is included from other service-specific PAM config files,
    # and should contain a list of modules that define the services to be
    # used to change user passwords. The default is pam_unix.

    # Explanation of pam_unix options:
    #
    # The "sha512" option enables salted SHA512 passwords. Without this option,
    # the default is Unix crypt. Prior releases used the option "md5".
    #
    # The "obscure" option replaces the old `OBSCURE_CHECKS_ENAB' option in
    # login.defs.
    #
    # See the pam_unix manpage for other options.

    # As of pam 1.0.1-6, this file is managed by pam-auth-update by default.
    # To take advantage of this, it is recommended that you configure any
    # local modules either before or after the default block, and use
    # pam-auth-update to manage selection of other modules. See
    # pam-auth-update(8) for details.

    # here are the per-package modules (the "Primary" block)
    password requisite pam_pwquality.so retry=3 minlen=8
    minclass=2
    password [success=2 default=ignore] pam_unix.so obscure use_authtok
    try_first_pass sha512 remember=5
    password sufficient pam_sss.so use_authtok
    # here's the fallback if no module succeeds
    password requisite pam_deny.so
    # prime the stack with a positive return value if there isn't one already;
    # this avoids us returning an error just because nothing sets a success code
    # since the modules above will each just jump around
    password required pam_permit.so
    # and here are more per-package modules (the "Additional" block)
    # end of pam-auth-update config

```

```

owner: root:root
permissions: '0644'
runcmd:
- [vmware-toolbox-cmd, timesync, enable ]
bootcmd:
- "sed -i -e '/^200 *dra.relay/d' /etc/iproute2/rt_tables"
- "sh -c \"echo '200      dra.relay' >> /etc/iproute2/rt_tables\""

```


SLF Configuration

You can specify whether the IMSI and MSISDN values are validated in SLF API.

By default, SLF validation is disabled.

To set up SLF validation, create SLF Configuration from the Plugin Configuration in Policy Builder.

Figure 56: SLF Configuration



The following table describes the SLF API validations that you can configure:

Table 12: SLF Configuration

Field	Description
Validate IMSI is Numeric	<p>If checked: IMSI received in the SLF API request must be numeric</p> <p>If unchecked: IMSI numeric validation is not performed on the IMSI received in the SLF API request</p>

Field	Description
Validate IMSI Length	<p>If checked: IMSI length is validated based on the specified IMSI Minimum Length (inclusive) and IMSI Maximum Length (inclusive)</p> <p>If unchecked: IMSI length validation is not performed on the IMSI received in the SLF API request</p>
Validate MSISDN is Numeric	<p>If checked: MSISDN received in the SLF API request must be numeric</p> <p>If unchecked: MSISDN numeric validation is not performed on the MSISDN received in the SLF API request</p>
Validate MSISDN Length	<p>If checked: MSISDN length is validated based on the specified MSISDN Minimum Length (inclusive) and MSISDN Maximum Length (inclusive)</p> <p>If unchecked: MSISDN length validation is not performed on the MSISDN received in the SLF API request</p>

Diameter Application

Sd Application

For Sd, an Application Routing table is used to map specific diameter command codes and CC-Request-Types to a table, typically, an Sd New Session table for routing Sd TSRs to a peer route. The Sd New Session CD table will choose a peer route based on the Destination-Realm. The peer route will then point to a Peer-Group which contains multiple peer connections to a TDF and the DRA will load balance among the TDF peer connections in the Peer Group.

An example configuration is shown below:

Figure 57: Diameter Application - Sd Application Example

Name	*Priority	*Command Code	Cc Request Type	*Destination Host	Action Tables
Sd-TSR	0	8388637	0	<input checked="" type="checkbox"/>	New Sd Session
Sd-CCR-I	0	272	1	<input checked="" type="checkbox"/>	New Sd Session
Sd-CCR-U	0	272	2	<input checked="" type="checkbox"/>	New Sd Session
Sd-CCR-T	0	272	3	<input checked="" type="checkbox"/>	New Sd Session
RAR	0	258	0	<input checked="" type="checkbox"/>	New Sd Session

The following parameters are configured under Sd Application:

Table 13: Sd Application Parameters

Parameter	Description
Name	Name of the Sd application.
Application Id	16777303, 3GPP specified Application Identifier for Sd interface.
Vendor Ids	Vendor Identifiers that are required to be supported on Sd interface.
Tgpp Application check box	If this check box is selected, indicates this is a 3GPP defined application interface.
Application Route table	
Name	Identifier of the route.
Priority	Indicates the priority of the route.
Command Code	Indicates value of command code AVP within the message.
Cc Request Type	Indicates if the Credit Control Request type is Initial(1)/Update(2) or Terminate(3).
Destination Host Null	If this check box is selected, indicates if Destination Host will be null in messages received for this application.
Action Tables	Identifies the request routing table for this interface and message.

Gx Application

For Gx, an Application Routing table is used to map specific diameter command codes and CC-Request-Types to a table. When “Destination Host Null” is checked, it means Destination-Host AVP is null. It will then check for table driven routing.

An example configuration is shown below:

Figure 58: Diameter Application - Gx Application Example

Diameter Application

Name: Gx Application *Application Id: 16777238

Vendor Ids: 8164, 9, 10415 Add Remove Tgpp Application

Name	*Priority	*Command Code	Cc Request Type	*Destination Host	Action Tables
Gx_Initial	1	272	1	<input checked="" type="checkbox"/>	New Gx Session
Gx_Terminate	1	272	3	<input checked="" type="checkbox"/>	New Gx Session
Gx_Update	1	272	2	<input checked="" type="checkbox"/>	New Gx Session

Add Remove ↑ ↓

C-DRA attempts to do Dest-Host routing before doing table driven routing. If the Dest-Host AVP is absent, empty, or equal to the CDRA FQDN, then we skip Dest-Host routing altogether and proceed to Table-Driven routing.

The following parameters are configured under Gx Application:

Table 14: Gx Application Parameters

Parameter	Description
Name	Name of the Gx application.
Application Id	16777238, 3GPP specified Application Identifier for Gx interface.
Vendor Ids	Vendor Identifiers that are required to be supported on Gx interface.
Tgpp Application check box	If this check box is selected, indicates this is a 3GPP defined application interface.
Application Route table	
Name	Identifier of the route.
Priority	Indicates the priority of the route.
Command Code	Indicates value of command code AVP within the message.

Parameter	Description
Cc Request Type	Indicates if the Credit Control Request type is Initial(1)/Update(2) or Terminate(3).
Destination Host Null	If this check box is selected, indicates the message will contain a Destination-Host.
Action Tables	Identifies the request routing table for this interface and message.

Rx Application

Identifies the request routing table for this interface and message.

Figure 59: Diameter Application - Rx Application Example

Diameter Application

Name: Rx Application *Application Id: 16777236

Vendor Ids: 13019, 8164, 9 Add, Remove Tgpp Application

Name	*Priority	*Command Code	Cc Request Type	*Destination Host	Action Tables
Rx Initial	1	265	1	<input checked="" type="checkbox"/>	New Rx Session
Rx Termination	1	275	1	<input checked="" type="checkbox"/>	New Rx Session

Add, Remove, ↑, ↓

The following parameters are configured under Rx Application:

Table 15: Rx Application Parameters

Parameter	Description
Name	Name of the Rx application.
Application Id	16777236, 3GPP specified Application Identifier for Rx interface.
Vendor Ids	Vendor Identifiers that are required to be supported on Rx interface.
Tgpp Application check box	If this check box is selected, indicates this is a 3GPP defined application interface.
Application Route table	
Name	Identifier of the route.

Parameter	Description
Priority	Indicates the priority of the route.
Command Code	Indicates value of command code AVP within the message.
Cc Request Type	Not supported for Rx interface.
Destination Host Null	If this check box is selected, indicates if Destination Host will be null in messages received for this application.
Action Tables	Identifies the request routing table for this interface and message.

Sh Application

Sh interface is used for communication between AS and HSS for Call data query/Push subscriber profile and subscriber notification procedures.



Note In certain scenarios, the customer might use the Sh interface between PCRF and HSS also.

An example configuration is shown below:

Figure 60: Diameter Application - Sh Application Example

Diameter Application

Name

***Application Id**

Vendor Ids

10415

Tgpp Application

Application Route

Name	*Priority	*Command Code	Cc Request Type	*Destination Hc	Action Tables
UDR	0	306	0	<input checked="" type="checkbox"/>	Sh_Application
PUR	0	307	0	<input checked="" type="checkbox"/>	Sh_Application
SNR	0	308	0	<input checked="" type="checkbox"/>	Sh_Application
PNR	0	309	0	<input checked="" type="checkbox"/>	Sh_Application

The following parameters are configured under Sh Application:

Table 16: Sh Application Parameters

Parameter	Description
Name	Name of the Sh application.
Application Id	16777217, 3GPP specified Application Identifier for Sh interface.
Vendor Ids	Vendor Identifiers that are required to be supported on Sh interface.
Tgpp Application check box	If this check box is selected, indicates this is a 3GPP defined application interface.
Application Route table	
Name	Identifier of the route.
Priority	Indicates the priority of the route.
Command Code	Indicates value of command code AVP within the message.
Cc Request Type	CC-Request-Type is not applicable for Sh interface.
Destination Host Null	If this check box is selected, indicates the message will contain a Destination-Host.
Action Tables	Identifies the request routing table for this interface and message.

S6a Application

DRA supports S6a interface with the implementation of Subscriber Location Function(SLF) feature. S6a is an interface which supports the mobility management and subscriber data management procedures between MME and HSS in an LTE EPC network.

An example configuration is shown below:

Figure 61: Diameter Application - S6a Application Example

Diameter Application

Name

***Application Id**

Vendor Ids

10415

Tgpp Application

Application Route

Name	*Priority	*Command Code	Request Type	*Destination Host Null	Action Tables
AIR	1	318	0	<input checked="" type="checkbox"/>	S6a_Application
ULR	1	316	0	<input checked="" type="checkbox"/>	S6a_Application

The following parameters are configured under S6a Application:

Table 17: S6a Application Parameters

Parameter	Description
Name	Name of the S6a application.
Application Id	16777251, 3GPP specified Application Identifier for S6a interface.
Vendor Ids	Vendor Identifiers that are required to be supported on S6a interface.
Tgpp Application check box	If this check box is selected, indicates this is a 3GPP defined application interface.
Application Route table	
Name	Identifier of the route.
Priority	Indicates the priority of the route.
Command Code	Indicates value of command code AVP within the message.
Cc Request Type	CC-Request-Type is not applicable for S6a interface.
Destination Host Null	If this check box is selected, indicates the message will contain a Destination-Host.
Action Tables	Identifies the request routing table for this interface and message.

Routing AVP Definition

Gx Session

An example configuration is shown below:

Figure 62: Routing AVP Definition - Gx Session

Routing Avp Definition

Name
New Gx Session

Routing Avp Lookup

*Search Table Group
apn_mapping_table
TB_GX_NEW_SESSION

Add Remove ↑ ↓

215584

Rx Session

An example configuration is shown below:

Figure 63: Routing AVP Definition - Rx Session

Routing Avp Definition

Name
New Rx Session

Routing Avp Lookup

*Search Table Group
TB_RX_NEW_SESSION
apn_mapping_table

Add Remove ↑ ↓

215583

Rx New Session Rules - CRD Table

An example configuration is shown below:

Figure 64: Rx New Session Rules - CRD Table

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name:** TB_RX_NEW_SESSION **Display Name:** Rx New Session Rules Cache Results

Activation Condition: Rx Best Match ***Evaluation Order:** 0

*Name	Display Name	*Use In Condi	*Type	Key	Required
logical_apn	Logical APN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_host	Origin Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_host	Destination Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values The values allowed in Control Center for this column

List of Valid Values

*Name	Display Name
-------	--------------

Valid values pulled from another table's column (Key)

Validation Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Retrieve Destination Host (Cisco)

Bind to a result column from another table

Bind to Diameter request AVP code

Matching Operator eq

215566

Gx New Session Rules - CRD Table

For Gx, an Application Routing table is used to map specific diameter command codes and CC-Request-Types to a table, typically, for routing Gx CCR-Is. The Gx CCR-I should be routed based on a logical APN and the Origin-Host attribute. Regular expression matching of logical APNs and Origin-Hosts can also be configured. The implementation should be flexible to allow CRDs to be configured for routing of other attributes such as Destination-Realm and Origin-Realm.

An example configuration is shown below:

Figure 65: Gx New Session Rules - CRD Table

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name:** TB_GX_NEW_SESSION **Display Name:** Gx New Session Rules Cache Results

Activation Condition: Gx Best Match ***Evaluation Order:** 1

*Name	Display Name	*Use In Condi	*Type	Key	Required
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_realm	Origin Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_realm	Destination Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_host	Origin Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
logical_apn	Logical APN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
imsi	IMSI	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values The values allowed in Control Center for this column

List of Valid Values

*Name	Display Name
-------	--------------

Valid values pulled from another table's column (Key)

Validation Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Retrieve Origin Realm (Cisco DR)

Bind to a result column from another table

Bind to Diameter request AVP code

Matching Operator eq

215566

Sd New Session Rules - CRD Table

An example configuration is shown below:

Figure 66: Sd New Session Rules - CRD Table

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name** **Display Name** Cache Results

Activation Condition Best Match ***Evaluation Order**

*Name	Display Name	*Use In Condi	*Type	Key	Required
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_realm	Origin Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_realm	Destination Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_host	Destination Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
logical_apn	Logical APN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
msisdn	MSISDN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All

List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (Key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Bind to a result column from another table

Bind to Diameter request AVP code

Matching Operator

215567

Logical APN List - CRD Table

An example configuration is shown below:

Figure 67: Logical APN List - CRD Table

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name** **Display Name** Cache Results

Activation Condition

*Name	Display Name	*Use In Condi	*Type	Key	Required
logical_apn	Logical APN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All

List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (Key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Bind to a result column from another table

Bind to Diameter request AVP code

Matching Operator

215568

Dynamic AVP Retriever for Routing

DRA supports routing messages based on the following AVPs from request message:

- Destination-Host
- Destination-Realm
- Origin-Host
- Origin-Realm
- APN (from Called-Station-ID)

- IMSI (from Subscription-ID)
- MSISDN (from Subscription-ID)

Regular-expression matching and combinations of AVPs is supported. This requirement is not applicable across all messages on different interfaces. The following table shows applicability of the AVP's at a message and interface level.

Table 18: Regular-expression Matching and Combinations of AVPs

Interface	Message	Origin Host	Origin Realm	Destination Host	Destination Realm	APN (Called-Station-ID)	IMSI	MSISDN
Gx	CCR-I	Yes	Yes	Yes	Yes	Yes	Yes	Yes
	CCR-U	No	No	No	No	No	No	No
	RAR	No	No	Yes	No	No	No	No
Sd	TSR	Yes	Yes	Yes	Yes	No	No	No
	CCR-I	Yes	Yes	Yes	Yes	No	No	No
	CCR-U/T	No	No	Yes	No	No	No	No
	RAR	No	No	Yes	No	No	No	No
Rx	RAR	No	No	Yes	No	No	No	No

Dynamic AVP Retrievers are used mostly used in Custom Reference Data where data has to be fetched from messages at runtime.

Configure Dynamic AVP Retriever


The following sample configuration shows how to retrieve the AVP and bind it to a Key Column in the CRD.

Step 1 Select the column name from the **Columns** table and click **select** near **Bind to Session/Policy State Field** to open the **Please select an object...** dialog box.

Note You can use **Bind to Session/Policy State Field** only for those columns in the **Columns** table where **Key** column has been selected.

Step 2 Select the required object from the dialog box and click **OK**.

Figure 68: Adding AVPs



Step 3 Repeat these steps to add additional AVPs.

Custom Reference Data Tables

Search Table Groups

Peer Rate Limit Profile

This is a Search Table Group whose key columns are Peer Group, Peer FQDN or Origin Host in the message and Message Direction.

Using this search table group, the user can configure a maximum rate for each of the configured and defined diameter peers. It also allows the user to configure a maximum rate for each server process.

The peer rate limit is shown below:

Figure 69: Peer Rate Limit - STG

Custom Reference Data Table (Read Only)

***Name** peer_rate_limit_profile **Display Name** Peer Rate Limit Profile Cache Results

Activation Condition Best Match ***Evaluation Order** 0

***Columns**

*Name	Display Name	*Use In Condit	*Type	Key	Required
peer_group	Peer Group	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
peer_fqdn	Peer FQDN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
direction	Message Direction	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
rate_limit_profile	Rate Limit Profile	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
peer_rate_limit	Peer Rate Limit	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>	<input type="checkbox"/>
discard_behavior	Discard Behavior	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code

Bind to Session/Policy State Field

Bind to a result column from another table

Bind to Diameter request AVP code

Matching Operator

- Peer Group: This is the group of peers classified together using Peer Group and Peer Group Peer values initiating the message.
- Peer FQDN: The origin host of the peer. A specific diameter peer with its Fully Qualified Domain Name can be specified in this field or use wildcards specified by * in this field for any peer or matching peers like hss*.
- Direction: Message direction (Ingress and Egress).
 - Ingress: Any diameter messages received by CPS vDRA from diameter peer. The routing decision by CPS vDRA will be taken after the ingress side rate limiting has been applied.
 - Egress: Any diameter messages forwarded/routed by CPS vDRA to diameter peer. The egress side rate limiting will be applied after the routing decision has been taken by CPS vDRA.
- Peer Rate Limit: This field is to specify the threshold in TPS above which the diameter messages are discarded. This can be left empty if none of the messages are to be dropped or only message level rate limit is to be applied.
- Rate Limit Profile: Profile Name applicable for this Peer Group and Peer, if specified. This profile maps to Rate Limiting at message level. This field enables the rate limit at per message/command code level. See [Message Rate Limit Profile, on page 121](#) for more details.
- Rate Limit Result Code: The result code sent by CPS vDRA for response message towards diameter peer when Discard Behavior is configured as Send Error Answer. In case Discard Behavior is configured as Drop Message, this field is ignored.
- Error String: The string specified in this field is populated by CPS vDRA in AVP Error Message for response message towards diameter peer when Discard Behavior is configured as Send Error Answer. In case Discard Behavior is configured as Drop Message, this field is ignored. This is an optional field when Discard Behavior is configured as Send Error Answer.



Note If both Rate Limit Error Code and Rate Limit Error String are provided along with Rate Limit Action as "Drop Message", the Rate Limit Action takes precedence and the other two fields will be ignored.

For more information, see [Peer Rate Limit Profile](#), on page 111.

Peer Group Mapping

Figure 70: Peer Group Mapping - STG

Custom Reference Data Table (Read Only)

***Name** **Display Name** Cache Results

Activation Condition Best Match ***Evaluation Order**

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key
realm_pattern	Realm Pattern	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>
fqdn_pattern	FQDN Pattern	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>
peer_group	Peer Group	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>
weight	Weight	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>

Column Details

Valid Values		Validation	Runtime Binding				
The values allowed in Control Center for this column		Validation used by Control Center	Which rows match when a message				
<input checked="" type="radio"/> All <input type="radio"/> List of Valid Values		Regular Expression <input type="text"/>	<input checked="" type="radio"/> None				
<table border="1"> <thead> <tr> <th>*Name</th> <th>Display Name</th> </tr> </thead> <tbody> <tr> <td><input type="text"/></td> <td><input type="text"/></td> </tr> </tbody> </table>		*Name	Display Name	<input type="text"/>	<input type="text"/>	Regular Expression Description <input type="text"/>	<input type="radio"/> Bind to Subscriber AVP code
*Name	Display Name						
<input type="text"/>	<input type="text"/>						
			<input type="radio"/> Bind to Session/Policy State File				

For more information, see [Peer Group Mapping](#), on page 114.

Message Retry Profile

Message retry profile has been added.

Figure 71: Message Retry Profile - STG

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name** **Display Name** Cache Results

Activation Condition Best Match ***Evaluation Order**

***Columns**

*Name	Display Name	*Use In Condi	*Type	Key	Required
peer_group	Peer Group	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
app_id	Application Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
cmd_code	Command Code	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
rc_in_resp	Result Code	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
exp_rc	Experimental RC	<input checked="" type="checkbox"/>	True/False	<input type="checkbox"/>	<input type="checkbox"/>
num_retries	Number Of Retries	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name
-------	--------------

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field
 Bind to a result column from another table
 Bind to Diameter request AVP code

Matching Operator

- Peer Group: Peer group for which the retry has to be happen.
- Application Id: Application Id of the diameter applications.
- Command Code: Command Code of the message.
- Result Code: Result code received from PCRF for timeout. The value is 7000.
- Experimental RC: Indicates whether result code is experimental or not. This is for future purpose and value in this has no effect on the message retry functionality.
- Number of Retries: Number of retries for the message.

For more information, see [Message Retry Profile, on page 118](#).

Message Mediation Profile

The message mediation profile is used to provide support for mediation of AVPs in Diameter request and answer.

- For Diameter requests, only remove is supported.
- For Diameter answers, the following actions are supported:
 - "remove" meaning remove all matching AVPs in the request.
 - "copy" meaning copy from the request if no AVPs are present in the answer.

- If the AVP is present in answer, no action is performed.
- "overwrite" meaning first remove and then copy from the request.
 - Check if the AVP is present in answer, if so remove and add from request.
 - If AVP is not present in answer, copy from request.

A new **Message Mediation Profile** STG has been added:

Figure 72: Message Mediation Profile - STG

Custom Reference Data Table (Read Only)

*Name: message_mediation_profile Display Name: Message Mediation Profile Cache Results

Activation Condition: Best Match *Evaluation Order: 0

*Name	Display Name	*Use In Conditio	*Type	Key	Required
app_id	Application Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
cmd_code	Command Code	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
msg_type	Message Type	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
avp_code	Avp Code	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
vendor_id	Avp Vendor Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
avp_action	Avp Action	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name
-------	--------------

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field

 Bind to a result column from another table

 Bind to Diameter request AVP code

Matching Operator

- Application Id: Application ID of the Diameter applications.
- Command Code: Command code of the message.
- Message Type : Request/Answer for which the rule has to be applied.
- Avp Code : AVP code of the Diameter message.
- Vendor Id : AVP vendor ID.
- Avp Action : Provides options for copy/remove/overwrite.



Note

Application ID, Command Code, AVP Code and Vendor Id are used as key, so no duplicate rows could be defined for this combination and the same AVP action. For example, you cannot define both "remove" and "Copy from request" for the same set of Application ID, Command Code, AVP Code and Vendor Id.

Best Match check box needs to be checked if you want to use the wildcard feature.

For more information, see Message Mediation Profile in Custom Reference Data Tables chapter.

Peer Group Answer Timeout

New search table Peer Group Answer Timeout has been added.

Figure 73: Peer Group Answer Timeout - STG

Custom Reference Data Table (Read Only)

*Name: peer_group_answer_timeout Display Name: Peer Group Answer Timeout Cache Results

Activation Condition: Best Match *Evaluation Order: 0

*Name	Display Name	*Use In Condition	*Type
peer_group	Peer Group	<input checked="" type="checkbox"/>	Text
app_id	Application Id	<input checked="" type="checkbox"/>	Text
cmd_code	Command Code	<input checked="" type="checkbox"/>	Text
answer_timeout	Timeout Milliseconds	<input checked="" type="checkbox"/>	Text

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Validation
Validation used by Control Center

Regular Expression:

Regular Expression Description:

- Application Id: Application Id of the diameter applications.
- Peer Group: Peer group for which the timeout is applied.
- Command code (to enable different timeouts for different Diameter commands)
- Timeout: Timeout in milliseconds.

For more information, see [Peer Group Answer Timeout](#), on page 120.

Error Result Code Profile

Error result code profile can be used to map errors to Result-Code value and an error message string for the Error-Message AVP. It also provides support for configurable error result codes.

Figure 74: Error Result Code Profile - STG

Custom Reference Data Table (Read Only)

***Name** error_profile **Display Name** Error Result Code Profile Cache Results

Activation Condition Best Match ***Evaluation Order** 0

*Name	Display Name	*Use In Conditio	*Type	Key	Required
app_id	Application Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
internal_err	Error	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
rc_in_resp	Result Code	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
exp_rc_in_resp	Exp Result Code	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
exp_vendor_id	Vendor Id	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
err_msg	Err Msg	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All

List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Bind to a result column from another table

Bind to Diameter request AVP code

Matching Operator

Valid values is the place where all the valid error values can be configured in STG so that they are visible in CRD drop-down.

- ApplicationId: Application ID for which the mapping of Result-Code has to be done.
- Error: Internal error list.
- ResultCode: Result Code to be sent in answer.
- ExpResultCode: Experimental result code to be sent in answer. Vendor-Id will be sent in Answer only for Experimental result-Code.
- ErrMsg: Error message AVP sent in answer.



Note Experiment result code will be sent when Result-Code is not configured. If both Result-Code and experimental Result-Code are present, Result-Code would take precedence.

For more information, see [Error Result Code Profile, on page 122](#).

Gx Session Routing

Gx Session Routing table is required for "table driven routing". Here an example for Gx New Session Rules is provided. If table driven routing is required for Rx or Sd, user needs to create similar tables for Sd and Rx as well.

Figure 75: Gx Session Routing

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name** **Display Name** Cache Results

Activation Condition Best Match ***Evaluation Order**

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key	Required
logical_apn	Logical APN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_host	Origin Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
origin_realm	Origin Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_host	Destination Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_realm	Destination Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Bind to a result column from another table

Bind to Diameter request AVP code

For more information, see [Gx New Session Rules](#), on page 122.

SLF Trigger Profile

This table is used to derive SLF destination type and SLF lookup type. Keys used for this table are: Application Id, cmd_code, and dest_realm. Output of this table are slf_lookup_type and slf_destination_type.

An example configuration is given.

Figure 76: SLF Trigger Profile - STG

Custom Reference Data Table (Read Only)

*Name: Display Name: Cache Results

Activation Condition: Best Match *Evaluation Order:

*Name	Display Name	*Use In Condit	*Type	Key	Required
application_id	Application ID	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
cmd_code	Command Code	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
dest_realm	Destination Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
slf_lookup_type	SLF Lookup Type	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>
slf_destination_type	SLF Destination Type	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code

 Bind to Session/Policy State Field

 Bind to a result column from another table

 Bind to Diameter request AVP code

Matching Operator

For more information, see [SLF Trigger Profile](#), on page 124.

SLF Routing

This table is used to derive SLF session route key from SLF Destination. An example configuration is given.

Figure 77: SLF Routing - STG

Custom Reference Data Table (Read Only)

*Name: Display Name: Cache Results

Activation Condition: Best Match *Evaluation Order:

*Name	Display Name	*Use In Condit	*Type	Key	Required
slf_destination	SLF Destination	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
slf_session_route_key	SLF Session Route Key	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code

 Bind to Session/Policy State Field

 Bind to a result column from another table

 Bind to Diameter request AVP code

Matching Operator

For more information, see [SLF Routing, on page 125](#).

S6/Sh Table Driven Rules

This table is used for the table driven routing of S6/Sh messages. Fields origin_host, origin_realm, dest_realm, dest_host, msisdn, imsi are used as keys to derive the peer_route.

An example configuration is given.

Figure 78: S6 Table Driven Rules - STG

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

*Name: TB_S6 Display Name: S6_TB_Rules Cache Results

Activation Condition: (select) clear Best Match *Evaluation Order: 0

*Name	Display Name	*Use In Condi	*Type	Key	Required
origin_host	Origin Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_realm	Origin Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_host	Destination Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
destination_realm	Destination Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
imsi	IMSI	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name
-------	--------------

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression:

Regular Expression Description:

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field
 Bind to a result column from another table
 Bind to Diameter request AVP code

Matching Operator

For more information, see [S6/Sh Table Driven Rules, on page 125](#).

Custom Reference Data Tables

APN Mapping

This table provides information related to APN Mapping. The read-only APN Mapping are shown below:

Figure 79: APN Mapping - CRD Table

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name** **Display Name** Cache Results

Activation Condition Best Match ***Evaluation Order**

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key	Required
called_station_id	Called Station Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
logical_apn	Logical APN	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None

Bind to Subscriber AVP code

Bind to Session/Policy State Field

Bind to a result column from another table

Bind to Diameter request AVP code

- Called-Station-Id: This is the AVP from which APN is derived. This also is the key column for this table. It is bound to the session or Policy State field as shown in the snapshot.
- Logical_APN: This is the mapped logical name that is used for referencing and processing the message within the system.



Note For sample data configuration, refer the *CPS Control Center Interface Guide for Full Privilege Administrators* for this release.

Peer Access Control List

You can use the Peer Access Control List to specify the list of peers (by realm, FQDN, and applications) that can establish peer connections to vDRA so that unknown peers are not permitted to create Diameter peer connections.

Figure 80: Peer Access Control List

Custom Reference Data Table (Read Only)

***Name** peer_access_control_list **Display Name** Peer Access Control List Cache Results

Activation Condition Best Match ***Evaluation Order** 0

*Name	Display Name	*Use In Conditio	*Type	Key	Required
origin_host	Origin Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_realm	Origin Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
auth_action	Authorization Action	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>	<input checked="" type="checkbox"/>
error_code	Authorization Action Deny - Result Code	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>	<input type="checkbox"/>
error_msg	Authorization Action Deny - Error Message	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
application_id	Application Id	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field

Peer Routes

This table provides the information related to Peer Routes available in the system. The read-only peer routes are shown below:

Figure 81: Peer Routes - CRD Table

***Name** peer_route **Display Name** Peer Routes Cache Results Activation Condition

*Name	Display Name	*Use In Conditio	*Type	Key	Required
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field

215568

Peer Group SRK Mapping

This table provides the information related to Peer Groups in the system. The read-only peer groups are shown below:

Figure 82: Peer Group - CRD Table

Custom Reference Data Table (Read Only)

*Name: peer_group_srk_mapping Display Name: Peer Group SRK Mapping Cache Results: Activation Condition:

*Columns

*Name	Display Name	*Use In Conditio	*Type	Key	Required
peer_group	Peer Group	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
session_routing_key	Session Routing Key	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
dest_host_routing_rule	Destination Host Routing Rule	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>
dest_host_replace_rule	Destination Host Replace	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
dest_realm_replace_rule	Destination Realm Replace	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field
 Bind to a result column from another table
 Bind to Diameter request AVP code

Matching Operator

Actions
Copy:

- Peer Group: Name of the peer group.
- Session Routing Key: Routing token for this Peer Group.
- Destination Host Routing Rule: Defines Routing behavior of this group.

Peer Routing

This table provides the information related to peer routing in the system. The read-only peer routings are shown below:

Figure 83: Peer Routing - CRD Table

Custom Reference Data Table (Read Only)

*Name: peer_routing Display Name: Peer Routing Cache Results: Activation Condition:

*Columns

*Name	Display Name	*Use In Conditio	*Type	Key	Required
peer_route	Peer Route	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
system_id	System Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
peer_group	Peer Group	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>
precedence	Precedence	<input type="checkbox"/>	Number	<input type="checkbox"/>	<input checked="" type="checkbox"/>
weight	Weight	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field

- Peer Route: Identifier of this Peer Route.

215570

- System ID: System Identifier for this VM.
- Peer Group: Identifier of the Peer group on this peer Route.
- Precedence: of the peer group on this Peer Route.
- Weight: Weight of the peer group on this Peer Route.

PCRF Session Query Peers

Use this CRD to configure the REST API parameters for Rx AAR fallback routing.

Policy DRA supports a fallback routing for Rx AARs for VoLTE using the PCRF session query.

For an Rx AAR with an IPv6 binding query, vDRA provides the ability to route the Rx AAR based on an API query to the PCRF to determine if it has a session for the IPv6. The queries can be made in parallel to a configured set of query points on PCRFs.



Note Ensure you have enabled PCRF Session Query in the DRA plugin configuration to use this feature.

Figure 84: PCRF Session Query Peers CRD

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns

*Name: pcrf_session_query_peers Display Name: pcrf_session_query_peers Cache Results Activation Condition:

Svn Crd Data

*Columns

*Name	Display Name	*Use In Condi*	Type	Key
base_url	BASE_URL	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>
pcrf_group	PCRF GROUP	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>
session_query_parameter	SESSION QUERY PARAMETER	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>
user_id	USER ID	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>
password	PASSWORD	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>
timeout_ms	TIMEOUT_MS	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>

Column Details

Valid Values	Validation	Runtime Binding
The values allowed in Control Center for this column <input type="radio"/> All <input checked="" type="radio"/> List of Valid Values	Validation used by Control Center Regular Expression <input type="text"/> Regular Expression Description <input type="text"/>	Which rows match when a <input checked="" type="radio"/> None <input type="radio"/> Bind to Subscriber APP <input type="radio"/> Bind to Session/Policy S
*Name: framedIpv6PrefixKey Display Name: framedIpv6PrefixKey		

This CRD contains the following fields:

- base_url: The HTTP URL for the PCRF REST API, supports both HTTP and HTTPS. This does not contain the Rest API endpoint name.
- pcrf_group: The PCRFs can be configured in logical groups by defining the common pcrf_group. vDRA triggers the REST API request one after another for multiple PCRFs configured with same group name. This is to support PCRF with primary and secondary API endpoints. (Optional)
- session_query_parameter: PCRF session query parameter. Currently, only one value is supported: framedIpv6PrefixKey
- user_id: User ID for REST API request if PCRF requires any basic authentication. (Optional)
- password: Password for REST API request if PCRF requires any basic authentication. (Optional)

- `timeout_ms`: REST API request timeout value. Default: 250ms. (Optional)

You can also configure a session route key for the PCRF response. When vDRA makes REST API requests to multiple PCRFs for session query using the Framed-IPv6-Prefix received in the Rx AAR message, the PCRF that has the corresponding Gx session sends a session route key in the response. vDRA then uses this key to look up the peer group and route the Rx AAR message to the correct PCRF. To configure a session route key in the response, see the Unified API Plugin Configuration in *CPS Mobile Configuration Guide*.

Additionally, diameter load balancing ensures that when a PCRF is connected to two directors and the PCEF traffic passes on one director, the traffic is then equally distributed to both directors.

vDRA can also load balance session query REST requests across multiple PCRF API endpoints. Previously, all REST queries were sent to the primary endpoint and only if the primary query fails, then the request is sent to secondary. Now, the requests are load balanced across the different PCRF endpoints within a peer group. If the session query results indicate that the PCRF does not have the corresponding Gx session for the IPv6 prefix, then vDRA does not send the query to the other PCRF configured in the same group. Similarly, for all other failures, vDRA sends the session query request to a different PCRF REST API in the same group. It is recommended that a group may contain a maximum of four PCRF REST API endpoints. If there is no group name, the PCRF API endpoint is considered as a standalone PCRF.

IPv6 Ranges System ID Mapping

Use this CRD to specify a range of IPv6 addresses and the relay vDRA system ID.

This CRD is used to relay Rx AAR messages to other vDRA clusters based on the IPv6 range defined in the CRD.

When an Rx-AAR reaches vDRA, the AAR is checked for an IPv6 prefix. If there is an IPv6 prefix, then this CRD is checked for IPv6 ranges and to find the related primary and secondary vDRA system ID.

If the primary or secondary system is the current vDRA system-ID, then AAR message is processed locally. If the primary/secondary system ID is not the current vDRA, then current vDRA checks the relay links between current system and primary system. If the relay link is up, the the AAR is relayed to the primary system; else vDRA checks link to the secondary system.

Figure 85: IPv6 Ranges System ID Mapping CRD

Custom Reference Data Table Some or all columns in this table have been published and will be read only. Newly added columns will be editable.

***Name** `ipv6_range_sys_id_map` **Display Name** IPv6 Ranges System ID Mapping Cache Results **Activation Condition**

Svn Crd Data

*Name	Display Name	*Use In Conditio	*Type	Key	Required
<code>ipv6_start_range</code>	IPv6 Start Range	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
<code>ipv6_end_range</code>	IPv6 End Range	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
<code>primary_system_id</code>	Primary System Id	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>
<code>secondary_system_id</code>	Secondary System ID	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Table 19: IPv6 Ranges System ID Mapping Fields

Fields	Description
IPv6 Start Range	Starting IP of IPv6 range in long format.
IPv6 End Range	Ending IP of IPv6 range in long format.

Fields	Description
Primary system ID	Mandatory field. Indicates the System ID of vDRA in a vDRA cluster to which the request can be relayed.
Secondary system ID	Secondary vDRA to which the request can be relayed if the primary is not present.



Note The ranges are expected to be mutually exclusive and unique. Verify the values when provisioning the same.

Binding Key Profile

This table provides the information related to binding key profile in the system. The read-only keys are shown below:

Figure 86: Binding Key Profile - CRD Table

Custom Reference Data Table (Read Only)

*Name: binding_key_profile Display Name: Binding Key Profile Cache Results Activation Condition: [] [select] [clear]

*Name	Display Name	*Use In Condition	*Type	Key	Required
profile_name	Profile Name	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
imsi_apn	IMSI APN Key Enabled	<input checked="" type="checkbox"/>	True/False	<input type="checkbox"/>	<input type="checkbox"/>
msisdn_apn	MSISDN APN Key Enabled	<input checked="" type="checkbox"/>	True/False	<input type="checkbox"/>	<input type="checkbox"/>
framed_ipv6_prefix	Framed IPv6 Enabled	<input checked="" type="checkbox"/>	True/False	<input type="checkbox"/>	<input type="checkbox"/>
framed_ipv4	Framed IPv4 Enabled	<input checked="" type="checkbox"/>	True/False	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression
[]

Regular Expression Description
[]

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field
 Bind to a result column from another table
 Bind to Diameter request AVP code

Matching Operator
[]

Actions
Copy:

- **Profile Name:** This is the name given to the Bind profile that is associated with keys that are either enabled and/or disabled.
- **MSI APN Key Enabled:** Enabling this field would mean that bindings will be stored in IMSI APN collections in bindings database.
- **MSISDN APN Key Enabled:** Enabling this field would mean that bindings will be stored in MSISDN APN collections in bindings database.
- **Framed IPv6 Enabled:** Enabling this would mean binding data would be stored in “ipv6bindings” collection.
- **Framed IPv4 Enabled:** Enabling this would mean binding data getting stored in “ipv4bindings” collection.

Refer to [Binding Key Profile, on page 117](#) for configuration in Control Center.

AppId Key Profile Mapping

This table stores the mapping between Application Identifiers and Bind Key Profile Names. The Application Identifiers are pre-provisioned for two Application Identifiers as Gx and Rx. Similarly, the BindingKeyProfile is also tied to the Profile Name column of the “BindingKeyType_Profile” table:

Figure 87: AppId Key Profile Mapping- CRD Table

Custom Reference Data Table (Read Only)

***Name** **Display Name** Cache Results **Activation Condition**

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key	Required
application_id	Application Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
profile_name	Profile Name	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Actions
Copy:

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field

 Bind to a result column from another table

 Bind to Diameter request AVP code

Matching Operator

Message Rate Limit Profile

This table gives a provision to configure Message Rate Limits at a profile level.

Figure 88: Message Rate Limit Profile - CRD Table

Custom Reference Data Table (Read Only)

***Name** **Display Name** Cache Results **Activation Condition**

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key	Required
profile_name	Rate Limit Profile Name	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
app_id	Application Identifier	<input checked="" type="checkbox"/>	Number	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
command_code	Command Code	<input checked="" type="checkbox"/>	Number	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
mesg_type	Message/Request Type	<input checked="" type="checkbox"/>	Number	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
rate_limit	Message Rate Limit	<input checked="" type="checkbox"/>	Number	<input type="checkbox"/>	<input checked="" type="checkbox"/>

Column Details

Valid Values
The values allowed in Control Center for this column

All
 List of Valid Values

*Name	Display Name

Valid values pulled from another table's column (key)

Validation
Validation used by Control Center

Regular Expression

Regular Expression Description

Runtime Binding
Which rows match when a message is received

None
 Bind to Subscriber AVP code
 Bind to Session/Policy State Field
 Bind to a result column from another table
 Bind to Diameter request AVP code

- Profile Name: Unique Identifier for a profile.
- Application ID: Application Identifier for this row. 3GPP App Ids only are allowed here.
- Command Code: Command Code of the message that is applicable on the said interface specified by Application Id above.
- Message Type: Initial/Update/Terminate or None for messages that do not have them. The message request type should be same as specified for the command code in Policy Builder under Diameter Application.
- Rate Limit: This field is to specify the threshold in TPS above which the diameter messages are discarded. This value should be more than the Peer Rate Limit in order for message level rate limit to be applied.
- Profile Name: Unique Identifier for a profile.

Refer to Message Rate Limit Profile for configuration in Control Center.

Reserved IMSI

You can configure the Reserved IMSI CRD table to validate a parsed IMSI for SLF routing against a configured list of reserved MCC ranges.

The CRD has two main columns : MCC Start range and MCC End Range. The MCC consists of the first three digits of an IMSI.

If the IMSI matches a reserved IMSI, the value is ignored for SLF routing.

You can provide support up to ten distinct (non-overlapping) MCC ranges as Reserved IMSIs.

The DRA/SLF ignores AVPs that contain such IMSIs, and continues searching other AVPs in the Diameter request, for a valid address to be used for address resolution.

The following image shows a sample Reserved IMSI configuration:

Figure 89: Reserved IMSI

Custom Reference Data Table (Read Only)

*Name: reserved_mcc Display Name: Reserved MCC Cache Results Activation Condition: [] [select] [clear]

*Columns

*Name	Display Name	*Use In Condit*	*Type
mcc_start	MCC Start	<input checked="" type="checkbox"/>	Number
mcc_end	MCC End	<input checked="" type="checkbox"/>	Number

Column Details

Valid Values
The values allowed in Control Center for this column
 All
 List of Valid Values

Validation
Validation used by Control Center
 Regular Expression: []
 Regular Expression Description: []

Runtime Binding
Which rows match
 None
 Bind to Subscrib
 Bind to Session?

Trusted Realm Profile

Trusted Realm Profile is used for topology hiding. The CRD includes the following columns:

- Trusted Profile Name: Profile Name having a trusted realm mapped to it.
- Trusted Realm: Realm for which Topology Hiding is not required.

Figure 90: Trusted Realm Profile

Custom Reference Data Table (Read Only)

*Name: trusted_realm_profile Display Name: Trusted Realm Profile Cache Results

Activation Condition: [] [select] [clear] Skip Cnd Data Rest Match

*Evaluation Order: 0

*Columns

*Name	Display Name	*Use In Condit*	*Type	Key	Required
profile_name	Trusted Profile Name	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
trusted_realm	Trusted Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>

Protected Realm Trusted Profile Mapping

Protected Realm Trusted Profile Mapping is used for topology hiding. The CRD includes the following columns:

- Protected Realm: Realm that is protected (topology hiding is required).
- Profile Name: Profile having realms that are trusted for this protected realm and that do not require topology hiding.

Figure 91: Protected Realm Trusted Profile Mapping

The screenshot shows the configuration for a Custom Reference Data Table (Read Only) named "protected_realm_trusted_profile". The display name is "Protected Realm Trusted Profile". The activation condition is "Real Match". The evaluation order is 0. The table has two columns:

*Name	Display Name	*Use In Conditio	*Type	Key	Required
protected_realm	Protected Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
profile_name	Trusted Profile Name	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>

MME Alias Map

MME Alias Map is used for topology hiding. The CRD includes the following columns:

- MME FQDN: FQDN of MME that requires topology hiding.
- Alias1: Mandatory. An alias identity used for the protected host that belongs to an MME in the network.
- Alias 2: Optional. Alternate Alias that can be used for Topology Hiding for the given MME FQDN.
- Alias 3: Optional. Alternate Alias that can be used for Topology Hiding for the given MME FQDN.

Figure 92: MME Alias Map

The screenshot shows the configuration for a Custom Reference Data Table (Read Only) named "mme_alias_map". The display name is "MME Alias Map". The activation condition is empty. The evaluation order is 0. The table has four columns:

*Name	Display Name	*Use In Conditio	*Type	Key	Required
mme_host	MME FQDN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
alias1	Alias 1	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>
alias2	Alias 2	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
alias3	Alias 3	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

HSS Aliases

HSS Aliases is used for topology hiding. The CRD includes the following columns:

- HSS Alias FQDN: Alias FQDN used to replace a protected HSS FQDN.
- Shared Alias: Boolean variable used to indicate whether the Alias FQDN is shared across multiple HSS servers or not.

Figure 93: HSS Aliases

Custom Reference Data Table (Read Only)

*Name: Display Name: Cache Results Activation Condition:

Show Crd Data

*Name	Display Name	*Use In Condit	*Type	Key	Required
hss_alias	HSS Alias FQDN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
is_shared_alias	Shared Alias	<input checked="" type="checkbox"/>	True/False	<input type="checkbox"/>	<input checked="" type="checkbox"/>

HSS Alias Map

HSS Alias Map is used for topology hiding. The CRD includes the following columns:

- HSS FQDN: FQDN of HSS peer.
- Alias1: Required field which is derived from HSS Alias CRD.
- Alias2: Optional. Alias for the HSS FQDN.
- Alias3: Optional. Alias for the HSS FQDN.

Figure 94: HSS Alias Map

Custom Reference Data Table (Read Only)

*Name: Display Name: Cache Results Activation Condition:

Show Crd Data

*Name	Display Name	*Use In Condit	*Type	Key	Required
hss_host	HSS FQDN	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
alias1	Alias1	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>
alias2	Alias2	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>
alias3	Alias3	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input type="checkbox"/>

Binding Key Profile Creation Map

This table provides the information related to binding key type profile creation map in the system. The read-only keys are shown below:

Figure 95: Binding Key Profile Creation Map - CRD Table

Custom Reference Data Table (Read Only)

***Name**
bind_key_profile_creation_map

Display Name
Binding Key Profile Creation Map

Cache Results

Activation Condition
 clear Svn Crd Data Best Match

***Evaluation Order**
0

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key	Required
appl_id	Application Identifier	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
called_station_id	Called Station Id	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
profile_name	Binding Key Profile	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>



Note If there is no profile configured for any Application ID and Called Station ID pair, then a default profile is automatically selected. This profile has only Framed-IPv4-Enabled as false/disabled, while all other keys are true/enabled.

- Application Identifier: Application ID of the message.
- Called Station Id: Called-Station-Id AVP value from the Diameter message.
- Binding Key Profile: Profile name from binding key profile.

Refer to [Binding Key Profile Creation Map, on page 128](#) for configuration in CPS Central.

Binding Key Profile Read Map

This table provides the information related to binding key type profile read map in the system. The read-only keys are shown below:

Figure 96: Binding Key Profile Read Map - CRD Table

Custom Reference Data Table (Read Only)

***Name**
bind_key_profile_read_map

Display Name
Binding Key Profile Read Map

Cache Results

Activation Condition
 clear Svn Crd Data Best Match

***Evaluation Order**
0

***Columns**

*Name	Display Name	*Use In Conditio	*Type	Key	Required
appl_id	Application Identifier	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_host	Origin Host	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
origin_realm	Origin Realm	<input checked="" type="checkbox"/>	Text	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
binding_profile	Binding Key Profile	<input checked="" type="checkbox"/>	Text	<input type="checkbox"/>	<input checked="" type="checkbox"/>

- Application ID: Application ID from the message.

- Origin Host: Origin host from the message.
- Origin Realm: Origin realm from the message.
- Binding Key Profile: Profile name from binding key profile.

Refer to [Binding Key Profile Read Map, on page 129](#) for configuration in CPS Central.

Best Effort Binding

This table enables you to configure best effort binding on APN basis. The Caller Station Id column accepts regular expressions.

Figure 97: Best Effort Binding - CRD Table

Called Station Id *	Session Enabled	Framed IPv6 Enabled	Framed IPv4 Enabled	IMSI APN Key Enabled	MSISDN APN Key Enabled	Actions
ims.com	true	true	true	true	true	

Filter CRD Tables

[Add Row](#) [Close](#)



CHAPTER 4

Custom Reference Data Configuration

- Logical APN List, on page 108
- Avp Condition Profile, on page 108
- Avp Action Profile, on page 109
- APN Mapping Table, on page 110
- DOIC Profile, on page 111
- Diameter Avp Dictionary, on page 112
- Peer Access Control List, on page 113
- Peer Routes, on page 114
- Peer Group Mapping, on page 114
- Peer Group SRK Mapping, on page 115
- Peer Routing, on page 115
- IPv6 Ranges System ID Mapping, on page 116
- Binding Key Profile, on page 117
- AppId Key Profile Mapping, on page 117
- Message Class Profile, on page 118
- Message Retry Profile, on page 118
- Message Mediation Profile, on page 119
- Peer Group Answer Timeout, on page 120
- Message Rate Limit Profile, on page 121
- Error Result Code Profile, on page 122
- Gx New Session Rules, on page 122
- Rest API Error Code Profile, on page 123
- SLF Trigger Profile, on page 124
- SLF Routing, on page 125
- S6/Sh Table Driven Rules, on page 125
- Range Based Routing , on page 126
- IMSI Range, on page 127
- MSISDN Range, on page 127
- Binding Key Profile Creation Map, on page 128
- Binding Key Profile Read Map, on page 129

Logical APN List

The logical APN feature allows multiple users to access different physical target networks through a shared APN access point. The logical APN feature reduces the amount of APN provisioning required by consolidating access all real APNs through a single virtual APN. Therefore, only the virtual APN needs to be provisioned at Control Centre, instead of each of the real APNs to be reached.

For details on System ID, refer to [Peer Routing, on page 115](#).

For details on Peer Group, refer to Peer Group Mapping and Peer Group SRK Mapping.

An example configuration is shown below:

Figure 98: Logical APN List

Logical APN * (key)	Actions
INTERNET	Edit Delete
IMS-1	Edit Delete
ims4.com	Edit Delete

+ Add Row

Show 10 rows | 1 out of 1

Avp Condition Profile

The Avp Condition profile is used to specify the value and condition to apply to AVP.

The following table describes the fields of Avp Condition Profile:

Table 20: Avp Condition Profile

Field	Description
Profile Name	Profile name of the condition. Each row in the table is a condition. You can define multiple conditions for one Profile Name.
Avp	Avp that condition is applied to.
Avp Value	Value of the condition. If there is no AVP, configure the value as AVP_IS_MISSING

Figure 99: Avp Condition Profile

Profile Name * (key)	Avp * (key)	Avp Value *	Actions
ResultCodes3xxx	ResultCode	match=3.*	

+ Add Row

Avp Action Profile

You can use the Avp Action Profile to perform mediation at different directions (ingress, egress). You can modify both request and response messages. You can replace, append, prepend value AVP. The value may be static or dynamically retrieved from another AVP or can be extracted as substring from another AVP.

The following table describes the AVP actions that you can perform in Avp Action Profile:

Table 21: AVP Actions

Avp Action	Description
Remove Avp	Removes the AVP from the message.
Add with value	If the AVP is not present in the message, add the AVP with the value defined in CRD.
Add with Avp from Request	If the AVP is not present in the message, the AVP received from the request message is added to it.
Overwrite with value	Overwrite the AVP with the value defined in CRD.
Overwrite with Avp from Request	Overwrite the AVP with the AVP received from the request message
Add Prefix	Add prefix to the value of AVP.
Add Postfix	Add postfix to the value of AVP.
Remove Prefix	Remove prefix from the value of AVP.
Remove Postfix	Remove postfix from the value of AVP.

Figure 100: Avp Action Profile

Avp Action Profile				
				Filter CRD Tables
Profile Name * (key)	Avp * (key)	Avp Action	Avp Value	Actions
ChangeResultCode	ResultCode	Overwrite with value	3002	✎ 🗑
PrependLabel	DestinationHost	Add Prefix	core-	✎ 🗑
Hiding	OriginHost	Overwrite with value	dra	✎ 🗑
Hiding	OriginRealm	Overwrite with value	dra.cisco.com	✎ 🗑
ExtractHostFromSessionId	DestinationHost	Overwrite with value	SubString("\${SessionId}", "[^+];", 1)	✎ 🗑
AppendLabel	DestinationHost	Add Postfix	-suffix	✎ 🗑
StripPrependLabel	OriginHost	Remove Prefix	core-	✎ 🗑
StripAppendLabel	OriginHost	Remove Postfix	-suffix	✎ 🗑
AddAvp	User-Name	Overwrite with Avp from Request		✎ 🗑
AddQos	QoS-Information	Add with Avp from Request		✎ 🗑
AddSubscriptionId	Subscription-Id	Add with Avp from Request		✎ 🗑
DeleteAvp	User-Name	Remove Avp		✎ 🗑
AddAvpValue	User-Name	Add with value	0011223344	✎ 🗑
AddRatType	RAT-Type	Overwrite with value	1004	✎ 🗑

APN Mapping Table

The APN is composed of two parts which are as follows:

- The APN Network Identifier. This part of the APN is mandatory.
- The APN Operator Identifier. This part of the APN is optional.

The actual APN of any interface is filled-in with Called-Station-Id AVP. This table keeps a mapping of actual APNs and logical APNs configured in logical APN list.

An example configuration is shown below:

Figure 101: APN Mapping Table

Apn Mapping Table		
		Filter CRD Tables
CalledStationId * (key)	Logical APN	Actions
internet.com	INTERNET	✎ 🗑
ims-1.com	IMS-1	✎ 🗑
ims4.com	ims4.com	✎ 🗑

[+ Add Row](#)

Show 10 rows | < 1 out of 1 >

Peer Rate Limit Profile

CPS vDRA can rate limit traffic coming from and going towards a particular peer. This can work for both Ingress and Egress traffic. User needs to define the peer group, FQDN, traffic direction and the CPS vDRA behavior, whether to silently drop or send error message. User can also define the error code and the error message when error responses need to be sent back.

Figure 102: Peer Rate Limit Profile

Peer Group * (key)	Peer FQDN * (key)	Message Direction * (key)	Rate Limit Profile	Peer Rate Limit	Discard Behavior *	Result Code	Error String	Actions
match=GX_DC.*	*	Ingress	GX-CCR-I	3	Send Error Answer	3002	OVERLOAD_GX	✎ 🗑️

DOIC Profile

Use the DOIC Profile table to define the abatement action for Diameter messages in case of Diameter peer overload or congestion.

For more information about DOIC, see [Configure Throttling of Diameter Messages Using DOIC](#), on page 26.

The following table describes the DOIC Profile table parameters:

Table 22: DOIC Profile

Fields	Description	Value
Egress Peer Group	Name of egress peer group.	Referenced from the Peer Group name in Peer Group SRK Mapping.
Message Class	Message classification. Priority P0 is considered for emergency message class. Hence, it cannot be configured in DOIC for throttling. In case abatement treatment is applicable for P0 message as per Loss Algorithm (with random number), the message is forwarded.	P1, P2, P3, P4
Abatement Action (output)	The abatement action to be taken by vDRA.	Divert, Forward, Drop

The following abatement actions are supported:

- Forward: Forward allows the message to be sent to the destination peer, even though the peer is overloaded.

- **Divert:** Messages are diverted to the non-congested secondary peer as found using Peer Group SRK Mapping. If the secondary peer is congested, the next non-congested peer is used. If all peers are congested, the messages are dropped.
- **Drop:** Message is throttled with error response 3002

When a message is throttled, a default result-code of 3002 and default message "Throttled due to DOIC congestion" is sent.

The error message can be configured in Error Result Code Profile table with the Error key as Doic Throttled/Dropped.

Default Error Message is "3002: 012 - Throttled due to DOIC congestion"

Figure 103: DOIC Profile

Egress Peer Group * (key)	Message Class * (key)	Abatement Action	Actions
*	P1	Drop	 

Diameter Avp Dictionary

Use the Diameter Avp Dictionary CRD table to define the AVP name, AVP code, vendor ID, and the type.

The following table describes the parameters of the Diameter Avp Dictionary:

Table 23: Diameter Avp Dictionary

Field	Description
Name	Name of the AVP.
Avp Code	Code of the AVP.
Vendor Id	Vendor ID of the AVP.
Avp Type	Type of AVP (Integer32, Unsigned32, Integer64, OctetString, UTF8String, Grouped)

Figure 104: Diameter Avp Dictionary

Diameter Avp Dictionary

Name * (key)	Avp Code	Vendor Id	Avp Type
ResultCode	268	10415	Unsigned32

+ Add Row

Show 10 rows 1 out of 1

Peer Access Control List

You can use the Peer Access Control List to specify the list of peers (by realm, FQDN, and application ID) that can establish peer connections to vDRA.

Peers that are not listed with realm or host in the CRD are allowed to establish peer connections by default.

Specify the following parameters:

- Origin Host - Diameter identity or FQDN(host) of the client either in full or as a regular expression
- Origin Realm - Diameter Identity or realm of the client either in full or as a regular expression
- Authorization Action: Specifies whether the incoming client connection is allowed or denied.
- Authorization Deny - Result Code: Configurable result code. If not configured, the default value of 3010 (Unknown Application) or 3007 (Unsupported Application) is sent. Applicable only when the Authorization action is set to “Deny”
- Authorization Deny - Error Message: Configurable Message. If not configured default values are Unknown Peer or Unsupported Application.
Applicable only when the Authorization action is set to “Deny”
- Application ID: single, comma-separated, or regular expression.

The key fields are Origin Host and Origin realm, hence it is possible to have only one row for each unique pair.

If the peer connection is rejected due to mismatch of Applications, customized result-code / error messages are not applicable in this case.

Figure 105: Peer Access Control List

Origin Host *	Origin Realm *	Authorization Action *	Authorization Deny - Result Code	Authorization Deny - Error Message	Application Id *	Actions
gx-pcef10	match=gc-pcef1.*	Permit			16777238	✎ 🗑
match=gc-pcef1.*	gx-pcef11.cisco.com	Deny			16777238	✎ 🗑
gx-pcef14	gx-pcef14.cisco.com	Deny	3008	Peer is Blacklisted	16777238, 16777236	✎ 🗑
match=gc-pcef.*	gx-pcef12.cisco.com	Permit			16777236	✎ 🗑

Peer Routes

Request forwarding is done using Peer Routes to discover peers. These routes are different for different interfaces. There can be multiple peer routes for a particular interface.



Note If multiple remote peers (having same FQDN) are connected with DRA and one remote peer goes down after sending a request then response message is also dropped. DRA does not send the request to any other remote peers (having same FQDN).

Figure 106: Peer Routes

Peer Route * (key)	Actions
GX_CONSUMER	✎ 🗑
GX_ENTERPRISE	✎ 🗑
RX_CONSUMER	✎ 🗑
RX_CONSUMER_SITE	✎ 🗑
GX_CONSUMER_C	✎ 🗑
SD_CONSUMER	✎ 🗑
SD_CONSUMER_1	✎ 🗑
RX_ENTERPRISE	✎ 🗑
SD_CONSUMER_2	✎ 🗑

[+ Add Row](#)

Show 10 rows out of 1

Peer Group Mapping

One or more peers are combined into single peer group based on their realms patterns and FQDN patterns. Peer groups have respective peer routes.

Figure 107: Peer Group Mapping

Peer Group Mapping

Realm Pattern *	FQDN Pattern *	Peer Group	Weight	Actions
pcrf-rx-dra2.seagull.com	pcrf-rx-dra2-seagull	RX_PG	100	
pcrf-rx3.seagull.com	pcrf-rx3-seagull	RX_PG	200	
match=pcrf-gx.*	match=pcrf-gx.*	GX_PG	300	
pcef-gx-dra2.seagull.com	pcef-gx-dra2.seagull.com	PCEF_GX	200	
match=pcef-gx.*	match=pcef-gx.*	PCEF_GX	500	
rx-af-dra2.seagull.com	rx-af-dra2.seagull	PCEF_RX	100	
match=rx-af-dra2.*	match=rx-af-dra2.*	PCEF_RX	300	

+ Add Row

Show 10 rows out of 1

Peer Group SRK Mapping

All the peer groups consisting of one or more peers are listed in this table. Also various features like Session Key Routing or Destination Host Routing can be configured as Only, Never, Preferred depending upon the need. Use the DOIC Enabled column (YES/NO) to enable or disable Diameter Overload Indication Conveyance (DOIC). This option is used to throttle or divert Diameter requests towards PCRF, HSS, AAA, and OCS servers based on reporting of overloaded conditions.

Figure 108: Peer Group SRK Mapping

Peer Group SRK Mapping

Peer Group * (key)	Session Routing Key	Destination Host Routing Rule *	Destination Host Replace	Destination Realm Replace	Doic Enabled	Actions
pcrf-g	pcrf-cluster.pcrf1	Preferred	YES	YES	NO	
pcef-g	pcef-cluster.pcef1	Preferred	YES	YES	NO	
mme-g	mme-cluster.mme1	Preferred	YES	YES	NO	
hss-g	hss-cluster.hss1	Preferred	YES	YES	YES	
hss2-g	hss-clusterb.hss1	Preferred			YES	

Peer Routing

This table consists of a mapping of Peer Groups to Peer Routes on a particular CPS vDRA. It also has precedence and weight columns which play a vital role in load balancing behavior of CPS vDRA.

Figure 109: Peer Routing

Peer Route * (key)	System Id * (key)	Peer Group * (key)	Precedence *	Weight *	Actions
SD_CONSUMER_2	system-1	SD_DC_1	1	1	edit delete
GX_CONSUMER	system-1	GX_DC_1	1	1	edit delete
RX_CONSUMER	system-1	GX_DC_1	1	1	edit delete
RX_CONSUMER	system-1	GX_DC_2	1	1	edit delete
SD_CONSUMER	system-1	SD_DC_2	1	1	edit delete
GX_CONSUMER_C	system-1	GX_DC_3	1	1	edit delete
SD_CONSUMER_1	system-1	SD_DC_2	1	1	edit delete

+ Add Row

Show 10 rows | < 1 out of 1 >

IPv6 Ranges System ID Mapping

Use this table to specify a range of IPv6 addresses and the primary and secondary vDRA system ID.

Figure 110: IPv6 Ranges System ID Mapping

IPv6 Start Range	IPv6 End Range	Primary System Id	Secondary System
No rows available on the server.			

Table 24: IPv6 Ranges System ID Mapping Fields

Fields	Description
IPv6 Start Range	Indicates the start of range in ASCII.
IPv6 End Range	Indicates the end of range in ASCII.
Primary System ID	Mandatory field. Indicates the System ID of vDRA in a vDRA cluster to which the request can be relayed.
Secondary System ID	Secondary vDRA System ID where lookup can happen.



Note The ranges are expected to be mutually exclusive and unique. Verify the values when provisioning the same.

Binding Key Profile



Important For routing to work in DRA, user must configure **AppId Key Profile Mapping** and **Binding Key Profile** tables.

The available fields are Boolean fields and can be edited by selecting the check boxes.



Note It is expected a minimum of one row to be configured with the value “DefaultProfile”. This will be used in case there is nothing configured for an application Id. For this “DefaultProfile”, “imsiAPN” and “FramedIPv6Prefix” should be enabled.



Note The field **MSISDN APN Key Enabled** is a place holder only. Modifying this field will not have an effect on the application behavior.

Figure 111: Binding Key Profile

Profile Name * (key)	IMSI APN Key Enabled	MSISDN APN Key Enabled	Framed IPv6 Enabled	Framed IPv4 Enabled	Actions
DefaultProfile	true	false	false	false	
Rx_Profile	false	false	true	false	

+ Add Row

Show 10 rows out of 1

AppId Key Profile Mapping



Important For routing to work in CPS vDRA, you must configure **AppId Key Profile Mapping** and **Binding Key Profile** tables.

Figure 112: AppId Key Profile Mapping

Application Id * (key)	Profile Name	Actions
Gx	DefaultProfile	✎ 🗑️
Rx	Rx_Profile	✎ 🗑️

The Binding Key Profile column is tied to the Profile Name column from the previous CRD and takes the available Profile Name in the system.

There are two application Identifiers that have been provisioned in the system which are Gx and Rx and can be tied to the same or different Bind Key Profile as the case may be.

Message Class Profile

To determine the abatement action from the DOIC Profile table (for throttling or diverting Diameter requests), you require a Message class. You can query the Message class from the Message Class Profile table.

The Message Class Profile table takes inputs such as Ingress Peer Group, Application Id, Command Code, Message/Request Type and provides the Condition Profile and Message Class. Message Class can be one of P0, P1, P2, P3, P4.

Figure 113: Message Class Profile

Ingress Peer Group * (key)	Application Id * (key)	Command Code * (key)	Message/Request Type * (key)	Condition Profile * (key)	Message Class	Actions
pcef-g	16777238	272	None	IsEmergency	P0	✎ 🗑️
*	16777251	318	None	*	P1	✎ 🗑️

Message Retry Profile

CPS vDRA supports configurable retries, so that the specific behavior of CPS vDRA in congestion scenarios can be configured.

Configurable retry mechanism (i.e., number of retries) per:















- Application ID
- Peer Group
- Answer Timeout error occurred
- Error Result Code of Response

This should be in the form of a CRD and applied to a peer group. The user can use the SRK peers to select an alternate peer.

If all SRK peers fail, the user should use one alternate CPS vDRA if it connects to the SRK. If the SRK matches exactly, CPS vDRA would look for the second label match of SRK like clusterb.dc1 and clusterc.dc1 and retry the message to other peer group.

Figure 114: Message Retry Profile - Control Center

Message Retry Profile

Peer Group * (key)	Application Id * (key)	Command Code * (key)	Result Code * (key)	Experimental RC	Number Of Retries	Actions
GX_DC_1	16777238	272	3003	false	6	 
GX_DC_1	16777238	272	3004	false	6	 
GX_DC_2	16777238	272	3003	false	6	 
GX_DC_2	16777238	272	3004	false	6	 
match=SD_DC.*	16777303	8388637	3004	false	6	 
RX_DC_1	16777236	258	7000	false	6	 
GX_DC_2	16777238	272	7000	false	6	 

+ Add Row

Show 10 rows | 1 out of 1

Wild card match is supported for Peer Group, Application Id, Command Code, Result Code columns. For example, 300.* supports all RC starting with 300.

- * is supported to allow all RC.
- * is supported for all peer groups.
- Match = GX_DC_.* is supported for groups starting with GX_DC

RC = 7000 is interpreted as retry for timeout.

Experimental result code is for future purposes and value in that column has no effect on retry processing.



Note **Best Match** check box needs to be checked in Policy Builder if you want to use the wildcard feature.

Refer to [Message Retry Profile, on page 86](#) for configuration in **Search Table Group**.

Message Mediation Profile

CPS vDRA supports message mediation profile for following use cases:

- Store an AVP from the request and insert it into the answer. The answer is forwarded from an endpoint or an error generated by CPS vDRA. The known use case for this is storing the MSISDN from a request from the OCS (Sy SNR, Gy RAR) and inserting it in the answer to the OCS. The endpoint cannot handle all cases since the DRA can generate the error response in case of request timeout or inability to route the request to a peer. The MSISDN is in the Subscription-ID AVP.
- Remove an AVP from a request or answer.

Figure 115: Message Mediation Profile - Control Center

Message Mediation Profile

Filter CRD Tables

Application Id * (key)	Command Code * (key)	Message Type * (key)	Peer Group * (key)	Message Direction * (key)	Condition Profile	Action Profile * (key)	Actions
16777302	8388635	Request	*	Ingress		RemovePolicyCounterStatusReport	✎ 🗑
16777302	8388635	Answer	*	Egress		OverwriteSubscriptionId	✎ 🗑
16777302	8388635	Request	*	Ingress		RemoveSubscriptionId	✎ 🗑
4	258	Request	*	Ingress		RemoveSubscriptionId	✎ 🗑
4	258	Answer	*	Egress		OverwriteSubscriptionId	✎ 🗑
16777302	8388635	Answer	*	Egress		RemovePolicyCounterStatusReport	✎ 🗑
4	258	Answer	*	Egress		RemoveRatingGroup	✎ 🗑

[+ Add Row](#)

Show 10 rows | 1 out of 1

Peer Group Answer Timeout

CPS vDRA support for the following use cases:

- Configurable answer timeout for initial try and subsequent retries for the following parameters:
 - Application ID
 - Peer Group (to which request is sent)
 - Command code (to enable different timeouts for different Diameter commands)
 - Timeout value (in milliseconds)
- Default value if unspecified is 1700 milliseconds.

Peer group answer timeout is applicable for every message routed using:

- Destination host routing
- SRK routing
- Table driven routing

Sample peer group answer timeout is shown below:

Figure 116: Peer Group Answer Timeout

Peer Group Answer Timeout

Peer Group *	Application Id *	Command Code *	Timeout Milliseconds	Actions
SD_DC_2	16777303	*	15000	
RX_DC_2	16777236	*	22000	
GX_DC_3	16777238	*	20000	
SD_DC_2	16777303	8388637	25000	
SD_DC_1	16777303	272	25000	
RX_DC_1	16777236	*	20000	
GX_DC_2	16777238	272	22000	
GX_DC_1	16777238	match=2.*	25000	

+ Add Row

Show 10 rows out of 1

Wild card match is supported for application_id, peer_group, command code. * indicates all application_id, peer_group.

The following rules have been applied for answer timeout:

- Default timeout for any message routed from CPS vDRA is 1700 ms.
- In case of retry, if an alternate group is chosen for routing, corresponding timeout for the peer group is applied.

For Policy Builder related configuration, refer to [Peer Group Answer Timeout, on page 89](#).

Message Rate Limit Profile

Further to peer level rate limit, CPS vDRA provides the granularity of limiting diameter traffic at message level for each peer. Message level rate limit always works in conjunction with peer level rate limit and is an additional control in peer level rate limit configuration. Since message level rate limit works in conjunction with peer level rate limit, all the fields specified for peer level rate limit are applicable to message level rate limit.

Message Rate Limit Profile table is used to get the condition for such rate limiting. User can define the type of message, command code and the application for which the limiting has to be implemented.

Figure 117: Message Rate Limit Profile

Message Rate Limit Profile

Rate Limit Profile Name * (key)	Application Identifier * (key)	Command Code * (key)	Message/Request Type * (key)	Message Rate Limit *	Actions
GX-CCR-I	Gx	272	1	7	

+ Add Row

Show 10 rows out of 1

Error Result Code Profile

Sample CRD data looks like this:

Figure 118: Error Result Code Profile

Application Id * (key)	Error * (key)	Result Code	Exp Result Code	Vendor Id	Err Msg	Actions
*	No Available Peer	4004	5004	10415	Peer not available	✎ 🗑
*	No Peer Group	4005		10415	No Peer Group Available	✎ 🗑
*	No Binding Found	3024		10415	No Binding found for request	✎ 🗑
*	Message Loop Detected	4007		10415	Loop Detected in Message	✎ 🗑
*	No Binding Key For Lookup		4008	10415	No Binding Key for Lookup	✎ 🗑

+ Add Row

Show 10 rows | 1 out of 1

- For any CPS vDRA error or message timeout, CPS vDRA has the ability to map the error to a Result-Code value and an error message string for the Error-Message AVP.
- Errors include things like "binding not found", "message timeout", "no peer connections".
- The Result Code value is sent in the Result-Code AVP in the response.
- The error message string is sent in the Error-Message AVP in the response.
- When both Result Code and Exp Result Code are configured in this table, Result Code will take precedence. In case Result Code is not configured in this table, Exp Result Code will be sent with Vendor-ID.





















Gx New Session Rules

Gx New Session Rules table is used by CPS vDRA when performing Table Driven routing. CPS vDRA could derive the "Peer Route" from this table, when the incoming message has no destination host to be routed to. From peer route, CPS vDRA derives further route where the request could be sent. This table supports both wildcard and exact match for the various parameters. The "Peer Route" used in this table should be defined in "Peer Routes" table. Here an example for Gx New Session Rules is provided. Similar tables can be created for Rx or Sd.

Figure 119: Gx New Session Rules

Gx New Session Rules

Filter CRD Tables

Logical APN * (key)	Origin Host * (key)	Peer Route	Origin Realm * (key)	Destination Host * (key)	Destination Realm * (key)	MSISDN * (key)	IMSI * (key)	Actions
ims4.com	gx-pcef	GX_CONSUMER	*	*	*	*	*	 
ims3.com	*	GX_CONSUMER	gx-pcef.cisco.com	*	*	*	*	 
ims.com	*	GX_CONSUMER	*	*	*	*	*	 
ims2.com	*	GX_CONSUMER	*	*	*	*	45005978851107	 
ims1.com	*	GX_CONSUMER	*	*	*	match=*2829	*	 
ims5.com	*	GX_CONSUMER	*	*	gx-dra1.cisco.com	*	*	 
ims6.com	*	GX_CONSUMER	*	gx-dra1	*	*	*	 
ims.com	gx-pcef1	GX_CONSUMER	*	*	*	*	*	 
ims.com	gx-pcef2	GX_CONSUMER	*	*	*	*	*	 
ims.com	gx-pcef3	GX_CONSUMER	*	*	*	*	*	 

+ Add Row

Show 10 rows | 1 out of 3

Rest API Error Code Profile

You can configure the HTTP response error code (such as 4xx, 5xx) corresponding to each vDRA Rest API JSON error response code for the GET binding (for example imsi, imsiApn, msisdn, msisdnApn, ipv4, ipv6) Rest API.

This HTTP response code is used in the response for any GET binding Rest API request. If this CRD is not configured with HTTP response codes, then vDRA returns the default HTTP response status code.

If you do not configure the Rest API HTTP Error Code in the CRD, vDRA uses the default HTTP error codes for GET binding Rest API. For a list of the default HTTP error codes, see the *CPS vDRA Troubleshooting Guide*.

The following table describes the mandatory parameters in the Rest API Error Code profile CRD:

Table 25: Rest API Error Code Profile

Parameter	Description
Rest API Error Code	vDRA Rest API JSON error response code for the GET binding (for example imsi, imsiApn, msisdn, msisdnApn, ipv4, ipv6) Rest API
Http Error Code	HTTP response error code (such as 4xx, 5xx) corresponding to each vDRA Rest API JSON error response code.

Figure 120: Rest API Error Code Profile

Rest API Error Code *	Http Error Code *	Actions
1001 (INTERNAL_ERROR)	500 (Internal Server Error)	
2014 (DATA_NOT_FOUND)	404 (Not Found)	

SLF Trigger Profile

In this table, there are three input keys: Application Id, Command Code and Destination Realm. If all these input keys are matched from the Diameter incoming requests and trigger condition for the SLF trigger table is matched, then CPS vDRA derives the Primary Lookup Type (IMSI/MSISDN) and SLF Destination Type as output of SLF trigger table. Then a query is made in the SLF Database using the Primary Lookup Type (IMSI/MSISDN) and SLF-Destination-Type.

This table is used in the case when the Diameter Request does not contain any “Destination-Host” AVP or, in case the “Destination-Host” AVP comes with the Diameter Host Name of CPS vDRA.

Figure 121: SLF Trigger Profile

Application ID * (key)	Command Code * (key)	Destination Realm * (key)	Primary Lookup Type *	Secondary Lookup Type	SLF Destination Type *	Actions
16777251	*	s6-hss.com	IMSI		LTE-HSS	
16777291	*	slh-hss.com	IMSI		LTE-HSS	
16777217	*	sh-hss.com	MSISDN		LTE-HSS	
16777251	316	mnc286.mcc311.3gppnetwork.org	IMSI		S6a-HSS	
16777251	*	mnc286.mcc311.dranetwork.org	IMSI		S6a-HSS	

Based on Application ID 16777251, Command Code 316 and Destination Realm of `ims.mnc286.mcc311.3gppnetwork.org`, Primary Lookup Type selected is IMSI and SLF Destination Type is selected as S6a-HSS. This Primary Lookup Type and SLF Destination Type is used to query SLF database for the configured lookup type.

SLF Routing

This table contains the mapping of SLF destination and the SRK of peer groups where the message could be routed. The SLF destination is derived from SLF subscriber database.

Figure 122: SLF Routing

SLF Destination * (key)	SLF Session Route Key *	Actions
lte_hss_a	hss_cluster_dc1	
S6a-HSS1	LTE.S6a.HSS	
SLF-S6a-HSS	LTE.S6a.HSS	

+ Add Row

Show 10 rows 1 out of 1

S6/Sh Table Driven Rules

This table is used for table driven routing of S6/Sh messages when the destination host is not available in the incoming request and there is no match SRK found in SLF Trigger table/SLF Mapping table. Keys used for deriving the peer route are Origin Host, Origin Realm, Destination Host, Destination Realm, MSISDN, IMSI and the output is Peer Route.

An S6 Table Driven Rules example configuration is given.

Figure 123: S6/Sh Table Driven Rules

Logical APN * (key)	Origin Host * (key)	Peer Route	Origin Realm * (key)	Destination Host * (key)	Destination Realm * (key)	MSISDN * (key)	IMSI * (key)	Actions
ims4.com	gx-pcef	GX_CONSUMER	*	*	*	*	*	
ims3.com	*	GX_CONSUMER	gx-pcef.cisco.com	*	*	*	*	
ims.com	*	GX_CONSUMER	*	*	*	*	*	
ims2.com	*	GX_CONSUMER	*	*	*	*	45005978851107	
ims1.com	*	GX_CONSUMER	*	*	*	match=.*2829	*	
ims5.com	*	GX_CONSUMER	*	*	gx-dra1.cisco.com	*	*	
ims6.com	*	GX_CONSUMER	*	gx-dra1	*	*	*	
ims.com	gx-pcef1	GX_CONSUMER	*	*	*	*	*	
ims.com	gx-pcef2	GX_CONSUMER	*	*	*	*	*	
ims.com	gx-pcef3	GX_CONSUMER	*	*	*	*	*	

+ Add Row

Show 10 rows 1 out of 3

Range Based Routing

CPS vDRA provides range-based routing based on MSISDN and IMSI values so that Diameter requests are routed to the correct HSS or AAA server. Range-based routing occurs if the destination-host routing, binding-based routing and SLF-based routing fails.

- vDRA checks whether the primary lookup type is IMSI or MSISDN and also checks whether the IMSI/MSISDN value present in the request matches against the range configured in CRD.
- The primary lookup type is evaluated first and if it fails, the secondary lookup type is evaluated.
- If primary lookup type evaluation fails and if the secondary lookup type is not configured, the request is routed with table-driven routing (if configured).
- If both the primary lookup type credential and the secondary lookup type evaluation fail, the request is rejected or routed with table driven routing (if configured).

vDRA matches the request against the Range Based Routing table and based on the result of the credential match, SRK routing is initiated.

Table 26: Range Based Routing

Field	Description	Value
Application Id (input)	The diameter application of the message received	Integer value of the application id
Command Code (input)	The message command code	Integer value of the command code
Destination Realm (input)	The destination realm in the message	String value of destination realm
Primary Lookup Type (input)	Primary lookup type for range based routing	IMSI or MSISDN
Secondary Lookup Type (input)	Secondary lookup type for range based routing	NONE or IMSI or MSISDN
Routing Profile (output)	Routing profile	Any string value. (Should match the routing profile in either or both the IMSI and MSISDN range CRD for a successful match).

Figure 124: Range Based Routing

Range Based Routing
Filter CRD Tables

Application ID *	Command Code *	Destination Realm *	Primary Lookup Type *	Secondary Lookup Type *	Routing Profile *	Actions
16777238	272	pcrf-gx-dra2.seagull.com	MSISDN	IMSI	routingProfile	✎ 🗑

IMSI Range

The IMSI Range is used in range-based routing to configure the range of IMSI values.

Table 27: IMSI Range

Field	Description	Value
Routing Profile (input)	The routing profile name	Any string value
IMSI lower bound (input)	The lower bound for the IMSI value	For a numeric range, enter the IMSI value. For a regex, use the syntax: <code>match=<regex></code>
IMSI upper bound (input)	The upper bound for the IMSI value	For a numeric range, enter the IMSI value. For a regex, leave it blank.
SRK (output)	The SRK key	Any string value

Examples:

- For configuring numeric range between 9840510345 to 984059999: Lower bound: 9840510345, Upper bound: 9840598823
- For configuring regex for numbers in range 9840500000 to 9840599999: Lower bound: `match=98405[0-9]*`, Upper bound : <leave it empty>
- For configuring regex for numbers in range 9840501333 to 9840502999: Lower bound: `match=984050(1|2)[3-9]*` , Upper bound : <leave it empty>
- For configuring regex for numbers in range 9840500000 to 9840599999: Lower bound: `match=98405(([2-7][0-9]*)(8[0-8][0-4][0-5][0-6])(1[0-9][2-9][3-9][4-9]))`, Upper bound : <leave it empty>

Figure 125: IMSI Range

The screenshot shows a configuration table for IMSI Range. The table has five columns: Routing Profile *, IMSI lower bound *, IMSI upper bound, SRK *, and Actions. The first row contains the values: routingProfile, 333333333300000, 333333333344444, and srk_dc3. There are edit and delete icons in the Actions column.

Routing Profile *	IMSI lower bound *	IMSI upper bound	SRK *	Actions
routingProfile	333333333300000	333333333344444	srk_dc3	

MSISDN Range

The MSISDN Range is used in range-based routing to configure the range of MSISDN values.

Table 28: MSISDN Range

Field	Description	Value
Routing Profile (input)	The routing profile name	Any string value
IMSI lower bound (input)	The lower bound for the IMSI value	For a numeric range, enter the IMSI value. For a regex, use the syntax: match=<regex>
IMSI upper bound (input)	The upper bound for the IMSI value	For a numeric range, enter the IMSI value. For a regex, leave it blank.
SRK (output)	The SRK key	Any string value

Examples:

- For configuring numeric range between 9840510345 to 984059999: Lower bound: 9840510345, Upper bound: 9840598823
- For configuring regex for numbers in range 9840500000 to 9840599999: Lower bound: match=98405[0-9]*, Upper bound : <leave it empty>
- For configuring regex for numbers in range 9840501333 to 9840502999: Lower bound: match=984050(1|2)[3-9]* , Upper bound : <leave it empty>
- For configuring regex for numbers in range 9840500000 to 9840599999: Lower bound: match=98405(((2-7)[0-9]*)(8[0-8][0-4][0-5][0-6])(1[0-9][2-9][3-9][4-9])), Upper bound : <leave it empty>

Figure 126: MSISDN Range

Routing Profile *	MSISDN lower bound *	MSISDN upper bound	SRK *	Actions
routingProfile	match=99999[0-9]*		srk.dc3	

Binding Key Profile Creation Map

The available fields are Boolean fields and can be edited by selecting the check boxes.

Figure 127: Binding Key Profile Creation Map

Reference Data

import close all create snapshot revert snapshot import all export all Last refresh on 01/20 at 07:34:03PM

Binding Key Creation Profile Map

Application Identifier	APN	Binding Profile	import add search refresh
16777238	ims.com	Gx	save cancel

- APN field supports both wildcard "*" and regex match like "match=ims.*".

- For Binding Key profile Read Map, both Origin-Host and Origin-Realm support wildcard and regex match.
- Binding Profile and Binding Key Profile fields use values from Profile name field in Binding Key Profile table. Any profile first has to be defined in Binding Key Profile and then only it could be used in create or read tables.

Binding Key Profile Read Map

The available fields are Boolean fields and can be edited by selecting the check boxes.

Figure 128: Binding Key Profile Read Map

The screenshot shows a web interface for configuring a Binding Key Profile Read Map. At the top, there is a 'Reference Data' section with a yellow background. Below it, there are several action buttons: 'import', 'close all', 'create snapshot', 'revert snapshot', 'import all', and 'export all'. A timestamp 'Last refresh on 01/20 at 07:36:21PM' is displayed on the right. The main configuration area is titled 'Binding Key Profile Read Map' and contains a table with the following columns: 'Application Identifier', 'Origin Host', 'Origin Realm', and 'Binding Key Profile'. The table has one row with the following values: '16777238', 'testHost.cisco.com', 'testrealm.cisco.com', and 'Gx'. To the right of the table, there are buttons for 'import', 'add', 'search', and 'refresh'. Below the table, there are 'save' and 'cancel' buttons.

Application Identifier	Origin Host	Origin Realm	Binding Key Profile	import	add	search	refresh
16777238	testHost.cisco.com	testrealm.cisco.com	Gx				



CHAPTER 5

DRA Distributor Configuration

- [DRA Distributor Configuration Overview, on page 131](#)
- [Configuring DRA Distributor, on page 131](#)
- [Configuration Status Check, on page 134](#)

DRA Distributor Configuration Overview

DRA distributor configuration includes the following:

- Configuring the dra-distributor VMs.
- Adding VIPs to the dra-directors.
- Suppressing IPv4 ARP/IPv6 neighbor discovery for the VIPs on the dra-director.
- Adding static routes to clients (PGW, PCRF, and so on) on the dra-director.

Configuring DRA Distributor

Configuring DRA Distributor VM is performed using the ConfD CLI interface.

CLI Configuration

network dra-distributor

Add a dra-distributor cluster

Syntax

```
network dra-distributor <client> <range>
```

The following table describes the DRA Distributor configuration parameters:

Table 29: DRA Distributor Configuration Parameters

Parameter	Description
client	Name of cluster to be configured. Value range is from 1 - 8 characters

Parameter	Description
sync-id	Unique ID per cluster. VMs with the same sync-id synchronize connection data. All VMs in the named dra-distributor synchronize their connection data in case of VM failure. Value range is from 0 - 255
sync-interface	Interface used to send multicast connection sync data. Typically an interface on the Internal network. Example: ens192
global-tracking-service	Container to track for health check of dra-director VMs for all services. Default value is diameter-endpoint
host-ip	IP address of member VM. Value: Any IP address that exists on the VM. Typically, internal IP address.
global-priority	Global priority for all services of the host on which the service must run. Can be overridden in an individual service configuration. Priority range is from 1 to 255. Larger values have higher priority than lower values. Example: 10 has a higher priority than 5.
service-name	Unique name for peer service.
virtual-router-id	Virtual router ID is the identity for a virtual router for hosts that are managed for the virtual IP of the service. Value range is from 0 - 255. For more details, refer to VRRP (Virtual Router Redundancy Protocol) RFC 3768 and keepalive documentation.
tracking-service	Container to track for health check of dra-director VM. Overrides global-tracking-service. Default value is global-tracking-service.
preempt-delay	Preempt delay is delay in seconds before a VIP switches from backup to master. Default value is 30 seconds. Value range is from 1 - 1000.
interface	Interface of the host where the virtual IP is installed as secondary address when active.
service-ip	Virtual IP address of service.
service-port	TCP port of service.

Parameter	Description
service-host-ip	IP address of VM. Used to override global priority.
service-priority	Overrides global-priority. This allows a VIP to run on VM1 and another VIP to run on VM2. Example: Gx VIP on VM1 and Rx VIP on VM2.
preempt	Enable or disable VIP preemption for a single VIP. Default value is true. Value: true, false
real-service-ip	IP address of a dra-director supporting the service.
weight	Relative weight of real-server used by weighted least connection scheduling algorithm. Value range is from 0 - 255. Default value is 1. A value of 0 disables new connections to this real-server.
connection-timeout tcp	Idle timer for TCP connections in seconds. A connection is dropped if no traffic is seen for the duration of the timer. Default value is 30 seconds.
connection-timeout tcpfin	Timeout value in seconds for a connection after receiving a TCP FIN packet. A connection is dropped if no traffic is seen for the duration of the timer. Default value is 5 seconds.

Sample Configuration

```

network dra-distributor client
  sync-id 1
  sync-interface ens192
  tracking-service diameter-endpoint
  preempt-delay 5
  host 192.169.21.20
    priority 10
  !
  host 192.169.21.21
    priority 5
  !
  service Gx
    virtual-router-id 60
    interface ens224
    service-ip 192.169.22.50
    service-port 3868
    real-server 192.169.22.13
      weight 100
    !
    real-server 192.169.22.14
    !
  !

```

```

service Rx
virtual-router-id 61
interface      ens224
service-ip    192.169.25.80
service-port  3868
host 192.169.21.20
  priority 4
!
host 192.169.21.21
  priority 9
!
real-server 192.169.25.13
!
real-server 192.169.25.14
!
!
network dra-distributor server
sync-id      2
sync-interface  ens192
tracking-service diameter-endpoint
preempt-delay 5
host 192.169.21.30
  priority 10
!
host 192.169.21.31
  priority 5
!
service Gx
virtual-router-id 70
interface      ens224
service-ip    192.169.23.70
service-port  3868
real-server 192.169.23.13
  weight 100
!
real-server 192.169.23.14
!
!
service Rx
virtual-router-id 71
interface      ens256
service-ip    192.169.28.70
service-port  3668
real-server 192.169.28.13
!
real-server 192.169.28.14
!
!
!

```

Configuration Status Check

To check the distributor status use `show dra-distributor` command.

Example:

```

admin@orchestrator[master-0]# show dra-distributor ?
Possible completions:
  daemon list rate stats
admin@orchestrator[master-0]# show dra-distributor

```

To verify distributor VIPs use `show network ips` command.

To verify director VIP/netfilter rules use the following commands:

```
ip -4 addr show (Confirm VIP address exists)
ip -6 addr show (Confirm VIP address exists)
sudo arptables --list (Confirm rule exist for each vip)
sudo iptables --list (Confirm ipv6 neighbor-solicitation/advertisement filters for each vip)
```

