



IPv6 First-Hop Security Configuration Guide, Cisco IOS XE Fuji 16.7.x

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE SET FORTH IN THE INFORMATION PACKET THAT SHIPPED WITH THE PRODUCT AND ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NON-INFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: <https://www.cisco.com/go/trademarks>. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

© 2018 Cisco Systems, Inc. All rights reserved.



CONTENTS

CHAPTER 1

Read Me First 1

CHAPTER 2

IPv6 RA Guard 3

- Finding Feature Information 3
- Restrictions for IPv6 RA Guard 3
- Information About IPv6 RA Guard 4
 - IPv6 Global Policies 4
 - IPv6 RA Guard 4
- How to Configure IPv6 RA Guard 4
 - Configuring the IPv6 RA Guard Policy on the Device 4
 - Configuring IPv6 RA Guard on an Interface 7
- Configuration Examples for IPv6 RA Guard 8
 - Example: IPv6 RA Guard Configuration 8
 - Example: Configuring IPv6 ND Inspection and RA Guard 8
- Additional References 9
- Feature Information for IPv6 RA Guard 10

CHAPTER 3

IPv6 Snooping 11

- Finding Feature Information 11
- Restrictions for IPv6 Snooping 11
- Information About IPv6 Snooping 12
 - IPv6 Snooping 12
 - IPv6 Device Tracking 12
 - IPv6 First-Hop Security Binding Table 12
 - Recovery Protocols and Prefix Lists 12
 - IPv6 Device Tracking 13
 - IPv6 Address Glean 13
- How to Configure IPv6 Snooping 15

Configuring IPv6 Snooping on an Interface	15
Verifying and Troubleshooting IPv6 ND Inspection	16
Configuring IPv6 Device Tracking	17
Configuring IPv6 First-Hop Security Binding Table Content	17
Configuring the IPv6 First-Hop Security Binding Table Recovery Mechanism	19
Configuring Address Gleaning and Associating Recovery Protocols with Prefix Lists	21
Configuring IPv6 Device Tracking	22
Configuring IPv6 Prefix Glean	23
Configuration Examples for IPv6 Snooping	24
Example: Configuring IPv6 ND Inspection on an Interface	24
Example: Configuring IPv6 Binding Table Content	24
Example: Configuring IPv6 First-Hop Security Binding Table Recovery	24
Example: Configuring Address Gleaning and Associating Recovery Protocols with Prefix Lists	25
Additional References for IPv6 Source Guard and Prefix Guard	25
Feature Information for IPv6 Snooping	26

CHAPTER 4
IPv6 DAD Proxy 29

Finding Feature Information	29
Restrictions for IPv6 DAD Proxy	29
Information About IPv6 DAD Proxy	30
Overview of IPv6 DAD Proxy	30
How to Configure IPv6 DAD Proxy	31
Configuring IPv6 DAD Proxy	31
Configuration Examples for IPv6 DAD Proxy	32
Example: Configuring IPv6 DAD Proxy	32
Additional References for IPv6 DAD Proxy	32
Feature Information for IPv6 DAD Proxy	33

CHAPTER 5
IPv6 Neighbor Discovery Multicast Suppress 35

Finding Feature Information	35
Information About IPv6 Neighbor Discovery Multicast Suppress	36
Overview of IPv6 Neighbor Discovery Multicast Suppress	36
How to Configure IPv6 Neighbor Discovery Multicast Suppress	37

Configuring IPv6 Neighbor Discovery Multicast Suppress on an Interface	37
Configuration Examples for IPv6 Neighbor Discovery Multicast Suppress	38
Example: Configuring IPv6 Neighbor Discovery Suppress on an Interface	38
Additional References for IPv6 Neighbor Discovery Multicast Suppress	38
Feature Information for IPv6 Neighbor Discovery Multicast Suppress	39

CHAPTER 6**DHCP—DHCPv6 Guard 41**

Finding Feature Information	41
Restrictions for DHCPv6 Guard	41
Information About DHCPv6 Guard	42
DHCPv6 Guard Overview	42
How to Configure DHCPv6 Guard	42
Configuring DHCP—DHCPv6 Guard	42
Configuration Examples for DHCPv6 Guard	45
Example: Configuring DHCP—DHCPv6 Guard	45
Additional References	45
Feature Information for DHCP—DHCPv6 Guard	46

CHAPTER 7**IPv6 Source Guard and Prefix Guard 49**

Finding Feature Information	49
Information About IPv6 Source Guard and Prefix Guard	49
IPv6 Source Guard Overview	49
IPv6 Prefix Guard Overview	51
How to Configure IPv6 Source Guard and Prefix Guard	52
Configuring IPv6 Source Guard	52
Configuring IPv6 Source Guard on an Interface	53
Configuring IPv6 Prefix Guard	54
Configuration Examples for IPv6 Source Guard and Prefix Guard	55
Example: Configuring IPv6 Source Guard and Prefix Guard	55
Additional References for IPv6 Source Guard and Prefix Guard	56
Feature Information for IPv6 Source Guard and Prefix Guard	56

CHAPTER 8**IPv6 Destination Guard 59**

Finding Feature Information	59
Prerequisites for IPv6 Destination Guard	59

- Information About IPv6 Destination Guard 60
 - IPv6 Destination Guard Overview 60
- How to Configure the IPv6 Destination Guard 60
 - Configuring IPv6 Destination Guard 60
- Configuration Examples for IPv6 Destination Guard 62
 - Example: Configuring an IPv6 Destination Guard Policy 62
- Additional References 62
- Feature Information for IPv6 Destination Guard 63

CHAPTER 9

IPv6 RFCs 65



Read Me First

Important Information about Cisco IOS XE 16

Effective Cisco IOS XE Release 3.7.0E (for Catalyst Switching) and Cisco IOS XE Release 3.17S (for Access and Edge Routing) the two releases evolve (merge) into a single version of converged release—the Cisco IOS XE 16—providing one release covering the extensive range of access and edge products in the Switching and Routing portfolio.

Feature Information

Use [Cisco Feature Navigator](#) to find information about feature support, platform support, and Cisco software image support. An account on Cisco.com is not required.

Related References

- [Cisco IOS Command References, All Releases](#)

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, using the Cisco Bug Search Tool (BST), submitting a service request, and gathering additional information, see [What's New in Cisco Product Documentation](#).

To receive new and revised Cisco technical content directly to your desktop, you can subscribe to the [What's New in Cisco Product Documentation RSS feed](#). RSS feeds are a free service.



CHAPTER 2

IPv6 RA Guard

The IPv6 RA Guard feature provides support for allowing the network administrator to block or reject unwanted or rogue router advertisement (RA) guard messages that arrive at the network device platform.

- [Finding Feature Information, page 3](#)
- [Restrictions for IPv6 RA Guard, page 3](#)
- [Information About IPv6 RA Guard, page 4](#)
- [How to Configure IPv6 RA Guard, page 4](#)
- [Configuration Examples for IPv6 RA Guard, page 8](#)
- [Additional References, page 9](#)
- [Feature Information for IPv6 RA Guard, page 10](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Restrictions for IPv6 RA Guard

- The IPv6 RA Guard feature does not offer protection in environments where IPv6 traffic is tunneled.
- This feature is supported only in hardware when the ternary content addressable memory (TCAM) is programmed.
- This feature can be configured on a switch port interface in the ingress direction.
- This feature supports host mode and router mode.

- This feature is supported only in the ingress direction; it is not supported in the egress direction.
- This feature is not supported on EtherChannel and EtherChannel port members.
- This feature is not supported on trunk ports with merge mode.
- This feature is supported on auxiliary VLANs and private VLANs (PVLANS). In the case of PVLANS, primary VLAN features are inherited and merged with port features.
- Packets dropped by the IPv6 RA Guard feature can be spanned.
- If the **platform ipv6 acl icmp optimize neighbor-discovery command** is configured, the IPv6 RA Guard feature cannot be configured and an error message will be displayed. This command adds default global Internet Control Message Protocol (ICMP) entries that will override the RA guard ICMP entries.

Information About IPv6 RA Guard

IPv6 Global Policies

IPv6 global policies provide storage and access policy database services. IPv6 ND inspection and IPv6 RA guard are IPv6 global policies features. Every time an ND inspection or RA guard is configured globally, the policy attributes are stored in the software policy database. The policy is then applied to an interface, and the software policy database entry is updated to include this interface to which the policy is applied.

IPv6 RA Guard

The IPv6 RA Guard feature provides support for allowing the network administrator to block or reject unwanted or rogue RA guard messages that arrive at the network device platform. RAs are used by devices to announce themselves on the link. The IPv6 RA Guard feature analyzes these RAs and filters out RAs that are sent by unauthorized devices. In host mode, all RA and router redirect messages are disallowed on the port. The RA guard feature compares configuration information on the Layer 2 (L2) device with the information found in the received RA frame. Once the L2 device has validated the content of the RA frame and router redirect frame against the configuration, it forwards the RA to its unicast or multicast destination. If the RA frame content is not validated, the RA is dropped.

How to Configure IPv6 RA Guard

Configuring the IPv6 RA Guard Policy on the Device

**Note**

When the **ipv6 nd raguard** command is configured on ports, router solicitation messages are not replicated to these ports. To replicate router solicitation messages, all ports that face routers must be set to the router role.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 nd rguard policy *policy-name***
4. **device-role {host | router}**
5. **hop-limit {maximum | minimum *limit*}**
6. **managed-config-flag {on | off}**
7. **match ipv6 access-list *ipv6-access-list-name***
8. **match ra prefix-list *ipv6-prefix-list-name***
9. **other-config-flag {on | off}**
10. **router-preference maximum {high | low | medium}**
11. **trusted-port**
12. **exit**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 nd rguard policy <i>policy-name</i> Example: Device(config)# ipv6 nd rguard policy policy1	Defines the RA guard policy name and enters RA guard policy configuration mode.
Step 4	device-role {host router} Example: Device(config-ra-guard)# device-role router	Specifies the role of the device attached to the port.
Step 5	hop-limit {maximum minimum <i>limit</i>} Example: Device(config-ra-guard)# hop-limit minimum 3	(Optional) Enables verification of the advertised hop count limit. <ul style="list-style-type: none"> • If not configured, this check will be bypassed.

	Command or Action	Purpose
Step 6	managed-config-flag {on off} Example: Device(config-ra-guard)# managed-config-flag on	(Optional) Enables verification that the advertised managed address configuration flag is on. <ul style="list-style-type: none"> • If not configured, this check will be bypassed.
Step 7	match ipv6 access-list <i>ipv6-access-list-name</i> Example: Device(config-ra-guard)# match ipv6 access-list list1	(Optional) Enables verification of the sender's IPv6 address in inspected messages from the configured authorized device source access list. <ul style="list-style-type: none"> • If not configured, this check will be bypassed.
Step 8	match ra prefix-list <i>ipv6-prefix-list-name</i> Example: Device(config-ra-guard)# match ra prefix-list listname1	(Optional) Enables verification of the advertised prefixes in inspected messages from the configured authorized prefix list. <ul style="list-style-type: none"> • If not configured, this check will be bypassed.
Step 9	other-config-flag {on off} Example: Device(config-ra-guard)# other-config-flag on	(Optional) Enables verification of the advertised "other" configuration parameter.
Step 10	router-preference maximum {high low medium} Example: Device(config-ra-guard)# router-preference maximum high	(Optional) Enables verification that the advertised default router preference parameter value is lower than or equal to a specified limit.
Step 11	trusted-port Example: Device(config-ra-guard)# trusted-port	(Optional) Specifies that this policy is being applied to trusted ports. <ul style="list-style-type: none"> • All RA guard policing will be disabled.
Step 12	exit Example: Device(config-ra-guard)# exit	Exits RA guard policy configuration mode and returns to global configuration mode.

Configuring IPv6 RA Guard on an Interface

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface** *type number*
4. **ipv6 nd rguard attach-policy** [*policy-name* [vlan {add | except | none | remove | all} *vlan* [*vlan1*, *vlan2*, *vlan3*...]]]
5. **exit**
6. **show ipv6 nd rguard policy** [*policy-name*]
7. **debug ipv6 snooping rguard** [*filter* | *interface* | *vlanid*]

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	interface <i>type number</i> Example: Device(config)# interface fastethernet 3/13	Specifies an interface type and number, and places the device in interface configuration mode.
Step 4	ipv6 nd rguard attach-policy [<i>policy-name</i> [vlan {add except none remove all} <i>vlan</i> [<i>vlan1</i> , <i>vlan2</i> , <i>vlan3</i> ...]]] Example: Device(config-if)# ipv6 nd rguard attach-policy	Applies the IPv6 RA Guard feature to a specified interface.
Step 5	exit Example: Device(config-if)# exit	Exits interface configuration mode.

	Command or Action	Purpose
Step 6	show ipv6 nd raguard policy [<i>policy-name</i>] Example: Device# show ipv6 nd raguard policy raguard1	Displays the RA guard policy on all interfaces configured with the RA guard.
Step 7	debug ipv6 snooping raguard [<i>filter interface vlanid</i>] Example: Device# debug ipv6 snooping raguard	Enables debugging for IPv6 RA guard snooping information.

Configuration Examples for IPv6 RA Guard

Example: IPv6 RA Guard Configuration

```

Device(config)# interface fastethernet 3/13

Device(config-if)# ipv6 nd raguard attach-policy

Device# show running-config interface fastethernet 3/13

Building configuration...
Current configuration : 129 bytes
!
interface FastEthernet3/13
 switchport
 switchport access vlan 222
 switchport mode access
 access-group mode prefer port
 ipv6 nd raguard
end

```

Example: Configuring IPv6 ND Inspection and RA Guard

This example provides information about an interface on which both the Neighbor Discovery Inspection and RA Guard features are configured:

```

Device# show ipv6 snooping capture-policy interface ethernet 0/0

Hardware policy registered on Ethernet 0/0
Protocol Protocol value Message Value Action Feature
ICMP 58 RS 85 punt RA Guard
punt ND Inspection
ICMP 58 RA 86 drop RA guard
punt ND Inspection
ICMP 58 NS 87 punt ND Inspection
ICM 58 NA 88 punt ND Inspection

```

ICMP 58 REDIR 89 drop RA Guard
punt ND Inspection

Additional References

Related Documents

Related Topic	Document Title
IPv6 addressing and connectivity	<i>IPv6 Configuration Guide</i>
Cisco IOS commands	Cisco IOS Master Commands List, All Releases
IPv6 commands	<i>Cisco IOS IPv6 Command Reference</i>
Cisco IOS IPv6 features	Cisco IOS IPv6 Feature Mapping

Standards and RFCs

Standard/RFC	Title
RFCs for IPv6	<i>IPv6 RFCs</i>

MIBs

MIB	MIBs Link
No new or modified MIBs are supported by this feature, and support for existing MIBs has not been modified by this feature.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for IPv6 RA Guard

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 1: Feature Information for IPv6 RA Guard

Feature Name	Releases	Feature Information
IPv6 RA Guard	12.2(33)SX14 12.2(50)SY 12.2(54)SG 15.0(2)SE 15.0(2)SG Cisco IOS XE Release 3.8S Cisco IOS XE Release 3.2SE Cisco IOS XE Release 3.2SG	The IPv6 RA Guard feature provides support for allowing the network administrator to block or reject unwanted or rogue router advertisement (RA) guard messages that arrive at the network device platform. The following commands were introduced or modified: debug ipv6 snooping raguard , device-role , hop-limit , ipv6 nd raguard attach-policy , ipv6 nd raguard policy , managed-config-flag , match ipv6 access-list , match ra prefix-list , other-config-flag , router-preference maximum , show ipv6 nd raguard policy .



IPv6 Snooping

The IPv6 Snooping feature bundles several Layer 2 IPv6 first-hop security features, including IPv6 neighbor discovery inspection, IPv6 device tracking, IPv6 address glean, and IPv6 binding table recovery, to provide security and scalability. IPv6 ND inspection operates at Layer 2, or between Layer 2 and Layer 3, to provide IPv6 functions with security and scalability.

- [Finding Feature Information, page 11](#)
- [Restrictions for IPv6 Snooping, page 11](#)
- [Information About IPv6 Snooping, page 12](#)
- [How to Configure IPv6 Snooping, page 15](#)
- [Configuration Examples for IPv6 Snooping, page 24](#)
- [Additional References for IPv6 Source Guard and Prefix Guard, page 25](#)
- [Feature Information for IPv6 Snooping, page 26](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Restrictions for IPv6 Snooping

The IPv6 snooping feature is not supported on Etherchannel ports.

Information About IPv6 Snooping

IPv6 Snooping

The IPv6 Snooping feature bundles several Layer 2 IPv6 first-hop security features, including IPv6 Address Glean and IPv6 Device Tracking. The feature operates at Layer 2, or between Layer 2 and Layer 3, and provides IPv6 features with security and scalability. This feature mitigates some of the inherent vulnerabilities for the neighbor discovery mechanism, such as attacks on duplicate address detection (DAD), address resolution, device discovery, and the neighbor cache.

IPv6 Snooping learns and secures bindings for stateless autoconfiguration addresses in Layer 2 neighbor tables and analyzes ND messages in order to build a trusted binding table. IPv6 ND messages that do not have valid bindings are dropped. An ND message is considered trustworthy if its IPv6-to-MAC mapping is verifiable.

When IPv6 Snooping is configured on a target (which varies depending on platform target support and may include device ports, switch ports, Layer 2 interfaces, Layer 3 interfaces, and VLANs), capture instructions are downloaded to the hardware to redirect the ND protocol and Dynamic Host Configuration Protocol (DHCP) for IPv6 traffic up to the switch integrated security features (SISF) infrastructure in the routing device. For ND traffic, messages such as NS, NA, RS, RA, and REDIRECT are directed to SISF. For DHCP, UDP messages sourced from port 546 or 547 are redirected.

IPv6 Snooping registers its "capture rules" to the classifier, which aggregates all rules from all features on a given target and installs the corresponding ACL down into the platform-dependent modules. Upon receiving redirected traffic, the classifier calls all entry points from any registered feature (for the target on which the traffic is being received), including the IPv6 snooping entry point. This entry point is the last to be called, so any decision (such as drop) made by another feature supersedes the IPv6 Snooping decision.

IPv6 Device Tracking

IPv6 device tracking provides IPv6 host liveness tracking so that a neighbor table can be immediately updated when an IPv6 host disappears.

IPv6 First-Hop Security Binding Table

The IPv6 First-Hop Security Binding Table recovery mechanism feature enables the binding table to recover in the event of a device reboot. A database table of IPv6 neighbors connected to the device is created from information sources such as ND snooping. This database, or binding, table is used by various IPv6 guard features to validate the link-layer address (LLA), the IPv4 or IPv6 address, and prefix binding of the neighbors to prevent spoofing and redirect attacks.

This mechanism enables the binding table to recover in the event of a device reboot. The recovery mechanism will block any data traffic sourced from an unknown source; that is, a source not already specified in the binding table and previously learned through ND or DHCP gleaning. This feature recovers the missing binding table entries when the resolution for a destination address fails in the destination guard. When a failure occurs, a binding table entry is recovered by querying the DHCP server or the destination host, depending on the configuration.

Recovery Protocols and Prefix Lists

The IPv6 First-Hop Security Binding Table Recovery Mechanism feature introduces the capability to provide a prefix list that is matched before the recovery is attempted for both DHCP and NDP.

If an address does not match the prefix list associated with the protocol, then the recovery of the binding table entry will not be attempted with that protocol. The prefix list should correspond to the prefixes that are valid for address assignment in the Layer 2 domain using the protocol. The default is that there is no prefix list, in which case the recovery is attempted for all addresses. The command to associate a prefix list to a protocol is **protocol {dhcp | ndp} [prefix-list *prefix-list-name*]**.

IPv6 Device Tracking


IPv6 device tracking provides IPv6 host liveness tracking so that a neighbor table can be immediately updated when an IPv6 host disappears.

IPv6 Address Glean

IPv6 address glean is the foundation for many other IPv6 features that depend on an accurate binding table. It inspects ND and DHCP messages on a link to glean addresses, and then populates the binding table with these addresses. This feature also enforces address ownership and limits the number of addresses any given node is allowed to claim.

The following figure shows how IPv6 address glean works.

Figure 1: IPv6 Address Glean



How to Configure IPv6 Snooping

Configuring IPv6 Snooping on an Interface

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 snooping policy** *snooping-policy*
4. **exit**
5. **interface** *type number*
6. **ipv6 snooping attach-policy** *snooping-policy*

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 snooping policy <i>snooping-policy</i> Example: Device(config)# ipv6 snooping policy policy1	Configures an IPv6 snooping policy and enters IPv6 snooping configuration mode.
Step 4	exit Example: Device(config-ipv6-snooping)# exit	Exits IPv6 snooping configuration mode.
Step 5	interface <i>type number</i> Example: Device(config)# interface Gigabitethernet 0/0/1	Enters interface configuration mode.

	Command or Action	Purpose
Step 6	ipv6 snooping attach-policy <i>snooping-policy</i> Example: Device(config-if)# ipv6 snooping attach-policy policy1	Attaches the IPv6 snooping policy to the interface.

Verifying and Troubleshooting IPv6 ND Inspection

SUMMARY STEPS

1. enable
2. show ipv6 snooping capture-policy [interface type number]
3. show ipv6 snooping counter [interface type number]
4. show ipv6 snooping features
5. show ipv6 snooping policies [interface type number]
6. debug ipv6 snooping

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	show ipv6 snooping capture-policy [interface type number] Example: Device# show ipv6 snooping capture-policy interface ethernet 0/0	Displays snooping ND message capture policies.
Step 3	show ipv6 snooping counter [interface type number] Example: Device# show ipv6 snooping counter interface FastEthernet 4/12	Displays information about the packets counted by the interface counter.

	Command or Action	Purpose
Step 4	show ipv6 snooping features Example: Device# show ipv6 snooping features	Displays information about snooping features configured on the device.
Step 5	show ipv6 snooping policies [interface type number] Example: Device# show ipv6 snooping policies	Displays information about the configured policies and the interfaces to which they are attached.
Step 6	debug ipv6 snooping Example: Device# debug ipv6 snooping	Enables debugging for snooping information in IPv6.

Configuring IPv6 Device Tracking

Configuring IPv6 First-Hop Security Binding Table Content

SUMMARY STEPS

1. enable
2. configure terminal
3. ipv6 neighbor binding {ipv6-address | ipv6-prefix} interface type number [hardware-address | mac-address][tracking [disable | enable | retry-interval value] | reachable-lifetime value]
4. ipv6 neighbor binding max-entries entries
5. ipv6 neighbor binding logging
6. exit
7. show ipv6 neighbor binding

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.

	Command or Action	Purpose
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 neighbor binding { <i>ipv6-address</i> <i>ipv6-prefix</i> } interface <i>type number</i> [<i>hardware-address</i> <i>mac-address</i>][tracking [disable enable retry-interval <i>value</i>] reachable-lifetime <i>value</i>] Example: Device(config)# ipv6 neighbor binding 2001:DB8:0:ABCD::1 interface GigabitEthernet 0/0/1 reachable-lifetime 100	Adds a static entry to the binding table database.
Step 4	ipv6 neighbor binding max-entries <i>entries</i> Example: Device(config)# ipv6 neighbor binding max-entries 100	Specifies the maximum number of entries that are allowed to be inserted in the binding table cache.
Step 5	ipv6 neighbor binding logging Example: Device(config)# ipv6 neighbor binding logging	Enables the logging of binding table main events.
Step 6	exit Example: Device(config)# exit	Exits global configuration mode and enters privileged EXEC mode.
Step 7	show ipv6 neighbor binding Example: Device# show ipv6 neighbor binding	Displays the contents of a binding table.

Configuring the IPv6 First-Hop Security Binding Table Recovery Mechanism

SUMMARY STEPS

1. enable
2. configure terminal
3. ipv6 neighbor binding *ipv6-address* interface *type number*
4. ipv6 prefix-list *list-name* permit *ipv6-prefix/prefix-length* ge *ge-value*
5. ipv6 snooping policy *snooping-policy-id*
6. destination-glean {recovery | log-only} [dhcp]
7. data-glean {recovery | log-only} [ndp | dhcp]
8. prefix-glean
9. protocol dhcp [prefix-list *prefix-list-name*]
10. exit
11. ipv6 destination-guard policy *policy-name*
12. enforcement {always | stressed}
13. exit
14. interface *type number*
15. ipv6 snooping attach-policy *snooping-policy*
16. ipv6 destination-guard attach-policy *policy-name*
17. end

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 neighbor binding <i>ipv6-address</i> interface <i>type number</i> Example: Device(config)# ipv6 neighbor binding 2001:db8::1 interface GigabitEthernet3/0/1	Adds a static entry to the binding table database.

	Command or Action	Purpose
Step 4	<p>ipv6 prefix-list <i>list-name</i> permit <i>ipv6-prefix/prefix-length ge ge-value</i></p> <p>Example:</p> <pre>Device(config)# ipv6 prefix-list abc permit 2001:DB8::/64 ge 128</pre>	Creates an entry in an IPv6 prefix list.
Step 5	<p>ipv6 snooping policy <i>snooping-policy-id</i></p> <p>Example:</p> <pre>Device(config)# ipv6 snooping policy xyz</pre>	Enters IPv6 snooping configuration mode and allows you to modify the configuration of the snooping policy specified.
Step 6	<p>destination-glean {recovery log-only} [dhcp]</p> <p>Example:</p> <pre>Device(config-ipv6-snooping)# destination-glean recovery dhcp</pre>	Specifies that destination addresses should be recovered from DHCP. Note If logging (without recovery) is required, use the destination-glean log-only command.
Step 7	<p>data-glean {recovery log-only} [ndp dhcp]</p> <p>Example:</p> <pre>Device(config-ipv6-snooping)# data-glean recovery ndp</pre>	Enables IPv6 first-hop security binding table recovery using source (or “data”) address gleaning. Note If logging (without recovery) is required, use the data-glean log-only command.
Step 8	<p>prefix-glean</p> <p>Example:</p> <pre>Device(config-ipv6-snooping)# prefix-glean</pre>	Enables the device to glean prefixes from IPv6 router advertisements (RAs) or Dynamic Host Configuration protocol (DHCP)
Step 9	<p>protocol dhcp [prefix-list <i>prefix-list-name</i>]</p> <p>Example:</p> <pre>Device(config-ipv6-snooping)# protocol dhcp prefix-list abc</pre>	(Optional) Specifies that addresses should be gleaned with DHCP and associates the protocol with a specific IPv6 prefix list.
Step 10	<p>exit</p> <p>Example:</p> <pre>Device(config-ipv6-snooping)# exit</pre>	Exits IPv6 snooping configuration mode and returns to global configuration mode.
Step 11	<p>ipv6 destination-guard policy <i>policy-name</i></p> <p>Example:</p> <pre>Device(config)# ipv6 destination-guard policy xyz</pre>	(Optional) Enters destination guard configuration mode and allows you to modify the configuration of the specified destination guard policy.

	Command or Action	Purpose
Step 12	enforcement {always stressed} Example: Device(config-destguard)# enforcement stressed	Sets the enforcement level of the policy to be either enforced under all conditions or only when the system is under stress.
Step 13	exit Example: Device(config-destguard)# exit	Exits destination guard configuration mode and returns to global configuration mode.
Step 14	interface <i>type number</i> Example: Device(config)# interface GigabitEthernet 0/0/1	Enters interface configuration mode.
Step 15	ipv6 snooping attach-policy <i>snooping-policy</i> Example: Device(config-if)# ipv6 snooping attach-policy xyz	Attaches the IPv6 snooping policy to the interface.
Step 16	ipv6 destination-guard attach-policy <i>policy-name</i> Example: Device(config-if)# ipv6 destination-guard attach-policy xyz	Attaches the destination guard policy to the specified interface. Note For information about how to configure an IPv6 destination guard policy, see the “IPv6 Destination Guard” module.
Step 17	end Example: Device(config-if)# end	Exits interface configuration mode and returns to privileged EXEC mode.

Configuring Address Gleaning and Associating Recovery Protocols with Prefix Lists

SUMMARY STEPS

1. enable
2. configure terminal
3. ipv6 snooping policy *snooping-policy-id*
4. protocol {dhcp | ndp} [**prefix-list** *prefix-list-name*]
5. end

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 snooping policy <i>snooping-policy-id</i> Example: Device(config)# ipv6 snooping policy 200	Enters IPv6 snooping configuration mode and allows you to modify the configuration of the snooping policy specified.
Step 4	protocol {dhcp ndp} [prefix-list <i>prefix-list-name</i>] Example: Device(config-ipv6-snooping)# protocol dhcp prefix-list dhcp_prefix_list	Specifies that address should be gleaned with dynamic Host Configuration Protocol (DHCP) and associates a recovery protocol (DHCP) with the prefix list.
Step 5	end Example: Device(config-ipv6-snooping)# end	Exits IPv6 snooping configuration mode and returns to privileged EXEC mode.

Configuring IPv6 Device Tracking

Perform this task to provide fine tuning for the life cycle of an entry in the binding table for the IPv6 Device Tracking feature. For IPv6 device tracking to work, the binding table needs to be populated.

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 neighbor tracking [retry-interval *value*]**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 neighbor tracking [retry-interval value] Example: Device(config)# ipv6 neighbor tracking	Tracks entries in the binding table.

Configuring IPv6 Prefix Glean

SUMMARY STEPS

1. enable
2. configure terminal
3. ipv6 snooping policy *snooping-policy*
4. prefix-glean [only]

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.

	Command or Action	Purpose
Step 3	ipv6 snooping policy <i>snooping-policy</i> Example: Device(config)# ipv6 snooping policy policy1	Configures an IPv6 snooping policy and enters IPv6 snooping policy configuration mode.
Step 4	prefix-glean [only] Example: Device(config-ipv6-snooping)# prefix-glean	Enables the device to glean prefixes from IPv6 RAs or DHCPv6 traffic.

Configuration Examples for IPv6 Snooping

Example: Configuring IPv6 ND Inspection on an Interface

```

Device(config)# ipv6 snooping policy policy1
Device(config-ipv6-snooping)# exit
Device(config)# interface GigabitEthernet 0/0/1
Device(config-if)# ipv6 snooping attach-policy policy1
.
.
.
Device# show ipv6 snooping policies interface gigabitEthernet 0/0/1
Target          Type Policy          Feature          Target range
Gi0/0/1         PORT my_policy        Destination Gu   vlan all
Gi0/0/1         PORT policy1      Snooping         vlan all

```

Example: Configuring IPv6 Binding Table Content

```

Device(config)# ipv6 neighbor binding 2001:DB8:0:ABCD::1 interface GigabitEthernet 0/0/1
reachable-lifetime 100
Device(config)# ipv6 neighbor binding max-entries 100
Device(config)# ipv6 neighbor binding logging
Device(config)# exit

```

Example: Configuring IPv6 First-Hop Security Binding Table Recovery

```

Device> enable
Device# configure terminal
Device(config)# ipv6 neighbor binding 2001:db8::1 interface GigabitEthernet3/0/1
Device(config)# ipv6 prefix-list abc permit 2001:DB8::/64 ge 128
Device(config)# ipv6 snooping policy xyz
Device(config-ipv6-snooping)# destination-glean recovery dhcp
Device(config-ipv6-snooping)# data-glean recovery ndp
Device(config-ipv6-snooping)# prefix-glean
Device(config-ipv6-snooping)# protocol dhcp prefix-list abc
Device(config-ipv6-snooping)# exit
Device(config)# ipv6 destination-guard policy xyz
Device(config-destguard)# enforcement stressed

```

```

Device(config-destguard)# exit
Device(config)# interface GigabitEthernet 0/0/1
Device(config-if)# ipv6 snooping attach-policy xyz
Device(config-if)# ipv6 destination-guard attach-policy xyz
Device(config-if)# end

```

Example: Configuring Address Gleaning and Associating Recovery Protocols with Prefix Lists

The following example shows that NDP will be used for the recovery for all addresses and that DHCP will be used to recover addresses that match the prefix list called `dhcp_prefix_list`:

```

Device(config-ipv6-snooping)# protocol ndp
Device(config-ipv6-snooping)# protocol dhcp prefix-list dhcp_prefix_list

```

Additional References for IPv6 Source Guard and Prefix Guard

Related Documents

Related Topic	Document Title
IPv6 addressing and connectivity	<i>IPv6 Configuration Guide</i>
IPv4 addressing	<i>IP Addressing: IPv4 Addressing Configuration Guide</i>
Cisco IOS commands	Cisco IOS Master Command List, All Releases
IPv6 commands	<i>Cisco IOS IPv6 Command Reference</i>
Cisco IOS IPv6 features	Cisco IOS IPv6 Feature Mapping

Standards and RFCs

Standard/RFC	Title
RFCs for IPv6	<i>IPv6 RFCs</i>

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for IPv6 Snooping

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 2: Feature Information for IPv6 Snooping

Feature Name	Releases	Feature Information
IPv6 Snooping	12.2(50)SY 15.0(1)SY 15.0(2)SE 15.1(2)SG 15.3(1)S Cisco IOS XE Release 3.2SE Cisco IOS XE Release 3.8S Cisco IOS XE Release 3.9S Cisco IOS Release 15.2(1)E	<p>IPv6 snooping bundles several Layer 2 IPv6 first-hop security features, including IPv6 ND inspection, IPv6 device tracking, IPv6 address glean, and IPv6 first-hop security binding table recovery, to provide security and scalability. IPv6 snooping operates at Layer 2, or between Layer 2 and Layer 3, to provide IPv6 functions with security and scalability.</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco CSR 1000V and the Cisco ASR 1000 Series Routers.</p> <p>The following commands were introduced or modified: data-glean, debug ipv6 snooping, destination-glean, device-role, drop-unsecure, ipv6 nd inspection, ipv6 nd inspection policy, ipv6 neighbor binding logging, ipv6 neighbor binding max-entries, ipv6 neighbor binding vlan, ipv6 neighbor tracking, ipv6 snooping attach-policy, ipv6 snooping policy, prefix-glean, protocol (IPv6), sec-level minimum, show ipv6 neighbor binding, show ipv6 snooping capture-policy, show ipv6 snooping counters, show ipv6 snooping features, show ipv6 snooping policies, tracking, trusted-port.</p>



IPv6 DAD Proxy

IPv6 Duplicate Address Detection (DAD) Proxy feature responds to the DAD queries on behalf of a node that owns the queried address. It is useful in environments where nodes cannot communicate directly on the link.

- [Finding Feature Information, page 29](#)
- [Restrictions for IPv6 DAD Proxy, page 29](#)
- [Information About IPv6 DAD Proxy, page 30](#)
- [How to Configure IPv6 DAD Proxy, page 31](#)
- [Configuration Examples for IPv6 DAD Proxy, page 32](#)
- [Additional References for IPv6 DAD Proxy, page 32](#)
- [Feature Information for IPv6 DAD Proxy, page 33](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Restrictions for IPv6 DAD Proxy

- The IPv6 Duplicate Address Detection (DAD) Proxy feature is not supported on Etherchannel ports.

Information About IPv6 DAD Proxy


Overview of IPv6 DAD Proxy

The IPv6 Duplicate Address Detection (DAD) feature ensures that all the IP addresses assigned on a particular segment are unique. The process operates when IPv6 hosts directly communicate with one another where hosts cannot communicate directly, and a proxy is required.

After a host verifies that its address is unique, it enables the DAD procedure. However, when two hosts cannot communicate with each other, this procedure cannot detect a duplicate address. If the DAD procedure cannot run, both the hosts assigns the same link-local address, which causes both hosts to fail when they try to reach the Dynamic Host Configuration Protocol version 6 (DHCPv6) server. The IPv6 DAD Proxy feature responds on behalf of the address owner when an address is in use.

The following figure provides an overview of the IPv6 DAD Proxy feature:

Figure 2: IPv6 DAD Proxy



3386590

How to Configure IPv6 DAD Proxy

Configuring IPv6 DAD Proxy

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **interface** *type number*
4. **[no] ipv6 nd dad-proxy**
5. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	interface <i>type number</i> Example: Device(config)# interface GigabitEthernet 0/0/1	Specifies an interface type and number, and enters interface configuration mode.
Step 4	[no] ipv6 nd dad-proxy Example: Device(config-if)# ipv6 nd dad-proxy	Specifies if the ND suppress must operate in DAD-proxy mode. In this mode, the DAD messages are not forwarded. They respond to an existing entry or are added to the binding table.
Step 5	end Example: Device(config-if)# end	Exits router interface configuration mode and returns to privileged EXEC mode.

Configuration Examples for IPv6 DAD Proxy

Example: Configuring IPv6 DAD Proxy

```
Device> enable
Device# configure terminal
Device(config)# interface Ethernet 0/0
Device(config-if)# ipv6 nd dad-proxy
Device(config-if)# end
```

Additional References for IPv6 DAD Proxy

Related Documents

Related Topic	Document Title
IPv6 addressing and connectivity	<i>IPv6 Configuration Guide</i>
Cisco IOS commands	Cisco IOS Master Commands List, All Releases
IPv6 commands	<i>Cisco IOS IPv6 Command Reference</i>
Cisco IOS IPv6 features	Cisco IOS IPv6 Feature Mapping

MIBs

MIB	MIBs Link
	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for IPv6 DAD Proxy

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 3: Feature Information for IPv6 DAD Proxy

Feature Name	Releases	Feature Information
IPv6 DAD Proxy	Cisco IOS XE Release 3.8S Cisco IOS XE Release 3SE Cisco IOS XE Release 3.9S	IPv6 Duplicate Address Detection (DAD) Proxy feature responds to the DAD queries on behalf of a node that owns the queried address. It is useful in environments where nodes cannot communicate directly on the link. The following commands were introduced or modified: ipv6 nd dad-proxy , mode dad-proxy , mode md-proxy .



CHAPTER

5

IPv6 Neighbor Discovery Multicast Suppress

IPv6 Neighbor Discovery (ND) Multicast Suppress suppresses the ND multicast Neighbor Solicit (NS) messages, by either dropping it (and responding to solicitations on behalf of the targets) or converting it into unicast traffic. The conversion of multicast traffic into unicast traffic is performed by replacing a Layer-2 Multicast Destination MAC with a Layer-2 Unicast Destination MAC. This requires the knowledge of addresses on the link and their binding to the Layer-2. The multicast messages suppressed are Neighbor Solicitation (NS) messages.

- [Finding Feature Information, page 35](#)
- [Information About IPv6 Neighbor Discovery Multicast Suppress, page 36](#)
- [How to Configure IPv6 Neighbor Discovery Multicast Suppress, page 37](#)
- [Configuration Examples for IPv6 Neighbor Discovery Multicast Suppress, page 38](#)
- [Additional References for IPv6 Neighbor Discovery Multicast Suppress, page 38](#)
- [Feature Information for IPv6 Neighbor Discovery Multicast Suppress, page 39](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.


Information About IPv6 Neighbor Discovery Multicast Suppress

Overview of IPv6 Neighbor Discovery Multicast Suppress

The IPv6 Neighbor Discovery (ND) multicast suppress feature stops the ND multicast Neighbor Solicit (NS) messages by dropping them (and responding to solicitations on behalf of the targets) or by converting them into unicast traffic. This feature reduces the amount of control traffic necessary for proper link operations.

When an address is inserted into the binding table, an address resolution request sent to a multicast address is intercepted, and the device either responds on behalf of the address owner or converts the request into a unicast message and forwards it to its destination.

The following figure provides an overview of this feature:



How to Configure IPv6 Neighbor Discovery Multicast Suppress

Configuring IPv6 Neighbor Discovery Multicast Suppress on an Interface

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 nd suppress policy *policy-name***
4. **[no] mode mc-proxy**
5. **[no] mode full-proxy**
6. **end**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 nd suppress policy <i>policy-name</i> Example: Device (config)# ipv6 nd suppress policy policy1 Device (config-nd-suppress)#	Specifies a name for the Neighbor Discovery (ND) suppress policy to be configured.
Step 4	[no] mode mc-proxy Example: Device (config-nd-suppress)# mode mc-proxy	Specifies if the ND suppress must proxy all multicast Neighbor Solicitation (NS) messages.
Step 5	[no] mode full-proxy Example: Device (config-nd-suppress)# mode full-proxy	Specifies if the ND suppress must proxy both unicast and multicast NS messages.

	Command or Action	Purpose
Step 6	end Example: Device (config-nd-suppress)# end	Exits the ND suppress mode and returns to privileged EXEC mode.

Configuration Examples for IPv6 Neighbor Discovery Multicast Suppress

Example: Configuring IPv6 Neighbor Discovery Suppress on an Interface

```
Device> enable
Device(config)# interface Ethernet 0/0
Device(config-if)# ipv6 nd suppress attach-policy policy1
```

Additional References for IPv6 Neighbor Discovery Multicast Suppress

Related Documents

Related Topic	Document Title
IPv6 addressing and connectivity	<i>IPv6 Configuration Guide</i>
Cisco IOS commands	Cisco IOS Master Commands List, All Releases
IPv6 commands	<i>Cisco IOS IPv6 Command Reference</i>
Cisco IOS IPv6 features	Cisco IOS IPv6 Feature Mapping

MIBs

MIB	MIBs Link
	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for IPv6 Neighbor Discovery Multicast Suppress

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 4: Feature Information for IPv6 Neighbor Discovery Multicast Suppress

Feature Name	Releases	Feature Information
IPv6 Neighbor Discovery Multicast Suppress with DAD Proxy	Cisco IOS XE Release 3.8S Cisco IOS XE Release 3.9S	<p>IPv6 Duplicate Address Detection (DAD) Proxy feature responds to the DAD queries on behalf of a node that owns the queried address. It is useful in environments where nodes cannot communicate directly on the link.</p> <p>The following commands were introduced or modified: ipv6 nd dad-proxy, mode dad-proxy, mode md-proxy.</p>



CHAPTER 6

DHCP—DHCPv6 Guard

This module describes the Dynamic Host Configuration Protocol version 6 (DHCPv6) Guard feature. This feature blocks DHCP reply and advertisement messages that originate from unauthorized DHCP servers and relay agents that forward DHCP packets from servers to clients. Client messages or messages sent by relay agents from clients to servers are not blocked. The filtering decision is determined by the device role assigned to the receiving switch port, trunk, or VLAN. In addition, to provide a finer level of filter granularity, messages can be filtered based on the address of the sending server or relay agent, or by the prefixes and addresses ranges listed in the reply message. This functionality helps to prevent traffic redirection or denial of service (DoS).

- [Finding Feature Information, page 41](#)
- [Restrictions for DHCPv6 Guard, page 41](#)
- [Information About DHCPv6 Guard, page 42](#)
- [How to Configure DHCPv6 Guard, page 42](#)
- [Configuration Examples for DHCPv6 Guard, page 45](#)
- [Additional References, page 45](#)
- [Feature Information for DHCP—DHCPv6 Guard, page 46](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Restrictions for DHCPv6 Guard

- The DHCPv6 guard feature is not supported on Etherchannel ports.

Information About DHCPv6 Guard

DHCPv6 Guard Overview

The DHCPv6 Guard feature blocks reply and advertisement messages that come from unauthorized DHCP servers and relay agents.

Packets are classified into one of the three DHCP type messages. All client messages are always switched regardless of device role. DHCP server messages are only processed further if the device role is set to server. Further processing of server messages includes DHCP server advertisements (for source validation and server preference) and DHCP server replies (for permitted prefixes).

If the device is configured as a DHCP server, all the messages need to be switched, regardless of the device role configuration.

How to Configure DHCPv6 Guard

Configuring DHCP—DHCPv6 Guard

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 access-list** *access-list-name*
4. **permit host** *address* **any**
5. **exit**
6. **ipv6 prefix-list** *list-name* **permit** *ipv6-prefix* **128**
7. **ipv6 dhcp guard policy** *policy-name*
8. **device-role** {*client* | *server*}
9. **match server access-list** *ipv6-access-list-name*
10. **match reply prefix-list** *ipv6-prefix-list-name*
11. **preference min** *limit*
12. **preference max** *limit*
13. **trusted-port**
14. **exit**
15. **interface** *type number*
16. **switchport**
17. **exit**
18. **exit**
19. **show ipv6 dhcp guard policy** [*policy-name*]

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 access-list <i>access-list-name</i> Example: Device(config)# ipv6 access-list acl1	Defines the IPv6 access list and enters IPv6 access list configuration mode.
Step 4	permit host <i>address any</i> Example: Device(config-ipv6-acl)# permit host FE80::A8BB:CCFF:FE01:F700 any	Sets the conditions in the named IP access list.
Step 5	exit Example: Device(config-ipv6-acl)# exit	Exits IPv6 access list configuration mode and returns to global configuration mode.
Step 6	ipv6 prefix-list <i>list-name permit ipv6-prefix 128</i> Example: Device(config)# ipv6 prefix-list abc permit 2001:0DB8::/64 le 128	Creates an entry in an IPv6 prefix list.
Step 7	ipv6 dhcp guard policy <i>policy-name</i> Example: Device(config)# ipv6 dhcp guard policy poll	Defines the DHCPv6 guard policy name and enters DHCP guard configuration mode.
Step 8	device-role {client server} Example: Device(config-dhcp-guard)# device-role server	Specifies the device role of the device attached to the target (interface or VLAN).

	Command or Action	Purpose
Step 9	match server access-list <i>ipv6-access-list-name</i> Example: <pre>Device(config-dhcp-guard)# match server access-list acl1</pre>	(Optional) Enables verification of the advertised DHCP server and relay address in inspected messages from the configured authorized server access list. If not configured, this check will be bypassed. An empty access list is treated as a permit.
Step 10	match reply prefix-list <i>ipv6-prefix-list-name</i> Example: <pre>Device(config-dhcp-guard)# match reply prefix-list abc</pre>	(Optional) Enables verification of the advertised prefixes in DHCP reply messages from the configured authorized prefix list. If not configured, this check will be bypassed. An empty prefix list is treated as a permit.
Step 11	preference min <i>limit</i> Example: <pre>Device(config-dhcp-guard)# preference min 0</pre>	(Optional) Enables verification that the advertised preference (in preference option) is greater than the specified limit. If not specified, this check will be bypassed.
Step 12	preference max <i>limit</i> Example: <pre>Device(config-dhcp-guard)# preference max 255</pre>	(Optional) Enables verification that the advertised preference (in preference option) is less than the specified limit. If not specified, this check will be bypassed.
Step 13	trusted-port Example: <pre>Device(config-dhcp-guard)# trusted-port</pre>	(Optional) Specifies that this policy is being applied to trusted ports. All DHCP guard policing will be disabled.
Step 14	exit Example: <pre>Device(config-dhcp-guard)# exit</pre>	Exits DHCP guard configuration mode and returns to global configuration mode.
Step 15	interface <i>type number</i> Example: <pre>Device(config)# interface GigabitEthernet 0/2/0</pre>	Specifies an interface and enters interface configuration mode.
Step 16	switchport Example: <pre>Device(config-if)# switchport</pre>	Puts an interface that is in Layer 3 mode into Layer 2 mode for Layer 2 configuration.

	Command or Action	Purpose
Step 17	exit Example: Device(config-if)# exit	Exits interface configuration mode and returns to global configuration mode.
Step 18	exit Example: Device(config)# exit	Exits global configuration mode and returns to privileged EXEC mode.
Step 19	show ipv6 dhcp guard policy [<i>policy-name</i>] Example: Device# show ipv6 dhcp policy guard poll	(Optional) Displays the policy configuration as well as all the interfaces where the policy is applied.

Configuration Examples for DHCPv6 Guard

Example: Configuring DHCP—DHCPv6 Guard

The following example displays a sample configuration for DHCPv6 Guard:

Additional References

Related Documents

Related Topic	Document Title
Cisco IOS commands	Cisco IOS Master Commands List, All Releases
DHCP commands: complete command syntax, command modes, command history, defaults, usage guidelines, and examples	<i>Cisco IOS IP Addressing Services Command Reference</i>
DHCP conceptual and configuration information	<i>Cisco IOS IP Addressing Services Configuration Guide</i>

Standards/RFCs

Standard	Title
No new or modified standards/RFCs are supported by this feature.	—

MIBs

MIB	MIBs Link
No new or modified MIBs are supported by this feature.	To locate and download MIBs for selected platforms, Cisco IOS releases, and feature sets, use Cisco MIB Locator found at the following URL: http://www.cisco.com/go/mibs

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for DHCP—DHCPv6 Guard

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 5: Feature Information for DHCP—DHCPv6 Guard

Feature Name	Releases	Feature Information
DHCP—DHCPv6 Guard	Cisco IOS XE Release 3.8S	<p>The DHCP—DHCPv6 Guard feature blocks DHCP reply and advertisement messages that originate from unauthorized DHCP servers and relay agents that forward DHCP packets from servers to clients. Client messages or messages sent by relay agents from clients to servers are not blocked.</p> <p>The following commands were introduced or modified: device-role , ipv6 dhcp guard attach-policy (DHCPv6 Guard), ipv6 dhcp guard policy, match reply prefix-list, match server access-list, preference (DHCPv6 Guard), show ipv6 dhcp guard policy, trusted-port (DHCPv6 Guard).</p>



CHAPTER

7

IPv6 Source Guard and Prefix Guard

IPv6 Source Guard and IPv6 Prefix Guard are Layer 2 snooping features that validate the source of IPv6 traffic. IPv6 Source Guard blocks any data traffic from an unknown source. For example, one that is not already populated in the binding table or previously learned through Neighbor Discovery (ND) or Dynamic Host Configuration Protocol (DHCP) gleaning. IPv6 Prefix Guard prevents home-node sourcing traffic outside of the authorized and delegated traffic.

- [Finding Feature Information, page 49](#)
- [Information About IPv6 Source Guard and Prefix Guard, page 49](#)
- [How to Configure IPv6 Source Guard and Prefix Guard, page 52](#)
- [Configuration Examples for IPv6 Source Guard and Prefix Guard, page 55](#)
- [Additional References for IPv6 Source Guard and Prefix Guard, page 56](#)
- [Feature Information for IPv6 Source Guard and Prefix Guard, page 56](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Information About IPv6 Source Guard and Prefix Guard

IPv6 Source Guard Overview


IPv6 source guard is an interface feature between the populated binding table and data traffic filtering. This feature enables the device to deny traffic when it is originated from an address that is not stored in the binding table. IPv6 source guard does not inspect ND or DHCP packets; rather, it works in conjunction with IPv6

neighbor discovery (ND) inspection or IPv6 address glean, both of which detect existing addresses on the link and store them into the binding table. IPv6 source guard is an interface between the populated binding table and data traffic filtering, and the binding table must be populated with IPv6 prefixes for IPv6 source guard to work.

IPv6 source guard can deny traffic from unknown sources or unallocated addresses, such as traffic from sources not assigned by a DHCP server. When traffic is denied, the IPv6 address glean feature is notified so that it can try to recover the traffic by querying the DHCP server or by using IPv6 ND. The data-glean function prevents the device and end user from getting deadlocked, whereupon a valid address fails to be stored into the binding table, there is no recovery path, and the end user is unable to connect.

The following illustration provides an overview of how IPv6 source guard works with IPv6 address glean.

Figure 3: IPv6 Source Guard and Address Glean Overview



IPv6 Prefix Guard Overview

The IPv6 Prefix Guard feature works within the IPv6 Source Guard feature, enabling the device to deny traffic originated from nontopologically correct addresses. IPv6 prefix guard is often used when IPv6 prefixes are delegated to devices (for example, home gateways) using DHCP prefix delegation. The feature discovers ranges of addresses assigned to the link and blocks any traffic sourced with an address outside this range.


To determine which prefixes should be allowed and which prefixes should be blocked, IPv6 prefix guard uses the following:

- Prefix glean in Router Advertisements (RAs)
- Prefix glean in DHCP prefix delegation
- Static configuration

Whenever a prefix is to be allowed, IPv6 prefix guard downloads it to the hardware table. Whenever a packet is switched, the hardware matches the source of the packet against this table and drops the packet if no match is found.

The following figure shows a service provider (SP) scenario in which prefixes are gleaned in DHCP-PD messages.

Figure 4: Prefixes Gleaned in DHCP-PD Messages Scenario



334714

How to Configure IPv6 Source Guard and Prefix Guard

Configuring IPv6 Source Guard

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 source-guard policy *source-guard-policy***
4. **permit link-local**
5. **deny global-autoconf**
6. **trusted**
7. **exit**
8. **show ipv6 source-guard policy [*snooping-policy*]**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 source-guard policy <i>source-guard-policy</i> Example: Device(config)# ipv6 source-guard policy my_sourceguard_policy	Defines an IPv6 source-guard policy name and enters switch integrated security features source-guard policy configuration mode.
Step 4	permit link-local Example: Device(config-sisf-sourceguard)# permit link-local	Allows hardware bridging for all data traffic sourced by a link-local address.
Step 5	deny global-autoconf Example: Device(config-sisf-sourceguard)# deny global-autoconf	Denies data traffic from auto-configured global addresses.

	Command or Action	Purpose
Step 6	trusted Example: Device(config-sisf-sourceguard)# trusted	Allows hardware bridging for all data traffic on the target where the policy is applied.
Step 7	exit Example: Device(config-sisf-sourceguard)# exit	Exits source-guard policy configuration mode and returns to privileged EXEC mode.
Step 8	show ipv6 source-guard policy [snooping-policy] Example: Device# show ipv6 source-guard policy policy1	Displays the IPv6 source-guard policy configuration.

Configuring IPv6 Source Guard on an Interface

SUMMARY STEPS

1. enable
2. configure terminal
3. interface *type number*
4. ipv6 source-guard attach-policy *source-guard-policy*
5. exit
6. show ipv6 source-guard policy *source-guard-policy*

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.

	Command or Action	Purpose
Step 3	interface <i>type number</i> Example: Device(config)# interface fastethernet 3/13	Specifies an interface type and number, and enters interface configuration mode.
Step 4	ipv6 source-guard attach-policy <i>source-guard-policy</i> Example: Device(config-if)# ipv6 source-guard attach-policy my_source_guard_policy	Applies IPv6 source guard on an interface.
Step 5	exit Example: Device(config-if) # exit	Exits interface configuration mode and places the device in privileged EXEC mode.
Step 6	show ipv6 source-guard policy <i>source-guard-policy</i> Example: Device# show ipv6 source-guard policy policy1	Displays all the interfaces on which IPv6 source guard is applied.

Configuring IPv6 Prefix Guard

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 source-guard policy** *source-guard-policy*
4. **validate address**
5. **validate prefix**
6. **exit**
7. **show ipv6 source-guard policy** [*source-guard-policy*]

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.

	Command or Action	Purpose
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 source-guard policy <i>source-guard-policy</i> Example: Device(config)# ipv6 source-guard policy my_snooping_policy	Defines an IPv6 source-guard policy name and enters switch integrated security features source-guard policy configuration mode.
Step 4	validate address Example: Device(config-sisf-sourceguard)# no validate address	Disables the validate address feature and enables the IPv6 prefix guard feature to be configured.
Step 5	validate prefix Example: Device(config-sisf-sourceguard)# validate prefix	Enables IPv6 source guard to perform the IPv6 prefix-guard operation.
Step 6	exit Example: Device(config-sisf-sourceguard)# exit	Exits switch integrated security features source-guard policy configuration mode and returns to privileged EXEC mode.
Step 7	show ipv6 source-guard policy [<i>source-guard-policy</i>] Example: Device# show ipv6 source-guard policy policy1	Displays the IPv6 source-guard policy configuration.

Configuration Examples for IPv6 Source Guard and Prefix Guard

Example: Configuring IPv6 Source Guard and Prefix Guard

```
Device# ipv6 source-guard policy policy1

Policy guard configuration:
  validate prefix
  validate address
```

Additional References for IPv6 Source Guard and Prefix Guard

Related Documents

Related Topic	Document Title
IPv6 addressing and connectivity	<i>IPv6 Configuration Guide</i>
IPv4 addressing	<i>IP Addressing: IPv4 Addressing Configuration Guide</i>
Cisco IOS commands	Cisco IOS Master Command List, All Releases
IPv6 commands	<i>Cisco IOS IPv6 Command Reference</i>
Cisco IOS IPv6 features	Cisco IOS IPv6 Feature Mapping

Standards and RFCs

Standard/RFC	Title
RFCs for IPv6	<i>IPv6 RFCs</i>

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for IPv6 Source Guard and Prefix Guard

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 6: Feature Information for IPv6 Source Guard and Prefix Guard

Feature Name	Releases	Feature Information
IPv6 Prefix Guard	15.3(1)S Cisco IOS XE Release 3.9S	<p>The IPv6 Prefix Guard feature enables a device to deny traffic originated from nontopologically correct addresses.</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco CSR 1000V</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco ASR 1000 Series Routers.</p> <p>The following commands were introduced or modified: ipv6 source-guard policy, permit link-local, show ipv6 source-guard policy, validate address, validate prefix.</p>
IPv6 Source Guard	15.0(2)SE 15.3(1)S Cisco IOS XE Release 3.9S IOS XE 3.6.0E, IOS 15.2(2)E	<p>The IPv6 source guard feature blocks any data traffic sourced from an unknown source. For example, one that is not already populated in the binding table or previously learned through ND or DHCP gleaning.</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco CSR 1000V</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco ASR 1000 Series Routers.</p> <p>The following commands were introduced or modified: deny global-autoconfig, ipv6 source-guard attach-policy, ipv6 source-guard policy, permit link-local, show ipv6 source-guard policy, trusted.</p>



IPv6 Destination Guard

The IPv6 Destination Guard feature works with IPv6 neighbor discovery to ensure that the device performs address resolution only for those addresses that are known to be active on the link. It relies on the address glean functionality to populate all destinations active on the link into the binding table and then blocks resolutions before they happen when the destination is not found in the binding table.

- [Finding Feature Information, page 59](#)
- [Prerequisites for IPv6 Destination Guard, page 59](#)
- [Information About IPv6 Destination Guard, page 60](#)
- [How to Configure the IPv6 Destination Guard, page 60](#)
- [Configuration Examples for IPv6 Destination Guard, page 62](#)
- [Additional References, page 62](#)
- [Feature Information for IPv6 Destination Guard, page 63](#)

Finding Feature Information

Your software release may not support all the features documented in this module. For the latest caveats and feature information, see [Bug Search Tool](#) and the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the feature information table.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Prerequisites for IPv6 Destination Guard

- You should be familiar with the IPv6 Neighbor Discovery feature. For information about IPv6 neighbor discovery, see the “Implementing IPv6 Addressing and Basic Connectivity” module.
- You should be familiar with the IPv6 First-Hop Security Binding Table feature. For information, see the “IPv6 First-Hop Security Binding Table” module.

Information About IPv6 Destination Guard

IPv6 Destination Guard Overview

The IPv6 Destination Guard feature works with IPv6 neighbor discovery to ensure that the device performs address resolution only for those addresses that are known to be active on the link. It relies on the address glean functionality to populate all destinations active on the link into the binding table and then blocks resolutions before they happen when the destination is not found in the binding table.

Prior to filtering incoming routed traffic, the device gleans addresses on the link, by snooping Neighbor Discovery Protocol (NDP) and DHCP messages. When a packet reaches the device and there is not yet an adjacency for the destination or for the next hop, the NDP consults the device binding table to verify that the destination on link or the next-hop have been previously gleaned. If the destination is not found in the binding table, the packet is dropped. Otherwise, neighbor discovery resolution is performed.

How to Configure the IPv6 Destination Guard

Configuring IPv6 Destination Guard

SUMMARY STEPS

1. **enable**
2. **configure terminal**
3. **ipv6 destination-guard policy *policy-name***
4. **enforcement {always | stressed}**
5. **exit**
6. **interface *type number***
7. **ipv6 destination-guard attach-policy [*policy-name*]**
8. **exit**
9. **show ipv6 destination-guard policy [*policy-name*]**

DETAILED STEPS

	Command or Action	Purpose
Step 1	enable Example: Device> enable	Enables privileged EXEC mode. <ul style="list-style-type: none"> • Enter your password if prompted.

	Command or Action	Purpose
Step 2	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 3	ipv6 destination-guard policy <i>policy-name</i> Example: Device(config)# ipv6 destination-guard policy poll	Defines the destination guard policy name and enters destination-guard configuration mode.
Step 4	enforcement {always stressed} Example: Device(config-destguard)# enforcement always	Sets the enforcement level for the target address.
Step 5	exit Example: Device(config-destguard)# exit	Exits destination-guard configuration mode and returns to global configuration mode.
Step 6	interface <i>type number</i> Example: Device(config)# interface GigabitEthernet 0/0/1	Enters interface configuration mode.
Step 7	ipv6 destination-guard attach-policy [<i>policy-name</i>] Example: Device(config-if)# ipv6 destination-guard attach-policy poll	Attaches a destination guard policy to an interface.
Step 8	exit Example: Device(config-if)# exit	Exits interface configuration mode and returns to privileged EXEC configuration mode.
Step 9	show ipv6 destination-guard policy [<i>policy-name</i>] Example: Device# show ipv6 destination-guard policy poll	(Optional) Displays the policy configuration and all interfaces where the policy is applied.

Configuration Examples for IPv6 Destination Guard

Example: Configuring an IPv6 Destination Guard Policy

The following example shows how to configure a destination guard policy:

```
Router> enable
Router# configure terminal
Router(config)# interface GigabitEthernet 0/0/1
Router(config-if)# ipv6 destination-guard attach-policy destination

Router# show ipv6 destination-guard policy destination
Destination guard policy Destination:
  enforcement always
  Target: Gi0/0/1
```

Additional References

Related Documents

Related Topic	Document Title
Cisco IOS commands	Cisco IOS Master Command List, All Releases
IPv6 addressing and connectivity	<i>IPv6 Configuration Guide</i>
IPv6 commands	Cisco IOS IPv6 Command Reference
Cisco IOS IPv6 features	Cisco IOS IPv6 Feature Mapping

Technical Assistance

Description	Link
The Cisco Support and Documentation website provides online resources to download documentation, software, and tools. Use these resources to install and configure the software and to troubleshoot and resolve technical issues with Cisco products and technologies. Access to most tools on the Cisco Support and Documentation website requires a Cisco.com user ID and password.	http://www.cisco.com/cisco/web/support/index.html

Feature Information for IPv6 Destination Guard

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to www.cisco.com/go/cfn. An account on Cisco.com is not required.

Table 7: Feature Information for IPv6 Destination Guard

Feature Name	Releases	Feature Information
IPv6 Destination Guard	15.2(4)S 15.1(2)SG Cisco IOS XE Release 3.9S IOS XE 3.6.0E, IOS 15.2(2)E	<p>The IPv6 Destination Guard feature blocks data traffic from an unknown source and filters IPv6 traffic based on the destination address.</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco CSR 1000V.</p> <p>In Cisco IOS XE Release 3.9S, support was added for the Cisco ASR 1000 Series Routers.</p> <p>The following commands were introduced or modified: enforcement, ipv6 destination-guard attach-policy, ipv6 destination-guard policy, show ipv6 destination-guard policy.</p>



CHAPTER 9

IPv6 RFCs

Standards and RFCs

RFCs	Title
RFC 1195	<i>Use of OSI IS-IS for Routing in TCP/IP and Dual Environments</i>
RFC 1267	<i>A Border Gateway Protocol 3 (BGP-3)</i>
RFC 1305	<i>Network Time Protocol (Version 3) Specification, Implementation and Analysis</i>
RFC 1583	<i>OSPF version 2</i>
RFC 1772	<i>Application of the Border Gateway Protocol in the Internet</i>
RFC 1886	<i>DNS Extensions to Support IP version 6</i>
RFC 1918	<i>Address Allocation for Private Internets</i>
RFC 1981	<i>Path MTU Discovery for IP version 6</i>
RFC 2080	<i>RIPng for IPv6</i>
RFC 2281	<i>Cisco Hot Standby Router Protocol (HSRP)</i>
RFC 2332	<i>NBMA Next Hop Resolution Protocol (NHRP)</i>
RFC 2373	<i>IP Version 6 Addressing Architecture</i>
RFC 2374	<i>An Aggregatable Global Unicast Address Format</i>
RFC 2375	<i>IPv6 Multicast Address Assignments</i>
RFC 2401	<i>Security Architecture for the Internet Protocol</i>

RFCs	Title
RFC 2402	<i>IP Authentication Header</i>
RFC 2404	<i>The Use of Hash Message Authentication Code Federal Information Processing Standard 180-1 within Encapsulating Security Payload and Authentication Header</i>
RFC 2406	<i>IP Encapsulating Security Payload (ESP)</i>
RFC 2407	<i>The Internet Security Domain of Interpretation for ISAKMP</i>
RFC 2408	<i>Internet Security Association and Key Management Protocol</i>
RFC 2409	<i>Internet Key Exchange (IKE)</i>
RFC 2427	<i>Multiprotocol Interconnect over Frame Relay</i>
RFC 2428	<i>FTP Extensions for IPv6 and NATs</i>
RFC 2460	<i>Internet Protocol, Version 6 (IPv6) Specification</i>
RFC 2461	<i>Neighbor Discovery for IP Version 6 (IPv6)</i>
RFC 2462	<i>IPv6 Stateless Address Autoconfiguration</i>
RFC 2463	<i>Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification</i>
RFC 2464	<i>Transmission of IPv6 Packets over Ethernet</i>
RFC 2467	<i>Transmission of IPv6 Packets over FDDI</i>
RFC 2472	<i>IP Version 6 over PPP</i>
RFC 2473	<i>Generic Packet Tunneling in IPv6 Specification</i>
RFC 2474	<i>Definition of the Differentiated Services Field (DS Field) in the IPv4 and IPv6 Headers</i>
RFC 2475	<i>An Architecture for Differentiated Services Framework</i>
RFC 2492	<i>IPv6 over ATM</i>
RFC 2545	<i>Use of BGP-4 Multiprotocol Extensions for IPv6 Inter-Domain Routing</i>

RFCs	Title
RFC 2590	<i>Transmission of IPv6 Packets over Frame Relay Specification</i>
RFC 2597	<i>Assured Forwarding PHB</i>
RFC 2598	<i>An Expedited Forwarding PHB</i>
RFC 2640	<i>Internet Protocol, Version 6 Specification</i>
RFC 2684	<i>Multiprotocol Encapsulation over ATM Adaptation Layer 5</i>
RFC 2697	<i>A Single Rate Three Color Marker</i>
RFC 2698	<i>A Two Rate Three Color Marker</i>
RFC 2710	<i>Multicast Listener Discovery (MLD) for IPv6</i>
RFC 2711	<i>IPv6 Router Alert Option</i>
RFC 2732	<i>Format for Literal IPv6 Addresses in URLs</i>
RFC 2765	<i>Stateless IP/ICMP Translation Algorithm (SIIT)</i>
RFC 2766	<i>Network Address Translation-Protocol Translation (NAT-PT)</i>
RFC 2858	<i>Multiprotocol Extensions for BGP-4</i>
RFC 2893	<i>Transition Mechanisms for IPv6 Hosts and Routers</i>
RFC 3056	<i>Connection of IPv6 Domains via IPv4 Clouds</i>
RFC 3068	<i>An Anycast Prefix for 6to4 Relay Routers</i>
RFC 3095	<i>RObust Header Compression (ROHC): Framework and Four Profiles: RTP, UDP, ESP, and Uncompressed</i>
RFC 3107	<i>Carrying Label Information in BGP-4</i>
RFC 3137	<i>OSPF Stub Router Advertisement</i>
RFC 3147	<i>Generic Routing Encapsulation over CLNS</i>
RFC 3152	<i>Delegation of IP6.ARPA</i>
RFC 3162	<i>RADIUS and IPv6</i>

RFCs	Title
RFC 3315	<i>Dynamic Host Configuration Protocol for IPv6 (DHCPv6)</i>
RFC 3319	<i>Dynamic Host Configuration Protocol (DHCPv6) Options for Session Initiated Protocol (SIP) Servers</i>
RFC 3392	<i>Capabilities Advertisement with BGP-4</i>
RFC 3414	<i>User-based Security Model (USM) for version 3 of the Simple Network Management Protocol (SNMPv3)</i>
RFC 3484	<i>Default Address Selection for Internet Protocol version 6 (IPv6)</i>
RFC 3513	<i>Internet Protocol Version 6 (IPv6) Addressing Architecture</i>
RFC 3576	<i>Change of Authorization</i>
RFC 3587	<i>IPv6 Global Unicast Address Format</i>
RFC 3590	<i>Source Address Selection for the Multicast Listener Discovery (MLD) Protocol</i>
RFC 3596	<i>DNS Extensions to Support IP Version 6</i>
RFC 3633	<i>DHCP IPv6 Prefix Delegation</i>
RFC 3646	<i>DNS Configuration options for Dynamic Host Configuration Protocol for IPv6 (DHCPv6)</i>
RFC 3697	<i>IPv6 Flow Label Specification</i>
RFC 3736	<i>Stateless DHCP Service for IPv6</i>
RFC 3756	<i>IPv6 Neighbor Discovery (ND) Trust Models and Threats</i>
RFC 3759	<i>RObust Header Compression (ROHC): Terminology and Channel Mapping Examples</i>
RFC 3775	<i>Mobility Support in IPv6</i>
RFC 3810	<i>Multicast Listener Discovery Version 2 (MLDv2) for IPv6</i>
RFC 3846	<i>Mobile IPv4 Extension for Carrying Network Access Identifiers</i>

RFCs	Title
RFC 3879	<i>Deprecating Site Local Addresses</i>
RFC 3898	<i>Network Information Service (NIS) Configuration Options for Dynamic Host Configuration Protocol for IPv6 (DHCPv6)</i>
RFC 3954	<i>Cisco Systems NetFlow Services Export Version 9</i>
RFC 3956	<i>Embedding the Rendezvous Point (RP) Address in an IPv6 Multicast Address</i>
RFC 3963	<i>Network Mobility (NEMO) Basic Support Protocol</i>
RFC 3971	<i>SEcure Neighbor Discovery (SEND)</i>
RFC 3972	<i>Cryptographically Generated Addresses (CGA)</i>
RFC 4007	<i>IPv6 Scoped Address Architecture</i>
RFC 4075	<i>Simple Network Time Protocol (SNTP) Configuration Option for DHCPv6</i>
RFC 4087	<i>IP Tunnel MIB</i>
RFC 4091	<i>The Alternative Network Address Types (ANAT) Semantics for the Session Description Protocol (SDP) Grouping Framework</i>
RFC 4092	<i>Usage of the Session Description Protocol (SDP) Alternative Network Address Types (ANAT) Semantics in the Session Initiation Protocol (SIP)</i>
RFC 4109	<i>Algorithms for Internet Key Exchange version 1 (IKEv1)</i>
RFC 4191	<i>Default Router Preferences and More-Specific Routes</i>
RFC 4193	<i>Unique Local IPv6 Unicast Addresses</i>
RFC 4214	<i>Intra-Site Automatic Tunnel Addressing Protocol (ISATAP)</i>
RFC 4242	<i>Information Refresh Time Option for Dynamic Host Configuration Protocol for IPv6 (DHCPv6)</i>
RFC 4282	<i>The Network Access Identifier</i>
RFC 4283	<i>Mobile Node Identifier Option for Mobile IPv6</i>

RFCs	Title
RFC 4285	<i>Authentication Protocol for Mobile IPv6</i>
RFC 4291	<i>IP Version 6 Addressing Architecture</i>
RFC 4292	<i>IP Forwarding Table MIB</i>
RFC 4293	<i>Management Information Base for the Internet Protocol (IP)</i>
RFC 4302	<i>IP Authentication Header</i>
RFC 4306	<i>Internet Key Exchange (IKEv2) Protocol</i>
RFC 4308	<i>Cryptographic Suites for IPsec</i>
RFC 4364	<i>BGP MPLS/IP Virtual Private Networks (VPNs)</i>
RFC 4382	<i>MPLS/BGP Layer 3 Virtual Private Network (VPN) Management Information Base</i>
RFC 4443	<i>Internet Control Message Protocol (ICMPv6) for the Internet Protocol Version 6 (IPv6) Specification</i>
RFC 4552	<i>Authentication/Confidentiality for OSPFv3</i>
RFC 4594	<i>Configuration Guidelines for DiffServ Service Classes</i>
RFC 4601	<i>Protocol Independent Multicast - Sparse Mode (PIM-SM): Protocol Specification</i>
RFC 4610	<i>Anycast-RP Using Protocol Independent Multicast (PIM)</i>
RFC 4649	<i>Dynamic Host Configuration Protocol for IPv6 (DHCPv6) Relay Agent Remote-ID Option</i>
RFC 4659	<i>BGP-MPLS IP Virtual Private Network (VPN) Extension for IPv6 VPN</i>
RFC 4724	<i>Graceful Restart Mechanism for BGP</i>
RFC 4798	<i>Connecting IPv6 Islands over IPv4 MPLS Using IPv6 Provider Edge Routers (6PE)</i>
RFC 4818	<i>RADIUS Delegated-IPv6-Prefix Attribute</i>
RFC 4861	<i>Neighbor Discovery for IP version 6 (IPv6)</i>

RFCs	Title
RFC 4862	<i>IPv6 Stateless Address Autoconfiguration</i>
RFC 4884	<i>Extended ICMP to Support Multi-Part Messages</i>
RFC 4885	<i>Network Mobility Support Terminology</i>
RFC 4887	<i>Network Mobility Home Network Models</i>
RFC 5015	<i>Bidirectional Protocol Independent Multicast (BIDIR-PIM)</i>
RFC 5059	<i>Bootstrap Router (BSR) Mechanism for Protocol Independent Multicast (PIM)</i>
RFC 5072	<i>IPv6 over PPP</i>
RFC 5095	<i>Deprecation of Type 0 Routing Headers in IPv6</i>
RFC 5120	<i>M-ISIS: Multi Topology (MT) Routing in Intermediate System to Intermediate Systems (IS-ISs)</i>
RFC 5130	<i>A Policy Control Mechanism in IS-IS Using Administrative Tags</i>
RFC 5187	<i>OSPFv3 Graceful Restart</i>
RFC 5213	<i>Proxy Mobile IPv6</i>
RFC 5308	<i>Routing IPv6 with IS-IS</i>
RFC 5340	<i>OSPF for IPv6</i>
RFC 5460	<i>DHCPv6 Bulk Leasequery</i>
RFC 5643	<i>Management Information Base for OSPFv3</i>
RFC 5838	<i>Support of Address Families in OSPFv3</i>
RFC 5844	<i>IPv4 Support for Proxy Mobile IPv6</i>
RFC 5845	<i>Generic Routing Encapsulation (GRE) Key Option for Proxy Mobile IPv6</i>
RFC 5846	<i>Binding Revocation for IPv6 Mobility</i>
RFC 5881	<i>Bidirectional Forwarding Detection (BFD) for IPv4 and IPv6 (Single Hop)</i>

RFCs	Title
RFC 5905	<i>Network Time Protocol Version 4: Protocol and Algorithms Specification</i>
RFC 5969	<i>IPv6 Rapid Deployment on IPv4 Infrastructures (6RD) -- Protocol Specification</i>
RFC 6105	<i>IPv6 Router Advertisement Guard</i>
RFC 6620	<i>FCFS SAVI: First-Come, First-Served Source Address Validation Improvement for Locally Assigned IPv6 Addresses</i>