



CHAPTER 2

Installing and Configuring Licenses

This chapter describes how to install and configure licenses.

This chapter includes the following sections:

- [Information About Installing Licenses, page 2-1](#)
- [Prerequisites for Installing and Configuring Licenses, page 2-1](#)
- [Guidelines and Limitations, page 2-2](#)
- [Default Settings, page 2-2](#)
- [Obtaining and Installing a License, page 2-3](#)
- [Transferring Licenses, page 2-6](#)
- [Uninstalling a License, page 2-9](#)
- [Configuring Nonvolatile Licenses, page 2-12](#)
- [Verifying the License Configuration, page 2-14](#)
- [Changing the Serial Number in a License, page 2-17](#)
- [Feature History for Licenses, page 2-19](#)

Information About Installing Licenses

The Cisco VSG software is available for download at the following URL:

http://www.cisco.com/en/US/products/ps13095/tsd_products_support_series_home.html

When you download the software from the above location, you are prompted to fill in the online form. When the form has been completed appropriately, you will receive an email that contains the software license claim certificate. The number of licenses you receive depends on how many VEMs you indicate you have and how many CPU sockets you indicate are available on those VEMs.

For detailed information about licenses, see [Chapter 1, “Overview.”](#)

Prerequisites for Installing and Configuring Licenses

License installation and configuration has the following prerequisites:

- You have a copy of your existing license file(s) with the host ID of the existing VSM.

Send document comments to vsg-docfeedback@cisco.com.

- A license file is tied to each VSM by the host ID, or the serial number, that is associated with the VSM device.
- A license file contains the number of licenses that you ordered for your VSM. One license is required for each CPU on each VEM.
- A VSM can have more than one license file depending on the number of installed VEM CPUs.
- If you have multiple license files stacked on your VSM, repeat the configuration procedures for each license file.

Guidelines and Limitations

Permanent licenses have the following guidelines and limitations:

- If you modify a permanent license key file, the license key file is invalidated.
- When you purchase permanent licenses, the license key file is sent to you in an e-mail. The license key authorizes use on only the host ID device. You must obtain a separate license key file for each of your VSMs.
- A license file contains the number of licenses that you ordered for your VSM. One license is required for each CPU on each VEM.
- A VSM can have more than one license file depending on the number of installed VEM CPUs.
- You must have a role equivalent to that of network-admin to install, uninstall, or copy a permanent license file. For information about user accounts and roles, see the *Cisco Nexus 1000V Security Configuration Guide, Release 4.2(1)SV1(5.1)*.
- If you are installing multiple permanent licenses for the same VSM, also called license stacking, each permanent license key filename must be unique.
- Licenses cannot be applied to a VEM unless there are enough licenses in the pool to cover all of its CPUs.
- If a license is in use, you cannot delete its license file. You must first transfer all licenses from the VEMs to the VSM license pool before uninstalling the license file.
- When you install a permanent license file, all default licenses are invalidated. Installing a permanent license file has no effect on evaluation licenses. For more detailed information on licenses, see the [“Information About Licenses” section on page 1-1](#).

Default Settings

[Table 2-1](#) lists the default settings for the Cisco Virtual Security Gateway license configuration.

Table 2-1 **Default License Parameters**

Parameter	Default
volatile license	Enabled Licenses are returned to the VSM pool when a VEM has no VM that has Cisco VSG service configured or the VEM is out of service. 16 evaluation licenses are available for 60 days.

Send document comments to vsg-docfeedback@cisco.com.

Obtaining and Installing a License

This section describes how to obtain the license file that is required for each VSM and then install it.


This section includes the following topics:

- [Flow Chart: Obtaining and Installing a License, page 2-3](#)
- [Obtaining the License File, page 2-3](#)
- [Installing the License File on the VSM, page 2-5](#)
- [Verifying the License Configuration, page 2-14](#)

Flow Chart: Obtaining and Installing a License

Use the flow chart in [Figure 1](#) to guide you through the process of installing a license on a VSM. After completing a procedure, return to the flow chart to make sure that you complete all procedures in the correct sequence.

Figure 1 *Flow Chart: Obtaining and Installing a License*



Obtaining the License File

Use the following procedure to obtain a license file for a VSM.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- A license file is tied to each VSM by the host ID or the serial number that is associated with the VSM device.

Send document comments to vsg-docfeedback@cisco.com.

- Make sure that you have your product authorization key (PAK). The PAK is found in your software license claim certificate.
If you cannot locate your software license claim certificate, contact [Cisco Technical Support](#).
- You are logged in to the CLI in EXEC mode.
- In this procedure, you must copy a license file, which means that your username must have a role that is equivalent to that of the network-admin role that allows you to copy files. For information about user accounts and roles, see the *Cisco Nexus 1000V Security Configuration Guide, Release 4.2(1)SV1(5.1)*.

PROCEDURE

Step 1 Obtain the serial number, also called the host ID, for your VSM.

```
n1000v# show license host-id
License hostid: VDH=1280389551234985805
```



Note The host ID includes everything that appears after the equal sign (=). In this example, the host ID is 1280389551234985805. You will need the host ID in [Step 5](#).

Step 2 From your software license claim certificate, locate the product authorization key (PAK).
You will need the PAK in [Step 5](#).

Step 3 Go to the [Software Download](#) site.

Step 4 From the Software Download site, go to the [Product License Registration](#) site.

Step 5 From the Product License Registration site, follow the instructions for registering your VSM license.
The license key file is sent to you in an e-mail. The license key authorizes use on only the host ID device.
You must obtain separate license key file(s) for each of your VSMs.



Caution The license key file is invalidated if you modify it.

Step 6 Save your license to a TFTP server.

Step 7 Copy your license to bootflash on the VSM.

```
n1000v@ copy scp://user@linux-box.cisco.com/home/user/nlkv_license.lic bootflash:
Enter vrf (If no input, current vrf 'default' is considered):
user@linux-box.cisco.com's password:
nlkv_license.lic                               100% 252      0.3KB/s   00:00

n1000v@
```

Send document comments to vsg-docfeedback@cisco.com.

Installing the License File on the VSM

Use the following procedure to install the license file(s) on a VSM. Installing multiple licenses is called stacking.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- Default licenses are invalidated when a permanent license file is installed. Make sure that the license file you are installing contains the number of licenses needed to cover all VEMs. For more information on default licenses, see the [“Default Licenses” section on page 1-2](#).
- This procedure installs the license file using the name, `license_file.lic`. You can specify a different name if needed.
- If you are installing multiple licenses for the same VSM, also called license stacking, make sure that each license key filename is unique.
- Repeat this procedure for each additional license file you are installing, or stacking, on the VSM.
- You are logged in to the CLI in EXEC mode.
- You must have a role with privileges equivalent to that of the `network-admin` role to install a license. For information about user accounts and roles, see the *Cisco Nexus 1000V Security Configuration Guide, Release 4.2(1)SVI(5.1)*.

SUMMARY STEPS

1. **install license bootflash:** *filename*
2. **show license file** *filename*
3. **show license usage** *package_name*
4. **copy running-config startup-config**

DETAILED STEPS

	Command	Purpose
Step 1	install license bootflash: <i>filename</i> Example: <pre>n1000v# install license bootflash:license_file.lic Installing license ..done n1000v#</pre>	Installs the license from the active VSM console. Note If you specify a license filename, the file is installed with the specified name. Otherwise, the default filename is used. The license is installed on the VSM and each VEM automatically acquires a license for every CPU socket.
Step 2	show license file <i>filename</i> Example: <pre>n1000v# show license file license_file.lic</pre>	Verifies the license installation by displaying the license configured for the VSM.

Send document comments to vsg-docfeedback@cisco.com.

	Command	Purpose
Step 3	show license usage <i>package_name</i> Example: n1000v# show license usage NEXUS_VSG_SERVICES_PKG	Verifies the license installation by displaying it in the license usage table. Note If you already have VEMs using Cisco VSG services, the output of this command shows VEMs and sockets.
Step 4	copy running-config startup-config Example: n1000v(config)# copy running-config startup-config	(Optional) Saves the running configuration persistently through reboots and restarts by copying it to the startup configuration.

Examples

This example shows how to install a license file and then display its contents and usage:

```
n1000v# install license bootflash:license_file.lic
Installing license ..done
n1000v# show license file license_file.lic
SERVER this_host ANY
VENDOR cisco
INCREMENT NEXUS_VSG_SERVICES_PKG cisco 1.0 permanent 10 \
  HOSTID=VDH=1575337335122974806 \
  NOTICE="<LicFileID>license_file.lic</LicFileID><LicLineID>0</LicLineID> \
  <PAK>PAK12345678</PAK>" SIGN=3AF5C2D26E1A
n1000v# show license usage NEXUS_VSG_SERVICES_PKG
-----
Feature Usage Info
-----
      Installed Licenses : 10
      Default Eval Licenses : 0
      Max Overdraft Licenses : 16
      Installed Licenses in Use : 2
      Overdraft Licenses in Use : 0
      Default Eval Lic in Use : 0
      Licenses Available : 24
      Shortest Expiry      : Never
-----
Application
-----
VEM 3 - Socket 1
VEM 3 - Socket 2
-----
```

Transferring Licenses

You can use the following procedures in this section to transfer licenses between VEMs and uninstall a license by transferring it from a VEM to the VSM license pool:

- [Transferring Licenses Between VEMs, page 2-7](#)
- [Transferring Licenses to the License Pool, page 2-8](#)

Send document comments to vsg-docfeedback@cisco.com.

Transferring Licenses Between VEMs

Use the following procedure to transfer licenses from one VEM to another. For example, you might transfer licenses between VEMs after moving a VM from one host to another.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- You are logged in to the CLI in EXEC mode.
- You know the VEM that you want to transfer licenses from and the number of licenses it has.
- You know the VEM that you are transferring licenses to and the number of licenses required.
- You know the number of CPUs installed on the destination VEM.
- Licenses cannot be transferred to a VEM unless there are enough licenses in the pool to cover all of its CPUs.
- Licenses cannot be transferred to a VEM that does not have a VSG service configured.
- When licenses are successfully transferred from one VEM to another, the virtual machines on the source VEM can no longer use Cisco VSG services and the virtual machines on the destination VEM can now use Cisco VSG services.
- For detailed information about the fields in the output of these commands, see the *Cisco Nexus 1000V Command Reference, Release 4.2(1)SV1(5.1)*.

SUMMARY STEPS

1. **vsg license transfer src-vem** *vem_no* **dst-vem** *vem_no*
2. **show license usage** *package_name*

DETAILED STEPS

	Command	Purpose
Step 1	vsg license transfer src-vem <i>vem_no</i> dst-vem <i>vem_no</i> Example: n1000v# vsg license transfer src-vem 3 dst-vem 5 n1000v(config)#	Transfers the licenses from one VEM to another.
Step 2	show license usage <i>package_name</i> Example: n1000v# show license usage	Verifies the transfer by displaying the licenses in use on each VEM.

Send document comments to vsg-docfeedback@cisco.com.

EXAMPLES

This example shows how to transfer a license from VEM 3 to VEM 5 and verify the transfer in the license usage:

```
n1000v# vsg license transfer src-vem 3 dst-vem 5
n1000v(config)#
n1000v# show license usage NEXUS_VSG_SERVICES_PKG
-----
Feature Usage Info
-----
          Installed Licenses :    10
            Eval Licenses :     0
      Max Overdraft Licenses :    16
Installed Licenses in Use :     4
Overdraft Licenses in Use :     0
      Eval Licenses in Use :     0
          Licenses Available :    22
-----
Application
-----
VEM 4 - Socket 1
VEM 4 - Socket 2
VEM 5 - Socket 1
VEM 5 - Socket 2
-----
```

Transferring Licenses to the License Pool

Use the following procedure to transfer licenses from a VEM to the VSM license pool. For example, you might remove a license from a VEM and transfer it to the VSM license pool.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- You are logged in to the CLI in EXEC mode.
- When you transfer its licenses to the VSM license pool, all VMs on the VEM can no longer use the Cisco VSG service.
- For detailed information about the fields in the output of these commands, see the *Cisco Nexus 1000V Command Reference, Release 4.2(1)SV1(5.1)*.

SUMMARY STEPS

1. **vsg license transfer src-vem *vem no* license_pool**
2. **show license usage *package_name***

Send document comments to vsg-docfeedback@cisco.com.

DETAILED STEPS

	Command	Purpose
Step 1	vsg license transfer src-vem <i>vem_no</i> license_pool Example: n1000v# vsg license transfer src-vem 3 license_pool n1000v(config)#	Transfers the licenses from a VEM to the license pool. All virtual machines on the VEM can no longer use the Cisco VSG service.
Step 2	show license usage <i>package_name</i> Example: n1000v# show license usage	Verifies the transfer by displaying the licenses in use on each VEM.

EXAMPLES

This example shows how to display the licenses in use on each VEM. Notice that the licenses on VEM 3 are no longer in use.

```
n1000v# show license usage NEXUS_VSG_SERVICES_PKG
-----
Feature Usage Info
-----
          Installed Licenses :    10
             Eval Licenses :     0
    Max Overdraft Licenses :    16
Installed Licenses in Use :     2
Overdraft Licenses in Use :     0
             Eval Licenses in Use :  0
          Licenses Available :    24
-----
Application
-----
VEM 4 - Socket 1
VEM 4 - Socket 2
-----
```

Uninstalling a License

Use the following procedure to uninstall a license that is not in use.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:



Caution

When you uninstall a license file from a VSM, the VMs on the VEMs can no longer use Cisco VSG services, which could cause a service disruption in your network.

- You are logged in to the CLI in EXEC mode.
- If a license is in use, you cannot delete it. This procedure includes instructions for transferring all licenses from the VEMs to the VSM license pool before uninstalling the license file.

Send document comments to vsg-docfeedback@cisco.com.

- Only users with the network-admin role can uninstall licenses. For information on user accounts and roles, see the *Cisco Nexus 1000V Security Configuration Guide, Release 4.2(1)SV1(5.1)*.
- For detailed information about the fields in the output of these commands, see the *Cisco Nexus 1000V Command Reference, Release 4.2(1)SV1(5.1)*.

SUMMARY STEPS

1. **copy running-configure terminalftp://server/path/filename**
2. **show license brief**
3. **show license usage package_name**
4. **vsg license transfer src-vem vem no license_pool**
5. Repeat Step 4 for each VEM.
6. **clear license license_name**
7. **copy running-config startup-config**

DETAILED STEPS

	Command	Purpose
Step 1	copy running-configure terminalftp://server/path/filename Example: n1000v# copy running-configure terminalftp: n1000v(config)#	Copies the VSM running configuration to a remote server.
Step 2	show license brief Example: n1000v# show license brief Enterprise.lic n1000v#	Identifies the name of the license file to uninstall.

Send document comments to vsg-docfeedback@cisco.com.

	Command	Purpose
Step 3	<p>show license usage <i>package_name</i></p> <p>Example: n1000v# show license usage NEXUS_VSG_SERVICES_PKG ----- Feature Usage Info ----- Installed Licenses : 10 Eval Licenses : 0 Max Overdraft Licenses : 16 Installed Licenses in Use : 4 Overdraft Licenses in Use : 0 Eval Licenses in Use : 0 Licenses Available : 22 ----- Application ----- VEM 3 - Socket 1 VEM 3 - Socket 2 VEM 4 - Socket 1 VEM 4 - Socket 2 ----- n1000v#</p>	<p>Displays the licenses in use on each VEM so that you can transfer them back to the VSM license pool before uninstalling the license file.</p>
Step 4	<p>vsg license transfer src-vem <i>vem_no</i> license_pool</p> <p>Example: n1000v# vsg license transfer src-vem 3 license_pool n1000v#</p>	<p>Transfers the licenses from the VEM back to the VSM license pool.</p> <p>As the licenses are transferred from a VEM, the VMs on the VEM can no longer use the Cisco VSG service.</p>
Step 5	<p>Repeat Step 4 for each VEM until all licenses in use have been transferred back to the VSM license pool.</p>	
Step 6	<p>clear license <i>license_name</i></p> <p>Example: n1000v# clear license Enterprise.lic Clearing license Enterprise.lic: SERVER this_host ANY VENDOR cisco Do you want to continue? (y/n) y Clearing license ..done</p>	<p>Begins the uninstall of the named license file.</p> <p>In this example, the Enterprise.lic file is uninstalled.</p>
Step 7	<p>copy running-config startup-config</p> <p>Example: n1000v(config)# copy running-config startup-config</p>	<p>(Optional) Saves the running configuration persistently through reboots and restarts by copying it to the startup configuration.</p>

Send document comments to vsg-docfeedback@cisco.com.

EXAMPLES

This example shows how to uninstall a license that is no longer in use. In this example, the file to uninstall is the Enterprise.lic file.

```
n1000v# show license brief
Enterprise.lic
n1000v#
n1000v# show license usage NEXUS_VSG_SERVICES_PKG
-----
Feature Usage Info
-----
          Installed Licenses :    10
            Eval Licenses :     0
      Max Overdraft Licenses :    16
Installed Licenses in Use :     4
Overdraft Licenses in Use :     0
      Eval Licenses in Use :     0
          Licenses Available :    22
-----
Application
-----
VEM 3 - Socket 1
VEM 3 - Socket 2
VEM 4 - Socket 1
VEM 4 - Socket 2
-----
n1000v# vsg license transfer src-vem 3 license_pool
n1000v# vsg license transfer src-vem 4 license_pool
n1000v# clear license Enterprise.lic
Clearing license Enterprise.lic:
SERVER this_host ANY
VENDOR cisco
Do you want to continue? (y/n) y
Clearing license ..done
n1000v(config)# copy running-config startup-config
```

Configuring Nonvolatile Licenses

This section provides information about enabling and disabling the nonvolatile license feature and includes the following topics:

- [Enabling Nonvolatile Licenses, page 2-12](#)
- [Disabling Nonvolatile Licenses, page 2-13](#)

Enabling Nonvolatile Licenses

Use the following procedure to enable nonvolatile licenses so that whenever a VEM is taken out of service, it keeps its license and does not return the license to the VSM pool of available licenses.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- You are logged in to the CLI in EXEC mode.

Send document comments to vsg-docfeedback@cisco.com.

- A nonvolatile license is disabled by default. The licenses are returned to the VSM pool when a VEM is removed from service or no VMs use Cisco VSG service on the VEM.

SUMMARY STEPS

1. **configure terminal**
2. **no vsg license volatile**
3. **copy running-config startup-config**

DETAILED STEPS

	Command	Purpose
Step 1	configure terminal Example: n1000v# configure terminal n1000v(config)#	Places you into global configuration mode.
Step 2	no vsg license volatile Example: n1000v(config)# no vsg license volatile n1000v(config)#	Enables nonvolatile licenses in the running configuration.
Step 3	copy running-config startup-config Example: n1000v(config)# copy running-config startup-config	(Optional) Saves the running configuration persistently through reboots and restarts by copying it to the startup configuration.

Disabling Nonvolatile Licenses

Use the following procedure to disable nonvolatile licenses so that when a VEM is taken out of service, its licenses are returned to the VSM pool of available licenses.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- You are logged in to the CLI in EXEC mode.
- Your license must be in nonvolatile mode to configure for volatile mode.
- For detailed information about the fields in the output of these commands, see the *Cisco Nexus 1000V Command Reference, Release 4.2(1)SVI(5.1)*.



Note

For the Cisco VSG, the licenses are by default volatile. We recommend that you leave the Cisco VSG license configuration to be volatile by default.

Send document comments to vsg-docfeedback@cisco.com.

**Note**

The volatile licenses feature is disabled by default for the Cisco Nexus 1000V Series Switch. That is, the licenses in VEMs are nonvolatile and are not released when a VEM is removed from service.

**Note**

If you configure the license from nonvolatile to volatile, if the VEM does not use the Cisco VSG services, the license possessed by the VEM is returned to the license pool.

SUMMARY STEPS

1. **configure terminal**
2. **vsg license volatile**
3. **copy running-config startup-config**

DETAILED STEPS

	Command	Purpose
Step 1	configure terminal Example: n1000v# configure terminal n1000v(config)#	Places you into global configuration mode.
Step 2	vsg license volatile Example: n1000v(config)# vsg license volatile n1000v(config)#	Disables nonvolatile licenses in the running configuration.
Step 3	copy running-config startup-config Example: n1000v(config)# copy running-config startup-config	(Optional) Saves the running configuration persistently through reboots and restarts by copying it to the startup configuration.

Verifying the License Configuration

To display the license configuration, do one of the following tasks:

Command	Purpose
show license	Displays the license filename for the VSM.
show license brief	Displays the license installed on the VSM.
show license file <i>filename</i>	Displays the contents of the license file installed on the VSM, including the license filename and the expiration date for evaluation licenses.

Send document comments to vsg-docfeedback@cisco.com.

Command	Purpose
show license usage	Displays the total number of licenses in use on the VEMs.
show license usage <i>package_name</i>	Displays statistics about the number of evaluation and permanent licenses available, installed, and in use on the VSM.

Send document comments to vsg-docfeedback@cisco.com.

Examples for the Show Commands

The following example shows how to use the **show license usage** command to display the license usage:

```
n1000v# show license usage NEXUS_VSG_SERVICES_PKG
-----
Feature Usage Info
-----
      Installed Licenses : 10
      Default Eval Licenses : 0
      Max Overdraft Licenses : 16
      Installed Licenses in Use : 2
      Overdraft Licenses in Use : 0
      Default Eval Lic in Use : 0
      Licenses Available : 24
      Shortest Expiry      : 25 May 2010
-----
Application
-----
VEM 3 - Socket 1
VEM 4 - Socket 1
-----
```

The following example shows how to use the **show license brief** command to display the license name:

```
n1000v# show license brief
Enterprise.lic
n1000v#
```

The following example shows how to use the **show license file** command to display the evaluation license parameters:

```
n1000v# show license file eval.lic
SERVER this_host ANY
VENDOR cisco
INCREMENT NEXUS1_VSG_SERVICES_PKG cisco 1.0 1-dec-2010 16 \
  HOSTID=VDH=0871396331270074457 \
  NOTICE="<LicFileID>eval.lic</LicFileID><LicLineID>0</LicLineID> \
  <PAK>dummyPak</PAK>" SIGN=E08A38544DBE
```

The following example shows how to use the **show license file** command to display the evaluation license parameters:

```
n1000v# show license file Enterprise.lic
SERVER this_host ANY
VENDOR cisco
INCREMENT NEXUS_VSG_SERVICES_PKG cisco 1.0 permanent 16 \
  HOSTID=VDH=0871396331270074457 \
  NOTICE="<LicFileID>Enterprise.lic</LicFileID><LicLineID>0</LicLineID> \
  <PAK>dummyPak</PAK>" SIGN=E08A38544DBE
```


Send document comments to vsg-docfeedback@cisco.com.

Changing the Serial Number in a License

Use the following procedure to change the serial number, or host ID, associated with a license. This process is also called rehosting and is required if you replace a VSM in your network with a new VSM.

This section includes the following topics:

- [Flow Chart: Changing the Serial Number in a License, page 2-17](#)
- [Obtaining the License File, page 2-3](#)
- [Installing the License File on the VSM, page 2-5](#)
- [Verifying the License Configuration, page 2-14](#)




Caution

When you remove a VSM from your network, the vEthernet interfaces on the VEMs are removed from service and the traffic flowing to them from the virtual machines is dropped. This traffic flow is not resumed until you add a new VSM and new license file with the new host ID.

Flow Chart: Changing the Serial Number in a License

Use the flow chart in [Figure 2](#) to guide you through the process required to change the serial number, or host ID, in an existing license. After completing a procedure, return to the flow chart to make sure you complete all procedures in the correct sequence.

Figure 2 *Flow Chart: Changing the Serial Number in a License*



Send document comments to vsg-docfeedback@cisco.com.

Obtaining a License File for Rehosting

Use the following procedure to obtain a license file for a new VSM host, if the old VSM host is lost or destroyed.

BEFORE YOU BEGIN

Before beginning this procedure, you must know or do the following:

- A license file is tied to each VSM by the host ID, or the VSM serial number.
- You are logged in to the CLI in EXEC mode.
- You must copy a license file. Your username must have the network-admin role that allows you to copy files. For information about user accounts and roles, see the *Cisco Nexus 1000V Security Configuration Guide, Release 4.2(1)SVI(5.1)*.

PROCEDURE

Step 1 Obtain the serial number, also called the host ID, for your new VSM:

```
n1000v# show license host-id
License hostid: VDH=1280389551234985805
```



Note The host ID number appears after the equal sign (=). In this example, the host ID is 1280389551234985805. You will need the host ID in [Step 5](#).

Step 2 E-mail the following information to licensing@cisco.com, requesting the license file be rehosted to the new host ID:

- The new host ID
- A copy of the existing license file from the old VSM

A new license key file, with the host ID of the new VSM, is sent to you in an e-mail within 48 hours.



Note Do not modify the license key file. The license key file is invalidated if you modify it.

Step 3 Save your license to a TFTP server.

Step 4 Copy your license to bootflash on the VSM.

```
n1000v@ copy scp://user@linux-box.cisco.com/home/user/n1kv_license.lic bootflash:
Enter vrf (If no input, current vrf 'default' is considered):
user@linux-box.cisco.com's password:
n1kv_license.lic                               100% 252      0.3KB/s   00:00
n1000v@
```

Send document comments to vsg-docfeedback@cisco.com.

Feature History for Licenses

This section provides the release history for the license feature.

Feature Name	Releases	Feature Information
Evaluation license	4.0(4)SV1(3)	16 evaluation licenses that are good for 60 days are included in the software image. More evaluation licenses of varied durations can be downloaded from Cisco.com and installed separately.
Evaluation license	4.0(4)SV1(2)	Evaluation licenses are part of the software installation or upgrade. A separate evaluation license file no longer must be installed.
show license usage <i>package_name</i> command	4.0(4)SV1(2)	The show license usage <i>filename</i> command output is updated to show statistics about the number of evaluation and permanent licenses available, installed, and in use on the VSM.
License	4.0(4)SV1(1)	This feature was introduced.

Send document comments to vsg-docfeedback@cisco.com.