



IE 4000 MODBUS TCP Registers

First Published: July 8, 2019

This document lists the IE 4000-specific read-only registers for IE 4000 models. MODBUS clients use them to communicate with a MODBUS server (the switch). There are no writable registers. For information about MODBUS TCP, see [Configuring MODBUS TCP](#).

- [IE-4000-4TC4G-E, page 1](#)
- [IE-4000-8T4G-E, page 5](#)
- [IE-4000-8S4G-E, page 9](#)
- [IE-4000-4T4P4G-E, page 14](#)
- [IE-4000-16T4G-E, page 19](#)
- [IE-4000-4S8P4G-E, page 27](#)
- [IE-4000-8GT4G-E, page 32](#)
- [IE-4000-8GS4G-E, page 37](#)
- [IE-4000-4GC4GP4G-E, page 42](#)
- [IE-4000-16GT4G-E, page 47](#)
- [IE-4000-8GT8GP4G-E, page 54](#)
- [IE-4000-4GS8GP4G-E, page 61](#)

IE-4000-4TC4G-E

System Information Registers

Table 1 IE-4000-4TC4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command

Table 1 IE-4000-4TC4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
900	64	Alarm 1 description	R	Text	" Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	" Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 2 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 3 IE-4000-4TC4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	1	Port 1 State	R	Uint16
1201	1	Port 2 State	R	Uint16
1202	1	Port 3 State	R	Uint16
1203	1	Port 4 State	R	Uint16
1204	1	Port 5 State	R	Uint16
1205	1	Port 6 State	R	Uint16
1206	1	Port 7 State	R	Uint16
1207	1	Port 8 State	R	Uint16
1208	4	Port 1 Statistics - Number of packets received	R	Uint64
120C	4	Port 2 Statistics - Number of packets received	R	Uint64
1210	4	Port 3 Statistics - Number of packets received	R	Uint64
1214	4	Port 4 Statistics - Number of packets received	R	Uint64
1218	4	Port 5 Statistics - Number of packets received	R	Uint64
121C	4	Port 6 Statistics - Number of packets received	R	Uint64
1220	4	Port 7 Statistics - Number of packets received	R	Uint64
1224	4	Port 8 Statistics - Number of packets received	R	Uint64
1228	4	Port 1 Statistics - Number of packets sent	R	Uint64
122C	4	Port 2 Statistics - Number of packets sent	R	Uint64
1230	4	Port 3 Statistics - Number of packets sent	R	Uint64
1234	4	Port 4 Statistics - Number of packets sent	R	Uint64
1238	4	Port 5 Statistics - Number of packets sent	R	Uint64
123C	4	Port 6 Statistics - Number of packets sent	R	Uint64
1240	4	Port 7 Statistics - Number of packets sent	R	Uint64
1244	4	Port 8 Statistics - Number of packets sent	R	Uint64
1248	4	Port 1 Statistics - Number of bytes received	R	Uint64
124C	4	Port 2 Statistics - Number of bytes received	R	Uint64

Table 3 IE-4000-4TC4G-E Port Information Registers (continued)

1250	4	Port 3 Statistics – Number of bytes received	R	Uint64
1254	4	Port 4 Statistics – Number of bytes received	R	Uint64
1258	4	Port 5 Statistics – Number of bytes received	R	Uint64
125C	4	Port 6 Statistics – Number of bytes received	R	Uint64
1260	4	Port 7 Statistics – Number of bytes received	R	Uint64
1264	4	Port 8 Statistics – Number of bytes received	R	Uint64
1268	4	Port 1 Statistics – Number of bytes sent	R	Uint64
126C	4	Port 2 Statistics – Number of bytes sent	R	Uint64
1270	4	Port 3 Statistics – Number of bytes sent	R	Uint64
1274	4	Port 4 Statistics – Number of bytes sent	R	Uint64
1278	4	Port 5 Statistics – Number of bytes sent	R	Uint64
127C	4	Port 6 Statistics – Number of bytes sent	R	Uint64
1280	4	Port 7 Statistics – Number of bytes sent	R	Uint64
1284	4	Port 8 Statistics – Number of bytes sent	R	Uint64
1286	2	Port 1 Statistics – Number of packets received	R	Uint32
1288	2	Port 2 Statistics – Number of packets received	R	Uint32
128A	2	Port 3 Statistics – Number of packets received	R	Uint32
128C	2	Port 4 Statistics – Number of packets received	R	Uint32
128E	2	Port 5 Statistics – Number of packets received	R	Uint32
1290	2	Port 6 Statistics – Number of packets received	R	Uint32
1292	2	Port 7 Statistics – Number of packets received	R	Uint32
1294	2	Port 8 Statistics – Number of packets received	R	Uint32
1296	2	Port 1 Statistics – Number of packets sent	R	Uint32
1298	2	Port 2 Statistics – Number of packets sent	R	Uint32
129A	2	Port 3 Statistics – Number of packets sent	R	Uint32
129C	2	Port 4 Statistics – Number of packets sent	R	Uint32
129E	2	Port 5 Statistics – Number of packets sent	R	Uint32
12A0	2	Port 6 Statistics – Number of packets sent	R	Uint32
12A2	2	Port 7 Statistics – Number of packets sent	R	Uint32
12A4	2	Port 8 Statistics – Number of packets sent	R	Uint32
12A6	2	Port 1 Statistics – Number of bytes received	R	Uint32
12A8	2	Port 2 Statistics – Number of bytes received	R	Uint32
12AA	2	Port 3 Statistics – Number of bytes received	R	Uint32
12AC	2	Port 4 Statistics – Number of bytes received	R	Uint32
12AE	2	Port 5 Statistics – Number of bytes received	R	Uint32
12B0	2	Port 6 Statistics – Number of bytes received	R	Uint32
12B2	2	Port 7 Statistics – Number of bytes received	R	Uint32
12B4	2	Port 8 Statistics – Number of bytes received	R	Uint32

Table 3 IE-4000-4TC4G-E Port Information Registers (continued)

12B6	2	Port 1 Statistics - Number of bytes sent	R	Uint32
12B8	2	Port 2 Statistics - Number of bytes sent	R	Uint32
12BA	2	Port 3 Statistics - Number of bytes sent	R	Uint32
12BC	2	Port 4 Statistics - Number of bytes sent	R	Uint32
12BE	2	Port 5 Statistics - Number of bytes sent	R	Uint32
12C0	2	Port 6 Statistics - Number of bytes sent	R	Uint32
12C2	2	Port 7 Statistics - Number of bytes sent	R	Uint32
12C4	2	Port 8 Statistics - Number of bytes sent	R	Uint32

IE-4000-8T4G-E

System Information Registers

Table 4 IE-4000-8T4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 5 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 6 IE-4000-8T4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
12C1	1	Port 1 State	R	Uint16
12C2	1	Port 2 State	R	Uint16
12C2	1	Port 3 State	R	Uint16
12C3	1	Port 4 State	R	Uint16
12C4	1	Port 5 State	R	Uint16
12C5	1	Port 6 State	R	Uint16
12C6	1	Port 7 State	R	Uint16
12C7	1	Port 8 State	R	Uint16
12C8	1	Port 9 State	R	Uint16
12C9	1	Port 10 State	R	Uint16
12CA	1	Port 11 State	R	Uint16
12CB	1	Port 12 State	R	Uint16
12CC	4	Port 1 Statistics - Number of packets received	R	Uint64
12D0	4	Port 2 Statistics - Number of packets received	R	Uint64

Table 6 IE-4000-8T4G-E Port Information Registers (continued)

12D4	4	Port 3 Statistics - Number of packets received	R	Uint64
12D8	4	Port 4 Statistics - Number of packets received	R	Uint64
12DC	4	Port 5 Statistics - Number of packets received	R	Uint64
12E0	4	Port 6 Statistics - Number of packets received	R	Uint64
12E4	4	Port 7 Statistics - Number of packets received	R	Uint64
12E8	4	Port 8 Statistics - Number of packets received	R	Uint64
12EC	4	Port 9 Statistics - Number of packets received	R	Uint64
12F0	4	Port 10 Statistics - Number of packets received	R	Uint64
12F4	4	Port 11 Statistics - Number of packets received	R	Uint64
12F8	4	Port 12 Statistics - Number of packets received	R	Uint64
12FC	4	Port 1 Statistics - Number of packets sent	R	Uint64
1300	4	Port 2 Statistics - Number of packets sent	R	Uint64
1304	4	Port 3 Statistics - Number of packets sent	R	Uint64
1308	4	Port 4 Statistics - Number of packets sent	R	Uint64
130C	4	Port 5 Statistics - Number of packets sent	R	Uint64
1310	4	Port 6 Statistics - Number of packets sent	R	Uint64
1314	4	Port 7 Statistics - Number of packets sent	R	Uint64
1318	4	Port 8 Statistics - Number of packets sent	R	Uint64
131C	4	Port 9 Statistics - Number of packets sent	R	Uint64
1320	4	Port 10 Statistics - Number of packets sent	R	Uint64
1324	4	Port 11 Statistics - Number of packets sent	R	Uint64
1328	4	Port 12 Statistics - Number of packets sent	R	Uint64
132C	4	Port 1 Statistics - Number of bytes received	R	Uint64
1330	4	Port 2 Statistics - Number of bytes received	R	Uint64
1334	4	Port 3 Statistics - Number of bytes received	R	Uint64
1338	4	Port 4 Statistics - Number of bytes received	R	Uint64
133C	4	Port 5 Statistics - Number of bytes received	R	Uint64
1340	4	Port 6 Statistics - Number of bytes received	R	Uint64
1344	4	Port 7 Statistics - Number of bytes received	R	Uint64
1348	4	Port 8 Statistics - Number of bytes received	R	Uint64
134C	4	Port 9 Statistics - Number of bytes received	R	Uint64
1350	4	Port 10 Statistics - Number of bytes received	R	Uint64
1354	4	Port 11 Statistics - Number of bytes received	R	Uint64
1358	4	Port 12 Statistics - Number of bytes received	R	Uint64
135C	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1360	4	Port 2 Statistics - Number of bytes sent	R	Uint64
1364	4	Port 3 Statistics - Number of bytes sent	R	Uint64

Table 6 IE-4000-8T4G-E Port Information Registers (continued)

1368	4	Port 4 Statistics - Number of bytes sent	R	Uint64
136C	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1370	4	Port 6 Statistics - Number of bytes sent	R	Uint64
1374	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1378	4	Port 8 Statistics - Number of bytes sent	R	Uint64
137C	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1380	4	Port 10 Statistics - Number of bytes sent	R	Uint64
1384	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1388	4	Port 12 Statistics - Number of bytes sent	R	Uint64
138A	2	Port 1 Statistics - Number of packets received	R	Uint32
138C	2	Port 2 Statistics - Number of packets received	R	Uint32
138E	2	Port 3 Statistics - Number of packets received	R	Uint32
1390	2	Port 4 Statistics - Number of packets received	R	Uint32
1392	2	Port 5 Statistics - Number of packets received	R	Uint32
1394	2	Port 6 Statistics - Number of packets received	R	Uint32
1396	2	Port 7 Statistics - Number of packets received	R	Uint32
1398	2	Port 8 Statistics - Number of packets received	R	Uint32
139A	2	Port 9 Statistics - Number of packets received	R	Uint32
139C	2	Port 10 Statistics - Number of packets received	R	Uint32
139E	2	Port 11 Statistics - Number of packets received	R	Uint32
13A0	2	Port 12 Statistics - Number of packets received	R	Uint32
13A2	2	Port 1 Statistics - Number of packets sent	R	Uint32
13A4	2	Port 2 Statistics - Number of packets sent	R	Uint32
13A6	2	Port 3 Statistics - Number of packets sent	R	Uint32
13A8	2	Port 4 Statistics - Number of packets sent	R	Uint32
13AA	2	Port 5 Statistics - Number of packets sent	R	Uint32
13AC	2	Port 6 Statistics - Number of packets sent	R	Uint32
13AE	2	Port 7 Statistics - Number of packets sent	R	Uint32
13B0	2	Port 8 Statistics - Number of packets sent	R	Uint32
13B2	2	Port 9 Statistics - Number of packets sent	R	Uint32
13B4	2	Port 10 Statistics - Number of packets sent	R	Uint32
13B6	2	Port 11 Statistics - Number of packets sent	R	Uint32
13B8	2	Port 12 Statistics - Number of packets sent	R	Uint32
13BA	2	Port 1 Statistics - Number of bytes received	R	Uint32
13BC	2	Port 2 Statistics - Number of bytes received	R	Uint32
13BE	2	Port 3 Statistics - Number of bytes received	R	Uint32
13C0	2	Port 4 Statistics - Number of bytes received	R	Uint32
13C2	2	Port 5 Statistics - Number of bytes received	R	Uint32

Table 6 IE-4000-8T4G-E Port Information Registers (continued)

13C4	2	Port 6 Statistics - Number of bytes received	R	Uint32
13C6	2	Port 7 Statistics - Number of bytes received	R	Uint32
13C8	2	Port 8 Statistics - Number of bytes received	R	Uint32
13CA	2	Port 9 Statistics - Number of bytes received	R	Uint32
13CC	2	Port 10 Statistics - Number of bytes received	R	Uint32
13CE	2	Port 11 Statistics - Number of bytes received	R	Uint32
13D0	2	Port 12 Statistics - Number of bytes received	R	Uint32
13D2	2	Port 1 Statistics - Number of bytes sent	R	Uint32
13D4	2	Port 2 Statistics - Number of bytes sent	R	Uint32
13D8	2	Port 3 Statistics - Number of bytes sent	R	Uint32
13DA	2	Port 4 Statistics - Number of bytes sent	R	Uint32
13DC	2	Port 5 Statistics - Number of bytes sent	R	Uint32
13DE	2	Port 6 Statistics - Number of bytes sent	R	Uint32
13E0	2	Port 7 Statistics - Number of bytes sent	R	Uint32
13E2	2	Port 8 Statistics - Number of bytes sent	R	Uint32
13E4	2	Port 9 Statistics - Number of bytes sent	R	Uint32
13E6	2	Port 10 Statistics - Number of bytes sent	R	Uint32
13E8	2	Port 11 Statistics - Number of bytes sent	R	Uint32
13EA	2	Port 12 Statistics - Number of bytes sent	R	Uint32

IE-4000-8S4G-E

System Information Registers

Table 7 IE-4000-8S4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	

Table 7 IE-4000-8S4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 8 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 9 IE-4000-8S4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
12C1	1	Port 1 State	R	Uint16
12C2	1	Port 2 State	R	Uint16
12C3	1	Port 3 State	R	Uint16
12C4	1	Port 4 State	R	Uint16
12C5	1	Port 5 State	R	Uint16
12C6	1	Port 6 State	R	Uint16
12C7	1	Port 7 State	R	Uint16
12C8	1	Port 8 State	R	Uint16
12C9	1	Port 9 State	R	Uint16
12CA	1	Port 10 State	R	Uint16
12CB	1	Port 11 State	R	Uint16
12CC	4	Port 12 State	R	Uint16
12CC	4	Port 1 Statistics - Number of packets received	R	Uint64
12D0	4	Port 2 Statistics - Number of packets received	R	Uint64
12D4	4	Port 3 Statistics - Number of packets received	R	Uint64
12D8	4	Port 4 Statistics - Number of packets received	R	Uint64
12DC	4	Port 5 Statistics - Number of packets received	R	Uint64
12E0	4	Port 6 Statistics - Number of packets received	R	Uint64
12E4	4	Port 7 Statistics - Number of packets received	R	Uint64
12E8	4	Port 8 Statistics - Number of packets received	R	Uint64
12EC	4	Port 9 Statistics - Number of packets received	R	Uint64
12F0	4	Port 10 Statistics - Number of packets received	R	Uint64

Table 9 IE-4000-8S4G-E Port Information Registers (continued)

12F4	4	Port 11 Statistics - Number of packets received	R	Uint64
12F8	4	Port 12 Statistics - Number of packets received	R	Uint64
12FC	4	Port 1 Statistics - Number of packets sent	R	Uint64
1300	4	Port 2 Statistics - Number of packets sent	R	Uint64
1304	4	Port 3 Statistics - Number of packets sent	R	Uint64
1308	4	Port 4 Statistics - Number of packets sent	R	Uint64
130C	4	Port 5 Statistics - Number of packets sent	R	Uint64
1310	4	Port 6 Statistics - Number of packets sent	R	Uint64
1314	4	Port 7 Statistics - Number of packets sent	R	Uint64
1318	4	Port 8 Statistics - Number of packets sent	R	Uint64
131C	4	Port 9 Statistics - Number of packets sent	R	Uint64
1320	4	Port 10 Statistics - Number of packets sent	R	Uint64
1324	4	Port 11 Statistics - Number of packets sent	R	Uint64
1328	4	Port 12 Statistics - Number of packets sent	R	Uint64
132C	4	Port 1 Statistics - Number of bytes received	R	Uint64
1330	4	Port 2 Statistics - Number of bytes received	R	Uint64
1334	4	Port 3 Statistics - Number of bytes received	R	Uint64
1338	4	Port 4 Statistics - Number of bytes received	R	Uint64
133C	4	Port 5 Statistics - Number of bytes received	R	Uint64
1340	4	Port 6 Statistics - Number of bytes received	R	Uint64
1344	4	Port 7 Statistics - Number of bytes received	R	Uint64
1348	4	Port 8 Statistics - Number of bytes received	R	Uint64
134C	4	Port 9 Statistics - Number of bytes received	R	Uint64
1350	4	Port 10 Statistics - Number of bytes received	R	Uint64
1354	4	Port 11 Statistics - Number of bytes received	R	Uint64
1358	4	Port 12 Statistics - Number of bytes received	R	Uint64
135C	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1360	4	Port 2 Statistics - Number of bytes sent	R	Uint64
1364	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1368	4	Port 4 Statistics - Number of bytes sent	R	Uint64
136C	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1370	4	Port 6 Statistics - Number of bytes sent	R	Uint64
1374	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1378	4	Port 8 Statistics - Number of bytes sent	R	Uint64
137C	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1380	4	Port 10 Statistics - Number of bytes sent	R	Uint64
1384	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1388	4	Port 12 Statistics - Number of bytes sent	R	Uint64

Table 9 IE-4000-8S4G-E Port Information Registers (continued)

138A	2	Port 1 Statistics - Number of packets received	R	Uint32
138C	2	Port 2 Statistics - Number of packets received	R	Uint32
138E	2	Port 3 Statistics - Number of packets received	R	Uint32
1390	2	Port 4 Statistics - Number of packets received	R	Uint32
1392	2	Port 5 Statistics - Number of packets received	R	Uint32
1394	2	Port 6 Statistics - Number of packets received	R	Uint32
1396	2	Port 7 Statistics - Number of packets received	R	Uint32
1398	2	Port 8 Statistics - Number of packets received	R	Uint32
139A	2	Port 9 Statistics - Number of packets received	R	Uint32
139C	2	Port 10 Statistics - Number of packets received	R	Uint32
139E	2	Port 11 Statistics - Number of packets received	R	Uint32
13A0	2	Port 12 Statistics - Number of packets received	R	Uint32
13A2	2	Port 1 Statistics - Number of packets sent	R	Uint32
13A4	2	Port 2 Statistics - Number of packets sent	R	Uint32
13A6	2	Port 3 Statistics - Number of packets sent	R	Uint32
13A8	2	Port 4 Statistics - Number of packets sent	R	Uint32
13AA	2	Port 5 Statistics - Number of packets sent	R	Uint32
13AC	2	Port 6 Statistics - Number of packets sent	R	Uint32
13AE	2	Port 7 Statistics - Number of packets sent	R	Uint32
13B0	2	Port 8 Statistics - Number of packets sent	R	Uint32
13B2	2	Port 9 Statistics - Number of packets sent	R	Uint32
13B4	2	Port 10 Statistics - Number of packets sent	R	Uint32
13B6	2	Port 11 Statistics - Number of packets sent	R	Uint32
13B8	2	Port 12 Statistics - Number of packets sent	R	Uint32
13BA	2	Port 1 Statistics - Number of bytes received	R	Uint32
13BC	2	Port 2 Statistics - Number of bytes received	R	Uint32
13BE	2	Port 3 Statistics - Number of bytes received	R	Uint32
13C0	2	Port 4 Statistics - Number of bytes received	R	Uint32
13C2	2	Port 5 Statistics - Number of bytes received	R	Uint32
13C4	2	Port 6 Statistics - Number of bytes received	R	Uint32
13C6	2	Port 7 Statistics - Number of bytes received	R	Uint32
13C8	2	Port 8 Statistics - Number of bytes received	R	Uint32
13CA	2	Port 9 Statistics - Number of bytes received	R	Uint32
13CC	2	Port 10 Statistics - Number of bytes received	R	Uint32
13CE	2	Port 11 Statistics - Number of bytes received	R	Uint32
13D0	2	Port 12 Statistics - Number of bytes received	R	Uint32
13D2	2	Port 1 Statistics - Number of bytes sent	R	Uint32

Table 9 IE-4000-8S4G-E Port Information Registers (continued)

13D4	2	Port 2 Statistics - Number of bytes sent	R	Uint32
13D8	2	Port 3 Statistics - Number of bytes sent	R	Uint32
13DA	2	Port 4 Statistics - Number of bytes sent	R	Uint32
13DC	2	Port 5 Statistics - Number of bytes sent	R	Uint32
13DE	2	Port 6 Statistics - Number of bytes sent	R	Uint32
13E0	2	Port 7 Statistics - Number of bytes sent	R	Uint32
13E2	2	Port 8 Statistics - Number of bytes sent	R	Uint32
13E4	2	Port 9 Statistics - Number of bytes sent	R	Uint32
13E6	2	Port 10 Statistics - Number of bytes sent	R	Uint32
13E8	2	Port 11 Statistics - Number of bytes sent	R	Uint32
13EA	2	Port 12 Statistics - Number of bytes sent	R	Uint32

IE-4000-4T4P4G-E

System Information Registers

Table 10 IE-4000-4T4P4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command

Table 10 IE-4000-4T4P4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 11 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 12 IE-4000-4T4P4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
12C1	1	Port 1 State	R	Uint16
12C2	1	Port 2 State	R	Uint16
12C2	1	Port 3 State	R	Uint16
12C3	1	Port 4 State	R	Uint16
12C4	1	Port 5 State	R	Uint16
12C5	1	Port 6 State	R	Uint16
12C6	1	Port 7 State	R	Uint16
12C7	1	Port 8 State	R	Uint16
12C8	1	Port 9 State	R	Uint16
12C9	1	Port 10 State	R	Uint16
12CA	1	Port 11 State	R	Uint16
12CB	1	Port 12 State	R	Uint16
12CC	4	Port 1 Statistics - Number of packets received	R	Uint64
12D0	4	Port 2 Statistics - Number of packets received	R	Uint64
12D4	4	Port 3 Statistics - Number of packets received	R	Uint64
12D8	4	Port 4 Statistics - Number of packets received	R	Uint64
12DC	4	Port 5 Statistics - Number of packets received	R	Uint64
12E0	4	Port 6 Statistics - Number of packets received	R	Uint64
12E4	4	Port 7 Statistics - Number of packets received	R	Uint64
12E8	4	Port 8 Statistics - Number of packets received	R	Uint64
12EC	4	Port 9 Statistics - Number of packets received	R	Uint64
12F0	4	Port 10 Statistics - Number of packets received	R	Uint64
12F4	4	Port 11 Statistics - Number of packets received	R	Uint64

Table 12 IE-4000-4T4P4G-E Port Information Registers (continued)

12F8	4	Port 12 Statistics - Number of packets received	R	Uint64
12FC	4	Port 1 Statistics - Number of packets sent	R	Uint64
1300	4	Port 2 Statistics - Number of packets sent	R	Uint64
1304	4	Port 3 Statistics - Number of packets sent	R	Uint64
1308	4	Port 4 Statistics - Number of packets sent	R	Uint64
130C	4	Port 5 Statistics - Number of packets sent	R	Uint64
1310	4	Port 6 Statistics - Number of packets sent	R	Uint64
1314	4	Port 7 Statistics - Number of packets sent	R	Uint64
1318	4	Port 8 Statistics - Number of packets sent	R	Uint64
131C	4	Port 9 Statistics - Number of packets sent	R	Uint64
1320	4	Port 10 Statistics - Number of packets sent	R	Uint64
1324	4	Port 11 Statistics - Number of packets sent	R	Uint64
1328	4	Port 12 Statistics - Number of packets sent	R	Uint64
132C	4	Port 1 Statistics - Number of bytes received	R	Uint64
1330	4	Port 2 Statistics - Number of bytes received	R	Uint64
1334	4	Port 3 Statistics - Number of bytes received	R	Uint64
1338	4	Port 4 Statistics - Number of bytes received	R	Uint64
133C	4	Port 5 Statistics - Number of bytes received	R	Uint64
1340	4	Port 6 Statistics - Number of bytes received	R	Uint64
1344	4	Port 7 Statistics - Number of bytes received	R	Uint64
1348	4	Port 8 Statistics - Number of bytes received	R	Uint64
134C	4	Port 9 Statistics - Number of bytes received	R	Uint64
1350	4	Port 10 Statistics - Number of bytes received	R	Uint64
1354	4	Port 11 Statistics - Number of bytes received	R	Uint64
1358	4	Port 12 Statistics - Number of bytes received	R	Uint64
135C	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1360	4	Port 2 Statistics - Number of bytes sent	R	Uint64
1364	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1368	4	Port 4 Statistics - Number of bytes sent	R	Uint64
136C	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1370	4	Port 6 Statistics - Number of bytes sent	R	Uint64
1374	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1378	4	Port 8 Statistics - Number of bytes sent	R	Uint64
137C	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1380	4	Port 10 Statistics - Number of bytes sent	R	Uint64
1384	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1388	4	Port 12 Statistics - Number of bytes sent	R	Uint64

Table 12 IE-4000-4T4P4G-E Port Information Registers (continued)

138A	2	Port 1 Statistics - Number of packets received	R	Uint32
138C	2	Port 2 Statistics - Number of packets received	R	Uint32
138E	2	Port 3 Statistics - Number of packets received	R	Uint32
1390	2	Port 4 Statistics - Number of packets received	R	Uint32
1392	2	Port 5 Statistics - Number of packets received	R	Uint32
1394	2	Port 6 Statistics - Number of packets received	R	Uint32
1396	2	Port 7 Statistics - Number of packets received	R	Uint32
1398	2	Port 8 Statistics - Number of packets received	R	Uint32
139A	2	Port 9 Statistics - Number of packets received	R	Uint32
139C	2	Port 10 Statistics - Number of packets received	R	Uint32
139E	2	Port 11 Statistics - Number of packets received	R	Uint32
13A0	2	Port 12 Statistics - Number of packets received	R	Uint32
13A2	2	Port 1 Statistics - Number of packets sent	R	Uint32
13A4	2	Port 2 Statistics - Number of packets sent	R	Uint32
13A6	2	Port 3 Statistics - Number of packets sent	R	Uint32
13A8	2	Port 4 Statistics - Number of packets sent	R	Uint32
13AA	2	Port 5 Statistics - Number of packets sent	R	Uint32
13AC	2	Port 6 Statistics - Number of packets sent	R	Uint32
13AE	2	Port 7 Statistics - Number of packets sent	R	Uint32
13B0	2	Port 8 Statistics - Number of packets sent	R	Uint32
13B2	2	Port 9 Statistics - Number of packets sent	R	Uint32
13B4	2	Port 10 Statistics - Number of packets sent	R	Uint32
13B6	2	Port 11 Statistics - Number of packets sent	R	Uint32
13B8	2	Port 12 Statistics - Number of packets sent	R	Uint32
13BA	2	Port 1 Statistics - Number of bytes received	R	Uint32
13BC	2	Port 2 Statistics - Number of bytes received	R	Uint32
13BE	2	Port 3 Statistics - Number of bytes received	R	Uint32
13C0	2	Port 4 Statistics - Number of bytes received	R	Uint32
13C2	2	Port 5 Statistics - Number of bytes received	R	Uint32
13C4	2	Port 6 Statistics - Number of bytes received	R	Uint32
13C6	2	Port 7 Statistics - Number of bytes received	R	Uint32
13C8	2	Port 8 Statistics - Number of bytes received	R	Uint32
13CA	2	Port 9 Statistics - Number of bytes received	R	Uint32
13CC	2	Port 10 Statistics - Number of bytes received	R	Uint32
13CE	2	Port 11 Statistics - Number of bytes received	R	Uint32
13D0	2	Port 12 Statistics - Number of bytes received	R	Uint32
13D2	2	Port 1 Statistics - Number of bytes sent	R	Uint32
13D4	2	Port 2 Statistics - Number of bytes sent	R	Uint32

Table 12 IE-4000-4T4P4G-E Port Information Registers (continued)

13D8	2	Port 3 Statistics - Number of bytes sent	R	Uint32
13DA	2	Port 4 Statistics - Number of bytes sent	R	Uint32
13DC	2	Port 5 Statistics - Number of bytes sent	R	Uint32
13DE	2	Port 6 Statistics - Number of bytes sent	R	Uint32
13E0	2	Port 7 Statistics - Number of bytes sent	R	Uint32
13E2	2	Port 8 Statistics - Number of bytes sent	R	Uint32
13E4	2	Port 9 Statistics - Number of bytes sent	R	Uint32
13E6	2	Port 10 Statistics - Number of bytes sent	R	Uint32
13E8	2	Port 11 Statistics - Number of bytes sent	R	Uint32
13EA	2	Port 12 Statistics - Number of bytes sent	R	Uint32

IE-4000-16T4G-E

System Information Registers

Table 13 IE-4000-16T4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command

Table 13 IE-4000-16T4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 14 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 15 IE-4000-16T4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
1300	64	Port 13 Name	R	Text
1340	64	Port 14 Name	R	Text
1380	64	Port 15 Name	R	Text
13C0	64	Port 16 Name	R	Text
1400	64	Port 17 Name	R	Text
1440	64	Port 18 Name	R	Text
1480	64	Port 19 Name	R	Text
14C0	64	Port 20 Name	R	Text
1500	1	Port 1 State	R	Uint16
1501	1	Port 2 State	R	Uint16
1502	1	Port 3 State	R	Uint16
1503	1	Port 4 State	R	Uint16
1504	1	Port 5 State	R	Uint16
1505	1	Port 6 State	R	Uint16
1506	1	Port 7 State	R	Uint16
1507	1	Port 8 State	R	Uint16
1508	1	Port 9 State	R	Uint16
1509	1	Port 10 State	R	Uint16
150a	1	Port 11 State	R	Uint16
150b	1	Port 12 State	R	Uint16
150c	1	Port 13 State	R	Uint64
150d	1	Port 14 State	R	Uint64

Table 15 IE-4000-16T4G-E Port Information Registers (continued)

150e	1	Port 15 State	R	Uint64
150f	1	Port 16 State	R	Uint64
1510	1	Port 17 State	R	Uint64
1511	1	Port 18 State	R	Uint64
1512	1	Port 19 State	R	Uint64
1513	1	Port 20 State	R	Uint64
1514	4	Port 1 Statistics - Number of packets received	R	Uint64
1518	4	Port 2 Statistics - Number of packets received	R	Uint64
151c	4	Port 3 Statistics - Number of packets received	R	Uint64
1520	4	Port 4 Statistics - Number of packets received	R	Uint64
1524	4	Port 5 Statistics - Number of packets received	R	Uint64
1528	4	Port 6 Statistics - Number of packets received	R	Uint64
152c	4	Port 7 Statistics - Number of packets received	R	Uint64
1530	4	Port 8 Statistics - Number of packets received	R	Uint64
1534	4	Port 9 Statistics - Number of packets received	R	Uint64
1538	4	Port 10 Statistics - Number of packets received	R	Uint64
153c	4	Port 11 Statistics - Number of packets received	R	Uint64
1540	4	Port 12 Statistics - Number of packets received	R	Uint64
1544	4	Port 13 Statistics - Number of packets received	R	Uint64
1548	4	Port 14 Statistics - Number of packets received	R	Uint64
154c	4	Port 15 Statistics - Number of packets received	R	Uint64
1550	4	Port 16 Statistics - Number of packets received	R	Uint64
1554	4	Port 17 Statistics - Number of packets received	R	Uint64
1558	4	Port 18 Statistics - Number of packets received	R	Uint64
155c	4	Port 19 Statistics - Number of packets received	R	Uint64
1560	4	Port 20 Statistics - Number of packets received	R	Uint64
1564	4	Port 1 Statistics - Number of packets sent	R	Uint64
1568	4	Port 2 Statistics - Number of packets sent	R	Uint64
156c	4	Port 3 Statistics - Number of packets sent	R	Uint64
1570	4	Port 4 Statistics - Number of packets sent	R	Uint64
1574	4	Port 5 Statistics - Number of packets sent	R	Uint64
1578	4	Port 6 Statistics - Number of packets sent	R	Uint64
157c	4	Port 7 Statistics - Number of packets sent	R	Uint64
1580	4	Port 8 Statistics - Number of packets sent	R	Uint64
1584	4	Port 9 Statistics - Number of packets sent	R	Uint64
1588	4	Port 10 Statistics - Number of packets sent	R	Uint64
158c	4	Port 11 Statistics - Number of packets sent	R	Uint64
1590	4	Port 12 Statistics - Number of packets sent	R	Uint64

Table 15 IE-4000-16T4G-E Port Information Registers (continued)

1594	4	Port 13 Statistics - Number of packets sent	R	Uint64
1598	4	Port 14 Statistics - Number of packets sent	R	Uint64
159c	4	Port 15 Statistics - Number of packets sent	R	Uint64
15a0	4	Port 16 Statistics - Number of packets sent	R	Uint64
15a4	4	Port 17 Statistics - Number of packets sent	R	Uint64
15a8	4	Port 18 Statistics - Number of packets sent	R	Uint64
15ac	4	Port 19 Statistics - Number of packets sent	R	Uint64
15b0	4	Port 20 Statistics - Number of packets sent	R	Uint64
15b4	4	Port 1 Statistics - Number of bytes received	R	Uint64
15b8	4	Port 2 Statistics - Number of bytes received	R	Uint64
15bc	4	Port 3 Statistics - Number of bytes received	R	Uint64
15c0	4	Port 4 Statistics - Number of bytes received	R	Uint64
15c4	4	Port 5 Statistics - Number of bytes received	R	Uint64
15c8	4	Port 6 Statistics - Number of bytes received	R	Uint64
15cc	4	Port 7 Statistics - Number of bytes received	R	Uint64
15d0	4	Port 8 Statistics - Number of bytes received	R	Uint64
15d4	4	Port 9 Statistics - Number of bytes received	R	Uint64
15d8	4	Port 10 Statistics - Number of bytes received	R	Uint64
15dc	4	Port 11 Statistics - Number of bytes received	R	Uint64
15E0	4	Port 12 Statistics - Number of bytes received	R	Uint64
15E4	4	Port 13 Statistics - Number of bytes received	R	Uint64
15E8	4	Port 14 Statistics - Number of bytes received	R	Uint64
15ec	4	Port 15 Statistics - Number of bytes received	R	Uint64
15f0	4	Port 16 Statistics - Number of bytes received	R	Uint64
15f4	4	Port 17 Statistics - Number of bytes received	R	Uint64
15f8	4	Port 18 Statistics - Number of bytes received	R	Uint64
15fc	4	Port 19 Statistics - Number of bytes received	R	Uint64
1600	4	Port 20 Statistics - Number of bytes received	R	Uint64
1604	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1608	4	Port 2 Statistics - Number of bytes sent	R	Uint64
160c	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1610	4	Port 4 Statistics - Number of bytes sent	R	Uint64
1614	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1618	4	Port 6 Statistics - Number of bytes sent	R	Uint64
161c	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1620	4	Port 8 Statistics - Number of bytes sent	R	Uint64
1624	4	Port 9 Statistics - Number of bytes sent	R	Uint64

Table 15 IE-4000-16T4G-E Port Information Registers (continued)

1628	4	Port 10 Statistics - Number of bytes sent	R	Uint64
162c	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1630	4	Port 12 Statistics - Number of bytes sent	R	Uint64
1634	4	Port 13 Statistics - Number of bytes sent	R	Uint64
1638	4	Port 14 Statistics - Number of bytes sent	R	Uint64
163c	4	Port 15 Statistics - Number of bytes sent	R	Uint64
1640	4	Port 16 Statistics - Number of bytes sent	R	Uint64
1644	4	Port 17 Statistics - Number of bytes sent	R	Uint64
1648	4	Port 18 Statistics - Number of bytes sent	R	Uint64
164c	4	Port 19 Statistics - Number of bytes sent	R	Uint64
1650	4	Port 20 Statistics - Number of bytes sent	R	Uint64
1652	2	Port 1 Statistics - Number of packets received	R	Uint32
1654	2	Port 2 Statistics - Number of packets received	R	Uint32
1656	2	Port 3 Statistics - Number of packets received	R	Uint32
1658	2	Port 4 Statistics - Number of packets received	R	Uint32
165a	2	Port 5 Statistics - Number of packets received	R	Uint32
165c	2	Port 6 Statistics - Number of packets received	R	Uint32
165e	2	Port 7 Statistics - Number of packets received	R	Uint32
1660	2	Port 8 Statistics - Number of packets received	R	Uint32
1662	2	Port 9 Statistics - Number of packets received	R	Uint32
1664	2	Port 10 Statistics - Number of packets received	R	Uint32
1666	2	Port 11 Statistics - Number of packets received	R	Uint32
1668	2	Port 12 Statistics - Number of packets received	R	Uint32
166a	2	Port 13 Statistics - Number of packets received	R	Uint32
166c	2	Port 14 Statistics - Number of packets received	R	Uint32
166e	2	Port 15 Statistics - Number of packets received	R	Uint32
1670	2	Port 16 Statistics - Number of packets received	R	Uint32
1672	2	Port 17 Statistics - Number of packets received	R	Uint32
1674	2	Port 18 Statistics - Number of packets received	R	Uint32
1676	2	Port 19 Statistics - Number of packets received	R	Uint32
1678	2	Port 20 Statistics - Number of packets received	R	Uint32
167a	2	Port 1 Statistics - Number of packets sent	R	Uint32
167c	2	Port 2 Statistics - Number of packets sent	R	Uint32
167e	2	Port 3 Statistics - Number of packets sent	R	Uint32
1680	2	Port 4 Statistics - Number of packets sent	R	Uint32
1682	2	Port 5 Statistics - Number of packets sent	R	Uint32
1684	2	Port 6 Statistics - Number of packets sent	R	Uint32
1686	2	Port 7 Statistics - Number of packets sent	R	Uint32

Table 15 IE-4000-16T4G-E Port Information Registers (continued)

1688	2	Port 8 Statistics - Number of packets sent	R	Uint32
168a	2	Port 9 Statistics - Number of packets sent	R	Uint32
168c	2	Port 10 Statistics - Number of packets sent	R	Uint32
168e	2	Port 11 Statistics - Number of packets sent	R	Uint32
1690	2	Port 12 Statistics - Number of packets sent	R	Uint32
1692	2	Port 13 Statistics - Number of packets sent	R	Uint32
1694	2	Port 14 Statistics - Number of packets sent	R	Uint32
1696	2	Port 15 Statistics - Number of packets sent	R	Uint32
1698	2	Port 16 Statistics - Number of packets sent	R	Uint32
169a	2	Port 17 Statistics - Number of packets sent	R	Uint32
169c	2	Port 18 Statistics - Number of packets sent	R	Uint32
169e	2	Port 19 Statistics - Number of packets sent	R	Uint32
16a0	2	Port 20 Statistics - Number of packets sent	R	Uint32
16a2	2	Port 1 Statistics - Number of bytes received	R	Uint32
16a4	2	Port 2 Statistics - Number of bytes received	R	Uint32
16a6	2	Port 3 Statistics - Number of bytes received	R	Uint32
16a8	2	Port 4 Statistics - Number of bytes received	R	Uint32
16aa	2	Port 5 Statistics - Number of bytes received	R	Uint32
16ac	2	Port 6 Statistics - Number of bytes received	R	Uint32
16ae	2	Port 7 Statistics - Number of bytes received	R	Uint32
16b0	2	Port 8 Statistics - Number of bytes received	R	Uint32
16b2	2	Port 9 Statistics - Number of bytes received	R	Uint32
16b4	2	Port 10 Statistics - Number of bytes received	R	Uint32
16b6	2	Port 11 Statistics - Number of bytes received	R	Uint32
16b8	2	Port 12 Statistics - Number of bytes received	R	Uint32
16ba	2	Port 13 Statistics - Number of bytes received	R	Uint32
16bc	2	Port 14 Statistics - Number of bytes received	R	Uint32
16be	2	Port 15 Statistics - Number of bytes received	R	Uint32
16c0	2	Port 16 Statistics - Number of bytes received	R	Uint32
16c2	2	Port 17 Statistics - Number of bytes received	R	Uint32
16c4	2	Port 18 Statistics - Number of bytes received	R	Uint32
16c6	2	Port 19 Statistics - Number of bytes received	R	Uint32
16c8	2	Port 20 Statistics - Number of bytes received	R	Uint32
16ca	2	Port 1 Statistics - Number of bytes sent	R	Uint32
16cc	2	Port 2 Statistics - Number of bytes sent	R	Uint32
16ce	2	Port 3 Statistics - Number of bytes sent	R	Uint32
16d0	2	Port 4 Statistics - Number of bytes sent	R	Uint32

Table 15 IE-4000-16T4G-E Port Information Registers (continued)

16d2	2	Port 5 Statistics - Number of bytes sent	R	Uint32
16d4	2	Port 6 Statistics - Number of bytes sent	R	Uint32
16d6	2	Port 7 Statistics - Number of bytes sent	R	Uint32
16d8	2	Port 8 Statistics - Number of bytes sent	R	Uint32
16da	2	Port 9 Statistics - Number of bytes sent	R	Uint32
16dc	2	Port 10 Statistics - Number of bytes sent	R	Uint32
16de	2	Port 11 Statistics - Number of bytes sent	R	Uint32
16e0	2	Port 12 Statistics - Number of bytes sent	R	Uint32
16e0	2	Port 13 Statistics - Number of bytes sent	R	Uint32
16e2	2	Port 14 Statistics - Number of bytes sent	R	Uint32
16e4	2	Port 15 Statistics - Number of bytes sent	R	Uint32
16e8	2	Port 16 Statistics - Number of bytes sent	R	Uint32
16ea	2	Port 17 Statistics - Number of bytes sent	R	Uint32
16ec	2	Port 18 Statistics - Number of bytes sent	R	Uint32
16ee	2	Port 19 Statistics - Number of bytes sent	R	Uint32
16f0	2	Port 20 Statistics - Number of bytes sent	R	Uint32

IE-4000-4S8P4G-E

System Information Registers

Table 16 IE-4000-4S8P4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example	CLI Command
800	64	Product ID	R	Text	"IE-4000-8S4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSA LK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0F	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 17 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 18 IE-4000-4S8P4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
1300	64	Port 13 Name	R	Text
1340	64	Port 14 Name	R	Text
1380	64	Port 15 Name	R	Text
13C0	64	Port 16 Name	R	Text
1400	1	Port 1 State	R	Uint16
1401	1	Port 2 State	R	Uint16
1402	1	Port 3 State	R	Uint16
1403	1	Port 4 State	R	Uint16
1404	1	Port 5 State	R	Uint16
1405	1	Port 6 State	R	Uint16
1406	1	Port 7 State	R	Uint16
1407	1	Port 8 State	R	Uint16
1408	1	Port 9 State	R	Uint16
1409	1	Port 10 State	R	Uint16
140a	1	Port 11 State	R	Uint16
140b	1	Port 12 State	R	Uint16
140c	1	Port 13 State	R	Uint64
140d	1	Port 14 State	R	Uint64
140e	1	Port 15 State	R	Uint64
140f	1	Port 16 State	R	Uint64
1410	4	Port 1 Statistics - Number of packets received	R	Uint64
1414	4	Port 2 Statistics - Number of packets received	R	Uint64
1418	4	Port 3 Statistics - Number of packets received	R	Uint64
141c	4	Port 4 Statistics - Number of packets received	R	Uint64
1420	4	Port 5 Statistics - Number of packets received	R	Uint64

Table 18 IE-4000-4S8P4G-E Port Information Registers (continued)

Address in Hex	Number of Registers	Description	R/W	Format
1424	4	Port 6 Statistics - Number of packets received	R	Uint64
1428	4	Port 7 Statistics - Number of packets received	R	Uint64
142c	4	Port 8 Statistics - Number of packets received	R	Uint64
1430	4	Port 9 Statistics - Number of packets received	R	Uint64
1434	4	Port 10 Statistics - Number of packets received	R	Uint64
1438	4	Port 11 Statistics - Number of packets received	R	Uint64
143c	4	Port 12 Statistics - Number of packets received	R	Uint64
1440	4	Port 13 Statistics - Number of packets received	R	Uint64
1444	4	Port 14 Statistics - Number of packets received	R	Uint64
1448	4	Port 15 Statistics - Number of packets received	R	Uint64
144c	4	Port 16 Statistics - Number of packets received	R	Uint64
1450	4	Port 1 Statistics - Number of packets sent	R	Uint64
1454	4	Port 2 Statistics - Number of packets sent	R	Uint64
1458	4	Port 3 Statistics - Number of packets sent	R	Uint64
145c	4	Port 4 Statistics - Number of packets sent	R	Uint64
1460	4	Port 5 Statistics - Number of packets sent	R	Uint64
1464	4	Port 6 Statistics - Number of packets sent	R	Uint64
1468	4	Port 7 Statistics - Number of packets sent	R	Uint64
146c	4	Port 8 Statistics - Number of packets sent	R	Uint64
1470	4	Port 9 Statistics - Number of packets sent	R	Uint64
1474	4	Port 10 Statistics - Number of packets sent	R	Uint64
1478	4	Port 11 Statistics - Number of packets sent	R	Uint64
147c	4	Port 12 Statistics - Number of packets sent	R	Uint64
1480	4	Port 13 Statistics - Number of packets sent	R	Uint64
1484	4	Port 14 Statistics - Number of packets sent	R	Uint64
1488	4	Port 15 Statistics - Number of packets sent	R	Uint64
148c	4	Port 16 Statistics - Number of packets sent	R	Uint64
1490	4	Port 1 Statistics - Number of bytes received	R	Uint64
1494	4	Port 2 Statistics - Number of bytes received	R	Uint64
1498	4	Port 3 Statistics - Number of bytes received	R	Uint64
149c	4	Port 4 Statistics - Number of bytes received	R	Uint64
14a0	4	Port 5 Statistics - Number of bytes received	R	Uint64
14a4	4	Port 6 Statistics - Number of bytes received	R	Uint64
14a8	4	Port 7 Statistics - Number of bytes received	R	Uint64
14ac	4	Port 8 Statistics - Number of bytes received	R	Uint64
14b0	4	Port 9 Statistics - Number of bytes received	R	Uint64
14b4	4	Port 10 Statistics - Number of bytes received	R	Uint64

Table 18 IE-4000-4S8P4G-E Port Information Registers (continued)

Address in Hex	Number of Registers	Description	R/W	Format
14b8	4	Port 11 Statistics - Number of bytes received	R	Uint64
14bc	4	Port 12 Statistics - Number of bytes received	R	Uint64
14c0	4	Port 13 Statistics - Number of bytes received	R	Uint64
14c4	4	Port 14 Statistics - Number of bytes received	R	Uint64
14c8	4	Port 15 Statistics - Number of bytes received	R	Uint64
14cc	4	Port 16 Statistics - Number of bytes received	R	Uint64
14D0	4	Port 1 Statistics - Number of bytes sent	R	Uint64
14d4	4	Port 2 Statistics - Number of bytes sent	R	Uint64
14d8	4	Port 3 Statistics - Number of bytes sent	R	Uint64
14dc	4	Port 4 Statistics - Number of bytes sent	R	Uint64
14E0	4	Port 5 Statistics - Number of bytes sent	R	Uint64
14E4	4	Port 6 Statistics - Number of bytes sent	R	Uint64
14e8	4	Port 7 Statistics - Number of bytes sent	R	Uint64
14ec	4	Port 8 Statistics - Number of bytes sent	R	Uint64
14f0	4	Port 9 Statistics - Number of bytes sent	R	Uint64
14f4	4	Port 10 Statistics - Number of bytes sent	R	Uint64
14f8	4	Port 11 Statistics - Number of bytes sent	R	Uint64
14fc	4	Port 12 Statistics - Number of bytes sent	R	Uint64
1500	4	Port 13 Statistics - Number of bytes sent	R	Uint64
1504	4	Port 14 Statistics - Number of bytes sent	R	Uint64
1508	4	Port 15 Statistics - Number of bytes sent	R	Uint64
150c	4	Port 16 Statistics - Number of bytes sent	R	Uint64
150E	2	Port 1 Statistics - Number of packets received	R	Uint32
1510	2	Port 2 Statistics - Number of packets received	R	Uint32
1512	2	Port 3 Statistics - Number of packets received	R	Uint32
1514	2	Port 4 Statistics - Number of packets received	R	Uint32
1516	2	Port 5 Statistics - Number of packets received	R	Uint32
1518	2	Port 6 Statistics - Number of packets received	R	Uint32
151a	2	Port 7 Statistics - Number of packets received	R	Uint32
151c	2	Port 8 Statistics - Number of packets received	R	Uint32
151e	2	Port 9 Statistics - Number of packets received	R	Uint32
1520	2	Port 10 Statistics - Number of packets received	R	Uint32
1522	2	Port 11 Statistics - Number of packets received	R	Uint32
1524	2	Port 12 Statistics - Number of packets received	R	Uint32
1526	2	Port 13 Statistics - Number of packets received	R	Uint32
1528	2	Port 14 Statistics - Number of packets received	R	Uint32
152a	2	Port 15 Statistics - Number of packets received	R	Uint32
152c	2	Port 16 Statistics - Number of packets received	R	Uint32

Table 18 IE-4000-4S8P4G-E Port Information Registers (continued)

Address in Hex	Number of Registers	Description	R/W	Format
152E	2	Port 1 Statistics - Number of packets sent	R	Uint32
1530	2	Port 2 Statistics - Number of packets sent	R	Uint32
1532	2	Port 3 Statistics - Number of packets sent	R	Uint32
1534	2	Port 4 Statistics - Number of packets sent	R	Uint32
1536	2	Port 5 Statistics - Number of packets sent	R	Uint32
1538	2	Port 6 Statistics - Number of packets sent	R	Uint32
153a	2	Port 7 Statistics - Number of packets sent	R	Uint32
153c	2	Port 8 Statistics - Number of packets sent	R	Uint32
153e	2	Port 9 Statistics - Number of packets sent	R	Uint32
1540	2	Port 10 Statistics - Number of packets sent	R	Uint32
1542	2	Port 11 Statistics - Number of packets sent	R	Uint32
1544	2	Port 12 Statistics - Number of packets sent	R	Uint32
1546	2	Port 13 Statistics - Number of packets sent	R	Uint32
1548	2	Port 14 Statistics - Number of packets sent	R	Uint32
154a	2	Port 15 Statistics - Number of packets sent	R	Uint32
154c	2	Port 16 Statistics - Number of packets sent	R	Uint32
154E	2	Port 1 Statistics - Number of bytes received	R	Uint32
1550	2	Port 2 Statistics - Number of bytes received	R	Uint32
1552	2	Port 3 Statistics - Number of bytes received	R	Uint32
1554	2	Port 4 Statistics - Number of bytes received	R	Uint32
1556	2	Port 5 Statistics - Number of bytes received	R	Uint32
1558	2	Port 6 Statistics - Number of bytes received	R	Uint32
155a	2	Port 7 Statistics - Number of bytes received	R	Uint32
155c	2	Port 8 Statistics - Number of bytes received	R	Uint32
155e	2	Port 9 Statistics - Number of bytes received	R	Uint32
1560	2	Port 10 Statistics - Number of bytes received	R	Uint32
1562	2	Port 11 Statistics - Number of bytes received	R	Uint32
1564	2	Port 12 Statistics - Number of bytes received	R	Uint32
1566	2	Port 13 Statistics - Number of bytes received	R	Uint32
1568	2	Port 14 Statistics - Number of bytes received	R	Uint32
156a	2	Port 15 Statistics - Number of bytes received	R	Uint32
156c	2	Port 16 Statistics - Number of bytes received	R	Uint32
156E	2	Port 1 Statistics - Number of bytes sent	R	Uint32
1570	2	Port 2 Statistics - Number of bytes sent	R	Uint32
1572	2	Port 3 Statistics - Number of bytes sent	R	Uint32
1574	2	Port 4 Statistics - Number of bytes sent	R	Uint32
1576	2	Port 5 Statistics - Number of bytes sent	R	Uint32

Table 18 IE-4000-4S8P4G-E Port Information Registers (continued)

Address in Hex	Number of Registers	Description	R/W	Format
1578	2	Port 6 Statistics - Number of bytes sent	R	Uint32
157a	2	Port 7 Statistics - Number of bytes sent	R	Uint32
157c	2	Port 8 Statistics - Number of bytes sent	R	Uint32
157e	2	Port 9 Statistics - Number of bytes sent	R	Uint32
1580	2	Port 10 Statistics - Number of bytes sent	R	Uint32
1582	2	Port 11 Statistics - Number of bytes sent	R	Uint32
1584	2	Port 12 Statistics - Number of bytes sent	R	Uint32
1586	2	Port 13 Statistics - Number of bytes sent	R	Uint32
1588	2	Port 14 Statistics - Number of bytes sent	R	Uint32
158a	2	Port 15 Statistics - Number of bytes sent	R	Uint32
158c	2	Port 16 Statistics - Number of bytes sent	R	Uint32

IE-4000-8GT4G-E

System Information Registers

Table 19 IE-4000-8GT4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command

Table 19 IE-4000-8GT4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 20 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 21 IE-4000-8GT4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
12C1	1	Port 1 State	R	Uint16
12C2	1	Port 2 State	R	Uint16
12C2	1	Port 3 State	R	Uint16
12C3	1	Port 4 State	R	Uint16
12C4	1	Port 5 State	R	Uint16
12C5	1	Port 6 State	R	Uint16
12C6	1	Port 7 State	R	Uint16
12C7	1	Port 8 State	R	Uint16
12C8	1	Port 9 State	R	Uint16
12C9	1	Port 10 State	R	Uint16
12CA	1	Port 11 State	R	Uint16
12CB	1	Port 12 State	R	Uint16
12CC	4	Port 1 Statistics - Number of packets received	R	Uint64
12D0	4	Port 2 Statistics - Number of packets received	R	Uint64
12D4	4	Port 3 Statistics - Number of packets received	R	Uint64
12D8	4	Port 4 Statistics - Number of packets received	R	Uint64
12DC	4	Port 5 Statistics - Number of packets received	R	Uint64
12E0	4	Port 6 Statistics - Number of packets received	R	Uint64
12E4	4	Port 7 Statistics - Number of packets received	R	Uint64
12E8	4	Port 8 Statistics - Number of packets received	R	Uint64
12EC	4	Port 9 Statistics - Number of packets received	R	Uint64
12F0	4	Port 10 Statistics - Number of packets received	R	Uint64
12F4	4	Port 11 Statistics - Number of packets received	R	Uint64

Table 21 IE-4000-8GT4G-E Port Information Registers (continued)

12F8	4	Port 12 Statistics - Number of packets received	R	Uint64
12FC	4	Port 1 Statistics - Number of packets sent	R	Uint64
1300	4	Port 2 Statistics - Number of packets sent	R	Uint64
1304	4	Port 3 Statistics - Number of packets sent	R	Uint64
1308	4	Port 4 Statistics - Number of packets sent	R	Uint64
130C	4	Port 5 Statistics - Number of packets sent	R	Uint64
1310	4	Port 6 Statistics - Number of packets sent	R	Uint64
1314	4	Port 7 Statistics - Number of packets sent	R	Uint64
1318	4	Port 8 Statistics - Number of packets sent	R	Uint64
131C	4	Port 9 Statistics - Number of packets sent	R	Uint64
1320	4	Port 10 Statistics - Number of packets sent	R	Uint64
1324	4	Port 11 Statistics - Number of packets sent	R	Uint64
1328	4	Port 12 Statistics - Number of packets sent	R	Uint64
132C	4	Port 1 Statistics - Number of bytes received	R	Uint64
1330	4	Port 2 Statistics - Number of bytes received	R	Uint64
1334	4	Port 3 Statistics - Number of bytes received	R	Uint64
1338	4	Port 4 Statistics - Number of bytes received	R	Uint64
133C	4	Port 5 Statistics - Number of bytes received	R	Uint64
1340	4	Port 6 Statistics - Number of bytes received	R	Uint64
1344	4	Port 7 Statistics - Number of bytes received	R	Uint64
1348	4	Port 8 Statistics - Number of bytes received	R	Uint64
134C	4	Port 9 Statistics - Number of bytes received	R	Uint64
1350	4	Port 10 Statistics - Number of bytes received	R	Uint64
1354	4	Port 11 Statistics - Number of bytes received	R	Uint64
1358	4	Port 12 Statistics - Number of bytes received	R	Uint64
135C	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1360	4	Port 2 Statistics - Number of bytes sent	R	Uint64
1364	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1368	4	Port 4 Statistics - Number of bytes sent	R	Uint64
136C	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1370	4	Port 6 Statistics - Number of bytes sent	R	Uint64
1374	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1378	4	Port 8 Statistics - Number of bytes sent	R	Uint64
137C	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1380	4	Port 10 Statistics - Number of bytes sent	R	Uint64
1384	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1388	4	Port 12 Statistics - Number of bytes sent	R	Uint64

Table 21 IE-4000-8GT4G-E Port Information Registers (continued)

138A	2	Port 1 Statistics - Number of packets received	R	Uint32
138C	2	Port 2 Statistics - Number of packets received	R	Uint32
138E	2	Port 3 Statistics - Number of packets received	R	Uint32
1390	2	Port 4 Statistics - Number of packets received	R	Uint32
1392	2	Port 5 Statistics - Number of packets received	R	Uint32
1394	2	Port 6 Statistics - Number of packets received	R	Uint32
1396	2	Port 7 Statistics - Number of packets received	R	Uint32
1398	2	Port 8 Statistics - Number of packets received	R	Uint32
139A	2	Port 9 Statistics - Number of packets received	R	Uint32
139C	2	Port 10 Statistics - Number of packets received	R	Uint32
139E	2	Port 11 Statistics - Number of packets received	R	Uint32
13A0	2	Port 12 Statistics - Number of packets received	R	Uint32
13A2	2	Port 1 Statistics - Number of packets sent	R	Uint32
13A4	2	Port 2 Statistics - Number of packets sent	R	Uint32
13A6	2	Port 3 Statistics - Number of packets sent	R	Uint32
13A8	2	Port 4 Statistics - Number of packets sent	R	Uint32
13AA	2	Port 5 Statistics - Number of packets sent	R	Uint32
13AC	2	Port 6 Statistics - Number of packets sent	R	Uint32
13AE	2	Port 7 Statistics - Number of packets sent	R	Uint32
13B0	2	Port 8 Statistics - Number of packets sent	R	Uint32
13B2	2	Port 9 Statistics - Number of packets sent	R	Uint32
13B4	2	Port 10 Statistics - Number of packets sent	R	Uint32
13B6	2	Port 11 Statistics - Number of packets sent	R	Uint32
13B8	2	Port 12 Statistics - Number of packets sent	R	Uint32
13BA	2	Port 1 Statistics - Number of bytes received	R	Uint32
13BC	2	Port 2 Statistics - Number of bytes received	R	Uint32
13BE	2	Port 3 Statistics - Number of bytes received	R	Uint32
13C0	2	Port 4 Statistics - Number of bytes received	R	Uint32
13C2	2	Port 5 Statistics - Number of bytes received	R	Uint32
13C4	2	Port 6 Statistics - Number of bytes received	R	Uint32
13C6	2	Port 7 Statistics - Number of bytes received	R	Uint32
13C8	2	Port 8 Statistics - Number of bytes received	R	Uint32
13CA	2	Port 9 Statistics - Number of bytes received	R	Uint32
13CC	2	Port 10 Statistics - Number of bytes received	R	Uint32
13CE	2	Port 11 Statistics - Number of bytes received	R	Uint32
13D0	2	Port 12 Statistics - Number of bytes received	R	Uint32
13D2	2	Port 1 Statistics - Number of bytes sent	R	Uint32
13D4	2	Port 2 Statistics - Number of bytes sent	R	Uint32

Table 21 IE-4000-8GT4G-E Port Information Registers (continued)

13D8	2	Port 3 Statistics - Number of bytes sent	R	Uint32
13DA	2	Port 4 Statistics - Number of bytes sent	R	Uint32
13DC	2	Port 5 Statistics - Number of bytes sent	R	Uint32
13DE	2	Port 6 Statistics - Number of bytes sent	R	Uint32
13E0	2	Port 7 Statistics - Number of bytes sent	R	Uint32
13E2	2	Port 8 Statistics - Number of bytes sent	R	Uint32
13E4	2	Port 9 Statistics - Number of bytes sent	R	Uint32
13E6	2	Port 10 Statistics - Number of bytes sent	R	Uint32
13E8	2	Port 11 Statistics - Number of bytes sent	R	Uint32
13EA	2	Port 12 Statistics - Number of bytes sent	R	Uint32

IE-4000-8GS4G-E

System Information Registers

Table 22 IE-4000-8GS4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command

Table 22 IE-4000-8GS4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 23 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 24 IE-4000-8GS4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
12C1	1	Port 1 State	R	Uint16
12C2	1	Port 2 State	R	Uint16
12C3	1	Port 3 State	R	Uint16
12C4	1	Port 4 State	R	Uint16
12C5	1	Port 5 State	R	Uint16
12C6	1	Port 6 State	R	Uint16
12C7	1	Port 7 State	R	Uint16
12C8	1	Port 8 State	R	Uint16
12C9	1	Port 9 State	R	Uint16
12CA	1	Port 10 State	R	Uint16
12CB	1	Port 11 State	R	Uint16
12CC	4	Port 12 State	R	Uint16
12CC	4	Port 1 Statistics - Number of packets received	R	Uint64
12D0	4	Port 2 Statistics - Number of packets received	R	Uint64
12D4	4	Port 3 Statistics - Number of packets received	R	Uint64
12D8	4	Port 4 Statistics - Number of packets received	R	Uint64
12DC	4	Port 5 Statistics - Number of packets received	R	Uint64
12E0	4	Port 6 Statistics - Number of packets received	R	Uint64
120000	4	Port 7 Statistics - Number of packets received	R	Uint64
12E8	4	Port 8 Statistics - Number of packets received	R	Uint64
12EC	4	Port 9 Statistics - Number of packets received	R	Uint64
12F0	4	Port 10 Statistics - Number of packets received	R	Uint64

Table 24 IE-4000-8GS4G-E Port Information Registers (continued)

12F4	4	Port 11 Statistics - Number of packets received	R	Uint64
12F8	4	Port 12 Statistics - Number of packets received	R	Uint64
12FC	4	Port 1 Statistics - Number of packets sent	R	Uint64
1300	4	Port 2 Statistics - Number of packets sent	R	Uint64
1304	4	Port 3 Statistics - Number of packets sent	R	Uint64
1308	4	Port 4 Statistics - Number of packets sent	R	Uint64
130C	4	Port 5 Statistics - Number of packets sent	R	Uint64
1310	4	Port 6 Statistics - Number of packets sent	R	Uint64
1314	4	Port 7 Statistics - Number of packets sent	R	Uint64
1318	4	Port 8 Statistics - Number of packets sent	R	Uint64
131C	4	Port 9 Statistics - Number of packets sent	R	Uint64
1320	4	Port 10 Statistics - Number of packets sent	R	Uint64
1324	4	Port 11 Statistics - Number of packets sent	R	Uint64
1328	4	Port 12 Statistics - Number of packets sent	R	Uint64
132C	4	Port 1 Statistics - Number of bytes received	R	Uint64
1330	4	Port 2 Statistics - Number of bytes received	R	Uint64
1334	4	Port 3 Statistics - Number of bytes received	R	Uint64
1338	4	Port 4 Statistics - Number of bytes received	R	Uint64
133C	4	Port 5 Statistics - Number of bytes received	R	Uint64
1340	4	Port 6 Statistics - Number of bytes received	R	Uint64
1344	4	Port 7 Statistics - Number of bytes received	R	Uint64
1348	4	Port 8 Statistics - Number of bytes received	R	Uint64
134C	4	Port 9 Statistics - Number of bytes received	R	Uint64
1350	4	Port 10 Statistics - Number of bytes received	R	Uint64
1354	4	Port 11 Statistics - Number of bytes received	R	Uint64
1358	4	Port 12 Statistics - Number of bytes received	R	Uint64
135C	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1360	4	Port 2 Statistics - Number of bytes sent	R	Uint64
1364	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1368	4	Port 4 Statistics - Number of bytes sent	R	Uint64
136C	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1370	4	Port 6 Statistics - Number of bytes sent	R	Uint64
1374	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1378	4	Port 8 Statistics - Number of bytes sent	R	Uint64
137C	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1380	4	Port 10 Statistics - Number of bytes sent	R	Uint64
1384	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1388	4	Port 12 Statistics - Number of bytes sent	R	Uint64

Table 24 IE-4000-8GS4G-E Port Information Registers (continued)

138A	2	Port 1 Statistics - Number of packets received	R	Uint32
138C	2	Port 2 Statistics - Number of packets received	R	Uint32
138E	2	Port 3 Statistics - Number of packets received	R	Uint32
1390	2	Port 4 Statistics - Number of packets received	R	Uint32
1392	2	Port 5 Statistics - Number of packets received	R	Uint32
1394	2	Port 6 Statistics - Number of packets received	R	Uint32
1396	2	Port 7 Statistics - Number of packets received	R	Uint32
1398	2	Port 8 Statistics - Number of packets received	R	Uint32
139A	2	Port 9 Statistics - Number of packets received	R	Uint32
139C	2	Port 10 Statistics - Number of packets received	R	Uint32
139E	2	Port 11 Statistics - Number of packets received	R	Uint32
13A0	2	Port 12 Statistics - Number of packets received	R	Uint32
13A2	2	Port 1 Statistics - Number of packets sent	R	Uint32
13A4	2	Port 2 Statistics - Number of packets sent	R	Uint32
13A6	2	Port 3 Statistics - Number of packets sent	R	Uint32
13A8	2	Port 4 Statistics - Number of packets sent	R	Uint32
13AA	2	Port 5 Statistics - Number of packets sent	R	Uint32
13AC	2	Port 6 Statistics - Number of packets sent	R	Uint32
13AE	2	Port 7 Statistics - Number of packets sent	R	Uint32
13B0	2	Port 8 Statistics - Number of packets sent	R	Uint32
13B2	2	Port 9 Statistics - Number of packets sent	R	Uint32
13B4	2	Port 10 Statistics - Number of packets sent	R	Uint32
13B6	2	Port 11 Statistics - Number of packets sent	R	Uint32
13B8	2	Port 12 Statistics - Number of packets sent	R	Uint32
13BA	2	Port 1 Statistics - Number of bytes received	R	Uint32
13BC	2	Port 2 Statistics - Number of bytes received	R	Uint32
13BE	2	Port 3 Statistics - Number of bytes received	R	Uint32
13C0	2	Port 4 Statistics - Number of bytes received	R	Uint32
13C2	2	Port 5 Statistics - Number of bytes received	R	Uint32
13C4	2	Port 6 Statistics - Number of bytes received	R	Uint32
13C6	2	Port 7 Statistics - Number of bytes received	R	Uint32
13C8	2	Port 8 Statistics - Number of bytes received	R	Uint32
13CA	2	Port 9 Statistics - Number of bytes received	R	Uint32
13CC	2	Port 10 Statistics - Number of bytes received	R	Uint32
13CE	2	Port 11 Statistics - Number of bytes received	R	Uint32
13D0	2	Port 12 Statistics - Number of bytes received	R	Uint32
13D2	2	Port 1 Statistics - Number of bytes sent	R	Uint32

Table 24 IE-4000-8GS4G-E Port Information Registers (continued)

13D4	2	Port 2 Statistics - Number of bytes sent	R	Uint32
13D8	2	Port 3 Statistics - Number of bytes sent	R	Uint32
13DA	2	Port 4 Statistics - Number of bytes sent	R	Uint32
13DC	2	Port 5 Statistics - Number of bytes sent	R	Uint32
13DE	2	Port 6 Statistics - Number of bytes sent	R	Uint32
13E0	2	Port 7 Statistics - Number of bytes sent	R	Uint32
13E2	2	Port 8 Statistics - Number of bytes sent	R	Uint32
13E4	2	Port 9 Statistics - Number of bytes sent	R	Uint32
13E6	2	Port 10 Statistics - Number of bytes sent	R	Uint32
13E8	2	Port 11 Statistics - Number of bytes sent	R	Uint32
13EA	2	Port 12 Statistics - Number of bytes sent	R	Uint32

IE-4000-4GC4GP4G-E

System Information Registers

Table 25 IE-4000-4GC4GP4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command

Table 25 IE-4000-4GC4GP4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 26 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 27 IE-4000-4GC4GP4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
12C1	1	Port 1 State	R	Uint16
12C2	1	Port 2 State	R	Uint16
12C2	1	Port 3 State	R	Uint16
12C3	1	Port 4 State	R	Uint16
12C4	1	Port 5 State	R	Uint16
12C5	1	Port 6 State	R	Uint16
12C6	1	Port 7 State	R	Uint16
12C7	1	Port 8 State	R	Uint16
12C8	1	Port 9 State	R	Uint16
12C9	1	Port 10 State	R	Uint16
12CA	1	Port 11 State	R	Uint16
12CB	1	Port 12 State	R	Uint16
12CC	4	Port 1 Statistics - Number of packets received	R	Uint64
12D0	4	Port 2 Statistics - Number of packets received	R	Uint64
12D4	4	Port 3 Statistics - Number of packets received	R	Uint64
12D8	4	Port 4 Statistics - Number of packets received	R	Uint64
12DC	4	Port 5 Statistics - Number of packets received	R	Uint64
12E0	4	Port 6 Statistics - Number of packets received	R	Uint64
120000	4	Port 7 Statistics - Number of packets received	R	Uint64
12E8	4	Port 8 Statistics - Number of packets received	R	Uint64
12EC	4	Port 9 Statistics - Number of packets received	R	Uint64
12F0	4	Port 10 Statistics - Number of packets received	R	Uint64
12F4	4	Port 11 Statistics - Number of packets received	R	Uint64

Table 27 IE-4000-4GC4GP4G-E Port Information Registers (continued)

12F8	4	Port 12 Statistics - Number of packets received	R	Uint64
12FC	4	Port 1 Statistics - Number of packets sent	R	Uint64
1300	4	Port 2 Statistics - Number of packets sent	R	Uint64
1304	4	Port 3 Statistics - Number of packets sent	R	Uint64
1308	4	Port 4 Statistics - Number of packets sent	R	Uint64
130C	4	Port 5 Statistics - Number of packets sent	R	Uint64
1310	4	Port 6 Statistics - Number of packets sent	R	Uint64
1314	4	Port 7 Statistics - Number of packets sent	R	Uint64
1318	4	Port 8 Statistics - Number of packets sent	R	Uint64
131C	4	Port 9 Statistics - Number of packets sent	R	Uint64
1320	4	Port 10 Statistics - Number of packets sent	R	Uint64
1324	4	Port 11 Statistics - Number of packets sent	R	Uint64
1328	4	Port 12 Statistics - Number of packets sent	R	Uint64
132C	4	Port 1 Statistics - Number of bytes received	R	Uint64
1330	4	Port 2 Statistics - Number of bytes received	R	Uint64
1334	4	Port 3 Statistics - Number of bytes received	R	Uint64
1338	4	Port 4 Statistics - Number of bytes received	R	Uint64
133C	4	Port 5 Statistics - Number of bytes received	R	Uint64
1340	4	Port 6 Statistics - Number of bytes received	R	Uint64
1344	4	Port 7 Statistics - Number of bytes received	R	Uint64
1348	4	Port 8 Statistics - Number of bytes received	R	Uint64
134C	4	Port 9 Statistics - Number of bytes received	R	Uint64
1350	4	Port 10 Statistics - Number of bytes received	R	Uint64
1354	4	Port 11 Statistics - Number of bytes received	R	Uint64
1358	4	Port 12 Statistics - Number of bytes received	R	Uint64
135C	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1360	4	Port 2 Statistics - Number of bytes sent	R	Uint64
1364	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1368	4	Port 4 Statistics - Number of bytes sent	R	Uint64
136C	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1370	4	Port 6 Statistics - Number of bytes sent	R	Uint64
1374	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1378	4	Port 8 Statistics - Number of bytes sent	R	Uint64
137C	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1380	4	Port 10 Statistics - Number of bytes sent	R	Uint64
1384	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1388	4	Port 12 Statistics - Number of bytes sent	R	Uint64

Table 27 IE-4000-4GC4GP4G-E Port Information Registers (continued)

138A	2	Port 1 Statistics – Number of packets received	R	Uint32
138C	2	Port 2 Statistics – Number of packets received	R	Uint32
138E	2	Port 3 Statistics – Number of packets received	R	Uint32
1390	2	Port 4 Statistics – Number of packets received	R	Uint32
1392	2	Port 5 Statistics – Number of packets received	R	Uint32
1394	2	Port 6 Statistics – Number of packets received	R	Uint32
1396	2	Port 7 Statistics – Number of packets received	R	Uint32
1398	2	Port 8 Statistics – Number of packets received	R	Uint32
139A	2	Port 9 Statistics – Number of packets received	R	Uint32
139C	2	Port 10 Statistics – Number of packets received	R	Uint32
139E	2	Port 11 Statistics – Number of packets received	R	Uint32
13A0	2	Port 12 Statistics – Number of packets received	R	Uint32
13A2	2	Port 1 Statistics – Number of packets sent	R	Uint32
13A4	2	Port 2 Statistics – Number of packets sent	R	Uint32
13A6	2	Port 3 Statistics – Number of packets sent	R	Uint32
13A8	2	Port 4 Statistics – Number of packets sent	R	Uint32
13AA	2	Port 5 Statistics – Number of packets sent	R	Uint32
13AC	2	Port 6 Statistics – Number of packets sent	R	Uint32
13AE	2	Port 7 Statistics – Number of packets sent	R	Uint32
13B0	2	Port 8 Statistics – Number of packets sent	R	Uint32
13B2	2	Port 9 Statistics – Number of packets sent	R	Uint32
13B4	2	Port 10 Statistics – Number of packets sent	R	Uint32
13B6	2	Port 11 Statistics – Number of packets sent	R	Uint32
13B8	2	Port 12 Statistics – Number of packets sent	R	Uint32
13BA	2	Port 1 Statistics – Number of bytes received	R	Uint32
13BC	2	Port 2 Statistics – Number of bytes received	R	Uint32
13BE	2	Port 3 Statistics – Number of bytes received	R	Uint32
13C0	2	Port 4 Statistics – Number of bytes received	R	Uint32
13C2	2	Port 5 Statistics – Number of bytes received	R	Uint32
13C4	2	Port 6 Statistics – Number of bytes received	R	Uint32
13C6	2	Port 7 Statistics – Number of bytes received	R	Uint32
13C8	2	Port 8 Statistics – Number of bytes received	R	Uint32
13CA	2	Port 9 Statistics – Number of bytes received	R	Uint32
13CC	2	Port 10 Statistics – Number of bytes received	R	Uint32
13CE	2	Port 11 Statistics – Number of bytes received	R	Uint32
13D0	2	Port 12 Statistics – Number of bytes received	R	Uint32
13D2	2	Port 1 Statistics – Number of bytes sent	R	Uint32
13D4	2	Port 2 Statistics – Number of bytes sent	R	Uint32

Table 27 IE-4000-4GC4GP4G-E Port Information Registers (continued)

13D8	2	Port 3 Statistics - Number of bytes sent	R	Uint32
13DA	2	Port 4 Statistics - Number of bytes sent	R	Uint32
13DC	2	Port 5 Statistics - Number of bytes sent	R	Uint32
13DE	2	Port 6 Statistics - Number of bytes sent	R	Uint32
13E0	2	Port 7 Statistics - Number of bytes sent	R	Uint32
13E2	2	Port 8 Statistics - Number of bytes sent	R	Uint32
13E4	2	Port 9 Statistics - Number of bytes sent	R	Uint32
13E6	2	Port 10 Statistics - Number of bytes sent	R	Uint32
13E8	2	Port 11 Statistics - Number of bytes sent	R	Uint32
13EA	2	Port 12 Statistics - Number of bytes sent	R	Uint32

IE-4000-16GT4G-E

System Information Registers

Table 28 IE-4000-16GT4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command

Table 28 IE-4000-16GT4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 29 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 30 IE-4000-16GT4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
1300	64	Port 13 Name	R	Text
1340	64	Port 14 Name	R	Text
1380	64	Port 15 Name	R	Text
13C0	64	Port 16 Name	R	Text
1400	64	Port 17 Name	R	Text
1440	64	Port 18 Name	R	Text
1480	64	Port 19 Name	R	Text
14C0	64	Port 20 Name	R	Text
1500	1	Port 1 State	R	Uint16
1501	1	Port 2 State	R	Uint16
1502	1	Port 3 State	R	Uint16
1503	1	Port 4 State	R	Uint16
1504	1	Port 5 State	R	Uint16
1505	1	Port 6 State	R	Uint16
1506	1	Port 7 State	R	Uint16
1507	1	Port 8 State	R	Uint16
1508	1	Port 9 State	R	Uint16
1509	1	Port 10 State	R	Uint16
150a	1	Port 11 State	R	Uint16
150b	1	Port 12 State	R	Uint16
150c	1	Port 13 State	R	Uint64
150d	1	Port 14 State	R	Uint64

Table 30 IE-4000-16GT4G-E Port Information Registers (continued)

150e	1	Port 15 State	R	Uint64
150f	1	Port 16 State	R	Uint64
1510	1	Port 17 State	R	Uint64
1511	1	Port 18 State	R	Uint64
1512	1	Port 19 State	R	Uint64
1513	1	Port 20 State	R	Uint64
1514	4	Port 1 Statistics - Number of packets received	R	Uint64
1518	4	Port 2 Statistics - Number of packets received	R	Uint64
151c	4	Port 3 Statistics - Number of packets received	R	Uint64
1520	4	Port 4 Statistics - Number of packets received	R	Uint64
1524	4	Port 5 Statistics - Number of packets received	R	Uint64
1528	4	Port 6 Statistics - Number of packets received	R	Uint64
152c	4	Port 7 Statistics - Number of packets received	R	Uint64
1530	4	Port 8 Statistics - Number of packets received	R	Uint64
1534	4	Port 9 Statistics - Number of packets received	R	Uint64
1538	4	Port 10 Statistics - Number of packets received	R	Uint64
153c	4	Port 11 Statistics - Number of packets received	R	Uint64
1540	4	Port 12 Statistics - Number of packets received	R	Uint64
1544	4	Port 13 Statistics - Number of packets received	R	Uint64
1548	4	Port 14 Statistics - Number of packets received	R	Uint64
154c	4	Port 15 Statistics - Number of packets received	R	Uint64
1550	4	Port 16 Statistics - Number of packets received	R	Uint64
1554	4	Port 17 Statistics - Number of packets received	R	Uint64
1558	4	Port 18 Statistics - Number of packets received	R	Uint64
155c	4	Port 19 Statistics - Number of packets received	R	Uint64
1560	4	Port 20 Statistics - Number of packets received	R	Uint64
1564	4	Port 1 Statistics - Number of packets sent	R	Uint64
1568	4	Port 2 Statistics - Number of packets sent	R	Uint64
156c	4	Port 3 Statistics - Number of packets sent	R	Uint64
1570	4	Port 4 Statistics - Number of packets sent	R	Uint64
1574	4	Port 5 Statistics - Number of packets sent	R	Uint64
1578	4	Port 6 Statistics - Number of packets sent	R	Uint64
157c	4	Port 7 Statistics - Number of packets sent	R	Uint64
1580	4	Port 8 Statistics - Number of packets sent	R	Uint64
1584	4	Port 9 Statistics - Number of packets sent	R	Uint64
1588	4	Port 10 Statistics - Number of packets sent	R	Uint64
158c	4	Port 11 Statistics - Number of packets sent	R	Uint64
1590	4	Port 12 Statistics - Number of packets sent	R	Uint64

Table 30 IE-4000-16GT4G-E Port Information Registers (continued)

1594	4	Port 13 Statistics - Number of packets sent	R	Uint64
1598	4	Port 14 Statistics - Number of packets sent	R	Uint64
159c	4	Port 15 Statistics - Number of packets sent	R	Uint64
15a0	4	Port 16 Statistics - Number of packets sent	R	Uint64
15a4	4	Port 17 Statistics - Number of packets sent	R	Uint64
15a8	4	Port 18 Statistics - Number of packets sent	R	Uint64
15ac	4	Port 19 Statistics - Number of packets sent	R	Uint64
15b0	4	Port 20 Statistics - Number of packets sent	R	Uint64
15b4	4	Port 1 Statistics - Number of bytes received	R	Uint64
15b8	4	Port 2 Statistics - Number of bytes received	R	Uint64
15bc	4	Port 3 Statistics - Number of bytes received	R	Uint64
15c0	4	Port 4 Statistics - Number of bytes received	R	Uint64
15c4	4	Port 5 Statistics - Number of bytes received	R	Uint64
15c8	4	Port 6 Statistics - Number of bytes received	R	Uint64
15cc	4	Port 7 Statistics - Number of bytes received	R	Uint64
15d0	4	Port 8 Statistics - Number of bytes received	R	Uint64
15d4	4	Port 9 Statistics - Number of bytes received	R	Uint64
15d8	4	Port 10 Statistics - Number of bytes received	R	Uint64
15dc	4	Port 11 Statistics - Number of bytes received	R	Uint64
15E0	4	Port 12 Statistics - Number of bytes received	R	Uint64
15E4	4	Port 13 Statistics - Number of bytes received	R	Uint64
15E8	4	Port 14 Statistics - Number of bytes received	R	Uint64
15ec	4	Port 15 Statistics - Number of bytes received	R	Uint64
15f0	4	Port 16 Statistics - Number of bytes received	R	Uint64
15f4	4	Port 17 Statistics - Number of bytes received	R	Uint64
15f8	4	Port 18 Statistics - Number of bytes received	R	Uint64
15fc	4	Port 19 Statistics - Number of bytes received	R	Uint64
1600	4	Port 20 Statistics - Number of bytes received	R	Uint64
1604	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1608	4	Port 2 Statistics - Number of bytes sent	R	Uint64
160c	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1610	4	Port 4 Statistics - Number of bytes sent	R	Uint64
1614	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1618	4	Port 6 Statistics - Number of bytes sent	R	Uint64
161c	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1620	4	Port 8 Statistics - Number of bytes sent	R	Uint64
1624	4	Port 9 Statistics - Number of bytes sent	R	Uint64

Table 30 IE-4000-16GT4G-E Port Information Registers (continued)

1628	4	Port 10 Statistics - Number of bytes sent	R	Uint64
162c	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1630	4	Port 12 Statistics - Number of bytes sent	R	Uint64
1634	4	Port 13 Statistics - Number of bytes sent	R	Uint64
1638	4	Port 14 Statistics - Number of bytes sent	R	Uint64
163c	4	Port 15 Statistics - Number of bytes sent	R	Uint64
1640	4	Port 16 Statistics - Number of bytes sent	R	Uint64
1644	4	Port 17 Statistics - Number of bytes sent	R	Uint64
1648	4	Port 18 Statistics - Number of bytes sent	R	Uint64
164c	4	Port 19 Statistics - Number of bytes sent	R	Uint64
1650	4	Port 20 Statistics - Number of bytes sent	R	Uint64
1652	2	Port 1 Statistics - Number of packets received	R	Uint32
1654	2	Port 2 Statistics - Number of packets received	R	Uint32
1656	2	Port 3 Statistics - Number of packets received	R	Uint32
1658	2	Port 4 Statistics - Number of packets received	R	Uint32
165a	2	Port 5 Statistics - Number of packets received	R	Uint32
165c	2	Port 6 Statistics - Number of packets received	R	Uint32
165e	2	Port 7 Statistics - Number of packets received	R	Uint32
1660	2	Port 8 Statistics - Number of packets received	R	Uint32
1662	2	Port 9 Statistics - Number of packets received	R	Uint32
1664	2	Port 10 Statistics - Number of packets received	R	Uint32
1666	2	Port 11 Statistics - Number of packets received	R	Uint32
1668	2	Port 12 Statistics - Number of packets received	R	Uint32
166a	2	Port 13 Statistics - Number of packets received	R	Uint32
166c	2	Port 14 Statistics - Number of packets received	R	Uint32
166e	2	Port 15 Statistics - Number of packets received	R	Uint32
1670	2	Port 16 Statistics - Number of packets received	R	Uint32
1672	2	Port 17 Statistics - Number of packets received	R	Uint32
1674	2	Port 18 Statistics - Number of packets received	R	Uint32
1676	2	Port 19 Statistics - Number of packets received	R	Uint32
1678	2	Port 20 Statistics - Number of packets received	R	Uint32
167a	2	Port 1 Statistics - Number of packets sent	R	Uint32
167c	2	Port 2 Statistics - Number of packets sent	R	Uint32
167e	2	Port 3 Statistics - Number of packets sent	R	Uint32
1680	2	Port 4 Statistics - Number of packets sent	R	Uint32
1682	2	Port 5 Statistics - Number of packets sent	R	Uint32
1684	2	Port 6 Statistics - Number of packets sent	R	Uint32
1686	2	Port 7 Statistics - Number of packets sent	R	Uint32

Table 30 IE-4000-16GT4G-E Port Information Registers (continued)

1688	2	Port 8 Statistics - Number of packets sent	R	Uint32
168a	2	Port 9 Statistics - Number of packets sent	R	Uint32
168c	2	Port 10 Statistics - Number of packets sent	R	Uint32
168e	2	Port 11 Statistics - Number of packets sent	R	Uint32
1690	2	Port 12 Statistics - Number of packets sent	R	Uint32
1692	2	Port 13 Statistics - Number of packets sent	R	Uint32
1694	2	Port 14 Statistics - Number of packets sent	R	Uint32
1696	2	Port 15 Statistics - Number of packets sent	R	Uint32
1698	2	Port 16 Statistics - Number of packets sent	R	Uint32
169a	2	Port 17 Statistics - Number of packets sent	R	Uint32
169c	2	Port 18 Statistics - Number of packets sent	R	Uint32
169e	2	Port 19 Statistics - Number of packets sent	R	Uint32
16a0	2	Port 20 Statistics - Number of packets sent	R	Uint32
16a2	2	Port 1 Statistics - Number of bytes received	R	Uint32
16a4	2	Port 2 Statistics - Number of bytes received	R	Uint32
16a6	2	Port 3 Statistics - Number of bytes received	R	Uint32
16a8	2	Port 4 Statistics - Number of bytes received	R	Uint32
16aa	2	Port 5 Statistics - Number of bytes received	R	Uint32
16ac	2	Port 6 Statistics - Number of bytes received	R	Uint32
16ae	2	Port 7 Statistics - Number of bytes received	R	Uint32
16b0	2	Port 8 Statistics - Number of bytes received	R	Uint32
16b2	2	Port 9 Statistics - Number of bytes received	R	Uint32
16b4	2	Port 10 Statistics - Number of bytes received	R	Uint32
16b6	2	Port 11 Statistics - Number of bytes received	R	Uint32
16b8	2	Port 12 Statistics - Number of bytes received	R	Uint32
16ba	2	Port 13 Statistics - Number of bytes received	R	Uint32
16bc	2	Port 14 Statistics - Number of bytes received	R	Uint32
16be	2	Port 15 Statistics - Number of bytes received	R	Uint32
16c0	2	Port 16 Statistics - Number of bytes received	R	Uint32
16c2	2	Port 17 Statistics - Number of bytes received	R	Uint32
16c4	2	Port 18 Statistics - Number of bytes received	R	Uint32
16c6	2	Port 19 Statistics - Number of bytes received	R	Uint32
16c8	2	Port 20 Statistics - Number of bytes received	R	Uint32
16ca	2	Port 1 Statistics - Number of bytes sent	R	Uint32
16cc	2	Port 2 Statistics - Number of bytes sent	R	Uint32
16ce	2	Port 3 Statistics - Number of bytes sent	R	Uint32
16d0	2	Port 4 Statistics - Number of bytes sent	R	Uint32

Table 30 IE-4000-16GT4G-E Port Information Registers (continued)

16d2	2	Port 5 Statistics - Number of bytes sent	R	Uint32
16d4	2	Port 6 Statistics - Number of bytes sent	R	Uint32
16d6	2	Port 7 Statistics - Number of bytes sent	R	Uint32
16d8	2	Port 8 Statistics - Number of bytes sent	R	Uint32
16da	2	Port 9 Statistics - Number of bytes sent	R	Uint32
16dc	2	Port 10 Statistics - Number of bytes sent	R	Uint32
16de	2	Port 11 Statistics - Number of bytes sent	R	Uint32
16e0	2	Port 12 Statistics - Number of bytes sent	R	Uint32
16e0	2	Port 13 Statistics - Number of bytes sent	R	Uint32
16e2	2	Port 14 Statistics - Number of bytes sent	R	Uint32
16e4	2	Port 15 Statistics - Number of bytes sent	R	Uint32
16e8	2	Port 16 Statistics - Number of bytes sent	R	Uint32
16ea	2	Port 17 Statistics - Number of bytes sent	R	Uint32
16ec	2	Port 18 Statistics - Number of bytes sent	R	Uint32
16ee	2	Port 19 Statistics - Number of bytes sent	R	Uint32
16f0	2	Port 20 Statistics - Number of bytes sent	R	Uint32

IE-4000-8GT8GP4G-E

System Information Registers

Table 31 IE-4000-8GT8GP4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	

Table 31 IE-4000-8GT8GP4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 32 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 33 IE-4000-8GT8GP4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
1300	64	Port 13 Name	R	Text
1340	64	Port 14 Name	R	Text
1380	64	Port 15 Name	R	Text
13C0	64	Port 16 Name	R	Text
1400	64	Port 17 Name	R	Text
1440	64	Port 18 Name	R	Text
1480	64	Port 19 Name	R	Text
14C0	64	Port 20 Name	R	Text
1500	1	Port 1 State	R	Uint16
1501	1	Port 2 State	R	Uint16
1502	1	Port 3 State	R	Uint16
1503	1	Port 4 State	R	Uint16
1504	1	Port 5 State	R	Uint16
1505	1	Port 6 State	R	Uint16
1506	1	Port 7 State	R	Uint16
1507	1	Port 8 State	R	Uint16
1508	1	Port 9 State	R	Uint16
1509	1	Port 10 State	R	Uint16
150a	1	Port 11 State	R	Uint16
150b	1	Port 12 State	R	Uint16
150c	1	Port 13 State	R	Uint64
150d	1	Port 14 State	R	Uint64
150e	1	Port 15 State	R	Uint64

Table 33 IE-4000-8GT8GP4G-E Port Information Registers (continued)

150f	1	Port 16 State	R	Uint64
1510	1	Port 17 State	R	Uint64
1511	1	Port 18 State	R	Uint64
1512	1	Port 19 State	R	Uint64
1513	1	Port 20 State	R	Uint64
1514	4	Port 1 Statistics - Number of packets received	R	Uint64
1518	4	Port 2 Statistics - Number of packets received	R	Uint64
151c	4	Port 3 Statistics - Number of packets received	R	Uint64
1520	4	Port 4 Statistics - Number of packets received	R	Uint64
1524	4	Port 5 Statistics - Number of packets received	R	Uint64
1528	4	Port 6 Statistics - Number of packets received	R	Uint64
152c	4	Port 7 Statistics - Number of packets received	R	Uint64
1530	4	Port 8 Statistics - Number of packets received	R	Uint64
1534	4	Port 9 Statistics - Number of packets received	R	Uint64
1538	4	Port 10 Statistics - Number of packets received	R	Uint64
153c	4	Port 11 Statistics - Number of packets received	R	Uint64
1540	4	Port 12 Statistics - Number of packets received	R	Uint64
1544	4	Port 13 Statistics - Number of packets received	R	Uint64
1548	4	Port 14 Statistics - Number of packets received	R	Uint64
154c	4	Port 15 Statistics - Number of packets received	R	Uint64
1550	4	Port 16 Statistics - Number of packets received	R	Uint64
1554	4	Port 17 Statistics - Number of packets received	R	Uint64
1558	4	Port 18 Statistics - Number of packets received	R	Uint64
155c	4	Port 19 Statistics - Number of packets received	R	Uint64
1560	4	Port 20 Statistics - Number of packets received	R	Uint64
1564	4	Port 1 Statistics - Number of packets sent	R	Uint64
1568	4	Port 2 Statistics - Number of packets sent	R	Uint64
156c	4	Port 3 Statistics - Number of packets sent	R	Uint64
1570	4	Port 4 Statistics - Number of packets sent	R	Uint64
1574	4	Port 5 Statistics - Number of packets sent	R	Uint64
1578	4	Port 6 Statistics - Number of packets sent	R	Uint64
157c	4	Port 7 Statistics - Number of packets sent	R	Uint64
1580	4	Port 8 Statistics - Number of packets sent	R	Uint64
1584	4	Port 9 Statistics - Number of packets sent	R	Uint64
1588	4	Port 10 Statistics - Number of packets sent	R	Uint64
158c	4	Port 11 Statistics - Number of packets sent	R	Uint64
1590	4	Port 12 Statistics - Number of packets sent	R	Uint64

Table 33 IE-4000-8GT8GP4G-E Port Information Registers (continued)

1594	4	Port 13 Statistics - Number of packets sent	R	Uint64
1598	4	Port 14 Statistics - Number of packets sent	R	Uint64
159c	4	Port 15 Statistics - Number of packets sent	R	Uint64
15a0	4	Port 16 Statistics - Number of packets sent	R	Uint64
15a4	4	Port 17 Statistics - Number of packets sent	R	Uint64
15a8	4	Port 18 Statistics - Number of packets sent	R	Uint64
15ac	4	Port 19 Statistics - Number of packets sent	R	Uint64
15b0	4	Port 20 Statistics - Number of packets sent	R	Uint64
15b4	4	Port 1 Statistics - Number of bytes received	R	Uint64
15b8	4	Port 2 Statistics - Number of bytes received	R	Uint64
15bc	4	Port 3 Statistics - Number of bytes received	R	Uint64
15c0	4	Port 4 Statistics - Number of bytes received	R	Uint64
15c4	4	Port 5 Statistics - Number of bytes received	R	Uint64
15c8	4	Port 6 Statistics - Number of bytes received	R	Uint64
15cc	4	Port 7 Statistics - Number of bytes received	R	Uint64
15d0	4	Port 8 Statistics - Number of bytes received	R	Uint64
15d4	4	Port 9 Statistics - Number of bytes received	R	Uint64
15d8	4	Port 10 Statistics - Number of bytes received	R	Uint64
15dc	4	Port 11 Statistics - Number of bytes received	R	Uint64
15E0	4	Port 12 Statistics - Number of bytes received	R	Uint64
15E4	4	Port 13 Statistics - Number of bytes received	R	Uint64
15E8	4	Port 14 Statistics - Number of bytes received	R	Uint64
15ec	4	Port 15 Statistics - Number of bytes received	R	Uint64
15f0	4	Port 16 Statistics - Number of bytes received	R	Uint64
15f4	4	Port 17 Statistics - Number of bytes received	R	Uint64
15f8	4	Port 18 Statistics - Number of bytes received	R	Uint64
15fc	4	Port 19 Statistics - Number of bytes received	R	Uint64
1600	4	Port 20 Statistics - Number of bytes received	R	Uint64
1604	4	Port 1 Statistics - Number of bytes sent	R	Uint64
1608	4	Port 2 Statistics - Number of bytes sent	R	Uint64
160c	4	Port 3 Statistics - Number of bytes sent	R	Uint64
1610	4	Port 4 Statistics - Number of bytes sent	R	Uint64
1614	4	Port 5 Statistics - Number of bytes sent	R	Uint64
1618	4	Port 6 Statistics - Number of bytes sent	R	Uint64
161c	4	Port 7 Statistics - Number of bytes sent	R	Uint64
1620	4	Port 8 Statistics - Number of bytes sent	R	Uint64
1624	4	Port 9 Statistics - Number of bytes sent	R	Uint64
1628	4	Port 10 Statistics - Number of bytes sent	R	Uint64

Table 33 IE-4000-8GT8GP4G-E Port Information Registers (continued)

162c	4	Port 11 Statistics - Number of bytes sent	R	Uint64
1630	4	Port 12 Statistics - Number of bytes sent	R	Uint64
1634	4	Port 13 Statistics - Number of bytes sent	R	Uint64
1638	4	Port 14 Statistics - Number of bytes sent	R	Uint64
163c	4	Port 15 Statistics - Number of bytes sent	R	Uint64
1640	4	Port 16 Statistics - Number of bytes sent	R	Uint64
1644	4	Port 17 Statistics - Number of bytes sent	R	Uint64
1648	4	Port 18 Statistics - Number of bytes sent	R	Uint64
164c	4	Port 19 Statistics - Number of bytes sent	R	Uint64
1650	4	Port 20 Statistics - Number of bytes sent	R	Uint64
1652	2	Port 1 Statistics - Number of packets received	R	Uint32
1654	2	Port 2 Statistics - Number of packets received	R	Uint32
1656	2	Port 3 Statistics - Number of packets received	R	Uint32
1658	2	Port 4 Statistics - Number of packets received	R	Uint32
165a	2	Port 5 Statistics - Number of packets received	R	Uint32
165c	2	Port 6 Statistics - Number of packets received	R	Uint32
165e	2	Port 7 Statistics - Number of packets received	R	Uint32
1660	2	Port 8 Statistics - Number of packets received	R	Uint32
1662	2	Port 9 Statistics - Number of packets received	R	Uint32
1664	2	Port 10 Statistics - Number of packets received	R	Uint32
1666	2	Port 11 Statistics - Number of packets received	R	Uint32
1668	2	Port 12 Statistics - Number of packets received	R	Uint32
166a	2	Port 13 Statistics - Number of packets received	R	Uint32
166c	2	Port 14 Statistics - Number of packets received	R	Uint32
166e	2	Port 15 Statistics - Number of packets received	R	Uint32
1670	2	Port 16 Statistics - Number of packets received	R	Uint32
1672	2	Port 17 Statistics - Number of packets received	R	Uint32
1674	2	Port 18 Statistics - Number of packets received	R	Uint32
1676	2	Port 19 Statistics - Number of packets received	R	Uint32
1678	2	Port 20 Statistics - Number of packets received	R	Uint32
167a	2	Port 1 Statistics - Number of packets sent	R	Uint32
167c	2	Port 2 Statistics - Number of packets sent	R	Uint32
167e	2	Port 3 Statistics - Number of packets sent	R	Uint32
1680	2	Port 4 Statistics - Number of packets sent	R	Uint32
1682	2	Port 5 Statistics - Number of packets sent	R	Uint32
1684	2	Port 6 Statistics - Number of packets sent	R	Uint32
1686	2	Port 7 Statistics - Number of packets sent	R	Uint32

Table 33 IE-4000-8GT8GP4G-E Port Information Registers (continued)

1688	2	Port 8 Statistics - Number of packets sent	R	Uint32
168a	2	Port 9 Statistics - Number of packets sent	R	Uint32
168c	2	Port 10 Statistics - Number of packets sent	R	Uint32
168e	2	Port 11 Statistics - Number of packets sent	R	Uint32
1690	2	Port 12 Statistics - Number of packets sent	R	Uint32
1692	2	Port 13 Statistics - Number of packets sent	R	Uint32
1694	2	Port 14 Statistics - Number of packets sent	R	Uint32
1696	2	Port 15 Statistics - Number of packets sent	R	Uint32
1698	2	Port 16 Statistics - Number of packets sent	R	Uint32
169a	2	Port 17 Statistics - Number of packets sent	R	Uint32
169c	2	Port 18 Statistics - Number of packets sent	R	Uint32
169e	2	Port 19 Statistics - Number of packets sent	R	Uint32
16a0	2	Port 20 Statistics - Number of packets sent	R	Uint32
16a2	2	Port 1 Statistics - Number of bytes received	R	Uint32
16a4	2	Port 2 Statistics - Number of bytes received	R	Uint32
16a6	2	Port 3 Statistics - Number of bytes received	R	Uint32
16a8	2	Port 4 Statistics - Number of bytes received	R	Uint32
16aa	2	Port 5 Statistics - Number of bytes received	R	Uint32
16ac	2	Port 6 Statistics - Number of bytes received	R	Uint32
16ae	2	Port 7 Statistics - Number of bytes received	R	Uint32
16b0	2	Port 8 Statistics - Number of bytes received	R	Uint32
16b2	2	Port 9 Statistics - Number of bytes received	R	Uint32
16b4	2	Port 10 Statistics - Number of bytes received	R	Uint32
16b6	2	Port 11 Statistics - Number of bytes received	R	Uint32
16b8	2	Port 12 Statistics - Number of bytes received	R	Uint32
16ba	2	Port 13 Statistics - Number of bytes received	R	Uint32
16bc	2	Port 14 Statistics - Number of bytes received	R	Uint32
16be	2	Port 15 Statistics - Number of bytes received	R	Uint32
16c0	2	Port 16 Statistics - Number of bytes received	R	Uint32
16c2	2	Port 17 Statistics - Number of bytes received	R	Uint32
16c4	2	Port 18 Statistics - Number of bytes received	R	Uint32
16c6	2	Port 19 Statistics - Number of bytes received	R	Uint32
16c8	2	Port 20 Statistics - Number of bytes received	R	Uint32
16ca	2	Port 1 Statistics - Number of bytes sent	R	Uint32
16cc	2	Port 2 Statistics - Number of bytes sent	R	Uint32
16ce	2	Port 3 Statistics - Number of bytes sent	R	Uint32
16d0	2	Port 4 Statistics - Number of bytes sent	R	Uint32
16d2	2	Port 5 Statistics - Number of bytes sent	R	Uint32

Table 33 IE-4000-8GT8GP4G-E Port Information Registers (continued)

16d4	2	Port 6 Statistics - Number of bytes sent	R	Uint32
16d6	2	Port 7 Statistics - Number of bytes sent	R	Uint32
16d8	2	Port 8 Statistics - Number of bytes sent	R	Uint32
16da	2	Port 9 Statistics - Number of bytes sent	R	Uint32
16dc	2	Port 10 Statistics - Number of bytes sent	R	Uint32
16de	2	Port 11 Statistics - Number of bytes sent	R	Uint32
16e0	2	Port 12 Statistics - Number of bytes sent	R	Uint32
16e0	2	Port 13 Statistics - Number of bytes sent	R	Uint32
16e2	2	Port 14 Statistics - Number of bytes sent	R	Uint32
16e4	2	Port 15 Statistics - Number of bytes sent	R	Uint32
16e8	2	Port 16 Statistics - Number of bytes sent	R	Uint32
16ea	2	Port 17 Statistics - Number of bytes sent	R	Uint32
16ec	2	Port 18 Statistics - Number of bytes sent	R	Uint32
16ee	2	Port 19 Statistics - Number of bytes sent	R	Uint32
16f0	2	Port 20 Statistics - Number of bytes sent	R	Uint32

IE-4000-4GS8GP4G-E

System Information Registers

Table 34 IE-4000-4GS8GP4G-E System Information Registers

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
800	64	Product ID	R	Text	"IE-4000-4GC4GP4G-E"	show version user EXEC command
840	64	Software image name	R	Text	"IE4000-UNIVERSALK9-M"	
880	64	Software image version	R	Text	"15.2EA"	
08C0	64	Host name	R	Text	"IE4000"	show running-config privileged EXEC command
900	64	Alarm 1 description	R	Text	"Door 1"	show env alarm-contact user EXEC command
940	64	Alarm 2 description	R	Text	"Door 2"	
980	1	Alarm 1 status	R	Uint16	0x1	
981	1	Alarm 2 status	R	Uint16	0x0	
982	1	Total number of 10/100 Ethernet ports	R	Uint16	0x0	show version user EXEC command
983	1	Total number of Gigabit Ethernet ports	R	Uint16	0x0C	

Table 34 IE-4000-4GS8GP4G-E System Information Registers (continued)

Address	Number of Registers	Description	R/W	Format	Example/Note	CLI Command
984	1	Total number of alarms	R	Uint16	0x2	show env alarm-contact user EXEC command
985	1	Total number of power supplies	R	Uint16	0x2	show env power user EXEC command
986	1	PS1 status	R	Uint16	0x0	
987	1	PS2 status	R	Uint16	0x1	
988	1	System temperature (in Celsius)	R	Uint16	48	show env temperature user EXEC command

Table 35 System Information: Interpretation of Uint16 Values

Address	Description	Value
981	Alarm 1 status	0x0: Alarm not asserted
982	Alarm 2 status	0x1: Alarm asserted
986	Power supply 1 status	0x0: PS is functional
		0x1: PS is not functional
		0x2: PS is not present
987	Power supply 2 status	0x3: PS is not recognized

Port Information Registers

Table 36 IE-4000-4GS8GP4G-E Port Information Registers

Address in Hex	Number of Registers	Description	R/W	Format
1000	64	Port 1 Name	R	Text
1040	64	Port 2 Name	R	Text
1080	64	Port 3 Name	R	Text
10C0	64	Port 4 Name	R	Text
1100	64	Port 5 Name	R	Text
1140	64	Port 6 Name	R	Text
1180	64	Port 7 Name	R	Text
11C0	64	Port 8 Name	R	Text
1200	64	Port 9 Name	R	Text
1240	64	Port 10 Name	R	Text
1280	64	Port 11 Name	R	Text
12C0	64	Port 12 Name	R	Text
1300	64	Port 13 Name	R	Text
1340	64	Port 14 Name	R	Text
1380	64	Port 15 Name	R	Text
13C0	64	Port 16 Name	R	Text
1400	1	Port 1 State	R	Uint16
1401	1	Port 2 State	R	Uint16
1402	1	Port 3 State	R	Uint16
1403	1	Port 4 State	R	Uint16
1404	1	Port 5 State	R	Uint16
1405	1	Port 6 State	R	Uint16
1406	1	Port 7 State	R	Uint16
1407	1	Port 8 State	R	Uint16
1408	1	Port 9 State	R	Uint16
1409	1	Port 10 State	R	Uint16
140a	1	Port 11 State	R	Uint16
140b	1	Port 12 State	R	Uint16
140c	1	Port 13 State	R	Uint64
140d	1	Port 14 State	R	Uint64
140e	1	Port 15 State	R	Uint64
140f	1	Port 16 State	R	Uint64
1410	4	Port 1 Statistics - Number of packets received	R	Uint64
1414	4	Port 2 Statistics - Number of packets received	R	Uint64

Table 36 IE-4000-4GS8GP4G-E Port Information Registers (continued)

1418	4	Port 3 Statistics – Number of packets received	R	Uint64
141c	4	Port 4 Statistics – Number of packets received	R	Uint64
1420	4	Port 5 Statistics – Number of packets received	R	Uint64
1424	4	Port 6 Statistics – Number of packets received	R	Uint64
1428	4	Port 7 Statistics – Number of packets received	R	Uint64
142c	4	Port 8 Statistics – Number of packets received	R	Uint64
1430	4	Port 9 Statistics – Number of packets received	R	Uint64
1434	4	Port 10 Statistics – Number of packets received	R	Uint64
1438	4	Port 11 Statistics – Number of packets received	R	Uint64
143c	4	Port 12 Statistics – Number of packets received	R	Uint64
1440	4	Port 13 Statistics – Number of packets received	R	Uint64
1444	4	Port 14 Statistics – Number of packets received	R	Uint64
1448	4	Port 15 Statistics – Number of packets received	R	Uint64
144c	4	Port 16 Statistics – Number of packets received	R	Uint64
1450	4	Port 1 Statistics – Number of packets sent	R	Uint64
1454	4	Port 2 Statistics – Number of packets sent	R	Uint64
1458	4	Port 3 Statistics – Number of packets sent	R	Uint64
145c	4	Port 4 Statistics – Number of packets sent	R	Uint64
1460	4	Port 5 Statistics – Number of packets sent	R	Uint64
1464	4	Port 6 Statistics – Number of packets sent	R	Uint64
1468	4	Port 7 Statistics – Number of packets sent	R	Uint64
146c	4	Port 8 Statistics – Number of packets sent	R	Uint64
1470	4	Port 9 Statistics – Number of packets sent	R	Uint64
1474	4	Port 10 Statistics – Number of packets sent	R	Uint64
1478	4	Port 11 Statistics – Number of packets sent	R	Uint64
147c	4	Port 12 Statistics – Number of packets sent	R	Uint64
1480	4	Port 13 Statistics – Number of packets sent	R	Uint64
1484	4	Port 14 Statistics – Number of packets sent	R	Uint64
1488	4	Port 15 Statistics – Number of packets sent	R	Uint64
148c	4	Port 16 Statistics – Number of packets sent	R	Uint64
1490	4	Port 1 Statistics – Number of bytes received	R	Uint64
1494	4	Port 2 Statistics – Number of bytes received	R	Uint64
1498	4	Port 3 Statistics – Number of bytes received	R	Uint64
149c	4	Port 4 Statistics – Number of bytes received	R	Uint64
14a0	4	Port 5 Statistics – Number of bytes received	R	Uint64
14a4	4	Port 6 Statistics – Number of bytes received	R	Uint64
14a8	4	Port 7 Statistics – Number of bytes received	R	Uint64
14ac	4	Port 8 Statistics – Number of bytes received	R	Uint64

Table 36 IE-4000-4GS8GP4G-E Port Information Registers (continued)

14b0	4	Port 9 Statistics - Number of bytes received	R	Uint64
14b4	4	Port 10 Statistics - Number of bytes received	R	Uint64
14b8	4	Port 11 Statistics - Number of bytes received	R	Uint64
14bc	4	Port 12 Statistics - Number of bytes received	R	Uint64
14c0	4	Port 13 Statistics - Number of bytes received	R	Uint64
14c4	4	Port 14 Statistics - Number of bytes received	R	Uint64
14c8	4	Port 15 Statistics - Number of bytes received	R	Uint64
14cc	4	Port 16 Statistics - Number of bytes received	R	Uint64
14D0	4	Port 1 Statistics - Number of bytes sent	R	Uint64
14d4	4	Port 2 Statistics - Number of bytes sent	R	Uint64
14d8	4	Port 3 Statistics - Number of bytes sent	R	Uint64
14dc	4	Port 4 Statistics - Number of bytes sent	R	Uint64
14E0	4	Port 5 Statistics - Number of bytes sent	R	Uint64
14E4	4	Port 6 Statistics - Number of bytes sent	R	Uint64
14e8	4	Port 7 Statistics - Number of bytes sent	R	Uint64
14ec	4	Port 8 Statistics - Number of bytes sent	R	Uint64
14f0	4	Port 9 Statistics - Number of bytes sent	R	Uint64
14f4	4	Port 10 Statistics - Number of bytes sent	R	Uint64
14f8	4	Port 11 Statistics - Number of bytes sent	R	Uint64
14fc	4	Port 12 Statistics - Number of bytes sent	R	Uint64
1500	4	Port 13 Statistics - Number of bytes sent	R	Uint64
1504	4	Port 14 Statistics - Number of bytes sent	R	Uint64
1508	4	Port 15 Statistics - Number of bytes sent	R	Uint64
150c	4	Port 16 Statistics - Number of bytes sent	R	Uint64
150E	2	Port 1 Statistics - Number of packets received	R	Uint32
1510	2	Port 2 Statistics - Number of packets received	R	Uint32
1512	2	Port 3 Statistics - Number of packets received	R	Uint32
1514	2	Port 4 Statistics - Number of packets received	R	Uint32
1516	2	Port 5 Statistics - Number of packets received	R	Uint32
1518	2	Port 6 Statistics - Number of packets received	R	Uint32
151a	2	Port 7 Statistics - Number of packets received	R	Uint32
151c	2	Port 8 Statistics - Number of packets received	R	Uint32
151e	2	Port 9 Statistics - Number of packets received	R	Uint32
1520	2	Port 10 Statistics - Number of packets received	R	Uint32
1522	2	Port 11 Statistics - Number of packets received	R	Uint32
1524	2	Port 12 Statistics - Number of packets received	R	Uint32
1526	2	Port 13 Statistics - Number of packets received	R	Uint32

Table 36 IE-4000-4GS8GP4G-E Port Information Registers (continued)

1528	2	Port 14 Statistics - Number of packets received	R	Uint32
152a	2	Port 15 Statistics - Number of packets received	R	Uint32
152c	2	Port 16 Statistics - Number of packets received	R	Uint32
152E	2	Port 1 Statistics - Number of packets sent	R	Uint32
1530	2	Port 2 Statistics - Number of packets sent	R	Uint32
1532	2	Port 3 Statistics - Number of packets sent	R	Uint32
1534	2	Port 4 Statistics - Number of packets sent	R	Uint32
1536	2	Port 5 Statistics - Number of packets sent	R	Uint32
1538	2	Port 6 Statistics - Number of packets sent	R	Uint32
153a	2	Port 7 Statistics - Number of packets sent	R	Uint32
153c	2	Port 8 Statistics - Number of packets sent	R	Uint32
153e	2	Port 9 Statistics - Number of packets sent	R	Uint32
1540	2	Port 10 Statistics - Number of packets sent	R	Uint32
1542	2	Port 11 Statistics - Number of packets sent	R	Uint32
1544	2	Port 12 Statistics - Number of packets sent	R	Uint32
1546	2	Port 13 Statistics - Number of packets sent	R	Uint32
1548	2	Port 14 Statistics - Number of packets sent	R	Uint32
154a	2	Port 15 Statistics - Number of packets sent	R	Uint32
154c	2	Port 16 Statistics - Number of packets sent	R	Uint32
154E	2	Port 1 Statistics - Number of bytes received	R	Uint32
1550	2	Port 2 Statistics - Number of bytes received	R	Uint32
1552	2	Port 3 Statistics - Number of bytes received	R	Uint32
1554	2	Port 4 Statistics - Number of bytes received	R	Uint32
1556	2	Port 5 Statistics - Number of bytes received	R	Uint32
1558	2	Port 6 Statistics - Number of bytes received	R	Uint32
155a	2	Port 7 Statistics - Number of bytes received	R	Uint32
155c	2	Port 8 Statistics - Number of bytes received	R	Uint32
155e	2	Port 9 Statistics - Number of bytes received	R	Uint32
1560	2	Port 10 Statistics - Number of bytes received	R	Uint32
1562	2	Port 11 Statistics - Number of bytes received	R	Uint32
1564	2	Port 12 Statistics - Number of bytes received	R	Uint32
1566	2	Port 13 Statistics - Number of bytes received	R	Uint32
1568	2	Port 14 Statistics - Number of bytes received	R	Uint32
156a	2	Port 15 Statistics - Number of bytes received	R	Uint32
156c	2	Port 16 Statistics - Number of bytes received	R	Uint32
156E	2	Port 1 Statistics - Number of bytes sent	R	Uint32
1570	2	Port 2 Statistics - Number of bytes sent	R	Uint32
1572	2	Port 3 Statistics - Number of bytes sent	R	Uint32

Table 36 IE-4000-4GS8GP4G-E Port Information Registers (continued)

1574	2	Port 4 Statistics - Number of bytes sent	R	Uint32
1576	2	Port 5 Statistics - Number of bytes sent	R	Uint32
1578	2	Port 6 Statistics - Number of bytes sent	R	Uint32
157a	2	Port 7 Statistics - Number of bytes sent	R	Uint32
157c	2	Port 8 Statistics - Number of bytes sent	R	Uint32
157e	2	Port 9 Statistics - Number of bytes sent	R	Uint32
1580	2	Port 10 Statistics - Number of bytes sent	R	Uint32
1582	2	Port 11 Statistics - Number of bytes sent	R	Uint32
1584	2	Port 12 Statistics - Number of bytes sent	R	Uint32
1586	2	Port 13 Statistics - Number of bytes sent	R	Uint32
1588	2	Port 14 Statistics - Number of bytes sent	R	Uint32
158a	2	Port 15 Statistics - Number of bytes sent	R	Uint32
158c	2	Port 16 Statistics - Number of bytes sent	R	Uint32

Related Documents

For Cisco Industrial Ethernet 4000 Series Switches documentation, see <http://www.cisco.com/go/ie4000>.

Communications, Services, and Additional Information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions and services, visit [Cisco Marketplace](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a web-based tool that acts as a gateway to the Cisco bug tracking system that maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. BST provides you with detailed defect information about your products and software.

THE SPECIFICATIONS AND INFORMATION REGARDING THE PRODUCTS IN THIS MANUAL ARE SUBJECT TO CHANGE WITHOUT NOTICE. ALL STATEMENTS, INFORMATION, AND RECOMMENDATIONS IN THIS MANUAL ARE BELIEVED TO BE ACCURATE BUT ARE PRESENTED WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED. USERS MUST TAKE FULL RESPONSIBILITY FOR THEIR APPLICATION OF ANY PRODUCTS.

THE SOFTWARE LICENSE AND LIMITED WARRANTY FOR THE ACCOMPANYING PRODUCT ARE INCORPORATED HEREIN BY THIS REFERENCE. IF YOU ARE UNABLE TO LOCATE THE SOFTWARE LICENSE OR LIMITED WARRANTY, CONTACT YOUR CISCO REPRESENTATIVE FOR A COPY.

The Cisco implementation of TCP header compression is an adaptation of a program developed by the University of California, Berkeley (UCB) as part of UCB's public domain version of the UNIX operating system. All rights reserved. Copyright © 1981, Regents of the University of California.

NOTWITHSTANDING ANY OTHER WARRANTY HEREIN, ALL DOCUMENT FILES AND SOFTWARE OF THESE SUPPLIERS ARE PROVIDED "AS IS" WITH ALL FAULTS. CISCO AND THE ABOVE-NAMED SUPPLIERS DISCLAIM ALL WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, WITHOUT LIMITATION, THOSE OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT OR ARISING FROM A COURSE OF DEALING, USAGE, OR TRADE PRACTICE.

IN NO EVENT SHALL CISCO OR ITS SUPPLIERS BE LIABLE FOR ANY INDIRECT, SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES, INCLUDING, WITHOUT LIMITATION, LOST PROFITS OR LOSS OR DAMAGE TO DATA ARISING OUT OF THE USE OR INABILITY TO USE THIS MANUAL, EVEN IF CISCO OR ITS SUPPLIERS HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES.

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

All printed copies and duplicate soft copies of this document are considered uncontrolled. See the current online version for the latest version.

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco website at www.cisco.com/go/offices.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1721R)

No combinations are authorized or intended under this document.

© 2019 Cisco Systems, Inc. All rights reserved.