

## Cisco 10GBASE XENPAK Modules

### Product Overview

The range of Cisco® 10GBASE XENPAK modules offers a wide variety of 10 Gigabit Ethernet connectivity options for data center, enterprise wiring closet, and service provider transport applications (Figure 1).

**Figure 1.** Cisco 10GBASE XENPAK Modules



Main features of Cisco 10GBASE XENPAK modules include:

- Supports 10GBASE Ethernet
- Hot-swappable input/output device plugs into an Ethernet XENPAK port of a Cisco switch or router to link the port with the network
- Provides flexibility of interface choice
- Supports “pay-as-you-populate” model
- Supports the Cisco quality identification feature that enables a Cisco switch or router to identify whether the module is a Cisco certified and tested XENPAK module

Cisco offers eight modules in this product family:

- **Cisco XENPAK-10GB-CX4:** Supports link lengths of up to 15m on CX4 cable.
- **Cisco XENPAK-10GB-LX4:** Supports link lengths of 300m on standard Fiber Distributed Data Interface (FDDI) grade multimode fiber (MMF). To ensure that specifications are met, the transmitter output should be coupled through a mode conditioning patch cord. For additional information on mode conditioning patch cord requirements please see: [http://www.cisco.com/en/US/prod/collateral/modules/ps5455/product\\_bulletin\\_c25-530836.html](http://www.cisco.com/en/US/prod/collateral/modules/ps5455/product_bulletin_c25-530836.html).
- **Cisco XENPAK-10GB-LRM:** Supports link lengths 220m on standard FDDI-grade multimode fiber (MMF). To ensure that specifications are met over FDDI-grade, OM1 and OM2 fibers, the transmitter should be coupled through a mode conditioning patch cord. No

mode conditioning patch cord is required for applications over OM3. For additional information on mode conditioning patch cord requirements please see:

[http://www.cisco.com/en/US/prod/collateral/modules/ps5455/product\\_bulletin\\_c25-530836.html](http://www.cisco.com/en/US/prod/collateral/modules/ps5455/product_bulletin_c25-530836.html).

- **Cisco XENPAK-10GB-SR:** Supports a link length of 26m on standard FDDI grade MMF. Up to 300m link lengths are possible when using 2000 MHz/km MMF (OM3).
- **Cisco XENPAK-10GB-LR / -LR+:** Supports a link length of 10 km on standard single-mode fiber (SMF) (G.652).
- **Cisco XENPAK-10GB-ER / -ER+:** Supports a link length of up to 40 km on SMF (G.652).
- **Cisco XENPAK-10GB-ZR:** Supports link lengths of up to about 80 km on SMF. This interface is not part of the 10 Gigabyte Ethernet standard but is built according to Cisco optical specifications.
- **Cisco XENPAK-10GB-LW (WAN PHY):** Supports a link length of 10 km on standard single-mode fiber (SMF) (G.652). WAN-PHY is intended to allow the transport of 10 Gigabit Ethernet over a traditional SONET/SDH infrastructure by rendering 10 Gigabit Ethernet compatible with SONET STS-192c format and data rate, as defined by ANSI, as well as the SDH VC-4-64c container specified by ITU.

## Technical Specifications

### Platform Support

Cisco XENPAK modules are supported on Cisco switches and routers. For more details, refer to the document Cisco XENPAK/X2 Compatibility Matrix.

### Connectors and Cabling

#### Connectors:

- XENPAK-10GB-CX4: InfiniBand 4x connector
- All others: Dual SC/PC connector

**Note:** Only connections with patch cords with PC or UPC connectors are supported. Patch cords with APC connectors are not supported. All cables and cable assemblies used must be compliant with the standards specified in the standards section.

Table 1 provides cabling specifications for the Cisco XENPAK modules.

**Table 1.** XENPAK Port Cabling Specifications

Product	Wavelength (nm)	Cable Type	Core Size (micron)	Modal Bandwidth (MHz/km)	Cable Distance*
Cisco XENPAK-10GB-CX4	–	CX4 (copper)	–	–	15m
Cisco XENPAK-10GB-LX4	1310	MMF	62.5	500	300m
			50.0	400	240m
			50.0	500	300m
Cisco XENPAK-10GB-LRM	1310	MMF	62.5	500	220m
			50.0	400	100m
			50.0	500	220m

Cisco XENPAK-10GB-SR	850	MMF	62.5	160	26m
			62.5	200	33m
			50.0	400	66m
			50.0	500	82m
			50.0	2000	300m
Cisco XENPAK-10GB-LR / -LR+	1310	SMF	G.652**	–	10 km
Cisco XENPAK-10GB-LW	1310	SMF	G.652**	–	10 km
Cisco XENPAK-10GB-ER / -ER+***	1550	SMF	G.652**	–	40 km****
Cisco XENPAK-10GB-ZR	1550	SMF	Operates on any SMF type	–	80 km

\* Minimum cabling distance for optical XENPAK modules (-LX4, -SR, -LR, -ER) is 2m, according to the IEEE 802.3ae standard, and minimum cabling distance for -LRM modules is 0.5m, according to IEEE 802.3aq standard.

\*\* Data based on standard G.652 SMF. Even though dispersion-shifted fiber enables reducing signal dispersion to travel longer distances, the signal attenuation still limits its distance.

\*\*\* Requires 5 dB 1550 nm fixed loss attenuator for < 20 km. Attenuator is available as a spare. The part number is WS-X6K-5DB-ATT=.

\*\*\*\* Links longer than 30 km are considered engineered links.

### Standards

- IEEE 802.3ae (-LX4, -SR, -LR, -LW, -ER)
- IEEE 802.3aq (-LRM)
- IEEE 802.3ak (-CX4)

Table 2 shows the main optical characteristics for the Cisco XENPAK modules. The Cisco XENPAK-10GB-CX4 is not an optical module and therefore is not listed in the table.

**Table 1.** Optical Transmit and Receive Specifications for IEEE 802.3 standard compliant modules

Product	Type	Transmit Power (dBm)		Receive Power (dBm)		Transmit and Receive Wavelength range (nm)	
		Maximum	Minimum	Maximum	Minimum	Transmit	Receive
Cisco XENPAK-10GB-LX4	10GBASE-LX4 WWDMM 1300 nm MMF	-0.5 per lane	-6.75 per lane in OMA	-0.5 per lane	-14.25 per lane in OMA	Four lanes; overall range: 1269 to 1356	
Cisco XENPAK-10GB-LRM	10GBASE-LRM 1300nm MMF	0.5	-6.5	0.5	-8.4 (in average) and -6.4 (in OMA)****	1260 to 1355	
Cisco XENPAK-10GB-SR	10GBASE-SR 850 nm MMF	-1.2*	-7.3	-1.0	-9.9	840 to 860	
Cisco XENPAK-10GB-LR / -LR+**	10GBASE-LR 1310 nm SMF	0.5	-8.2	0.5	-14.4	1260 to 1355	1260 to 1565*****
Cisco XENPAK-10GB-LW	10GBASE-LW 1310 nm SMF	0.5	-8.2	0.5	-14.4	1260 to 1355	1260 to 1565*****
Cisco XENPAK-10GB-ER / -ER+***	10GBASE-ER 1550 nm SMF	4	-4.7	-1.0	-15.8	1530 to 1565	1260 to 1565*****

\* The launch power shall be the lesser of the class 1 safety limit or the maximum receive power. Class 1 laser requirements are defined by IEC 60825-1: 2001.

\*\* WS-G6488 has the same optical parameters as XENPAK-10GB-LR.

\*\*\* WS-G6483 has the same optical parameters as XENPAK-10GB-ER.

\*\*\*\* Both average and OMA specifications need to be met simultaneously

\*\*\*\*\* Even though the receiver can tolerate a wide wavelength range, the specifications are guaranteed for a signal within the transmit wavelength range

Table 3 details optical specifications for the Cisco XENPAK-10GB-ZR modules.

**Table 2.** XENPAK-10GB-ZR Optical Parameters

Parameter	Symbol	Minimum	Typical	Maximum	Units	Notes and Conditions
<b>Transmitter</b>						
Transmitter wavelength		1530		1565	nm	
Side-mode suppression ratio	SMSR	30			dB	
Transmitter extinction ratio	OMI	9			dB	
Transmitter optical output power	$P_{out}$	0		4.0	dBm	Average power coupled into single-mode fiber
<b>Receiver</b>						
Receiver optical input wavelength	$\lambda_{in}$	1530		1565	nm	
Receiver damage threshold				-1	dBm	
Dispersion tolerance		0		1600	ps/nm	
Optical input power	$P_{in}$	-24.0		-7.0	dBm	At bit error rate (BER) = $10e^{-12}$ with IEEE 802.3 test pattern
Dispersion power penalty at 1600 ps/nm				3	dB	At bit error rate (BER) = $10e^{-12}$ with IEEE 802.3 test pattern

**Note:** Parameters are specified over temperature and at end of life unless otherwise noted. When shorter distances of single-mode fiber are used, an inline optical attenuator must be used to avoid overloading and damaging the receiver.

### Dimensions

Dimensions (DxWxH): 4.76" x 1.42" x 0.47" (121 x 36 x 18 mm). Cisco XENPAK modules typically weigh less than 300 g.

### Environmental Conditions and Power Requirements

- Operating temperature range is between 0 and 40°C (32 to 104°F); storage temperature range is -40 to 75°C (-40 to 167°F).
- Maximum power consumption per Cisco XENPAK module is 8W.

### Warranty

- Standard warranty: 90 days
- Extended warranty (optional): Cisco XENPAK modules can be covered in a Cisco SMARTnet® support contract for the Cisco switch or router chassis

Table 4 provides the ordering information for Cisco XENPAK modules and related cables.

## Ordering Information

**Table 3.** Ordering Cisco XENPAK Modules and Respective Cables

Description	Product Number
<b>XENPAK modules</b>	
Cisco 10GBASE-CX4 XENPAK Module for CX4 cable	XENPAK-10GB-CX4
Cisco 10GBASE-LX4 XENPAK Module for MMF	XENPAK-10GB-LX4
Cisco 10GBASE-LRM XENPAK Module for MMF	XENPAK-10GB-LRM
Cisco 10GBASE-SR XENPAK Module for MMF	XENPAK-10GB-SR
Cisco 10GBASE-LR XENPAK Module for SMF	XENPAK-10GB-LR
Cisco 10GBASE-LR XENPAK Module for SMF for the CRS-1	CRS-XENPAK10GB-LR
Cisco 10GBASE-LR XENPAK Module for SMF for the 3750	C3-XENPAK10GB-LR
Cisco 10GBASE-LR XENPAK Module for SMF	XENPAK-10GB-LR+
Cisco 10GBASE-ER XENPAK Module for SMF	XENPAK-10GB-ER
Cisco 10GBASE-ER XENPAK Module for SMF	XENPAK-10GB-ER+
Cisco 10GBASE-ZR XENPAK Module for SMF	XENPAK-10GB-ZR
Cisco 10GBASE-LW XENPAK Module for SMF	XENPAK-10GB-LW
<b>Cables</b>	
Mode conditioning patch cable 62.5um, dual SC connectors	CAB-GELX-625=
Mode conditioning patch cable 50um, dual SC connectors	CAB-MCP50-SC=
1 m cable for 10GBase-CX4 module	CAB-INF-28G-1=
5 m cable for 10GBase-CX4 module	CAB-INF-28G-5=
10 m cable for 10GBase-CX4 module	CAB-INF-28G-10=
15 m cable for 10GBase-CX4 module	CAB-INF-26G-15=

## Regulatory and Standards Compliance

### Standards:

- GR-20-CORE: Generic Requirements for Optical Fiber and Optical Fiber Cable
- GR-326-CORE: Generic Requirements for Single-mode Optical Connectors and Jumper Assemblies
- GR-1435-CORE: Generic Requirements for Multi-Fiber Optical Connectors

### Safety

- Laser Class 1 21CFR-1040 LN#50 7/2001
- Laser Class 1 IEC60825-1

## For More Information

For more information about Cisco XENPAK modules, contact your local account representative.



**Americas Headquarters**  
Cisco Systems, Inc.  
San Jose, CA

**Asia Pacific Headquarters**  
Cisco Systems (USA) Pte. Ltd.  
Singapore

**Europe Headquarters**  
Cisco Systems International BV  
Amsterdam, The Netherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).

CCDE, CCENT, CCSI, Cisco Eos, Cisco HealthPresence, Cisco IronPort, the Cisco logo, Cisco Lumin, Cisco Nexus, Cisco Nurse Connect, Cisco StackPower, Cisco StadiumVision, Cisco TelePresence, Cisco Unified Computing System, Cisco WebEx, DCE, Flip Channels, Flip for Good, Flip Mino, Flip Video, Flip Video (Design), Flipshare (Design), Flip Ultra, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn, Cisco Store, and Flip Gift Card are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0907R)