



Cisco Nexus Data Broker, Release 3.5, Release Notes

This document describes the features, caveats, and limitations for the Cisco Nexus Data Broker (NDB) software, Release 3.5.

Additional product **documentation is listed in the “Related Documentation” section.**

[Table 1](#) shows the online change history for this document.

Table 1 Online History Change

Date	Description
Dec 22, 2017	Created the release notes for the 3.5 release.
Feb 22, 2018	Added hardware and software interoperability matrix for Nexus Data Broker.
Feb 25, 2019	Updated Known Caveats section and Open Caveats section.
June 7, 2019	Updated Feature Limitations section.

Contents

This document includes the following sections:

- INTRODUCTION
- COMPATIBILITY INFORMATION
- USAGE GUIDELINES
- VERIFIED SCALABILITY LIMITS
- NEW AND CHANGED INFORMATION
- CAVEATS
- RELATED DOCUMENTATION

Introduction

Visibility into application traffic is important for infrastructure operations to maintain security and compliance, and to perform resource planning and troubleshooting. With the technological advances and growth in cloud-based applications, it has become imperative to gain increased visibility into the network traffic. Traditional approaches to gain visibility into network traffic are expensive and rigid, making it difficult for managers of large-scale deployments.

Cisco Nexus Data Broker (NDB) with Cisco Nexus Switches provides a software-defined, programmable solution to aggregate copies of network traffic using SPAN or network taps for monitoring and visibility. As opposed to traditional network taps and monitoring solutions, this packet-brokering approach offers a simple, scalable and cost-effective solution well-suited for customers who need to monitor higher-volume and business-critical traffic for efficient use of security, compliance, and application performance monitoring tools.

Cisco NDB also provides a software-defined, programmable solution to perform inline inspection of the network traffic for monitoring and visibility purpose. Inline traffic inspection is performed on specific traffic by redirecting it through multiple security tools before it enters or exits a network.

New and Changed Information

This section lists the new and changed features in this release:

- Cisco NDB now supports EX and FX modular line cards on Cisco Nexus 95XX device.
- Cisco Nexus 93XX-EX and 93XX-FX devices are now supported on NDB.
- Support to truncate packets on egress ports on 93XX-EX and 93XX-FX devices.
- NDB restart option is now added to startup script.
- Internet explorer version 11 is now supported for NDB 3.5.
- Support to edit an existing connection for adding additional monitoring devices without packet drops.
- Starting with this release, the switches are listed in alphabetical order in all the drop-down lists.
- Starting with this release, interfaces in the Port Group details are lists
- NDB now supports sorting the statistic reports based on packet count numerical values.
- NDB now supports searching for connection using connection name, interface name, node name, description, filter name, monitor device name, and priority.

Feature Limitations

The following feature limitation apply for the Cisco Nexus Data Broker, Release 3.5:

- NDB Openflow embedded is not supported on Cisco Nexus 3000/9000 series switches running 7.0(3)I6.1 and 7.0(3)I7.1 NXOS image.

Usage Guidelines and Limitations

This section lists the usage guidelines and limitations for the Cisco Nexus Data Broker.

- By default, NDB cluster URL is <https://<NDBIP>:8443>.
- NDB supports Google Chrome version 45.x and later, FireFox version 45.x and later, and Internet Explorer version 11 and later.

Usage Guidelines and Limitations

- APIC versions supported are 1.1, 1.2, and 2.0 series.
- The switchport mode trunk and spanning-tree bpdfilter enable command should be enabled for all the inter-switch ports on all the NDB managed switches.
- Cisco Nexus Data Broker Embedded will be supported on NxOS 7.0(I4).1 onwards, and 7.0(3)I6.1 onwards. For more information, see the *Nexus Data Broker Hardware and Software Interoperability Matrix* section.
- The following features will not be supported in embedded mode deployment of Cisco Nexus Data Broker:
 - Adding another NDB device
 - Adding APIC for ACI SPAN session
 - Adding production device for the SPAN session
 - Configuring SPAN session
 - Configuring copy device
 - Configuring copy sessions
 - Scheduling Configuration Backup
 - NDB High availability is not supported
 - TLS communication between the NDB controller and the switches is not supported
 - Secured communication between the browser and NDB controller is not supported
- Cisco Nexus switches managed by Cisco Nexus Data Broker in NX-API mode must have LLDP feature enabled. Disabling LLDP may cause inconsistencies and require device rediscovery.
- When removing devices from the Cisco Nexus Data Broker, the device associated port definitions and connections should be removed first. Otherwise, the device might contain stale configurations created by the Cisco Nexus Data Broker.
- For secured communication between Nexus Data Broker and Device through HTTPS, start Nexus Data Broker in TLS mode for the first time only. Subsequent NDB restarts does not require TLS mode. For more details, refer to *Cisco Nexus Data Broker Configuration Guide*.
- The TLS KeyStore and TrustStore passwords are sent to the Cisco Nexus Data Broker so it can read the password-protected TLS KeyStore and TrustStore files only through HTTPS.

```
./xnc config-keystore-passwords [--user {user} --password {password} --url {url} --verbose --prompt --keystore-password {keystore_password} --truststore-password {truststore_password}.
```

Here default URL to be - https://Nexus_Data_Broker_IP:8443
- A Cisco Nexus Data Broker instance can support either the OpenFlow or NX-API configuration mode, it does not support both configuration modes at an instance.
- VLAN based IP filtering is not supported for Nexus Series switch with NxOS version 7.0(3)I6.1. Hence, the filtering fails when you filter the traffic for the following series of switches: 92160YC-X Switch, 92300YC Swicth, 9272Q switch, 92304Q Switch, 9236C Switch.

Compatibility Information

- For the NDB cluster deployment, the round trip delay across the various servers participating in the cluster should be less than 50 milliseconds. If the round trip delay is more, the NDB cluster behaves unexpectedly. The NDB server round trip delay should be less than 50 ms. If anything above that will have issue in NDB sync up with member servers.
- Do not configure TACACS on the NDB switches. You can configure it only for authentication and authorization. Not to be used for accounting.
- For Cisco NDB Release 3.5, Cisco NX-OS Release versions 7.0(3)I5(1), 7.0(3)I5(2), and 7.0(3)I7(2) are not recommended for NXAPI deployment and Cisco NX-OS Release versions 7.0(3)I5(1) and 7.0(3)I5(2) are not recommended OpenFlow deployments.

Compatibility Information

The 3.5 release supports the following operating systems for the full visibility software sensors:

Device Model	Cisco Nexus Data Broker Minimum version	Deployment Mode Supported	Supported Use Cases
Cisco Nexus 3000 Series	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation and In-line redirection
Cisco Nexus 3100 platform	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation and In-line redirection
Cisco Nexus 3164Q Switch	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 3200 switch	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 3500 Series	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 9200 switch	Cisco Nexus Data Broker 3.1 or later	Centralized and Embedded Note: Cisco Nexus 9200 Series switches support only one switch deployment.	Tap/SPAN aggregation only

Device Model	Cisco Nexus Data Broker Minimum version	Deployment Mode Supported	Supported Use Cases
Cisco Nexus 9300 platform	Cisco Nexus Data Broker 3.0 or later	Centralized and Embedded	Tap/SPAN aggregation and In-line redirection
Cisco Nexus 9300-EX switch	Cisco Nexus Data Broker 3.1 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 9300-FX switch	Cisco Nexus Data Broker 3.5 or later	Centralized and Embedded	Tap/SPAN aggregation only
Cisco Nexus 9500 platform	Cisco Nexus Data Broker 3.0 or later	Centralized only	Tap/SPAN aggregation only
Cisco Nexus 9500-EX switch	Cisco Nexus Data Broker 3.5 or later	Centralized only	Tap/SPAN aggregation only
Cisco Nexus 9500-FX switch	Cisco Nexus Data Broker 3.5 or later	Centralized only	Tap/SPAN aggregation only

Nexus Data Broker Hardware and Software Interoperability Matrix

The following table lists the hardware and software interoperability matrix for NDB Release 3.5.

Table 2 Scalability Limits for Cisco Nexus Data Broker

Nexus Switch Model(s)	Implementation Type	Supported NX-OS Versions	Open Flow Agent
3048/3064/3172	OpenFlow	6.0(2)U6(x), I2(x), and I3(x)	1.1.5
3048/3064/3172	OpenFlow	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(2) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	2.1.4
3046/3064	NXAPI	6.0(2)U6(x), 7.0(3)I4(1) to 7.0(3)I4(8b)	Not Supported
3172	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA

Nexus Switch Model(s)	Implementation Type	Supported NX-OS Versions	Open Flow Agent
3164	OpenFlow	Not Supported	Not Supported
3164	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
3232	OpenFlow	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(2) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	2.1.4
3232	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
3548	OpenFlow	6.0(2)A6(x) and 6.0(2)A8(x) I7(5) and I7(5a) (OF agent is not required) 7.0(3)I7(2) to 7.0(3)I7(6)	1.1.5
3548	NXAPI	Not Supported	Not Supported
92160/92304	OpenFlow	Not Supported	Not Supported
92160/92304	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
9372/9396/93128	OpenFlow	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(2) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	2.14
9372/9396/93128	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
93180LC-EX	OpenFlow	Not Supported	Not Supported
93180LC-EX	NXAPI	7.0(3)I6(1), 7.0(3)I7(3), 7.0(3)I7(4), 7.0(3)I7(5), 7.0(3)I7(6), 9.2(1), 9.2(2), 9.2(3), and 9.3(1).	NA
93180TC-EX / 93180YC-EX	OpenFlow	Not Supported	Not Supported
93180TC-EX / 93180YC-EX	NXAPI	7.0(3)I4(1) to 7.0(3)I4(8), 7.0(3)I6(1), 7.0(3)I7(3), 7.0(3)I7(4) 7.0(3)I7(5), 7.0(3)I7(6), 9.2(1), 9.2(2), 9.2(3), and 9.3(1).	NA
93180TC-FX / 93180YC-FX	OpenFlow	Not Supported	Not Supported
93180TC-FX / 93180YC-FX	NXAPI	7.0(3)I6(1), 7.0(3)I7(3), 7.0(3)I7(4), 7.0(3)I7(5), 7.0(3)I7(6), 9.2(1), 9.2(2), 9.2(3), and 9.3(1).	NA

APIC versions supported on NDB

Nexus Switch Model(s)	Implementation Type	Supported NX-OS Versions	Open Flow Agent
9504/9508/9516	OpenFlow	Not Supported	Not Supported
9504/9508/9516	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
31108TC-V / 31108PC-V	NXAPI	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
31108TC-V / 31108PC-V	OpenFlow	7.0(3)I4(1) to 7.0(3)I4(9), 7.0(3)I6(1), 7.0(3)I7(3) to 7.0(3)I7(6), 9.2(1) to 9.2(3).	NA
9336C-FX2 / 93240YC-FX2	NXAPI	I7(5)/9.2(1), 7.0(3)I7(5), 7.0(3)I7(5a), 9.2(1), and 9.2(3).	NA

APIC versions supported on NDB

The following tables provide the APIC versions supported on NDB.

Table 3 Scalability Limits for Cisco Nexus Data Broker

APIC Version	Cisco Nexus Data Broker Minimum version	Deployment Mode Supported
1.1, 1.2 and 2.0	NDB 3.0	Centralized only
2.X	NDB 3.1 and above	Centralized only

Verified Scalability Limits

The following tables provide the scalability limits for Cisco Nexus Data Broker for Centralized Deployment

Table 4 Scalability Limits for Cisco Nexus Data Broker

Description	Small	Medium	Large
Number of switches used for Tap and SPAN aggregation	25	50	75

Caveats

This section contains lists of open and resolved caveats and known behaviors.

- Open Caveats
- Resolved Caveats
- Known Caveats

Open Caveats

This section lists the open caveats. Click the bug ID to access the Bug Search tool and see additional information about the bug.

Open Caveats in the 3.5 Release

Bug ID	Description
CSCvk47961	Port configuration fails due to unsupported characters in description: Import.
CSCvg17154	False flow inconsistencies are seen when switches are added in NXAPI mode.
CSCvc41941	Node Id of the device group is not updated after upgrading from NDB release 3.X to 3.2 and above.
CSCuy81389	Cisco Nexus 9000 devices do not have an error pop up message for the connection installation of VLAN + Layer 3 filters.
CSCvg26989	Export operation does not retrieve Node specific configuration.
CSCvg29188	Limitations in uploading a configuration that has redirections (bi-directional).
CSCvg10351	NDB Server backup entries are not shown in the UI after the upgrade.
CSCvh24374	Cisco NDB does not support NXOS 7.0(3)I7(2) NXAPI mode.
CSCvh24146	Stale ACE entries are created on switch when TACACS+ server is unreachable.
CSCvh04723	Unable to remove MAC ACE using sequence number in Cisco NXOS I7(2) release.

Resolved Caveats

This section lists the resolved caveats. Click the bug ID to access the Bug Search tool and see additional information about the bug.

Resolved Caveats in the 3.5 Release

Bug ID	Description
CSCvg27252	Default-match-all filter supports additional ethertypes.
CSCvg28640	PTP and Timestamp configuration fails for ports that are in the port-channel.
CSCvh14853	Programmed ACLs should Include 'ndb' in the name.

Known Caveats

This section lists the known caveats from the previous releases. Click the bug ID to access the Bug Search tool and see additional information about the bug.

Known Caveats For Cisco Nexus Data Broker

Bug ID	Description
CSCvn52641	Disk space not reclaimed in switch I7.x versions while uninstalling Embedded NDB.
CSCve58719	Module Serial number instead of Switch serial number in OF statistics.
CSCve57428	Unable to attach VLAN access list entry to the interface in NXOS Release 7.0(3)I6.1.
CSCve44700	Flows are not installing in switch with simple IPv6 match criteria.
CSCvd89813	NXAPI w/TACACS authentication failing.
CSCvd87975	Reconnecting the switch with NXOS I5.2 from NDB periodically.
CSCve60078	Device in NDB becomes suddenly disconnected - nginx_f crash.
CSCvd15455	Openflow - Portchannel links are not seen on NDB, Release 2.1.
CSCvc87992	Connections are not matched with the VLAN ID of source ports on ISL links with an IPv6 filter.
CSCvh22148	IPv6 traffic is not hitting appropriate ACL deny entries that are configured with UDF.
CSCvg96645	Redirect interface is missing from ACL after an upgrade operation.

Related Documentation

The Cisco Nexus Data Broker documentation can be accessed from the following websites:

Nexus Data Broker Datasheet http://www.cisco.com/c/en/us/products/collateral/cloud-systems-management/nexus-data-broker/data_sheet_c78-729452.html

General Documentation: <http://www.cisco.com/c/en/us/support/cloud-systems-management/nexus-data-broker/tsd-products-support-series-home.html>

The documentation includes installation information and release notes.

Table 5 Installation Documentation

Document	Description
<i>Cisco Nexus Data Broker Embedded Deployment Guide</i>	Describes the deployment Nexus Data Broker on NxOS devices either as a separate NDB virtual service or as a application along with GuestShell+ virtual service
<i>Cisco Nexus Data Broker Centralized Deployment Guide</i>	Describes the deployment of Nexus Data Broker in a Linux VM that be used to manage multiple NxOS device for SPAN configuration

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: www.cisco.com/go/trademarks. Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2018 Cisco Systems, Inc. All rights reserved.