



## Release Notes for Cisco ASR 9000 Series Routers, IOS XR Release 24.4.1

[Release Notes for Cisco ASR 9000 Series Routers, IOS XR Release 24.4.1](#) 2

[What's New in Cisco IOS XR Release 24.4.1](#) 2

[Caveats](#) 11

[Behavior Changes](#) 11

[Supported Packages and System Requirements](#) 11

[Supported Hardware](#) 39

[Compatibility Matrix for EPNM and Crosswork with Cisco IOS XR Software](#) 47

[Important Notes](#) 47

[Related Documentation](#) 49

Revised: December 16, 2024

# Release Notes for Cisco ASR 9000 Series Routers, IOS XR Release 24.4.1

IOS XR 64-bit on Cisco ASR 9000 Series is the next generation operating system running in a virtualized environment with an underlying 64-bit Linux kernel. Cisco IOS XR operating system delivers greater agility, automation, and simplicity while reducing the cost of operating the networks.

## References

For more information about Cisco ASR 9000 Series, see:

- [Cisco ASR 9000 Data Sheet listing page](#)
- [Migration Guide for Cisco ASR 9000 Series Routers](#)

## What's New in Cisco IOS XR Release 24.4.1

Cisco IOS XR Release 24.4.1 is a new feature release for Cisco ASR 9000 Series routers.

For more details on the Cisco IOS XR release model and associated support, see [Software Lifecycle Support Statement - IOS XR](#).

## Software Features Enhanced and Introduced

Feature	Description
<b>Programmability</b>	
<a href="#">Data logging with gNSI AcctzStream service</a>	<p>This feature replaces the existing bi-directional data streaming service, <b>Acctz</b>, with the new server-streaming service, <b>AcctzStream</b> and ensures effective network optimization and resource utilization.</p> <p>With this feature, you can configure the maximum memory allocated for cached accounting history records using the <b>grpc aaa accounting history-memory</b> command.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"><li>• <a href="#">grpc aaa accounting history-memory</a></li></ul> <p>For the specification on the gNSI Accounting (AcctzStream) RPCs and messages, see the <a href="#">Github</a> repository.</p>
<a href="#">gNOI Healthz</a>	<p>With gNOI Healthz, you can monitor and troubleshoot device health by collecting logs and conducting root-cause analysis (RCA) on detected issues. This proactive approach allows for the early identification and resolution of system health problems, thereby reducing downtime and enhancing reliability.</p> <p>For the specification on gNOI.healthz, see the <a href="#">GitHub</a> repository.</p>
<b>Cloud Native BNG User Plane</b>	

Feature	Description
<a href="#">Enable SLAAC for PPPoE Subscriber Sessions</a>	<p>You can achieve seamless connectivity for Customer Premise Equipment (CPEs) using Stateless Address Auto-Configuration (SLAAC) with PPPoE for IPv6 address assignment.</p> <p>This method enables CPEs to automatically configure IPv6 addresses without relying on a DHCP server.</p> <p>By leveraging SLAAC, devices can self-assign addresses based on the IPv6 prefix from the router, simplifying address configuration and reducing administrative overhead.</p> <p>Previously, PPPoE only supported DHCPv6 for IPv6 address assignment.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• <a href="#">slaac</a></li> </ul> <p><b>YANG Data Models:</b></p> <ul style="list-style-type: none"> <li>• <a href="#">Cisco-IOS-XR-ptp-cfg.yang</a></li> </ul> <p>(see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</p>
<b>Segment Routing</b>	
<a href="#">Delay and synthetic loss measurement for GRE tunnel interfaces</a>	<p>You can now measure the latency or delay experienced by data packets when they traverse a network, and also proactively monitor and address potential network issues before they impact users by measuring key parameters such as packet loss, and jitter for GRE tunnel interfaces.</p> <p>This feature enables you to report synthetic Two-Way Active Measurement Protocol (TWAMP) test packets that are deployed in delay-profile or delay measurement sessions, and enables delay measurement for GRE tunnel interfaces.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <p>The <a href="#">performance-measurement interface</a> command supports the <b>tunnel-ip</b> keyword.</p>
<a href="#">Fallback delay advertisement for interfaces</a>	<p>You can now advertise fallback delay value, retaining delay information in performance metrics even when delay metrics for interfaces are temporarily unavailable due to hardware, synchronization, or network connectivity issues. The feature ensures optimal routing decisions, by maintaining network stability and continuous performance, even when real-time metrics are temporarily inaccessible.</p> <p>Previously, the performance metrics did not include delay metrics when they were temporarily inaccessible, resulting in visibility gaps in the network and less effective routing.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <p>The <a href="#">performance-measurement interface</a> command is modified with a new <b>advertise-delay fallback</b> keyword.</p> <p><b>YANG Data Models:</b></p> <ul style="list-style-type: none"> <li>• <a href="#">Cisco-IOS-XR-um-performance-measurement-cfg.yang</a></li> </ul> <p>See (<a href="#">GitHub</a>, <a href="#">Yang Data Models Navigator</a>)</p>

Feature	Description
<a href="#">Far-end delay metrics in one-way measurement mode</a>	<p>SR PM now enables network operators to compute both far-end (T4 – T3) and near-end (T2 – T1) delay metrics, providing a complete view of end-to-end delay across the entire data path. Measuring the far-end delay from the responder to the querier node improves visibility, and allows operators to accurately monitor and evaluate network performance.</p> <p>Previously, you could measure the near-end delay metrics for a given data path.</p>
<a href="#">Flexible algorithm with bandwidth optimization</a>	<p>The enhanced IGP flexible algorithm path computation optimizes paths by automatically adjusting to changes in link bandwidth, which is particularly advantageous for handling parallel L3 links and dynamic changes in link bandwidth, such as in L2 link bundles. This ensures optimal capacity paths by considering cumulative bandwidth in parallel links, preferring paths with the best available bandwidth and benefiting high-bandwidth traffic flows. In addition to traditional metrics like link delay or monetary cost, the algorithm also optimizes paths based on the maximum available bandwidth of links. The bandwidth metric can be locally configured or computed from advertised link bandwidth.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• <a href="#">bandwidth-metric flex-algo</a></li> <li>• <a href="#">metric-type bandwidth</a></li> <li>• <a href="#">reference-bandwidth</a></li> <li>• <a href="#">group-mode</a></li> </ul> <p><b>YANG Data Models:</b></p> <ul style="list-style-type: none"> <li>• New Xpaths are introduced for <code>Cisco-IOS-XR-um-router-isis-cfg.yang</code> (see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</li> </ul>
<a href="#">SR-TE policy with enhanced flexible algorithm metric types</a>	<p>We have enhanced the SR-TE policy at headend with flexible algorithm that supports additional metric types, user-defined and bandwidth, ensuring consistent path computation across flexible algorithm metric types and constraints, on both intra-IGP and inter-IGP domains. The feature also supports headend computed inter-domain SR policies with Flex Algo constraints and IGP redistribution or leaking.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• The <b>flex-algo-metric-type</b> keyword is introduced in the <b>effective-metric admin-distance</b> command.</li> </ul> <p><b>YANG Data Models:</b></p> <ul style="list-style-type: none"> <li>• New Xpaths are introduced for <code>Cisco-IOS-XR-infra-statsd-oper.yang</code> (see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</li> </ul>

Feature	Description
<a href="#">Segment routing Tree-SID interoperability and SR-P2MP enhancements</a>	<p>The feature introduces enhancements to the SR Tree-SID functionality and SR-P2MP Policy, enabling full alignment with the Path Computation Element Protocol (PCEP) standard as per IETF specifications. These improvements enable interoperability between Path Computation Client (PCC) devices from different vendors connected to the PCE, while still supporting the previous Cisco-proprietary implementation.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• The <a href="#">show pce ipv4</a> and <a href="#">show segment-routing traffic-eng pcc ipv4</a> commands are enhanced to display the SR-P2MP capability and the number of SR-P2MP instances.</li> </ul>
<a href="#">VRF-to-VRF route leaking in SRv6 core</a>	<p>VRF-to-VRF route leaking enables sharing of routes between VRFs while maintaining their isolation. This feature allows the source VRF to send leaked routes to remote PEs or Route Reflectors (RRs) across an SRv6 core network, similar to an MPLS core network, enabling communication between different service tenants or administrative domains without compromising VRF isolation.</p>
<p><b>Broadband Network Gateway</b></p>	
<a href="#">BNG with EVPN Port-Active Multihoming to Manage Service Redundancy Group</a>	<p>You can now ensure faster detection of device failures, more accurate response, and a quicker redundancy mechanism using BNG with EVPN Port-Active multihoming. EVPN Port-Active multihoming with BNG allows EVPN to manage port status and control the Service Redundancy Group (SRG) roles, eliminating the need for additional protocols and providing uninterrupted connectivity for subscriber sessions, resulting in simplified access network management and improved overall reliability.</p>
<a href="#">Duplicate Framed-Route for PTA Subscribers</a>	<p>You can enhance the efficiency of your network by enabling PTA subscribers to use identical Framed-Routes with different metric values for subscriber WAN redundancy and load balancing</p> <p>Earlier only one Framed-Route per subscriber was supported.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• <a href="#">ppp duplicate-framed-route</a></li> </ul> <p><b>YANG Data Models:</b></p> <ul style="list-style-type: none"> <li>• <a href="#">Cisco-IOS-XR-ppp-ma-global-cfg</a></li> </ul> <p>(see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</p>

Feature	Description
<a href="#">Performance Tuning for ipoe-dhcp-client-reboot Feature</a>	<p>You can minimize subscriber network churn during network faults, such as Optical Network Terminal (ONT) reboots and network flaps by managing the <b>ipoe-dhcp-client-reboot</b> functionality.</p> <p>We have enabled two timers by default to monitor network flaps and disable the <b>ipoe-dhcp-client-reboot</b> functionality during network flaps. Disabling the functionality temporarily prevents unnecessary session terminations and reduces network churn.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• <b>ont-reboot sir-flap-duration</b></li> <li>• <b>ont-reboot ont-disable-duration</b></li> <li>• The <b>backpressure-level</b> keyword is modified in the <b>subscriber database</b> command.</li> </ul>
<b>L2VPN and Ethernet Services</b>	

Feature	Description
<a href="#">EVPN MAC Scale Limit and Fast Age Out</a>	<p>Introduced in this release on: Modular Systems (ASR 9010, ASR 9912, ASR 9922, ASR 9903)(select variants only*);</p> <p>*This feature is supported on:</p> <ul style="list-style-type: none"> <li>• A9K-4HG-FLEX-TR</li> <li>• A9K-4HG-FLEX-SE</li> <li>• A99-4HG-FLEX-TR</li> <li>• A99-4HG-FLEX-SE</li> <li>• A9K-8HG-FLEX-TR</li> <li>• A9K-8HG-FLEX-SE</li> <li>• A9K-20HG-FLEX-TR</li> <li>• A9K-20HG-FLEX-SE</li> <li>• A99-24HG-FLEX-SE</li> <li>• A99-24HG-FLEX-TR</li> <li>• A99-32X100GE-X-SE</li> <li>• A99-32X100GE-X-TR</li> <li>• A99-10X400GE-X-TR</li> <li>• A99-10X400GE-X-SE</li> <li>• A9K-RSP5-SE</li> <li>• A9K-RSP5-X-SE</li> <li>• A99-RP3-SE</li> <li>• A99-RP3-X-SE</li> </ul> <p>To reduce the maximum aging time for EVPN learned MAC addresses from 2 hours to 30 minutes, you must reduce the MAC scale to 500k using the <b>hw-module profile scale l2-mac-500k</b> command.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>• The <b>l2-mac-500k</b> keyword is introduced in the <a href="#">hw-module profile scale</a> command.</li> </ul> <p><b>YANG Data Model:</b></p> <ul style="list-style-type: none"> <li>• <code>Cisco-IOS-XR-um-asr9k-hw-module-prm-cfg.yang</code></li> </ul> <p>(see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</p>
<b>General Administration</b>	

Feature	Description
<a href="#">Dynamic iTCAM partitioning for a higher BVI scale for A99-12X100GE and A9K-4X100GE line cards</a>	<p>This feature enables you to recarve the internal TCAM partition for BVI in the L2 table for A99-12X100GE and A9K-4X100GE line cards thus facilitating a higher BVI scale.</p> <p>This feature allows to set the two new profiles, <b>to-profile-se2</b> and <b>to-profile-se3</b> so that the scale of the partition where BVI exists in the internal TCAM increases to 2.5K entries with <b>to-profile-se2</b> and 3K entries with <b>to-profile-se3</b> in the L2 table for A99-12X100GE and A9K-4X100GE line cards.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <p>The <b>to-profile-se2</b> and <b>to-profile-se3</b> keywords are introduced in the <b>hw-module profile itcam</b> command.</p> <p><b>YANG Data Model:</b></p> <p>New XPath for <code>Cisco-IOS-XR-um-asr9k-hw-module-prm-cfg.yang</code></p> <p>(see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</p>
<b>System Security</b>	
<a href="#">RADIUS with TLS protection</a>	<p>Remote Authentication Dial-In User Service (RADIUS) over Transport Layer Security (TLS) or RADSEC is now supported on Cisco IOS XR NCS 540 routers. You can configure the RADIUS protocol on the Cisco router (RADIUS client) to redirect RADIUS packets to a remote RADIUS server connected over TLS for Authentication, Authorization, and Accounting (AAA) services.</p> <p>Without TLS, RADIUS packets may be subject to potential security vulnerabilities, including data exposure, replay attacks, weak authentication, and encryption vulnerabilities, especially when transmitted across untrusted networks.</p> <p>The feature introduces these changes:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>The keyword <b>radsec-server</b> is introduced in the <b>radius-server host</b> command.</li> </ul> <p><b>YANG Data Models:</b></p> <ul style="list-style-type: none"> <li>New XPath for <code>Cisco-IOS-XR-um-aaa-cfg.yang</code></li> <li>New XPath for <code>Cisco-IOS-XR-aaa-lib-cfg.yang</code></li> </ul> <p>(see <a href="#">GitHub</a>, <a href="#">YANG Data Models Navigator</a>)</p>
<b>System Monitoring</b>	
<a href="#">Syslog Message Sent to Syslog Servers using Rsyslog Daemon</a>	<p>To handle a high rate of system logging, you can use the rsyslog daemon to forward syslog messages to remote syslog servers.</p>

## YANG Data Models Introduced and Enhanced

This release introduces or enhances the following data models. For detailed information about the supported and unsupported sensor paths of all the data models, see the [Github](#) repository. To get a comprehensive list of the data models supported in a release, navigate to the Available-Content.md file for the release in the Github repository. The unsupported sensor paths are documented as deviations.



For example, `openconfig-acl.yang` provides details about the supported sensor paths, whereas `cisco-xr-openconfig-acl-deviations.yang` provides the unsupported sensor paths for `openconfig-acl.yang` on Cisco IOS XR routers.

You can also view the data model definitions using the [YANG Data Models Navigator](#) tool. This GUI-based and easy-to-use tool helps you explore the nuances of the data model and view the dependencies between various containers in the model. You can view the list of models supported across Cisco IOS XR releases and platforms, locate a specific model, view the containers and their respective lists, leaves, and leaf lists presented visually in a tree structure.

Feature	Description
<b>Programmability</b>	
<p><code>openconfig-aft-summary.yang</code></p>	<p>The OpenConfig data model is revised from version 2.4.0 to 4.3.0. The new <code>aft-summaries</code> container provides the count of routes per origin protocol for both IPv4 and IPv6 protocols. The feature introduces the following change:</p> <p><b>CLI:</b></p> <ul style="list-style-type: none"> <li>The <code>detail</code> keyword is introduced in the <code>show cef tables</code> command.</li> </ul> <p>You can stream Model-driven telemetry (MDT) and Event-driven telemetry (EDT) data for this OpenConfig data model.</p>
<p><code>Openconfig-platform-transceiver</code> Version 0.13.0</p>	<p>The OpenConfig data model provides various metrics and thresholds for transceiver monitoring on gNMI subscribe. It includes minimum, maximum, average, instant, interval, minimum-time, and maximum-time values for containers such as <code>supply-voltage</code>, <code>laser-temperature</code>, <code>tec-current</code>, and <code>target-frequency-deviation</code>. The model also defines upper thresholds for transceiver with leaves like <code>laser-temperature-upper</code>, <code>output-power-upper</code>, <code>input-power-upper</code>, <code>laser-bias-current-upper</code>, <code>supply-voltage-upper</code>, and <code>module-temperature-upper</code>, as well as lower thresholds leaves such as <code>laser-temperature-lower</code>, <code>output-power-lower</code>, <code>input-power-lower</code>, <code>laser-bias-current-lower</code>, <code>supply-voltage-lower</code>, and <code>module-temperature-lower</code>. Additionally, it supports transceiver leaves such as <code>state</code>, <code>enabled</code> and <code>module-functional-type</code>, and transceiver <code>physical-channels</code> leaves including <code>associated-optical-channel</code>, <code>tx-laser</code>, <code>target-output-power</code>, and <code>laser-age</code>.</p> <p>This OC model supports event-driven and model-driven telemetry.</p>

Feature	Description
Openconfig-terminal-device.yang Version 1.9.0	The OpenConfig data model provides instant, minimum, maximum, and average values for parameters of a terminal device using the pre-fec-ber, post-fec-ber, carrier-frequency-offset, modulator-bias-x-phase, modulator-bias-y-phase, modulator-bias-yi, modulator-bias-yq, osnr, q-value, and sop-roc containers. These parameters include Bit Error Rate (BER), channel quality value in decibels, and electrical signal-to-noise ratio in Baud Rate. Additionally, the model offers information on signal distortion, target output power, operational mode of a channel, the frequency of the optical channel, and the input optical power of the port using leaves chromatic-dispersion and target-output-power.
Cisco-IOS-XR-um-performance-measurement-cfg	This unified data model is enhanced with a new container fallback to advertise a fallback delay value, retaining delay information in performance metrics even when the delay metrics for interfaces is temporarily unavailable due to hardware, synchronization, or network connectivity issues.
Cisco-IOS-XR-um-asr9k-hw-module-prm-cfg.yang	This unified data model for PRM is enhanced with new enumerations under the existing leaf, <b>internal-itcam</b> , which allows to switch between TCAM profiles to carve a higher BVI scale for the A99-12X100GE and A9K-4X100GE line cards.
Cisco-IOS-XR-um-router-isis-cfg.yang	<p>The latest update to the Cisco-IOS-XR-um-router-isis-cfg.yang unified data model includes the following additions:</p> <ul style="list-style-type: none"> <li>• The <b>metric-typeleaf</b> is enhanced to include <b>bandwidth</b> and <b>generic</b> as metric types.</li> <li>• The <b>auto-cost</b> container - This is a new container in the <b>flex-algo</b> container to configure the auto-cost for bandwidth metric.</li> </ul> <p>The newly added <b>reference-bandwidth-number</b>, <b>granularity</b>, and <b>group-mode</b> leaves enable you to configure the different parameters required for bandwidth metric auto-cost calculation.</p>

## Hardware Introduced

There are no new hardware introduced in this release.

## Caveats

Table 1: Cisco ASR 9000 Series Router Specific Bugs

Bug ID	Headline
<a href="#">CSCwn01183</a>	Post router reload ,interface creation failed for 4x10G breakout on A9K-16X100GE-TR LC

## Behavior Changes

- You can monitor traffic statistics in bytes for an Access Control Entry (ACE) in an Access Control List (ACL) in the ingress direction. The traffic statistics per ACE includes the total bytes of traffic permitted or denied through an ACE in an ACL across all router interfaces where the ACL is applied. You can use the [show access-lists ipv4](#) command or `Cisco-IOS-XR-ipv4-acl-oper` native yang model to view traffic statistics per ACE in bytes for IPv4 ACLs, and the [show access-lists ipv6](#) command or `Cisco-IOS-XR-ipv6-acl-oper` native yang model to view traffic statistics per ACE in bytes for IPv6 ACLs.
- The directory disk0/disk2 maps to the /misc/scratch partition for IOS-XR, which may be erased during upgrades. Due to the new disk encryption feature requiring re-partitioning, it's advised to move user scripts to a subdirectory under the /harddisk partition to preserve the content.

## Supported Packages and System Requirements

### Feature Set (Software Images)

Visit the [Cisco Software Download page](#) to download the Cisco IOS XR software.

#### Cisco IOS XR 64 bit

This table lists the feature set matrix (ISO and RPM files) and associated filenames available for the Cisco IOS XR 64 bit 24.3.2 Release supported on the Cisco ASR 9000 Series Aggregation Services Router.

**Table 2: Cisco IOS XR 64 bit Software Release 24.4.1 TAR Files**

Feature Set	Filename	Description
Cisco IOS XR IP/MPLS Core Software [for RSP and RP systems]	ASR9K-x64-iosxr-px-24.4.1.tar	<ul style="list-style-type: none"> <li>• Cisco IOS XR Manageability Package</li> <li>• Cisco IOS XR MPLS Package</li> <li>• Cisco IOS XR MPLS -TE and RSVP Package</li> <li>• Cisco IOS XR Multicast Package</li> <li>• Cisco IOS XR Optics Package</li> <li>• Cisco IOS XR BNG Package</li> <li>• Cisco IOS XR Lawful Intercept Package</li> <li>• Cisco IOS XR Satellite Package</li> <li>• Cisco IOS XR EIGRP Package</li> <li>• Cisco IOS XR ISIS Package</li> <li>• Cisco IOS XR OSPF Package</li> <li>• Cisco IOS XR Service Package</li> </ul>
Cisco IOS XR IP/MPLS Core Software 3DES [for RSP and RP systems]	ASR9K-x64-iosxr-px-k9-24.4.1.tar	<ul style="list-style-type: none"> <li>• Cisco IOS XR Manageability Package</li> <li>• Cisco IOS XR MPLS Package</li> <li>• Cisco IOS XR MPLS -TE and RSVP Package</li> <li>• Cisco IOS XR Multicast Package</li> <li>• Cisco IOS XR Optics Package</li> <li>• Cisco IOS XR BNG Package</li> <li>• Cisco IOS XR Lawful Intercept Package</li> <li>• Cisco IOS XR Satellite Package</li> <li>• Cisco IOS XR Security Package</li> <li>• Cisco IOS XR EIGRP Package</li> <li>• Cisco IOS XR ISIS Package</li> <li>• Cisco IOS XR OSPF Package</li> <li>• Cisco IOS XR Service Package</li> </ul>

Feature Set	Filename	Description
Cisco IOS XR IP Unicast Routing Core Bundle and Migration to IOS XR 64 bit tar image	asr9k-mini-x64-migrate_to_eXR.tar-24.4.1	Contains the required core packages, including OS, Admin, Base, Forwarding, Modular Services Card, Routing, FPD, SNMP Agent, and Alarm Correlation.  Contains mini.iso file for XR 64 bit 24.3.2 and additional software for migration to 64 bit.

**Table 3: Cisco IOS XR 64 bit Software Release 24.4.1 ISO and RPM Files**

Composite Package		
Feature Set	Filename	Description
Cisco IOS XR IP Unicast Routing Core Bundle	asr9k-mini-x64-24.4.1.iso	Contains the required core packages, including OS, Admin, Base, Forwarding, Modular Services Card, Routing, FPD, SNMP Agent, and Alarm Correlation.  The mini iso file is used for upgrading to the new release.
Individually-Installable Optional Packages		
Feature Set	Filename	Description
Cisco IOS XR 64 bit EIGRP package	asr9k-eigrp-x64-1.0.0.0-r2441.x86_64.rpm	Includes EIGRP protocol support software
Cisco IOS XR BNG Package	asr9k-bng-x64-1.1.0.0-r2441.x86_64.rpm	Includes binaries to support BNG features.
Cisco IOS XR 64 bit ISIS package	asr9k-isis-x64-1.1.0.0-r2441.x86_64.rpm	Includes IS-IS Link state protocol support software
Cisco IOS XR 64 bit OSPF package	asr9k-ospf-x64-1.1.0.0-r2441.x86_64.rpm	Includes OSPF link state protocol support software
Cisco IOS XR Manageability Package	asr9k-mgbl-x64-3.0.0.0-r2441.x86_64.rpm	CORBA2 agent, XML3 Parser, and HTTP server packages. This RPM also contains some SNMP MIB infrastructure. Certain MIBs won't work if this RPM is not installed.  IPSLA and environment MIBs are part of the mgbl rpm.
Cisco IOS XR 64 bit MPLS-TE and RSVP package	asr9k-mpls-te-rsvp-x64-1.2.0.0-r2441.x86_64.rpm	MPLS Traffic Engineering (MPLS-TE), Resource Reservation Protocol (RSVP).

Cisco IOS XR 64 bit MPLS Package	asr9k-mpls-x64-2.1.0.0-r2441.x86_64.rpm	Label Distribution Protocol (LDP), MPLS Forwarding, MPLS Operations, Administration, and Maintenance (OAM), Link Manager Protocol (LMP), Optical User Network Interface (OUNI) and Layer-3 VPN.
Cisco IOS XR 64 bit Multicast Package	asr9k-mcast-x64-2.0.0.0-r2441.x86_64.rpm	Multicast Routing Protocols (PIM, Multicast Source Discovery Protocol [MSDP], Internet Group Management Protocol [IGMP], Auto-RP), Tools (SAP, MTrace), and Infrastructure [(Multicast Routing Information Base [MRIB], Multicast-Uncast RIB [MURIB], Multicast forwarding [MFWD]), and Bidirectional Protocol Independent Multicast (BIDIR-PIM).
Cisco IOS XR 64 bit Optics Package	asr9k-optic-x64-1.0.0.0-r2441.x86_64.rpm	Firmware for the optics feature for Cisco ASR 9000 Series Aggregation Services Router Chassis. It enables Transport / OTN feature under interfaces.
Cisco IOS XR 64 bit Lawful Intercept (LI) Package	asr9k-li-x64-1.1.0.0-r2441.x86_64.rpm	Includes LI software images.
Cisco IOS XR Security Package	asr9k-k9sec-x64-3.1.0.0-r2441.x86_64.rpm	Support for Encryption, Decryption,, Secure Shell (SSH), Secure Socket Layer (SSL), and Public-key infrastructure (PKI).
Cisco IOS XR Satellite Package -ASR9000v	asr9k-9000v-nV-x64-1.0.0.0-r2441.x86_64.rpm	Includes RPM to support Cisco ASR9000v Series Router Software and to support Cisco ASR 9000v Series Router as a satellite for Cisco ASR 9000 Series Router
Cisco IOS XR 64 bit Services Package	asr9k-services-x64-1.0.0.0-r2441.x86_64.rpm	Includes RPM to support Cisco IOS XR 64-bit inline MAP-T function

## Memory



**Caution** If you remove the media in which the software image or configuration is stored, the router may become unstable and fail.

The available memory for Cisco ASR 9000 Series Aggregation Services Router running Cisco IOS XR Software Release 24.4.1 consist of the following:

- 32 GB memory on the A99-RP-F
- 16 GB memory on the RP2 transport optimised (TR) variant and 32 GB memory on the RP2 service edge (SE) variant
- 24 GB memory on the RP3 transport optimised (TR) variant and 40 GB memory on the RP3 service edge (SE) variant

- 24 GB memory on the RP3-X transport optimised (TR) variant and 48 GB memory on the RP3-X service edge (SE) variant
- 24 GB memory on the RSP5 transport optimised (TR) variant and 40 GB memory on the RSP5 service edge (SE) variant
- 24 GB memory on the RSP5-X transport optimised (TR) variant and 48 GB memory on the RSP5-X service edge (SE) variant
- 2 GB compact flash on route switch processors (RSPs)
- 8 GB memory on the line cards (LCs) running Cisco IOS XR 64-bit image

## Software Compatibility

Cisco IOS XR Software Release 24.4.1 is compatible with the following Cisco ASR 9000 Series Aggregation Services Router systems.

- Cisco ASR 9900 Series Chassis
  - Cisco ASR 9922 Chassis
  - Cisco ASR 9912 Chassis
  - Cisco ASR 9910 Chassis
  - Cisco ASR 9906 Chassis
  - Cisco ASR 9904 Chassis
  - Cisco ASR 9903 Chassis
  - Cisco ASR 9902 Chassis
  - Cisco ASR 9901 Chassis
- Cisco ASR 9000 Series Chassis
  - Cisco ASR 9010 Chassis
  - Cisco ASR 9006 Chassis

For Cisco license support, please contact your Cisco Sales Representative or Customer Service at 800- 553-NETS (6387) or 408-526-4000. For questions on the program other than ordering, please send e-mail to: [cwm-license@cisco.com](mailto:cwm-license@cisco.com).

## Determining Installed Packages

To determine the version of Cisco IOS XR Software packages installed on your router, log in to the router and enter the **show install active summary** command:

### Cisco IOS XR 64 bit

```
Router# show install active summary
Mon Dec 16 14:10:40.287 IST

Label : 24.4.1-v1

Active Packages: 18
  asr9k-xr-24.4.1 version=24.4.1 [Boot image]
  asr9k-9000v-nV-x64-1.0.0.0-r2441
  asr9k-m2m-x64-1.0.0.0-r2441
  asr9k-eigrp-x64-1.0.0.0-r2441
```

```
asr9k-optic-x64-1.0.0.0-r2441
asr9k-isis-x64-1.0.0.0-r2441
asr9k-bng-x64-1.0.0.0-r2441
asr9k-bng-pppoe-x64-1.0.0.0-r2441
asr9k-ospf-x64-1.0.0.0-r2441
asr9k-k9sec-x64-1.0.0.0-r2441
asr9k-bng-ipoe-x64-1.0.0.0-r2441
asr9k-mcast-x64-1.0.0.0-r2441
asr9k-li-x64-1.0.0.0-r2441
asr9k-services-x64-1.0.0.0-r2441
asr9k-mpls-x64-1.0.0.0-r2441
asr9k-bng-supp-x64-1.0.0.0-r2441
asr9k-mgbl-x64-1.0.0.0-r2441
asr9k-mpls-te-rsvp-x64-1.0.0.0-r2441
```

## Firmware Support on Cisco IOS XR 64-bit

To check the firmware code running on the Cisco ASR 9000 Series Router, run the **show fpd package** command in admin mode:





**Note**

The show command output lists supported and EOL hardware PIDs. To know the PIDs that are supported in this release, see the Supported Hardware section in this Release Notes.

```
(sysadmin-vm)#show fpd package
Mon Dec 16 08:40:15.225 UTC+00:00
```

```
=====
```

Field Programmable Device Package					
Card Type	FPD Description	Req Reload	SW Ver	Min Req SW Ver	Min Req Board Ver
A99-10X400GE-X-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	Beachcomber-0	YES	0.01	0.01	0.0
	Beachcomber-1	YES	0.01	0.01	0.0
	CBC	NO	62.05	62.05	0.0
	IPU-DDR4	YES	1.06	1.06	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
A99-10X400GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	Beachcomber-0	YES	0.01	0.01	0.0
	Beachcomber-1	YES	0.01	0.01	0.0
	CBC	NO	62.05	62.05	0.0
	IPU-DDR4	YES	1.06	1.06	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
A99-10X400GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	Beachcomber-0	YES	0.01	0.01	0.0
	Beachcomber-1	YES	0.01	0.01	0.0
	CBC	NO	62.05	62.05	0.0
	IPU-DDR4	YES	1.06	1.06	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Trailbreaker-1	YES	0.24	0.24	0.0
A99-12X100GE	CBC	NO	46.06	46.06	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Morra-0	YES	1.05	1.05	0.1
	Morra-1	YES	1.05	1.05	0.1
	Primary-BIOS	YES	9.33	9.33	0.1
	Sideswipe-0	YES	1.02	1.02	0.1
	Sideswipe-1	YES	1.02	1.02	0.1
A99-12X100GE-CM	CBC	NO	46.06	46.06	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Morra-0	YES	1.05	1.05	0.1
	Morra-1	YES	1.05	1.05	0.1
	Primary-BIOS	YES	9.33	9.33	0.1
	Sideswipe-0	YES	1.02	1.02	0.1

```
=====
```

	Sideswipe-1	YES	1.02	1.02	0.1
-----					
A99-16X100GE-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
-----					
A99-16X100GE-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
-----					
A99-16X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
-----					
A99-16X100GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
-----					
A99-24HG-FLEX-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A99-24HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0

	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A99-24HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A99-24X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A99-24X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A99-24X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A99-32X100GE-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	Grapple-1	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
	Skylynx-1	YES	0.12	0.12	0.0
-----					
A99-32X100GE-DENS	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	57.04	57.04	0.0
	Grapple-0	YES	0.12	0.12	0.0
	Grapple-1	YES	0.12	0.12	0.0
	IPU-DDR4	YES	1.08	1.08	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Mixmaster-1	YES	0.13	0.13	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skylynx-0	YES	0.08	0.08	0.0
	Skylynx-1	YES	0.08	0.08	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0

-----						
A99-32X100GE-SE	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	48.09	48.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	Grapple-1	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.09	1.09	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Mixmaster-1	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	21.43	21.43	0.0	
	Scamper	YES	0.23	0.23	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Skylynx-1	YES	0.12	0.12	0.0	
-----						
A99-32X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	48.09	48.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	Grapple-1	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.09	1.09	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Mixmaster-1	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	21.43	21.43	0.0	
	Scamper	YES	0.23	0.23	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Skylynx-1	YES	0.12	0.12	0.0	
-----						
A99-32X100GE-X-CM	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	57.04	57.04	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	Grapple-1	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Mixmaster-1	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Skylynx-1	YES	0.12	0.12	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
-----						
A99-32X100GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	57.04	57.04	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	Grapple-1	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Mixmaster-1	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Skylynx-1	YES	0.12	0.12	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
-----						
A99-32X100GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	57.04	57.04	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	Grapple-1	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Mixmaster-1	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Skylynx-1	YES	0.12	0.12	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
-----						

A99-48X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A99-48X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A99-48X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A99-4HG-FLEX-FC	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A99-4HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A99-4HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A99-4HG-FLEX-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	64.01	64.01	0.0
	IPU-DDR4	YES	1.01	1.01	0.0
	Moonracer	YES	0.01	0.01	0.0
	Primary-BIOS	YES	25.32	25.32	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0

-----					
A99-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					

A99-8X100GE-CM	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-8X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0



	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99-RP-F	Aldrin-0-FPGA	YES	1.06	1.06	0.0
	CBC	NO	59.13	59.13	0.0
	Lionheart-FPGA	YES	0.30	0.30	0.0
	Longshot	YES	2.16	2.16	0.0
	Primary-BIOS	YES	33.31	33.31	0.0
	TamFW-Longshot	YES	2.65	2.65	0.0
	Wolfpack-FPGA	YES	0.19	0.19	0.0
-----					
A99-RP2-SE	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC-0	NO	35.14	35.14	0.0
	CBC-1	NO	35.14	35.14	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	14.39	14.39	0.0
-----					
A99-RP2-TR	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC-0	NO	35.14	35.14	0.0
	CBC-1	NO	35.14	35.14	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	14.39	14.39	0.0
-----					
A99-RP3-SE	Aldrin-0-FPGA	YES	1.03	1.03	0.0
	Aldrin-1-FPGA	YES	1.00	1.00	0.0
	Beta-FPGA	YES	0.07	0.07	0.0
	CBC-0	NO	51.12	51.12	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	0.20	0.20	0.0
	Orion-FPGA	YES	0.23	0.23	0.0
	Primary-BIOS	YES	30.37	30.37	0.0
	Zenith-FPGA	YES	0.12	0.12	0.0
-----					
A99-RP3-TR	Aldrin-0-FPGA	YES	1.03	1.03	0.0
	Aldrin-1-FPGA	YES	1.00	1.00	0.0
	Beta-FPGA	YES	0.07	0.07	0.0
	CBC-0	NO	51.12	51.12	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	0.20	0.20	0.0
	Orion-FPGA	YES	0.23	0.23	0.0
	Primary-BIOS	YES	30.37	30.37	0.0
	Zenith-FPGA	YES	0.12	0.12	0.0
-----					
A99-RP3-X-SE	Aldrin-0-FPGA	YES	1.00	1.00	0.0
	Aldrin-1-FPGA	YES	32.00	32.00	0.0
	Beta-FPGA	YES	2.02	2.02	0.0
	CBC-0	NO	12.04	12.04	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	3.04	3.04	0.0

	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.12	35.12	0.0
	Sigma	YES	3.34	3.34	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.08	2.08	0.0
-----					
A99-RP3-X-TR	Aldrin-0-FPGA	YES	1.00	1.00	0.0
	Aldrin-1-FPGA	YES	32.00	32.00	0.0
	Beta-FPGA	YES	2.02	2.02	0.0
	CBC-0	NO	12.04	12.04	0.0
	CBC-1	NO	51.12	51.12	0.0
	IPU-DDR4	YES	3.04	3.04	0.0
	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.12	35.12	0.0
	Sigma	YES	3.34	3.34	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.08	2.08	0.0
-----					
A99-RSP-SE	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	43.03	43.03	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	16.18	16.18	0.0
-----					
A99-RSP-TR	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	43.03	43.03	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	16.18	16.18	0.0
-----					
A99-SFC-S	CBC	NO	44.02	44.02	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0
-----					
A99-SFC-T	CBC	NO	44.02	44.02	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0
-----					
A99-SFC2	CBC	NO	37.20	37.20	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0
-----					
A99-SFC3	CBC	NO	49.03	49.03	0.0
	IPU-DDR4	YES	0.25	0.25	0.0
-----					
A99-SFC3-S	CBC	NO	44.02	44.02	0.0
	IPU-DDR4	YES	0.25	0.25	0.0
-----					
A99-SFC3-T	CBC	NO	44.02	44.02	0.0
	IPU-DDR4	YES	0.25	0.25	0.0
-----					
A99L-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0

	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99L-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99L-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99L-8X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99L-8X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A99L-8X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-1600W-AC	PO-PrimMCU	NO	17.137	17.137	0.0
-----					
A9K-1600W-DC	PO-PrimMCU	NO	1.09	1.09	0.0
-----					
A9K-16X100GE-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

-----						
A9K-16X100GE-SE	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	48.09	48.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.09	1.09	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	21.43	21.43	0.0	
	Scamper	YES	0.23	0.23	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
-----						
A9K-16X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	48.09	48.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.09	1.09	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	21.43	21.43	0.0	
	Scamper	YES	0.23	0.23	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
-----						
A9K-16X100GE-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	48.09	48.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.09	1.09	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	21.43	21.43	0.0	
	Scamper	YES	0.23	0.23	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
-----						
A9K-20HG-FLEX-CM	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	58.09	58.09	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
	Trailbreaker-0	YES	0.24	0.24	0.0	
	Trailbreaker-1	YES	0.24	0.24	0.0	
	Windcharger-0	YES	0.08	0.08	0.0	
	Windcharger-1	YES	0.08	0.08	0.0	
-----						
A9K-20HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	58.09	58.09	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
	Trailbreaker-0	YES	0.24	0.24	0.0	
	Trailbreaker-1	YES	0.24	0.24	0.0	
	Windcharger-0	YES	0.08	0.08	0.0	
	Windcharger-1	YES	0.08	0.08	0.0	
-----						
A9K-20HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	58.09	58.09	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
	Trailbreaker-0	YES	0.24	0.24	0.0	
	Trailbreaker-1	YES	0.24	0.24	0.0	
	Windcharger-0	YES	0.08	0.08	0.0	
	Windcharger-1	YES	0.08	0.08	0.0	
-----						
A9K-24X10GE-1G-CM	CBC	NO	47.03	47.03	0.1	
	IPU-FPGA	YES	1.90	1.90	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	

	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A9K-24X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A9K-24X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A9K-400G-DWDM-TR	CBC	NO	42.04	42.04	0.0
	Doran	YES	1.05	1.05	0.0
	Frenzy	YES	49.00	49.00	0.0
	IPU-FPGA	YES	1.97	1.97	0.1
	IPU-FSBL	YES	1.103	1.103	0.1
	IPU-Linux	YES	1.103	1.103	0.1
	Martell	YES	1.03	1.03	0.0
	Meldun	YES	1.07	1.07	0.1
	Primary-BIOS	YES	8.51	8.51	0.1
-----					
A9K-400GE-LSP	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A9K-48X10GE-1G-CM	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A9K-48X10GE-1G-SE	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1
	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A9K-48X10GE-1G-TR	CBC	NO	47.03	47.03	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Leadfoot-0	YES	1.00	1.00	0.1

	Leadfoot-1	YES	1.00	1.00	0.1
	Lewis	YES	1.11	1.11	0.1
	Primary-BIOS	YES	18.33	18.33	0.1
-----					
A9K-4HG-FLEX-FC	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A9K-4HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A9K-4HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	63.03	63.03	0.0
	IPU-DDR4	YES	1.05	1.05	0.0
	Moonracer	YES	0.14	0.14	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A9K-4HG-FLEX-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	64.01	64.01	0.0
	IPU-DDR4	YES	1.01	1.01	0.0
	Moonracer	YES	0.01	0.01	0.0
	Primary-BIOS	YES	25.32	25.32	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
A9K-4X100GE	CBC	NO	46.06	46.06	0.1
	IPU-FPGA	YES	1.90	1.90	0.1
	IPU-FSBL	YES	1.113	1.113	0.1
	IPU-Linux	YES	1.113	1.113	0.1
	Morra-0	YES	1.05	1.05	0.1
	Primary-BIOS	YES	9.33	9.33	0.1
	Sideswipe-0	YES	1.02	1.02	0.1
-----					
A9K-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0

	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-4X100GE-TR-V2	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
-----					
A9K-8HG-FLEX-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0

	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
-----					
A9K-8HG-FLEX-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
-----					
A9K-8HG-FLEX-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
-----					
A9K-8X100GE-CM	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-L-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-L-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-L-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-SE	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0



	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-TR	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9K-8X100GE-X-CM	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
-----					
A9K-8X100GE-X-SE	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0
-----					
A9K-8X100GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	48.09	48.09	0.0
	Grapple-0	YES	0.15	0.15	0.0
	IPU-DDR4	YES	1.09	1.09	0.0
	Mixmaster-0	YES	0.13	0.13	0.0
	Primary-BIOS	YES	21.43	21.43	0.0
	Scamper	YES	0.23	0.23	0.0
	Skylynx-0	YES	0.12	0.12	0.0

-----						
A9K-8X100GE-X-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	48.09	48.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.09	1.09	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	21.43	21.43	0.0	
	Scamper	YES	0.23	0.23	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
-----						
A9K-8X100GE-X2-CM	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	58.09	58.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
-----						
A9K-8X100GE-X2-SE	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	58.09	58.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
-----						
A9K-8X100GE-X2-TR	Aldrin-FPGA	YES	1.05	1.05	0.0	
	CBC	NO	58.09	58.09	0.0	
	Grapple-0	YES	0.15	0.15	0.0	
	IPU-DDR4	YES	1.18	1.18	0.0	
	Mixmaster-0	YES	0.13	0.13	0.0	
	Primary-BIOS	YES	25.31	25.31	0.0	
	Skylynx-0	YES	0.12	0.12	0.0	
	Sunstreaker	YES	0.19	0.19	0.0	
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0	
-----						
A9K-8X100GELSE-TAA	CBC	NO	38.23	38.23	0.0	
	Dalla	YES	1.09	1.09	0.0	
	IPU-FPGA	YES	1.99	1.99	0.0	
	IPU-FSBL	YES	1.113	1.113	0.0	
	IPU-Linux	YES	1.113	1.113	0.0	
	Meldun-0	YES	1.07	1.07	0.0	
	Meldun-1	YES	1.07	1.07	0.0	
	Primary-BIOS	YES	8.51	8.51	0.0	
-----						
A9K-8X100GELTR-TAA	CBC	NO	38.23	38.23	0.0	
	Dalla	YES	1.09	1.09	0.0	
	IPU-FPGA	YES	1.99	1.99	0.0	
	IPU-FSBL	YES	1.113	1.113	0.0	
	IPU-Linux	YES	1.113	1.113	0.0	
	Meldun-0	YES	1.07	1.07	0.0	
	Meldun-1	YES	1.07	1.07	0.0	
	Primary-BIOS	YES	8.51	8.51	0.0	
-----						
A9K-MOD200-CM	Blaster	YES	1.27	1.27	0.1	
	CBC	NO	39.09	39.09	0.1	
	IPU-FPGA	YES	1.101	1.101	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	
	IPU-Linux	YES	1.113	1.113	0.1	
	Primary-BIOS	YES	8.51	8.51	0.1	

-----						
A9K-MOD200-SE	Blaster	YES	1.27	1.27	0.1	
	CBC	NO	39.09	39.09	0.1	
	IPU-FPGA	YES	1.101	1.101	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	
	IPU-Linux	YES	1.113	1.113	0.1	
	Primary-BIOS	YES	8.51	8.51	0.1	
-----						
A9K-MOD200-TR	Blaster	YES	1.27	1.27	0.1	
	CBC	NO	39.09	39.09	0.1	
	IPU-FPGA	YES	1.101	1.101	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	
	IPU-Linux	YES	1.113	1.113	0.1	
	Primary-BIOS	YES	8.51	8.51	0.1	
-----						
A9K-MOD400-CM	Blaster	YES	1.27	1.27	0.1	
	CBC	NO	39.09	39.09	0.1	
	IPU-FPGA	YES	1.101	1.101	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	
	IPU-Linux	YES	1.113	1.113	0.1	
	Primary-BIOS	YES	8.51	8.51	0.1	
-----						
A9K-MOD400-SE	Blaster	YES	1.27	1.27	0.1	
	CBC	NO	39.09	39.09	0.1	
	IPU-FPGA	YES	1.101	1.101	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	
	IPU-Linux	YES	1.113	1.113	0.1	
	Primary-BIOS	YES	8.51	8.51	0.1	
-----						
A9K-MOD400-TR	Blaster	YES	1.27	1.27	0.1	
	CBC	NO	39.09	39.09	0.1	
	IPU-FPGA	YES	1.101	1.101	0.1	
	IPU-FSBL	YES	1.113	1.113	0.1	
	IPU-Linux	YES	1.113	1.113	0.1	
	Primary-BIOS	YES	8.51	8.51	0.1	
-----						
A9K-RSP5-SE	Aldrin-0-FPGA	YES	1.06	1.06	0.0	
	Beta-FPGA	YES	0.07	0.07	0.0	
	CBC	NO	53.10	53.10	0.0	
	IPU-DDR4	YES	0.20	0.20	0.0	
	Orion-FPGA	YES	0.23	0.23	0.0	
	Primary-BIOS	YES	31.37	31.37	0.0	
	Zenith-FPGA	YES	0.12	0.12	0.0	
-----						
A9K-RSP5-TR	Aldrin-0-FPGA	YES	1.06	1.06	0.0	
	Beta-FPGA	YES	0.07	0.07	0.0	
	CBC	NO	53.10	53.10	0.0	
	IPU-DDR4	YES	0.20	0.20	0.0	
	Orion-FPGA	YES	0.23	0.23	0.0	
	Primary-BIOS	YES	31.37	31.37	0.0	
	Zenith-FPGA	YES	0.12	0.12	0.0	
-----						
A9K-RSP5-X-SE	Aldrin-0-FPGA	YES	51.00	51.00	0.0	
	Beta-FPGA	YES	2.02	2.02	0.0	
	CBC	NO	14.04	14.04	0.0	
	IPU-DDR4	YES	3.04	3.04	0.0	
	Orion-FPGA	YES	2.03	2.03	0.0	
	Primary-BIOS	YES	35.12	35.12	0.0	
	Sigma	YES	3.34	3.34	0.0	
	TamFW-Sigma	YES	2.07	2.07	0.0	
	Zenith-FPGA	YES	2.08	2.08	0.0	
-----						
A9K-RSP5-X-TR	Aldrin-0-FPGA	YES	51.00	51.00	0.0	
	Beta-FPGA	YES	2.02	2.02	0.0	

	CBC	NO	14.04	14.04	0.0
	IPU-DDR4	YES	3.04	3.04	0.0
	Orion-FPGA	YES	2.03	2.03	0.0
	Primary-BIOS	YES	35.12	35.12	0.0
	Sigma	YES	3.34	3.34	0.0
	TamFW-Sigma	YES	2.07	2.07	0.0
	Zenith-FPGA	YES	2.08	2.08	0.0
-----					
A9K-RSP880-LT-SE	Aldrin-FPGA	YES	1.11	1.11	0.0
	Alpha-FPGA	YES	0.05	0.05	0.0
	CBC	NO	50.03	50.03	0.0
	IPU-FPGA	YES	0.20	0.20	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.07	0.07	0.0
	Optimus-FPGA	YES	0.05	0.05	0.0
	Primary-BIOS	YES	17.40	17.40	0.0
-----					
A9K-RSP880-LT-TR	Aldrin-FPGA	YES	1.11	1.11	0.0
	Alpha-FPGA	YES	0.05	0.05	0.0
	CBC	NO	50.03	50.03	0.0
	IPU-FPGA	YES	0.20	0.20	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.07	0.07	0.0
	Optimus-FPGA	YES	0.05	0.05	0.0
	Primary-BIOS	YES	17.40	17.40	0.0
-----					
A9K-RSP880-SE	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	34.40	34.40	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	10.69	10.69	0.0
-----					
A9K-RSP880-TR	Alpha-FPGA	YES	0.16	0.16	0.0
	CBC	NO	34.40	34.40	0.0
	Cha-FPGA	YES	0.09	0.09	0.0
	IPU-FPGA	YES	0.72	0.72	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Omega-FPGA	YES	0.20	0.20	0.0
	Optimus-FPGA	YES	0.12	0.12	0.0
	Primary-BIOS	YES	10.69	10.69	0.0
-----					
A9K-TEST_LSQ_DX1	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	58.09	58.09	0.0
	IPU-DDR4	YES	1.18	1.18	0.0
	Primary-BIOS	YES	25.31	25.31	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Trailbreaker-0	YES	0.24	0.24	0.0
	Windcharger-0	YES	0.08	0.08	0.0
-----					
A9KL-4X100GE-SE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0

	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9KL-4X100GE-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
A9KL-4X100GE-TR-TAA	CBC	NO	38.23	38.23	0.0
	Dalla	YES	1.09	1.09	0.0
	IPU-FPGA	YES	1.99	1.99	0.0
	IPU-FSBL	YES	1.113	1.113	0.0
	IPU-Linux	YES	1.113	1.113	0.0
	Meldun-0	YES	1.07	1.07	0.0
	Meldun-1	YES	1.07	1.07	0.0
	Primary-BIOS	YES	8.51	8.51	0.0
-----					
ASR-9006-AC	CBC	NO	7.105	7.105	0.0
-----					
ASR-9006-AC-V2	CBC	NO	7.105	7.105	0.0
-----					
ASR-9006-FAN	CBC	NO	5.04	5.04	0.0
-----					
ASR-9006-FAN-V2	CBC	NO	5.05	5.05	0.0
-----					
ASR-9010-AC	CBC	NO	7.105	7.105	0.0
-----					
ASR-9010-AC-V2	CBC	NO	7.105	7.105	0.0
-----					
ASR-9010-FAN	CBC	NO	4.03	4.03	0.0
-----					
ASR-9010-FAN-V2	CBC	NO	29.12	29.12	0.0
-----					
ASR-9901-LC	CBC	NO	55.07	55.07	0.1
	Gamora-FPGA	YES	0.36	0.36	0.1
	IPU-FPGA	YES	1.10	1.10	0.1
	IPU-FSBL	YES	1.104	1.104	0.1
	IPU-Linux	YES	1.104	1.104	0.1
	Primary-BIOS	YES	23.24	23.24	0.1
-----					
ASR-9901-RP	CBC	NO	54.11	54.11	0.1
	Drax-FPGA	YES	0.38	0.38	0.1
	IPU-FPGA	YES	2.05	2.05	0.1
	IPU-FSBL	YES	1.104	1.104	0.1
	IPU-Linux	YES	1.104	1.104	0.1
	Primary-BIOS	YES	22.29	22.29	0.1
-----					
ASR-9902	FAN-CBC	NO	61.25	61.25	0.0
-----					
ASR-9902-LC	Aldrin-FPGA	YES	1.05	1.05	0.0
	CBC	NO	17.03	17.03	0.0
	Chromia	YES	0.14	0.14	0.0
	IPU-DDR4	YES	1.17	1.17	0.0
	Primary-BIOS	YES	34.31	34.31	0.0
	Skywarp-0	YES	0.11	0.11	0.0
	Skywarp-1	YES	0.11	0.11	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
-----					
ASR-9903	FAN-CBC	NO	61.25	61.25	0.0
-----					

ASR-9903-LC	Aldrin-0-FPGA	YES	1.05	1.05	0.0
	CBC	NO	60.12	60.12	0.0
	Harpoon-0	YES	0.11	0.11	0.0
	Harpoon-1	YES	0.11	0.11	0.0
	IPU-DDR4	YES	1.25	1.25	0.0
	Metalmaster-0	YES	0.02	0.02	0.0
	Metalmaster-1	YES	0.02	0.02	0.0
	Primary-BIOS	YES	34.31	34.31	0.0
	Scattershot	YES	0.14	0.14	0.0
	Sunstreaker	YES	0.19	0.19	0.0
	Supernaut	YES	0.14	0.14	0.0
	TAMFW-Sunstreaker	YES	2.72	2.72	0.0
	Warstar-0	YES	0.02	0.02	0.0
	Warstar-1	YES	0.02	0.02	0.0
-----					
ASR-9903-PXC800G-LC	Harpoon-0	YES	0.11	0.11	0.0
	Harpoon-1	YES	0.11	0.11	0.0
-----					
ASR-9904-AC	CBC	NO	7.105	7.105	0.0
-----					
ASR-9904-FAN	CBC	NO	31.06	31.06	0.0
-----					
ASR-9906	CBC	NO	7.105	7.105	0.0
-----					
ASR-9906-FAN	CBC	NO	56.01	56.01	0.0
	PSOC	NO	2.06	2.06	0.0
-----					
ASR-9910	CBC	NO	7.105	7.105	0.0
-----					
ASR-9910-FAN	CBC	NO	45.02	45.02	0.0
	PSOC	NO	2.06	2.06	0.0
-----					
ASR-9912-AC	CBC	NO	7.105	7.105	0.0
-----					
ASR-9912-FAN	CBC	NO	31.06	31.06	0.0
-----					
ASR-9912-SFC220	CBC	NO	37.20	37.20	0.0
	IPU-FPGA	YES	0.37	0.37	0.0
	IPU-FSBL	YES	1.100	1.100	0.0
	IPU-Linux	YES	1.100	1.100	0.0
-----					
ASR-9922-AC	CBC-0	NO	7.105	7.105	0.0
	CBC-1	NO	7.105	7.105	0.0
-----					
ASR-9922-FAN	CBC	NO	29.12	29.12	0.0
-----					
ASR-9922-FAN-V2	CBC	NO	40.07	40.07	0.0
	PSOC	NO	2.06	2.06	0.0
-----					
ASR-9922-FAN-V3	CBC	NO	40.07	40.07	0.0
	PSOC	NO	2.06	2.06	0.0
-----					
PWR-1.6KW-AC	PO-PrimMCU	NO	17.20	17.20	0.0
	QCS-PrimMCU	NO	3.02	3.02	0.1
	QCS-SecMCU	NO	4.04	4.04	0.1
-----					
PWR-1.6KW-DC	PO-PrimMCU	NO	1.03	1.03	0.0
	QCS-PrimMCU	NO	1.05	1.05	0.0
-----					
PWR-2KW-DC-V2	DT-PrimMCU	NO	6.03	6.03	0.12
	DT-Sec54vMCU	NO	6.02	6.02	0.12
	DT-Sec5vMCU	NO	6.03	6.03	0.12
	EM-PrimMCU	NO	3.13	3.13	0.12
	EM-Sec54vMCU	NO	3.21	3.21	0.12

	EM-Sec5vMCU	NO	3.20	3.20	0.12
PWR-3KW-AC-V2	DT-PriMCU	NO	6.02	6.02	1.0
	DT-Sec54vMCU	NO	6.02	6.02	1.0
	DT-Sec5vMCU	NO	6.04	6.04	1.0
	EM-Sec54vMCU	NO	3.12	3.12	0.21
	EM-Sec5vMCU	NO	3.18	3.18	0.21
PWR-3KW-HVDC	DT-PriMCU	NO	2.02	2.02	1.0
	DT-Sec54vMCU	NO	2.02	2.02	1.0
	DT-Sec5vMCU	NO	2.03	2.03	1.0
PWR-4.4KW-DC-V3	AB-Pri0MCU	NO	3.02	3.02	0.1
	AB-Pri1MCU	NO	3.02	3.02	0.1
	AB-Sec054vMCU	NO	3.04	3.04	0.1
	AB-Sec154vMCU	NO	3.04	3.04	0.1
	AB-Sec5vMCU	NO	3.06	3.06	0.1
	DT-Pri0MCU	NO	3.01	3.01	0.1
	DT-Pri1MCU	NO	3.01	3.01	0.1
	DT-Sec054vMCU	NO	3.03	3.03	0.1
	DT-Sec154vMCU	NO	3.03	3.03	0.1
	DT-Sec5vMCU	NO	3.02	3.02	0.1
	QCS-Pri0MCU	NO	1.04	1.04	0.1
	QCS-Pri1MCU	NO	1.04	1.04	0.1
	QCS-Sec054vMCU	NO	1.10	1.10	0.1
	QCS-Sec154vMCU	NO	1.10	1.10	0.1
	QCS-Sec5vMCU	NO	1.06	1.06	0.1
PWR-6KW-AC-V3	AB-Pri0MCU	NO	3.02	3.02	0.1
	AB-Pri1MCU	NO	3.02	3.02	0.1
	AB-Sec054vMCU	NO	3.02	3.02	0.1
	AB-Sec154vMCU	NO	3.02	3.02	0.1
	AB-Sec5vMCU	NO	3.05	3.05	0.1
	DT-Pri0MCU	NO	4.02	4.02	0.1
	DT-Pri1MCU	NO	4.02	4.02	0.1
	DT-Sec054vMCU	NO	4.03	4.03	0.1
	DT-Sec154vMCU	NO	4.03	4.03	0.1
	DT-Sec5vMCU	NO	4.04	4.04	0.1

## Supported Hardware

The following table lists the supported hardware components on the Cisco ASR 9000 Series Router and the minimum required software versions. For more information, see the *Firmware Support* section.

All hardware features are supported on Cisco IOS XR Software, subject to the memory requirements specified in the section.

For information on the end-of-sale and end-of-life dates for the Cisco ASR 9000 Series Router hardware, refer to the [End-of-Life and End-of-Sale Notices](#) page.

**Table 4: Cisco ASR 9000 Series Aggregation Services Router Supported Hardware and Minimum Software Requirements**

Cisco ASR 9000 Series Aggregation Services Router - Route Switch Processor Cards		
Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
A9K-RSP5-X-SE	ASR 9000 Series Route Switch Processor 5 for Service Edge, Premium	Release 7.6.2

A9K-RSP5-X-TR	ASR 9000 Series Route Switch Processor 5 for Packet Transport, Premium	Release 7.6.2
A9K-RSP5-SE	ASR 9000 Route Switch Processor 5 for Service Edge	Release 6.5.15
A9K-RSP5-TR	ASR 9000 Route Switch Processor 5 for Packet Transport	Release 6.5.15
A9K-RSP880-SE	ASR9K Route Switch Processor with 880G/slot and 32 GB for Service Edge	Release 6.1.2
<b>Cisco ASR 9000 Series Aggregation Services Router - Route Processor Cards</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
A99-RP3-X-SE	ASR 9900 Route Processor 3 for Service Edge, Premium	Release 7.6.2
A99-RP3-X-TR	ASR 9900 Route Processor 3 for Packet Transport, Premium	Release 7.6.2
A99-RP3-SE	ASR 9900 Route Processor 3 for Service Edge	Release 6.5.15
A99-RP3-TR	ASR 9900 Route Processor 3 for Packet Transport	Release 6.5.15
<b>Cisco ASR 9901 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9901	Cisco ASR 9000 Series Aggregation Services Router 2-RU Fixed Port	Release 6.4.1
ASR-9901-FAN	Cisco ASR 9000 Series Aggregation Services Router 2-RU Fixed Port Fan Tray	Release 6.4.1
A9K-1600W-AC	Cisco ASR 9000 Series Aggregation Services Router 2-RU 1600W AC Power Module	Release 6.4.1
A9K-1600W-DC	Cisco ASR 9000 Series Aggregation Services Router 2-RU 1600W DC Power Module	Release 6.4.1
<b>Cisco ASR 9902 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9902	Cisco ASR 9902 2RU Chassis with fixed ports	Release 7.4.1
A99-RP-F	Cisco ASR 9900 Fixed Chassis Route Processor	Release 7.1.3
ASR-9902-4P-KIT	Cisco ASR 9902 4-Post Mounting Kit for 19-Inch and 23-Inch Rack	Release 7.4.1
ASR-9902-4P-KIT-L	ASR 9902 4-Post Mounting Kit for 19 & 23 inch Rack – Long	Release 7.4.1
ASR-9902-2P-KIT	Cisco ASR 9902 2-Post Mounting Kit for 19-Inch and 23-Inch Rack	Release 7.4.1
ASR-9902-CAB-MGMT	Cisco ASR 9902 Cable Management	Release 7.4.1



ASR-9902-FILTER	Cisco ASR 9902 Air Filter	Release 7.4.1
ASR-9902-FAN	Cisco ASR 9902 Fan Tray	Release 7.4.1
<b>Cisco ASR 9903 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9903	Cisco ASR 9903 Compact High-Performance Router with fixed ports and PEC (Port Expansion Card) slot.	Release 7.1.3
A99-RP-F	Cisco ASR 9900 Fixed Chassis Route Processor	Release 7.1.3
ASR-9903-FAN	Cisco ASR 9903 Router Fan Tray	Release 7.1.3
ASR-9903-4P-KIT	ASR 9903 4-Post Mounting Kit for 19-inch Rack	Release 7.1.3
ASR-9903-CAB-MGMT	ASR 9903 Cable Management Brackets	Release 7.1.3
ASR-9903-FILTER	ASR 9903 Air Filter	Release 7.1.3
<b>Cisco ASR 9904 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9904	Cisco ASR 9000 Series Aggregation Services Router 4-Slot 2 Line Card Slot Chassis, 6 RU	Release 6.1.2
ASR-9904-AC	Cisco ASR 9000 Series Aggregation Services Router 4-Slot 2 Line Card Slot AC Chassis w/ PEM V2	Release 6.1.2
ASR-9904-DC	Cisco ASR 9000 Series Aggregation Services Router 4-Slot 2 Line Card Slot DC Chassis w/ PEM V2	Release 6.1.2
ASR-9904-FAN	Cisco ASR 9000 Series Aggregation Services Router 4-Slot Fan Tray	Release 6.1.2
ASR-9904-FILTER	Cisco ASR 9000 Series Aggregation Services Router 4-Slot Filter	Release 6.1.2
ASR-9904-BAFFLE	Cisco ASR 9000 Series Aggregation Services Router 4-Slot Baffle	Release 6.1.2
<b>Cisco ASR 9912 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9912	Cisco ASR 9000 Series Aggregation Services Router 12-Slot 10 Line Card Slot Chassis	Release 6.1.2
ASR-9912-AC	Cisco ASR 9000 Series Aggregation Services Router 12-Slot 10 Line Card Slot AC Chassis w/ PEM V2	Release 6.1.2
ASR-9912-DC	Cisco ASR 9000 Series Aggregation Services Router 12-Slot 10 Line Card Slot DC Chassis w/ PEM V2	Release 6.1.2

A99-SFC3	Cisco ASR 9900 Switch Fabric Card 3	Release 6.5.15
ASR-9912-FAN	Cisco ASR 9000 Series Aggregation Services Router 12-Slot Fan Tray	Release 6.1.2
<b>Cisco ASR 9922 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9922	Cisco ASR 9922 20 Line Card Slot Chassis, 44 RU	Release 6.1.2
ASR-9922-AC	Cisco ASR 9000 Series Aggregation Services Router 22-Slot 20 Line Card Slot AC Chassis w/ PEM V2	Release 6.1.2
ASR-9922-DC	Cisco ASR 9000 Series Aggregation Services Router 22-Slot 20 Line Card Slot DC Chassis w/ PEM V2	Release 6.1.2
A99-SFC3	Cisco ASR 9900 Switch Fabric Card 3	Release 6.5.15
ASR-9922-FAN-V3	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Fan Tray version 3	Release 6.5.15
ASR-9922-FLTR-CV2	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Air Filter with Media, Center	Release 6.1.2
ASR-9922-FLTR-LR	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Air Filter with Media, Left & Right	Release 6.1.2
ASR-9922-RP-FILR	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Route Processor Filler	Release 6.1.2
ASR-9922-FAN-V2	Cisco ASR 9000 Series Aggregation Services Router 22-Slot Version 2 Fan Tray	Release 6.1.2
<b>Cisco ASR 9006 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9006-SYS	Cisco ASR 9000 Series Aggregation Services Router 6-Slot System	Release 6.1.2
ASR-9006-AC-V2	Cisco ASR 9000 Series Aggregation Services Router 6-Slot AC Chassis Version 2	Release 6.1.2
ASR-9006-DC-V2	Cisco ASR 9000 Series Aggregation Services Router 6-Slot DC Chassis Version 2	Release 6.1.2
ASR-9006-FAN	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Fan Tray	Release 6.1.2
ASR-9006-DOOR	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Door Kit	Release 6.1.2
ASR-9006-FILTER	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Air Filter	Release 6.1.2
<b>Cisco ASR 9906 Router</b>		

<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9906	Cisco ASR 9000 Series Aggregation Services Router 6-Slot chassis	Release 6.3.1
ASR-9906-FAN	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Fan Tray	Release 6.3.1
ASR-9906-FILTER	Cisco ASR 9000 Series Aggregation Services Router 6-Slot Fan Filter	Release 6.3.1
A99-SFC3-T	ASR 9906 Switch Fabric Card	Release 6.5.15
<b>Cisco ASR 9010 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9010-SYS	Cisco ASR 9000 Series Aggregation Services Router 10-Slot System	Release 6.1.2
ASR-9010-AC-V2	Cisco ASR 9000 Series Aggregation Services Router 10-Slot AC Chassis Version 2	Release 6.1.2
ASR-9010-DC-V2	Cisco ASR 9000 Series Aggregation Services Router 10-Slot DC Chassis Version 2	Release 6.1.2
ASR-9010-FAN	Cisco ASR 9000 Series Aggregation Services Router 10-Slot Fan Tray	Release 6.1.2
ASR-9010-DOOR	Cisco ASR 9000 Series Aggregation Services Router 10-Slot Door Kit	Release 6.1.2
ASR-9010-2P-KIT	Cisco ASR 9000 Series Aggregation Services Router 2 Post Mounting Kit	Release 6.1.2
ASR-9010-2P-KIT	Cisco ASR 9000 Series Aggregation Services Router 4 Post Mounting Kit	Release 6.1.2
ASR-9010-FILTER	Cisco ASR 9000 Series Aggregation Services Router 10-Slot Air Filter	Release 6.1.2
<b>Cisco ASR 9910 Router</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
ASR-9910	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) System	Release 6.2.1
ASR-9910-FAN	Cisco ASR 9000 Series Aggregation Services Router 10-Slot(9910) Fan Tray	Release 6.2.1
ASR-9910-ACC-KIT	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Accessory Kit	Release 6.2.1
ASR-9910-4P-KIT	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) 4 Post Rack Mounting Kit	Release 6.2.1

ASR-9910-2P-KIT	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) 2 Post Rack Mounting Kit	Release 6.2.1
ASR-9910-AIRREF	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Air Reflector	Release 6.2.1
ASR-9910-FILTER	Cisco ASR 9000 Series Aggregation Services Router 10-Slot (9910) Air Filter	Release 6.2.1
A99-SFC3-S	ASR 9910 Switch Fabric Card 3	Release 6.5.15
<b>Cisco ASR 9000 Series Aggregation Services Router - Power Modules</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
PWR-2KW-DC-V2	Cisco ASR 9000 Series Aggregation Services Router 2KW DC Power Module, version 2	Release 6.1.2
PWR-3KW-AC-V2	Cisco ASR 9000 Series Aggregation Services Router 3KW AC Power Module, version 2	Release 6.1.2
A9K-AC-PEM-V2	Cisco ASR 9000 Series Aggregation Services Router AC Power Entry Module Version 2	Release 6.1.2
A9K-DC-PEM-V2	Cisco ASR 9000 Series Aggregation Services Router DC Power Entry Module Version 2	Release 6.1.2
A9K-PEM-V2-FILR	Cisco ASR 9000 Series Aggregation Services Router Power Entry Module Version 2 Filler	Release 6.1.2
A9K-AC-PEM-V3	Cisco ASR 9000 Series Aggregation Services Router AC Power Enclosure Module Version 3	Release 6.1.2
A9K-DC-PEM-V3	Cisco ASR 9000 Series Aggregation Services Router DC Power Enclosure Module Version 3	Release 6.1.2
PWR-6KW-AC-V3	Cisco ASR 9000 Series Aggregation Services Router 6kW AC Power Module Version 3	Release 6.1.2
PWR-4.4KW-DC-V3	Cisco ASR 9000 Series Aggregation Services Router 4.4kW DC Power Module Version 3	Release 6.1.2
PWR-1.6KW-AC	ASR 9900 Fixed Chassis AC Power Supply	Release 7.1.25
PWR-1.6KW-DC	ASR 9900 Fixed Chassis DC Power Supply	Release 7.1.25
<b>Cisco ASR 9000 Series Aggregation Services Router - Line Cards</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
A9K-4HG-FLEX-SE	ASR 9000 400GE Combo Service Edge Line Card - 5th Generation	Release 7.4.1
A9K-4HG-FLEX-TR	ASR 9000 400GE Combo Packet Transport Line Card - 5th Generation	Release 7.4.1

A99-4HG-FLEX-SE	ASR 9900 400GE Combo Service Edge Line Card - 5th Generation	Release 7.4.1
A99-4HG-FLEX-TR	ASR 9900 400GE Combo Packet Transport Line Card - 5th Generation	Release 7.4.1
A9903-8HG-PEC	ASR 9903 800G Multi-rate Port Expansion Card	Release 7.4.1
A99-10X400GE-X-SE	ASR 9900 4T Service Edge Line Card - 5th Generation	Release 7.3.1
A99-10X400GE-X-TR	ASR 9900 4T Packet Transport Line Card - 5th Generation	Release 7.3.1
A9903-20HG-PEC	ASR 9903 2T Multi-rate Port Expansion Card	Release 7.1.3
A99-32X100GE-X-SE	ASR 9000 32-Port 100GE QSFP28/QSFP+ Service Edge optimized Line Card - 5th Generation	Release 7.1.15
A99-32X100GE-X-TR	ASR 9000 32-Port 100GE QSFP28/QSFP+ Packet Transport optimized Line Card - 5th Generation	Release 7.1.15
A9K-20HG-FLEX-SE A9K-20HG-FLEX-TR	ASR 9000 2T Combo Line Card - 5th Generation	Release 7.1.15
A9K-8HG-FLEX-SE A9K-8HG-FLEX-TR	ASR 9000 800G Combo Line Card - 5th Generation	Release 7.1.15
A9K-16X100GE-TR	ASR 9000 16-port 100GE QSFP TR line card	Release 6.5.15
A99-32X100GE-TR	ASR 9900 32-port 100GE QSFP TR line card	Release 6.5.15
A99-48X10GE-1G-SE	ASR 9000 48 port dual rate 10G/1G Service Edge line card	Release 6.5.2
A99-48X10GE-1G-TR	ASR 9000 48 port dual rate 10G/1G Transport Optimised line card	Release 6.5.2
A99-16X100GE-X-SE	ASR 9900 16-port 100GE QSFP SE	Release 6.5.3
A9K-48X10GE-1G-CM	ASR 9000 48-port dual-rate 10G/1G Consumption Model line card	Release 6.4.1
A9K-24X10GE-1G-CM	ASR 9000 24-port dual-rate 10G/1G Consumption Model line card	Release 6.4.1
A9K-48X10GE-1G-SE	ASR9000 48-port dual-rate 10G/1G service edge-optimized line card	Release 6.3.2
A9K-48X10GE-1G-TR	ASR9000 48-port dual-rate 10G/1G packet transport-optimized line card	Release 6.3.2
A9K-24X10GE-1G-SE	ASR9000 24-port dual-rate 10G/1G service edge-optimized line card	Release 6.3.2
A9K-24X10GE-1G-TR	ASR9000 24-port dual-rate 10G/1G packet transport-optimized line card	Release 6.3.2
<b>Cisco ASR 9000 Series Aggregation Services Router - Modular Line Cards</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
A9K-MOD400-CM	Cisco ASR 9000 Modular 400G Consumption Model Line Card	Release 6.2.1

A9K-MOD400-SE	Cisco ASR 9000 Series Aggregation Services Router 400 Gigabyte Modular Line Card, Service Edge Optimized	Release 6.2.1
A9K-MOD400-TR	Cisco ASR 9000 Series Aggregation Services Router 400 Gigabyte Modular Line Card, Packet Transport Optimized	Release 6.2.1
<b>Cisco ASR 9000 Series Aggregation Services Router - Modular Port Adapters (MPAs)</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
A9K-MPA-1X200GE	Cisco ASR 9000 1-port 200-Gigabit Ethernet MPA, requires CFP2-DCO optics	Release 6.6.2
A9K-MPA-32X1GE	Cisco ASR 9000 32-port 1-Gigabit Ethernet MPA with MACSec	Release 6.6.2
A9K-MPA20X10GE-CM	Cisco ASR 9000 20x10GE Consumption Model MPA	Release 6.5.1
A9K-MPA2X100GE-CM	Cisco ASR 9000 2x100GE Consumption Model MPA	Release 6.5.1
A9K-MPA-1X100GE	Cisco ASR 9000 Series Aggregation Services Router 1-port 100-Gigabit Modular Port Adapter	Release 6.3.1
A9K-MPA-2X100GE	Cisco ASR 9000 Series Aggregation Services Router 2-port 100-Gigabit Modular Port Adapter	Release 6.2.2
A9K-MPA-20x10GE	20-Port 10-Gigabit Ethernet Modular Port Adapter with SFP+	Release 6.2.1
A9K-MPA-8X10GE	Cisco ASR 9000 Series Aggregation Services Router 8-port 10GE Modular Port Adapter	Release 6.3.2
A9K-MPA-4X10GE	Cisco ASR 9000 Series Aggregation Services Router 4-port 10GE Modular Port Adapter	Release 6.2.1
A9K-MPA-20X1GE	Cisco ASR 9000 Series Aggregation Services Router 20-port 1GE Modular Port Adapter	Release 6.2.1
A9K-MPA-2X40GE	Cisco ASR 9000 Series Aggregation Services Router 2-port 40GE Modular Port Adapter	Release 6.3.1
<b>Cisco ASR 9000v Satellite Shelf</b>		
<b>Part Number</b>	<b>Description</b>	<b>Support Initially Provided in IOS XR 64 bit Release</b>
A9KV-V2-DC-A=	Cisco ASR 9000v Satellite Shelf Version 2 DC power ANSI chassis	Release 6.2.1
A9KV-V2-DC-E=	Cisco ASR 9000v Satellite Shelf Version 2 DC power chassis	Release 6.2.1
A9KV-V2-AC=	Cisco ASR 9000v Satellite Shelf AC power chassis	Release 6.2.1
A9KV-V2-FAN=	Cisco ASR 9000v Satellite Shelf Version 2 Fan Tray	Release 6.2.1
<b>Cisco NCS 5000 Satellite Shelf</b>		

Part Number	Description	Support Initially Provided in IOS XR 64 bit Release
NCS-5001	Cisco NCS 5001 Series Router	Release 6.2.1
NCS-5002	Cisco NCS 5002 Series Router	Release 6.2.1
NCS-5001-ACSR	Cisco NCS 5001 Router Accessory Kit	Release 6.2.1
NCS-5002-ACSR	Cisco NCS 5002 Router Accessory Kit	Release 6.2.1
NCS-5001-FN-BK	Cisco NCS 5001 Router Fan Back to Front AirFlow	Release 6.2.1
NCS-5002-FN-BK	Cisco NCS 5002 Router Fan Back to Front AirFlow	Release 6.2.1
NCS-5001-FLT-BK	Cisco NCS 5001 Air Filter Back to Front Airflow	Release 6.2.1
NCS-5002-FLT-BK	Cisco NCS 5002 Air Filter Back to Front Airflow	Release 6.2.1
NCS-5001-FN-FR	Cisco NCS 5001 Fan Front to Back Airflow	Release 6.2.1
NCS-5002-FN-FR	Cisco NCS 5002 Fan Front to Back Airflow	Release 6.2.1
NCS-5001-FLT-FR	Cisco NCS 5001 Air Filter Front to Back Airflow	Release 6.2.1
NCS-5002-FLT-FR	Cisco NCS 5002 Air Filter Front to Back Airflow	Release 6.2.1

## Compatibility Matrix for EPNM and Crosswork with Cisco IOS XR Software

The compatibility matrix lists the version of EPNM and Crosswork that are supported with Cisco IOS XR Release in this release.

**Table 5: Compatibility Matrix**

Cisco IOS XR	Crosswork	EPNM
Release 24.4.1	<a href="#">Crosswork Optimization Engine 6.0</a>	<a href="#">Evolved Programmable Network Manager 7.1.1</a>

## Important Notes

- Repetitive Smart Licensing evaluation expired warning messages are displayed on the console every hour, but no functionality impact is observed on the device. To stop these repetitive messages, you should register the device again with a new registration token.
- From IOS XR Release 7.0, 1st and 2nd generation of Ethernet ASR 9000 line cards are not supported.
- Country-specific laws, regulations, and licenses—In certain countries, use of these products may be prohibited and subject to laws, regulations, or licenses, including requirements applicable to the use of the products under telecommunications and other laws and regulations; customers must comply with all such applicable laws in the countries in which they intend to use the products.

- Exceeding Cisco testing—If you intend to test beyond the combined maximum configuration tested and published by Cisco, contact your Cisco Account Team or Technical Support representative to discuss how to engineer a large-scale configuration for your purpose.
- Starting Cisco IOS XR Software Release 24.1.1, ISSU upgrades and ISSU SMU are not supported for ASR 9000 third-generation line cards.
- Installing a Line Card—For a fully populated Line Card with cable optics, maintenance time required for card replacement is higher. For more information about Line Card installation and removal, refer to the *Cisco ASR 9000 Aggregation Services Router Ethernet Line Card Installation Guide*.
- For ZTP, In Cisco IOS XR Release 7.3.1 and earlier, the system accepts the device sending **user-class = "exr-config"**; however starting Cisco IOS XR Release 7.3.2 and later, you must use only **user-class = "xr-config"**.

In Cisco IOS XR Release 7.3.2 and later, use:

```
host cisco-rp0 {
  hardware ethernet e4:c7:22:be:10:ba;
  fixed-address 172.30.12.54;
  if exists user-class and option user-class = "iPXE" {
    filename = "http://172.30.0.22/boot.ipxe";
  } elseif exists user-class and option user-class = "xr-config" {
    filename = "http://172.30.0.22/scripts/cisco-rp0_ztp.sh";
  }
}
```

- The auto FPD upgrade may result in certain intentional exceptions, which may need manual upgrades or reloading for a few FPDs. We recommend you use the **show hw-module fpd** command to check the hardware module status immediately after the FPD auto upgrade is complete and take necessary action in both admin and XR VM mode. That is, if any FPD displays a **NEED UPGD** status, then upgrade those FPDs individually by the manual upgrade and follow it with a reload in admin mode, and if any FPDs show a **RLOAD REQ** status, perform a hardware module reload from admin mode.

## Licensing

Starting with Cisco IOS XR Release 24.1.1, Smart Licensing Using Policy (SLP) is the default Licensing model. When you upgrade to the Cisco IOS XR Release 24.1.1 release or later, the Smart Licensing Using Policy is enabled by default.

You can migrate your devices to Smart Licensing with Policy model, see *Migrating from Smart Licensing to Smart Licensing Using Policy*, [Smart Licensing Using Policy on Cisco IOS XR Routers](#).

We recommend that you update to the latest version of [SSM On-Prem](#) or [Cisco Smart Licensing Utility](#).




---

**Note** SSM On-Prem and CSSM both support SLP devices and SL devices. SLP devices and SL devices can coexist in a network. The Smart Licensing (SL) model is available in releases Cisco IOS XR Release 7.11.1 and earlier.

---

## Supported Transceiver Modules

To determine the transceivers that Cisco hardware device supports, refer to the [Transceiver Module Group \(TMG\) Compatibility Matrix](#) tool.

## Supported Modular Port Adapters

For the compatibility details of Modular Port Adapters (MPAs) on the line cards, see the [datasheet](#) of that specific line card.



## Production Software Maintenance Updates (SMUs)

A production SMU is a SMU that is formally requested, developed, tested, and released. Production SMUs are intended for use in a live network environment and are formally supported by the Cisco TAC and the relevant development teams. Software bugs identified through software recommendations or Bug Search Tools are not a basis for production SMU requests.

For information on production SMU types, refer the [Production SMU Types](#) section of the *IOS XR Software Maintenance Updates (SMUs)* guide.

## Upgrading Cisco IOS XR Software

Cisco IOS XR Software is installed and activated from modular packages, allowing specific features or software patches to be installed, upgraded, or downgraded without affecting unrelated processes. Software packages can be upgraded or downgraded on all supported card types, or on a single card (node).

Software packages are installed from Route Processor Module (RPM) files that contain one or more software components.

The upgrade document is available along with the software images.



---

**Note** If you have mLACP/ICCP Redundancy Model setup, ensure that you upgrade the active and standby nodes to the same IOS XR version while upgrading to a newer version of the ASR 9000 router.

---

## Cisco IOS XR Error messages

To view, search, compare, and download Cisco IOS XR Error Messages, refer to the [Cisco IOS XR Error messages](#) tool.

## Cisco IOS XR MIBs

To determine the MIBs supported by platform and release, refer to the [Cisco IOS XR MIBs](#) tool.

## Related Documentation

The most current Cisco ASR 9000 router documentation is located at the following URL:

<https://www.cisco.com/c/en/us/td/docs/iosxr/asr-9000-series-routers.html>





**Americas Headquarters**  
Cisco Systems, Inc.  
San Jose, CA 95134-1706  
USA

**Asia Pacific Headquarters**  
CiscoSystems(USA)Pte.Ltd.  
Singapore

**Europe Headquarters**  
CiscoSystemsInternationalBV  
Amsterdam,TheNetherlands

Cisco has more than 200 offices worldwide. Addresses, phone numbers, and fax numbers are listed on the Cisco Website at [www.cisco.com/go/offices](http://www.cisco.com/go/offices).