



## **F Commands**

---

This chapter describes the Cisco Nexus Cloud Services Platform commands that begin with the letter F.

*Send document comments to [nexus1k-docfeedback@cisco.com](mailto:nexus1k-docfeedback@cisco.com).*

## feature auxillary

To enable the auxillary feature in the Cisco Nexus Cloud Services Platform, use the **feature auxillary** command. To disable the feature, use the **no** form of this command.

**feature auxillary [cdromusb]**

**no feature auxillary [cdromusb]**

---

**Syntax Description** This command has no arguments or keywords.

---

**Defaults** Disabled

---

**Command Modes** Global configuration (config)

---

**SupportedUserRoles** network-admin

---

Command History	Release	Modification
	4.2(1)SP1(5.1)	This command was introduced.

---



---

**Usage Guidelines** The file system gets mounted to bootflash:usb (or v-usb for virtual usb, cdrom for physical cd, v-cdrom for virtual cd) . The copy command can be used to copy the logs to the repository.

---

**Examples** This example shows how to enable access to external USB:

```
switch# configure terminal
switch(config)# feature auxillary usb
switch(config)#
```

---

Related Commands	Command	Description
	<b>mount</b>	Enables access an external USB or CD to copy the logs for troubleshooting.

---

***Send document comments to [nexus1k-docfeedback@cisco.com](mailto:nexus1k-docfeedback@cisco.com).***

## find

To find filenames beginning with a character string, use the **find** command.

```
find filename-prefix
```

<b>Syntax Description</b>	<i>filename-prefix</i>	First part or all of a filename. The filename prefix is case sensitive.
<b>Defaults</b>	None	
<b>Command Modes</b>	Any command mode	
<b>SupportedUserRoles</b>	network-admin	
<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	4.0(4)SP1(1)	This command was introduced.
<b>Usage Guidelines</b>	The <b>find</b> command searches all subdirectories under the current working directory. You can use the <b>cd</b> and <b>pwd</b> commands to navigate to the starting directory.	
<b>Examples</b>	This example shows how to display filenames beginning with ospf:	
	<pre>n1010# <b>find ospf</b> /usr/bin/find: ./lost+found: Permission denied ./ospf-gr.cfg ./ospfgrconfig ./ospf-gr.conf</pre>	
<b>Related Commands</b>	<b>Command</b>	<b>Description</b>
	<b>cd</b>	Changes the current working directory.
	<b>pwd</b>	Displays the name of the current working directory.

***Send document comments to [nexus1k-docfeedback@cisco.com](mailto:nexus1k-docfeedback@cisco.com).***

# format

To format an external Flash device to erase the contents and restore it to its factory-shipped state, use the **format** command.

**format** *filesystem:*

<b>Syntax Description</b>	<i>filesystem:</i>	Name of the file system. The valid values are <b>bootflash</b> , <b>logflash</b> , <b>slot0</b> , <b>usb1</b> , or <b>usb2</b> .
---------------------------	--------------------	--

<b>Defaults</b>	None
-----------------	------

<b>Command Modes</b>	Any command mode
----------------------	------------------

<b>SupportedUserRoles</b>	network-admin
---------------------------	---------------

<b>Command History</b>	<b>Release</b>	<b>Modification</b>
	4.0(4)SP1(1)	This command was introduced.

**Examples** This example shows how to format an external Flash device:

```
n1010# format slot0:
```

<b>Related Commands</b>	<b>Command</b>	<b>Description</b>
	<b>cd</b>	Changes the current working directory.
	<b>dir</b>	Displays the directory contents.
	<b>pwd</b>	Displays the name of the current working directory.