

RV320およびRV325 VPNルータの日時の設定

目的

この記事では、RV32x VPNルータシリーズで手動および自動の時刻と日付の設定を行う方法について説明します。

概要

日付と時刻の設定は、デバイス間のデータ転送を同期するのに便利です。RV32x VPNルータシリーズでは、日付と時刻を手動で設定するか、ネットワークタイムプロトコル(NTP)サーバを使用して日付と時刻を自動的に更新できます。

該当するデバイス


- ・ RV320デュアルWAN VPNルータ
- ・ RV325ギガビットデュアルWAN VPNルータ

[Software Version]

- ・ v1.1.0.09

日時の設定

ステップ1: Web構成ユーティリティにログインし、[Setup] > [Time]を選択します。



「時間」ページが開きます。

Time

Current Time: 04/20/2013 03:20:52
 Modification time: 04/20/2013 02:20:52
 Time Zone: Alaska (GMT-9:00) ▼
 Daylight Saving:
 From: 06 month 25 day
 To: 12 month 25 day
 Set Date and Time: Auto Manual
 NTP Server: time.nist.gov
 Enter Date and Time: 3 hours 20 min 51 sec
 4 month 20 day 2013 year

Save Cancel

このページには、次の情報が表示されます。

- *Current Time* : これは最近の日時を表します。
- *Modification Time* : 最後に変更が行われた日時を表します。

注 : 手動および自動の時間設定では、夏時間とタイムゾーンを設定する必要があります。NTPサーバは夏時間とタイムゾーンを認識していないため、ルータのタイムゾーンの場所で夏時間が行われる場合は、デバイスで夏時間を設定する必要があります。

ステップ2:[Time Zone]ドロップダウンリストから、ルータの場所に基づいてタイムゾーンを選択します。

Time

Current Time: 2016-01-12, 23:21:59
 Modification time: 2016-01-12, 23:21:59
 Time Zone: Pacific Time (US & Canada) (GMT-8:00) ▼
 Adjust for Daylight Savings Time: Eniwetok (GMT-12:00)
 Daylight Saving Mode: Midway Island (GMT-11:00)
 From: Hawaii (GMT-10:00)
 To: Alaska (GMT-9:00)
 From: Pacific Time (US & Canada) (GMT-8:00)
 To: Mountain Time (US & Canada) (GMT-7:00)
 From: Central Time (US & Canada) (GMT-6:00)
 To: Mexico City (GMT-6:00)
 Daylight Saving Offset: Bogota (GMT-5:00)
 Set Date and Time: Lima (GMT-5:00)
 NTP Server: Eastern Time (US & Canada) (GMT-5:00)
 Enter Date and Time: Atlantic Time (Canada) (GMT-4:00)
 Caracas (GMT-4:00)
 La Paz (GMT-4:00)
 Buenos Aires (GMT-3:00)
 Mid-Atlantic (GMT-2:00)
 Azores (GMT-1:00)
 Greenwich Mean Time: London (GMT+00:00)
 Amsterdam (GMT+01:00)
 Berlin (GMT+01:00)

Save Cancel

ステップ3: (オプション) 選択したタイムゾーンに夏時間がある場合は、[夏時間]チェック

ボックスをオンにします。このチェックボックスをオンにした場合は、ステップ4に進み、それ以外の場合はステップ [10に進みます](#)。

Time

Current Time: 2016-01-12, 23:21:59

Modification time: 2016-01-12, 23:21:59

Time Zone: Pacific Time (US & Canada) (GMT-8:00) ▾

Adjust for Daylight Savings Time:

Daylight Saving Mode: By date Recurring

ステップ4：夏時間モードを選択します。次のオプションがあります。

- *日付*：これを選択した場合は、ステップ5に[進みます](#)。
- *Recurring*：これを選択した場合は、ステップ7に[進みます](#)。

Time

Current Time: 2016-01-12, 23:21:59

Modification time: 2016-01-12, 23:21:59

Time Zone: Pacific Time (US & Canada) (GMT-8:00) ▾

Adjust for Daylight Savings Time:

Daylight Saving Mode: By date Recurring

From: Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾

To: Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾

From: Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾

To: Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾

Daylight Saving Offset: +60 ▾ Minutes

ステップ5:[From]フィールドに、夏時間を開始する月、日、時刻を入力します。

Time

Current Time:	2016-01-12, 23:21:59
Modification time:	2016-01-12, 23:21:59
Time Zone:	Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:	<input checked="" type="checkbox"/>
Daylight Saving Mode:	<input checked="" type="radio"/> By date <input type="radio"/> Recurring
From:	Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To:	Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From:	Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To:	Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾

ステップ6:[To]フィールドに、夏時間が終了する月、日、時刻を入力します。

Time

Current Time:	2016-01-12, 23:21:59
Modification time:	2016-01-12, 23:21:59
Time Zone:	Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:	<input checked="" type="checkbox"/>
Daylight Saving Mode:	<input checked="" type="radio"/> By date <input type="radio"/> Recurring
From:	Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To:	Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From:	Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To:	Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾

ステップ7:[開始]フィールドで、夏時間を開始する月、週、日、時刻を入力します。

Time

Current Time: 2016-01-12, 23:21:59
Modification time: 2016-01-12, 23:21:59
Time Zone: Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:
Daylight Saving Mode: By date Recurring
From: Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To: Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From: Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To: Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾
Daylight Saving Offset: +60 ▾ Minutes

ステップ8:[To]フィールドで、夏時間が終了する[Month]、[Week]、[Day]、[Time]を入力します。

Time

Current Time: 2016-01-12, 23:21:59
Modification time: 2016-01-12, 23:21:59
Time Zone: Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:
Daylight Saving Mode: By date Recurring
From: Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To: Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From: Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To: Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾
Daylight Saving Offset: +60 ▾ Minutes

ステップ9：ら、適切な

Time

Current Time: 2016-01-12, 23:21:59
Modification time: 2016-01-12, 23:21:59
Time Zone: Pacific Time (US & Canada) (GMT-8:00)
Adjust for Daylight Savings Time:
Daylight Saving Mode: By date Recurring
From: Month: 06 Day: 25 Time: 12 00
To: Month: 12 Day: 25 Time: 12 00
From: Month: 06 Week: 2nd Day: Tue
To: Month: 12 Week: 3rd Day: Wed
Daylight Saving Offset: +60 Minutes
Set Date and Time: Manual
NTP Server:
Enter Date and Time: hours 21 min 59 sec
month 12 day 2016 year

Save Cancel

ステップ10：目的のオプションボタンをクリックして、日時を設定する方法を選択します。

- [自動(Auto)]:NTPサーバの日付と時刻に従って日付と時刻を自動的に設定します。
- [Manual]：デバイスの日付と時刻を手動で設定するために使用します。

Time

Current Time: 2016-01-12, 23:21:59
Modification time: 2016-01-12, 23:21:59
Time Zone: Pacific Time (US & Canada) (GMT-8:00)
Adjust for Daylight Savings Time:
Daylight Saving Mode: By date Recurring
From: Month: 06 Day: 25 Time: 12 00
To: Month: 12 Day: 25 Time: 12 00
From: Month: 06 Week: 2nd Day: Tue Time: 12 : 00
To: Month: 12 Week: 3rd Day: Wed Time: 12 : 00
Daylight Saving Offset: +60 Minutes
Set Date and Time: Auto Manual
NTP Server:
Enter Date and Time: 23 hours 21 min 59 sec
1 month 12 day 2016 year

ステップ11：前のステップで[Auto]を選択した場合は、完全修飾NTPサーバ名またはIPアドレスを入力します。

Time

Current Time:	2016-01-12, 23:21:59
Modification time:	2016-01-12, 23:21:59
Time Zone:	Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:	<input type="checkbox"/>
Daylight Saving Mode:	<input checked="" type="radio"/> By date <input type="radio"/> Recurring
From:	Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To:	Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From:	Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To:	Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾
Daylight Saving Offset:	+60 ▾ Minutes
Set Date and Time:	<input checked="" type="radio"/> Auto <input type="radio"/> Manual
NTP Server:	time.nist.gov
Enter Date and Time:	23 hours 21 min 59 sec
	1 month 12 day 2016 year

ステップ12 : ステップ10で「手動」を選択した場合は、「日付と時刻の入力」フィールドに、時間、最小、秒の各フィールドに目的の値を入力して時刻を設定します。月、日、年の各フィールドでも同じことを行います。

Time

Current Time:	2016-01-12, 23:21:59
Modification time:	2016-01-12, 23:21:59
Time Zone:	Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:	<input type="checkbox"/>
Daylight Saving Mode:	<input checked="" type="radio"/> By date <input type="radio"/> Recurring
From:	Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To:	Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From:	Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To:	Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾
Daylight Saving Offset:	+60 ▾ Minutes
Set Date and Time:	<input checked="" type="radio"/> Auto <input type="radio"/> Manual
NTP Server:	time.nist.gov
Enter Date and Time:	23 hours 21 min 59 sec
	1 month 12 day 2016 year

ステップ13:[Save]をクリックして、設定を保存します。

Time

Current Time: 2016-01-12, 23:21:59
Modification time: 2016-01-12, 23:21:59
Time Zone: Pacific Time (US & Canada) (GMT-8:00) ▾
Adjust for Daylight Savings Time:
Daylight Saving Mode: By date Recurring
From: Month: 06 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
To: Month: 12 ▾ Day: 25 ▾ Time: 12 ▾ 00 ▾
From: Month: 06 ▾ Week: 2nd ▾ Day: Tue ▾ Time: 12 ▾ : 00 ▾
To: Month: 12 ▾ Week: 3rd ▾ Day: Wed ▾ Time: 12 ▾ : 00 ▾
Daylight Saving Offset: +60 ▾ Minutes
Set Date and Time: Auto Manual
NTP Server: time.nist.gov
Enter Date and Time: 23 hours 21 min 59 sec
1 month 12 day 2016 year

Save **Cancel**

結論

これで、RV32x VPNルータシリーズの手動および自動の時刻と日付の設定の手順が正しく学習されました。

RV320およびRV325ルータの詳細については、次のビデオをご覧ください。

[RV320およびRV325ルータのクイックセットアップ](#)

[RV320およびRV325ルータ基本設定チュートリアル](#)