



# Configuring NetFlow Aggregation Caches

---

**Last Updated: December 8, 2011**

This module contains information about and instructions for configuring NetFlow aggregation caches. The NetFlow main cache is the default cache used to store the data captured by NetFlow. By maintaining one or more extra caches, called aggregation caches, the NetFlow Aggregation feature allows limited aggregation of NetFlow data export streams on a router. The aggregation scheme that you select determines the specific kinds of data that are exported to a remote host.

NetFlow is a Cisco IOS XE application that provides statistics on packets flowing through the router. It is emerging as a primary network accounting and security technology.

- [Finding Feature Information, page 1](#)
- [Prerequisites for Configuring NetFlow Aggregation Caches, page 1](#)
- [Restrictions for Configuring NetFlow Aggregation Caches, page 2](#)
- [Information About Configuring NetFlow Aggregation Caches, page 2](#)
- [How to Configure NetFlow Aggregation Caches, page 24](#)
- [Configuration Examples for Configuring NetFlow Aggregation Caches, page 30](#)
- [Additional References, page 35](#)
- [Feature Information for Configuring NetFlow Aggregation Caches, page 36](#)
- [Glossary, page 37](#)

## Finding Feature Information

Your software release may not support all the features documented in this module. For the latest feature information and caveats, see the release notes for your platform and software release. To find information about the features documented in this module, and to see a list of the releases in which each feature is supported, see the Feature Information Table at the end of this document.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.

## Prerequisites for Configuring NetFlow Aggregation Caches

Before you enable NetFlow you must:



---

**Americas Headquarters:**  
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

- Configure the router for IP routing
- Ensure that either Cisco Express Forwarding or fast switching is enabled on your router and on the interfaces on which you want to configure NetFlow.
- Understand the resources required on your router because NetFlow consumes additional memory and CPU resources

If you intend to use Version 8 export format with an aggregation cache, configure Version 5 export format for the main cache.

If you need autonomous system (AS) information from the aggregation, make sure to specify either the **peer-asor origin-as** keyword in your export command if you have not configured an export format version.

You must explicitly enable each NetFlow aggregation cache by entering the **enabled** keyword from aggregation cache configuration mode.

Router-based aggregation must be enabled for minimum masking.

## Restrictions for Configuring NetFlow Aggregation Caches

### Performance Impact

Configuring Egress NetFlow accounting with the **ip flow egress** command might adversely affect network performance because of the additional accounting-related computation that occurs in the traffic-forwarding path of the router.

- [NetFlow Data Export Restrictions, page 2](#)

## NetFlow Data Export Restrictions

### Restrictions for NetFlow Version 9 Data Export

- Backward compatibility--Version 9 is not backward-compatible with Version 5 or Version 8. If you need Version 5 or Version 8, you must configure it.
- Export bandwidth--Export bandwidth use increases for Version 9 (because of template flowsets) versus Version 5. The increase in bandwidth usage versus Version 5 varies with the frequency with which template flowsets are sent. The default is to resend templates every 20 packets, which has a bandwidth cost of about 4 percent. If necessary, you can lower the resend rate with the **ip flow-export template refresh-rate packets** command.
- Performance impact--Version 9 slightly decreases overall performance, because generating and maintaining valid template flowsets require additional processing.

### Restrictions for NetFlow Version 8 Export Format

Version 8 export format is available only for aggregation caches, and it cannot be expanded to support new features.

## Information About Configuring NetFlow Aggregation Caches

- [NetFlow Aggregation Caches, page 3](#)

- [NetFlow Data Export Format Versions 9 and 8 for NetFlow Aggregation Caches Overview](#), page 24

## NetFlow Aggregation Caches

- [NetFlow Aggregation Cache Benefits](#), page 3
- [NetFlow Aggregation Cache Schemes](#), page 3
- [NetFlow Aggregation Scheme Fields](#), page 4
- [NetFlow AS Aggregation Scheme](#), page 6
- [NetFlow AS-ToS Aggregation Scheme](#), page 7
- [NetFlow Destination Prefix Aggregation Scheme](#), page 9
- [NetFlow Destination Prefix-ToS Aggregation Scheme](#), page 11
- [NetFlow Prefix Aggregation Scheme](#), page 12
- [NetFlow Prefix-Port Aggregation Scheme](#), page 14
- [NetFlow Prefix-ToS Aggregation Scheme](#), page 16
- [NetFlow Protocol Port Aggregation Scheme](#), page 18
- [NetFlow Protocol-Port-ToS Aggregation Scheme](#), page 19
- [NetFlow Source Prefix Aggregation Scheme](#), page 21
- [NetFlow Source Prefix-ToS Aggregation Scheme](#), page 22

## NetFlow Aggregation Cache Benefits

Aggregation of export data is typically performed by NetFlow collection tools on management workstations. Router-based aggregation allows limited aggregation of NetFlow export records to occur on the router. Thus, you can summarize NetFlow export data on the router before the data is exported to a NetFlow data collection system, which has the following benefits:

- Reduces the bandwidth required between the router and the workstations
- Reduces the number of collection workstations required
- Improves performance and scalability on high flow-per-second routers

## NetFlow Aggregation Cache Schemes

Cisco IOS XE NetFlow aggregation maintains one or more extra caches with different combinations of fields that determine which flows are grouped together. These extra caches are called aggregation caches. The combinations of fields that make up an aggregation cache are referred to as schemes.

You can configure each aggregation cache with its individual cache size, cache age timeout parameter, export destination IP address, and export destination UDP port. The normal flow age process runs on each active aggregation cache the same way it runs on the main cache. On-demand aging is also supported. Each aggregation cache contains different field combinations that determine which data flows are grouped. The default aggregation cache size is 4096 bytes.

You configure a cache aggregation scheme through the use of arguments to the **ip flow-aggregation cache** command. NetFlow supports the following five non-ToS based cache aggregation schemes:

- Autonomous system (AS) aggregation scheme
- Destination prefix aggregation scheme
- Prefix aggregation scheme

- Protocol port aggregation scheme
- Source prefix aggregation scheme

The NetFlow Type of Service-Based Router Aggregation feature introduced support for additional cache aggregation schemes, all of which include the Type of Service (ToS) byte as one of the fields in the aggregation cache. The following are the six ToS-based aggregation schemes:

- AS-ToS aggregation scheme
- Destination prefix-ToS aggregation scheme
- Prefix-port aggregation scheme
- Prefix-ToS aggregation scheme
- Protocol-port-ToS aggregation scheme
- Source prefix-ToS aggregation scheme

**Note**

[NetFlow Aggregation Scheme Fields, page 4](#) through [NetFlow Aggregation Cache Schemes, page 3](#) illustrate the Version 8 export formats of the aggregation schemes listed above. Additional export formats (for instance, Version 9) are also supported. If you are using Version 9, the formats will be different from those shown in the figures. For more information about Version 9 export formats, see the "Configuring NetFlow and NetFlow Data Export" module.

## NetFlow Aggregation Scheme Fields

Each cache aggregation scheme contains field combinations that differ from any other cache aggregation scheme. The combination of fields determines which data flows are grouped and collected when a flow expires from the main cache. A flow is a set of packets that has common fields, such as the source IP address, destination IP address, protocol, source and destination ports, type-of-service, and the same interface on which the flow is monitored. To manage flow aggregation on your router, you need to configure the aggregation cache scheme that groups and collects the fields from which you want to examine data. The two tables below show the NetFlow fields that are grouped and collected for non-ToS and ToS based cache aggregation schemes.

The table below shows the NetFlow fields used in the non-ToS based aggregation schemes.

**Table 1** *NetFlow Fields Used in the Non-ToS Based Aggregations Schemes*

Field	AS	Protocol Port	Source Prefix	Destination Prefix	Prefix
Source prefix			X		X
Source prefix mask			X		X
Destination prefix				X	X
Destination prefix mask				X	X
Source app port		X			

Field	AS	Protocol Port	Source Prefix	Destination Prefix	Prefix
Destination app port		X			
Input interface	X		X		X
Output interface	X			X	X
IP protocol		X			
Source AS	X		X		X
Destination AS	X			X	X
First time stamp	X	X	X	X	X
Last time stamp	X	X	X	X	X
Number of flows <sup>1</sup>	X	X	X	X	X
Number of packets	X	X	X	X	X
Number of bytes	X	X	X	X	X

The table below shows the NetFlow fields used in the ToS based aggregation schemes.

**Table 2** *NetFlow Fields Used in the ToS Based Aggregation Schemes*

Field	AS-ToS	Protocol Port-ToS	Source Prefix-ToS	Destination Prefix-ToS	Prefix-ToS	Prefix-Port
Source prefix			X		X	X
Source prefix mask			X		X	X
Destination prefix				X	X	X
Destination prefix mask				X	X	X
Source app port		X				X

<sup>1</sup> For the Cisco ASR 1000 series router, this value is always 0. This is because on the Cisco ASR 1000 series router, aggregation caches are managed not by extracting data from main cache flow records as they are aged out, but rather by examining each packet, independently of any main cache processing.

Field	AS-ToS	Protocol Port-ToS	Source Prefix-ToS	Destination Prefix-ToS	Prefix-ToS	Prefix-Port
Destination app port		X				X
Input interface	X	X	X		X	X
Output interface	X	X		X	X	X
IP protocol		X				X
Source AS	X		X		X	
Destination AS	X			X	X	
ToS	X	X	X	X	X	X
First time stamp	X	X	X	X	X	X
Last time stamp	X	X	X	X	X	X
Number of flows <sup>2</sup>	X	X	X	X	X	X
Number of packets	X	X	X	X	X	X
Number of bytes	X	X	X	X	X	X

## NetFlow AS Aggregation Scheme

The NetFlow AS aggregation scheme reduces NetFlow export data volume substantially and generates AS-to-AS traffic flow data. The scheme groups data flows that have the same source BGP AS, destination BGP AS, input interface, and output interface.

The aggregated NetFlow data export records report the following:

- Source and destination BGP AS
- Number of packets summarized by the aggregated record
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Source interface
- Destination interface
- Time stamp when the first packet was switched and time stamp when the last packet was switched

<sup>2</sup> For the Cisco ASR 1000 series router, this value is always 0. This is because on the Cisco ASR 1000 series router, aggregation caches are managed not by extracting data from main cache flow records as they are aged out, but rather by examining each packet, independently of any main cache processing.

The figure below shows the data export format for the AS aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 1 Data Export Format for AS Aggregation Scheme**

0	Flows	
4	Packets	
8	Bytes	
12	First time stamp	
16	Last time stamp	
20	Source AS	Destination AS
24	Source interface	Destination interface

The table below lists definitions for the data export record fields used in the AS aggregation scheme.

**Table 3 Data Export Record Field Definitions for AS Aggregation Scheme**

Field	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Source AS	Autonomous system of the source IP address (peer or origin)
Destination AS	Autonomous system of the destination IP address (peer or origin)
Source interface	SNMP index of the input interface
Destination interface	SNMP index of the output interface

## NetFlow AS-ToS Aggregation Scheme

The NetFlow AS-ToS aggregation scheme groups flows that have the same source BGP AS, destination BGP AS, source and destination interfaces, and ToS byte. The aggregated NetFlow export record based on the AS-ToS aggregation scheme reports the following:

- Source BGP AS
- Destination BGP AS
- ToS byte
- Number of flows summarized by the aggregated record
- Number of bytes summarized by this aggregated record
- Number of packets summarized by this aggregation record
- Source and destination interface
- Time stamp when the first packet was switched and time stamp when the last packet was switched

This aggregation scheme is particularly useful for generating AS-to-AS traffic flow data, and for reducing NetFlow export data volume substantially. The figure below shows the data export format for the AS-ToS aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 2** Data Export Format for AS-ToS Aggregation Scheme

0	Flows		
4	Packets		
8	Bytes		
12	First time stamp		
16	Last time stamp		
20	Source AS	Destination AS	
24	Source interface	Destination interface	
28	ToS	PAD	Reserved

The table below lists definitions for the data export record terms used in the AS-ToS aggregation scheme.

**Table 4** Data Export Record Term Definitions for AS-ToS Aggregation Scheme

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched



Term	Definition
Source AS	Autonomous system of the source IP address (peer or origin)
Destination AS	Autonomous system of the destination IP address (peer or origin)
Source interface	SNMP index of the input interface
Destination interface	SNMP index of the output interface
ToS	Type of service byte
PAD	Zero field
Reserved	Zero field

## NetFlow Destination Prefix Aggregation Scheme

The destination prefix aggregation scheme generates data so that you can examine the destinations of network traffic passing through a NetFlow-enabled device. The scheme groups data flows that have the same destination prefix, destination prefix mask, destination BGP AS, and output interface.

The aggregated NetFlow data export records report the following:

- Destination prefix
- Destination prefix mask
- Destination BGP AS
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregated record
- Output interface
- Time stamp when the first packet was switched and time stamp when the last packet was switched

The figure below shows the data export format for the destination prefix aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 3** Destination Prefix Aggregation Data Export Record Format

0	Flows	
4	Packets	
8	Bytes	
12	First time stamp	
16	Last time stamp	
20	Destination prefix	
24	Destination mask bits	Destination AS
28	Destination interface	Reserved

The table below lists definitions for the data export record terms used in the destination prefix aggregation scheme.

**Table 5** Data Export Record Term Definitions for Destination Prefix Aggregation Scheme

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Destination prefix	Destination IP address ANDed with the destination prefix mask
Destination mask bits	Number of bits in the destination prefix
PAD	Zero field
Destination AS	Autonomous system of the destination IP address (peer or origin)
Destination interface	SNMP index of the output interface

Term	Definition
Reserved	Zero field

## NetFlow Destination Prefix-ToS Aggregation Scheme

The NetFlow destination prefix-ToS aggregation scheme groups flows that have the same destination prefix, destination prefix mask, destination BGP AS, ToS byte, and output interface. The aggregated NetFlow export record reports the following:

- Destination IP address
- Destination prefix mask
- Destination AS
- ToS byte
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregated record
- Output interface
- Time stamp when the first packet was switched and time stamp when the last packet was switched

This aggregation scheme is particularly useful for capturing data with which you can examine the destinations of network traffic passing through a NetFlow-enabled device. The figure below shows the data export format for the Destination prefix-ToS aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 4** Data Export Format for Destination Prefix-ToS Aggregation Scheme

0	Flows		
4	Packets		
8	Bytes		
12	First time stamp		
16	Last time stamp		
20	Destination prefix		
24	Destination mask bits	ToS	Destination AS
28	Destination interface		Reserved

The table below lists definitions for the data export record terms used in the destination prefix-ToS aggregation scheme.

**Table 6** *Data Export Record Term Definitions for Destination Prefix-ToS Aggregation Scheme*

<b>Term</b>	<b>Definition</b>
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Destination prefix	Destination IP address ANDed with the destination prefix mask
Dest mask bits	Number of bits in the destination prefix
ToS	Type of service byte
Destination AS	Autonomous system of the destination IP address (peer or origin)
Destination interface	SNMP index of the output interface
Reserved	Zero field

## NetFlow Prefix Aggregation Scheme

The NetFlow prefix aggregation scheme generates data so that you can examine the sources and destinations of network traffic passing through a NetFlow-enabled device. The scheme groups data flows that have the same source prefix, destination prefix, source prefix mask, destination prefix mask, source BGP AS, destination BGP AS, input interface, and output interface. See the figure below.

The aggregated NetFlow data export records report the following:

- Source and destination prefix
- Source and destination prefix mask
- Source and destination BGP AS
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregated record
- Input and output interfaces
- Time stamp when the first packet is switched and time stamp when the last packet is switched

The figure below shows the data export format for the prefix aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 5 Data Export Format for Prefix Aggregation Scheme**

0	Flows		
4	Packets		
8	Bytes		
12	First time stamp		
16	Last time stamp		
20	Source prefix		
24	Destination prefix		
28	Destination mask bits	Source mask bits	Reserved
32	Source AS		Destination AS
36	Source interface		Destination interface

The table below lists definitions for the data export record terms used in the prefix aggregation scheme.

**Table 7 Data Export Record Terms and Definitions for Prefix Aggregation Scheme**

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Source prefix	Source IP address ANDed with the source prefix mask, or the prefix to which the source IP address of the aggregated flows belongs
Destination prefix	Destination IP address ANDed with the destination prefix mask

Term	Definition
Destination mask bits	Number of bits in the destination prefix
Source mask bits	Number of bits in the source prefix
Reserved	Zero field
Source AS	Autonomous system of the source IP address (peer or origin)
Destination AS	Autonomous system of the destination IP address (peer or origin)
Source interface	SNMP index of the input interface
Destination interface	SNMP index of the output interface

## NetFlow Prefix-Port Aggregation Scheme

The NetFlow prefix-port aggregation scheme groups flows that have a common source prefix, source mask, destination prefix, destination mask, source port and destination port when applicable, input interface, output interface, protocol, and ToS byte. The aggregated NetFlow export record reports the following:

- Source prefix
- Source prefix mask
- Destination prefix
- Destination prefix mask
- Source port
- Destination port
- Source interface
- Destination interface
- Protocol
- ToS byte
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregation record
- Time stamp when the first packet was switched and time stamp when the last packet was switched

This aggregation scheme is particularly useful for capturing data with which you can examine the sources and destinations of network traffic passing through a NetFlow-enabled device. The figure below shows the

data export record for the prefix-port aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 6** Data Export Record for Prefix-Port Aggregation Scheme

0	Flows			
4	Packets			
8	Bytes			
12	First time stamp			
16	Last time stamp			
20	Source prefix			
24	Destination prefix			
28	Destination mask bits	Source mask bits	ToS	Protocol
32	Source port		Destination port	
36	Source interface		Destination interface	

The table below lists definitions for the data export record terms used in the prefix-port aggregation scheme.

**Table 8** Data Export Record Term Definitions for Prefix-Port Aggregation Scheme

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Source prefix	Source IP address ANDed with the source prefix mask, or the prefix to which the source IP address of the aggregated flows belongs
Destination prefix	Destination IP address ANDed with the destination prefix mask

Term	Definition
Destination mask bits	Number of bits in the destination prefix
Source mask bits	Number of bits in the source prefix
ToS	Type of service byte
Protocol	IP protocol byte
Source port	Source UDP or TCP port number if applicable
Destination port	Destination User Datagram Protocol (UDP) or TCP port number
Source interface	SNMP index of the input interface
Destination interface	SNMP index of the output interface

## NetFlow Prefix-ToS Aggregation Scheme

The NetFlow prefix-tos aggregation scheme groups together flows that have a common source prefix, source mask, destination prefix, destination mask, source BGP AS, destination BGP AS, input interface, output interface, and ToS byte. The aggregated NetFlow export record reports the following:

- Source prefix
- Source prefix mask
- Destination prefix
- Destination prefix mask
- Source AS
- Destination AS
- Source interface
- Destination interface
- ToS byte
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregated record
- Time stamp when the first packet was switched and time stamp when the last packet was switched

This aggregation scheme is particularly useful for capturing data so that you can examine the sources and destinations of network traffic passing through a NetFlow-enabled device. The figure below displays the



data export format for the prefix-tos aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 7 Data Export Format for Prefix-ToS Aggregation Scheme**

0	Flows			
4	Packets			
8	Bytes			
12	First time stamp			
16	Last time stamp			
20	Source prefix			
24	Destination prefix			
28	Destination mask bits	Source mask bits	ToS	PAD
32	Source AS		Destination AS	
36	Source interface		Destination interface	

The table below lists definitions for the data export record terms used in the prefix-ToS aggregation scheme.

**Table 9 Data Export Record Term Definitions for Prefix-ToS Aggregation Scheme**

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Source prefix	Source IP address ANDed with the source prefix mask, or the prefix to which the source IP address of the aggregated flows belongs
Destination prefix	Destination IP address ANDed with the destination prefix mask

Term	Definition
Destination mask bits	Number of bits in the destination prefix
Source mask bits	Number of bits in the source prefix
ToS	Type of service byte
Pad	Zero field
Source AS	Autonomous system of the source IP address (peer or origin)
Destination AS	Autonomous system of the destination IP address (peer or origin)
Source interface	SNMP index of the input interface
Destination interface	SNMP index of the output interface

## NetFlow Protocol Port Aggregation Scheme

The NetFlow protocol port aggregation scheme captures data so that you can examine network usage by traffic type. The scheme groups data flows with the same IP protocol, source port number, and (when applicable) destination port number.

The aggregated NetFlow data export records report the following:

- Source and destination port numbers
- IP protocol (where 6 = TCP, 17 = UDP, and so on)
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregated record
- Time stamp when the first packet was switched and time stamp when the last packet was switched

The figure below shows the data export format for the protocol port aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 8** Data Export Format for Protocol Port Aggregation Scheme

0	Flows	
4	Packets	
8	Bytes	
12	First time stamp	
16	Last time stamp	
20	Protocol	Reserved
24	Source port	Destination port

The table below lists definitions for the data export record terms used in the protocol port aggregation scheme.

**Table 10**      *Data Export Record Term Definitions for Protocol Port Aggregation Scheme*

<b>Term</b>	<b>Definition</b>
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Protocol	IP protocol byte
PAD	Zero field
Reserved	Zero field
Source port	Source UDP or TCP port number if applicable
Destination port	Destination User Datagram Protocol (UDP) or TCP port number

## NetFlow Protocol-Port-ToS Aggregation Scheme

The NetFlow protocol-port-tos aggregation scheme groups flows that have a common IP protocol, ToS byte, source and (when applicable) destination port numbers, and source and destination interfaces. The aggregated NetFlow Export record reports the following:

- Source application port number
- Destination port number
- Source and destination interface
- IP protocol
- ToS byte
- Number of flows summarized by the aggregated record
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregation record
- Time stamp when the first packet was switched and time stamp when the last packet was switched

This aggregation scheme is particularly useful for capturing data so that you can examine network usage by type of traffic. The figure below shows the data export format for the protocol-port-to-s aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 9** Data Export Format for Protocol-Port-ToS Aggregation Scheme

0	Flows		
4	Packets		
8	Bytes		
12	First time stamp		
16	Last time stamp		
20	Protocol	ToS	Reserved
24	Source port		Destination port
28	Source interface		Destination interface

The table below lists definitions for the data export record terms used in the protocol-port-ToS aggregation scheme.

**Table 11** Data Export Record Term Definitions for Protocol-Port-ToS Aggregation Scheme

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Protocol	IP protocol byte
ToS	Type of service byte
Reserved	Zero field
Source port	Source UDP or TCP port number if applicable
Destination port	Destination User Datagram Protocol (UDP) or TCP port number

Term	Definition
Source interface	SNMP index of the input interface
Destination interface	SNMP index of the output interface

## NetFlow Source Prefix Aggregation Scheme

The NetFlow source prefix aggregation scheme captures data so that you can examine the sources of network traffic passing through a NetFlow-enabled device. The scheme groups data flows that have the same source prefix, source prefix mask, source BGP AS, and input interface.

The aggregated NetFlow data export records report the following:

- Source prefix
- Source prefix mask
- Source BGP AS
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregated record
- Input interface
- Time stamp when the first packet was switched and time stamp when the last packet was switched

The figure below shows the data export format for the source prefix aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.

**Figure 10** Data Export Format for Source Prefix Aggregation Scheme

0	Flows		
4	Packets		
8	Bytes		
12	First time stamp		
16	Last time stamp		
20	Source prefix		
24	Source mask bits	PAD	Source AS
28	Source interface		Reserved

The table below lists definitions for the data export record terms used in the source prefix aggregation scheme.

**Table 12**      **Data Export Record Term Definitions for Source Prefix Aggregation Scheme**

<b>Term</b>	<b>Definition</b>
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Source prefix	Source IP address ANDed with the source prefix mask, or the prefix to which the source IP address of the aggregated flows belongs
Source mask bits	Number of bits in the source prefix
PAD	Zero field
Source AS	Autonomous system of the source IP address (peer or origin)
Source interface	SNMP index of the input interface
Reserved	Zero field

## NetFlow Source Prefix-ToS Aggregation Scheme

The NetFlow source prefix-ToS aggregation scheme groups flows that have a common source prefix, source prefix mask, source BGP AS, ToS byte, and input interface. The aggregated NetFlow export record reports the following:

- Source prefix
- Source prefix mask
- Source AS
- ToS byte
- Number of bytes summarized by the aggregated record
- Number of packets summarized by the aggregation record
- Input interface
- Time stamp when the first packet was switched and time stamp when the last packet was switched

This aggregation scheme is particularly useful for capturing data so that you can examine the sources of network traffic passing through a NetFlow-enabled device. The figure below shows the data export format for the source prefix-ToS aggregation scheme. For a definition of the data export terms used in the aggregation scheme, see the table below.



**Note**

When a router does not have a prefix for the source IP address in the flow, NetFlow uses 0.0.0.0 with 0 mask bits rather than making /32 entries. This prevents DOS attacks that use random source addresses from thrashing the aggregation caches. This is also done for the destination in the destination prefix-ToS, the prefix-ToS, and prefix-port aggregation schemes.

**Figure 11** Data Export Format for Source Prefix-ToS Aggregation Scheme

0	Flows		
4	Packets		
8	Bytes		
12	First time stamp		
16	Last time stamp		
20	Source prefix		
24	Source mask bits	ToS	Source AS
28	Source interface		Reserved

The table below lists definitions for the data export record terms used in the source prefix-ToS aggregation scheme.

**Table 13** Data Export Record Term Definitions for Source Prefix-ToS Aggregation Scheme

Term	Definition
Flows	Number of main cache flows that were aggregated
Packets	Number of packets in the aggregated flows
Bytes	Number of bytes in the aggregated flows
First time stamp	System uptime when the first packet was switched
Last time stamp	System uptime when the last packet was switched
Source prefix	Source IP address ANDed with the source prefix mask, or the prefix to which the source IP address of the aggregated flows belongs
Source mask bits	Number of bits in the source prefix

Term	Definition
ToS	Type of service byte
Source AS	Autonomous system of the source IP address (peer or origin)
Source interface	SNMP index of the input interface
Reserved	Zero field

## NetFlow Data Export Format Versions 9 and 8 for NetFlow Aggregation Caches Overview

Export formats available for NetFlow aggregation caches are the Version 9 export format and the Version 8 export format.

- Version 9--A flexible and extensible format, which provides the versatility needed for support of new fields and record types. Version 9 export format enables you to use the same version for main and aggregation caches, and the format is extendable, so you can use the same export format with future features.
- Version 8--A format added to support data export from aggregation caches. Export datagrams contain a subset of the usual Version 5 export data, which is valid for the particular aggregation cache scheme. Version 8 is the default export version for aggregation caches when data export is configured.

The Version 9 export format is flexible and extensible, which provides the versatility needed for the support of new fields and record types. You can use the Version 9 export format for both main and aggregation caches.

The Version 8 export format was added to support data export from aggregation caches. This format allows export datagrams to contain a subset of the Version 5 export data that is valid for the cache aggregation scheme.

See the "NetFlow Data Export" section of the "Configuring NetFlow Aggregation Caches" module for more details on NetFlow Data Export Formats.

## How to Configure NetFlow Aggregation Caches

- [Configuring NetFlow Aggregation Caches, page 24](#)
- [Verifying the Aggregation Cache Configuration, page 28](#)

### Configuring NetFlow Aggregation Caches

Perform this task to enable NetFlow and configure a NetFlow aggregation cache.



**SUMMARY STEPS**

1. enable
2. configure terminal
3. ip flow-aggregation cache { as | as-tos | destination-prefix | destination-prefix-tos | prefix | prefix-port | prefix-tos | protocol-port | protocol-port-tos | source-prefix | source-prefix-tos }
4. cache entries *number*
5. cache timeout active *minutes*
6. cache timeout inactive *seconds*
7. export destination {{ *ip-address* | *hostname* } *udp-port* }
8. Repeat Step 7 to configure a second export destination.
9. export version [9 | 8]
10. enabled
11. exit
12. interface *interface-type interface-number*
13. ip flow { ingress | egress }
14. exit
15. Repeat Steps 12 through 14 to enable NetFlow on other interfaces
16. end

**DETAILED STEPS**

	Command or Action	Purpose
Step 1	<p><b>enable</b></p> <p><b>Example:</b></p> <pre>Router&gt; enable</pre>	<p>(Required) Enables privileged EXEC mode.</p> <ul style="list-style-type: none"> <li>• Enter your password if prompted.</li> </ul>
Step 2	<p><b>configure terminal</b></p> <p><b>Example:</b></p> <pre>Router# configure terminal</pre>	<p>(Required) Enters global configuration mode.</p>

Command or Action	Purpose
<p><b>Step 3</b> <b>ip flow-aggregation cache</b> {<b>as</b>   <b>as-tos</b>   <b>destination-prefix</b>   <b>destination-prefix-tos</b>   <b>prefix</b>   <b>prefix-port</b>   <b>prefix-tos</b>   <b>protocol-port</b>   <b>protocol-port-tos</b>   <b>source-prefix</b>   <b>source-prefix-tos</b>}</p> <p><b>Example:</b></p> <p><b>Example:</b></p> <pre>Router(config)# ip flow-aggregation cache destination-prefix</pre>	<p>(Required) Specifies the aggregation cache scheme and enables aggregation cache configuration mode.</p> <ul style="list-style-type: none"> <li>• The <b>as</b> keyword configures the AS aggregation cache.</li> <li>• The <b>as-tos</b> keyword configures the AS ToS aggregation cache.</li> <li>• The <b>destination-prefix</b> keyword configures the destination prefix aggregation cache.</li> <li>• The <b>destination-prefix-tos</b> keyword configures the destination prefix ToS aggregation cache.</li> <li>• The <b>prefix</b> keyword configures the prefix aggregation cache.</li> <li>• The <b>prefix-port</b> keyword configures the prefix port aggregation cache.</li> <li>• The <b>prefix-tos</b> keyword configures the prefix ToS aggregation cache.</li> <li>• The <b>protocol-port</b> keyword configures the protocol port aggregation cache.</li> <li>• The <b>protocol-port-tos</b> keyword configures the protocol port ToS aggregation cache.</li> <li>• The <b>source-prefix</b> keyword configures the source prefix aggregation cache.</li> <li>• The <b>source-prefix-tos</b> keyword configures the source prefix ToS aggregation cache.</li> </ul>
<p><b>Step 4</b> <b>cache entries</b> <i>number</i></p> <p><b>Example:</b></p> <pre>Router(config-flow-cache)# cache entries 2048</pre>	<p>(Optional) Configures aggregation cache operational parameters.</p> <ul style="list-style-type: none"> <li>• The <b>entries</b> <i>number</i> keyword-argument pair is the number of cached entries allowed in the aggregation cache. The range is from 1024 to 2000000. The default is 4096.</li> </ul>
<p><b>Step 5</b> <b>cache timeout active</b> <i>minutes</i></p> <p><b>Example:</b></p> <pre>Router(config-flow-cache)# cache timeout active 15</pre>	<p>(Optional) Configures aggregation cache operational parameters.</p> <ul style="list-style-type: none"> <li>• The <b>timeout</b> keyword dissolves the session in the aggregation cache.</li> <li>• The <b>active</b> <i>minutes</i> keyword-argument pair specifies the number of minutes that an entry is active. The range is from 1 to 60 minutes. The default is 30 minutes.</li> </ul>
<p><b>Step 6</b> <b>cache timeout inactive</b> <i>seconds</i></p> <p><b>Example:</b></p> <pre>Router(config-flow-cache)# cache timeout inactive 300</pre>	<p>(Optional) Configures aggregation cache operational parameters.</p> <ul style="list-style-type: none"> <li>• The <b>timeout</b> keyword dissolves the session in the aggregation cache.</li> <li>• The <b>inactive</b> <i>seconds</i> keyword-argument pair specifies the number of seconds that an inactive entry stays in the aggregation cache before the entry times out. The range is from 10 to 600 seconds. The default is 15 seconds.</li> </ul>

Command or Action	Purpose
<p><b>Step 7</b> <b>export destination</b> { <i>ip-address</i>   <i>hostname</i> } <i>udp-port</i> }</p> <p><b>Example:</b></p> <pre>Router(config-flow-cache)# export destination 172.30.0.1 991</pre>	<p>(Optional) Enables the exporting of information from NetFlow aggregation caches.</p> <ul style="list-style-type: none"> <li>• The <i>ip-address</i>   <i>hostname</i> argument is the destination IP address or hostname.</li> <li>• The <i>port</i> argument is the destination UDP port.</li> </ul>
<p><b>Step 8</b> Repeat Step 7 to configure a second export destination.</p>	<p>(Optional) You can configure a maximum of two export destinations for each NetFlow aggregation cache.</p>
<p><b>Step 9</b> <b>export version</b> [9   8]</p> <p><b>Example:</b></p> <pre>Router(config-flow-cache)# export version 9</pre>	<p>(Optional) Specifies data export format Version.</p> <ul style="list-style-type: none"> <li>• The <b>version 9</b> keyword specifies that the export packet uses the Version 9 format.</li> </ul>
<p><b>Step 10</b> <b>enabled</b></p> <p><b>Example:</b></p> <pre>Router(config-flow-cache)# enabled</pre>	<p>(Required) Enables the aggregation cache.</p>
<p><b>Step 11</b> <b>exit</b></p> <p><b>Example:</b></p> <pre>Router(config-if)# exit</pre>	<p>(Required) Exits NetFlow aggregation cache configuration mode and returns to global configuration mode.</p>
<p><b>Step 12</b> <b>interface</b> <i>interface-type</i> <i>interface-number</i></p> <p><b>Example:</b></p> <pre>Router(config)# interface fastethernet 0/0/0</pre>	<p>(Required) Specifies the interface that you want to enable NetFlow on and enters interface configuration mode.</p>
<p><b>Step 13</b> <b>ip flow</b> { <b>ingress</b>   <b>egress</b> }</p> <p><b>Example:</b></p> <pre>Router(config-if)# ip flow ingress</pre>	<p>(Required) Enables NetFlow on the interface.</p> <ul style="list-style-type: none"> <li>• <b>ingress</b> --captures traffic that is being received by the interface</li> <li>• <b>egress</b> --captures traffic that is being transmitted by the interface.</li> </ul>

Command or Action	Purpose
<b>Step 14</b> <code>exit</code>  <b>Example:</b>  <code>Router(config-if)# exit</code>	(Optional) Exits interface configuration mode and returns to global configuration mode.  <b>Note</b> You only need to use this command if you want to enable NetFlow on another interface.
<b>Step 15</b> Repeat Steps 12 through 14 to enable NetFlow on other interfaces	(Optional) --
<b>Step 16</b> <code>end</code>  <b>Example:</b>  <code>Router(config-if)# end</code>	Exits the current configuration mode and returns to privileged EXEC mode.

## Verifying the Aggregation Cache Configuration

To verify the aggregation cache configuration, use the following show commands. These commands allow you to:

- Verify that the NetFlow aggregation cache is operational.
- Verify that NetFlow Data Export for the aggregation cache is operational.
- View the aggregation cache statistics.

### SUMMARY STEPS

1. `enable`
2. `show ip cache flow aggregation {as | as-tos | destination-prefix | destination-prefix-tos | prefix | prefix-port | prefix-tos | protocol-port | protocol-port-tos | source-prefix | source-prefix-tos}`
3. `show ip flow export`
4. `end`

### DETAILED STEPS

#### Step 1 `enable`

Use this command to enable privileged EXEC mode. Enter your password if prompted.

#### Example:

```
Router> enable
Router#
```

#### Step 2 `show ip cache flow aggregation {as | as-tos | destination-prefix | destination-prefix-tos | prefix | prefix-port | prefix-tos | protocol-port | protocol-port-tos | source-prefix | source-prefix-tos}`

Use the `show ip cache flow aggregation destination-prefix` command to verify the configuration of an destination-prefix aggregation cache. For example:

**Example:**

```

Router# show ip cache flow aggregation destination-prefix
IP Flow Switching Cache, 139272 bytes
 5 active, 2043 inactive, 9 added
 841 ager polls, 0 flow alloc failures
 Active flows timeout in 15 minutes
 Inactive flows timeout in 300 seconds
IP Sub Flow Cache, 11144 bytes
 5 active, 507 inactive, 9 added, 9 added to flow
 0 alloc failures, 0 force free
 1 chunk, 2 chunks added
Dst If          Dst Prefix      Msk AS    Flows  Pkts B/Pk  Active
Null           0.0.0.0         /0  0       5     13   52   138.9
Et0/0.1        172.16.6.0     /24 0       1      1   56    0.0
Et1/0.1        172.16.7.0     /24 0       3    31K 1314  187.3
Et0/0.1        172.16.1.0     /24 0      16   104K 1398  188.4
Et1/0.1        172.16.10.0    /24 0       9     99K 1412  183.3
Router#

```

Use the **show ip cache verbose flow aggregation source-prefix** command to verify the configuration of a source-prefix aggregation cache. For example:

**Example:**

```

Router# show ip cache verbose flow aggregation source-prefix
IP Flow Switching Cache, 278544 bytes
 4 active, 4092 inactive, 4 added
 51 ager polls, 0 flow alloc failures
 Active flows timeout in 30 minutes
 Inactive flows timeout in 15 seconds
IP Sub Flow Cache, 21640 bytes
 4 active, 1020 inactive, 4 added, 4 added to flow
 0 alloc failures, 0 force free
 1 chunk, 1 chunk added
Src If          Src Prefix      Msk AS    Flows  Pkts B/Pk  Active
FEt1/0/0.1     172.16.10.0    /24 0       4    35K 1391   67.9
FEt0/0/0.1     172.16.6.0     /24 0       2      5   88   60.6
FEt1/0/0.1     172.16.7.0     /24 0       2   3515 1423   58.6
FEt0/0/0.1     172.16.1.0     /24 0       2    20K 1416   71.9
Router#

```

Use the **show ip cache verbose flow aggregation protocol-port** command to verify the configuration of a protocol-port aggregation cache. For example:

**Example:**

```

Router# show ip cache verbose flow aggregation protocol-port
IP Flow Switching Cache, 278544 bytes
 4 active, 4092 inactive, 4 added
 158 ager polls, 0 flow alloc failures
 Active flows timeout in 30 minutes
 Inactive flows timeout in 15 seconds
IP Sub Flow Cache, 21640 bytes
 0 active, 1024 inactive, 0 added, 0 added to flow
 0 alloc failures, 0 force free
 1 chunk, 1 chunk added
Protocol Source Port  Dest Port  Flows  Packets  Bytes/Packet  Active
0x01      0x0000     0x0000    6     52K     1405          104.3
0x11      0x0208     0x0208    1        3         52           56.9
0x01      0x0000     0x0800    2     846     1500          59.8
0x01      0x0000     0x0B01    2      10         56           63.0
Router#

```

**Step 3** **show ip flow export**

Use the **show ip flow export** command to verify that NetFlow Data Export is operational for the aggregation cache. For example:

**Example:**

```
Router# show ip flow export
Flow export v1 is disabled for main cache
Version 9 flow records
Cache for protocol-port aggregation:
  Exporting flows to 172.16.20.4 (991) 172.30.0.1 (991)
  Exporting using source IP address 172.16.6.2
Cache for source-prefix aggregation:
  Exporting flows to 172.16.20.4 (991) 172.30.0.1 (991)
  Exporting using source IP address 172.16.6.2
Cache for destination-prefix aggregation:
  Exporting flows to 172.16.20.4 (991) 172.30.0.1 (991)
  Exporting using source IP address 172.16.6.2
40 flows exported in 20 udp datagrams
0 flows failed due to lack of export packet
20 export packets were sent up to process level
0 export packets were dropped due to no fib
0 export packets were dropped due to adjacency issues
0 export packets were dropped due to fragmentation failures
0 export packets were dropped due to encapsulation fixup failures
Router#
```

**Step 4**

**end**

Use this command to exit privileged EXEC mode.

**Example:**

```
Router# end
```

## Configuration Examples for Configuring NetFlow Aggregation Caches

- [Configuring an AS Aggregation Cache Example, page 31](#)
- [Configuring a Destination Prefix Aggregation Cache Example, page 31](#)
- [Configuring a Prefix Aggregation Cache Example, page 31](#)
- [Configuring a Protocol Port Aggregation Cache Example, page 32](#)
- [Configuring a Source Prefix Aggregation Cache Example, page 32](#)
- [Configuring an AS-ToS Aggregation Cache Example, page 32](#)
- [Configuring a Prefix-ToS Aggregation Cache Example, page 33](#)
- [Configuring the Minimum Mask of a Prefix Aggregation Scheme Example, page 33](#)
- [Configuring the Minimum Mask of a Destination Prefix Aggregation Scheme Example, page 33](#)
- [Configuring the Minimum Mask of a Source Prefix Aggregation Scheme Example, page 34](#)
- [Configuring NetFlow Version 9 Data Export for Aggregation Caches Example, page 34](#)
- [Configuring NetFlow Version 8 Data Export for Aggregation Caches Example, page 34](#)

## Configuring an AS Aggregation Cache Example

The following example shows how to configure an AS aggregation cache with a cache size of 2046, an inactive timeout of 200 seconds, a cache active timeout of 45 minutes, an export destination IP address of 10.42.42.1, and a destination port of 9992:

```
configure terminal
!
ip flow-aggregation cache as
  cache entries 2046
  cache timeout inactive 200
  cache timeout active 45
  export destination 10.42.42.1 9992
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
!
end
```

## Configuring a Destination Prefix Aggregation Cache Example

The following example shows how to configure a destination prefix aggregation cache with a cache size of 2046, an inactive timeout of 200 seconds, a cache active timeout of 45 minutes, an export destination IP address of 10.42.42.1, and a destination port of 9992:

```
configure terminal
!
ip flow-aggregation cache destination-prefix
  cache entries 2046
  cache timeout inactive 200
  cache timeout active 45
  export destination 10.42.42.1 9992
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
!
end
```

## Configuring a Prefix Aggregation Cache Example

The following example shows how to configure a prefix aggregation cache with a cache size of 2046, an inactive timeout of 200 seconds, a cache active timeout of 45 minutes, an export destination IP address of 10.42.42.1, and a destination port of 9992:

```
configure terminal
!
ip flow-aggregation cache prefix
  cache entries 2046
  cache timeout inactive 200
  cache timeout active 45
  export destination 10.42.42.1 9992
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
```

```
!
end
```

## Configuring a Protocol Port Aggregation Cache Example

The following example shows how to configure a protocol port aggregation cache with a cache size of 2046, an inactive timeout of 200 seconds, a cache active timeout of 45 minutes, an export destination IP address of 10.42.42.1, and a destination port of 9992:

```
configure terminal

!

ip flow-aggregation cache protocol-port
  cache entries 2046
  cache timeout inactive 200
  cache timeout active 45
  export destination 10.42.42.1 9992
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
!
end
```

## Configuring a Source Prefix Aggregation Cache Example

The following example shows how to configure a source prefix aggregation cache with a cache size of 2046, an inactive timeout of 200 seconds, a cache active timeout of 45 minutes, an export destination IP address of 10.42.42.1, and a destination port of 9992:

```
configure terminal

!

ip flow-aggregation cache source-prefix
  cache entries 2046
  cache timeout inactive 200
  cache timeout active 45
  export destination 10.42.42.1 9992
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
!
end
```

## Configuring an AS-ToS Aggregation Cache Example

The following example shows how to configure an AS-ToS aggregation cache with a cache active timeout of 20 minutes, an export destination IP address of 10.2.2.2, and a destination port of 9991:

```
configure terminal

!

ip flow-aggregation cache as-tos
  cache timeout active 20
  export destination 10.2.2.2 9991
  enabled
```



```
!  
interface Fastethernet0/0/0  
  ip flow ingress  
!  
end
```

## Configuring a Prefix-ToS Aggregation Cache Example

The following example shows how to configure a prefix-ToS aggregation cache with an export destination IP address of 10.4.4.4 and a destination port of 9995:

```
configure terminal  
  
!  
  
ip flow-aggregation cache prefix-tos  
  export destination 10.4.4.4 9995  
  enabled  
!  
interface Fastethernet0/0/0  
  ip flow ingress  
!  
end
```

## Configuring the Minimum Mask of a Prefix Aggregation Scheme Example

The following example shows how to configure the minimum mask for a prefix aggregation scheme:

```
configure terminal  
  
!  
  
ip flow-aggregation cache prefix  
  mask source minimum 24  
  mask destination minimum 28  
  enabled  
!  
interface Fastethernet0/0/0  
  ip flow ingress  
!  
end
```

## Configuring the Minimum Mask of a Destination Prefix Aggregation Scheme Example

The following example shows how to configure the minimum mask for a destination prefix aggregation scheme:

```
configure terminal  
  
!  
  
ip flow-aggregation cache destination-prefix  
  mask destination minimum 32  
  enabled  
!  
interface Fastethernet0/0/0  
  ip flow ingress  
!  
end
```

## Configuring the Minimum Mask of a Source Prefix Aggregation Scheme Example

The following example shows how to configure the minimum mask for a source prefix aggregation scheme:

```
configure terminal
!
ip flow-aggregation cache source-prefix
  mask source minimum 30
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
!
end
```

## Configuring NetFlow Version 9 Data Export for Aggregation Caches Example

The following example shows how to configure NetFlow Version 9 data export for an AS aggregation cache scheme:

```
configure terminal
!
ip flow-aggregation cache as
  export destination 10.42.42.2 9991
  export template refresh-rate 10
  export version 9
  export template timeout-rate 60
  enabled
!
interface Ethernet0/0
  ip flow ingress
!
end
```

## Configuring NetFlow Version 8 Data Export for Aggregation Caches Example

The following example shows how to configure NetFlow Version 8 data export for an AS aggregation cache scheme:

```
configure terminal
!
ip flow-aggregation cache as
  export destination 10.42.42.2 9991
  export destination 10.42.41.1 9991
  export version 8
  enabled
!
interface FastEthernet0/0/0
  ip flow ingress
!
end
```

## Additional References

### Related Documents

Related Topic	Document Title
NetFlow commands: complete command syntax, command modes, command history, defaults, usage guidelines, and examples	<i>Cisco IOS NetFlow Command Reference</i>
Tasks for configuring NetFlow to capture and export network traffic data	"Configuring NetFlow and NetFlow Data Export"
Tasks for configuring NetFlow input filters	"Using NetFlow Filtering or Sampling to Select the Network Traffic to Track"
Tasks for configuring Random Sampled NetFlow	"Using NetFlow Filtering or Sampling to Select the Network Traffic to Track"
Information for installing, starting, and configuring the CNS NetFlow Collection Engine	<a href="#">"Cisco CNS NetFlow Collection Engine Documentation"</a>

### Standards

Standards	Title
No new or modified standards are supported by this feature, and support for existing standards has not been modified by this feature.	--

### MIBs

MIBs	MIBs Link
No new or modified MIBs are supported by this feature, and support for existing MIBs has not been modified by this feature.	To locate and download MIBs for selected platforms, Cisco IOS XE releases, and feature sets, use Cisco MIB Locator found at the following URL:  <a href="http://www.cisco.com/go/mibs">http://www.cisco.com/go/mibs</a>

### RFCs

RFCs	Title
No new or modified RFCs are supported by this feature, and support for existing RFCs has not been modified by this feature.	--

**Technical Assistance**

Description	Link
<p>The Cisco Support website provides extensive online resources, including documentation and tools for troubleshooting and resolving technical issues with Cisco products and technologies.</p> <p>To receive security and technical information about your products, you can subscribe to various services, such as the Product Alert Tool (accessed from Field Notices), the Cisco Technical Services Newsletter, and Really Simple Syndication (RSS) Feeds.</p> <p>Access to most tools on the Cisco Support website requires a Cisco.com user ID and password.</p>	<p><a href="http://www.cisco.com/cisco/web/support/index.html">http://www.cisco.com/cisco/web/support/index.html</a></p>

## Feature Information for Configuring NetFlow Aggregation Caches

The following table provides release information about the feature or features described in this module. This table lists only the software release that introduced support for a given feature in a given software release train. Unless noted otherwise, subsequent releases of that software release train also support that feature.

Use Cisco Feature Navigator to find information about platform support and Cisco software image support. To access Cisco Feature Navigator, go to [www.cisco.com/go/cfn](http://www.cisco.com/go/cfn). An account on Cisco.com is not required.

**Table 14** Feature Information for Configuring NetFlow Aggregation Caches

Feature Name	Releases	Feature Configuration Information
NetFlow ToS-Based Router Aggregation	Cisco IOS XE Release 2.1	<p>The NetFlow ToS-Based Router Aggregation feature enables you to limit router-based type of service (ToS) aggregation of NetFlow export data. The aggregation of export data provides a summarized NetFlow export data that can be exported to a collection device. The result is lower bandwidth requirements for NetFlow export data and reduced platform requirements for NetFlow data collection devices.</p> <p>In Cisco IOS XE Release 2.1, this feature was introduced on Cisco ASR 1000 Series Aggregation Services Routers.</p> <p>The following commands were modified by this feature: <b>ip flow-aggregation cache</b>, <b>show ip cache verbose flow aggregation</b>, <b>show ip flow export</b>.</p>
NetFlow Minimum Prefix Mask for Router-Based Aggregation	Cisco IOS XE Release 2.1	<p>The NetFlow Minimum Prefix Mask for Router-Based Aggregation feature allows you to set a minimum mask size for prefix aggregation, destination prefix aggregation, and source prefix aggregation schemes.</p> <p>In Cisco IOS XE Release 2.1, this feature was introduced on Cisco ASR 1000 Series Routers.</p> <p>The following commands were modified by this feature: <b>ip flow-aggregation cache</b>, <b>mask destination</b>, <b>mask source</b>, <b>show ip cache flow aggregation</b>.</p>

## Glossary

**AS** --autonomous system. A collection of networks under a common administration sharing a common routing strategy. Autonomous systems are subdivided by areas. An autonomous system must be assigned a unique 16-bit number by the Internet Assigned Numbers Authority (IANA).

**CEF** --Cisco Express Forwarding. A Layer 3 IP switching technology that optimizes network performance and scalability for networks with large and dynamic traffic patterns.

**export packet** --Type of packet built by a device (for example, a router) with NetFlow services enabled. The packet contains NetFlow statistics and is addressed to another device (for example, the NetFlow Collection Engine). The other device processes the packet (parses, aggregates, and stores information on IP flows).

**flow** --A set of packets with the same source IP address, destination IP address, protocol, source/destination ports, and type-of-service, and the same interface on which flow is monitored. Ingress flows are associated with the input interface, and egress flows are associated with the output interface.

**flowset** --Collection of flow records that follow the packet header in an export packet. A flowset contains information that must be parsed and interpreted by the NetFlow Collection Engine. There are two different types of flowsets: template flowsets and data flowsets. An export packet contains one or more flowsets, and both template and data flowsets can be mixed in the same export packet.

**NetFlow** --Cisco IOS XE accounting feature that maintains per-flow information.

**NetFlow Aggregation** --A NetFlow feature that lets you summarize NetFlow export data on an IOS router before the data is exported to a NetFlow data collection system such as the NetFlow Collection Engine. This feature lowers bandwidth requirements for NetFlow export data and reduces platform requirements for NetFlow data collection devices.

**NetFlow Collection Engine** (formerly NetFlow FlowCollector)--Cisco application that is used with NetFlow on Cisco routers and Catalyst series switches. The NetFlow Collection Engine collects packets from the router that is running NetFlow and decodes, aggregates, and stores them. You can generate reports on various aggregations that can be set up on the NetFlow Collection Engine.

**NetFlow v9** --NetFlow export format Version 9. A flexible and extensible means for carrying NetFlow records from a network node to a collector. NetFlow Version 9 has definable record types and is self-describing for easier NetFlow Collection Engine configuration.

**QoS** --quality of service. A measure of performance for a transmission system that reflects its transmission quality and service availability.

**template flowset** --One or more template records that are grouped in an export packet.

**ToS** --type of service. The second byte in the IP header. It indicates the desired quality of service (QoS) for a particular datagram.

Cisco and the Cisco logo are trademarks or registered trademarks of Cisco and/or its affiliates in the U.S. and other countries. To view a list of Cisco trademarks, go to this URL: [www.cisco.com/go/trademarks](http://www.cisco.com/go/trademarks). Third-party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1110R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2011 Cisco Systems, Inc. All rights reserved.