



Service Chain Configuration Mode Commands

The Service Chain configuration mode is a sub-mode of the Global Configuration mode. This sub-mode associates nsh-format to service-chain.

Command Modes

Exec > Global Configuration > Service Chain Configuration

configure > service-chain

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain) #
```



Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [end, on page 1](#)
- [exit, on page 1](#)
- [nsh-format, on page 2](#)

end

Exits the current configuration mode and returns to the Exec mode.

Product

All

Privilege

Security Administrator, Administrator

Syntax Description

end

Usage Guidelines

Use this command to return to the Exec mode.

exit

Exits the current mode and returns to the parent configuration mode.

Product	All
Privilege	Security Administrator, Administrator
Syntax Description	exit
Usage Guidelines	Use this command to return to the parent configuration mode.

nsh-format

This command associates nsh format with service-chain.

Product	P-GW SAEGW
Privilege	Security Administrator, Administrator
Command Modes	Exec > Global Configuration > Service Chain Configuration configure > service-chain Entering the above command sequence results in the following prompt: [local]host_name(config-service-chain)#

Syntax Description [**no**] **nsh-format** <nsh_format_name>

no

Disassociates nsh format with the service-chain configuration.

nsh-format

Associates nsh format with service chain.

nsh_format_name

Specifies the name of nsh-format. This is entered as an alphanumeric string of 1 through 63 characters.

Usage Guidelines Use this command to associate nsh-format with service-chain.

Example

The following commands associates a nsh-format to service-chain:

```
nsh-format ns1
```

The following commands disassociates the nsh-format with service-chain:

```
no nsh-format
```