# **RF Electronics**

# Scientific Atlanta

# Line Extender III Type 3 750 MHz with 55/70 MHz Split



23025

**Note:** The output tilt referenced in this document is defined as a LINEAR output tilt (as opposed to a CABLE output tilt). The distortion and noise figure specifications are applicable across the full operational temperature range (as opposed to being referenced to 68°F).

When calculating end of line performance, the specifications used for all of the amplifiers in a given cascade must be of similar format, due to the fact that all amplifiers in a cascade must operate with a similar output tilt (either all LINEAR output tilt or all CABLE output tilt).

# DESCRIPTION

The Line Extender III (LEIII) family of RF amplifiers provide optimum performance and reliability for broadband network applications. All LEIII amplifier modules offer 15 amp current carrying capacity, and are preconfigured with diplexers and reverse amplifier for optimum reverse performance.

The Type 3 versions of LEIII amplifier module are additionally preconfigured with interstage equalizer, interstage pad, and either AGC for a 3A or Thermal for a 3T, in order to achieve optimum station performance and simplify set up.

Additionally, maximum flexibility in reverse signal path alignment is


achieved via the reverse test point and plug-in pad for the reverse input.

The Type 3 amplifier module provides one (bridger level) output.

# **FEATURES**


- 60 and 90 V AC powering capability
- 15 ampere current capacity (steady state) and 25 ampere surge survivability
- Integrated reverse amplifier, with optimized diplex filter group delay for forward and reverse paths
- Reverse input test point and input pad allowing optimum reverse path alignment
- Improved station frequency response
- Unitized design (amplifier and power supply in a single module) enabling simplified and faster maintenance
- High efficiency, transformerless power supply lowering system operating cost
- Directional Coupler RF testpoints provide optimum accuracy
- Surge Resistant™ Circuitry ensuring hybrid protection without fuses or other nuisance failure causing devices

Scientific-Atlanta 1-800-433-6222



23026

# LINE EXTENDER III-TYPE 3 – 5-55/70-750 MHz



# LINE EXTENDER III TYPE 3 – 5-55/70-750 MHz

# **General Station Performance Data**

	Units	For	ward	Reverse			
Pass Band	MHz	70	-750	5-55			
Amplifier Type		Р	HD	PP			
Operational Temperature Range	degrees	-40 to	) +60 C	-40 to+60 C			
Frequency Response	dB	±	0.5	±0.5			
Auto Slope & Gain Range	dB	=	±4	N/A			
Return Loss	dB	•	16	16			
Operational AC Through Current	Amps	•	15	N/A			
Max AC Through Current (2 hrs)	Amps		25	N/A			
Hum Modulation @ 10 A	dB	70 (70-	750 MHz)	58 (5-15 MHz)			
(over specified frequency range)				65 (16-55 MHz)			
Hum Modulation @ 15 A	dB	62 (70-	150 MHz)	50 (5-15 MHz)			
(over specified frequency range)			600 MHz)	59 (16-55 MHz)			
		58 (601-	750 MHz)				
Test Points (±0.5 dB)	dB		20	-20			
Reference Output Level–High Freq.	dBmV	47.5 @	750 MHz	35 @ 55 MHz <sup>7</sup>			
		44 @ 5	550 MHz				
Reference Output Level–Low Freq.	dBmV	35 @ 70 MHz		35 @ 5 MHz <sup>7</sup>			
Reference Output Tilt 1	dB	+12.5		0			
		3T	3A				
Interstage Level Control (type)		Thermal	AGC w/	N/A			
			Man. Backoff				
Interstage Equalizer (value - type)	dB	14.5 - fixed	9 - fixed	N/A			
Current Draw @ 24 V DC	Amps	0.63	0.73	0.13			
Operational Gain (minimum) 3,9	dB	29.5	28.5	18.5			
Internal Tilt <sup>2</sup> (±0.5 dB)	dB	+6.7	+6.7	0			
Noise Figure 3,8 @ 70 MHz	dB	7.5	7.5				
Noise Figure 3,8 @ 750 MHz	dB	9	9				
Reverse Noise Figure 8,9	dB			6			

# Forward and Reverse Performance with Specified Channel Loading

	Units	3T	3A	Reverse
CW Channel Loading	NTSC	76 w/digital ⁴	76 w/digital 4	6
Composite Triple Beat 5,8	dB	71	70	92
Cross Modulation 6,8	dB	67	65	80
Composite Second Order 5,8 (high side)	dB	68	67	82

# **Delay Characteristics**

Forward		Reverse					
(Chrominance to Luminance Delay)		(Group Delay in 1.5 MHz BW)					
Freq. (MHz)	Delay (ns)	Freq. (MHz)	Delay (ns)				
72.00 - 76.43	25	53.5 - 55.0	19				
91.25 - 94.83	4	48.5 - 50.0	7				
		10.0 - 11.5	7				
		5.0 - 6.5	56				

- (1) Reference output tilt is specified as "LINEAR" tilt (as opposed to traditional "cable" tilt).
- (2) Down tilt, the effect of cable, is represented by a (-). Up tilt, the effect of equalization, is represented by a (+).
- (3) Forward gain and noise figure measured with 0 dB input EQ and 1 dB input pad.
- (4) "Digital" refers to 550-750 MHz loading with 33 QAM carriers at -6 dB levels relative to analog video carrier levels.
- (5) CTB and CSO measured using CW carriers, with spectrum analyzer as the measurement device.
   (6) X-Mod (@ 15.75 kHz) specified using 100% synchronous modulation and frequency selective measurement device.
- (7) Reverse output reference level with a 0 dB output equalizer and 1 dB output pad.
- (8) Distortions and noise figures are typical and specified over the operational temperature range.
- (9) Reverse gain and noise figure for station, with 0 dB reverse input pad, 0 dB reverse output EQ, and factory-selected reverse output pad.

Unless otherwise noted, the above specifications reflect typical station performance at stated reference levels in the recommended operating configuration, including the input equalizer and reverse filters where applicable. Unless otherwise noted, specifications are based on measurements made in accordance with NCTA Practices for Measurements on Cable Television Systems using standard frequency assignments and are referenced to 68°F (20°C).

# Line Extender III-Type 3 — 5-55/70-750 MHz

# Station Powering Data

		I DC	AC Voltage											
Line Extender III		(Amps)	90	85	80	75	70	65	60	55	50	45	40	35
Type 3T	AC Current (A)	0.76	0.38	0.41	0.42	0.44	0.46	0.48	0.49	0.52	0.55	0.58	0.61	0.67
	Power (W)		22.2	21.8	21.8	21.9	21.5	21.8	21.8	21.7	22.3	22.3	21.8	22.2
Type 3A	AC Current (A)	0.86	0.42	0.46	0.46	0.48	0.50	0.52	0.54	0.57	0.60	0.64	0.68	0.76
	Power (W)		24.7	24.4	24.3	24.4	24.2	24.3	24.4	24.3	24.8	24.8	24.4	24.6

Data is based on stations configured for 2-way operation. Power supply has 30 V AC undervoltage lockout. AC currents specified are based on measurements made with typical CATV type ferro-resonant AC power supply (quasi-square wave).

# ORDERING INFORMATION

# Amplifier Module - 1 required

• # 573887 - Type 3T amplifier module with Thermal **Note:** 3T amplifier module also comes configured with reverse amplifier, 14.5 dB interstage EQ, interstage pad, reverse output pad, 0 dB reverse output EQ, 55/70 diplex filters, integrated power supply.

• # 573889 - Type 3A amplifier module with AGC. AGC has 451.25 MHz pilot frequency and manual temperature backoff

**Note:** 3A amplifier module also comes configured with reverse amplifier, 9.0 dB interstage EQ, interstage pad, reverse output pad, 0 dB reverse output EQ, 55/70 diplex filters, integrated power supply.

# Housing - 1 required (all have 15 amp capacity)

- # 545443 Uncoated 2-port housing
- # 545444 Coated 2-port housing

# Required Accessories

- Plug-in Pads (attenuators):
  - 1 required for forward (1 input)
  - 2 required for reverse (1 input., 1 output)
  - 1 required for AGC only if amplifier output level at pilot frequency is NOT 42 dBmV (AGC comes configured with a 14 dB pad, which is appropriate for a 42 dBmV amplifier output level at pilot).

Available in 0.5 dB steps from 0 to 20 dB. Order Model PP-\* (\* denotes pad value); specify value.

- Plug-in Forward Input Equalizer, 1 required. Available in 1.5 dB steps from 0 to 28.5 dB at 750 MHz. Order Model EQ750-\* (\* denotes equalizer value); specify value.
- Plug-in Reverse Output Equalizer, 1 required. Available in 1.0 dB steps from 1.0 to 12.0 dB at 55 MHz. Order Model EQ55S -\* (\* denotes equalizer value); specify value.

# Optional Accessories

- #467351 230 V AC Crowbar Surge Protector
- · Plug-in Cable Simulator. Simulates cable losses, creating tilt opposite that of Equalizers. Use in place of Forward Input Equalizer as needed to maintain proper output tilt in short spaced locations. Available in 1.5 dB steps from 1.5 dB to 12.0 dB cable loss at 750 MHz. Order Model CS 750-\* (\* denotes CS value); specify value.

# Related Equipment

- #501111 Long Reach Test Point Adapter
- #276982 Reverse Injection Probe (3 dB insertion loss)
- #548771 Pad Insertion/Removal Tool

# MECHANICAL SPECIFICATIONS

**Housing Dimensions** 

11.5 in. L x 9.5 in. H x 4.0 in. D 292.1 mm L x 241.3 mm H x 101.6 mm D

Weight

Housing 6 lbs, 6 oz; 2.9 kg Module 2 lbs, 13 oz; 1.3 kg

Specifications and product availability are subject to change without notice.

Scientific Atlanta and the Scientific-Atlanta logo are registered trademarks of Scientific-Atlanta, Inc.

Surge Resistant is a trademark of Scientific-Atlanta, Inc.



Scientific-Atlanta, Inc. http://www.sciatl.com United States: 4261 Communications Drive, P.O. Box 6850, Norcross, GA 30091-6850; Tel: 800-722-2009; Fax: 770-903-4617 Germany: Europe GmbH, 61476 Kronberg, Germany; Tel: 49-6173-928-000; Fax: 49-6173-928-150 Australia: Unit 2, 2 Aquatic Drive, P.O. Box 292, Frenchs Forest, NSW 2086, Australia; Tel: 61-2-9452-3388; Fax: 61-2-9451-4432 Singapore: 1 Claymore Drive, #08-11 Orchard Towers, Singapore 229594; Tel: 65-733-4314; Fax: 65-733-2706 Hong Kong: Suite 56 & 57, 5/F New Henry House, 10 Ice House Street, Central, Hong Kong; Tel: 852-2522-5059; Fax: 852-2522-5624